



show controllers serial through show hw-module slot proc cpu

- [show etherchannel, page 2](#)

show etherchannel

To display EtherChannel information for a channel, use the **show etherchannel** command in privileged EXEC mode.

Cisco 2600 Series, Cisco 3600 Series, and Cisco 3700 Series Routers

show etherchannel [*channel-group*] { **port-channel** | **brief** | **detail** | **summary** | **port** | **load-balance** }

Cisco Catalyst Switches

show etherchannel [*channel-group*] { **port-channel** | **brief** | **detail** | **summary** | **port** | **load-balance** | **protocol** }
[*expression*]

Syntax Description

<i>channel-group</i>	(Optional) Number of the channel group. If you do not specify a value for the <i>channel-group</i> argument, all channel groups are displayed.
port-channel	Displays port channel information.
brief	Displays a summary of EtherChannel information.
detail	Displays detailed EtherChannel information.
summary	Displays a one-line summary per channel group.
port	Displays EtherChannel port information.
load-balance	Displays load-balance information.
protocol	Displays the enabled protocol.
<i>expression</i>	(Optional) Expression in the output to use as a reference point.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
12.0(7)XE	This command was introduced on Cisco Catalyst 6000 family switches.
12.1(3a)E3	This command was modified. The number of valid values for the <i>channel-group</i> argument were changed.

Release	Modification
12.1(5c)EX	This command was modified. The number of valid values for the <i>channel-group</i> argument were changed.
12.2(2)XT	This command was modified to support switchport creation on Cisco 2600 series, Cisco 3600 series, and Cisco 3700 series routers.
12.2(14)SX	This command was implemented on the Supervisor Engine 720.
12.2(17a)SX1	This command was modified. The output of the showetherchannelload-balance command was changed to include IPv6 information. The display was changed to include Multiprotocol Label Switching (MPLS) information.
12.2(17d)SXB	This command was modified to support the Supervisor Engine 2.
12.2(8)T	This command was modified to support switchport creation.
12.2(33)SXH	This command was modified. The output of the showetherchannelport-channel and the showetherchandeldetail commands was changed to include Link Aggregation Control Protocol (LACP) fast switchover status. The number of valid values for the <i>channel -group</i> argument was changed.
12.2(33)SRC	This command was modified. The output of the showetherchannelport-channel and the showetherchandeldetail commands was changed to show the status of the LACP Single Fault Direct Load Balance Swap feature, to show the last applied hash distribution algorithm, and to include LACP fast switchover status.
12.2(33)SXI3	This command was modified. The output of the showetherchannelsummary , showetherchannelport-channel , and showetherchandeldetail commands was changed to show the standalone disable option.

Usage Guidelines

Cisco 2600 Series, Cisco 3600 Series, and Cisco 3700 Series Routers

The *channel-group* argument supports six EtherChannels and eight ports in each channel.

If you do not specify a value for the *channel-group* argument, all channel groups are displayed.

Cisco Catalyst Switches

The number of valid values for the *channel-group* argument depends on the software release. For software releases prior to Cisco IOS Release 12.1(3a)E3, valid values are from 1 to 256; for Cisco IOS Release 12.1(3a)E3, 12.1(3a)E4, and 12.1(4)E1, valid values are from 1 to 64. Cisco IOS Release 12.1(5c)EX and later support a maximum of 64 values ranging from 1 to 256. Cisco IOS Release 12.2(33)SXH supports a maximum of 64 values ranging from 1 to 282.

If you do not specify a value for the *channel-group* argument, all channel groups are displayed.

In the output, the Passive port list field is displayed for Layer 3 port channels only. This field means that the physical interface, which is still not up, is configured to be in the channel group (and indirectly in the only port channel in the channel group).

The *channel-group* values from 257 to 282 are supported on the Catalyst 6500 series Cisco Services Module (CSM) and the Catalyst 6500 series Firewall Services Module (FWSM) only.

In the output, the Passive port list field is displayed for Layer 3 port channels only. This field means that the physical interface, which is still not up, is configured to be in the channel group (and indirectly is the only port channel in the channel group).

If the interface is configured as part of the channel in ON mode, the **show etherchannel protocol** command displays Protocol: - (Mode ON).

In the output of the **show etherchannel summary** command, the following conventions apply:

- In the column that displays the protocol that is used for the channel, if the channel mode is ON, a hyphen (-) is displayed.
- For LACP, multiple aggregators are supported. For example, if two different bundles are created, Po1 indicates the primary aggregator, and Po1A and Po1B indicates the secondary aggregators.

In the output of the **show etherchannel load-balance** command, the following conventions apply:

- For EtherChannel load balancing of IPv6 traffic, if the traffic is bridged onto an EtherChannel (for example, it is a Layer 2 channel and traffic in the same VLAN is bridged across it), the traffic is always load balanced by the IPv6 addresses or src, dest, or src-dest, depending on the configuration. For this reason, the switch ignores the MAC/IP/ports for bridged IPv6 traffic. If you configure src-dst-mac, the src-dst-ip(v6) address is displayed. If you configure src-mac, the src-ip(v6) address is displayed.
- IPv6 traffic that is routed over a Layer 2 or a Layer 3 channel is load balanced based on MAC addresses or IPv6 addresses, depending on the configuration. The MAC/IP and the src/dst/src-dst are supported, but load balancing that is based on Layer 4 ports is not supported. If you use the **port** keyword, the IPv6 addresses or either src, dst, or src-dst, is displayed.

Examples

Examples

The following example shows how to display the enabled protocol:

```
Router# show etherchannel protocol
Channel-group listing:
-----
Group: 12
-----
Protocol:   PAgP
Group: 24
-----
Protocol:   -   (Mode ON)
Router#
```

Examples

The following example shows how to display port channel information for a specific group:

```
Router# show etherchannel 12 port-channel
Group: 12
-----
Port-channels in the group:
-----
Port-channel: Po1
-----
Age of the Port-channel   = 143h:01m:12s
Logical slot/port        = 14/1           Number of ports = 2
GC                       = -              HotStandBy port = null
```

```

Port state          = Port-channel Ag-Inuse
Protocol            = LACP
Fast-switchover     = enabled
Ports in the Port-channel:
Index   Load   Port   EC state
-----+-----+-----+-----
    0     55   Fa4/1   active
    1     AA   Fa4/2   active
Time since last port bundled: 16h:28m:58s   Fa4/1
Time since last port Un-bundled: 16h:29m:00s   Fa4/4

```

The following example shows that direct load swapping is enabled.

```

Router# show etherchannel 15 port-channel
          Port-channels in the group:
Port-channel: Po15   (Primary Aggregator)
Age of the Port-channel   = 0d:18h:16m:49s
Logical slot/port   = 14/7           Number of ports = 1
HotStandBy port = null
Port state          = Port-channel Ag-Inuse
Protocol            = LACP
! The following line of output is added with support
of the LACP Single Fault Direct Load Swapping feature. !
Direct Load Swap = enabled
Ports in the Port-channel:
Index   Load   Port   EC state   No of bits
-----+-----+-----+-----+-----
    0     FF   Fa4/1   Active     8
Time since last port bundled: 0d:00h:06m:12s   Fa4/1

```

Examples

The following examples show how to display load-balancing information:

```

Router#
  show etherchannel load-balance
Source XOR Destination mac address
Router#
  show etherchannel load-balance
EtherChannel Load-Balancing Configuration:
  dst-mac
  mpls label-ip
EtherChannel Load-Balancing Addresses Used Per-Protocol:
Non-IP: Destination MAC address
  IPv4: Destination MAC address
  IPv6: Destination MAC address (routed packets)
        Destination IP address (bridged packets)
MPLS: Label or IP

```

Examples

The following example shows how to display a summary of information for a specific group:

```

Router#
  show etherchannel 1 brief
Group state = L3
Ports: 2   Maxports = 8
port-channels: 1 Max port-channels = 1
Partner's information:
The following example shows the hash distribution algorithm that was last applied:

```

```

Router# show etherchannel
10 summary
Flags: D - down          P - bundled in port-channel
       I - stand-alone   S - suspended
       H - Hot-standby (LACP only)
       R - Layer3        S - Layer2
       U - in use        N - not in use, no aggregation
       f - failed to allocate aggregator
<snip>

```

```

Group  Port-channel  Protocol  Ports
-----+-----+-----+-----
10     Po10(RU)         LACP      Gi3/7(P)   Gi3/9(P)
! The following line of output is added with support
of the EtherChannel Load Distribution feature. !
Last applied Hash Distribution Algorithm: Fixed
Router#

```

Examples

The following example shows how to display detailed information for a specific group:

```

Router#
show etherchannel 12 detail
Group state = L2
Ports: 1      Maxports = 8
Port-channels: 1 Max Port-channels = 1
Protocol:   PAgP
Fast-switchover = enabled
              Ports in the group:
              -----
Port: Fa5/2
-----
Port state      = Down Not-in-Bndl
Channel group   = 12              Mode = Desirable-Sl      Gcchange = 0
Port-channel    = null            GC   = 0x00000000      Pseudo port-channel = Po1
2
Port index      = 0              Load = 0x00          Protocol =   PAgP
Flags:  S - Device is sending Slow LACPDUs  F - Device is sending fast LACPDUs
        A - Device is in active mode        P - Device is in passive mode
Local information:
Port      Flags  State      LACP Port  Admin  Oper  Port  Port
Fa4/1     SA     bndl       32768      100    100   0xc1   0x75
Partner's information:
Port      Partner
Fa4/1     8000,00b0.c23e.d861
          LACP Partner  Partner
          Port Priority  Oper Key  Port State
          32768        128      0x81
Age of the port in the current state: 16h:27m:42s
Port-channels in the group:
-----
Port-channel: Po12
-----
Age of the Port-channel   = 04d:02h:52m:26s
Logical slot/port        = 14/1      Number of ports = 0
GC                        = 0x00000000  HotStandBy port = null
Port state                = Port-channel Ag-Not-Inuse
Protocol                  =   PAgP

```



Note

When LACP 1:1 redundancy is configured, the **show etherchannel detail** command also displays fast-switchover status information.

Examples

The following example shows how to display a one-line summary per channel group:

```

Router#
show etherchannel summary
U-in use I-in port-channel S-suspended D-down i-stand-alone d-default
Group Port-channel  Ports
-----+-----+-----
1      Po1(U)         Fa5/4(I) Fa5/5(I)
2      Po2(U)         Fa5/6(I) Fa5/7(I)

```

```

255                Fa5/9(i)
256                Fa5/8(i)

```

Examples

The following example shows how to display EtherChannel port information for all ports and all groups:

```

Router#
show etherchannel port
      Channel-group listing:
      -----
Group: 1
-----
      Ports in the group:
      -----
Port: Fa5/4
-----
Port state      = EC-Enbld Down Not-in-Bndl Usr-Config
Channel group = 1          Mode = Desirable      Gcchange = 0
Port-channel   = null      GC   = 0x00000000      Psudo-agport = Po1
Port indx      = 0          Load = 0x00
Flags:  S - Device is sending Slow hello.    C - Device is in Consistent state.
        A - Device is in Auto mode.          P - Device learns on physical port.
Timers: H - Hello timer is running.          Q - Quit timer is running.
        S - Switching timer is running.      I - Interface timer is running.
Local information:

Port      Flags State      Timers      Hello      Partner  PAgP      Learning  Group
Fa5/4     d      U1/S1      1s          Interval  Count    Priority   Method    Ifindex
                                1s          0          128       Any       0

Age of the port in the current state: 02h:40m:35s
Port: Fa5/5
-----
Port state      = EC-Enbld Down Not-in-Bndl Usr-Config
Channel group = 1          Mode = Desirable      Gcchange = 0
Port-channel   = null      GC   = 0x00000000      Psudo-agport = Po1
Port indx      = 0          Load = 0x00
Flags:  S - Device is sending Slow hello.    C - Device is in Consistent state.
        A - Device is in Auto mode.          P - Device learns on physical port.
Timers: H - Hello timer is running.          Q - Quit timer is running.
        S - Switching timer is running.      I - Interface timer is running.

```

Examples

The following example shows how to display the information about the EtherChannel port for a specific group:

```

Router#
show etherchannel 1 port
      Channel-group listing:
      -----
Group: 1
-----
      Ports in the group:
      -----
Port: Fa5/4
-----
Port state      = EC-Enbld Down Not-in-Bndl Usr-Config
Channel group = 1          Mode = Desirable      Gcchange = 0
Port-channel   = null      GC   = 0x00000000      Psudo-agport = Po1
Port index      = 0          Load = 0x00          Protocol = LACP
Flags:  S - Device is sending Slow LACPDUs  F - Device is sending fast LACPDUs
        A - Device is in active mode         P - Device is in passive mode
Local information:

Port      Flags  State      LACP Port  Admin  Oper  Port  Port
Fa5/4     SA     bndl      32768     100    100   0xc1  0x75
Partner's information:

Port      Partner
System ID  System ID  Port Number  Age  Flags
Fa5/4     8000,00b0.c23e.d861  0x81      14s  SP

```

```

LACP Partner      Partner      Partner
Port Priority     Oper Key    Port State
32768            128         0x81
Age of the port in the current state: 04d:02h:57m:38s

```

Examples

The following example shows the **show etherchannel summary** command output with a port in suspended state:

```

Router# show etherchannel 42 summary
Flags: D - down          P - bundled in port-channel
       I - stand-alone   S - suspended
       H - Hot-standby (LACP only)
       R - Layer3        S - Layer2
       U - in use        f - failed to allocate aggregator
       M - not in use, minimum links not met
       u - unsuitable for bundling
       w - waiting to be aggregated
Number of channel-groups in use: 8
Number of aggregators:          8
Group  Port-channel  Protocol    Ports
-----+-----+-----+-----
2      Po42(SU)      LACP        Fa1/17(s) Fa1/18(P) Fa1/19(P) Fa1/20(P)

```

The following example shows the **show etherchannel port-channel** command output with the status of Standalone Disable option:

```

Router# show etherchannel 42 port-channel
Port-channels in the group:
-----
Port-channel: Po42      (Primary Aggregator)
-----
Age of the Port-channel   = 0d:21h:28m:22s
Logical slot/port        = 14/42      Number of ports = 3
HotStandBy port = null
Port state                = Port-channel Ag-Inuse
Protocol                  = LACP
Fast-switchover          = disabled
Load share deferral      = disabled
Standalone Disable       = enabled
Ports in the Port-channel:
Index   Load    Port          EC state    No of bits
-----+-----+-----+-----+-----
2       49      Fa1/18        Active      3
1       92      Fa1/19        Active      3
3       24      Fa1/20        Active      2
Time since last port bundled: 0d:03h:37m:07s Fa1/18
Time since last port Un-bundled: 0d:03h:34m:27s Fa1/17
Last applied Hash Distribution Algorithm: Fixed

```

The following example shows the **show etherchannel detail** command output with the status of Standalone Disable option:

```

Router# show etherchannel 42 detail

Group state = L2
Ports: 4    Maxports = 16
Port-channels: 1 Max Port-channels = 16
Protocol: LACP
Minimum Links: 2
Standalone Disable: enabled
Ports in the group:
-----
Port: Fa1/17
-----
Port state      = Up Cnt-bndl Suspend Not-in-Bndl
Channel group   = 42          Mode = Active      Gcchange = -
Port-channel    = null       GC    = -          Pseudo port-channel = Po2
Port index      = 0          Load = 0x00       Protocol = LACP

```

```

Flags: S - Device is sending Slow LACPDUs   F - Device is sending fast LACPDUs.
      A - Device is in active mode.         P - Device is in passive mode.
Local information:
Port      Flags   State   LACP port   Admin   Oper   Port   Port
Fal/17    FP      susp    1           0x2     0x2    0x112  0x82
Partner's information:
Port      Flags   State   LACP Partner  Partner  Partner  Partner  Partner
Fal/17    FP      susp    1           0x0     0x2    0x312  0x36
Age of the port in the current state: 0d:03h:44m:04s
Port: Fal/18
-----
Port state      = Up Mstr In-Bndl
Channel group = 42          Mode = Active          Gcchange = -
Port-channel = Po2          GC = -                Pseudo port-channel = Po2
Port index     = 2          Load = 0x49          Protocol = LACP
Flags: S - Device is sending Slow LACPDUs   F - Device is sending fast LACPDUs.
      A - Device is in active mode.         P - Device is in passive mode.
Local information:
Port      Flags   State   LACP port   Admin   Oper   Port   Port
Fal/18    SA      bndl    2           0x2     0x2    0x113  0x3D
Partner's information:
Port      Flags   State   LACP Partner  Partner  Partner  Partner  Partner
Fal/18    SA      bndl    2           0x0     0x2    0x313  0x3D
Age of the port in the current state: 0d:03h:43m:24s
Port-channels in the group:
Port-channel: Po42 (Primary Aggregator)
Age of the Port-channel = 0d:21h:34m:45s
Logical slot/port = 14/42          Number of ports = 3
HotStandBy port = null
Port state      = Port-channel Ag-Inuse
Protocol        = LACP
Fast-switchover = disabled
Load share deferral = disabled
Standalone Disable = enabled
Ports in the Port-channel:
Index  Load   Port          EC state      No of bits
-----+-----+-----+-----+-----+
  2     49     Fal/18        Active        3
  1     92     Fal/19        Active        3
  3     24     Fal/20        Active        2
Time since last port bundled: 0d:03h:43m:30s   Fal/18
Time since last port Un-bundled: 0d:03h:40m:50s   Fal/17
Last applied Hash Distribution Algorithm: Fixed

```

Related Commands

Command	Description
channel-group	Assigns and configures an EtherChannel interface to an EtherChannel group.
channel-protocol	Sets the protocol that is used on an interface to manage channeling.
interface port-channel	Accesses or creates the IDB port channel.

