



snmp mib event trigger owner through snmp-server enable informs

- [snmp mib event trigger owner, page 2](#)
- [snmp mib expression delta, page 4](#)
- [snmp mib expression owner, page 6](#)
- [snmp mib flash cache, page 8](#)
- [snmp mib flowmon alarmhistorysize, page 9](#)
- [snmp mib notification-log default, page 10](#)
- [snmp mib notification-log default disable, page 12](#)
- [snmp mib notification-log globalageout, page 14](#)
- [snmp mib notification-log globalsize, page 16](#)
- [snmp mib persist, page 18](#)
- [snmp mib target list, page 20](#)
- [snmp trap link-status, page 22](#)
- [snmp set, page 25](#)
- [snmp-server cache, page 28](#)
- [snmp-server contact, page 30](#)
- [snmp-server context, page 31](#)
- [snmp-server drop vrf-traffic, page 33](#)
- [snmp-server enable informs, page 34](#)

snmp mib event trigger owner

To specify an event trigger owner while configuring management event trigger information, use the **snmp mib event trigger owner** command in global configuration mode. To disable event trigger configuration and set the default parameters, use the **no** form of this command.

snmp mib event trigger owner *trigger-owner* **name** *trigger-name*
no snmp mib event trigger owner *trigger-owner* **name** *trigger-name*

Syntax Description

<i>trigger-owner</i>	Name of the trigger owner.
name	Indicates the name of the trigger.
<i>trigger-name</i>	Unique name of the trigger that is within the scope of the trigger owner. The trigger names are assigned by the administrator.

Command Default

By default, the trigger name and trigger owner are not defined.

Command Modes

Global configuration (config)

Command History

Release	Modification
12.4(20)T	This command was introduced.
12.2(50)SY	This command was integrated into Cisco IOS Release 12.2(50)SY.

Usage Guidelines

The **snmp mib event trigger owner** command enables event trigger configuration mode to configure conditions to trigger events. While configuring a trigger, you can associate each trigger to an event and configure the objects to be monitored.

Examples

The following example shows how to specify a trigger owner:

```
Router(config)# snmp mib event trigger owner owner1 name trigger1
Router(config-event-trigger)# end
```

Related Commands

Command	Description
description	Provides a description of the function and use of a trigger.
enable	Enables an event.
frequency	Specifies an interval between trigger samples.
object id	Specifies the object identifier of an object.
object list owner	Specifies the list of objects that can be added to notifications according to trigger type.

snmp mib expression delta

To specify a delta interval for object sampling, use the **snmp mib expression delta** command in global configuration mode. To disable the specified interval, use the **no** form of this command.

snmp mib expression delta {**minimum** {*delta-value* | *seconds*} | **wildcard maximum** *wildcard-instance*}

no snmp mib expression delta {**minimum** | **wildcard maximum**}

Syntax Description

minimum	Specifies the minimum value for object sampling.
<i>delta-value</i>	The delta value to use during object sampling.
<i>seconds</i>	Minimum number of seconds between delta samples. The default is 1.
wildcard	Specifies the number of instances that can be wildcarded during object sampling.
maximum	Specifies the maximum value for object.
<i>wildcard-instance</i>	The maximum number of dynamic instance entries. The default is 0.

Command Default

The default value for minimum delta interval is 1 second.

The default wildcard maximum value is 0.

Command Modes

Global configuration (config)

Command History

Release	Modification
12.4(20)T	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(50)SY	This command was integrated into Cisco IOS Release 12.2(50)SY.

Usage Guidelines

Applications may use larger values for minimum delta interval to lessen the impact of constantly computing delta. The **snmp mib expression delta minimum** command enforces a lower overhead for all expressions created after it is set.

For every instance of a delta object, one dynamic instance entry is required to restrict the instance value from the previous sample. The **snmp mib expression delta wildcard maximum** command limits the maximum number of dynamic instance entries that the system supports for wildcarded delta objects in expressions. For a given delta expression, the number of dynamic instances is the number of delta value (that meet all criteria) multiplied by the number of delta values in the expression.

A value of 0 indicates no preset limit. There is a dynamic limit based on system operation and resources. However, changing this value will not eliminate the existing delta wildcard instance objects, but will prevent the creation of more such objects.

Examples

The following example shows how to set the minimum delta interval to 60 seconds:

```
Router(config)# snmp mib expression delta minimum 60
Router(config-expression)# end
```

Related Commands

Command	Description
sample	Specifies the method of sampling an object.

snmp mib expression owner

To specify the owner of an expression, use the **snmp mib expression owner** command in global configuration mode. To disable the expression configuration, use the **no** form of this command.

snmp mib expression owner *expr-owner* **name** *expr-name*

no snmp mib expression owner *expr-owner* **name** *expr-name*

Syntax Description

<i>expr-owner</i>	Name of an expression owner.
name	Indicates the name of the expression.
<i>expr-name</i>	Name of the expression.

Command Default

By default, the expression owner and expression name are not defined.

Command Modes

Global configuration (config)

Command History

Release	Modification
12.4(20)T	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(50)SY	This command was integrated into Cisco IOS Release 12.2(50)SY.

Usage Guidelines

The **snmp mib expression owner** command enables expression configuration mode and configures expression information such as expression owner and name. You can configure expression properties by using commands such as **expression**, **delta interval**, and **expression**.

Examples

The following example shows how to specify an expression owner:

```
Router(config)# snmp mib expression owner owner1 name expression1
Router(config-expression)# end
```

Related Commands

Command	Description
delta interval	Specifies an interval for the delta sampling of objects used while evaluating an expression.

Command	Description
description (event)	Describes the function and use of an event.
enable (event)	Enables an event or event trigger.
expression	Specifies an expression for evaluation.
object	Specifies the objects to be used while evaluating an expression.
prefix object	Enables the application to determine the object based on the instance indexing.
value type	Specifies the type of expression value.

snmp mib flash cache

To enable the data collection process for Flash MIB, use the **snmp mib flash cache** command in global configuration mode. To set the command to its default interval, use the **no** form of this command.

snmp mib flash cache [*interval minutes*]
no snmp mib flash cache [*interval minutes*]

Syntax Description

interval	(Optional) Specifies the interval for Flash MIB data collection process.
<i>minutes</i>	(Optional) Data collection interval, in minutes. The values are 1 to 60. The default is 2.

Command Default

The Flash MIB data collection process is disabled.

Command Modes

Global configuration (config)

Command History

Release	Modification
12.2(33)SXI	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.

Usage Guidelines

The data collection process collects the data required for sorting the ciscoFlashFileTable in the Flash MIB according to device, partition, file indexes, and file type.

Examples

The following example shows how to set the data collection interval to 10 minutes:

```
Router# configure terminal
Router(config)# snmp mib flash cache interval 10
Router(config)#
```


snmp mib flowmon alarmhistorysize

To set the maximum number of entries maintained by the flow monitor alarm history log, use the **snmp mib flowmon alarmhistorysize** command in global configuration mode. To remove the setting for the maximum number of alarm history log entries, use the **no** form of this command.

snmp mib flowmon alarmhistorysize *num*

no snmp mib flowmon alarmhistorysize *num*

Syntax Description

<i>num</i>	Specifies the maximum number of entries maintained by the flow monitor
------------	--

Command Default

Flow monitor maintains a maximum number of 500 entries in the alarm history log.

Command Modes

Global configuration (config)

Command History

Release	Modification
15.0(1)S	This command was introduced.

Examples

The following example shows how to set the maximum number of entries maintained by the flow monitor to 400:

```
Router(config)# snmp mib flowmon alarmhistorysize 400
```

Related Commands

Command	Description
snmp -server community	Enables SNMP and sets the community string and access privileges.
snmp -server host	Specifies the recipient of an SNMP notification operation.

snmp mib notification-log default

To create an unnamed Simple Network Management Protocol (SNMP) notification log, use the **snmp mib notification-log default** command in global configuration mode. To delete the log, use the **no** form of this command.

snmp mib notification-log default [*size number*]

no snmp mib notification-log default [*size number*]

Syntax Description

size	(Optional) Sets the maximum number of entries that the log can contain.
<i>number</i>	(Optional) Maximum number of entries. The default is 500.

Command Default

500 entries

Command Modes

Global configuration

Command History

Release	Modification
12.0(22)S	This command was introduced.
12.2(13)T	This command was integrated into Cisco IOS Release 12.2(13)T.

Usage Guidelines

This command creates an unnamed default SNMP notification log. The default log has a zero length string as its name (appears in the output of the **show snmp mib notification-log** command as Log Name”).

Creation and removal of the default log can be performed using only the command-line interface (CLI). Creation of named logs using the CLI or SNMP tools (SET operations) is not currently supported. No filters (varbinds) can be associated with the default log.

SNMP notification logging is enabled by default, but logging does not start until either a specific log is created and defined using this command or a named log is created using a SNMP Set operation from a network management station (NMS).

The **no** form of this command deletes the default notification log and removes the notifications that were a part of this log from the Notification Log MIB database (recursively deletes the log and all its entries).

Examples

The following example shows how to create and activate a default SNMP notification log with a size of 600:

```
Router(config)# snmp mib notification-log default size 600
```

Related Commands

Command	Description
show snmp mib notification-log	Displays information about the state of local SNMP notification logging.
snmp mib notification-log globalageout	Sets the maximum age for a notification.
snmp mib notification-log globalsize	Sets the maximum number of notifications allowed in all logs.

snmp mib notification-log default disable

To disable Simple Network Management Protocol (SNMP) notification logging to the “default” log without deleting existing notification log entries, use the **snmp mib notification-log default disable** command in global configuration mode. To reenale logging, use the **no** form of this command.

snmp mib notification-log default disable

no snmp mib notification-log default disable

Syntax Description This command has no arguments or keywords

Command Default Logging is enabled.

Command Modes Global configuration

Command History	Release	Modification
	12.0(22)S	This command was introduced.
	12.2(13)T	This command was integrated into Cisco IOS Release 12.2(13)T.

Usage Guidelines

The “default” notification log is the null-named notification log.

This command disables SNMP notification logging. However, this command does not delete existing logs. To clear the existing “default” log, use the **no snmp mib notification-log default** command.

SNMP notification logging is enabled by default, but logging does not start until a specific log is created and defined using the **snmp mib notification-log default** command, or a named log is created using an SNMP Set operation from a network management station (NMS).

Examples In the following example, SNMP notification logging is disabled, but existing logs are not deleted:

```
Router(config)# snmp mib notification-log default ?
    disable    disable logging
    size       size of the default log
    <cr>
Router(config)# snmp mib notification-log default disable
Router(config)#
```

Related Commands

Command	Description
show snmp mib notification-log	Displays information about the state of local SNMP notification logging.
snmp mib notification-log default	Creates an SNMP notification log.
snmp mib notification-log globalageout	Sets the maximum age for a notification.
snmp mib notification-log globalsize	Sets the maximum number of notifications allowed in all logs.

snmp mib notification-log globalageout

To set the maximum amount of time Simple Network Management Protocol (SNMP) notification log entries remain in the system memory, use the **snmp mib notification-log globalageout** command in global configuration mode. To restore the default value, use the **no** form of this command.

snmp mib notification-log globalageout minutes

no snmp mib notification-log globalageout minutes

Syntax Description

<i>minutes</i>	Maximum age (in minutes) that a notification entry is retained in the system memory. The default is 15.
----------------	---

Command Default

The default global ageout value is 15 minutes.

Command Modes

Global configuration

Command History

Release	Modification
12.0(22)S	This command was introduced.
12.2(13)T	This command was integrated into Cisco IOS Release 12.2(13)T.

Usage Guidelines

The ageout value specifies the maximum time a notification log can remain in the Notification Log MIB database. This value applies to all logs (default log and named logs) in the Notification Log MIB database. The **no** form of the command restores the default value.

Examples

In the following example, the system is configured to delete entries in the SNMP Notification Log that were logged more than 20 minutes ago:

```
Router(config)# snmp mib notification-log globalageout 20
```

Related Commands

Command	Description
show snmp mib notification-log	Provides a summary of logs.
snmp mib notification-log default	Creates the default log in the MIB.

Command	Description
snmp mib notification-log globalsize	Sets the maximum number of notifications allowed in all logs.

snmp mib notification-log globalsize

To set the maximum number of entries that can be stored in all Simple Network Management Protocol (SNMP) notification Logs, use the **snmp mib notification-log globalsize** command in global configuration mode. To restore the default value, use the **no** form of this command.

snmp mib notification-log globalsize *number*

no snmp mib notification-log globalsize *number*

Syntax Description

<i>number</i>	Maximum number of log entries. The range is from 1 to 15000. This value cannot be set to 0 (limitless). The default is 500.
---------------	---

Command Default

The default global log size is 500 entries.

Command Modes

Global configuration

Command History

Release	Modification
12.0(22)S	This command was introduced.
12.2(13)T	This command was integrated into Cisco IOS Release 12.2(13)T.

Usage Guidelines

The size of the SNMP notification log database can be set globally (for all SNMP notification logs combined) or for each named log. The **snmp mib notification-log globalsize** command sets the maximum number of entries for all notification logs on the local system; in other words, this setting affects the whole Notification Log MIB database. This value is saved to the nlmConfigGlobalEntryLimit object in the SNMP Notification Log MIB.

The default global log size is 500 log entries. The default log size for each individual log (such as the “default log”) is 500 log entries. The maximum size for all logs combined is 15,000 log entries.

Examples

In the following example, the system is configured to delete older log entries when there are more than 600 log entries in all SNMP notification logs on the system:

```
Router(config)# snmp mib notification-log globalsize 600
```


Related Commands

Command	Description
show snmp mib notification-log	Provides a summary of logs.
snmp mib notification-log default	Creates the default log in the MIB.
snmp mib notification-log globalageout	Sets the maximum age for a notification.

snmp mib persist

To enable MIB persistence, use the **snmp mib persist** command in global configuration mode. To disable MIB persistence, use the **no** form of this command.

snmp mib persist [**event**| **expression**| **circuit**| **cbqos**| **v3mibs**]

no snmp mib persist [**event**| **expression**| **circuit**| **cbqos**| **v3mibs**]

Syntax Description

event	(Optional) Enables Event MIB persistence.
expression	(Optional) Enables Expression MIB persistence.
circuit	(Optional) Enables Circuit MIB persistence.
cbqos	(Optional) Enables class-based (CB) quality of service (QoS) MIB persistence.
v3mibs	(Optional) Enables persistence for Version 3 MIBs.

Command Default

MIB persistence is disabled.

Command Modes

Global configuration (config)

Command History

T Release	Modification
12.2(2)T	This command was introduced.
12.2(4)T3	The event and expression keywords were added.
12.4(4)T	The cbqos keyword was added.
12.4(20)T	The event and expression keywords were removed.
OS Release	Modification
12.0(32)S	This command was integrated into Cisco IOS Release 12.0(32)S. The event , expression , and cbqos keywords were added.
SB Release	Modification
12.2(31)SB	This command was integrated into Cisco IOS Release 12.2(31)SB. The v3mibs and cbqos keywords were added.

T Release	Modification
SX Release	Modification
12.2(33)SXI	This command was integrated into Cisco IOS Release 12.2(33)SXI. The cbqos keyword was added.
SR Release	Modification
12.2(33)SRB	This command was integrated into Cisco IOS Release 12.2(33)SRB. The cbqos keyword was added.
12.2(33)SRC	The v3mibs keyword was added.

Usage Guidelines

After entering the **snmp mib persist** command, you must enter the **write mib-data** command to save MIB persistence configuration data to NVRAM.

The Circuit Interface MIB provides a MIB object (cciDescr) that can be used to identify individual circuit-based interfaces for Simple Network Management Protocol (SNMP) monitoring. Circuit interface identification persistence maintains the user-defined name of the circuit across reboots by retaining the value of the cciDescr object in the Circuit Interface MIB (CISCO-CIRCUIT-INTERFACE-MIB). A consistent value for specific circuits is useful for network management applications that use SNMP. Circuit interface identification persistence is enabled using the **snmp mib persist circuit** global configuration command. This command is disabled by default because it uses NVRAM memory.

To enable MIB persistence for all available MIB types, use the **snmp mib persist** command without keywords.

Examples

The following example shows how to enable Event MIB persistence:

```
Router(config)# snmp mib persist cbqos
Router(config)# end

Router# write mib-data
```

Related Commands

Command	Description
snmp ifindex persist	Enables SNMP interface index values that remain constant across reboots only on a specific interface.
snmp-server ifindex persist	Globally enables SNMP interface index values that remain constant across reboots.
write mib-data	Saves MIB persistence configuration data to NVRAM.

snmp mib target list

To create a list of target virtual private network (VPN) routing and forwarding (VRF) instance and hosts to associate with a Simple Network Management Protocol (SNMP) community, use the **snmp mib target list** command in global configuration mode. To delete the list of VRF instances and hosts or to delete a particular VRF or host from the list, use the **no** form of this command.

snmp mib target list *vpn-list-name* {**vrf** *vrf-name*| **host** *ip-address*}

no snmp mib target list *vpn-list-name* {**vrf** *vrf-name*| **host** *ip-address*}

Syntax Description

<i>vpn-list-name</i>	Name of the target list.
vrf	Adds a specified VRF to the target list.
<i>vrf-name</i>	Name of a VRF to include in the list.
host	Adds a specified host to the target list.
<i>ip-address</i>	IP address of the host.

Command Default

No target list is created.

Command Modes

Global configuration (config)

Command History

Release	Modification
12.0(23)S	This command was introduced.
12.3(2)T	This command was integrated into Cisco IOS Release 12.3(2)T.
12.2(25)S	This command was integrated into Cisco IOS Release 12.2(25)S.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2(31)SB2	This command was integrated into Cisco IOS Release 12.2(31) SB2.
12.2(33)SXH	This command was integrated into Cisco IOS Release 12.2(33)SXH.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
12.2(33)SB	This command was integrated into Cisco IOS Release 12.2(33)SB.

Usage Guidelines

Use this command when using SNMPv1 or SNMPv2 in a VPN environment to configure a list of VRFs or hosts for source address validation. Configuring the target list ensures that the community is valid only if the incoming packet is received from a VRF or host on the target list.

- Only the following MIBs are context aware and all the tables in these MIBs can be polled:
 - CISCO-IPSEC-FLOW-MONITOR-MIB (Cisco IOS Release 12.4T and later)
 - CISCO-IPSEC-MIB (Cisco IOS Release 12.4T and later)
 - CISCO-PING-MIB
 - IP-FORWARD-MIB
 - MPLS-LDP-MIB
- Currently, two SNMP variables in the IP-FORWARD-MIB can be polled: 1.3.6.1.2.1.4.24.3 (ipCidrRouteNumber - Scalar) and 1.3.6.1.2.1.4.24.4.1 (ipCidrRouteEntry - Table).



Note

It is recommended that you use SNMPv3 with the authNoPriv or higher level of security when using SNMP in a VPN environment.

Examples

The following example shows how to add a target list named target1 and add a VRF named vrf1 to the newly created target list:

```
Router(config)# snmp mib target list target1 vrf vrf1
```

Related Commands

Command	Description
snmp mib community-map	Associates an SNMP community with an SNMP context, engine ID, or security name.

snmp trap link-status

To enable Simple Network Management Protocol (SNMP) link trap generation, use the **snmp trap link-status** command in either interface configuration mode or service instance configuration mode. To disable SNMP link trap generation, use the **no** form of this command.

```
snmp trap link-status [permit duplicates]
no snmp trap link-status [permit duplicates]
```

Syntax Description

permit duplicates	(Optional) Permits duplicate SNMP linkup and linkdown traps.
-------------------	--

Command Default

SNMP link traps are generated when an interface goes up or down.

Command Modes

Interface configuration (config-if) Service instance configuration (config-if-srv)

Command History

Release	Modification
10.0	This command was introduced.
12.2(30)S	This command was modified. The permit duplicates keyword pair was added.
12.3(8)T	This command was integrated into Cisco IOS Release 12.3(8)T.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
12.2(33)SB	This command’s behavior was modified on the Cisco 10000 series router for the PRE3 and PRE4 as described in the Usage Guidelines.
12.2(33)SRD1	Support for this command was extended to service instance configuration mode.
12.2(33)SRE6	This command was modified. This command must be enabled on each subinterface from this release onwards.
15.1(3)S3	This command was integrated into Cisco IOS Release 15.1(3)S3.

Usage Guidelines

By default, SNMP link traps are sent when an interface goes up or down. For interfaces such as ISDN interfaces, expected to go up and down during normal usage, the output generated by these traps may not be useful. The **no** form of this command disables these traps.

The **permit** and **duplicates** keywords are used together and cannot be used individually. Use the **permit duplicates** keyword pair when an interface is not generating SNMP linkup traps, linkdown traps, or both. When the **snmp trap link-status permit duplicates** command is configured, more than one trap may be sent for the same linkup or linkdown transition.

The **permit duplicates** keyword pair does not guarantee that SNMP link traps will be generated nor should configuring these keywords be required to receive traps.

By default, in service instance configuration mode, SNMP link traps are not sent. Also, the **permit duplicates** keyword pair is not available in service instance configuration mode.

The **snmp trap link-status** command must be used in conjunction with the **snmp-server enable traps atm subif** command in order to enable SNMP trap notifications on ATM subinterfaces. The **snmp-server enable traps atm subif** command must be configured in global configuration mode, and then the **snmp trap link-status** command must be configured on each ATM subinterface for which you want to enable SNMP trap notifications.

Cisco 10000 Series Router

In Cisco IOS Release 12.2(33)SB, the **virtual-template snmp** command has a new default configuration. Instead of being enabled by default, **no virtual-template snmp** is the default configuration. This setting enhances scaling and prevents large numbers of entries in the MIB ifTable, thereby avoiding CPU Hog messages as SNMP uses the interfaces MIB and other related MIBs.

If you configure the **no virtual-template snmp** command, the device no longer accepts the **snmp trap link-status** command under a virtual-template interface. Instead, the device displays a configuration error message such as the following:

```
Device(config)# interface virtual-template 1
Device(config-if)# snmp trap link-status
%Unable set link-status enable/disable for interface
```

If your configuration already has the **snmp trap link-status** command configured under a virtual-template interface and you upgrade to Cisco IOS Release 12.2(33)SB, the configuration error occurs when the device reloads even though the virtual template interface is already registered in the interfaces MIB.

Examples

The following example shows how to disable SNMP link traps related to the ISDN BRI interface 0:

```
Device(config)# interface bri 0
Device(config-if)# no snmp trap link-status
```

The following example shows how to enable SNMP link traps for service instance 50 on Ethernet interface 0/1:

```
Device(config)# interface ethernet 0/1
Device(config-if)# service instance 50 ethernet
Device(config-if-srv)# snmp trap link-status
Device(config-if-srv)# end
```

Related Commands

Command	Description
snmp-server enable traps atm subif	Enables the sending of ATM subinterface SNMP notifications.
virtual-template snmp	Allows virtual access interfaces to register with SNMP when they are created or reused.

snmp set

To set or modify the value of an object variable during the Simple Network Management Protocol (SNMP) set operation, use the **snmp set** command in privileged EXEC mode.

snmp set {**v1**|**v2c**|**v3**} *ip-address* [**vrf** *vrf-name*] *community-string* [**retry** *number*] [**timeout** *seconds*] **oid** *oid-value* *oid-type* *oid-type-value*

Syntax Description

v1	Specifies the use of the SNMPv1 security model for a set operation.
v2c	Specifies the use of the SNMPv2c security model for a set operation.
v3	Specifies the use of the SNMPv3 security model for a set operation.
<i>ip-address</i>	IPv4 or IPv6 address of the SNMP host.
vrf	(Optional) Specifies the use of a Virtual Private Network (VPN) routing and forwarding (VRF) instance to send SNMP notifications.
<i>vrf-name</i>	(Optional) Name or instance of a VPN VRF.
<i>community-string</i>	SNMP community string. A community string functions like a password to access the SNMP entity. The string can consist of 1 to 32 alphanumeric characters.
retry <i>number</i>	(Optional) Specifies the number of retries to consider for a set operation. The valid range is from 1 to 10.
timeout <i>seconds</i>	(Optional) Specifies the interval of time between each attempt to set data, in seconds. The valid range is from 1 to 1000.
oid	Specifies the object identifier value of the variable to set.
<i>oid-value</i>	The object identifier value. For example, sysName.0 or 1.3.6.1.4.1.9.9.10.1.3.0.5

<i>oid-type</i>	<p>The type of OID. The following values are valid:</p> <ul style="list-style-type: none"> • counter --A 32-bit number with a minimum value of 0. When the maximum value is reached, the counter resets to 0. • gauge --A 32-bit number with a minimum value of 0. For example, the interface speed on a router is measured using a gauge object type. • integer --A 32-bit number used to specify a numbered type within the context of a managed object. For example, to set the operational status of a router interface, 1 represents up and 2 represents down. • ip-address --IP address. • string --An octet string in text notation used to represent text strings. • timeticks --Specifies a value based on time ticks. Time ticks represents an integer value that specifies the elapsed time between two events, in units of hundredth of a second.
<i>oid-type-value</i>	<p>Integer or text string value of the OID type specified for the SNMP set operation. The following list describes the integer or text string values that are valid with each <i>oid-type</i> argument value:</p> <ul style="list-style-type: none"> • counter --Integer value in the range from 0 to 4294967295. • gauge --Integer value in the range from 0 to 4294967295. • integer --Integer value in the range from 0 to 4294967295. • ip-address --IP address in dotted decimal notation. • string --Text string. • timeticks --Integer value in the range from 0 to 4294967295.

Command Default

No variable is set by default.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
12.2(33)SRC	This command was introduced.
12.2(33)SXI	This command was integrated into Cisco IOS Release 12.2(33)SXI.

Usage Guidelines

The SNMP set operation modifies the individual variables in the SNMP entity.

The community string for a set operation can be set to either of the following types:

- ro--Sets the read-only access to the SNMP entity. The default value for this community string is public.
- rw--Sets read-write access to the SNMP entity. The default value for this community string is private.

Examples

The following example shows how to set the variable using SNMPv2c:

```
Router# snmp set v2c 10.16.2.8 public retry 2 timeout 60 oid 1.3.6.1.4.1.9.9.96.1.1.1.1.2.17
integer 4
SNMP Response: reqid 10, errstat 0, erridx 0
ccCopyTable.1.2.17 = 4
```

Related Commands

Command	Description
snmp-server community	Sets the community access string to enable access to an SNMP entity.

snmp-server cache

To enable the Simple Network Management Protocol (SNMP) cache and configure the SNMP cache expiry interval, use the **snmp-server cache** command in global configuration mode. To disable the cache for MIBs that are kept by the SNMP engine, use the **no** form of this command.

snmp-server cache [*interval seconds*]

no snmp-server cache

Syntax Description

<i>interval</i>	(Optional) Specifies the SNMP cache interval.
<i>seconds</i>	(Optional) SNMP cache interval, in seconds. Valid values are from 1 to 300. Default is 5.

Command Default

By default, the SNMP cache is enabled. The default expiry interval value is 5 seconds .

Command Modes

Global configuration (config)

Command History

Release	Modification
12.2(33)SXH	This command was introduced.

Usage Guidelines

This command is used in distributed or modular environments. The SNMP engine cache maintains the cache for MIBs.

Examples

The following example shows how to set the SNMP cache interval to 60 seconds:

```
Router(config)# snmp-server cache interval 60
```

This example shows how to disable the SNMP cache:

```
Router(config)# no snmp-server cache
```

Related Commands

Command	Description
snmp-server community	Sets the community access string to enable access to the SNMP entity.
snmp-server manager	Starts the SNMP server manager configuration process.

snmp-server contact

To set the system contact (sysContact) string, use the **snmp-server contact** command in global configuration mode. To remove the system contact information, use the **no** form of this command.

snmp-server contact *text*

no snmp-server contact

Syntax Description

<i>text</i>	String that describes the system contact information.
-------------	---

Command Default

No system contact string is set.

Command Modes

Global configuration

Command History

Release	Modification
10.0	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.

Examples

The following is an example of a system contact string:

```
Router(config)# snmp-server contact Dial System Operator at beeper # 27345
```

Related Commands

Command	Description
show snmp contact	Displays SNMP system contact information.
snmp-server location	Sets the system location string.

snmp-server context

To create a Simple Network Management Protocol (SNMP) context, use the **snmp-server context** command in global configuration mode. To delete an SNMP context, use the **no** form of this command.

snmp-server context *context-name*

no snmp-server context *context-name*

Syntax Description

<i>context-name</i>	Name of the SNMP context being created.
---------------------	---

Command Default

No SNMP contexts are configured.

Command Modes

Global configuration (config)

Command History

Release	Modification
12.0(23)S	This command was introduced.
12.3(2)T	This command was integrated into Cisco IOS Release 12.3(2)T.
12.2(25)S	This command was integrated into Cisco IOS Release 12.2(25)S.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2(31)SB2	This command was integrated into Cisco IOS Release 12.2(31)SB2.
12.2(33)SXH	This command was integrated into Cisco IOS Release 12.2(33)SXH.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
12.2(33)SB	This command was integrated into Cisco IOS Release 12.2(33)SB.
15.1(1)SY	This command was integrated into Cisco IOS Release 15.1(1)SY.

Usage Guidelines

When you use the **no snmp-server context** command, all SNMP instances in that context are deleted.

A route distinguisher (RD) is required when you configure an SNMP context. An RD creates routing and forwarding tables and specifies the default route distinguisher for a VPN. The RD is added to the beginning of a IPv4 prefix to make it globally unique. An RD is either ASN relative, which means it is composed of an

autonomous system number and an arbitrary number, or it is IP address relative and composed of an IP address and an arbitrary number.

Examples

The following example shows how to create an SNMP context named contextA and associate it with a virtual private network (VPN) routing and forwarding (VRF) instance named CustomerA:

```
Router(config)#
snmp-server context contextA
Router(config)# ip vrf CustomerA
Router(config-vrf)# rd 100:120
Router(config-vrf)# context contextA
```

Related Commands

Command	Description
context	Associates an SNMP context with a particular VRF.

snmp-server drop vrf-traffic

To configure a router to drop Simple Network Management Protocol (SNMP) packets coming from virtual routing and forwarding (VRF) interfaces, use the **snmp-server drop vrf-traffic** command in global configuration mode. To disable the configuration, use the **no** form of this command.

snmp-server drop vrf-traffic

no snmp-server drop vrf-traffic

Syntax Description This command has no arguments or keywords.

Command Default SNMP packets are not dropped from VRF interfaces.

Command Modes Global configuration (config)

Command History	Release	Modification
	15.0(1)M	This command was introduced in a release earlier than Cisco IOS Release 15.0(1)M.

Examples The following example shows how to configure a router to drop SNMP packets coming from VRF interfaces:

```
Router(config)# snmp-server drop vrf-traffic
```

Related Commands	Command	Description
	snmp-server chassis-id	Provides a message line identifying the SNMP server serial number.

snmp-server enable informs



Note

Effective with Cisco IOS Release 12.2(33)SXI, the **snmp-server enable informs** command is not available in Cisco IOS software.

This command has no functionality. To enable the sending of Simple Network Management Protocol (SNMP) inform notifications, use one of the **snmp-server enable trapsnotification-type** commands in global configuration mode combined with the **snmp-server hosthost-address informs** command in global configuration mode.

Command History

Release	Modification
10.0	This command was introduced.
12.2(33)SXI	This command was removed. Instead use one of the snmp-server enable trapsnotification-type commands in global configuration mode combined with the snmp-server hosthost-address informs command in global configuration mode.