



Cisco Security Appliance Command Reference

For the Cisco ASA 5500 Series and Cisco PIX 500 Series

Software Version 7.0(8)

Corporate Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 526-4100

Text Part Number: OL-6935-03



THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Cisco ASA 5500 Series Command Reference, Version 7.0.8

 Printed in the USA on recycled paper containing 10% postconsumer waste.

CCSP, CCVP, the Cisco Square Bridge logo, Follow Me Browsing, and StackWise are trademarks of Cisco Systems, Inc.; Changing the Way We Work, Live, Play, and Learn and iQuick Study are service marks of Cisco Systems, Inc.; and Access Registrar, Aironet, BPX, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Enterprise/Solver, EtherChannel, EtherFast, EtherSwitch, Fast Step, FormShare, GigaDrive, GigaStack, HomeLink, Internet Quotient, IOS, IP/TV, iQ Expertise, the iQ logo, iQ Net Readiness Scorecard, LightStream, Linksys, MeetingPlace, MGX, the Networkers logo, Networking Academy, Network Registrar, *Packet*, PIX, Post-Routing, Pre-Routing, ProConnect, RateMUX, ScriptShare, SlideCast, SMARTnet, The Fastest Way to Increase Your Internet Quotient, and TransPath are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0601R)

Copyright © 2008 Cisco Systems, Inc. All rights reserved.



About This Guide xxxvii

Document Objectives	xxxvii
Audience	xxxviii
Document Organization	xxxviii
Document Conventions	xxxviii
Related Documentation	xxxix
Obtaining Documentation	xxxix
Documentation Feedback	xl
Obtaining Technical Assistance	xl
Obtaining Additional Publications and Information	xlii

Using the Command-Line Interface 1-1

Firewall Mode and Security Context Mode	1-1
Command Modes and Prompts	1-2
Syntax Formatting	1-3
Abbreviating Commands	1-3
Command-Line Editing	1-3
Command Completion	1-3
Command Help	1-4
Filtering show Command Output	1-4
Command Output Paging	1-5
Adding Comments	1-5
Text Configuration Files	1-6

A through B Commands 2-1

aaa accounting	2-2
aaa accounting console	2-5
aaa accounting command	2-7
aaa accounting match	2-9
aaa authentication	2-11
aaa authentication console	2-17
aaa authentication match	2-20
aaa authentication secure-http-client	2-22

aaa authorization	2 - 24
aaa authorization command	2 - 28
aaa authorization match	2 - 30
aaa local authentication attempts max-fail	2 - 32
aaa mac-exempt	2 - 34
aaa proxy-limit	2 - 36
aaa-server host	2 - 38
aaa-server protocol	2 - 41
absolute	2 - 43
accept-subordinates	2 - 45
access-group	2 - 46
access-list alert-interval	2 - 48
access-list deny-flow-max	2 - 50
access-list ethertype	2 - 52
access-list extended	2 - 54
access-list remark	2 - 61
access-list standard	2 - 63
access-list webtype	2 - 65
accounting-mode	2 - 67
accounting-port	2 - 69
accounting-server-group	2 - 71
accounting-server-group (webvpn)	2 - 73
acl-netmask-convert	2 - 75
activation-key	2 - 77
address-pool	2 - 78
admin-context	2 - 80
alias	2 - 82
allocate-interface	2 - 85
area	2 - 88
area authentication	2 - 90
area default-cost	2 - 92
area filter-list prefix	2 - 94
area nssa	2 - 96
area range	2 - 98
area stub	2 - 100

- area virtual-link 2 - 102
- arp 2 - 105
- arp timeout 2 - 107
- arp-inspection 2 - 108
- asdm disconnect 2 - 110
- asdm disconnect log_session 2 - 112
- asdm group 2 - 114
- asdm history enable 2 - 115
- asdm image 2 - 116
- asdm location 2 - 118
- asr-group 2 - 119
- authentication 2 - 121
- authentication chap** 2 - 123
- authentication-port 2 - 125
- authentication-server-group** 2 - 127
- authentication-server-group (webvpn) 2 - 129
- authorization-dn-attributes** 2 - 131
- authorization-dn-attributes (webvpn) 2 - 133
- authorization-required** 2 - 135
- authorization-required (webvpn) 2 - 137
- authorization-server-group** 2 - 138
- authorization-server-group (webvpn) 2 - 140
- auth-prompt 2 - 142
- auto-update device-id 2 - 144
- auto-update poll-period 2 - 146
- auto-update server 2 - 148
- auto-update timeout 2 - 150
- backup-servers 2 - 152
- banner 2 - 154
- banner (group-policy) 2 - 156
- blocks 2 - 157
- boot 2 - 159

C Commands 3 - 1

- cache-time 3 - 2
- call-agent 3 - 3

- capture 3 - 5
- cd 3 - 12
- certificate 3 - 13
- chain** 3 - 15
- changeto 3 - 17
- checkheaps 3 - 19
- check-retransmission 3 - 21
- checksum-verification 3 - 23
- class (policy-map) 3 - 25
- class-map 3 - 27
- clear aaa local user fail-attempts 3 - 29
- clear aaa local user logout 3 - 31
- clear aaa-server statistics 3 - 33
- clear access-group 3 - 35
- clear access-list 3 - 36
- clear arp statistics 3 - 37
- clear asp drop 3 - 38
- clear blocks 3 - 40
- clear capture 3 - 41
- clear configure 3 - 42
- clear configure aaa** 3 - 44
- clear configure aaa-server 3 - 45
- clear configure access-group 3 - 47
- clear configure access-list 3 - 48
- clear configure alias 3 - 50
- clear configure arp-inspection 3 - 51
- clear configure asdm 3 - 52
- clear configure auth-prompt** 3 - 54
- clear configure banner 3 - 55
- clear configure ca certificate map 3 - 56
- clear configure class-map 3 - 57
- clear configure clock 3 - 58
- clear configure command-alias 3 - 59
- clear configure console 3 - 60
- clear configure context 3 - 61

clear configure crypto	3 - 63
clear configure crypto ca trustpoint	3 - 64
clear configure crypto dynamic-map	3 - 65
clear configure crypto map	3 - 66
clear configure dhcpd	3 - 67
clear configure dhcprelay	3 - 68
clear configure dns	3 - 69
clear configure established	3 - 70
clear configure failover	3 - 71
clear configure filter	3 - 72
clear configure fips	3 - 73
clear configure firewall	3 - 74
clear configure fixup	3 - 75
clear configure fragment	3 - 76
clear configure ftp	3 - 78
clear configure ftp-map	3 - 79
clear configure global	3 - 80
clear configure group-policy	3 - 81
clear configure gtp-map	3 - 82
clear configure http	3 - 83
clear configure http-map	3 - 84
clear configure icmp	3 - 85
clear configure imap4s	3 - 86
clear configure interface	3 - 87
clear configure ip	3 - 89
clear configure ip audit	3 - 90
clear configure ip local pool	3 - 91
clear configure ip verify reverse-path	3 - 92
clear configure ipv6	3 - 93
clear configure isakmp	3 - 94
clear configure isakmp policy	3 - 95
clear configure logging	3 - 96
clear configure mac-address-table	3 - 98
clear configure mac-learn	3 - 99
clear configure mac-list	3 - 100

clear configure management-access	3 - 101
clear configure mgcp-map	3 - 102
clear configure mroute	3 - 103
clear configure mtu	3 - 104
clear configure multicast-routing	3 - 105
clear configure name	3 - 106
clear configure nat	3 - 107
clear configure ntp	3 - 108
clear configure object-group	3 - 109
clear configure passwd	3 - 110
clear configure pim	3 - 111
clear configure policy-map	3 - 112
clear configure pop3s	3 - 113
clear configure port-forward	3 - 114
clear configure prefix-list	3 - 115
clear configure priority-queue	3 - 116
clear configure privilege	3 - 117
clear configure rip	3 - 118
clear configure route	3 - 119
clear configure route-map	3 - 120
clear configure router	3 - 121
clear configure service-policy	3 - 122
clear configure smtps	3 - 123
clear configure snmp-map	3 - 124
clear configure snmp-server	3 - 125
clear configure ssh	3 - 126
clear configure ssl	3 - 127
clear configure static	3 - 128
clear configure sunrpc-server	3 - 129
clear configure sysopt	3 - 130
clear configure tcp-map	3 - 131
clear configure telnet	3 - 132
clear configure terminal	3 - 133
clear configure timeout	3 - 134
clear configure tunnel-group	3 - 135

clear configure url-block	3 - 136
clear configure url-cache	3 - 137
clear configure url-list	3 - 138
clear configure url-server	3 - 139
clear configure username	3 - 140
clear configure virtual	3 - 141
clear configure vpn-load-balancing	3 - 142
clear console-output	3 - 143
clear counters	3 - 144
clear crashinfo	3 - 145
clear crypto accelerator statistics	3 - 146
clear crypto ca crls	3 - 147
clear [crypto] ipsec sa	3 - 148
clear crypto protocol statistics	3 - 150
clear dhcpd	3 - 152
clear dhcprelay statistics	3 - 153
clear dns-hosts cache	3 - 154
clear failover statistics	3 - 155
clear fragment	3 - 156
clear gc	3 - 157
clear igmp counters	3 - 158
clear igmp group	3 - 159
clear igmp traffic	3 - 160
clear interface	3 - 161
clear ip audit count	3 - 163
clear ip verify statistics	3 - 164
clear ipsec sa	3 - 165
clear ipv6 access-list counters	3 - 166
clear ipv6 neighbors	3 - 167
clear ipv6 traffic	3 - 168
clear isakmp sa	3 - 170
clear local-host	3 - 171
clear logging asdm	3 - 173
clear logging buffer	3 - 174
clear mac-address-table	3 - 175

clear memory profile 3 - 176

clear mfib counters 3 - 177

clear module recover 3 - 178

clear ospf 3 - 179

clear pim counters 3 - 181

clear pim reset 3 - 182

clear pim topology 3 - 183

clear priority-queue statistics 3 - 184

clear resource usage 3 - 185

clear route 3 - 187

clear service-policy 3 - 188

clear service-policy inspect gtp 3 - 190

clear shun 3 - 192

clear sunrpc-server active 3 - 193

clear traffic 3 - 194

clear uauth 3 - 195

clear url-block block statistics 3 - 197

clear url-cache statistics 3 - 199

clear url-server 3 - 201

clear xlate 3 - 202

client-access-rule 3 - 204

client-firewall 3 - 206

client-update 3 - 208

clock set 3 - 210

clock summer-time 3 - 212

clock timezone 3 - 214

cluster encryption 3 - 216

cluster ip address 3 - 218

cluster key 3 - 220

cluster port 3 - 222

command-alias 3 - 224

command-queue 3 - 226

compatible rfc1583 3 - 228

config-register 3 - 229

configure factory-default 3 - 232

- [configure http](#) 3 - 235
- [configure memory](#) 3 - 237
- [configure net](#) 3 - 239
- [configure terminal](#) 3 - 241
- [config-url](#) 3 - 242
- [console timeout](#) 3 - 245
- [content-length](#) 3 - 246
- [content-type-verification](#) 3 - 248
- [context](#) 3 - 250
- [copy](#) 3 - 252
- [copy capture](#) 3 - 254
- [crashinfo console disable](#) 3 - 257
- [crashinfo force](#) 3 - 259
- [crashinfo save disable](#) 3 - 261
- [crashinfo test](#) 3 - 263
- [crl](#) 3 - 264
- [crl configure](#) 3 - 265
- [crypto ca authenticate](#) 3 - 266
- [crypto ca certificate chain](#) 3 - 268
- [crypto ca certificate map](#) 3 - 269
- [crypto ca crl request](#) 3 - 271
- [crypto ca enroll](#) 3 - 272
- [crypto ca export](#) 3 - 274
- [crypto ca import](#) 3 - 276
- [crypto ca trustpoint](#) 3 - 278
- [crypto dynamic-map match address](#) 3 - 281
- [crypto dynamic-map set nat-t-disable](#) 3 - 282
- [crypto dynamic-map set peer](#) 3 - 283
- [crypto dynamic-map set pfs](#) 3 - 284
- [crypto dynamic-map set reverse route](#) 3 - 286
- [crypto map set security-association lifetime](#) 3 - 287
- [crypto dynamic-map set transform-set](#) 3 - 289
- [crypto ipsec df-bit](#) 3 - 291
- [crypto ipsec fragmentation](#) 3 - 293
- [crypto ipsec security-association lifetime](#) 3 - 295

crypto ipsec transform-set	3 - 297
crypto ipsec transform-set mode transport	3 - 300
crypto key generate dsa	3 - 302
crypto key generate rsa	3 - 304
crypto key zeroize	3 - 306
crypto map interface	3 - 307
crypto map ipsec-isakmp dynamic	3 - 309
crypto map match address	3 - 311
crypto map set connection-type	3 - 313
crypto map set inheritance	3 - 315
crypto map set nat-t-disable	3 - 317
crypto map set peer	3 - 318
crypto map set pfs	3 - 320
crypto map set phase1 mode	3 - 322
crypto map set reverse-route	3 - 324
crypto map set security-association lifetime	3 - 325
crypto map set transform-set	3 - 327
crypto map set trustpoint	3 - 329

D through F Commands 4 - 1

debug aaa	4 - 2
debug arp	4 - 4
debug arp-inspection	4 - 5
debug asdm history	4 - 6
debug cmgr	4 - 7
debug context	4 - 9
debug cplane	4 - 10
debug crypto ca	4 - 12
debug crypto engine	4 - 13
debug crypto ipsec	4 - 14
debug crypto isakmp	4 - 15
debug ctique	4 - 16
	4 - 18
debug dhcpc	4 - 19
debug dhcpd	4 - 21
debug dhcprelay	4 - 23

debug disk	4 - 25
debug dns	4 - 27
debug entity	4 - 28
4 - 30	
debug fixup	4 - 31
debug fover	4 - 32
debug fsm	4 - 34
debug ftp client	4 - 36
debug generic	4 - 38
debug gtp	4 - 40
debug h323	4 - 42
debug http	4 - 44
debug http-map	4 - 45
debug icmp	4 - 46
debug igmp	4 - 48
debug ils	4 - 50
debug imagemgr	4 - 52
debug ipsec-over-tcp	4 - 54
debug ipsec-pass-thru	4 - 56
debug ipv6	4 - 57
debug iua-proxy	4 - 59
debug kerberos	4 - 61
debug ldap	4 - 63
debug mac-address-table	4 - 65
debug menu	4 - 67
debug mfib	4 - 68
debug mgcp	4 - 70
debug module-boot	4 - 71
debug mrib	4 - 73
debug ntdomain	4 - 75
debug ntp	4 - 77
debug ospf	4 - 79
debug parser cache	4 - 81
debug pim	4 - 83
debug pix pkt2pc	4 - 85

[debug pix process](#) 4 - 86

[debug pptp](#) 4 - 87

[debug radius](#) 4 - 89

[debug rip](#) 4 - 92

[debug rtsp](#) 4 - 94

[debug sdi](#) 4 - 96

[debug sequence](#) 4 - 98

[debug session-command](#) 4 - 100

[debug sip](#) 4 - 101

[debug skinny](#) 4 - 103

[debug smtp](#) 4 - 105

[debug sqlnet](#) 4 - 107

[debug ssh](#) 4 - 109

[debug ssl](#) 4 - 111

[debug sunrpc](#) 4 - 113

[debug tacacs](#) 4 - 115

[debug tcp-map](#) 4 - 117

[debug timestamps](#) 4 - 119

[debug vpn-sessiondb](#) 4 - 121

[debug xdmcp](#) 4 - 123

[default](#) 4 - 125

[default \(crl configure\)](#) 4 - 127

[default \(time-range\)](#) 4 - 128

[default enrollment](#) 4 - 130

[default-domain](#) 4 - 131

[default-group-policy](#) 4 - 133

[default-group-policy \(webvpn\)](#) 4 - 135

[default-idle-timeout](#) 4 - 137

[default-information originate](#) 4 - 139

[delete](#) 4 - 141

[deny version](#) 4 - 142

[description](#) 4 - 144

[dhcp-network-scope](#) 4 - 146

[dhcp-server](#) 4 - 147

[dhcpd address](#) 4 - 149

[dhcpcd auto_config](#) 4 - 151

[dhcpcd dns](#) 4 - 153

[dhcpcd domain](#) 4 - 155

[dhcpcd enable](#) 4 - 157

[dhcpcd lease](#) 4 - 159

[dhcpcd option](#) 4 - 161

[dhcpcd ping_timeout](#) 4 - 163

[dhcpcd wins](#) 4 - 165

[dhcprelay enable](#) 4 - 167

[dhcprelay server](#) 4 - 169

[dhcprelay setroute](#) 4 - 171

[dhcprelay timeout](#) 4 - 173

[dir](#) 4 - 175

[disable](#) 4 - 177

[distance ospf](#) 4 - 178

[dns domain-lookup](#) 4 - 180

[dns-guard](#) 4 - 182

[dns name-server](#) 4 - 184

[dns retries](#) 4 - 186

[dns timeout](#) 4 - 187

[dns-server](#) 4 - 188

[domain-name](#) 4 - 189

[downgrade](#) 4 - 191

[drop](#) 4 - 195

[duplex](#) 4 - 197

[email](#) 4 - 199

[enable](#) 4 - 200

[enable \(webvpn\)](#) 4 - 202

[enable password](#) 4 - 203

[enforcenextupdate](#) 4 - 205

[enrollment retry count](#) 4 - 206

[enrollment retry period](#) 4 - 208

[enrollment terminal](#) 4 - 209

[enrollment url](#) 4 - 210

[erase](#) 4 - 211

established 4 - 213

exceed-mss 4 - 216

exit 4 - 218

failover 4 - 220

failover active 4 - 222

failover group 4 - 223

failover interface ip 4 - 225

failover interface-policy 4 - 227

failover key 4 - 229

failover lan enable 4 - 231

failover lan interface 4 - 233

failover lan unit 4 - 235

failover link 4 - 237

failover mac address 4 - 240

failover polltime 4 - 242

failover reload-standby 4 - 244

failover replication http 4 - 245

failover reset 4 - 247

failover timeout 4 - 248

filter 4 - 250

filter activex 4 - 252

filter ftp 4 - 254

filter https 4 - 256

filter java 4 - 258

filter url 4 - 260

fips enable 4 - 264

fips self-test poweron 4 - 266

firewall transparent 4 - 267

format 4 - 269

fqdn 4 - 271

fragment 4 - 272

ftp-map 4 - 274

ftp mode passive 4 - 276

functions 4 - 278

G through L Commands	5 - 1
gateway	5 - 2
global	5 - 4
group-delimiter	5 - 7
group-lock	5 - 8
group-object	5 - 9
group-policy	5 - 11
group-policy attributes	5 - 14
gtp-map	5 - 16
help	5 - 18
homepage	5 - 20
hostname	5 - 21
html-content-filter	5 - 22
http	5 - 24
http authentication-certificate	5 - 26
http redirect	5 - 28
http server enable	5 - 30
http-map	5 - 31
http-proxy	5 - 34
https-proxy	5 - 35
hw-module module recover	5 - 36
hw-module module reload	5 - 38
hw-module module reset	5 - 40
hw-module module shutdown	5 - 42
icmp	5 - 44
icmp-object	5 - 47
id-cert-issuer	5 - 49
igmp	5 - 51
igmp access-group	5 - 52
igmp forward interface	5 - 53
igmp join-group	5 - 54
igmp limit	5 - 56
igmp query-interval	5 - 57
igmp query-max-response-time	5 - 59
igmp query-timeout	5 - 61

igmp static-group	5 - 62
igmp version	5 - 63
ignore lsa mospf	5 - 65
imap4s	5 - 66
inspect ctiqbe	5 - 67
inspect cuseeme	5 - 69
inspect dns	5 - 71
inspect esmtp	5 - 74
inspect ftp	5 - 77
inspect gtp	5 - 80
inspect h323	5 - 82
inspect http	5 - 86
inspect icmp	5 - 89
inspect icmp error	5 - 91
inspect ils	5 - 93
inspect ipsec-pass-thru	5 - 95
inspect mgcp	5 - 97
inspect netbios	5 - 100
inspect pptp	5 - 102
inspect rsh	5 - 104
inspect rtsp	5 - 106
inspect sip	5 - 109
inspect skinny	5 - 112
inspect snmp	5 - 115
inspect sqlnet	5 - 117
inspect sunrpc	5 - 119
inspect tftp	5 - 121
inspect xdmcp	5 - 123
intercept-dhcp	5 - 125
interface	5 - 126
interface (vpn load-balancing)	5 - 129
interface-policy	5 - 131
ip-address	5 - 133
ip address	5 - 134
ip address dhcp	5 - 136

ip audit attack	5 - 138
ip audit info	5 - 140
ip audit interface	5 - 142
ip audit name	5 - 144
ip audit signature	5 - 146
ip local pool	5 - 155
ip-comp	5 - 157
ip-phone-bypass	5 - 158
ips	5 - 159
ipsec-udp	5 - 161
ipsec-udp-port	5 - 163
ip verify reverse-path	5 - 164
ipv6 access-list	5 - 166
ipv6 address	5 - 170
ipv6 enable	5 - 172
ipv6 icmp	5 - 173
ipv6 nd dad attempts	5 - 176
ipv6 nd ns-interval	5 - 178
ipv6 nd prefix	5 - 179
ipv6 nd ra-interval	5 - 181
ipv6 nd ra-lifetime	5 - 183
ipv6 nd reachable-time	5 - 185
ipv6 nd suppress-ra	5 - 186
ipv6 neighbor	5 - 187
ipv6 route	5 - 189
isakmp am-disable	5 - 191
isakmp disconnect-notify	5 - 192
isakmp enable	5 - 193
isakmp identity	5 - 194
isakmp ipsec-over-tcp	5 - 196
isakmp keepalive	5 - 197
isakmp nat-traversal	5 - 199
isakmp policy authentication	5 - 201
isakmp policy encryption	5 - 203
isakmp policy group	5 - 205

isakmp policy hash	5 - 207
isakmp policy lifetime	5 - 209
isakmp reload-wait	5 - 211
issuer-name	5 - 212
join-failover-group	5 - 214
kerberos-realm	5 - 216
key	5 - 218
keypair	5 - 220
kill	5 - 221
l2tp tunnel hello	5 - 222
ldap-base-dn	5 - 223
ldap-defaults	5 - 225
ldap-dn	5 - 226
ldap-login-dn	5 - 228
ldap-login-password	5 - 230
ldap-naming-attribute	5 - 232
ldap-scope	5 - 234
leap-bypass	5 - 236
log-adj-changes	5 - 238
login	5 - 239
logging asdm	5 - 241
logging asdm-buffer-size	5 - 243
logging buffered	5 - 245
logging buffer-size	5 - 247
logging class	5 - 249
logging console	5 - 252
logging debug-trace	5 - 254
logging device-id	5 - 256
logging emblem	5 - 258
logging enable	5 - 260
logging facility	5 - 262
logging flash-bufferwrap	5 - 264
logging flash-maximum-allocation	5 - 266
logging flash-minimum-free	5 - 268
logging from-address	5 - 270

- logging ftp-bufferwrap 5 - 272
- logging ftp-server 5 - 274
- logging history 5 - 276
- logging host 5 - 278
- logging list 5 - 280
- logging mail 5 - 283
- logging message 5 - 285
- logging monitor 5 - 287
- logging permit-hostdown 5 - 289
- logging queue 5 - 291
- logging rate-limit 5 - 293
- logging recipient-address 5 - 295
- logging savelog 5 - 297
- logging standby 5 - 299
- logging timestamp 5 - 301
- logging trap 5 - 302
- login-message 5 - 304
- logo 5 - 305
- logout 5 - 306
- logout-message 5 - 307

M through R Commands 6 - 1

- mac address 6 - 2
- mac-address-table aging-time 6 - 4
- mac-address-table static 6 - 5
- mac-learn 6 - 7
- mac-list 6 - 9
- management-access 6 - 11
- management-only 6 - 13
- mask-syst-reply 6 - 15
- match access-list 6 - 16
- match any 6 - 18
- match default-inspection-traffic 6 - 20
- match dscp 6 - 22
- match flow ip destination-address 6 - 24
- match interface 6 - 26

[match ip address](#) 6 - 28

[match ip next-hop](#) 6 - 30

[match ip route-source](#) 6 - 32

[match metric](#) 6 - 34

[match port](#) 6 - 36

[match precedence](#) 6 - 38

[match route-type](#) 6 - 40

[match rtp](#) 6 - 42

[match tunnel-group](#) 6 - 44

[max-failed-attempts](#) 6 - 46

[max-header-length](#) 6 - 48

[max-uri-length](#) 6 - 50

[mcc](#) 6 - 52

[media-type](#) 6 - 54

[memory caller-address](#) 6 - 56

[memory profile enable](#) 6 - 58

[memory profile text](#) 6 - 60

[message-length](#) 6 - 62

[mgcp-map](#) 6 - 64

[mkdir](#) 6 - 66

[mode](#) 6 - 67

[monitor-interface](#) 6 - 70

[more](#) 6 - 72

[mroute](#) 6 - 74

[mtu](#) 6 - 76

[multicast-routing](#) 6 - 78

[name](#) 6 - 80

[nameif](#) 6 - 82

[names](#) 6 - 84

[name-separator](#) 6 - 85

[nat](#) 6 - 86

[nat \(vpn load-balancing\)](#) 6 - 92

[nat-control](#) 6 - 94

[nbns-server](#) 6 - 96

[neighbor](#) 6 - 98

nem	6 - 100
network area	6 - 101
network-object	6 - 103
nt-auth-domain-controller	6 - 105
ntp authenticate	6 - 107
ntp authentication-key	6 - 109
ntp server	6 - 111
ntp trusted-key	6 - 113
object-group	6 - 115
ospf authentication	6 - 120
ospf authentication-key	6 - 122
ospf cost	6 - 123
ospf database-filter	6 - 125
ospf dead-interval	6 - 126
ospf hello-interval	6 - 127
ospf message-digest-key	6 - 128
ospf mtu-ignore	6 - 130
ospf network point-to-point non-broadcast	6 - 131
ospf priority	6 - 133
ospf retransmit-interval	6 - 134
ospf transmit-delay	6 - 135
outstanding	6 - 136
participate	6 - 137
passwd	6 - 139
password (crypto ca trustpoint)	6 - 141
password-prompt	6 - 143
password-storage	6 - 144
peer-id-validate	6 - 145
perfmon	6 - 147
periodic	6 - 149
permit errors	6 - 151
permit response	6 - 153
pfs	6 - 155
pim	6 - 156
pim accept-register	6 - 157

[pim dr-priority](#) 6 - 158

[pim hello-interval](#) 6 - 159

[pim join-prune-interval](#) 6 - 160

[pim old-register-checksum](#) 6 - 161

[pim rp-address](#) 6 - 162

[pim spt-threshold infinity](#) 6 - 164

[ping](#) 6 - 165

[police](#) 6 - 167

[policy](#) 6 - 169

[policy-map](#) 6 - 170

[polltime interface](#) 6 - 172

[pop3s](#) 6 - 174

[port](#) 6 - 175

[port-forward](#) 6 - 176

[port-forward \(webvpn\)](#) 6 - 178

[port-forward-name](#) 6 - 180

[port-misuse](#) 6 - 181

[port-object](#) 6 - 183

[preempt](#) 6 - 186

[prefix-list](#) 6 - 188

[prefix-list description](#) 6 - 191

[prefix-list sequence-number](#) 6 - 193

[pre-shared-key](#) 6 - 194

[primary](#) 6 - 195

[priority](#) 6 - 197

[priority \(vpn load balancing\)](#) 6 - 198

[priority-queue](#) 6 - 200

[privilege](#) 6 - 202

[protocol http](#) 6 - 204

[protocol ldap](#) 6 - 205

[protocol scep](#) 6 - 206

[protocol-object](#) 6 - 207

[pwd](#) 6 - 209

[queue-limit \(priority-queue\)](#) 6 - 210

[queue-limit \(tcp-map\)](#) 6 - 212

[quit](#) 6 - 214
[radius-common-pw](#) 6 - 216
[radius-with-expiry](#) 6 - 218
[reactivation-mode](#) 6 - 220
[redistribute](#) 6 - 222
[reload](#) 6 - 224
[remote-access threshold session-threshold-exceeded](#) 6 - 227
[rename](#) 6 - 228
[replication http](#) 6 - 230
[request-command deny](#) 6 - 232
[request-method](#) 6 - 234
[request-queue](#) 6 - 237
[reserved-bits](#) 6 - 239
[retry-interval](#) 6 - 241
[re-xauth](#) 6 - 243
[rip](#) 6 - 245
[rmdir](#) 6 - 248
[route](#) 6 - 249
[route-map](#) 6 - 251
[router-id](#) 6 - 253
[router ospf](#) 6 - 254

S Commands 7 - 1

[Tsame-security-traffic](#) 7 - 2
[sdi-pre-5-slave](#) 7 - 4
[sdi-version](#) 7 - 6
[secondary](#) 7 - 8
[secondary-color](#) 7 - 10
[secondary-color](#) 7 - 12
[secure-unit-authentication](#) 7 - 14
[security-level](#) 7 - 16
[serial-number](#) 7 - 18
[server](#) 7 - 19
[server-port](#) 7 - 20
[server-separator](#) 7 - 22
[service](#) 7 - 23

service internal	7 - 25
service password-recovery	7 - 27
service-policy	7 - 30
session	7 - 32
set connection	7 - 33
set connection advanced-options	7 - 35
set connection timeout	7 - 37
set metric	7 - 39
set metric-type	7 - 41
setup	7 - 43
show aaa local user	7 - 46
show aaa-server	7 - 48
show access-list	7 - 50
show activation-key	7 - 51
show admin-context	7 - 53
show arp	7 - 54
show arp-inspection	7 - 55
show arp statistics	7 - 56
show asdm history	7 - 58
show asdm image	7 - 65
show asdm log_sessions	7 - 66
show asdm sessions	7 - 67
show asp drop	7 - 68
show asp table arp	7 - 104
show asp table classify	7 - 106
show asp table interfaces	7 - 109
show asp table mac-address-table	7 - 111
show asp table routing	7 - 113
show asp table vpn-context	7 - 115
show blocks	7 - 117
show bootvar	7 - 123
show capture	7 - 125
show chardrop	7 - 127
show checkheaps	7 - 128
show checksum	7 - 129

[show chunkstat](#) 7 - 130

[show clock](#) 7 - 131

[show conn](#) 7 - 132

[show console-output](#) 7 - 137

[show context](#) 7 - 138

[show counters](#) 7 - 142

[show cpu](#) 7 - 144

[show crashinfo](#) 7 - 146

[show crashinfo console](#) 7 - 154

[show crypto accelerator statistics](#) 7 - 156

[show crypto ca certificates](#) 7 - 159

[show crypto ca crls](#) 7 - 161

[show crypto ipsec df-bit](#) 7 - 162

[show crypto ipsec fragmentation](#) 7 - 163

[show crypto key mypubkey](#) 7 - 164

[show crypto protocol statistics](#) 7 - 165

[show ctique](#) 7 - 168

[show curpriv](#) 7 - 170

[show debug](#) 7 - 172

[show dhcpd](#) 7 - 175

[show dhcprelay state](#) 7 - 177

[show dhcprelay statistics](#) 7 - 178

[show disk](#) 7 - 180

[show dns-hosts](#) 7 - 182

[show failover](#) 7 - 184

[show file](#) 7 - 188

[show firewall](#) 7 - 189

[show flash](#) 7 - 190

[show fragment](#) 7 - 192

[show gc](#) 7 - 194

[show h225](#) 7 - 195

[show h245](#) 7 - 197

[show h323-ras](#) 7 - 199

[show history](#) 7 - 201

[show icmp](#) 7 - 203

[show idb](#) 7 - 204

[show igmp groups](#) 7 - 206

[show igmp interface](#) 7 - 207

[show igmp traffic](#) 7 - 208

[show interface](#) 7 - 209

[show interface ip brief](#) 7 - 217

[show inventory](#) 7 - 219

[show ip address](#) 7 - 221

[show ip address dhcp](#) 7 - 223

[show ip audit count](#) 7 - 227

[show ip verify statistics](#) 7 - 229

[show ipsec sa](#) 7 - 230

[show ipsec sa summary](#) 7 - 237

[show ipsec stats](#) 7 - 239

[show ipv6 access-list](#) 7 - 241

[show ipv6 interface](#) 7 - 243

[show ipv6 neighbor](#) 7 - 245

[show ipv6 route](#) 7 - 247

[show ipv6 routers](#) 7 - 249

[show ipv6 traffic](#) 7 - 250

[show isakmp sa](#) 7 - 252

[show isakmp stats](#) 7 - 254

[show local-host](#) 7 - 257

[show logging](#) 7 - 260

[show logging rate-limit](#) 7 - 262

[show mac-address-table](#) 7 - 263

[show management-access](#) 7 - 265

[show memory](#) 7 - 266

[show memory binsize](#) 7 - 269

[show memory profile](#) 7 - 270

[show memory-caller address](#) 7 - 273

[show mfib](#) 7 - 275

[show mfib active](#) 7 - 276

[show mfib count](#) 7 - 278

[show mfib interface](#) 7 - 279

[show mfib reserved](#) 7 - 280

[show mfib status](#) 7 - 282

[show mfib summary](#) 7 - 283

[show mfib verbose](#) 7 - 284

[show mgcp](#) 7 - 285

[show mode](#) 7 - 287

[show module](#) 7 - 288

[show mrib client](#) 7 - 291

[show mrib route](#) 7 - 293

[show mroute](#) 7 - 295

[show nameif](#) 7 - 298

[show ntp associations](#) 7 - 300

[show ntp status](#) 7 - 304

[show ospf](#) 7 - 306

[show ospf border-routers](#) 7 - 308

[show ospf database](#) 7 - 309

[show ospf flood-list](#) 7 - 313

[show ospf interface](#) 7 - 314

[show ospf neighbor](#) 7 - 315

[show ospf request-list](#) 7 - 317

[show ospf retransmission-list](#) 7 - 318

[show ospf summary-address](#) 7 - 320

[show ospf virtual-links](#) 7 - 321

[show perfmon](#) 7 - 322

[show pim df](#) 7 - 324

[show pim group-map](#) 7 - 325

[show pim interface](#) 7 - 327

[show pim join-prune statistic](#) 7 - 328

[show pim neighbor](#) 7 - 329

[show pim range-list](#) 7 - 331

[show pim topology](#) 7 - 333

[show pim topology reserved](#) 7 - 335

[show pim topology route-count](#) 7 - 336

[show pim traffic](#) 7 - 337

[show pim tunnel](#) 7 - 339

[show priority-queue statistics](#) 7 - 340

[show processes](#) 7 - 342

[show reload](#) 7 - 345

[show resource types](#) 7 - 346

[show resource usage](#) 7 - 347

[show route](#) 7 - 350

[show run fips](#) 7 - 351

[show running-config](#) 7 - 352

[show running-config aaa](#) 7 - 355

[show running-config aaa-server](#) 7 - 357

[show running-config aaa-server host](#) 7 - 359

[show running-config access-group](#) 7 - 360

[show running-config access-list](#) 7 - 361

[show running-config alias](#) 7 - 363

[show running-config arp](#) 7 - 364

[show running-config arp timeout](#) 7 - 365

[show running-config arp-inspection](#) 7 - 366

[show running-config asdm](#) 7 - 367

[show running-config auth-prompt](#) 7 - 369

[show running-config banner](#) 7 - 370

[show running-config class-map](#) 7 - 371

[show running-config clock](#) 7 - 372

[show running-config command-alias](#) 7 - 374

[show running-config console timeout](#) 7 - 376

[show running-config context](#) 7 - 377

[show running-config crypto](#) 7 - 378

[show running-config crypto dynamic-map](#) 7 - 380

[show running-config crypto ipsec](#) 7 - 381

[show running-config crypto isakmp](#) 7 - 382

[show running-config crypto map](#) 7 - 383

[show running-config dhcpd](#) 7 - 384

[show running-config dhcprelay](#) 7 - 385

[show running-config dns](#) 7 - 386

[show running-config domain-name](#) 7 - 387

[show running-config enable](#) 7 - 388

show running-config established	7 - 389
show running-config failover	7 - 390
show running-config filter	7 - 391
show running-config fips	7 - 392
show running-config fragment	7 - 393
show running-config ftp-map	7 - 395
show running-config ftp mode	7 - 396
show running-config global	7 - 397
show running-config group-delimiter	7 - 398
show running-config group-policy	7 - 399
show running-config gtp-map	7 - 400
show running-config http	7 - 402
show running-config http-map	7 - 403
show running-config icmp	7 - 405
show running-config imap4s	7 - 406
show running-config interface	7 - 408
show running-config ip address	7 - 410
show running-config ip audit attack	7 - 412
show running-config ip audit info	7 - 413
show running-config ip audit interface	7 - 414
show running-config ip audit name	7 - 415
show running-config ip audit signature	7 - 416
show running-config ip local pool	7 - 417
show running-config ip verify reverse-path	7 - 419
show running-config ipv6	7 - 420
show running-config isakmp	7 - 421
show running-config logging	7 - 422
show logging rate-limit	7 - 423
show running-config mac-address-table	7 - 424
show running-config mac-learn	7 - 425
show running-config mac-list	7 - 426
show running-config management-access	7 - 427
show running-config mgcp-map	7 - 428
show running-config mroute	7 - 430
show running-config mtu	7 - 431

show running-config multicast-routing	7 - 432
show running-config name	7 - 433
show running-config nameif	7 - 434
show running-config names	7 - 436
show running-config nat	7 - 437
show running-config nat-control	7 - 439
show running-config ntp	7 - 440
show running-config object-group	7 - 441
show running-config passwd	7 - 443
show running-config pim	7 - 444
show running-config policy-map	7 - 445
show running-config pop3s	7 - 447
show running-config port-forward	7 - 449
show running-config prefix-list	7 - 450
show running-config priority-queue	7 - 451
show running-config privilege	7 - 452
show running-config rip	7 - 454
show running-config route	7 - 455
show running-config route-map	7 - 456
show running-config router	7 - 458
show running-config same-security-traffic	7 - 459
show running-config service	7 - 460
show running-config service-policy	7 - 461
show running-configuration smtps	7 - 462
show running-config snmp-map	7 - 464
show running-config snmp-server	7 - 465
show running-config ssh	7 - 466
show running-config ssl	7 - 468
show running-config static	7 - 469
show running-config sunrpc-server	7 - 470
show running-config sysopt	7 - 472
show running-config tcp-map	7 - 473
show running-config telnet	7 - 474
show running-config terminal	7 - 475
show running-config tftp-server	7 - 476

[show running-config timeout](#) 7 - 477

[show running-config tunnel-group](#) 7 - 478

[show running-config url-block](#) 7 - 480

[show running-config url-cache](#) 7 - 482

[show running-configuration url-list](#) 7 - 483

[show running-config url-server](#) 7 - 484

[show running-config username](#) 7 - 485

[show running-config virtual](#) 7 - 486

[show running-config vpn load-balancing](#) 7 - 487

[show running-configuration vpn-sessiondb](#) 7 - 489

[show running-configuration webvpn](#) 7 - 490

[show service-policy](#) 7 - 492

[show service-policy inspect gtp](#) 7 - 496

[show shun](#) 7 - 499

[show sip](#) 7 - 500

[show skinny](#) 7 - 502

[show snmp-server statistics](#) 7 - 504

[show ssh sessions](#) 7 - 506

[show startup-config](#) 7 - 508

[show sunrpc-server active](#) 7 - 510

[show tcpstat](#) 7 - 511

[show tech-support](#) 7 - 514

[show traffic](#) 7 - 519

[show uauth](#) 7 - 521

[show url-block](#) 7 - 523

[show url-cache statistics](#) 7 - 525

[show url-server](#) 7 - 527

[show version](#) 7 - 529

[show vpn load-balancing](#) 7 - 531

[show vpn-sessiondb](#) 7 - 533

[show vpn-sessiondb ratio](#) 7 - 537

[show vpn-sessiondb summary](#) 7 - 539

[show xlate](#) 7 - 540

[shun](#) 7 - 543

[shutdown](#) 7 - 545

smtps 7 - 547

smtp-server 7 - 548

snmp-server 7 - 549

snmp-map 7 - 552

snmp-server enable trap remote-access 7 - 554

speed 7 - 555

split-dns 7 - 557

split-tunnel-network-list 7 - 559

split-tunnel-policy 7 - 561

ssh 7 - 563

ssh disconnect 7 - 565

ssh scopy enable 7 - 567

ssh timeout 7 - 569

ssh version 7 - 571

ssl client-version 7 - 573

ssl encryption 7 - 575

ssl server-version 7 - 577

ssl trust-point 7 - 579

static 7 - 581

strict-http 7 - 609

strip-group 7 - 611

strip-realm 7 - 613

subject-name (crypto ca certificate map) 7 - 615

subject-name (crypto ca trustpoint) 7 - 617

summary-address 7 - 618

sunrpc-server 7 - 620

support-user-cert-validation 7 - 622

syn-data 7 - 624

sysopt connection permit-ipsec 7 - 626

sysopt connection tcpmss 7 - 628

sysopt connection timewait 7 - 630

sysopt nodnsalias 7 - 632

sysopt noproxyarp 7 - 634

sysopt radius ignore-secret 7 - 636

sysopt uauth allow-http-cache 7 - 638

T through Z Commands 8 - 1

- [tcp-map 8 - 2](#)
- [tcp-options 8 - 4](#)
- [telnet 8 - 6](#)
- [terminal 8 - 9](#)
- [terminal width 8 - 10](#)
- [test aaa-server 8 - 11](#)
- [8 - 13](#)
- [text-color 8 - 14](#)
- [tftp-server 8 - 15](#)
- [timeout 8 - 17](#)
- [timeout \(aaa-server host\) 8 - 20](#)
- [timeout \(gtp-map\) 8 - 22](#)
- [time-range 8 - 24](#)
- [timers lsa-group-pacing 8 - 26](#)
- [timers spf 8 - 27](#)
- [title 8 - 29](#)
- [title-color 8 - 30](#)
- [transfer-encoding 8 - 32](#)
- [trust-point 8 - 35](#)**
- [ttl-evasion-protection 8 - 37](#)
- [tunnel-group 8 - 39](#)
- [tunnel-group general-attributes 8 - 41](#)
- [tunnel-group ipsec-attributes 8 - 43](#)
- [tunnel-group-map default-group 8 - 45](#)
- [tunnel-group-map enable 8 - 47](#)
- [tunnel-limit 8 - 49](#)
- [tx-ring-limit 8 - 51](#)
- [urgent-flag 8 - 53](#)
- [url 8 - 55](#)
- [url-block 8 - 57](#)
- [url-cache 8 - 59](#)
- [url-list 8 - 61](#)
- [url-list \(webvpn\) 8 - 63](#)
- [url-server 8 - 65](#)

user-authentication	8 - 68
user-authentication-idle-timeout	8 - 70
username	8 - 72
username attributes	8 - 74
username-prompt	8 - 76
virtual http	8 - 77
virtual telnet	8 - 79
vlan	8 - 81
vpn-access-hours	8 - 83
vpn-addr-assign	8 - 84
vpn-filter	8 - 86
vpn-framed-ip-address	8 - 87
vpn-framed-ip-netmask	8 - 88
vpn-group-policy	8 - 89
vpn-idle-timeout	8 - 91
vpn load-balancing	8 - 93
vpn-sessiondb logoff	8 - 95
vpn-sessiondb max-session-limit	8 - 97
vpn-session-timeout	8 - 98
vpn-simultaneous-logins	8 - 100
vpn-tunnel-protocol	8 - 101
webvpn	8 - 102
webvpn (group-policy, username)	8 - 103
who	8 - 105
window-variation	8 - 106
wins-server	8 - 108
write erase	8 - 109
write memory	8 - 110
write net	8 - 112
write standby	8 - 114
write terminal	8 - 116



About This Guide

This preface introduces the *Cisco Security Appliance Command Reference*.

This preface includes the following sections:

- [Document Objectives, page xxxvii](#)
- [Audience, page xxxviii](#)
- [Document Organization, page xxxviii](#)
- [Document Conventions, page xxxviii](#)
- [Related Documentation, page xxxix](#)
- [Obtaining Documentation, page xxxix](#)
- [Documentation Feedback, page xl](#)
- [Obtaining Technical Assistance, page xl](#)
- [Obtaining Additional Publications and Information, page xlii](#)

Document Objectives

This guide contains the commands available for use with the security appliance to protect your network from unauthorized use and to establish Virtual Private Networks to connect remote sites and users to your network.

You can also configure and monitor the security appliance by using ASDM, a web-based GUI application. ASDM includes configuration wizards to guide you through some common configuration scenarios, and online Help for less common scenarios. For more information, see: <http://www.cisco.com/univercd/cc/td/doc/product/netsec/secmgmt/asdm/index.htm>.

This guide applies to the Cisco PIX 500 series security appliances (PIX 515/515E, PIX 525, and PIX 535) and the Cisco ASA 5500 series security appliances (ASA 5510, ASA 5520, and ASA 5540). Throughout this guide, the term “security appliance” applies generically to all supported models, unless specified otherwise. The PIX 501, PIX 506E, and PIX 520 security appliances are not supported in software Version 7.0.

Audience

This guide is for network managers who perform any of the following tasks:

- Manage network security
- Install and configure firewall/security appliances
- Configure VPNs
- Configure intrusion detection software

Use this guide with the *Cisco Security Appliance Command Line Configuration Guide*.

Document Organization

This guide includes the following chapters:

- [Chapter 1, “Using the Command-Line Interface,”](#) introduces you to the security appliance commands and access modes
- [Chapter 2, “A through B Commands,”](#) provides detailed descriptions of all commands that begin with the letters A through B.
- [Chapter 3, “C Commands,”](#) provides detailed descriptions of all commands that begin with the letter C.
- [Chapter 4, “D through F Commands,”](#) provides detailed descriptions of all commands that begin with the letters D through F.
- [Chapter 5, “G through L Commands,”](#) provides detailed descriptions of all commands that begin with the letters G through L.
- [Chapter 6, “M through R Commands,”](#) provides detailed descriptions of all commands that begin with the letters M through R.
- [Chapter 7, “S Commands,”](#) provides detailed descriptions of all commands that begin with the letter S.
- [Chapter 8, “T through Z Commands,”](#) provides detailed descriptions of all commands that begin with the letters T through Z.

Document Conventions

The security appliance command syntax descriptions use the following conventions:

Command descriptions use these conventions:

- Braces ({ }) indicate a required choice.
- Square brackets ([]) indicate optional elements.
- Vertical bars (|) separate alternative, mutually exclusive elements.
- **Boldface** indicates commands and keywords that are entered literally as shown.
- *Italics* indicate arguments for which you supply values.

Examples use these conventions:

- Examples depict screen displays and the command line in `screen` font.

- Information you need to enter in examples is shown in **boldface screen** font.
- Variables for which you must supply a value are shown in *italic screen* font.
- Examples might include output from different platforms; for example, you might not recognize an interface type in an example because it is not available on your platform. Differences should be minor.

**Note**

Means *reader take note*. Notes contain helpful suggestions or references to material not covered in the manual.

For information on modes, prompts, and syntax, see [Chapter 1, “Using the Command-Line Interface.”](#)

Related Documentation

For more information, refer to the following documentation:

- *Cisco Security Appliance Command Line Configuration Guide*
- *Cisco Security Appliance System Log Messages*
- *Guide for Cisco PIX 6.2 and 6.3 Users Upgrading to Cisco PIX Software Version 7.0*
- *Cisco PIX Security Appliance Release Notes*
- *Cisco PIX 515E Quick Start Guide*
- *Cisco ASA 5500 Series Quick Start Guide*
- *Cisco ASA 5500 Series Release Notes*
- *Cisco ASDM Release Notes*

Obtaining Documentation

Cisco documentation and additional literature are available on Cisco.com. Cisco also provides several ways to obtain technical assistance and other technical resources. These sections explain how to obtain technical information from Cisco Systems.

Cisco.com

You can access the most current Cisco documentation at this URL:

<http://www.cisco.com/univercd/home/home.htm>

You can access the Cisco website at this URL:

<http://www.cisco.com>

You can access international Cisco websites at this URL:

http://www.cisco.com/public/countries_languages.shtml

Ordering Documentation

You can find instructions for ordering documentation at this URL:

http://www.cisco.com/univercd/cc/td/doc/es_inpk/pdi.htm

You can order Cisco documentation in these ways:

- Registered Cisco.com users (Cisco direct customers) can order Cisco product documentation from the Ordering tool:

<http://www.cisco.com/en/US/partner/ordering/index.shtml>

- Nonregistered Cisco.com users can order documentation through a local account representative by calling Cisco Systems Corporate Headquarters (California, USA) at 408 526-7208 or, elsewhere in North America, by calling 1 800 553-NETS (6387).

Documentation Feedback

You can send comments about technical documentation to bug-doc@cisco.com.

You can submit comments by using the response card (if present) behind the front cover of your document or by writing to the following address:

Cisco Systems
Attn: Customer Document Ordering
170 West Tasman Drive
San Jose, CA 95134-9883

We appreciate your comments.

Obtaining Technical Assistance

For all customers, partners, resellers, and distributors who hold valid Cisco service contracts, Cisco Technical Support provides 24-hour-a-day, award-winning technical assistance. The Cisco Technical Support Website on Cisco.com features extensive online support resources. In addition, Cisco Technical Assistance Center (TAC) engineers provide telephone support. If you do not hold a valid Cisco service contract, contact your reseller.

Cisco Technical Support Website

The Cisco Technical Support Website provides online documents and tools for troubleshooting and resolving technical issues with Cisco products and technologies. The website is available 24 hours a day, 365 days a year, at this URL:

<http://www.cisco.com/techsupport>

Access to all tools on the Cisco Technical Support Website requires a Cisco.com user ID and password. If you have a valid service contract but do not have a user ID or password, you can register at this URL:

<http://tools.cisco.com/RPF/register/register.do>

**Note**

Use the Cisco Product Identification (CPI) tool to locate your product serial number before submitting a web or phone request for service. You can access the CPI tool from the Cisco Technical Support Website by clicking the **Tools & Resources** link under Documentation & Tools. Choose **Cisco Product Identification Tool** from the Alphabetical Index drop-down list, or click the **Cisco Product Identification Tool** link under Alerts & RMAs. The CPI tool offers three search options: by product ID or model name; by tree view; or for certain products, by copying and pasting **show** command output. Search results show an illustration of your product with the serial number label location highlighted. Locate the serial number label on your product and record the information before placing a service call.

Submitting a Service Request

Using the online TAC Service Request Tool is the fastest way to open S3 and S4 service requests. (S3 and S4 service requests are those in which your network is minimally impaired or for which you require product information.) After you describe your situation, the TAC Service Request Tool provides recommended solutions. If your issue is not resolved using the recommended resources, your service request is assigned to a Cisco TAC engineer. The TAC Service Request Tool is located at this URL:

<http://www.cisco.com/techsupport/servicerequest>

For S1 or S2 service requests or if you do not have Internet access, contact the Cisco TAC by telephone. (S1 or S2 service requests are those in which your production network is down or severely degraded.) Cisco TAC engineers are assigned immediately to S1 and S2 service requests to help keep your business operations running smoothly.

To open a service request by telephone, use one of the following numbers:

Asia-Pacific: +61 2 8446 7411 (Australia: 1 800 805 227)

EMEA: +32 2 704 55 55

USA: 1 800 553-2447

For a complete list of Cisco TAC contacts, go to this URL:

<http://www.cisco.com/techsupport/contacts>

Definitions of Service Request Severity

To ensure that all service requests are reported in a standard format, Cisco has established severity definitions.

Severity 1 (S1)—Your network is “down,” or there is a critical impact to your business operations. You and Cisco will commit all necessary resources around the clock to resolve the situation.

Severity 2 (S2)—Operation of an existing network is severely degraded, or significant aspects of your business operation are negatively affected by inadequate performance of Cisco products. You and Cisco will commit full-time resources during normal business hours to resolve the situation.

Severity 3 (S3)—Operational performance of your network is impaired, but most business operations remain functional. You and Cisco will commit resources during normal business hours to restore service to satisfactory levels.

Severity 4 (S4)—You require information or assistance with Cisco product capabilities, installation, or configuration. There is little or no effect on your business operations.

Obtaining Additional Publications and Information

Information about Cisco products, technologies, and network solutions is available from various online and printed sources.

- Cisco Marketplace provides a variety of Cisco books, reference guides, and logo merchandise. Visit Cisco Marketplace, the company store, at this URL:

<http://www.cisco.com/go/marketplace/>

- The Cisco *Product Catalog* describes the networking products offered by Cisco Systems, as well as ordering and customer support services. Access the Cisco Product Catalog at this URL:

<http://cisco.com/univercd/cc/td/doc/pcat/>

- *Cisco Press* publishes a wide range of general networking, training and certification titles. Both new and experienced users will benefit from these publications. For current Cisco Press titles and other information, go to Cisco Press at this URL:

<http://www.ciscopress.com>

- *Packet* magazine is the Cisco Systems technical user magazine for maximizing Internet and networking investments. Each quarter, Packet delivers coverage of the latest industry trends, technology breakthroughs, and Cisco products and solutions, as well as network deployment and troubleshooting tips, configuration examples, customer case studies, certification and training information, and links to scores of in-depth online resources. You can access Packet magazine at this URL:

<http://www.cisco.com/packet>

- *iQ Magazine* is the quarterly publication from Cisco Systems designed to help growing companies learn how they can use technology to increase revenue, streamline their business, and expand services. The publication identifies the challenges facing these companies and the technologies to help solve them, using real-world case studies and business strategies to help readers make sound technology investment decisions. You can access iQ Magazine at this URL:

<http://www.cisco.com/go/iqmagazine>

- *Internet Protocol Journal* is a quarterly journal published by Cisco Systems for engineering professionals involved in designing, developing, and operating public and private internets and intranets. You can access the Internet Protocol Journal at this URL:

<http://www.cisco.com/ipj>

- World-class networking training is available from Cisco. You can view current offerings at this URL:

<http://www.cisco.com/en/US/learning/index.html>



Using the Command-Line Interface

This describes how to use the CLI on the security appliance, and includes the following topics:

- [Firewall Mode and Security Context Mode, page 1-1](#)
- [Command Modes and Prompts, page 1-2](#)
- [Syntax Formatting, page 1-3](#)
- [Abbreviating Commands, page 1-3](#)
- [Command-Line Editing, page 1-3](#)
- [Command Completion, page 1-3](#)
- [Command Help, page 1-4](#)
- [Filtering show Command Output, page 1-4](#)
- [Command Output Paging, page 1-5](#)
- [Adding Comments, page 1-5](#)
- [Text Configuration Files, page 1-6](#)



Note

The CLI uses similar syntax and other conventions to the Cisco IOS CLI, but the security appliance operating system is not a version of Cisco IOS software. Do not assume that a Cisco IOS CLI command works with or has the same function on the security appliance.

Firewall Mode and Security Context Mode

The security appliance runs in a combination of the following modes:

- Transparent firewall or routed firewall mode

The firewall mode determines if the security appliance runs as a Layer 2 or Layer 3 firewall.

- Multiple context or single context mode

The security context mode determines if the security appliance runs as a single device or as multiple security contexts, which act like virtual devices.

Some commands are only available in certain modes.

Command Modes and Prompts

The security appliance CLI includes command modes. Some commands can only be entered in certain modes. For example, to enter commands that show sensitive information, you need to enter a password and enter a more privileged mode. Then, to ensure that configuration changes are not entered accidentally, you have to enter a configuration mode. All lower commands can be entered in higher modes, for example, you can enter a privileged EXEC command in global configuration mode.

When you are in the system configuration or in single context mode, the prompt begins with the hostname:

```
hostname
```

When you are within a context, the prompt begins with the hostname followed by the context name:

```
hostname/context
```

The prompt changes depending on the access mode:

- User EXEC mode

User EXEC mode lets you see minimum security appliance settings. The user EXEC mode prompt appears as follows when you first access the security appliance:

```
hostname>
```

```
hostname/context>
```

- Privileged EXEC mode

Privileged EXEC mode lets you see all current settings up to your privilege level. Any user EXEC mode command will work in privileged EXEC mode. Enter the **enable** command in user EXEC mode, which requires a password, to start privileged EXEC mode. The prompt includes the number sign (#):

```
hostname#
```

```
hostname/context#
```

- Global configuration mode

Global configuration mode lets you change the security appliance configuration. All user EXEC, privileged EXEC, and global configuration commands are available in this mode. Enter the **configure terminal** command in privileged EXEC mode to start global configuration mode. The prompt changes to the following:

```
hostname(config)#
```

```
hostname/context(config)#
```

- Command-specific configuration modes

From global configuration mode, some commands enter a command-specific configuration mode. All user EXEC, privileged EXEC, global configuration, and command-specific configuration commands are available in this mode. For example, the **interface** command enters interface configuration mode. The prompt changes to the following:

```
hostname(config-if)#
```

```
hostname/context(config-if)#
```


Syntax Formatting

Command syntax descriptions use the following conventions:

Table 1-1 **Syntax Conventions**

Convention	Description
bold	Bold text indicates commands and keywords that you enter literally as shown.
<i>italics</i>	Italic text indicates arguments for which you supply values.
[x]	Square brackets enclose an optional element (keyword or argument).
	A vertical bar indicates a choice within an optional or required set of keywords or arguments.
[x y]	Square brackets enclosing keywords or arguments separated by a vertical bar indicate an optional choice.
{x y}	Braces enclosing keywords or arguments separated by a vertical bar indicate a required choice.
[x {y z}]	Nested sets of square brackets or braces indicate optional or required choices within optional or required elements. Braces and a vertical bar within square brackets indicate a required choice within an optional element.

Abbreviating Commands

You can abbreviate most commands down to the fewest unique characters for a command; for example, you can enter **wr t** to view the configuration instead of entering the full command **write terminal**, or you can enter **en** to start privileged mode and **conf t** to start configuration mode. In addition, you can enter **0** to represent **0.0.0.0**.

Command-Line Editing

The security appliance uses the same command-line editing conventions as Cisco IOS software. You can view all previously entered commands with the **show history** command or individually with the up arrow or **^p** command. Once you have examined a previously entered command, you can move forward in the list with the down arrow or **^n** command. When you reach a command you wish to reuse, you can edit it or press the **Enter** key to start it. You can also delete the word to the left of the cursor with **^w**, or erase the line with **^u**.

The security appliance permits up to 512 characters in a command; additional characters are ignored.

Command Completion

To complete a command or keyword after entering a partial string, press the **Tab** key. The security appliance only completes the command or keyword if the partial string matches only one command or keyword. For example, if you enter **s** and press the **Tab** key, the security appliance does not complete the command because it matches more than one command. However, if you enter **dis**, the **Tab** key completes the command **disable**.

Command Help

Help information is available from the command line by entering the following commands:

- **help** *command_name*
Shows help for the specific command.
- **help** ?
Shows commands for which there is help.
- *command_name* ?
Shows a list of arguments available.
- *string*? (no space)
Lists the possible commands that start with the string.
- ? and +?
Lists all commands available. If you enter ?, the security appliance shows only commands available for the current mode. To show all commands available, including those for lower modes, enter +?.

**Note**

If you want to include a question mark (?) in a command string, you must press **Ctrl-V** before typing the question mark so you do not inadvertently invoke CLI help.

Filtering show Command Output

You can use the vertical bar (|) with any **show** command and include a filter option and filtering expression. The filtering is performed by matching each output line with a regular expression, similar to Cisco IOS software. By selecting different filter options you can include or exclude all output that matches the expression. You can also display all output beginning with the line that matches the expression.

The syntax for using filtering options with the **show** command is as follows:

```
hostname# show command | {include | exclude | begin | grep [-v]} regex
```

In this command string, the first vertical bar (|) is the operator and must be included in the command. This operator directs the output of the **show** command to the filter. In the syntax diagram, the other vertical bars (|) indicate alternative options and are not part of the command.

The **include** option includes all output lines that match the regular expression. The **grep** option without **-v** has the same effect. The **exclude** option excludes all output lines that match the regular expression. The **grep** option with **-v** has the same effect. The **begin** option shows all the output lines starting with the line that matches the regular expression.

Replace *regex* with any Cisco IOS regular expression. See The regular expression is not enclosed in quotes or double-quotes, so be careful with trailing white spaces, which will be taken as part of the regular expression.

When creating regular expressions, you can use any letter or number that you want to match. In addition, certain keyboard characters have special meaning when used in regular expressions. [Table 1-2](#) lists the keyboard characters that have special meaning.

Table 1-2 *Using Special Characters in Regular Expressions*

Character Type	Character	Special Meaning
period	.	Matches any single character, including white space.
asterisk	*	Matches 0 or more sequences of the pattern.
plus sign	+	Matches 1 or more sequences of the pattern.
question mark	? ¹	Matches 0 or 1 occurrences of the pattern.
caret	^	Matches the beginning of the input string.
dollar sign	\$	Matches the end of the input string.
underscore	_	Matches a comma (,), left brace ({), right brace (}), left parenthesis, right parenthesis, the beginning of the input string, the end of the input string, or a space.
brackets	[]	Designates a range of single-character patterns.
hyphen	-	Separates the end points of a range.

1. Precede the question mark with **Ctrl-V** to prevent the question mark from being interpreted as a help command.

To use these special characters as single-character patterns, remove the special meaning by preceding each character with a backslash (\).

Command Output Paging

On commands such as **help** or **?**, **show**, **show xlate**, or other commands that provide long listings, you can determine if the information displays a screen and pauses, or lets the command run to completion. The **pager** command lets you choose the number of lines to display before the More prompt appears.

When paging is enabled, the following prompt appears:

```
<--- More --->
```

The More prompt uses syntax similar to the UNIX **more** command:

- To view another screen, press the Space bar.
- To view the next line, press the **Enter** key.
- To return to the command line, press the **q** key.

Adding Comments

You can precede a line with a colon (:) to create a comment. However, the comment only appears in the command history buffer and not in the configuration. Therefore, you can view the comment with the **show history** command or by pressing an arrow key to retrieve a previous command, but because the comment is not in the configuration, the **write terminal** command does not display it.

Text Configuration Files

This section describes how to format a text configuration file that you can download to the security appliance, and includes the following topics:

- [How Commands Correspond with Lines in the Text File, page 1-6](#)
- [Command-Specific Configuration Mode Commands, page 1-6](#)
- [Automatic Text Entries, page 1-6](#)
- [Line Order, page 1-7](#)
- [Commands Not Included in the Text Configuration, page 1-7](#)
- [Passwords, page 1-7](#)
- [Multiple Security Context Files, page 1-7](#)

How Commands Correspond with Lines in the Text File

The text configuration file includes lines that correspond with the commands described in this guide.

In examples, commands are preceded by a CLI prompt. The prompt in the following example is “hostname(config)#”:

```
hostname(config)# context a
```

In the text configuration file you are not prompted to enter commands, so the prompt is omitted:

```
context a
```

Command-Specific Configuration Mode Commands

Command-specific configuration mode commands appear indented under the main command when entered at the command line. Your text file lines do not need to be indented, as long as the commands appear directly following the main command. For example, the following unindented text is read the same as indented text:

```
interface gigabitethernet0/0
nameif inside
interface gigabitethernet0/1
    nameif outside
```

Automatic Text Entries

When you download a configuration to the security appliance, the security appliance inserts some lines automatically. For example, the security appliance inserts lines for default settings or for the time the configuration was modified. You do not need to enter these automatic entries when you create your text file.

Line Order

For the most part, commands can be in any order in the file. However, some lines, such as ACEs, are processed in the order they appear, and the order can affect the function of the access list. Other commands might also have order requirements. For example, you must enter the **nameif** command for an interface first because many subsequent commands use the name of the interface. Also, commands in a command-specific configuration mode must directly follow the main command.

Commands Not Included in the Text Configuration

Some commands do not insert lines in the configuration. For example, a runtime command such as **show running-config** does not have a corresponding line in the text file.

Passwords

The login, enable, and user passwords are automatically encrypted before they are stored in the configuration. For example, the encrypted form of the password “cisco” might look like jMorNbK0514fadBh. You can copy the configuration passwords to another security appliance in their encrypted form, but you cannot unencrypt the passwords yourself.

If you enter an unencrypted password in a text file, the security appliance does not automatically encrypt them when you copy the configuration to the security appliance. The security appliance only encrypts them when you save the running configuration from the command line using the **copy running-config startup-config** or **write memory** command.

Multiple Security Context Files

For multiple security contexts, the entire configuration consists of multiple parts:

- The security context configurations
- The system configuration, which identifies basic settings for the security appliance, including a list of contexts
- The admin context, which provides network interfaces for the system configuration

The system configuration does not include any interfaces or network settings for itself. Rather, when the system needs to access network resources (such as downloading the contexts from the server), it uses a context that is designated as the admin context.

Each context is similar to a single context mode configuration. The system configuration differs from a context configuration in that the system configuration includes system-only commands (such as a list of all contexts) while other typical commands are not present (such as many interface parameters).



A through B Commands

aaa accounting

To enable, disable, or view TACACS+, or RADIUS user accounting (on a server designated by the **aaa-server host** command), use the **aaa accounting** command in global configuration mode. To disable these functions use the **no** form of this command.

```
aaa accounting {include | exclude} service interface-name local-ip local-mask foreign-ip
foreign-mask server-tag
```

```
no aaa accounting {include | exclude} service interface-name local-ip local-mask foreign-ip
foreign-mask server-tag
```

```
aaa accounting {include | exclude} service interface-name server-tag
```

```
no aaa accounting {include | exclude} service interface-name server-tag
```

Syntax Description

exclude	Create an exception to a previously stated rule by excluding the specified service from accounting. The exclude parameter allows the user to specify a service or protocol/port to exclude to a specific host or hosts.
<i>foreign-ip</i>	Specify the IP address of the hosts you want to access the <i>local-ip</i> address. Use 0 to mean all hosts. the <i>foreign-ip address</i> is always on the lowest security-level interface.
<i>foreign-mask</i>	Specify the network mask of <i>foreign-ip</i> . Always specify a specific mask value. Use 0 if the IP address is 0. Use 255.255.255.255 for a host.
<i>interface-name</i>	Specify the interface name from which users require authentication. Use <i>interface-name</i> in combination with the <i>local-ip</i> address and the <i>foreign-ip</i> address to determine where access is sought and from whom.
include	Create a new rule with the specified service to include.
<i>local-ip</i>	Specify the IP address of the host or network of hosts that you want to be authenticated or authorized. Set this address to 0 to mean all hosts and to let the authentication server decide which hosts are allowed access. The <i>local-ip</i> address is always on the highest security-level interface.
<i>local-mask</i>	Specify the network mask of <i>local-ip</i> . Always specify a specific mask value. Use 0 if the IP address is 0. Use 255.255.255.255 for a host.
<i>server-tag</i>	Specify the AAA server group tag defined by the aaa-server host command.
<i>service</i>	The services/access method that should be accounted for. Accounting is provided for all services, or you can limit it to one or more services. Possible values are enable , http , serial , ssh , telnet , or <i>protocol/port</i> . Use enable to provide accounting for all TCP services. To provide accounting for UDP services, use the <i>protocol/port</i> form.

Defaults

For *protocol/port*, the TCP protocol appears as 6, the UDP protocol appears as 17, and so on, and port is the TCP or UDP destination port. A port value of 0 (zero) means all ports. For protocols other than TCP and UDP, the *port* is not applicable and should not be used.

By default, AAA accounting for administrative access is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

User accounting services keep a record of which network services a user has accessed. These records are kept on the designated AAA server or servers. Accounting information is sent only to the active server in a server group unless you enable simultaneous accounting.

Before you can use this command, you must first designate an AAA server with the **aaa-server** command.

To enable accounting for traffic that is specified by an access list, use the **aaa accounting match** command.

**Note**

Traffic that is not specified by an **include** statement is not processed.

For outbound connections, first use the **nat** command to determine which IP addresses can access the security appliance. For inbound connections, first use the **static** and **access-list extended** command statements to determine which inside IP addresses can be accessed through the security appliance from the outside network.

If you want to allow connections to come from any host, code the local IP address and netmask as **0.0.0.0 0.0.0.0**, or **0 0**. The same convention applies to the foreign host IP address and netmask; **0.0.0.0 0.0.0.0** means any foreign host.

Examples

The following example enables accounting on all connections:

```
hostname(config)# aaa-server mygroup protocol tacacs+
hostname(config)# aaa-server mygroup (inside) host 192.168.10.10 thekey timeout 20
hostname(config)# aaa authentication include any inside 0 0 0 0 mygroup
hostname(config)# aaa authorization include any inside 0 0 0 0 mygroup
hostname(config)# aaa accounting include any inside 0 0 0 0 mygroup
hostname(config)# aaa authentication serial console mygroup
```

This example specifies that the authentication server with the IP address 192.168.10.10 resides on the inside interface and is in the TACACS+ server group. The next three command statements specify that any users starting outbound connections to any foreign host will be authenticated using TACACS+, that the users who are successfully authenticated are authorized to use any service, and that all outbound connection information will be logged in the accounting database. The last command statement specifies that access to the security appliance serial console requires authentication from the TACACS+ server.

Related Commands	Command	Description
	aaa accounting match	Enable or disable the use of a specified access list that must be matched to enable user accounting (on a server designated by the aaa-server command).
	aaa accounting command	Enable support for AAA accounting administrative access.
	aaa-server host	Configure host-related attributes.
	clear configure aaa	Remove/reset the configured AAA accounting values.
	show running-config aaa	Display the AAA configuration.

aaa accounting console

To enable support for AAA accounting for administrative access, use the **aaa accounting console** command in global configuration mode. To disable support for aaa accounting for administrative access, use the **no** form of this command.

aaa accounting {serial| telnet | ssh | enable} console server-tag

no aaa accounting {serial | telnet | ssh | enable} console server-tag

Syntax Description

enable	Enables or disables the generation of accounting records to mark the entry to and exit from privileged EXEC mode.
serial	Enables or disables the generation of accounting records to mark the establishment and termination of admin sessions that are established via the serial console interface.
<i>server-tag</i>	Specifies the server or group of servers to which accounting records are sent. Valid server group protocols are RADIUS and TACACS+.
ssh	Enables or disables the generation of accounting records to mark the establishment and termination of admin sessions created over SSH.
telnet	Enables or disables the generation of accounting records to mark the establishment and termination of admin sessions created over Telnet.

Defaults

By default, AAA accounting for administrative access is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines

You must specify the name of the server group, previously specified in an **aaa-server** command.

Examples

The following example specifies that accounting records will be generated for all Telnet transactions, and that these records are sent to the server named adminserver.

```
hostname(config)# aaa accounting telnet console adminserver
```

Related Commands	Command	Description
	aaa accounting match	Enables or disables TACACS+ or RADIUS user accounting (on a server designated by the aaa-server command),
	aaa accounting command	Specifies that each command, or commands of a specified privilege level or higher, entered by an administrator/user is recorded and sent to the accounting server or servers.
	clear configure aaa	Remove/reset the configured AAA accounting values.
	show running-config aaa	Display the AAA configuration.

aaa accounting command

To configure command accounting so that the security appliance sends to the accounting server each command entered by an administrator, use the **aaa accounting command** command in global configuration mode. To disable support for AAA command privilege accounting, use the **no** form of this command. The **aaa accounting command** command indicates the minimum level that must be associated with a command for an accounting record to be generated.

aaa accounting command [*privilege level*] *server-tag*

no aaa accounting command [*privilege level*] *server-tag*

Syntax Description

<i>server-tag</i>	The server or group of TACACS+ servers to which accounting records are sent.
<i>privilege level</i>	The minimum level that must be associated with a command for an accounting record to be generated. The default privilege level is 0.

Defaults

The default privilege level is 0. By default, AAA command-privilege accounting for administrative access is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was modified to include the administrative option.

Usage Guidelines

When you configure the **aaa accounting command** command, each command entered by an administrator/user is recorded and sent to the accounting server or servers. The optional **privilege** specification indicates the minimum privilege level that must be associated with a command for an accounting record to be generated.

This command applies only to TACACS+ servers.

You must specify the name of the server or group, previously specified in an **aaa-server** command, to which this command applies.

Examples

The following example specifies that accounting records will be generated for any command at privilege level 6 or higher, and that these records are sent to the server from the group named adminserver.

```
hostname(config)# aaa accounting command privilege 6 adminserver
```

Related Commands	Command	Description
	aaa accounting	Enables or disables TACACS+ or RADIUS user accounting (on a server designated by the aaa-server command).
	clear configure aaa	Remove/reset the configured AAA accounting values.
	show running-config aaa	Display the AAA configuration.

aaa accounting match

To enable accounting for traffic that is identified by an access list, use the **aaa accounting match** command in global configuration mode. To disable accounting for traffic that is identified by an access list, use the **no** form of this command. The **aaa accounting match** command specifies an access list name that must be matched, as well as an interface name and a server tag.

aaa accounting match *acl-name interface-name server-tag*

no aaa accounting match *acl-name interface-name server-tag*

Syntax Description

<i>acl-name</i>	Specifies the name of an ACL that matches the traffic that you want the security appliance to perform accounting for. The <i>acl-name</i> argument must be the name of an ACL created with the access-list command.
<i>interface-name</i>	Specify the interface name from which users require accounting.
<i>server-tag</i>	Specify the AAA server group tag defined by the aaa-server protocol command.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **aaa accounting match** command requires that you specify an ACL that permits the traffic for which you want the security appliance to send accounting data to AAA servers. The security appliance performs accounting for traffic permitted by the ACL and does not perform accounting for traffic denied by the ACL.

Before you can use this command, you must first create the AAA-server group tag by using the **aaa-server protocol** command.

User accounting services keep a record of which network services a user has accessed. These records are kept on the designated AAA servers. Accounting information is sent only to the active server in a server group unless simultaneous accounting is enabled. See the **accounting-mode** command for more information.

Examples

The following example enables accounting for traffic matching an ACL, acl2, followed by the output of the **show access-list** command that displays the ACL:

```
hostname(config) # aaa accounting match acl2 outside radserver1
hostname(config) # show access-list acl12
access-list acl12; 1 elements
access-list acl12 line 1 extended permit tcp any any (hitcnt=54021)
```

Related Commands

Command	Description
aaa accounting	Enable, disable, or view TACACS+ or RADIUS user accounting (on a server designated by the aaa-server command).
access-list extended	Create an access list or use a downloadable access list.
clear configure aaa	Remove/reset the configured AAA accounting values.
show running-config aaa	Display the AAA configuration.

aaa authentication

To include or exclude user authentication for traffic through the security appliance, use the **aaa authentication** command with the **include** or **exclude** keywords in global configuration mode. To disable user authentication, use the **no** form of this command.

Authentication lets you control access by requiring a valid username and password. You can configure the security appliance to authenticate the following items:

- All administrative connections to the security appliance including the following sessions:
 - Telnet
 - SSH
 - ASDM (using HTTPS)
 - VPN management access
- The **enable** command
- Network access through the security appliance

Each authentication server has a single pool of users. If you use the same server for multiple authentication rules and types, then a user needs to authenticate only one time for all rules and types, until the session expires. For example, if you configure the security appliance to authenticate Telnet and FTP, and a user successfully authenticates for Telnet, then as long as the session exists, the user does not also have to authenticate for FTP.

```
aaa authentication include | exclude authentication-service interface-name local-ip local-mask
[foreign-ip foreign-mask] server-tag
```

```
no aaa authentication include | exclude authentication-service interface-name local-ip
local-mask [foreign-ip foreign-mask] server-tag
```

```
aaa authentication {ftp | telnet | http | https } challenge disable
```

```
no aaa authentication {ftp | telnet | http | https } challenge disable
```

Syntax Description

<i>authentication-service</i>	The type of traffic to include or exclude from authentication, based on the service option selected.
exclude	Creates an exception to a previously stated rule by excluding the specified service from authentication. The exclude parameter improves the former except option by allowing the user to specify a port to exclude to a specific host or hosts.
<i>foreign-ip</i>	(Optional) IP address of the foreign host that is either the source or destination for connections requiring authentication; 0 indicates all hosts.
<i>foreign-mask</i>	(Optional) The network mask of <i>foreign-ip</i> .
include	Creates a new rule with the specified service to include.
<i>interface-name</i>	The interface name from which users require authentication.
<i>local-ip</i>	The IP address of the local/internal host or network of hosts that is either the source or destination for connections requiring authentication. You can set this address to 0 to mean all hosts and to let the authentication server decide which hosts are authenticated.

<i>local-mask</i>	The network mask of <i>local-ip</i> .
<i>server-tag</i>	The AAA server group tag defined by the aaa-server command.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To include or exclude traffic for authentication, you must designate an authentication server with the **aaa-server** command before using the **aaa authentication** command. Each combination of local and foreign IP addresses can have one **aaa authentication** command for inbound connections and one for outbound connections. A session whose IP address is identified by the **aaa-server authentication** command starts a connection through FTP, Telnet, HTTP, or HTTPS and is prompted for a username and password. If the username and password are verified by the designated authentication server, the security appliance allows further traffic between the authenticating host and the client address.

Use the *interface-name*, *local-ip*, and *foreign-ip* variables to define where access is sought and from whom. The address for *local-ip* is always on the highest security level interface and *foreign-ip* is always on the lowest.

**Note**

You cannot use the **aaa authentication** command between same-security interfaces. For that scenario, you must use the **aaa authentication match** command.

For the local and foreign IP address masks, you can use **0** as a shorthand representation if the IP address is 0.0.0.0. Use **255.255.255.255** for a host.

The authentication servers determine whether a user can or cannot access the system, what services can be accessed, and what IP addresses the user can access. The security appliance proxies FTP, HTTP, HTTPS, and Telnet to display the credentials prompts.

**Note**

When a cut-through proxy is configured, TCP sessions (TELNET, FTP, HTTP, or HTTPS) might have their sequence numbers randomized even if the **norandomseq** option is used in the **nat** or **static** command. This occurs when a AAA server proxies the TCP session to authenticate the user before permitting access.

local access authentication

To configure a AAA server (TACACS+, RADIUS, or LOCAL) to authenticate administrators, choose one of the following access authentication service options: **serial** for serial console access, **telnet** for Telnet access, **ssh** for SSH access, **http** for HTTP access, and **enable** for enable-mode access.

cut-through authentication

For cut-through proxy and “to the box” authentication, you can also use the local security appliance user authentication database by specifying the server group tag **LOCAL**. If **LOCAL** is specified for *server-tag* and the local user credential database is empty, the following warning message appears:

```
Warning:local database is empty! Use 'username' command to define local users.
```

Conversely, if the local database becomes empty when **LOCAL** is still present in the command, the following warning message appears:

```
Warning:Local user database is empty and there are still commands using 'LOCAL' for authentication.
```

The cut-through authentication service options are as follows: **telnet**, **ftp**, **http**, **https**, **icmp/type**, **proto**, **tcp/port**, and **udp/port**. The variable *proto* can be any supported IP protocol value or name: for example, **ip** or **igmp**. Only Telnet, FTP, HTTP, or HTTPS traffic triggers interactive user authentication.

The authentication ports that the security appliance supports for AAA are fixed:

- Port 21 for FTP
- Port 23 for Telnet
- Port 80 for HTTP
- Port 443 for HTTPS

For this reason, do not use Static PAT to reassign ports for services you want to authenticate. In other words, when the port to authenticate is not one of the three known ports, the security appliance rejects the connection instead of authenticating it.

You can enter an ICMP message type number for *type* to include or exclude that specific ICMP message type from authentication. For example, **icmp/8** includes or excludes type 8 (echo request) ICMP messages.

The **tcp/0** option enables authentication for all TCP traffic, which includes FTP, HTTP, HTTPS, and Telnet. When a specific *port* is specified, only the traffic with a matching destination port is included or excluded for authentication. Note that FTP, Telnet, HTTP, and HTTPS are equivalent to **tcp/21**, **tcp/23**, **tcp/80**, and **tcp/443**, respectively.

If you specify **ip**, all IP traffic is included or excluded for authentication, depending on whether **include** or **exclude** is specified. When all IP traffic is included for authentication, following are the expected behaviors:

- Before a user (source IP-based) is authenticated, an FTP, Telnet, HTTP, or HTTPS request triggers authentication, and all other IP requests are denied.
- After a user is authenticated through FTP, Telnet, HTTP, HTTPS, or virtual Telnet authentication (see the **virtual** command), all traffic is free from authentication until the uauth timeout.

Enabling Authentication

The **aaa authentication** command enables or disables the following features:

- User authentication services provided by a LOCAL, TACACS+, or RADIUS server are first designated with the **aaa-server** command. A user starting a connection via FTP, Telnet, HTTP, or HTTPS is prompted for the username and password. If the username and password are verified by the designated authentication server, the security appliance cut-through proxy feature allows further FTP, Telnet, HTTP, or HTTPS traffic between the source and destination.
- Administrative authentication services providing access to the security appliance console via Telnet, SSH, HTTP, or the serial console. Telnet access requires previous use of the **telnet** command. SSH access requires previous use of the **ssh** command.

The prompts users see requesting AAA credentials differ among the services that can access the security appliance for authentication: Telnet, FTP, HTTP, and HTTPS:

Option	Number of Login Attempts Allowed	Notes
ftp	Incorrect password causes the connection to be dropped immediately.	FTP users receive a prompt from the FTP program. Some FTP graphical user interfaces do not display challenge values
http	Continual reprompting until successful login.	HTTP users see a pop-up window generated by the browser itself if aaa authentication secure-http-client is <i>not</i> configured. If aaa authentication secure-http-client is configured, a form loads in the browser to collect username and password.
telnet	4 tries before dropping the connection.	Before the first command line prompt of a Telnet console connection

**Note**

For HTTP or HTTPS, when the web server and the authentication server are on different hosts, use the **virtual** command to get the correct authentication behavior.

You can specify an interface name with the **aaa authentication** command. For example, if you specified **aaa authentication include tcp outside 0 0 server-tag**, the security appliance authenticates a tcp connection originating on the outside interface.

**Note**

For HTTP or HTTPS authentication, once authenticated, a user never has to reauthenticate, no matter how low the security appliance uauth timer is set, because the browser caches the string “Basic=Uuhjksdkfhk==” in every subsequent connection to that particular site. This can be cleared only when the user exits *all* instances of Netscape Navigator or Internet Explorer and restarts. Flushing the cache is of no use.

TACACS+ and RADIUS servers

You can have up to 15 single-mode server groups or 4 multi-mode server groups. Each group can have up to 16 servers in single mode or 4 servers in multi-mode. The servers can be either TACACS+ or RADIUS servers—set with the **aaa-server** command. When a user logs in, the servers are accessed one at a time starting with the first server you specify in the configuration, until a server responds.

The security appliance permits only one authentication type per network. For example, if one network connects through the security appliance using TACACS+ for authentication, another network connecting through the security appliance can authenticate with RADIUS, but one network cannot authenticate with both TACACS+ and RADIUS.

**Note**

The security appliance does not enforce VPN attributes enforced by a RADIUS authentication server, if VPN attributes are enforced by the authorization server, since authorization takes place after authentication. For example, if the attribute-value pair “tunnel-group=VPN” is defined for RADIUS authentication and LDAP authorization, then all the VPN remote-access attributes configured on the LDAP server are enforced on the VPN remote-access tunnel. Those attributes defined by the RADIUS authentication server are ignored. This behavior affects the authentication/authorization parameters for tunnel-group, webvpn, pop, imap, and smtps.

Examples

The following examples show some uses of the **aaa authentication** command:

Example 1:

The following example includes for authentication TCP traffic on the outside interface, with a local IP address of 192.168.0.0 and a netmask of 255.255.0.0, with a remote/foreign IP address of all hosts, and using a server named “tacacs+”. The second command line excludes Telnet traffic on the outside interface with a local address of 192.168.38.0, with a remote/foreign IP address of all hosts:

```
hostname(config)# aaa authentication include tcp outside 192.168.0.0 255.255.0.0 0.0.0.0
0.0.0.0 tacacs+
hostname(config)# aaa authentication exclude telnet outside 192.168.38.0 255.255.255.0
0.0.0.0 0.0.0.0 tacacs+
```

Example 2:

The following examples demonstrate ways to use the *interface-name* parameter. The security appliance has an inside network of 192.168.1.0, an outside network of 209.165.201.0 (subnet mask 255.255.255.224), and a perimeter network of 209.165.202.128 (subnet mask 255.255.255.224).

This example enables authentication for connections originated from the inside network to the outside network:

```
hostname(config)# aaa authentication include tcp inside 192.168.1.0 255.255.255.0
209.165.201.0 255.255.255.224 tacacs+
```

Example 3:

This example enables authentication for connections originated from the inside network to the perimeter network:

```
hostname(config)#aaa authentication include tcp inside 192.168.1.0 255.255.255.0
209.165.202.128 255.255.255.224 tacacs+
```

Example 4:

This example enables authentication for connections originated from the outside network to the inside network:

```
hostname(config)# aaa authentication include tcp outside 209.165.201.0 255.255.255.224
192.168.1.0 255.255.255.0 tacacs+
```

Example 5:

This example enables authentication for connections originated from the outside network to the perimeter network:

```
hostname(config)# aaa authentication include tcp outside 209.165.201.0 255.255.255.224
209.165.202.128 255.255.255.224 tacacs+
```

Example 6:

This example enables authentication for connections originated from the perimeter network to the outside network:

```
hostname(config)#aaa authentication include tcp inside 209.165.202.128 255.255.255.224
209.165.201.0 255.255.255.224 tacacs+
```

Example 7:

This example specifies that IP addresses 10.0.0.1 through 10.0.0.254 must be authenticated by the security appliance when establishing connections through the outside interface. In this example, the first **aaa authentication** command requires authentication of all FTP, HTTP, and Telnet sessions. The second **aaa authentication** command lets host 10.0.0.42 start outbound connections without being authenticated. This example uses a server group named **tacacs+**.

```
hostname(config)# nat (inside) 1 10.0.0.0 255.255.255.0
hostname(config)# aaa authentication include tcp inside 0 0 tacacs+
hostname(config)# aaa authentication exclude tcp inside 10.0.0.42 255.255.255.255 tacacs+
```

Example 8:

This example permits inbound access to a tcp IP address in the range of 209.165.201.1 through 209.165.201.30 indicated by the 209.165.201.0 network address (subnet mask 255.255.255.224). All services are permitted by the **access-list** command, and the **aaa authentication** command requires authentication on HTTP. The authentication server is at IP address 10.16.1.20 on the inside interface.

```
hostname(config)# aaa-server AuthIn protocol tacacs+
hostname(config)# aaa-server AuthIn (inside) host 10.16.1.20 thisisakey timeout 20
hostname(config)# access-list acl-out permit tcp 10.16.1.0 255.255.255.0 209.165.201.0
255.255.255.224
hostname(config)# access-group acl-out in interface outside
hostname(config)# aaa authentication include http inside 0 0 0 0 AuthIn
```

Related Commands

Command	Description
aaa authentication console	Enables or disables authentication on entry to privileged mode or requires authentication verification to access the security appliance via the specified type of connection.
aaa authentication match	Specifies the name of an access list, previously defined in an access-list command, that must be matched, and then provides authentication for that match.
aaa authentication secure-http-client	Provides a secure method for user authentication to the security appliance prior to allowing HTTP requests to traverse the security appliance.
aaa-server protocol	Configures group-related server attributes.
aaa-server host	Configures host-related attributes.

aaa authentication console

To enable authentication service for access to the security appliance console over an SSH, HTTP, or Telnet connection or from the Console connector on the security appliance, use the **aaa authentication console** command in global configuration mode. This command also lets you enable access to privileged EXEC mode. To disable this authentication service, use the **no** form of this command.

aaa authentication { **serial** | **enable** | **telnet** | **ssh** | **http** } **console** { *server-tag* [**LOCAL**] | **LOCAL** }

no aaa authentication { **serial** | **enable** | **telnet** | **ssh** | **http** } **console** { *server-tag* [**LOCAL**] | **LOCAL** }

Syntax Description

enable	Enables authentication for entry to privileged EXEC mode using the enable command.
http	Enables authentication of ASDM sessions over HTTPS. The SDI server group protocol is not supported for HTTP management authentication.
LOCAL	The keyword LOCAL has two uses. It can designate the use of the local database, or it can specify fallback to the local database if the designated authentication server is unavailable.
serial	Enables authentication of admin sessions established on the serial console interface.
<i>server-tag</i>	Specifies the AAA server group tag defined by the aaa-server protocol command. You can also use the local user database by specifying the server group tag LOCAL .
ssh	Enables authentication of admin sessions over SSH.
telnet	Enables authentication of admin sessions over Telnet.

Defaults

By default, fallback to the local database is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If you enable CLI authentication, the security appliance prompts you for your username and password to log in. After you enter your information, you have access to user EXEC mode.

To enter privileged EXEC mode, enter the **enable** command or the **login** command (if you are using the local database only).

If you configure enable authentication, the security appliance prompts you for your username and password. If you do not configure enable authentication, enter the system enable password when you enter the **enable** command (set by the **enable password** command). However, if you do not use enable authentication, after you enter the **enable** command, you are no longer logged in as a particular user. To maintain your username, use enable authentication. This feature is particularly useful when you perform command authorization, where usernames are important to determine the commands a user can enter.

For authentication using the local database, you can use the **login** command, which maintains the username but requires no configuration to turn on authentication.

Before the security appliance can authenticate a Telnet, SSH, or HTTP user, you must first configure access to the security appliance using the **telnet**, **ssh**, and **http** commands. These commands identify the IP addresses that are allowed to communicate with the security appliance. Telnet access to the security appliance console is available from any internal interface, and from the outside interface with IPsec configured. SSH access to the security appliance console is available from any interface.

The **http** keyword authenticates the ASDM client that accesses the security appliance using HTTPS. You only need to configure HTTP authentication if you want to use a AAA server. By default, ASDM uses the local database for authentication even if you do not configure this command. HTTP management authentication does not support the SDI protocol for a AAA server group.

If you use a AAA server group for authentication, you can configure the security appliance to use the local database as a fallback method if the AAA server is unavailable. Specify the server group name followed by **LOCAL** (**LOCAL** is case sensitive). We recommend that you use the same username and password in the local database as the AAA server because the security appliance prompt does not give any indication which method is being used.

You can alternatively use the local database as your main method of authentication (with no fallback) by entering **LOCAL** alone.

The maximum username prompt for HTTP authentication is 30 characters. The maximum password length is 16 characters.

As the following table shows, the action of the prompts for authenticated access to the security appliance console differ, depending on the option you choose with this command.

Option	Number of Login Attempts Allowed
Enable	3 tries before access is denied
Serial	Continual until success
SSH	3 tries before access is denied
Telnet	Continual until success
HTTP	Continual until success

If the SSH authentication request times out (which implies the AAA servers may be down or not available), you can gain access to the security appliance using the username **pix** and the login password (set with the **password** command). By default, the login password is **cisco**.

If a **aaa authentication http console** command statement is not defined, you can gain access to the security appliance using ASDM with no username and the security appliance enable password (set with the **enable password** command). If the **aaa** commands are defined, but the HTTP authentication requests a time out, which implies the AAA servers might be down or not available, you can gain access to the security appliance using the default administrator username and the enable password. By default, the enable password is not set.

Examples

The following example shows use of the **aaa authentication console** command for a Telnet connection to a RADIUS server with the server tag “radius”:

```
hostname(config)# aaa authentication telnet console radius
```

The following example identifies the server group “AuthIn” for administrative authentication.

```
hostname(config)# aaa authentication enable console AuthIn
```

The following example shows use of the **aaa authentication console** command with fallback to the LOCAL user database if all the servers in the group “srvgrp1” fail:

```
hostname(config)# aaa-server srvgrp1 protocol tacacs+  
hostname(config)# aaa authentication serial console srvgrp1 LOCAL
```

Related Commands

Command	Description
aaa authentication	Enables or disables user authentication.
aaa-server host	Specifies the AAA server to use for user authentication.
clear configure aaa	Remove/reset the configured AAA accounting values.
show running-config aaa	Display the AAA configuration.

aaa authentication match

To enable the use of a specified access list that must be matched to enable LOCAL, TACACS+, or RADIUS user authentication on a server designated by the **aaa-server** command or ASDM user authentication, use the **aaa authentication match** command in global configuration mode. To disable the requirement to match a specified access list, use the **no** form of this command. The **aaa authentication match** command specifies the name of an access list, previously defined in an access-list command, that must be matched, and then provides authentication for that match.

aaa authentication match *acl-name interface-name server-tag*

no aaa authentication match *acl-name interface-name server-tag*

Syntax Description

<i>acl-name</i>	An access-list command statement name.
<i>interface-name</i>	The interface name from which to authenticate users.
<i>server-tag</i>	The AAA server group tag defined by the aaa-server command.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Using the **aaa authentication match** command requires that you have previously used the **aaa-server** command to designate an authentication server—unless you specify **LOCAL**, and that you have previously used the **access-list** command to define a named access list. Do not use an **access-list** command statement that uses the source port to identify matching traffic. The source port is not supported in the match criteria of the **aaa authentication match** command.

Use the *interface-name* variable to define where access is sought.

For cut-through proxy, you can also use the local user authentication database by specifying the server group tag **LOCAL**. If **LOCAL** is specified for server-tag and the local user credential database is empty, the following warning message appears:

Warning: local database is empty! Use 'username' command to define localisms.

Conversely, if the local database becomes empty when **LOCAL** is still present in the command, the following warning message appears:

Warning: local database is empty and there are still commands using 'LOCAL' for authentication.

Examples

The following set of examples illustrates how to use the **aaa authentication match** command:

```
hostname(config)# show access-list
access-list mylist permit tcp 10.0.0.0 255.255.255.0 172.23.2.0 255.255.255.0 (hitcnt=0)
access-list yourlist permit tcp any any (hitcnt=0)
```

```
hostname(config)# show running-config aaa
aaa authentication match mylist outbound TACACS+
```

In this context, the following command:

```
hostname(config)# aaa authentication match yourlist outbound tacacs
```

is equivalent to this command:

```
hostname(config)# aaa authentication include TCP/0 outbound 0.0.0.0 0.0.0.0 0.0.0.0
0.0.0.0 tacacs
```

The **aaa** command statement list is order-dependent between **access-list** command statements. If you enter the following command:

```
hostname(config)# aaa authentication match mylist outbound TACACS+
```

before this command:

```
hostname(config)# aaa authentication match yourlist outbound tacacs
```

the security appliance tries to find a match in the **mylist access-list** command statement group before it tries to find a match in the **yourlist access-list** command statement group.

Related Commands

Command	Description
aaa authorization	Enables or disable LOCAL or TACACS+ user authorization services.
access-list extended	Creates an access list or use a downloadable access list.
clear configure aaa	Remove/reset the configured AAA accounting values.
show running-config aaa	Display the AAA configuration.

aaa authentication secure-http-client

To enable SSL and secure username and password exchange between HTTP clients and the security appliance, use the **aaa authentication secure-http-client** command in global configuration mode. To disable this function, use the **no** form of this command. The **aaa authentication secure-http-client** command offers a secure method for user authentication to the security appliance prior to allowing user HTTP-based web requests to traverse the security appliance.

aaa authentication secure-http-client

no aaa authentication secure-http-client

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Release	Modification
Preexisting	This command was preexisting.

Command History

Usage Guidelines The **aaa authentication secure-http-client** command secures HTTP client authentication (through SSL). This command is used for HTTP cut-through proxy authentication.

The **aaa authentication secure-http-client** command has the following limitations:

- At runtime, a maximum of 16 HTTPS authentication processes is allowed. If all 16 HTTPS authentication processes are running, the 17th, new HTTPS connection requiring authentication is not allowed.
- When **uauth timeout 0** is configured (the **uauth timeout** is set to 0), HTTPS authentication might not work. If a browser initiates multiple TCP connections to load a web page after HTTPS authentication, the first connection is let through, but the subsequent connections trigger authentication. As a result, users are continuously presented with an authentication page, even if the correct username and password are entered each time. To work around this, set the **uauth timeout** to 1 second with the **timeout uauth 0:0:1** command. However, this workaround opens a 1-second window of opportunity that might allow non-authenticated users to go through the firewall if they are coming from the same source IP address.

- Because HTTPS authentication occurs on the SSL port 443, users must not configure an **access-list** command statement to block traffic from the HTTP client to HTTP server on port 443. Furthermore, if static PAT is configured for web traffic on port 80, it must also be configured for the SSL port. In the following example, the first line configures static PAT for web traffic and the second line must be added to support the HTTPS authentication configuration:

```
static (inside,outside) tcp 10.132.16.200 www 10.130.16.10 www
static (inside,outside) tcp 10.132.16.200 443 10.130.16.10 443
```

- HTTP users see a pop-up window generated by the browser itself if **aaa authentication secure-http-client** is not configured. If **aaa authentication secure-http-client** is configured, a form loads in the browser to collect username and password. In either case, if a user enters an incorrect password, the user is reprompted. When the web server and the authentication server are on different hosts, use the **virtual** command to get the correct authentication behavior.

**Tip**

The **help aaa** command displays the syntax and usage for the **aaa authentication** commands in summary form.

Examples

The following example configures HTTP traffic to be securely authenticated:

```
hostname(config)# aaa authentication secure-http-client
hostname(config)# aaa authentication include http...
```

where “...” represents your values for *authen_service if_name local_ip local_mask [foreign_ip foreign_mask] server_tag*.

The following command configures HTTPS traffic to be securely authenticated:

```
hostname (config)# aaa authentication include https...
```

where “...” represents your values for *authentication -service interface-name local-ip local-mask [foreign-ip foreign-mask] server-tag*.

**Note**

The **aaa authentication secure-https-client** command is not needed for HTTPS traffic.

Related Commands

Command	Description
aaa authentication	Enables LOCAL, TACACS+, or RADIUS user authentication, on a server designated by the aaa-server command.
virtual telnet	Accesses the security appliance virtual server.

aaa authorization

To enable or disable user authorization for services on the specified host, use the **aaa authorization** command in global configuration mode. To disable user authorization services for a specified host, use the **no** form of this command. The authentication server determines what services the user is authorized to access.

aaa authorization { **include** | **exclude** } *service interface-name local-ip local-mask foreign-ip foreign-mask server-tag*

no aaa authorization { **include** | **exclude** } *service interface-name local-ip local-mask foreign-ip foreign-mask server-tag*

Syntax Description

exclude	Creates an exception to a previously stated rule by excluding the specified service from authorization to the specified host.
<i>foreign-ip</i>	The IP address of the hosts you want to access the <i>local-ip</i> address. Use 0 to mean all hosts.
<i>foreign-mask</i>	Network mask of <i>foreign-ip</i> . Always specify a specific mask value. Use 0 if the IP address is 0. Use 255.255.255.255 for a host.
<i>interface-name</i>	Interface name from which users require authentication. Use <i>interface-name</i> in combination with the <i>local-ip</i> address and the <i>foreign-ip</i> address to determine where access is sought and from whom. The <i>local-ip</i> address is always on the highest security level interface and <i>foreign-ip</i> is always on the lowest.
include	Creates a new rule with the specified service to include.
<i>local-ip</i>	The IP address of the host or network of hosts that you want to be authenticated or authorized. You can set this address to 0 to mean all hosts and to let the authentication server decide which hosts are authenticated.
<i>local-mask</i>	Network mask of <i>local-ip</i> . Always specify a specific mask value. Use 0 if the IP address is 0. Use 255.255.255.255 for a host.
<i>server-tag</i>	The AAA server group tag as defined by the aaa-server command. You can also enter LOCAL for the group tag value and use the local firewall database AAA services such as local command authorization privilege levels.
<i>service</i>	The services that require authorization. Valid values are any , ftp , http , telnet , or <i>protocol/port</i> . Use any to provide authorization for all TCP services. To provide authorization for UDP services, use the <i>protocol/port</i> form. See the section “Usage Guidelines” for more information.

Defaults

An IP address of 0 means “all hosts.” Setting the local IP address to 0 lets the authorization server decide which hosts are authorized.

Fallback to the local database for authorization is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was modified for this release. The exclude parameter now allows the user to specify a port to exclude to a specific host or hosts.

Usage Guidelines

Except for its use with command authorization, the **aaa authorization** command requires previous configuration with the **aaa authentication** command; however, use of the **aaa authentication** command does not require use of a **aaa authorization** command.

The security appliance supports RADIUS authorization with the **aaa authorization** command only when authentication is performed with a different protocol. RADIUS servers return authorization information along with replies to authentication requests. See the description of the **aaa authentication** command. The **aaa authorization** command is permitted with LOCAL servers, only for command authorization, and with RADIUS or TACACS+ servers. You can set a dynamic ACL at the RADIUS server to provide authorization (even if it is not configured on the security appliance).

When VPN authorization is defined as LOCAL, the attributes configured in the default group policy DfltGrpPolicy are enforced. This affects the settings in the **tunnel-group** and **webvpn** commands.

**Tip**

The **help aaa** command displays the syntax and usage for the **aaa authentication** command in summary form.

For each IP address, one **aaa authorization** command is permitted. If you want to authorize more than one service with **aaa authorization**, use the **any** parameter for the service type.

If the first attempt at authorization fails and a second attempt causes a timeout, use the **service resetinbound** command to reset the client that failed the authorization so that it will not retransmit any connections. An example authorization timeout message in Telnet follows.

```
Unable to connect to remote host: Connection timed out
```

User authorization services control which network services a user can access. After a user is authenticated, attempts to access restricted services cause the security appliance to verify the access permissions of the user with the designated AAA server.

**Note**

RADIUS authorization is supported for use with **access-list deny-flow-max** command statements and for use in configuring a RADIUS server with an **acl=acl-name** vendor-specific identifier. For more information, refer to the **access-list deny-flow-port** command page and the **authentication-port** command page.

When specifying the foreign (destination) IP address, use **0** to indicate all hosts. For the destination and local masks, always specify a specific mask value. Use a mask of **0** if the IP address is **0**, and use a mask of **255.255.255.255** for a host.

Service Parameter

Services not specified are authorized implicitly. Services specified in the **aaa authentication** command do not affect the services that require authorization.

For *protocol/port*:

- *protocol*—the protocol (6 for TCP, 17 for UDP, 1 for ICMP, and so on).
- *port*—the TCP or UDP destination port, or port range. The *port* can also be the ICMP type; that is, 8 for ICMP echo or ping. A port value of 0 (zero) means all ports. Port ranges apply only to the TCP and UDP protocols, not to ICMP. For protocols other than TCP, UDP, and ICMP, do not use the *port* parameter. The following is a sample port specification.

```
hostname(config)# aaa authorization include udp/53-1024 outside 0 0 0 0
```

This example shows how to enable authorization for DNS lookups to the inside interface for all clients and authorizes access to any other services that have ports in the range of 53 to 1024.

A specific authorization rule does not require the equivalent authentication. Authentication is required only with FTP, HTTP, or Telnet to provide an interactive way for the user to enter the authorization credentials.



Note

Specifying a port range might produce unexpected results at the authorization server. The security appliance sends the port range to the server as a string, with the expectation that the server will parse it out into specific ports. Not all servers do this. In addition, you might want users to be authorized on specific services, which does not occur if a range is accepted.

The valid values for the *service* option are **telnet**, **ftp**, **http**, **https**, **tcp** or **0**, **tcp** or *port*, **udp** or *port*, **icmp** or *port*, or *protocol* [*/port*]. Only the Telnet, FTP, HTTP, and HTTPS traffic triggers user interactive authentication.

Examples

The following example uses the TACACS+ protocol:

```
hostname(config)#aaa-server tplus1 protocol tacacs+
hostname(config)#aaa-server tplus1 (inside) host 10.1.1.10 thekey timeout 20
hostname(config)#aaa authentication include any inside 0 0 0 0 tplus1
hostname(config)#aaa authorization include any inside 0 0 0 0
hostname(config)#aaa accounting include any inside 0 0 0 0 tplus1
hostname(config)#aaa authentication serial console tplus1
```

In this example, the first command statement creates a server group named **tplus1** and specifies the TACACS+ protocol for use with this group. The second command specifies that the authentication server with the IP address 10.1.1.10 resides on the inside interface and is in the **tplus1** server group. The next three command statements specify that any users starting connections through the outside interface to any foreign host will be authenticated using the **tplus1** server group, that the users who are successfully authenticated are authorized to use any service, and that all outbound connection information will be logged in the accounting database. The last command statement specifies that access to the security appliance serial console requires authentication from the **tplus1** server group.

The following example enables authorization for DNS lookups from the outside interface:

```
hostname(config)#aaa authorization include udp/53 outside 0.0.0.0 0.0.0.0
```


The following example enables authorization of ICMP echo-reply packets arriving at the inside interface from inside hosts:

```
hostname(config)#aaa authorization include 1/0 inside 0.0.0.0 0.0.0.0
```

This means that users cannot ping external hosts if they have not been authenticated using Telnet, HTTP, or FTP.

The following example enables authorization only for ICMP echoes (pings) that arrive at the inside interface from an inside host:

```
hostname(config)#aaa authorization include 1/8 inside 0.0.0.0 0.0.0.0
```

Related Commands

Command	Description
aaa authorization command	Specifies whether command execution is subject to authorization, or configure administrative authorization to support fallback to the local user database if all servers in the specified server group are disabled.
aaa authorization match	Enables or disables the LOCAL or TACACS+ user authorization services for a specific access-list command name.
clear configure aaa	Remove/reset the configured AAA accounting values.
show running-config aaa	Display the AAA configuration.

aaa authorization command

The **aaa authorization command** command specifies whether command execution is subject to authorization. To enable command authorization, use the **aaa authorization command** command in global configuration mode. To disable command authorization, use the **no** form of this command.

aaa authorization command {**LOCAL** | *server-tag*}

no aaa authorization command {**LOCAL** | *server-tag*}

The following syntax configures administrative authorization to support fallback to the local user database if all servers in the specified server group are disabled. This option is disabled by default.

aaa authorization command *server-tag* [**LOCAL**]

no aaa authorization command *server-tag* [**LOCAL**]

Syntax Description

LOCAL	Specify the use of the security appliance local user database for local command authorization (using privilege levels). If LOCAL is specified after a TACACS+ server group tag, the local user database is used for command authorization only as a fallback when the TACACS+ server group is unavailable.
<i>server-tag</i>	Specify a predefined server group tag for the TACACS+ authorization server. The AAA server group tag as defined by the aaa-server command. You can also enter LOCAL for the group tag value and use the local command authorization privilege levels.

Defaults

Fallback to the local database for authorization is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was modified to allow configuring administrative authorization to support fallback to the local user database if all servers in the specified group are disabled.

Usage Guidelines

When used for command authorization, the **aaa authorization command** command does not require previous configuration with the **aaa authentication** command.

The **aaa authorization** command is supported for use with TACACS+ servers and with LOCAL servers (only for command authorization), but not with RADIUS servers.

**Tip**

The **help aaa** command displays the syntax and usage for the **aaa authorization** command in summary form.

Examples

The following example shows how to enable command authorization using a TACACS+ server group named `tplus1`:

```
hostname(config)#aaa authorization command tplus1
```

The following example shows how to configure administrative authorization to support fallback to the local user database if all servers in the `tplus1` server group are unavailable.

```
hostname(config)#aaa authorization command tplus1 LOCAL
```

Related Commands

Command	Description
aaa authorization	Enable or disable user authorization for a LOCAL or a TACACS+ server designated by the aaa-server command, or for ASDM user authentication.
aaa-server host	Configure host-related attributes.
aaa-server protocol	Configure group-related server attributes.
clear configure aaa	Remove/reset the configured AAA accounting values.
show running-config aaa	Display the AAA configuration.

aaa authorization match

To enable the use of a specified access list that must be matched to enable or disable user authorization services, use the **aaa authorization match** command in global configuration mode. To disable the use of a specified access list for user authorization services, use the **no** form of this command. The authentication server determines what services the user is authorized to access.

aaa authorization match *acl-name interface-name server-tag*

no aaa authorization match *acl-name interface-name server-tag*

Syntax Description

<i>acl-name</i>	Specify an access-list command statement name.
<i>interface-name</i>	Interface name from which users require authentication.
<i>server-tag</i>	The AAA server group tag as defined by the aaa-server protocol command. You can also enter LOCAL for the group tag value and use the local security appliance database AAA services such as local command authorization privilege levels.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **aaa authorization match** command requires previous configuration with the **aaa authentication** command; however, use of the **aaa authentication** command does not require use of any **aaa authorization** command.

The security appliance supports RADIUS authorization with the **aaa authorization** command only when authentication is performed with a different protocol. RADIUS servers return authorization information along with replies to authentication requests. See the description of the **aaa authentication** command. The **aaa authorization** command is permitted with LOCAL servers, only for command authorization, and with RADIUS or TACACS+ servers. You can set a dynamic ACL at the RADIUS server to provide authorization (even if it is not configured on the security appliance).

**Tip**

The **help aaa** command displays the syntax and usage for the **aaa authorization match** command in summary form.

If the first attempt at authorization fails and a second attempt causes a timeout, use the **service resetinbound** command to reset the client that failed the authorization so that it will not retransmit any connections. An example authorization timeout message in Telnet follows.

Unable to connect to remote host: Connection timed out

User authorization services control which network services a user can access. After a user is authenticated, attempts to access restricted services cause the security appliance to verify the access permissions of the user with the designated AAA server.

Examples

The following example uses the tplus1 server group with the **aaa** commands:

```
hostname(config)#aaa-server tplus1 protocol tacacs+
hostname(config)#aaa-server tplus1 (inside) host 10.1.1.10 thekey timeout 20
hostname(config)#aaa authentication include any inside 0 0 0 0 tplus1
hostname(config)#aaa accounting include any inside 0 0 0 0 tplus1
hostname(config)#aaa authorization match myacl inside tplus1
```

In this example, the first command statement defines the tplus1 server group as a TACACS+ group. The second command specifies that the authentication server with the IP address 10.1.1.10 resides on the inside interface and is in the tplus1 server group. The next two command statements specify that any connections traversing the inside interface to any foreign host are authenticated using the tplus1 server group, and that all these connections are logged in the accounting database. The last command statement specifies that any connections that match the ACEs in myacl are authorized by the AAA servers in the tplus1 server group.

Related Commands

Command	Description
aaa authorization	Enable or disable user authorization for a LOCAL or a TACACS+ server designated by the aaa-server command, or for ASDM user authentication.
clear configure aaa	Reset all aaa configuration parameters to the default values.
clear uauth	Delete one user or all users' AAA authorization and authentication caches, which forces the user to reauthenticate the next time that he or she creates a connection.
show running-config aaa	Display the AAA configuration.
show uauth	Display the username provided to the authorization server for authentication and authorization purposes, the IP address to which the username is bound, and whether the user is only authenticated or has cached services.

aaa local authentication attempts max-fail

To limit the number of consecutive failed local login attempts that the security appliance allows any given user account, use the **aaa local authentication attempts max-fail** command in global configuration mode. This command only affects authentication with the local user database. To disable this feature and allow an unlimited number of consecutive failed local login attempts, use the **no** form of this command.

aaa local authentication attempts max-fail *number*

Syntax Description

<i>number</i>	The maximum number of times a user can enter a wrong password before being locked out. This number can be in the range 1-16.

Defaults

No default behavior or values..

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If you omit this command, there is no limit on the number of times a user can enter an incorrect password.

After a user makes the configured number of attempts with the wrong password, the user is locked out and cannot log in successfully until the administrator unlocks the username. Locking or unlocking a username results in a syslog message.

The administrator cannot be locked out of the device.

The number of failed attempts resets to zero and the lockout status resets to No when the user successfully authenticates or when the security appliance reboots.

Examples

The following example shows use of the **aaa local authentication attempts max-limits** command to set the maximum number of failed attempts allowed to 2:

```
hostname(config)# aaa local authentication attempts max-limits 2
hostname(config)#
```

Related Commands	Command	Description
	clear aaa local user lockout	Clears the lockout status of the specified users and set their failed-attempts counter to 0.
	clear aaa local user fail-attempts	Resets the number of failed user authentication attempts to zero without modifying the user's locked-out status.
	show aaa local user	Shows the list of usernames that are currently locked.

aaa mac-exempt

To specify the use of a predefined list of MAC addresses to exempt from authentication and authorization, use the **aaa mac-exempt** command in global configuration mode. To disable the use of a list of MAC addresses, use the **no** form of this command. The **aaa mac-exempt** command exempts a list of MAC addresses from authentication and authorization.

aaa mac-exempt match *id*

no aaa mac-exempt match *id*

Syntax Description

id A MAC access list number. (Configured with the **mac-list** command.)

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Configure the MAC access list number using the **mac-list** command before using the **aaa mac-exempt** command. Authorization is automatically exempted for MAC addresses for which authentication is exempted.

Examples

The following example shows how to specify the mac-exempt list:

```
hostname(config)# aaa mac-exempt mac-list-6
```

Related Commands

Command	Description
aaa authentication	Enable, disable, or view LOCAL, TACACS+, or RADIUS user authentication, on a server designated by the aaa-server command, or ASDM user authentication.
aaa authorization	Enable or disable LOCAL or TACACS+ user authorization services.
mac-list	Add a list of MAC addresses using a first-match search; used by the security appliance in performing MAC-based authentication.

aaa proxy-limit

To manually configure the uauth session limit by setting the maximum number of concurrent proxy connections allowed per user, use the **aaa proxy-limit** command in global configuration mode. To disable proxies, use the **disable** parameter. To return to the default proxy-limit value (16), use the **no** form of this command.

aaa proxy-limit *proxy_limit*

aaa proxy-limit **disable**

no **aaa proxy-limit**

Syntax Description

disable	No proxies allowed.
<i>proxy_limit</i>	Specify the number of concurrent proxy connections allowed per user, from 1 to 128.

Defaults

The default proxy-limit value is 16.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If a source address is a proxy server, consider excluding this IP address from authentication or increasing the number of allowable outstanding AAA requests.

Examples

The following example shows how to set the maximum number of outstanding authentication requests allowed per user:

```
hostname(config)# aaa proxy-limit 6
```

Related Commands	Command	Description
	aaa authentication	Enable, disable, or view LOCAL, TACACS+, or RADIUS user authentication, on a server designated by the aaa-server command, or ASDM user authentication
	aaa authorization	Enable or disable LOCAL or TACACS+ user authorization services.
	aaa-server host	Specifies a AAA server.
	clear configure aaa	Remove/reset the configured AAA accounting values.
	show running-config aaa	Display the AAA configuration.

aaa-server host

To configure a AAA server or to configure AAA server parameters that are host-specific, use the **aaa-server host** command in global configuration mode. When you use the **aaa-server host** command, you enter the aaa-server host mode, from which you can specify and manage host-specific AAA server connection data. To remove a host configuration, use the **no** form of this command:

aaa-server *server-tag* [(*interface-name*)] **host** *server-ip* [*key*] [**timeout** *seconds*]

no aaa-server *server-tag* [(*interface-name*)] **host** *server-ip* [*key*] [**timeout** *seconds*]

Syntax Description

<i>(interface-name)</i>	(Optional) The network interface where the authentication server resides. The parentheses are required in this parameter.
<i>key</i>	(Optional) A case-sensitive, alphanumeric keyword of up to 127 characters that is the same value as the key on the RADIUS or TACACS+ server. Any characters entered past 127 are ignored. The key is used between the security appliance and the server for encrypting data between them. the key must be the same on both the security appliance and server systems. Spaces are not permitted in the key, but other special characters are allowed. You can add or modify the key using the key command in host mode.
<i>server-ip</i>	The IP address of the AAA server.
<i>server-tag</i>	Symbolic name of the server group. Other aaa commands make reference to the <i>server-tag</i> group defined by the aaa-server command <i>server-tag</i> parameter.
timeout <i>seconds</i>	(Optional) The timeout interval for the request. This is the time after which the security appliance gives up on the request to the primary AAA server. If there is a standby AAA server, the security appliance sends the request to the backup server. You can modify the timeout interval using the timeout command in host mode.

Defaults

The default timeout value is 10 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

You can have up to 15 single-mode groups or 4 multi-mode groups. Each group can have up to 16 servers in single mode or 4 servers in multi-mode. When a user logs in, the servers are accessed one at a time starting with the first server you specify in the configuration, until a server responds.

If aaa accounting is in effect, the accounting information goes only to the active server, unless you specify simultaneous accounting in the **aaa-server protocol** command.

Since the security appliance version of the **aaa-server** command supports the specification of server ports on a per-host basis, the following command forms that were available on earlier PIX Firewall systems have been phased out (deprecated), with their semantics changing as indicated. This applies only to server groups that contain RADIUS servers. These commands will be accepted but will no longer be written to the configuration.

- **aaa-server radius-authport** [*auth-port*]*—*This command controls the *default* authentication port for all RADIUS servers. This means that if a host specific authentication port has not been specified, the value specified by this command is used. If a value has not been specified by this command, the default radius authentication port (1645) is used.
- **aaa-server radius-acctport** [*acct-port*]*—*This command applies the behavior described above to the RADIUS accounting port (default 1646).

The following are all the host mode commands. Only the ones that apply to the AAA server type for the server group you selected will be available. See the individual command descriptions for details.

Command	Applicable AAA Server Types	Default Value
accounting-port	RADIUS	1646
acl-netmask-convert	RADIUS	standard
authentication-port	RADIUS	1645
kerberos-realm	Kerberos	—
key ¹	RADIUS	—
	TACACS+	—
ldap-base-dn	LDAP	—
ldap-login-dn	LDAP	—
ldap-login-password	LDAP	—
ldap-naming-attribute	LDAP	—
ldap-scope	LDAP	—
nt-auth-domain-controller	NT	—
radius-common-pw	RADIUS	—
retry-interval	Kerberos	10 seconds
	RADIUS	10 seconds
sdi-pre-5-slave	SDI	—
sdi-version	SDI	sdi-5

Command	Applicable AAA Server Types	Default Value
server-port	Kerberos	88
	LDAP	389
	NT	139
	SDI	5500
	TACACS+	49
timeout²	All	10 seconds

1. If you specify the *key* parameter with the **aaa-server** command, that parameter has the same effect as using the **key** command in host mode.
2. If you specify the **timeout** parameter with the **aaa-server** command, that parameter has the same effect as using the **timeout** command in host mode.

The **aaa-server** command was modified for this release. It is now two separate commands, **aaa-server group-tag protocol** to enter group mode and **aaa-server host** to enter host mode.

Examples

The following example configures an SDI AAA server group named “svrgrp1” on host “192.168.3.4”, sets the timeout interval to 6 seconds, sets the retry interval to 7 seconds, and configures the SDI version to version 5.

```
hostname(config)# aaa-server svrgrp1 protocol sdi
hostname(config-aaa-server-group)# aaa-server svrgrp1 host 192.168.3.4
hostname(config-aaa-server-host)# timeout 6
hostname(config-aaa-server-host)# retry 7
hostname(config-aaa-server-host)# sdi-version sdi-5
hostname(config-aaa-server-host)# exit
hostname(config)#
```

Related Commands

Command	Description
clear configure aaa-server	Removes all AAA-server configuration.
show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol

aaa-server protocol

To configure AAA server parameters that are group-specific and common to all hosts, use the **aaa-server protocol** command in global configuration mode to enter the AAA-server group mode, from which you can configure these group parameters. To remove the designated group, use the **no** form of this command.

aaa-server *server-tag* **protocol** *server-protocol*

no aaa-server *server-tag* **protocol** *server-protocol*

Syntax Description

<i>server-tag</i>	Symbolic name of the server group. Other AAA commands make reference to the <i>server-tag</i> group defined by the aaa-server command <i>server-tag</i> parameter.
<i>server-protocol</i>	The AAA protocol that the servers in the group support: kerberos , ldap , nt , radius , sdi , or tacacs+ .

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can have up to 15 single-mode groups or 4 multi-mode groups. Each group can have up to 16 servers in single mode or 4 servers in multi-mode. When a user logs in, the servers are accessed one at a time starting with the first server you specify in the configuration, until a server responds.

If AAA accounting is in effect, the accounting information goes only to the active server unless you have configured simultaneous accounting.

You control AAA server configuration with two commands: **aaa-server protocol** to enter AAA-server group mode and **aaa-server host** to enter AAA-server host mode. In addition, group mode, which you enter by specifying the **aaa-server protocol** command, supports accounting mode and server reactivation features through the **accounting-mode** and **reactivation-mode** commands.

The supported commands in AAA-server group mode are as follows:

- **accounting-mode**
- **reactivation-mode**

- **max-failed-attempts**

See the individual command descriptions for details about these commands.

Examples

The following example shows the use of the **aaa-server protocol** command to modify details of a TACACS+ server group configuration:

```
hostname(config)# aaa-server svrgrp1 protocol tacacs+
hostname(config-aaa-server-group)# accounting-mode simultaneous
hostname(config-aaa-server-group)# reactivation mode timed
hostname(config-aaa-server-group)# max-failed attempts 2
hostname(config-aaa-server-group)# exit
hostname(config)#
```

Related Commands

Command	Description
accounting-mode	Indicates whether accounting messages are sent to a single server (single mode) or sent to all servers in the group (simultaneous mode).
reactivation-mode	Specifies the method by which failed servers are reactivated.
max-failed-attempts	Specifies the number of failures that will be tolerated for any given server in the server group before that server is deactivated.
clear configure aaa-server	Removes all AAA server configurations.
show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol.

absolute

To define an absolute time when a time range is in effect, use the **absolute** command in time-range configuration mode. To disable, use the **no** form of this command.

absolute [**end** *time date*] [**start** *time date*]

no absolute

Syntax Description

<i>date</i>	Specifies the date in the format day month year; for example, 1 January 2006. The valid range of years is 1993 through 2035.
<i>time</i>	Specifies the time in the format HH:MM. For example, 8:00 is 8:00 a.m. and 20:00 is 8:00 p.m.

Defaults

If no start time and date are specified, the permit or deny statement is in effect immediately and always on. Similarly, the maximum end time is 23:59 31 December 2035. If no end time and date are specified, the associated permit or deny statement is in effect indefinitely.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Time-range configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

To implement a time-based ACL, use the **time-range** command to define specific times of the day and week. Then use the with the **access-list extended time-range** command to bind the time range to an ACL.

Examples

The following example activates an ACL at 8:00 a.m. on 1 January 2006:

```
hostname(config-time-range)# absolute start 8:00 1 January 2006
```

Because no end time and date are specified, the associated ACL is in effect indefinitely.

Related Commands	Command	Description
	access-list extended	Configures a policy for permitting or denying IP traffic through the security appliance.
	default	Restores default settings for the time-range command absolute and periodic keywords.
	periodic	Specifies a recurring (weekly) time range for functions that support the time-range feature.
	time-range	Defines access control to the security appliance based on time.

accept-subordinates

To configure the security appliance to accept subordinate CA certificates if delivered during phase one IKE exchange when not previously installed on the device, use the **accept-subordinates** command in crypto ca trustpoint configuration mode. To restore the default setting, use the **no** form of the command.

accept-subordinates

no accept-subordinates

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting is on (subordinate certificates are accepted).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

During phase 1 processing, an IKE peer might pass both a subordinate certificate and an identity certificate. The subordinate certificate might not be installed on the security appliance. This command lets an administrator support subordinate CA certificates that are not configured as trustpoints on the device without requiring that all subordinate CA certificates of all established trustpoints be acceptable; in other words, this command lets the device authenticate a certificate chain without installing the entire chain locally.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and allows the security appliance to accept subordinate certificates for trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# accept-subordinates
hostname(ca-trustpoint)#
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint configuration mode.
default enrollment	Returns enrollment parameters to their defaults.

access-group

To bind an access list to an interface, use the **access-group** command in global configuration mode. To unbind an access list from the interface, use the **no** form of this command.

access-group *access-list* {**in** | **out**} **interface** *interface_name* [*per-user-override*]

no access-group *access-list* {**in** | **out**} **interface** *interface_name*

Syntax Description

<i>access-list</i>	Access list <i>id</i> .
in	Filters the inbound packets at the specified interface.
interface <i>interface-name</i>	Name of the network interface.
out	Filters the outbound packets at the specified interface.
<i>per-user-override</i>	(Optional) Allows downloadable user access lists to override the access list applied to the interface.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **access-group** command binds an access list to an interface. The access list is applied to traffic inbound to an interface. If you enter the **permit** option in an **access-list** command statement, the security appliance continues to process the packet. If you enter the **deny** option in an **access-list** command statement, the security appliance discards the packet and generates the following syslog message.

```
%hostname-4-106019: IP packet from source_addr to destination_addr, protocol
protocol received from interface interface_name deny by access-group id
```

The *per-user-override* option allows downloaded access lists to override the access list applied to the interface. If the *per-user-override* optional argument is not present, the security appliance preserves the existing filtering behavior. When *per-user-override* is present, the security appliance allows the **permit** or **deny** status from the per-user access-list (if one is downloaded) associated to a user to override the permit or deny status from the **access-group** command associated access list. Additionally, the following rules are observed:

- At the time a packet arrives, if there is no per-user access list associated with the packet, the interface access list will be applied.
- The per-user access list is governed by the timeout value specified by the **uauth** option of the **timeout** command but it can be overridden by the AAA per-user session timeout value.
- Existing access list log behavior will be the same. For example, if user traffic is denied because of a per-user access list, syslog message 109025 will be logged. If user traffic is permitted, no syslog message is generated. The log option in the per-user access-list will have no effect.

Always use the **access-list** command with the **access-group** command.

The **access-group** command binds an access list to an interface. The **in** keyword applies the access list to the traffic on the specified interface. The **out** keyword applies the access list to the outbound traffic.



Note

If all of the functional entries (the permit and deny statements) are removed from an access list that is referenced by one or more **access-group** commands, the **access-group** commands are automatically removed from the configuration. The **access-group** command cannot reference empty access lists or access lists that contain only a remark.

The **no access-group** command unbinds the access list from the interface *interface_name*.

The **show running config access-group** command displays the current access list bound to the interfaces.

The **clear configure access-group** command removes all the access lists from the interfaces.

Examples

The following example shows how to use the **access-group** command:

```
hostname(config)# static (inside,outside) 209.165.201.3 10.1.1.3
hostname(config)# access-list acl_out permit tcp any host 209.165.201.3 eq 80
hostname(config)# access-group acl_out in interface outside
```

The **static** command provides a global address of 209.165.201.3 for the web server at 10.1.1.3. The **access-list** command lets any host access the global address using port 80. The **access-group** command specifies that the **access-list** command applies to traffic entering the outside interface.

Related Commands

Command	Description
access-list extended	Creates an access list, or uses a downloadable access list.
clear configure access-group	Removes access groups from all the interfaces.
show running-config access-group	Displays the context group members.

access-list alert-interval

To specify the time interval between deny flow maximum messages, use the **access-list alert-interval** command in global configuration mode. To return to the default settings, use the **no** form of this command.

access-list alert-interval *secs*

no access-list alert-interval

Syntax Description

secs Time interval between deny flow maximum message generation; valid values are from 1 to 3600 seconds.

Defaults

The default is 300 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Global Configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **access-list alert-interval** command sets the time interval for generating the syslog message 106101. The syslog message 106101 alerts you that the security appliance has reached a deny flow maximum. When the deny flow maximum is reached, another 106101 message is generated if at least *secs* seconds have occurred since the last 106101 message.

See the **access-list deny-flow-max** command for information about the deny flow maximum message generation.

Examples

The following example shows how to specify the time interval between deny flow maximum messages:

```
hostname(config)# access-list alert-interval 30
```

Related Commands	Command	Description
	access-list deny-flow-max	Specifies the maximum number of concurrent deny flows that can be created.
	access-list extended	Adds an access list to the configuration and is used to configure policy for IP traffic through the security appliance.
	clear access-list	Clears an access list counter.
	clear configure access-list	Clears access lists from the running configuration.
	show access-list	Displays the access list entries by number.

access-list deny-flow-max

To specify the maximum number of concurrent deny flows that can be created, use the **access-list deny-flow-max** command in global configuration mode. To return to the default settings, use the **no** form of this command.

access-list deny-flow-max

no access-list deny-flow-max

Syntax Description

This command has no arguments or keywords.

Defaults

The default is 4096.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global Configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Syslog message 106101 is generated when the security appliance has reached the maximum number, *n*, of ACL deny flows.

Examples

The following example shows how to specify the maximum number of concurrent deny flows that can be created:

```
hostname(config)# access-list deny-flow-max 256
```

Related Commands

Command	Description
access-list extended	Adds an access list to the configuration and used to configure policy for IP traffic through the security appliance.
clear access-list	Clears an access list counter.
clear configure access-list	Clears access lists from the running configuration.

Command	Description
show access-list	Displays the access list entries by number.
show running-config access-list	Displays the current running access-list configuration.

access-list ethertype

To configure an access list that controls traffic based on its EtherType, use the **access-list ethertype** command in global configuration mode. To remove the access list, use the **no** form of this command.

access-list *id* **ethertype** {**deny** | **permit**} {**ipx** | **bpdu** | **mpls-unicast** | **mpls-multicast** | **any** | *hex_number*}

no access-list *id* **ethertype** {**deny** | **permit**} {**ipx** | **bpdu** | **mpls-unicast** | **mpls-multicast** | **any** | *hex_number*}

Syntax Description

any	Specifies access to anyone.
bpdu	Specifies access to bridge protocol data units. By default, BPDUs are denied.
deny	Denies access if the conditions are matched.
<i>hex_number</i>	A 16-bit hexadecimal number greater than or equal to 0x600 by which an EtherType can be identified.
<i>id</i>	Name or number of an access list.
ipx	Specifies access to IPX.
mpls-multicast	Specifies access to MPLS multicast.
mpls-unicast	Specifies access to MPLS unicast.
permit	Permits access if the conditions are matched.

Defaults

The defaults are as follows:

- The security appliance denies all packets on the originating interface unless you specifically permit access.
- ACL logging generates syslog message 106023 for denied packets—Deny packets must be present to log denied packets.

When the **log** optional keyword is specified, the default level for syslog message 106100 is 6 (informational).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	—	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The security appliance can control any EtherType identified by a 16-bit hexadecimal number. EtherType ACLs support Ethernet V2 frames. 802.3-formatted frames are not handled by the ACL because they use a length field as opposed to a type field. Bridge protocol data units, which are handled by the ACL, are the only exception; they are SNAP-encapsulated, and the security appliance is designed to specifically handle BPDUs.

Because EtherTypes are connectionless, you need to apply the ACL to both interfaces if you want traffic to pass in both directions.

If you allow MPLS, ensure that LDP and TDP TCP connections are established through the security appliance by configuring both MPLS routers connected to the security appliance to use the IP address on the security appliance interface as the router-id for LDP or TDP sessions. (LDP and TDP allow MPLS routers to negotiate the labels (addresses) used to forward packets.)

You can apply only one ACL of each type (extended and EtherType) to each direction of an interface. You can also apply the same ACLs on multiple interfaces.

**Note**

If an EtherType access list is configured to **deny all**, all ethernet frames are discarded. Only physical protocol traffic, such as auto-negotiation, for instance, is still allowed.

Examples

The following example shows how to add an EtherType access list:

```
hostname(config)# access-list ETHER ethertype permit ipx
hostname(config)# access-list ETHER ethertype permit bpdv
hostname(config)# access-list ETHER ethertype permit mpls-unicast
hostname(config)# access-group ETHER in interface inside
```

Related Commands

Command	Description
access-group	Binds the access list to an interface.
clear access-list	Clears access list counters.
clear configure access-list	Clears an access list from the running configuration.
show access-list	Displays the access list entries by number.
show running-config access-list	Displays the current running access-list configuration.

access-list extended

To add an Access Control Entry, use the **access-list extended** command in global configuration mode. An access list is made up of one or more ACEs with the same access list ID. Access lists are used to control network access or to specify traffic for many feature to act upon. To remove the ACE, use the **no** form of this command. To remove the entire access list, use the **clear configure access-list** command.

```
access-list id [line line-number] [extended] {deny | permit}
    {protocol | object-group protocol_obj_grp_id}
    {src_ip mask | interface ifc_name | object-group network_obj_grp_id}
    [operator port | object-group service_obj_grp_id]
    {dest_ip mask | interface ifc_name | object-group network_obj_grp_id}
    [operator port | object-group service_obj_grp_id | object-group icmp_type_obj_grp_id]
    [log [[level] [interval secs] | disable | default]]
    [inactive | time-range time_range_name]

no access-list id [line line-number] [extended] {deny | permit} {tcp | udp}
    {src_ip mask | interface ifc_name | object-group network_obj_grp_id}
    [operator port] | object-group service_obj_grp_id]
    {dest_ip mask | interface ifc_name | object-group network_obj_grp_id}
    [operator port | object-group service_obj_grp_id | object-group icmp_type_obj_grp_id]
    [log [[level] [interval secs] | disable | default]]
    [inactive | time-range time_range_name]
```

Syntax Description	
default	(Optional) Sets logging to the default method, which is to send system log message 106023 for each denied packet.
deny	Denies a packet if the conditions are matched. In the case of network access (the access-group command), this keyword prevents the packet from passing through the security appliance. In the case of applying application inspection to a class map (the class-map and inspect commands), this keyword exempts the traffic from inspection. Some features do not allow deny ACEs to be used, such as NAT. See the command documentation for each feature that uses an access list for more information.
<i>dest_ip</i>	Specifies the IP address of the network or host to which the packet is being sent. Enter the host keyword before the IP address to specify a single address. In this case, do not enter a mask. Enter the any keyword instead of the address and mask to specify any address.
disable	(Optional) Disables logging for this ACE.
<i>icmp_type</i>	(Optional) If the protocol is icmp , specifies the ICMP type.
<i>id</i>	Specifies the access list ID, as a string or integer up to 241 characters in length. The ID is case-sensitive. Tip: Use all capital letters so you can see the access list ID better in your configuration.
inactive	(Optional) Disables an ACE. To reenble it, enter the entire ACE without the inactive keyword. This feature lets you keep a record of an inactive ACE in your configuration to make reenabling easier.
interface ifc_name	Specifies the interface address as the source or destination address.
interval secs	(Optional) Specifies the log interval at which to generate a 106100 system log message. Valid values are from 1 to 600 seconds. The default is 300.

<i>level</i>	(Optional) Sets the 106100 system log message level from 0 to 7. The default level is 6.
line <i>line-num</i>	(Optional) Specifies the line number at which to insert the ACE. If you do not specify a line number, the ACE is added to the end of the access list. The line number is not saved in the configuration; it only specifies where to insert the ACE.
log	(Optional) Sets logging options when a deny ACE matches a packet for network access (an access list applied with the access-group command). If you enter the log keyword without any arguments, you enable system log message 106100 at the default level (6) and for the default interval (300 seconds). If you do not enter the log keyword, then the default logging occurs, using system log message 106023.
<i>mask</i>	The subnet mask for the IP address. When you specify a network mask, the method is different from the Cisco IOS software access-list command. The security appliance uses a network mask (for example, 255.255.255.0 for a Class C mask). The Cisco IOS mask uses wildcard bits (for example, 0.0.0.255).
object-group <i>icmp_type_obj_grp_id</i>	(Optional) If the protocol is icmp , specifies the identifier of an ICMP-type object group. See the object-group icmp-type command to add an object group.
object-group <i>network_obj_grp_id</i>	Specifies the identifier of a network object group. See the object-group network command to add an object group.
object-group <i>protocol_obj_grp_id</i>	Specifies the identifier of a protocol object group. See the object-group protocol command to add an object group.
object-group <i>service_obj_grp_id</i>	(Optional) If you set the protocol to tcp or udp , specifies the identifier of a service object group. See the object-group service command to add an object group.
<i>operator</i>	(Optional) Matches the port numbers used by the source or destination. The permitted operators are as follows: • lt—less than • gt—greater than • eq—equal to • neq—not equal to • range—an inclusive range of values. When you use this operator, specify two port numbers, for example: range 100 200
permit	Permits a packet if the conditions are matched. In the case of network access (the access-group command), this keyword lets the packet pass through the security appliance. In the case of applying application inspection to a class map (the class-map and inspect commands), this keyword applies inspection to the packet.
<i>port</i>	(Optional) If you set the protocol to tcp or udp , specifies the integer or name of a TCP or UDP port. DNS, Discard, Echo, Ident, NTP, RPC, SUNRPC, and Talk each require one definition for TCP and one for UDP. TACACS+ requires one definition for port 49 on TCP.

<i>protocol</i>	Specifies the IP protocol name or number. For example, UDP is 17, TCP is 6, and EGP is 47.
<i>src_ip</i>	Specifies the IP address of the network or host from which the packet is being sent. Enter the host keyword before the IP address to specify a single address. In this case, do not enter a mask. Enter the any keyword instead of the address and mask to specify any address.
time-range <i>time_range_name</i>	(Optional) Schedules each ACE to be activated at specific times of the day and week by applying a time range to the ACE. See the time-range command for information about defining a time range.

Defaults

The defaults are as follows:

- ACE logging generates syslog message 106023 for denied packets. A deny ACE must be present to log denied packets.
- When the **log** keyword is specified, the default level for syslog message 106100 is 6 (informational) and the default interval is 300 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Each ACE that you enter for a given access list name is appended to the end of the access list unless you specify the line number in the ACE.

The order of ACEs is important. When the security appliance decides whether to forward or drop a packet, the security appliance tests the packet against each ACE in the order in which the entries are listed. After a match is found, no more ACEs are checked. For example, if you create an ACE at the beginning of an access list that explicitly permits all traffic, no further statements are ever checked.

Access lists have an implicit deny at the end of the list, so unless you explicitly permit it, traffic cannot pass. For example, if you want to allow all users to access a network through the security appliance except for particular addresses, then you need to deny the particular addresses and then permit all others.

When you use NAT, the IP addresses you specify for an access list depend on the interface to which the access list is attached; you need to use addresses that are valid on the network connected to the interface. This guideline applies for both inbound and outbound access groups: the direction does not determine the address used, only the interface does.

For TCP and UDP connections, you do not need an access list to allow returning traffic, because the FWSM allows all returning traffic for established, bidirectional connections. For connectionless protocols such as ICMP, however, the security appliance establishes unidirectional sessions, so you

either need access lists to allow ICMP in both directions (by applying access lists to the source and destination interfaces), or you need to enable the ICMP inspection engine. The ICMP inspection engine treats ICMP sessions as bidirectional connections.

Because ICMP is a connectionless protocol, you either need access lists to allow ICMP in both directions (by applying access lists to the source and destination interfaces), or you need to enable the ICMP inspection engine. The ICMP inspection engine treats ICMP sessions as stateful connections. To control ping, specify **echo-reply (0)** (security appliance to host) or **echo (8)** (host to security appliance). See [Table 1](#) for a list of ICMP types.

You can apply only one access list of each type (extended and EtherType) to each direction of an interface. You can apply the same access lists on multiple interfaces. See the **access-group** command for more information about applying an access list to an interface.

**Note**

If you change the access list configuration, and you do not want to wait for existing connections to time out before the new access list information is used, you can clear the connections using the **clear local-host** command.

[Table 1](#) lists the possible ICMP types values.

Table 2-1 *ICMP Type Literals*

ICMP Type	Literal
0	echo-reply
3	unreachable
4	source-quench
5	redirect
6	alternate-address
8	echo
9	router-advertisement
10	router-solicitation
11	time-exceeded
12	parameter-problem
13	timestamp-request
14	timestamp-reply
15	information-request
16	information-reply
17	mask-request
18	mask-reply
30	traceroute
31	conversion-error
32	mobile-redirect

Examples

The following access list allows all hosts (on the interface to which you apply the access list) to go through the security appliance:

```
hostname(config)# access-list ACL_IN extended permit ip any any
```

The following sample access list prevents hosts on 192.168.1.0/24 from accessing the 209.165.201.0/27 network. All other addresses are permitted.

```
hostname(config)# access-list ACL_IN extended deny tcp 192.168.1.0 255.255.255.0
209.165.201.0 255.255.255.224
hostname(config)# access-list ACL_IN extended permit ip any any
```

If you want to restrict access to only some hosts, then enter a limited permit ACE. By default, all other traffic is denied unless explicitly permitted.

```
hostname(config)# access-list ACL_IN extended permit ip 192.168.1.0 255.255.255.0
209.165.201.0 255.255.255.224
```

The following access list restricts all hosts (on the interface to which you apply the access list) from accessing a website at address 209.165.201.29. All other traffic is allowed.

```
hostname(config)# access-list ACL_IN extended deny tcp any host 209.165.201.29 eq www
hostname(config)# access-list ACL_IN extended permit ip any any
```

The following access list that uses object groups restricts several hosts on the inside network from accessing several web servers. All other traffic is allowed.

```
hostname(config-network)# access-list ACL_IN extended deny tcp object-group denied
object-group web eq www
hostname(config)# access-list ACL_IN extended permit ip any any
hostname(config)# access-group ACL_IN in interface inside
```

To temporarily disable an access list that permits traffic from one group of network objects (A) to another group of network objects (B):

```
hostname(config)# access-list 104 permit ip host object-group A object-group B inactive
```

To implement a time-based access list, use the **time-range** command to define specific times of the day and week. Then use the **access-list extended** command to bind the time range to an access list. The following example binds an access list named “Sales” to a time range named “New_York_Minute”:

```
hostname(config)# access-list Sales line 1 extended deny tcp host 209.165.200.225 host
209.165.201.1 time-range New_York_Minute
hostname(config)#
```

See the **time-range** command for more information about how to define a time range.

Related Commands

Command	Description
access-group	Binds the access list to an interface.
clear access-group	Clears an access list counter.
clear configure access-list	Clears an access list from the running configuration.
show access-list	Displays ACEs by number.
show running-config access-list	Displays the current running access-list configuration.

access-list remark

To specify the text of the remark to add before or after an **access-list extended** command, use the **access-list remark** command in global configuration mode. To delete the remark, use the **no** form of this command.

access-list *id* [**line** *line-num*] **remark** *text*

no access-list *id* [**line** *line-num*] **remark** [*text*]

Syntax Description

<i>id</i>	Name of an access list.
line <i>line-num</i>	(Optional) The line number at which to insert a remark or an access control element (ACE).
remark <i>text</i>	Text of the remark to add before or after an access-list extended command.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global Configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The remark text can be up to 100 characters in length, including spaces and punctuation. The remark text must contain at least 1 non-space character; you cannot enter an empty remark.

You cannot use the **access-group** command on an ACL that includes a remark only.

Examples

The following example shows how to specify the text of the remark to add before or after an **access-list** command:

```
hostname(config)# access-list 77 remark checklist
```

Related Commands	Command	Description
	access-list extended	Adds an access list to the configuration and used to configure policy for IP traffic through the security appliance.
	clear access-list	Clears an access list counter.
	clear configure access-list	Clears access lists from the running configuration.
	show access-list	Displays the access list entries by number.
	show running-config access-list	Displays the current running access-list configuration.

access-list standard

To add an access list to identify the destination IP addresses of OSPF routes, which can be used in a route map for OSPF redistribution, use the **access-list standard** command in global configuration mode. To remove the access list, use the **no** form of this command.

```
access-list id standard [line line-num] {deny | permit} {any | host ip_address | ip_address
subnet_mask}
```

```
no access-list id standard [line line-num] {deny | permit} {any | host ip_address | ip_address
subnet_mask}
```

Syntax Description

any	Specifies access to anyone.
deny	Denies access if the conditions are matched. See the “Usage Guidelines” section for the description.
host <i>ip_address</i>	Specifies access to a host IP address.
<i>id</i>	Name or number of an access list.
<i>ip_address ip_mask</i>	Specifies access to a specific IP address and subnet mask.
line <i>line-num</i>	(Optional) The line number at which to insert an ACE.
permit	Permits access if the conditions are matched. See the “Usage Guidelines” section for the description.

Defaults

The defaults are as follows:

- The security appliance denies all packets on the originating interface unless you specifically permit access.
- ACL logging generates syslog message 106023 for denied packets—Deny packets must be present to log denied packets.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

When used with the **access-group** command, the **deny** optional keyword does not allow a packet to traverse the security appliance. By default, the security appliance denies all packets on the originating interface unless you specifically permit access.

When you specify the *protocol* to match any Internet protocol, including TCP and UDP, use the **ip** keyword.

Refer to the **object-group** command for information on how to configure object groups.

You can use the **object-group** command to group access lists.

Use the following guidelines for specifying a source, local, or destination address:

- Use a 32-bit quantity in four-part, dotted-decimal format.
- Use the keyword **any** as an abbreviation for an address and mask of 0.0.0.0 0.0.0.0. We do not recommend that you use this keyword with IPSec.

Use **host address** as an abbreviation for a mask of 255.255.255.255.

Examples

The following example shows how to deny IP traffic through the firewall:

```
hostname(config)# access-list 77 standard deny
```

The following example shows how to permit IP traffic through the firewall if conditions are matched:

```
hostname(config)# access-list 77 standard permit
```

Related Commands

Command	Description
access-group	Defines object groups that you can use to optimize your configuration.
clear access-list	Clears an access list counter.
clear configure access-list	Clears access lists from the running configuration.
show access-list	Displays the access list entries by number.
show running-config access-list	Displays the current running access-list configuration.

access-list webtype

To add an access list to the configuration that supports filtering for WebVPN, use the **access-list webtype** command in global configuration mode. To remove the access list, use the **no** form of this command.

```
access-list id webtype {deny | permit} url [url_string | any] [log [[disable | default] | level] [interval secs] [time_range name]]
```

```
no access-list id webtype {deny | permit} url [url_string | any] [log [[disable | default] | level] [interval secs] [time_range name]]
```

```
access-list id webtype {deny | permit} tcp [host ip_address | ip_address subnet_mask | any] [oper port [port]] [log [[disable | default] | level] [interval secs] [time_range name]]
```

```
no access-list id webtype {deny | permit} tcp [host ip_address | ip_address subnet_mask | any] [oper port [port]] [log [[disable | default] | level] [interval secs] [time_range name]]
```

Syntax Description

any	Specifies all IP addresses.
any	(Optional) Specifies all urls.
deny	Denies access if the conditions are matched.
<i>host ip_address</i>	Specifies a host IP address.
<i>id</i>	Name or number of an access list.
interval secs	(Optional) Specifies the time interval at which to generate an 106100 syslog message; valid values are from 1 to 600 seconds.
<i>ip_address ip_mask</i>	Specifies a specific IP address and subnet mask.
log [[disable default] <i>level</i>]	(Optional) Specifies that a syslog message 106100 is generated for the ACE. See the log command for information.
<i>oper</i>	Compares <i>ip_address</i> ports. Possible operands include lt (less than), gt (greater than), eq (equal), neq (not equal), and range (inclusive range).
permit	Permits access if the conditions are matched.
<i>port</i>	Specifies the decimal number or name of a TCP or UDP port.
time_range name	(Optional) Specifies a keyword for attaching the time-range option to this access list element.
url	Specifies that a url be used for filtering.
<i>url_string</i>	(Optional) Specifies the url to be filtered.

Defaults

The defaults are as follows:

- The security appliance denies all packets on the originating interface unless you specifically permit access.
- ACL logging generates syslog message 106023 for denied packets—Deny packets must be present to log denied packets.
- When the **log** optional keyword is specified, the default level for syslog message 106100 is 6 (informational).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global Configuration	•	•	•	•	—

Command History

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines

The **access-list webtype** command is used to configure WebVPN filtering. The url specified may be full or partial (no file specified), may include wildcards for the server, or may specify a port.

Valid protocol identifiers are: http, https, cifs, imap4, pop3, and smtp. The url may also contain the keyword **any** to refer to any url. An asterisk may be used to refer to a subcomponent of a DNS name.

Examples

The following example shows how to deny access to a specific company url:

```
hostname(config)# access-list acl_company webtype deny url http://*.company.com
```

The following example shows how to deny access to a specific file:

```
hostname(config)# access-list acl_file webtype deny url
https://www.company.com/dir/file.html
```

The following example shows how to deny http access to anywhere through port 8080:

```
hostname(config)# access-list acl_company webtype deny url http://my-server:8080/*
```

Related Commands

Command	Description
access-group	Defines object groups that you can use to optimize your configuration.
access-list ethertype	Configures an access list that controls traffic based on its EtherType.
access-list extended	Adds an access list to the configuration and configures policy for IP traffic through the firewall.
clear access-group	Clears an access list counter.
show running-config access-list	Displays the access list configuration running on the security appliance.

accounting-mode

To indicate whether accounting messages are sent to a single server (single mode) or sent to all servers in the group (simultaneous mode), use the **accounting-mode** command in AAA-server group mode. To remove the accounting mode specification, use the **no** form of this command:

accounting-mode simultaneous

accounting-mode single

no accounting-mode

Syntax Description

simultaneous	Sends accounting messages to all servers in the group.
single	Sends accounting messages to a single server.

Defaults

The default value is single mode

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
AAA-server group	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the keyword **single** to send accounting messages to a single server. Use the keyword **simultaneous** to send accounting messages to all servers in the server group.

This command is meaningful only when the server group is used for accounting (RADIUS or TACACS+).

Examples

The following example shows the use of the **accounting-mode** command to send accounting messages to all servers in the group:

```
hostname(config)# aaa-server svrgrp1 protocol tacacs+
hostname(config-aaa-server-group)# accounting-mode simultaneous
hostname(config-aaa-server-group)# exit
hostname(config)#
```

Related Commands	Command	Description
	aaa accounting	Enables or disables accounting services.
	aaa-server protocol	Enters AAA server group configuration mode, so you can configure AAA server parameters that are group-specific and common to all hosts in the group.
	clear configure aaa-server	Removes all AAA server configuration.
	show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol.

accounting-port

To specify the port number used for RADIUS accounting for this host, use the **accounting-port** command in AAA-server host mode. To remove the authentication port specification, use the **no** form of this command. This command specifies the destination TCP/UDP port number of the remote RADIUS server hosts to which you want to send accounting records:

accounting-port *port*

no accounting-port

Syntax Description

port A port number, in the range 1-65535, for RADIUS accounting.

Defaults

By default, the device listens for RADIUS on port 1646 for accounting (in compliance with RFC 2058). If the port is not specified, the RADIUS accounting default port number (1646) is used.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
AAA-server host	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If your RADIUS accounting server uses a port other than 1646, you must configure the security appliance for the appropriate port prior to starting the RADIUS service with the **aaa-server** command. This command is valid only for server groups that are configured for RADIUS.

Examples

The following example configures a RADIUS AAA server named “svrgrp1” on host “1.2.3.4”, sets a timeout of 9 seconds, sets a retry-interval of 7 seconds, and configures accounting port 2222.

```
hostname(config)# aaa-server svrgrp1 protocol radius
hostname(config-aaa-server-group)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# timeout 9
hostname(config-aaa-server-host)# retry-interval 7
hostname(config-aaa-server-host)# accounting-port 2222
hostname(config-aaa-server-host)# exit
hostname(config)#
```

Related Commands	Command	Description
	aaa accounting	Keeps a record of which network services a user has accessed.
	aaa-server host	Enters AAA server host configuration mode, so you can configure AAA server parameters that are host-specific.
	clear configure aaa-server	Removes all AAA command statements from the configuration.
	show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol.

accounting-server-group

To specify the aaa-server group for sending accounting records, use the **accounting-server-group** command in tunnel-group general-attributes configuration mode. To return this command to the default, use the **no** form of this command.

accounting-server-group *server-group*

no accounting-server-group

Syntax Description

server-group Specifies the name of the aaa-server group, which defaults to **NONE**.

Defaults

The default setting for this command is **NONE**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group general attributes configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute to all tunnel-group types.

Examples

The following example entered in config-general configuration mode, configures an accounting server group named aaa-server123 for an IPSec LAN-to-LAN tunnel group xyz:

```
hostname(config)# tunnel-group xyz type IPSec_L2L
hostname(config)# tunnel-group xyz general
hostname(config-general)# accounting-server-group aaa-server123
hostname(config-general)#
```

Related Commands

Command	Description
clear configure tunnel-group	Clears all configured tunnel groups.

Command	Description
show running-config tunnel-group	Shows the tunnel group configuration for all tunnel groups or for a particular tunnel group.
tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

accounting-server-group (webvpn)

To specify the set of accounting servers to use with WebVPN or e-mail proxy, use the **accounting-server-group** command. For WebVPN, use this command in webvpn mode. For e-mail proxies (IMAP4S, POP3S, SMTPS), use this command in the applicable e-mail proxy mode. To remove accounting servers from the configuration, use the **no** form of this command.

The security appliance uses accounting to keep track of the network resources that users access.

accounting-server-group *group tag*

no accounting-server-group

Syntax Description

group tag	Identifies the previously configured accounting server or group of servers. Use the aaa-server command to configure accounting servers. Maximum length of the group tag is 16 characters.

Defaults

No accounting servers are configured by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	•	—	—	•
Imap4s	•	•	—	—	•
Pop3s	•	•	—	—	•
SMTPS	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to configure WebVPN services to use the set of accounting servers named WEBVPNACCT:

```
hostname(config)# webvpn
hostname(config-webvpn)# accounting-server-group WEBVPNACCT
```

The following example shows how to configure POP3S e-mail proxy to use the set of accounting servers named POP3SSVRS:

```
hostname(config)# pop3s
hostname(config-pop3s)# accounting-server-group POP3SSVRS
```

 accounting-server-group (webvpn)**Related Commands**

Command	Description
aaa-server host	Configures authentication, authorization, and accounting servers.

acl-netmask-convert

To specify how the security appliance treats netmasks received in a downloadable ACL from a RADIUS server, use the **acl-netmask-convert** command in AAA-server host mode, which is accessed by using the **aaa-server host** command. Use the **no** form of this command to remove the command.

acl-netmask-convert { **auto-detect** | **standard** | **wildcard** }

no acl-netmask-convert

Syntax Description

auto-detect	Specifies that the security appliance should attempt to determine the type of netmask expression used. If it detects a wildcard netmask expression, it converts it to a standard netmask expression. See “Usage Guidelines” for more information about this keyword.
standard	Specifies that the security appliance assumes downloadable ACLs received from the RADIUS server contain only standard netmask expressions. No translation from wildcard netmask expressions is performed.
wildcard	Specifies that the security appliance assumes downloadable ACLs received from the RADIUS server contain only wildcard netmask expressions and it converts them all to standard netmask expressions when the ACLs are downloaded.

Defaults

By default, no conversion from wildcard netmask expressions is performed.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
AAA-server host	•	•	•	•	—

Command History

Release	Modification
7.0(4)	This command was introduced.

Usage Guidelines

Use the **acl-netmask-convert** command with the wildcard or auto-detect keywords when a RADIUS server provides downloadable ACLs that contain netmasks in wildcard format. The security appliance expects downloadable ACLs to contain standard netmask expressions whereas Cisco Secure VPN 3000 Series Concentrators expect downloadable ACLs to contain wildcard netmask expressions, which are the reverse of a standard netmask expression. A wildcard mask has ones in bit positions to ignore, zeros in bit positions to match. The **acl-netmask-convert** command helps minimize the effects of these differences upon how you configure downloadable ACLs on your RADIUS servers.

The **auto-detect** keyword is helpful when you are uncertain how the RADIUS server is configured; however, wildcard netmask expressions with “holes” in them cannot be unambiguously detected and converted. For example, the wildcard netmask 0.0.255.0 permits anything in the third octet and can be used validly on Cisco VPN 3000 Series Concentrators, but the security appliance may not detect this expression as a wildcard netmask.

Examples

The following example configures a RADIUS AAA server named “svrgrp1” on host “192.168.3.4”, enables conversion of downloadable ACL netmasks, sets a timeout of 9 seconds, sets a retry-interval of 7 seconds, and configures authentication port 1650.

```
hostname(config)# aaa-server svrgrp1 protocol radius
hostname(config-aaa-server-group)# aaa-server svrgrp1 host 192.168.3.4
hostname(config-aaa-server-host)# acl-netmask-convert wildcard
hostname(config-aaa-server-host)# timeout 9
hostname(config-aaa-server-host)# retry-interval 7
hostname(config-aaa-server-host)# authentication-port 1650
hostname(config-aaa-server-host)# exit
hostname(config)#
```

Related Commands

Command	Description
aaa authentication	Enables or disables LOCAL, TACACS+, or RADIUS user authentication, on a server designated by the aaa-server command, or ASDM user authentication.
aaa-server host	Enters AAA server host configuration mode, so you can configure AAA server parameters that are host-specific.
clear configure aaa-server	Removes all AAA command statements from the configuration.
show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol

activation-key

To change the activation key on the security appliance and check the activation key running on the security appliance against the activation key that is stored as a hidden file in the Flash partition of the security appliance, use the **activation-key** command in global configuration mode.

activation-key [*activation-key-four-tuple*| *activation-key-five-tuple*]

Syntax Description

<i>activation-key-four-tuple</i>	Activation key; see the “Usage Guidelines” section for formatting guidelines.
<i>activation-key-five-tuple</i>	Activation key; see the “Usage Guidelines” section for formatting guidelines.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•		•

Command History

Release	Modification
7.0	Support for this command was introduced on the security appliance.

Usage Guidelines

Enter the *activation-key-four-tuple* as a four-element hexadecimal string with one space between each element, or *activation-key-five-tuple* as a five-element hexadecimal string with the one space between each element as follows:

```
0xe02888da 0x4ba7bed6 0xf1c123ae 0xffd8624e
```

The leading 0x specifier is optional; all values are assumed to be hexadecimal.

The key is not stored in the configuration file. The key is tied to the serial number.

Examples

This example shows how to change the activation key on the security appliance:

```
hostname(config)# activation-key 0xe02888da 0x4ba7bed6 0xf1c123ae 0xffd8624e
```

Related Commands

Command	Description
show activation-key	Displays the activation key.

address-pool

To specify a list of address pools for allocating addresses to remote clients, use the **address-pool** command in tunnel-group general-attributes configuration mode. To eliminate address pools, use the **no** form of this command.

address-pool [(*interface name*)] *address_pool1* [...*address_pool6*]

no address-pool [(*interface name*)] *address_pool1* [...*address_pool6*]

Syntax Description

<i>address_pool</i>	Specifies the name of the address pool configured with the ip local pool command. You can specify up to 6 local address pools.
<i>interface name</i>	(Optional) Specifies the interface to be used for the address pool.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group general attributes configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can enter multiples of each of these commands, one per interface. If an interface is not specified, then the command specifies the default for all interfaces that are not explicitly referenced.

Examples

The following example entered in config-general configuration mode, specifies a list of address pools for allocating addresses to remote clients for an IPSec remote-access tunnel group xyz:

```
hostname(config)# tunnel-group xyz
hostname(config)# tunnel-group xyz general
hostname(config-general)# address-pool (inside) addrpool1 addrpool2 addrpool3
hostname(config-general)#
```

Related Commands	Command	Description
	ip local pool	Configures IP address pools to be used for VPN remote-access tunnels.
	clear configure tunnel-group	Clears all configured tunnel groups.
	show running-config tunnel-group	Shows the tunnel group configuration for all tunnel groups or for a particular tunnel group.
	tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

admin-context

To set the admin context for the system configuration, use the **admin-context** command in global configuration mode. The system configuration does not include any network interfaces or network settings for itself; rather, when the system needs to access network resources (such as downloading the security appliance software or allowing remote management for an administrator), it uses one of the contexts that is designated as the admin context.

admin-context *name*

Syntax Description

name

Sets the name as a string up to 32 characters long. If you have not defined any contexts yet, then first specify the admin context name with this command. Then, the first context you add using the **context** command must be the specified admin context name.

This name is case sensitive, so you can have two contexts named “customerA” and “CustomerA,” for example. You can use letters, digits, or hyphens, but you cannot start or end the name with a hyphen.

“System” or “Null” (in upper or lower case letters) are reserved names, and cannot be used.

Defaults

For a new security appliance in multiple context mode, the admin context is called “admin.”

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can set any context to be the admin context, as long as the context configuration resides on the internal Flash memory.

You cannot remove the current admin context, unless you remove all contexts using the **clear configure context** command.

Examples

The following example sets the admin context to be “administrator”:

```
hostname(config)# admin-context administrator
```

Related Commands

Command	Description
clear configure context	Removes all contexts from the system configuration.
context	Configures a context in the system configuration and enters context configuration mode.
show admin-context	shows the current admin context name.

alias

To manually translate an address and perform DNS reply modification, use the **alias** command in global configuration mode. To remove an **alias** command, use the **no** form of this command. This command functionality has been replaced by outside NAT commands, including the **nat** and **static** commands with the **dns** keyword. We recommend that you use outside NAT instead of the **alias** command.

alias *interface_name* *mapped_ip* *real_ip* [*netmask*]

[**no**] **alias** *interface_name* *mapped_ip* *real_ip* [*netmask*]

Syntax Description

<i>interface_name</i>	Specifies the ingress interface name for traffic destined for the mapped IP address (or the egress interface name for traffic from the mapped IP address).
<i>mapped_ip</i>	Specifies the IP address to which you want to translate the real IP address.
<i>real_ip</i>	Specifies the real IP address.
<i>netmask</i>	(Optional) Specifies the subnet mask for both IP addresses. Enter 255.255.255.255 for a host mask.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
1.1(1)	This command was introduced.

Usage Guidelines

You can also use this command to perform address translation on a destination address. For example, if a host sends a packet to 209.165.201.1, you can use the **alias** command to redirect traffic to another address, such as 209.165.201.30.



Note

If the **alias** command is used for DNS rewrite and not for other address translation, disable **proxy-arp** on the alias-enabled interface. Use the **sysopt noproxyarp** command to prevent the security appliance from pulling traffic toward itself via **proxy-arp** for generic NAT processing.

After changing or removing an **alias** command, use the **clear xlate** command.

You must have an A (address) record in the DNS zone file for the “dnat” address in the **alias** command.

The **alias** command has two uses that can be summarized in the following ways:

- If the security appliance gets a packet that is destined for the *mapped_ip*, you can configure the **alias** command to send it to the *real_ip*.
- If the security appliance gets a DNS packet that is returned to the security appliance destined for *real_ip*, you can configure the **alias** command to alter the DNS packet to change the destination network address to *mapped_ip*.

The **alias** command automatically interacts with the DNS servers on your network to ensure that domain name access to the aliased IP address is handled transparently.

You can specify a net alias by using network addresses for the *real_ip* and *mapped_ip* IP addresses. For example, the **alias 192.168.201.0 209.165.201.0 255.255.255.224** command creates aliases for each IP address between 209.165.201.1 and 209.165.201.30.

To access an **alias mapped_ip** address with **static** and **access-list** commands, specify the *mapped_ip* address in the **access-list** command as the address from which traffic is permitted as follows:

```
hostname(config)# alias (inside) 192.168.201.1 209.165.201.1 255.255.255.255
hostname(config)# static (inside,outside) 209.165.201.1 192.168.201.1 netmask
255.255.255.255
hostname(config)# access-list acl_out permit tcp host 192.168.201.1 host 209.165.201.1 eq
ftp-data
hostname(config)# access-group acl_out in interface outside
```

An alias is specified with the inside address 192.168.201.1 mapping to the destination address 209.165.201.1.

When the inside network client 209.165.201.2 connects to example.com, the DNS response from an external DNS server to the internal client's query would be altered by the security appliance to be 192.168.201.29. If the security appliance uses 209.165.200.225 through 209.165.200.254 as the global pool IP addresses, the packet goes to the security appliance with SRC=209.165.201.2 and DST=192.168.201.29. The security appliance translates the address to SRC=209.165.200.254 and DST=209.165.201.29 on the outside.

Examples

This example shows that the inside network contains the IP address 209.165.201.29, which on the Internet belongs to example.com. When inside clients try to access example.com, the packets do not go to the security appliance because the client assumes that the 209.165.201.29 is on the local inside network.

To correct this, use the **alias** command as follows:

```
hostname(config)# alias (inside) 192.168.201.0 209.165.201.0 255.255.255.224

hostname(config)# show running-config alias
alias 192.168.201.0 209.165.201.0 255.255.255.224
```

This example shows a web server that is on the inside at 10.1.1.11 and the **static** command that was created at 209.165.201.11. The source host is on the outside with address 209.165.201.7. A DNS server on the outside has a record for www.example.com as follows:

```
dns-server# www.example.com. IN A 209.165.201.11
```

You must include the period at the end of the www.example.com. domain name.

This example shows how to use the **alias** command:

```
hostname(config)# alias 10.1.1.11 209.165.201.11 255.255.255.255
```

The security appliance changes the name server replies to 10.1.1.11 for inside clients to directly connect to the web server.

To provide access you also need the following commands:

```
hostname(config)# static (inside,outside) 209.165.201.11 10.1.1.11

hostname(config)# access-list acl_grp permit tcp host 209.165.201.7 host 209.165.201.11 eq
telnet
hostname(config)# access-list acl_grp permit tcp host 209.165.201.11 eq telnet host
209.165.201.7
```

Related Commands

Command	Description
access-list extended	Creates an access list.
clear configure alias	Removes all alias commands from the configuration.
show running-config alias	Displays the overlapping addresses with dual NAT commands in the configuration.
static	Configures a one-to-one address translation rule by mapping a local IP address to a global IP address, or a local port to a global port.

allocate-interface

To allocate interfaces to a security context, use the **allocate-interface** command in context configuration mode. To remove an interface from a context, use the **no** form of this command.

allocate-interface *physical_interface* [*map_name*] [**visible** | **invisible**]

no allocate-interface *physical_interface*

allocate-interface *physical_interface.subinterface* [*-physical_interface.subinterface*]
[*map_name[-map_name]*] [**visible** | **invisible**]

no allocate-interface *physical_interface.subinterface* [*-physical_interface.subinterface*]

Syntax Description		
invisible		(Default) Allows context users to only see the mapped name (if configured) in the show interface command.
<i>map_name</i>		(Optional) Sets a mapped name. The <i>map_name</i> is an alphanumeric alias for the interface that can be used within the context instead of the interface ID. If you do not specify a mapped name, the interface ID is used within the context. For security purposes, you might not want the context administrator to know which interfaces are being used by the context. A mapped name must start with a letter, end with a letter or digit, and have as interior characters only letters, digits, or an underscore. For example, you can use the following names: <pre>int0 inta int_0</pre> For subinterfaces, you can specify a range of mapped names. See the “Usage Guidelines” section for more information about ranges.
<i>physical_interface</i>		Sets the interface ID, such as gigabitethernet0/1 . See the interface command for accepted values.
<i>subinterface</i>		Sets the subinterface number. You can identify a range of subinterfaces.
visible		(Optional) Allows context users to see physical interface properties in the show interface command even if you set a mapped name.

Defaults

The interface ID is invisible in the **show interface** command output by default if you set a mapped name.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Context configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can enter this command multiple times to specify different ranges. To change the mapped name or visible setting, reenter the command for a given interface ID, and set the new values; you do not need to enter the **no allocate-interface** command and start over. If you remove the **allocate-interface** command, the security appliance removes any interface-related configuration in the context.

Transparent firewall mode allows only two interfaces to pass through traffic; however, on the ASA adaptive security appliance, you can use the dedicated management interface, Management 0/0, (either the physical interface or a subinterface) as a third interface for management traffic.

**Note**

The management interface for transparent mode does not flood a packet out the interface when that packet is not in the MAC address table.

You can assign the same interfaces to multiple contexts in routed mode, if desired. Transparent mode does not allow shared interfaces.

If you specify a range of subinterfaces, you can specify a matching range of mapped names. Follow these guidelines for ranges:

- The mapped name must consist of an alphabetic portion followed by a numeric portion. The alphabetic portion of the mapped name must match for both ends of the range. For example, enter the following range:

```
int0-int10
```

If you enter **gigabitethernet0/1.1-gigabitethernet0/1.5 happy1-sad5**, for example, the command fails.

- The numeric portion of the mapped name must include the same quantity of numbers as the subinterface range. For example, both ranges include 100 interfaces:

```
gigabitethernet0/0.100-gigabitethernet0/0.199 int1-int100
```

If you enter **gigabitethernet0/0.100-gigabitethernet0/0.199 int1-int15**, for example, the command fails.

Examples

The following example shows gigabitethernet0/1.100, gigabitethernet0/1.200, and gigabitethernet0/2.300 through gigabitethernet0/1.305 assigned to the context. The mapped names are int1 through int8.

```
hostname(config-ctx)# allocate-interface gigabitethernet0/1.100 int1
```

```
hostname(config-ctx) # allocate-interface gigabitethernet0/1.200 int2  
hostname(config-ctx) # allocate-interface gigabitethernet0/2.300-gigabitethernet0/2.305  
int3-int8
```

Related Commands

Command	Description
context	Creates a security context in the system configuration and enters context configuration mode.
interface	Configures an interface and enters interface configuration mode.
show context	Shows a list of contexts (system execution space) or information about the current context.
show interface	Displays the runtime status and statistics of interfaces.
vlan	Assigns a VLAN ID to a subinterface.

area

To create an OSPF area, use the **area** command in router configuration mode. To remove the area, use the **no** form of this command.

area *area_id*

no area *area_id*

Syntax Description

area_id The ID of the area being created. You can specify the identifier as either a decimal number or an IP address. Valid decimal values range from 0 to 4294967295.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The area that you create does not have any parameters set. Use the related area commands to set the area parameters.

Examples

The following example shows how to create an OSPF area with an area ID of 1:

```
hostname(config-router)# area 1
hostname(config-router)#
```

Related Commands

Command	Description
area authentication	Enables authentication for the OSPF area.
area nssa	Defines the area as a not-so-stubby area.
area stub	Defines the area as a stub area.

Command	Description
router ospf	Enters router configuration mode.
show running-config router	Displays the commands in the global router configuration.

area authentication

To enable authentication for an OSPF area, use the **area authentication** command in router configuration mode. To disable area authentication, use the **no** form of this command.

area *area_id* **authentication** [**message-digest**]

no area *area_id* **authentication** [**message-digest**]

Syntax Description

<i>area_id</i>	The identifier of the area on which authentication is to be enabled. You can specify the identifier as either a decimal number or an IP address. Valid decimal values range from 0 to 4294967295.
message-digest	(Optional) Enables Message Digest 5 (MD5) authentication on the area specified by the <i>area_id</i> .

Defaults

Area authentication is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If the specified OSPF area does not exist, it is created when this command is entered. Entering the **area authentication** command without the **message-digest** keyword enables simple password authentication. Including the **message-digest** keyword enables MD5 authentication.

Examples

The following example shows how to enable MD5 authentication for area 1:

```
hostname(config-router)# area 1 authentication message-digest
hostname(config-router)#
```

Related Commands	Command	Description
	router ospf	Enters router configuration mode.
	show running-config router	Displays the commands in the global router configuration.

area default-cost

To specify a cost for the default summary route sent into a stub or NSSA, use the **area default-cost** command in router configuration mode. To restore the default cost value, use the **no** form of this command.

area *area_id* **default-cost** *cost*

no area *area_id* **default-cost**

Syntax Description

<i>area_id</i>	The identifier of the stub or NSSA whose default cost is being changed. You can specify the identifier as either a decimal number or an IP address. Valid decimal values range from 0 to 4294967295.
<i>cost</i>	Specifies the cost for the default summary route that is used for a stub or NSSA. Valid values range from 0 to 65535

Defaults

The default value of *cost* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If the specified area has not been previously defined using the **area** command, this command creates the area with the specified parameters.

Examples

The following example show how to specify a default cost for summary route sent into a stub or NSSA:

```
hostname(config-router)# area 1 default-cost 5
hostname(config-router)#
```

Related Commands

Command	Description
area nssa	Defines the area as a not-so-stubby area.
area stub	Defines the area as a stub area.

Command	Description
router ospf	Enters router configuration mode.
show running-config router	Displays the commands in the global router configuration.

area filter-list prefix

To filter prefixes advertised in type 3 LSAs between OSPF areas of an ABR, use the **area filter-list prefix** command in router configuration mode. To change or cancel the filter, use the **no** form of this command.

area *area_id* **filter-list prefix** *list_name* {**in** | **out**}

no area *area_id* **filter-list prefix** *list_name* {**in** | **out**}

Syntax Description

<i>area_id</i>	Identifier of the area for which filtering is configured. You can specify the identifier as either a decimal number or an IP address. Valid decimal values range from 0 to 4294967295.
in	Applies the configured prefix list to prefixes advertised inbound to the specified area.
<i>list_name</i>	Specifies the name of a prefix list.
out	Applies the configured prefix list to prefixes advertised outbound from the specified area.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If the specified area has not been previously defined using the **area** command, this command creates the area with the specified parameters.

Only type 3 LSAs can be filtered. If an ASBR is configured in the private network, then it will send type 5 LSAs (describing private networks) which are flooded to the entire AS including the public areas.

Examples

The following example filters prefixes that are sent from all other areas to area 1:

```
hostname(config-router)# area 1 filter-list prefix-list AREA_1 in
hostname(config-router)#
```

Related Commands	Command	Description
	router ospf	Enters router configuration mode.
	show running-config router	Displays the commands in the global router configuration.

area nssa

To configure an area as an NSSA, use the **area nssa** command in router configuration mode. To remove the NSSA designation from the area, use the **no** form of this command.

```
area area_id nssa [no-redistribution] [default-information-originate [metric-type {1 | 2}]
[metric value]] [no-summary]
```

```
no area area_id nssa [no-redistribution] [default-information-originate [metric-type {1 | 2}]
[metric value]] [no-summary]
```

Syntax Description

<i>area_id</i>	Identifier of the area being designated as an NSSA. You can specify the identifier as either a decimal number or an IP address. Valid decimal values range from 0 to 4294967295.
default-information-originate	Used to generate a Type 7 default into the NSSA area. This keyword only takes effect on an NSSA ABR or an NSSA ASBR.
metric <i>metric_value</i>	(Optional) Specifies the OSPF default metric value. Valid values range from 0 to 16777214.
metric-type { 1 2 }	(Optional) the OSPF metric type for default routes. Valid values are the following: 1—type 1 2—type 2. The default value is 2.
no-redistribution	(Optional) Used when the router is an NSSA ABR and you want the redistribute command to import routes only into the normal areas, but not into the NSSA area.
no-summary	(Optional) Allows an area to be a not-so-stubby area but not have summary routes injected into it.

Defaults

The defaults are as follows:

- No NSSA area is defined.
- The **metric-type** is 2.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If the specified area has not been previously defined using the **area** command, this command creates the area with the specified parameters.

If you configure one option for an area, and later specify another option, both options are set. For example, entering the following two command separately results in a single command with both options set in the configuration:

```
area 1 nssa no-redistribution
area area_id nssa default-information-originate
```

Examples

The following example shows how setting two options separately results in a single command in the configuration:

```
hostname(config-router)# area 1 nssa no-redistribution
hostname(config-router)# area 1 nssa default-information-originate
hostname(config-router)# exit
hostname(config-router)# show running-config router ospf 1
router ospf 1
  area 1 nssa no-redistribution default-information-originate
```

Related Commands

Command	Description
area stub	Defines the area as a stub area.
router ospf	Enters router configuration mode.
show running-config router	Displays the commands in the global router configuration.

area range

To consolidate and summarize routes at an area boundary, use the **area range** command in router configuration mode. To disable this function, use the **no** form of this command.

area *area_id* **range** *address mask* [**advertise** | **not-advertise**]

no area *area_id* **range** *address mask* [**advertise** | **not-advertise**]

Syntax Description

<i>address</i>	IP address of the subnet range.
advertise	(Optional) Sets the address range status to advertise and generates type 3 summary link-state advertisements (LSAs).
<i>area_id</i>	Identifier of the area for which the range is configured. You can specify the identifier as either a decimal number or an IP address. Valid decimal values range from 0 to 4294967295.
<i>mask</i>	IP address subnet mask.
not-advertise	(Optional) Sets the address range status to DoNotAdvertise. The type 3 summary LSA is suppressed, and the component networks remain hidden from other networks.

Defaults

The address range status is set to advertise.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If the specified area has not been previously defined using the **area** command, this command creates the area with the specified parameters.

The **area range** command is used only with ABRs. It is used to consolidate or summarize routes for an area. The result is that a single summary route is advertised to other areas by the ABR. Routing information is condensed at area boundaries. External to the area, a single route is advertised for each address range. This behavior is called *route summarization*. You can configure multiple **area range** commands for an area. Thus, OSPF can summarize addresses for many different sets of address ranges.

The **no area area_id range ip_address netmask not-advertise** command removes only the **not-advertise** optional keyword.

Examples

The following example specifies one summary route to be advertised by the ABR to other areas for all subnets on network 10.0.0.0 and for all hosts on network 192.168.110.0:

```
hostname(config-router)# area 10.0.0.0 range 10.0.0.0 255.0.0.0  
hostname(config-router)# area 0 range 192.168.110.0 255.255.255.0  
hostname(config-router)#
```

Related Commands

Command	Description
router ospf	Enters router configuration mode.
show running-config router	Displays the commands in the global router configuration.

area stub

To define an area as a stub area, use the **area stub** command in router configuration mode. To remove the stub area function, use the **no** form of this command.

area *area_id* [**no-summary**]

no area *area_id* [**no-summary**]

Syntax Description

<i>area_id</i>	Identifier for the stub area. You can specify the identifier as either a decimal number or an IP address. Valid decimal values range from 0 to 4294967295.
no-summary	Prevents an ABR from sending summary link advertisements into the stub area.

Defaults

The default behaviors are as follows:

- No stub areas are defined.
- Summary link advertisements are sent into the stub area.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The command is used only on an ABR attached to a stub or NSSA.

There are two stub area router configuration commands: the **area stub** and **area default-cost** commands. In all routers and access servers attached to the stub area, the area should be configured as a stub area using the **area stub** command. Use the **area default-cost** command only on an ABR attached to the stub area. The **area default-cost** command provides the metric for the summary default route generated by the ABR into the stub area.

Examples

The following example configures the specified area as a stub area:

```
hostname(config-router)# area 1 stub
hostname(config-router)#
```


Related Commands

Command	Description
area default-cost	Specifies a cost for the default summary route sent into a stub or NSSA
area nssa	Defines the area as a not-so-stubby area.
router ospf	Enters router configuration mode.
show running-config router	Displays the commands in the global router configuration.

area virtual-link

To define an OSPF virtual link, use the **area virtual-link** command in router configuration mode. To reset the options or remove the virtual link, use the **no** form of this command.

```
area area_id virtual-link router_id [authentication [message-digest | null]] [hello-interval
seconds] [retransmit-interval seconds] [transmit-delay seconds] [dead-interval seconds
[[authentication-key key] | [message-digest-key key_id md5 key]]
```

```
no area area_id virtual-link router_id [authentication [message-digest | null]] [hello-interval
seconds] [retransmit-interval seconds] [transmit-delay seconds] [dead-interval seconds
[[authentication-key key] | [message-digest-key key_id md5 key]]
```

Syntax Description

<i>area_id</i>	Area ID of the transit area for the virtual link. You can specify the identifier as either a decimal number or an IP address. Valid decimal values range from 0 to 4294967295.
authentication	(Optional) Specifies the authentication type.
authentication-key <i>key</i>	(Optional) Specifies an OSPF authentication password for use by neighboring routing devices.
dead-interval <i>seconds</i>	(Optional) Specifies the interval before declaring a neighboring routing device is down if no hello packets are received; valid values are from 1 to 65535 seconds.
hello-interval <i>seconds</i>	(Optional) Specifies the interval between hello packets sent on the interface; valid values are from 1 to 65535 seconds.
md5 <i>key</i>	(Optional) Specifies an alphanumeric key up to 16 bytes.
message-digest	(Optional) Specifies that message digest authentication is used.
message-digest-key <i>key_id</i>	(Optional) Enables the Message Digest 5 (MD5) authentication and specifies the numerical authentication key ID number; valid values are from 1 to 255.
null	(Optional) Specifies that no authentication is used. Overrides password or message digest authentication if configured for the OSPF area.
retransmit-interval <i>seconds</i>	(Optional) Specifies the time between LSA retransmissions for adjacent routers belonging to the interface; valid values are from 1 to 65535 seconds.
<i>router_id</i>	The router ID associated with the virtual link neighbor. The router ID is internally derived by each router from the interface IP addresses. This value must be entered in the format of an IP address. There is no default.
transmit-delay <i>seconds</i>	(Optional) Specifies the delay time between when OSPF receives a topology change and when it starts a shortest path first (SPF) calculation in seconds from 0 to 65535. The default is 5 seconds.

Defaults

The defaults are as follows:

- *area_id*: No area ID is predefined.
- *router_id*: No router ID is predefined.
- **hello-interval** *seconds*: 10 seconds.
- **retransmit-interval** *seconds*: 5 seconds.

- **transmit-delay** *seconds*: 1 second.
- **dead-interval** *seconds*: 40 seconds.
- **authentication-key** *key*: No key is predefined.
- **message-digest-key** *key_id md5 key*: No key is predefined.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

In OSPF, all areas must be connected to a backbone area. If the connection to the backbone is lost, it can be repaired by establishing a virtual link.

The smaller the hello interval, the faster topological changes are detected, but more routing traffic ensues.

The setting of the retransmit interval should be conservative, or needless retransmissions occur. The value should be larger for serial lines and virtual links.

The transmit delay value should take into account the transmission and propagation delays for the interface.

The specified authentication key is used only when authentication is enabled for the backbone with the **area area_id authentication** command.

The two authentication schemes, simple text and MD5 authentication, are mutually exclusive. You can specify one or the other or neither. Any keywords and arguments you specify after **authentication-key key** or **message-digest-key key_id md5 key** are ignored. Therefore, specify any optional arguments before such a keyword-argument combination.

If the authentication type is not specified for an interface, the interface uses the authentication type specified for the area. If no authentication type has been specified for the area, the area default is null authentication.



Note

Each virtual link neighbor must include the transit area ID and the corresponding virtual link neighbor router ID for a virtual link to be properly configured. Use the **show ospf** command to see the router ID.

To remove an option from a virtual link, use the **no** form of the command with the option that you want removed. To remove the virtual link, use the **no area area_id virtual-link** command.

Examples

The following example establishes a virtual link with MD5 authentication:

```
hostname(config-router)# area 10.0.0.0 virtual-link 10.3.4.5 message-digest-key 3 md5  
sa5721bk47
```

Related Commands

Command	Description
area authentication	Enables authentication for an OSPF area.
router ospf	Enters router configuration mode.
show ospf	Displays general information about the OSPF routing processes.
show running-config router	Displays the commands in the global router configuration.

arp

To add a static ARP entry to the ARP table, use the **arp** command in global configuration mode. To remove the static entry, use the **no** form of this command. A static ARP entry maps a MAC address to an IP address and identifies the interface through which the host is reached. Static ARP entries do not time out, and might help you solve a networking problem. In transparent firewall mode, the static ARP table is used with ARP inspection (see the **arp-inspection** command).

arp *interface_name* *ip_address* *mac_address* [*alias*]

no arp *interface_name* *ip_address* *mac_address*

Syntax Description

alias	(Optional) Enables proxy ARP for this mapping. If the security appliance receives an ARP request for the specified IP address, then it responds with the security appliance MAC address. When the security appliance receives traffic destined for the host belonging to the IP address, the security appliance forwards the traffic to the host MAC address that you specify in this command. This keyword is useful if you have devices that do not perform ARP, for example. In transparent firewall mode, this keyword is ignored; the security appliance does not perform proxy ARP.
<i>interface_name</i>	The interface attached to the host network.
<i>ip_address</i>	The host IP address.
<i>mac_address</i>	The host MAC address.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Although hosts identify a packet destination by an IP address, the actual delivery of the packet on Ethernet relies on the Ethernet MAC address. When a router or host wants to deliver a packet on a directly connected network, it sends an ARP request asking for the MAC address associated with the IP address, and then delivers the packet to the MAC address according to the ARP response. The host or router keeps an ARP table so it does not have to send ARP requests for every packet it needs to deliver.

The ARP table is dynamically updated whenever ARP responses are sent on the network, and if an entry is not used for a period of time, it times out. If an entry is incorrect (for example, the MAC address changes for a given IP address), the entry times out before it can be updated.

**Note**

In transparent firewall mode, dynamic ARP entries are used for traffic to and from the security appliance, such as management traffic.

Examples

The following example creates a static ARP entry for 10.1.1.1 with the MAC address 0009.7cbe.2100 on the outside interface:

```
hostname(config)# arp outside 10.1.1.1 0009.7cbe.2100
```

Related Commands

Command	Description
arp timeout	Sets the time before the security appliance rebuilds the ARP table.
arp-inspection	For transparent firewall mode, inspects ARP packets to prevent ARP spoofing.
show arp	Shows the ARP table.
show arp statistics	Shows ARP statistics.
show running-config arp	Shows the current configuration of the ARP timeout.

arp timeout

To set the time before the security appliance rebuilds the ARP table, use the **arp timeout** command in global configuration mode. To restore the default timeout, use the **no** form of this command. Rebuilding the ARP table automatically updates new host information and removes old host information. You might want to reduce the timeout because the host information changes frequently.

arp timeout *seconds*

no arp timeout *seconds*

Syntax Description	<i>seconds</i>	The number of seconds between ARP table rebuilds, from 60 to 4294967.

Defaults	The default value is 14,400 seconds (4 hours).

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Examples	The following example changes the ARP timeout to 5,000 seconds: hostname(config)# arp timeout 5000

Related Commands	Command	Description
	arp	Adds a static ARP entry.
	arp-inspection	For transparent firewall mode, inspects ARP packets to prevent ARP spoofing.
	show arp statistics	Shows ARP statistics.
	show running-config arp timeout	Shows the current configuration of the ARP timeout.

arp-inspection

To enable ARP inspection for transparent firewall mode, use the **arp-inspection** command in global configuration mode. To disable ARP inspection, use the **no** form of this command. ARP inspection checks all ARP packets against static ARP entries (see the **arp** command) and blocks mismatched packets. This feature prevents ARP spoofing.

arp-inspection *interface_name* **enable** [**flood** | **no-flood**]

no arp-inspection *interface_name* **enable**

Syntax Description

enable	Enables ARP inspection.
flood	(Default) Specifies that packets that do not match any element of a static ARP entry are flooded out all interfaces except the originating interface. If there is a mismatch between the MAC address, the IP address, or the interface, then the security appliance drops the packet. Note The management-specific interface, if present, never floods packets even if this parameter is set to flood.
<i>interface_name</i>	The interface on which you want to enable ARP inspection.
no-flood	(Optional) Specifies that packets that do not exactly match a static ARP entry are dropped.

Defaults

By default, ARP inspection is disabled on all interfaces; all ARP packets are allowed through the security appliance. When you enable ARP inspection, the default is to flood non-matching ARP packets.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	—	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Configure static ARP entries using the **arp** command before you enable ARP inspection.

When you enable ARP inspection, the security appliance compares the MAC address, IP address, and source interface in all ARP packets to static entries in the ARP table, and takes the following actions:

- If the IP address, MAC address, and source interface match an ARP entry, the packet is passed through.

- If there is a mismatch between the MAC address, the IP address, or the interface, then the security appliance drops the packet.
- If the ARP packet does not match any entries in the static ARP table, then you can set the security appliance to either forward the packet out all interfaces (flood), or to drop the packet.



Note The dedicated management interface, if present, never floods packets even if this parameter is set to flood.

ARP inspection prevents malicious users from impersonating other hosts or routers (known as ARP spoofing). ARP spoofing can enable a “man-in-the-middle” attack. For example, a host sends an ARP request to the gateway router; the gateway router responds with the gateway router MAC address. The attacker, however, sends another ARP response to the host with the attacker MAC address instead of the router MAC address. The attacker can now intercept all the host traffic before forwarding it on to the router.

ARP inspection ensures that an attacker cannot send an ARP response with the attacker MAC address, so long as the correct MAC address and the associated IP address are in the static ARP table.



Note In transparent firewall mode, dynamic ARP entries are used for traffic to and from the security appliance, such as management traffic.

Examples

The following example enables ARP inspection on the outside interface and sets the security appliance to drop any ARP packets that do not match the static ARP entry:

```
hostname(config)# arp outside 209.165.200.225 0009.7cbe.2100
hostname(config)# arp-inspection outside enable no-flood
```

Related Commands

Command	Description
arp	Adds a static ARP entry.
clear configure arp-inspection	Clears the ARP inspection configuration.
firewall transparent	Sets the firewall mode to transparent.
show arp statistics	Shows ARP statistics.
show running-config arp	Shows the current configuration of the ARP timeout.

asdm disconnect

To terminate an active ASDM session, use the **asdm disconnect** command in privileged EXEC mode.

asdm disconnect *session*

Syntax Description	<i>session</i>	The session ID of the active ASDM session to be terminated. You can display the session IDs of all active ASDM sessions using the show asdm sessions command.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was changed from the pdm disconnect command to the asdm disconnect command.

Usage Guidelines	Use the show asdm sessions command to display a list of active ASDM sessions and their associated session IDs. Use the asdm disconnect command to terminate a specific session. When you terminate an ASDM session, any remaining active ASDM sessions keep their associated session ID. For example, if there are three active ASDM sessions with the session IDs of 0, 1, and 2, and you terminate session 1, the remaining active ASDM sessions keep the session IDs 0 and 2. The next new ASDM session in this example would be assigned a session ID of 1, and any new sessions after that would begin with the session ID 3.

Examples	The following example terminates an ASDM session with a session ID of 0. The show asdm sessions commands display the active ASDM sessions before and after the asdm disconnect command is entered.

```
hostname# show asdm sessions

0 192.168.1.1
1 192.168.1.2
hostname# asdm disconnect 0
hostname# show asdm sessions

1 192.168.1.2
```

Related Commands

Command	Description
<code>show asdm sessions</code>	Displays a list of active ASDM sessions and their associated session ID.

asdm disconnect log_session

To terminate an active ASDM logging session, use the **asdm disconnect log_session** command in privileged EXEC mode.

asdm disconnect log_session *session*

Syntax Description

session The session ID of the active ASDM logging session to be terminated. You can display the session IDs of all active ASDM sessions using the **show asdm log_sessions** command.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **show asdm log_sessions** command to display a list of active ASDM logging sessions and their associated session IDs. Use the **asdm disconnect log_session** command to terminate a specific logging session.

Each active ASDM session has one or more associated ASDM logging sessions. ASDM uses the logging session to retrieve syslog messages from the security appliance. Terminating a log session may have an adverse effect on the active ASDM session. To terminate an unwanted ASDM session, use the **asdm disconnect** command.



Note

Because each ASDM session has at least one ASDM logging session, the output for the **show asdm sessions** and **show asdm log_sessions** may appear to be the same.

When you terminate an ASDM logging session, any remaining active ASDM logging sessions keep their associated session ID. For example, if there are three active ASDM logging sessions with the session IDs of 0, 1, and 2, and you terminate session 1, the remaining active ASDM logging sessions keep the session IDs 0 and 2. The next new ASDM logging session in this example would be assigned a session ID of 1, and any new logging sessions after that would begin with the session ID 3.

Examples

The following example terminates an ASDM session with a session ID of 0. The **show asdm log_sessions** commands display the active ASDM sessions before and after the **asdm disconnect log_sessions** command is entered.

```
hostname# show asdm log_sessions

0 192.168.1.1
1 192.168.1.2
hostname# asdm disconnect 0
hostname# show asdm log_sessions

1 192.168.1.2
```

Related Commands

Command	Description
show asdm log_sessions	Displays a list of active ASDM logging sessions and their associated session ID.

asdm group



Caution

Do not manually configure this command. ASDM adds **asdm group** commands to the running configuration and uses them for internal purposes. This command is included in the documentation for informational purposes only.

asdm group *real_grp_name* *real_if_name*

asdm group *ref_grp_name* *ref_if_name* **reference** *real_grp_name*

Syntax Description

<i>real_grp_name</i>	The name of an ASDM object group.
<i>real_if_name</i>	The name of the interface to which the specified object group is associated.
<i>ref_grp_name</i>	The name of an object group that contains translated IP addresses of the object group specified by the <i>real_grp_name</i> argument.
<i>ref_if_name</i>	The name of the interface from which the destination IP address of inbound traffic is translated.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was changed from the pdm group command to the asdm group command.

Usage Guidelines

Do not manually configure or remove this command.

asdm history enable

To enable ASDM history tracking, use the **asdm history enable** command in global configuration mode. To disable ASDM history tracking, use the **no** form of this command.

asdm history enable

no asdm history enable

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History	Release	Modification
	7.0	This command was changed from the pdm history enable command to the asdm history enable command.

Usage Guidelines The information obtained by enabling ASDM history tracking is stored in the ASDM history buffer. You can view this information using the **show asdm history** command. The history information is used by ASDM for device monitoring.

Examples The following example enables ASDM history tracking:

```
hostname(config)# asdm history enable
hostname(config)#
```

Related Commands	Command	Description
	show asdm history	Displays the contents of the ASDM history buffer.

asdm image

To specify the ASDM software image, use the **asdm image** command in global configuration mode. To remove the image specification, use the **no** form of this command.

asdm image *image_path*

no asdm image [*image_path*]

Syntax Description

image_path The path to the ASDM image file on the security appliance, for example, `flash:/asdm`.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command changed from the pdm image command to the asdm image command.

Usage Guidelines

The **asdm image** command specifies the ASDM software image used when ASDM sessions are initiated. If this command does not appear in the configuration, ASDM sessions cannot be started.

You can store more than one ASDM software image in Flash memory. Using the **asdm image** command to specify a new ASDM software image while there are active ASDM sessions does not disrupt the active sessions; active ASDM sessions will continue to use the ASDM software image they started with. New ASDM sessions will use the new software image.

Use the **no** form of this command to disable ASDM.

Examples

The following example sets the ASDM image to `asdm.bin`:

```
hostname(config)# asdm image flash:/asdm.bin
hostname(config)#
```


Related Commands

Command	Description
show asdm image	Displays the current ASDM image file.

asdm location



Caution

Do not manually configure this command. ASDM adds **asdm location** commands to the running configuration and uses them for internal communication. This command is included in the documentation for informational purposes only.

asdm location *ip_addr netmask if_name*

asdm location *ipv6_addr/prefix if_name*

Syntax Description

<i>ip_addr</i>	IP address used internally by ASDM to define the network topology.
<i>netmask</i>	The subnet mask for <i>ip_addr</i> .
<i>if_name</i>	The name of the interface through which ASDM is accessed.
<i>ipv6_addr/prefix</i>	The IPv6 address and prefix used internally by ASDM to define the network topology.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was changed from the pdm location command to the asdm location command.

Usage Guidelines

Do not manually configure or remove this command.

asr-group

To specify an asymmetrical routing interface group ID, use the **asr-group** command in interface configuration mode. To remove the ID, use the **no** form of this command.

asr-group *group_id*

no asr-group *group_id*

Syntax Description

group_id The asymmetric routing group ID. Valid values are from 1 to 32.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	•	—	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

When Active/Active failover is enabled, you may encounter situations where load balancing causes the return traffic for outbound connections to be routed through an active context on the peer unit, where the context for the outbound connection is in the standby group.

The **asr-group** command causes incoming packets to be re-classified with the interface of the same asr-group if a flow with the incoming interface cannot be found. If re-classification finds a flow with another interface, and the associated context is in standby state, then the packet is forwarded to the active unit for processing.

Stateful Failover must be enabled for this command to take effect.

You can view ASR statistics using the **show interface detail** command. These statistics include the number of ASR packets sent, received, and dropped on an interface.

Examples

The following example assigns the selected interfaces to the asymmetric routing group 1.

Context ctx1 configuration:

```
hostname/ctx1(config)# interface e2
hostname/ctx1(config-if)# nameif outside
hostname/ctx1(config-if)# ip address 192.168.1.11 255.255.255.0 standby 192.168.1.21
hostname/ctx1(config-if)# asr-group 1
```

Context ctx2 configuration:

```
hostname/ctx2(config)# interface e3  
hostname/ctx2(config-if)# nameif outside  
hostname/ctx2(config-if)# ip address 192.168.1.31 255.255.255.0 standby 192.168.1.41  
hostname/ctx2(config-if)# asr-group 1
```

Related Commands

Command	Description
interface	Enters interface configuration mode.
show interface	Displays interface statistics.

authentication

To configure authentication methods for WebVPN or e-mail proxy, use the **authentication** command. For WebVPN, use this command in webvpn mode. For e-mail proxies (IMAP4S, POP3S, SMTPS), use this command in the applicable e-mail proxy mode. To restore the default, AAA, use the **no** form of this command.

The security appliance authenticates users to verify their identity.

authentication {aaa | certificate | mailhost | piggyback}

no authentication

Syntax Description

aaa	Provides a username and password that the security appliance checks against a previously configured AAA server.
certificate	Provides a certificate during SSL negotiation.
mailhost	Authenticates via the remote mail server. You can configure mailhost for SMTPS only. For the IMAP4S and POP3S, mailhost authentication is mandatory, and not displayed as a configurable option.
piggyback	Requires that an HTTPS WebVPN session already exists. Piggyback authentication is available for e-mail proxies only.

Defaults

The following table shows the default authentication method for WebVPN and e-mail proxies:

Protocol	Default Authentication Method
WebVPN	AAA
IMAP4S	Mailhost (required)
POP3S	Mailhost (required)
SMTPS	AAA

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	—	•	—	—
Imap4s	•	—	•	—	—
Pop3s	•	—	•	—	—
SMTPS	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

For WebVPN, you can require both AAA and certificate authentication, in which case users must provide both a certificate *and* a username and password.

For e-mail proxy authentication, you can require more than one authentication method.

Specifying the command again overwrites the current configuration.

Examples

The following example shows how to require that WebVPN users provide certificates for authentication:

```
hostname(config)# webvpn
hostname(config-webvpn)# authentication certificate
```

authentication chap

For L2TP connections, to permit CHAP authentication for PPP, use the **authentication chap** command in tunnel-group ppp-attributes configuration mode. In response to the server challenge, the client returns the encrypted [challenge plus password], with a cleartext username. This protocol is more secure than the PAP, but it does not encrypt data.

To return the command to its default setting (permit CHAP and MS-CHAP), use the **no** form of this command.

authentication chap

no authentication chap

Syntax Description

This command has no arguments or keywords.

Defaults

By default, CHAP is a permitted authentication protocol.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group ppp attributes configuration	•	—	•	—	—

Command History

Release	Modification
7.2(1)	This command was introduced.

Usage Guidelines

You can apply this attribute only to the L2TP/IPSec tunnel-group type.

Examples

The following example entered in config-ppp configuration mode, permits CHAP for PPP connections for the tunnel group. The name of the tunnel group in this example is pppremotegrp:

```
hostname(config)# tunnel-group pppremotegrp
hostname(config)# tunnel-group pppremotegrp ppp-attributes
hostname(config-ppp)# authentication chap
hostname(config-ppp)#
```

Related Commands	Command	Description
	clear configure tunnel-group	Clears all configured tunnel groups.
	show running-config tunnel-group	Shows the indicated certificate map entry.
	tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

authentication-port

To specify the port number used for RADIUS authentication for this host, use the **authentication-port** command in AAA-server host mode. To remove the authentication port specification, use the **no** form of this command. This command specifies the destination TCP/UDP port number of the remote RADIUS server hosts to which you want to assign authentication functions:

authentication-port *port*

no authentication-port

Syntax Description

port A port number, in the range 1-65535, for RADIUS authentication.

Defaults

By default, the device listens for RADIUS on port 1645 (in compliance with RFC 2058). If the port is not specified, the RADIUS authentication default port number (1645) is used.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
AAA-server host	•	•	•	•	—

Command History

Release	Modification
7.0	Semantic change to the command to support the specification of server ports on a per-host basis for server groups that contain RADIUS servers.

Usage Guidelines

If your RADIUS authentication server uses a port other than 1645, you must configure the security appliance for the appropriate port prior to starting the RADIUS service with the **aaa-server** command. This command is valid only for server groups that are configured for RADIUS.

Examples

The following example configures a RADIUS AAA server named “svrgrp1” on host “1.2.3.4”, sets a timeout of 9 seconds, sets a retry-interval of 7 seconds, and configures authentication port 1650.

```
hostname(config)# aaa-server svrgrp1 protocol radius
hostname(config-aaa-server-group)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# timeout 9
hostname(config-aaa-server-host)# retry-interval 7
hostname(config-aaa-server-host)# authentication-port 1650
hostname(config-aaa-server-host)# exit
hostname(config)#
```

Related Commands	Command	Description
	aaa authentication	Enables or disables LOCAL, TACACS+, or RADIUS user authentication, on a server designated by the aaa-server command, or ASDM user authentication.
	aaa-server host	Enters AAA server host configuration mode, so you can configure AAA server parameters that are host-specific.
	clear configure aaa-server	Removes all AAA command statements from the configuration.
	show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol

authentication-server-group

To specify the aaa-server group to use for user authentication, use the **authentication-server-group** command in tunnel-group general-attributes mode. To return this command to the default, use the **no** form of this command.

authentication-server-group [(*interface name*)] *server group* [**LOCAL** | **NONE**]

no authentication-server-group [(*interface name*)] *server group*

Syntax Description

<i>interface name</i>	(Optional) Specifies the interface where the IPSec tunnel terminates.
LOCAL	(Optional) Specifies authentication to be performed against the local user database if all of the servers in the server group have been deactivated due to communication failures. If the server group name is either LOCAL or NONE , do not use the LOCAL keyword here.
NONE	(Optional) Specifies the server group name as none. To indicate that authentication is not required, use the NONE keyword as the server group name.
<i>server group</i>	Specifies the name of the aaa-server group, which defaults to LOCAL .

Defaults

The default setting for this command is **LOCAL**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group general-attributes	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute to the IPSec remote access tunnel-group type only:

Examples

The following example entered in config-general configuration mode, configures an authentication server group named aaa-server456 for an IPSec remote-access tunnel group named remotegrp:

```
hostname(config)# tunnel-group remotegrp type ipsec_ra
hostname(config)# tunnel-group remotegrp general
hostname(config-general)# authentication-server-group aaa-server456
hostname(config-general)#
```

Related Commands	Command	Description
	aaa-server host	Configures AAA-server parameters.
	clear configure tunnel-group	Clears all configured tunnel groups.
	show running-config tunnel-group	Shows the tunnel group configuration for all tunnel groups or for a particular tunnel group.
	tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

authentication-server-group (webvpn)

To specify the set of authentication servers to use with WebVPN or one of the e-mail proxies, use the **authentication-server-group** command. For WebVPN, use this command in webvpn mode. For e-mail proxies (IMAP4S, POP3S, or SMTPS), use this command in the applicable e-mail proxy mode. To remove authentication servers from the configuration, use the **no** form of this command.

The security appliance authenticates users to verify their identity.

authentication-server-group *group tag*

no authentication-server-group

Syntax Description

group tag	Identifies the previously configured authentication server or group of servers. Use the aaa-server command to configure authentication servers. Maximum length of the group tag is 16 characters.

Defaults

No authentication servers are configured by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	—	•	—	—
Imap4s	•	—	•	—	—
Pop3s	•	—	•	—	—
SMTPS	•	—	•	—	—

Command History

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines

If you configure AAA authentication, you must configure this attribute as well. Otherwise, authentication always fails.

Examples

The following example shows how to configure WebVPN services to use the set of authentication servers named WEBVPNAUTH:

```
hostname(config)# webvpn
hostname(config-webvpn)# authentication-server-group WEBVPNAUTH
```

The next example shows how to configure IMAP4S e-mail proxy to use the set of authentication servers named IMAP4SSVRS:

```
hostname(config)# imap4s  
hostname(config-imap4s)# authentication-server-group IMAP4SSVRS
```

Related Commands

Command	Description
aaa-server host	Configures authentication, authorization, and accounting servers.

authorization-dn-attributes

To specify what part of the subject DN field to use as the username for authorization, use the **authorization-dn-attributes** command in tunnel-group ipsec-attributes configuration mode. To return this command to the default, use the **no** form of this command.

authorization-dn-attributes {*primary-attr* [*secondary-attr*] | **use-entire-name**}

no authorization-dn-attributes

Syntax Description

<i>primary-attr</i>	Specifies the attribute to use in deriving a name for an authorization query from a certificate.
<i>secondary-attr</i>	(Optional) Specifies an additional attribute to use in deriving a name for an authorization query from a certificate, if the primary attribute does not exist.
use-entire-name	Specifies that the security appliance should use the entire subject DN (RFC1779) to derive the name.

Defaults

The default value for the primary attribute is CN (Common Name).

The default value for the secondary attribute is OU (Organization Unit).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group ipsec attributes configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute to IPSec remote access tunnel type only.

Primary and secondary attributes include the following:

Attribute	Definition
CN	Common Name: the name of a person, system, or other entity
OU	Organizational Unit: the subgroup within the organization (O)
O	Organization: the name of the company, institution, agency, association or other entity
L	Locality: the city or town where the organization is located

Attribute	Definition
SP	State/Province: the state or province where the organization is located
C	Country: the two-letter country abbreviation. These codes conform to ISO 3166 country abbreviations.
EA	E-mail address
T	Title
N	Name
GN	Given Name
SN	Surname
I	Initials
GENQ	Generational Qualifier
DNQ	Domain Name Qualifier
UID	User Identifier

Examples

The following example entered in config-ipsec configuration mode, creates a remote access tunnel group (ipsec_ra) named remotegrp, specifies IPSec group attributes and defines the Common Name to be used as the username for authorization:

```
hostname(config)# tunnel-group remotegrp type ipsec_ra
hostname(config)# tunnel-group remotegrp ipsec-attributes
hostname(config-ipsec)# authorization-dn-attributes CN
hostname(config-ipsec)#
```

Related Commands

Command	Description
clear configure tunnel-group	Clears all configured tunnel groups.
show running-config tunnel-group	Shows the indicated certificate map entry.
tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

authorization-dn-attributes (webvpn)

To specify the primary and secondary subject DN fields to use as the username for authorization, use the **authorization-dn-attributes** command.

For WebVPN, use this command in webvpn mode. For e-mail proxies (IMAP4S, POP3S, or SMTPS), use this command in the applicable e-mail proxy mode. To remove the attribute from the configuration and restore default values, use the **no** form of this command.

authorization-dn-attributes {*primary-attr*} [*secondary-attr*] | **use-entire-name**}

no authorization-dn-attributes

Syntax Description

<i>primary-attr</i>	Specifies the attribute to use to derive a name for an authorization query from a digital certificate.
<i>secondary-attr</i>	(Optional) Specifies an additional attribute to use with the primary attribute to derive a name for an authorization query from a digital certificate.
use-entire-name	Specifies that the security appliance should use the entire subject DN to derive a name for an authorization query from a digital certificate.

Defaults

The default value for the primary attribute is CN (Common Name).

The default value for the secondary attribute is OU (Organization Unit).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Tunnel-group ipsec-attributes	•	—	•	—	—
Webvpn	•	—	•	—	—
Imap4s	•	—	•	—	—
Pop3s	•	—	•	—	—
SMTPS	•	—	•	—	—

Command History

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines

The following table explains the DN fields.

DN Field	Explanation
C	Country
CN	Common Name
DNQ	DN Qualifier
EA	E-mail Address
GENQ	Generational Qualifier
GN	Given Name
I	Initials
L	Locality
N	Name
O	Organization
OU	Organizational Unit
SER	Serial Number
SN	Surname
SP	State/Province
T	Title
UID	User ID
user-entire-name	Use entire DN name

Examples

The following example shows how to specify that WebVPN users must authorize according to their e-mail address (primary attribute) and organization unit (secondary attribute):

```
hostname(config)# webvpn
hostname(config-webvpn)# authorization-dn-attributes EA OU
```

Related Commands

Command	Description
authorization-required	Requires users to authorize successfully prior to connecting.

authorization-required

To require users to authorize successfully to connect, use the **authorization-required** command in tunnel-group ipsec-attributes configuration mode. To return this command to the default, use the **no** form of this command.

authorization-required

no authorization-required

Defaults

The default setting of this command is disabled.

Syntax Description

This command has no arguments or keywords.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Tunnel-group ipsec attributes configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute to IPSec remote-access tunnel-group type only.

Examples

The following example entered in config-ipsec configuration mode, requires authorization based on the complete DN for users connecting through a remote-access tunnel group named remotegrp. The first command configures the tunnel-group type as ipsec_ra (IPSec remote access) for the remote group named remotegrp. The second command enters ipsec-attributes mode for the specified tunnel group, and the last command specifies authorization required for the named tunnel group:

```
hostname(config)# tunnel-group remotegrp type ipsec_ra
hostname(config)# tunnel-group remotegrp ipsec-attributes
hostname(config-ipsec)# authorization-required
hostname(config-ipsec)#
```

Related Commands

Command	Description
clear configure tunnel-group	Clears all configured tunnel groups.

Command	Description
show running-config tunnel-group	Shows the indicated certificate map entry.
tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

authorization-required (webvpn)

To require WebVPN users or e-mail proxy users to authorize successfully prior to connecting, use the **authorization-required** command. For WebVPN, use this command in webvpn mode. For e-mail proxies (IMAP4S, POP3S, or SMTPS), use this command in the applicable e-mail proxy mode. To remove the attribute from the configuration, use the **no** version of this command.

authorization-required

no authorization-required

Syntax Description

This command has no arguments or keywords.

Defaults

Authorization-required is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Webvpn	•	—	•	—	—
Imap4s	•	—	•	—	—
Pop3s	•	—	•	—	—
SMTPS	•	—	•	—	—

Command History

Release	Modification
7.0(1)	This command was introduced.

Examples

The following example shows how to require authorization for WebVPN users:

```
hostname(config)# webvpn
hostname(config-webvpn)# authorization-required
```

Related Commands

Command	Description
authorization-dn-attributes (webvpn)	Specifies the primary and secondary subject DN fields to use as the username for authorization

authorization-server-group

To specify the aaa-server group for user authorization, use the **authorization-server-group** command in tunnel-group general-attributes mode. To return this command to the default, use the **no** form of this command.

authorization-server-group *server group*

no authorization-server-group

Syntax Description

<i>server group</i>	Specifies the name of the aaa-server group, which defaults to none .

Defaults

The default setting for this command is **no authorization-server-group**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Tunnel-group general-attributes	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute only to IPSec remote access tunnel-group types.

When VPN Authorization is defined as LOCAL, the attributes configured in the default group policy DfltGrpPolicy are enforced.

Examples

The following example entered in config-general configuration mode, configures an authorization server group named “aaa-server78” for an IPSec remote-access tunnel group named “remotegrp”:

```
hostname(config)# tunnel-group remotegrp type ipsec-ra
hostname(config)# tunnel-group remotegrp general
hostname(config-general)# authorization-server-group aaa-server78
hostname(config-general)#
```

Related Commands

Command	Description
aaa-server host	Configures AAA-server parameters.
clear configure tunnel-group	Clears all configured tunnel groups.

Command	Description
show running-config tunnel-group	Shows the tunnel group configuration for all tunnel groups or for a particular tunnel group.
tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

authorization-server-group (webvpn)

To specify the set of authorization servers to use with WebVPN or one of the e-mail proxies, use the **authorization-server-group** command. For WebVPN, use this command in webvpn mode. For e-mail proxies (IMAP4S, POP3S, SMTPS), use this command in the applicable e-mail proxy mode. To remove authorization servers from the configuration, use the **no** form of this command.

The security appliance uses authorization to verify the level of access to network resources that users are permitted.

authorization-server-group *group tag*

no authorization-server-group

Syntax Description

group tag	Identifies the previously configured authorization server or group of servers. Use the aaa-server command to configure authorization servers.

Defaults

No authorization servers are configured by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	—	•	—	—
Imap4s	•	—	•	—	—
Pop3s	•	—	•	—	—
SMTPS	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to configure WebVPN services to use the set of authorization servers named WebVPNpermit:

```
hostname(config)# webvpn
hostname(config-webvpn)# authorization-server-group WebVPNpermit
```

The following example shows how to configure POP3S e-mail proxy to use the set of authorization servers named POP3Spermit:

```
hostname(config)# pop3s
hostname(config-pop3s)# authorization-server-group POP3Spermit
```


Related Commands

Command	Description
aaa-server host	Configures authentication, authorization, and accounting servers.

auth-prompt

To specify or change the AAA challenge text for through-the-security appliance user sessions, use the **auth-prompt** command in global configuration mode. To remove the authentication challenge text, use the **no** form of this command.

auth-prompt prompt [**prompt** | **accept** | **reject**] *string*

no auth-prompt prompt [**prompt** | **accept** | **reject**]

Syntax Description

accept	If a user authentication via Telnet is accepted, display the prompt <i>string</i> .
prompt	The AAA challenge prompt string follows this keyword.
reject	If a user authentication via Telnet is rejected, display the prompt <i>string</i> .
<i>string</i>	A string of up to 235 alphanumeric characters or 31 words, limited by whichever maximum is first reached. Special characters, spaces, and punctuation characters are permitted. Entering a question mark or pressing the Enter key ends the string. (The question mark appears in the string.)

Defaults

If you do not specify an authentication prompt:

- FTP users see `FTP authentication`,
- HTTP users see `HTTP Authentication`
- Telnet users see no challenge text.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
7.0	Minor semantic changes.

Usage Guidelines

The **auth-prompt** command lets you specify the AAA challenge text for HTTP, FTP, and Telnet access through the security appliance when requiring user authentication from TACACS+ or RADIUS servers. This text is primarily for cosmetic purposes and displays above the username and password prompts that users view when logging in.

If the user authentication occurs from Telnet, you can use the **accept** and **reject** options to display different status prompts to indicate that the authentication attempt is accepted or rejected by the AAA server.

If the AAA server authenticates the user, the security appliance displays the **auth-prompt accept** text, if specified, to the user; otherwise it displays the **reject** text, if specified. Authentication of HTTP and FTP sessions displays only the challenge text at the prompt. The **accept** and **reject** text are not displayed.

**Note**

Microsoft Internet Explorer displays up to 37 characters in an authentication prompt. Netscape Navigator displays up to 120 characters, and Telnet and FTP display up to 235 characters in an authentication prompt.

Examples

The following example sets the authentication prompt to the string “Please enter your username and password.”:

```
hostname(config)# auth-prompt prompt Please enter your username and password
```

After this string is added to the configuration, users see the following:

```
Please enter your username and password
User Name:
Password:
```

For Telnet users, you can also provide separate messages to display when the security appliance accepts or rejects the authentication attempt; for example:

```
hostname(config)# auth-prompt reject Authentication failed. Try again.
hostname(config)# auth-prompt accept Authentication succeeded.
```

The following example sets the authentication prompt for a successful authentication to the string, “You’re OK.”

```
hostname(config)# auth-prompt accept You’re OK.
```

After successfully authenticating, the user sees the following message:

```
You’re OK.
```

Related Commands

Command	Description
clear configure auth-prompt	Removes the previously specified authentication prompt challenge text and reverts to the default value, if any.
show running-config auth-prompt	Displays the current authentication prompt challenge text.

auto-update device-id

To configure the security appliance device ID for use with an Auto Update Server, use the **auto-update device-id** command in global configuration mode. To remove the device ID, use the **no** form of this command.

auto-update device-id [**hardware-serial** | **hostname** | **ipaddress** [*if_name*] | **mac-address** [*if_name*] | **string** *text*]

no auto-update device-id [**hardware-serial** | **hostname** | **ipaddress** [*if_name*] | **mac-address** [*if_name*] | **string** *text*]

Syntax Description

hardware-serial	Uses the hardware serial number of the security appliance to uniquely identify the device.
hostname	Uses the hostname of the security appliance to uniquely identify the device.
ipaddress [<i>if_name</i>]	Uses the IP address of the security appliance to uniquely identify the security appliance. By default, the security appliance uses the interface used to communicate with the Auto Update Server. If you want to use a different IP address, specify the <i>if_name</i> .
mac-address [<i>if_name</i>]	Uses the MAC address of the security appliance to uniquely identify the security appliance. By default, the security appliance uses the MAC address of the interface used to communicate with the Auto Update Server. If you want to use a different MAC address, specify the <i>if_name</i> .
string <i>text</i>	Specifies the text string to uniquely identify the device to the Auto Update Server.

Command History

Release	Modification
7.0	This command was introduced.

Defaults

The default ID is the hostname.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Examples

The following example sets the device ID to the serial number:

```
hostname(config)# auto-update device-id hardware-serial
```

Related Commands

auto-update poll-period	Sets how often the security appliance checks for updates from an Auto Update Server.
auto-update server	Identifies the Auto Update Server.
auto-update timeout	Stops traffic from passing through the security appliance if the Auto Update Server is not contacted within the timeout period.
clear configure auto-update	Clears the Auto Update Server configuration
show running-config auto-update	Shows the Auto Update Server configuration.

auto-update poll-period

To configure how often the security appliance checks for updates from an Auto Update Server, use the **auto-update poll-period** command in global configuration mode. To reset the parameters to the defaults, use the **no** form of this command.

auto-update poll-period *poll_period* [*retry_count* [*retry_period*]]

no auto-update poll-period *poll_period* [*retry_count* [*retry_period*]]

Syntax Description

<i>poll_period</i>	Specifies how often, in minutes, to poll an Auto Update Server, between 1 and 35791. The default is 720 minutes (12 hours).
<i>retry_count</i>	Specifies how many times to try reconnecting to the Auto Update Server if the first attempt fails. The default is 0.
<i>retry_period</i>	Specifies how long to wait, in minutes, between connection attempts, between 1 and 35791. The default is 5 minutes.

Defaults

The default poll period is 720 minutes (12 hours).

The default number of times to try reconnecting to the Auto Update Server if the first attempt fails is 0.

The default period to wait between connection attempts is 5 minutes.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example sets the poll period to 360 minutes, the retries to 1, and the retry period to 3 minutes:

```
hostname(config)# auto-update poll-period 360 1 3
```

Related Commands

auto-update device-id	Sets the security appliance device ID for use with an Auto Update Server.
auto-update server	Identifies the Auto Update Server.

auto-update timeout	Stops traffic from passing through the security appliance if the Auto Update Server is not contacted within the timeout period.
clear configure auto-update	Clears the Auto Update Server configuration
show running-config auto-update	Shows the Auto Update Server configuration.

auto-update server

To identify the Auto Update Server, use the **auto-update server** command in global configuration mode. To remove the server, use the **no** form of this command. The security appliance periodically contacts the Auto Update Server for any configuration, operating system, and ASDM updates.

auto-update server *url* [**source** *interface*] [*verify-certificate*]

no auto-update server *url* [**source** *interface*] [*verify-certificate*]

Syntax Description

<i>url</i>	Specifies the location of the Auto Update Server using the following syntax: http[s]: [[<i>user:password@</i>] <i>location</i> [: <i>port</i>]] / <i>pathname</i>
<i>interface</i>	Specifies which interface to use when sending requests to the auto-update server.
<i>verify_certificate</i>	Verifies the certificate returned by the Auto Update Server.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Only one server can be configured.

For auto update functionality to work properly, you must use the **boot system configuration** command and ensure it specifies a valid boot image.

If the interface specified in the **source** *interface* argument is the same interface specified with the **management-access** command, requests to the auto-update server will be sent over the VPN tunnel.

Examples

The following example sets the Auto Update Server URL and specifies the interface outside:

```
hostname(config)# auto-update server http://10.1.1.1:1741/ source outside
```


Related Commands	auto-update device-id	Sets the security appliance device ID for use with an Auto Update Server.
	auto-update poll-period	Sets how often the security appliance checks for updates from an Auto Update Server.
	auto-update timeout	Stops traffic from passing through the security appliance if the Auto Update Server is not contacted within the timeout period.
	clear configure auto-update	Clears the Auto Update Server configuration.
	management-access	Enables access to an internal management interface on the security appliance.
	show running-config auto-update	Shows the Auto Update Server configuration.

auto-update timeout

To set a timeout period in which to contact the Auto Update Server, use the **auto-update timeout** command in global configuration mode. If the Auto Update Server has not been contacted for the timeout period, the security appliance stops all traffic through the security appliance. Set a timeout to ensure that the security appliance has the most recent image and configuration. To remove the timeout, use the **no** form of this command.

auto-update timeout *period*

no auto-update timeout [*period*]

Syntax Description

<i>period</i>	Specifies the timeout period in minutes between 1 and 35791. The default is 0, which means there is no timeout. You cannot set the timeout to 0; use the no form of the command to reset it to 0.

Defaults

The default timeout is 0, which sets the security appliance to never time out.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

A timeout condition is reported with system log message 201008.

Examples

The following example sets the timeout to 24 hours:

```
hostname(config)# auto-update timeout 1440
```

Related Commands

auto-update device-id	Sets the security appliance device ID for use with an Auto Update Server.
auto-update poll-period	Sets how often the security appliance checks for updates from an Auto Update Server.
auto-update server	Identifies the Auto Update Server.

clear configure auto-update	Clears the Auto Update Server configuration
show running-config auto-update	Shows the Auto Update Server configuration.

backup-servers

To configure backup servers, use the **backup-servers** command in group-policy configuration mode. To remove a backup server, use the **no** form of this command. To remove the backup-servers attribute from the running configuration, use the **no** form of this command without arguments. This enables inheritance of a value for backup-servers from another group policy.

IPSec backup servers let a VPN client connect to the central site when the primary security appliance is unavailable. When you configure backup servers, the security appliance pushes the server list to the client as the IPSec tunnel is established.

backup-servers {server1 server2. . . server10 | clear-client-config | keep-client-config}

no backup-servers [server1 server2. . . server10 | clear-client-config | keep-client-config]

Syntax Description

clear-client-config	Specifies that the client uses no backup servers. The security appliance pushes a null server list.
keep-client-config	Specifies that the security appliance sends no backup server information to the client. The client uses its own backup server list, if configured.
server1 server 2.... server10	Provides a space delimited, priority-ordered list of servers for the VPN client to use when the primary security appliance is unavailable. Identifies servers by IP address or hostname. The list can be 500 characters long, but can contain only 10 entries.

Defaults

Backup servers do not exist until you configure them, either on the client or on the primary security appliance.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Group-policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Configure backup servers either on the client or on the primary security appliance. If you configure backup servers on the security appliance, it pushes the backup server policy to the clients in the group, replacing the backup server list on the client if one is configured.

**Note**

If you are using hostnames, it is wise to have backup DNS and WINS servers on a separate network from that of the primary DNS and WINS servers. Otherwise, if clients behind a hardware client obtain DNS and WINS information from the hardware client via DHCP, and the connection to the primary server is lost, and the backup servers have different DNS and WINS information, clients cannot be updated until the DHCP lease expires. Further, if you use hostnames and the DNS server is unavailable, significant delays can occur.

Examples

The following example shows how to configure backup servers with IP addresses 10.10.10.1 and 192.168.10.14, for the group policy named “FirstGroup”:

```
hostname(config)# group-policy FirstGroup attributes  
hostname(config-group-policy)# backup-servers 10.10.10.1 192.168.10.14
```

banner

To configure the session, login, or message-of-the-day banner, use the **banner** command in global configuration mode. The **no banner** command removes all lines from the banner keyword specified (**exec**, **login**, or **motd**).

banner {**exec** | **login** | **motd** *text*}

[**no**] **banner** {**exec** | **login** | **motd** [*text*]}

Syntax Description

exec	Configures the system to display a banner before displaying the enable prompt.
login	Configures the system to display a banner before the password login prompt when accessing the security appliance using Telnet.
motd	Configures the system to display a message-of-the-day banner when you first connect.
<i>text</i>	Line of message text to display.

Defaults

The default is no login, session, or message-of-the-day banner.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **banner** command configures a banner to display for the keyword specified. The *text* string consists of all characters following the first white space (space) until the end of the line (carriage return or line feed [LF]). Spaces in the text are preserved. However, you cannot enter tabs through the CLI.

Subsequent *text* entries are added to the end of an existing banner unless the banner is cleared first.



Note

The tokens \$(domain) and \$(hostname) are replaced with the hostname and domain name of the security appliance. When you enter a \$(system) token in a context configuration, the context uses the banner configured in the system configuration.

Multiple lines in a banner are handled by entering a new banner command for each line that you wish to add. Each line is then appended to the end of the existing banner. There is no limit on the length of a banner other than RAM and Flash limits.

When accessing the security appliance through Telnet or SSH, the session closes if there is not enough system memory available to process the banner messages or if a TCP write error occurs. Only the `exec` and `motd` banners support access to the security appliance through SSH. The login banner does not support SSH.

To replace a banner, use the **no banner** command before adding the new lines.

Use the **no banner {exec | login | motd}** command to remove all the lines for the banner keyword specified.

The **no banner** command does not selectively delete text strings, so any *text* that you enter at the end of the **no banner** command is ignored.

Examples

This example shows how to configure the **exec**, **login**, and **motd** banners:

```
hostname(config)# banner motd Think on These Things
hostname(config)# banner exec Enter your password carefully
hostname(config)# banner login Enter your password to log in
hostname(config)# show running-config banner
exec:
Enter your password carefully

login:
Enter your password to log in

motd:
Think on These Things
```

This example shows how to add a second line to the **motd** banner:

```
hostname(config)# banner motd and Enjoy Today
hostname(config)# show running-config banner motd
Think on These Things and Enjoy Today
```

Related Commands

Command	Description
clear configure banner	Removes all banners.
show running-config banner	Displays all banners.

banner (group-policy)

To display a banner, or welcome text, on remote clients when they connect, use the **banner** command in group-policy configuration mode. To delete a banner, use the **no** form of this command. This option allows inheritance of a banner from another group policy. To prevent inheriting a banner, use the **banner none** command.

banner { **value** *banner_string* | **none** }

no banner



Note

If you configure multiple banners under a VPN group-policy, and you delete any one of the banners, all banners will be deleted.

Syntax Description

none	Sets a banner with a null value, thereby disallowing a banner. Prevents inheriting a banner from a default or specified group policy.
value <i>banner_string</i>	Constitutes the banner text. Maximum string size is 500 characters. Use the “\n” sequence to insert a carriage return.

Defaults

There is no default banner.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to create a banner for the group policy named “FirstGroup”:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# banner value Welcome to Cisco Systems 7.0.
```


blocks

To allocate additional memory to block diagnostics (displayed by the **show blocks** command), use the **blocks** command in privileged EXEC mode. To set the value back to the default, use the **no** form of this command. The amount of memory allocated will be at most 150 KB but never more than 50% of free memory. Optionally, you can specify the memory size manually.

blocks queue history enable [*memory_size*]

no blocks queue history enable [*memory_size*]

Syntax Description

memory_size (Optional) Sets the memory size for block diagnostics in Bytes, instead of applying the dynamic value. If this value is greater than free memory, an error message displays and the value is not accepted. If this value is greater than 50% of free memory, a warning message displays, but the value is accepted.

Defaults

The default memory assigned to track block diagnostics is 2136 Bytes.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

To view the currently allocated memory, enter the **show blocks queue history** command. If you reload the security appliance, the memory allocation returns to the default.

Examples

The following example increases the memory size for block diagnostics:

```
hostname# blocks queue history enable
```

The following example increases the memory size to 3000 Bytes:

```
hostname# blocks queue history enable 3000
```

The following example attempts to increase the memory size to 3000 Bytes, but the value is more than free memory:

```
hostname# blocks queue history enable 3000
```

```
ERROR: memory size exceeds current free memory
```

The following example increases the memory size to 3000 Bytes, but the value is more than 50% of free memory:

```
hostname# blocks queue history enable 3000
```

```
WARNING: memory size exceeds 50% of current free memory
```

Related Commands

Command	Description
clear blocks	Clears the system buffer statistics.
show blocks	Shows the system buffer utilization.

boot

To specify which system image the system will use at next reload and which configuration file the system will use at startup, use the **boot** command in privileged EXEC mode. Use the **no** form of this command to restore the default value.

boot {**config** | **system**} *url*

no boot {**config** | **system**} *url*

Syntax Description

config	Specifies which configuration file to use when the system is loaded.
system	Specifies which system image file to use when the system is loaded.
<i>url</i>	Sets the context configuration URL. All remote URLs must be accessible from the admin context. See the following URL syntax: • disk0:/[path]/filename This option is only available for the ASA platform, and indicates the internal Flash card. You can also use flash instead of disk0; they are aliased. • disk1:/[path]/filename This option is only available for the ASA platform, and indicates the external Flash card. • flash:/[path]/filename • tftp://[user[:password]]@[server[:port]]/[path]/filename

Defaults

If the **boot config** command is not specified, the startup-config will be saved to a hidden location, and used only with commands that utilize it, such as the **show startup-config** command and the **copy startup-config** command.

For the **boot system** command, there are no defaults. If the BOOT environment variable is not configured, the system searches only the internal Flash for the first valid image to boot. If no valid image is found no system image will be loaded, and the system will boot loop until ROMMON or Monitor mode is broken into.

You can enter up to four **boot system** command entries, to specify different images to boot from in order, and the security appliance will boot the first valid image it finds.



Note

The PIX platform **boot system** command does not support loading an image using a TFTP location.

The following table shows the modes in which you can enter the command.

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You set the CONFIG_FILE environment variable in the current running memory when you use the **boot config** command. This variable specifies which configuration file to load when the system boots.

**Note**

Only one **boot system tftp:** command may be configured, and it must be the first one configured. Subsequent multiple **boot system tftp:** commands will fail unless a **no boot system** command is issued.

When you use this global configuration command, you affect only the running configuration. Use the **write memory** or **copy** command to save the environment variable from your running configuration to your startup configuration. Note that saving the running configuration to the startup configuration will also overwrite the configured file with the running configuration, so change this variable and execute the **write memory** command before copying the new configuration file to the configured name.

The system stores and executes the boot system commands in the order in which you enter them in the configuration file. To execute the configuration when the reloads use the **write memory** command or **copy** command to save the environment variable from your running configuration to your startup configuration.

**Tip**

The ASDM image file is specified by the **asdm image** command.

Examples

The following example specifies that at startup the security appliance should load a configuration file called configuration.txt:

```
hostname(config)# boot config configuration.txt
```

Related Commands

Command	Description
asdm image	Specifies the ASDM software image.
show bootvar	Displays boot file and configuration properties.



C Commands

cache-time

To specify in minutes how long to allow a CRL to remain in the cache before considering it stale, use the **cache-time** command in ca-crl configuration mode. To return to the default value, use the **no** form of this command.

cache-time *refresh-time*

no cache-time

Syntax Description

refresh-time Specifies the number of minutes to allow a CRL to remain in the cache. The range is 1 - 1440 minutes. If the NextUpdate field is not present in the CRL, the CRL is not cached.

Defaults

The default setting is 60 minutes.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
CRL configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters ca-crl configuration mode, and specifies a cache time refresh value of 10 minutes for trustpoint central:

```
hostname(configure)# crypto ca trustpoint central
hostname(ca-trustpoint)# crl configure
hostname(ca-crl)# cache-time 10
hostname(ca-crl)#
```

Related Commands

Command	Description
crl configure	Enters crl configuration mode.
crypto ca trustpoint	Enters trustpoint configuration mode.
enforcenextupdate	Specifies how to handle the NextUpdate CRL field in a certificate.

call-agent

To specify a group of call agents, use the **call-agent** command in MGCP map configuration mode, which is accessible by using the **mgcp-map** command. To remove the configuration, use the **no** form of this command.

call-agent *ip_address* *group_id*

no call-agent *ip_address* *group_id*

Syntax Description

<i>ip_address</i>	The IP address of the gateway.
<i>group_id</i>	The ID of the call agent group, from 0 to 2147483647.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **call-agent** command to specify a group of call agents that can manage one or more gateways. The call agent group information is used to open connections for the call agents in the group (other than the one a gateway sends a command to) so that any of the call agents can send the response. Call agents with the same *group_id* belong to the same group. A call agent may belong to more than one group. The *group_id* option is a number from 0 to 4294967295. The *ip_address* option specifies the IP address of the call agent.

Examples

The following example allows call agents 10.10.11.5 and 10.10.11.6 to control gateway 10.10.10.115, and allows call agents 10.10.11.7 and 10.10.11.8 to control both gateways 10.10.10.116 and 10.10.10.117:

```
hostname(config)# mgcp-map mgcp_inbound
hostname(config-mgcp-map)# call-agent 10.10.11.5 101
hostname(config-mgcp-map)# call-agent 10.10.11.6 101
hostname(config-mgcp-map)# call-agent 10.10.11.7 102
hostname(config-mgcp-map)# call-agent 10.10.11.8 102
hostname(config-mgcp-map)# gateway 10.10.10.115 101
hostname(config-mgcp-map)# gateway 10.10.10.116 102
```

```
hostname(config-mgcp-map)# gateway 10.10.10.117 102
```

Related Commands

Commands	Description
debug mgcp	Enables the display of debug information for MGCP.
mgcp-map	Defines an MGCP map and enables MGCP map configuration mode.
show mgcp	Displays MGCP configuration and session information.

capture

To enable packet capture capabilities for packet sniffing and network fault isolation, use the **capture** command. To disable packet capture capabilities, use the **no** form of this command (see the “Usage Guidelines” section for additional information about the **no** form of this command).

```
capture capture_name [access-list access_list_name] [buffer buf_size] [ethernet-type type]
[interface interface_name] [packet-length bytes] [circular-buffer]
```

```
capture capture_name type asp-drop all [drop-code] [buffer buf_size] [circular-buffer]
[packet-length bytes]
```

```
capture capture_name type isakmp [access-list access_list_name] [buffer buf_size]
[circular-buffer] [interface interface_name] [packet-length bytes]
```

```
capture capture_name type raw-data [access-list access_list_name] [buffer buf_size]
[circular-buffer] [ethernet-type type] [interface interface_name] [packet-length bytes]
```

```
capture capture_name type webvpn user webvpn-user [url url]
```

```
no capture capture_name
```

Syntax Description

access-list <i>access_list_name</i>	(Optional) Selects packets based on IP or higher fields for a specific access list identification.
all	Captures all the packets that the security appliance drops
buffer <i>buf_size</i>	(Optional) Defines the buffer size used to store the packet in bytes.
<i>capture_name</i>	Specifies the name of the packet capture.
circular-buffer	(Optional) Overwrites the buffer, starting from the beginning, when the buffer is full.
ethernet-type <i>type</i>	(Optional) Selects an Ethernet type to capture.
interface <i>interface_name</i>	(Optional) Specifies the interface on which to use packet capture, where <i>interface_name</i> is the name assigned to the interface by the nameif command.
packet-length <i>bytes</i>	(Optional) Sets the maximum number of bytes of each packet to store in the capture buffer.
type asp-drop <i>drop-code</i>	(Optional) Captures packets dropped for a reason. You can specify a particular reason by using the <i>drop-code</i> argument. Valid values for the <i>drop-code</i> argument are listed in the “Usage Guidelines” section, below.
type isakmp	(Optional) Captures encrypted and decrypted ISAKMP payloads.
type raw-data	(Optional) Captures inbound and outbound packets on one or more interfaces. This is the default.
type webvpn	(Optional) Captures WebVPN data for a specific WebVPN connection.
url <i>url</i>	(Optional) Specifies a URL for a WebVPN connection capture.
user <i>webvpn-user</i>	(Optional) Specifies a username for a WebVPN capture.

Defaults

The defaults are as follows:

- The capture type is raw data.
- The **buffer** *size* is 512 KB.
- All the Ethernet types are accepted.
- All the IP packets are matched.
- The **packet-length** is 68 bytes.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged mode	•	•	•	•	•

Command History

Release	Modification
6.2	Support for this command was introduced on the security appliance.
7.0	This command was modified to include several new keywords, most notably the type asp-drop , type isakmp , type raw-data , and type webvpn keywords.
7.2(4)	Added the all option to capture all packets that the security appliance drops.

Usage Guidelines

Capturing packets is useful when troubleshooting connectivity problems or monitoring suspicious activity. The security appliance can track packet information for traffic that passes through it, including management traffic and inspection engines. Packet information for all traffic that passes through the device can be captured.

With ISAKMP, the ISAKMP subsystem does not have access to the upper layer protocols. The capture is a pseudo capture, with the Physical, IP, and UDP layers combined together to satisfy a PCAP parser. The peer addresses are obtained from the SA exchange and are stored in the IP layer.

When selecting an Ethernet type to be included from capture, an exception occurs with the 802.1Q or VLAN type. The 802.1Q tag is automatically skipped and the inner Ethernet type is used for matching. By default, all the Ethernet types are accepted.

Once the byte buffer is full, packet capture stops.

To enable packet capturing, attach the capture to an interface with the *interface* optional argument. Multiple **capture** command statements attach the capture to multiple interfaces.

If you copy the buffer contents to a TFTP server in ASCII format, you will see only the headers, not the details and hexadecimal dump of the packets. To see the details and hexadecimal dump, you need to transfer the buffer in PCAP format and read it with TCPDUMP or Ethereal.

The **ethernet-type** and **access-list** optional keywords select the packets to store in the buffer. A packet must pass both the Ethernet and access list filters before the packet is stored in the capture buffer.

The **circular-buffer** keyword allows you to enable the capture buffer to overwrite itself, starting from the beginning, when the capture buffer is full.

Enter the **no capture** command with either the **access-list** or **interface** optional keyword unless you want to clear the capture itself. Entering **no capture** without optional keywords deletes the capture. If the **access-list** optional keyword is specified, the access list is removed from the capture and the capture is preserved. If the **interface** optional keyword is specified, the capture is detached from the specified interface and the capture is preserved.

**Note**

The **capture** command is not saved to the configuration, and the **capture** command is not copied to the standby module during failover.

Use the **copy capture:** *capture_name tftp://server/path [pcap]* command to copy capture information to a remote TFTP server.

Use the **https://securityappliance-ip-address/capture/capture_name[/pcap]** command to see the packet capture information with a web browser.

If you specify the **pcap** optional keyword, then a libpcap-format file is downloaded to the web browser and can be saved using the web browser. (A libcap file can be viewed with TCPDUMP or Ethereal.)

When you enable WebVPN capture, the security appliance creates a pair of matching files: *capture name_ORIGINAL.000* and *capture name_MANGLED.000*. For each subsequent capture, the security appliance generates additional matching pairs of files and increments the file extensions. *url* is the URL prefix to match for data capture. Use the URL *http://server/path* to capture HTTP traffic to the server. Use *https://server/path* to capture HTTPS traffic to the server.

**Note**

Enabling WebVPN capture affects the performance of the security appliance. Be sure to disable the capture after you generate the capture files that you need for troubleshooting.

type asp-drop Drop Codes

The following table lists valid values for the optional *drop-code* argument that can follow the **type asp-drop** keyword.

Drop Code	Description
acl-drop	Flow is denied by access rule.
all	All packet drop reasons.
bad-crypto	Bad crypto return in packet.
bad-ipsec-natt	Bad IPSEC NATT packet.
bad-ipsec-prot	IPSEC not AH or ESP.
bad-ipsec-udp	Bad IPSEC UDP packet.
bad-tcp-cksum	Bad TCP checksum.
bad-tcp-flags	Bad TCP flags.
buffer	Configure size of capture buffer, default is 512 KB.
circular-buffer	Overwrite buffer from beginning when full, default is non-circular.
conn-limit	Connection limit reached.
ctm-error	CTM returned error.
dns-guard-id-not-matched	DNS Guard id not matched.

Drop Code	Description
dns-guard-out-of-app-id	DNS Guard out of app id.
dst-l2_lookup-fail	Dst MAC L2 Lookup Failed.
flow-expired	Expired flow.
fo-standby	Dropped by standby unit.
host-move-pkt	FP host move packet.
ifc-classify	Virtual firewall classification failed.
inspect-dns-id-not-matched	DNS Inspect id not matched.
inspect-dns-invalid-domain-label	DNS Inspect invalid domain label.
inspect-dns-invalid-pak	DNS Inspect invalid packet.
inspect-dns-out-of-app-id	DNS Inspect out of app id.
inspect-dns-pak-too-long	DNS Inspect packet too long.
inspect-icmp-error-different-embedded-conn	ICMP Error Inspect different embedded conn.
inspect-icmp-error-no-existing-conn	ICMP Error Inspect no existing conn.
inspect-icmp-out-of-app-id	ICMP Inspect out of app id.
inspect-icmp-seq-num-not-matched	ICMP Inspect seq num not matched.
inspect-icmpv6-error-invalid-pak	ICMPv6 Error Inspect invalid packet.
inspect-icmpv6-error-no-existing-conn	ICMPv6 Error Inspect no existing conn.
intercept-unexpected	Intercept unexpected packet.
interface-down	Interface is down.
invalid-app-length	Invalid app length.
invalid-encap	Invalid encapsulation.
invalid-ethertype	Invalid ethertype.
invalid-ip-addr	Invalid IP address.
invalid-ip-header	Invalid IP header.
invalid-ip-length	Invalid IP length.
invalid-ip-option	IP option configured drop.
invalid-tcp-hdr-length	Invalid tcp length.
invalid-tcp-pak	Invalid TCP packet.
invalid-udp-length	Invalid udp length.
ip-fragment	IP fragment (unsupported).
ips-fail-close	IPS card is down.
ips-request	IPS Module requested drop.
ipsec-clearpkt-notun	IPSEC Clear Pkt w/no tunnel.
ipsec-ipv6	IPSEC via IPV6.
ipsec-need-sa	IPSEC SA Not negotiated yet.
ipsec-spoof	IPSEC Spoof detected.
ipsec-tun-down	IPSEC tunnel is down.

Drop Code	Description
ipsevudp-keepalive	IPSEC/UDP keepalive message.
ipv6_fp-security-failed	IPv6 fastpath security checks failed.
ipv6_sp-security-failed	IPv6 slowpath security checks failed.
l2_acl	FP L2 rule drop.
l2_same-lan-port	L2 Src/Dst same LAN port.
large-buf-alloc-fail	FP fp large buffer alloc failed.
loopback-buffer-full	Loopback buffer full.
lu-invalid-pkt	Invalid LU packet.
natt-keepalive	NAT-T keepalive message.
no-adjacency	No valid adjacency.
no-mcast-entry	FP no mcast entry.
no-mcast-intrf	FP no mcast output intrf.
no-punt-cb	No registered punt cb.
no-route	No route to host.
non-ip-pkt-in-routed-mode	Non-IP packet received in routed mode.
np-sp-invalid-spi	Invalid SPI.
packet-length	Configure maximum length to save from each packet, default is 68 bytes.
punt-rate-limit	Punt rate limit exceeded.
queue-removed	Queued packet dropped.
rate-exceeded	QoS rate exceeded.
rpf-violated	Reverse-path verify failed.
security-failed	Early security checks failed.
send-ctm-error	Send to CTM returned error.
sp-security-failed	Slowpath security checks failed.
tcp-3whs-failed	TCP failed 3 way handshake.
tcp-ack-syn-diff	TCP ACK in SYNACK invalid.
tcp-acked	TCP DUP and has been ACKed.
tcp-bad-option-len	Bad option length in TCP.
tcp-bad-option-list	TCP option list invalid.
tcp-bad-sack-allow	Bad TCP SACK ALLOW option.
tcp-bad-winscale	Bad TCP window scale value.
tcp-buffer-full	TCP packet buffer full.
tcp-conn-limit	TCP Connection limit reached.
tcp-data-past-fin	TCP data send after FIN.
tcp-discarded-ooo	TCP packet out of order.
tcp-dual-open	TCP Dual open denied.
tcp-fo-drop	TCP replicated flow pak drop.

Drop Code	Description
tcp-invalid-ack	TCP invalid ACK.
tcp-mss-exceeded	TCP MSS was too large.
tcp-mss-no-syn	TCP MSS option on non-SYN.
tcp-not-syn	First TCP packet not SYN.
tcp-paws-fail	TCP packet failed PAWS test.
tcp-reserved-set	TCP reserved flags set.
tcp-rst-syn-in-win	TCP RST/SYN in window.
tcp-rstfin-ooo	TCP RST/FIN out of order.
tcp-seq-past-win	TCP packet SEQ past window.
tcp-seq-syn-diff	TCP SEQ in SYN/SYNACK.
tcp-syn-data	TCP SYN with data.
tcp-syn-ooo	TCP SYN on established conn.
tcp-synack-data	TCP SYNACK with data.
tcp-synack-ooo	TCP SYNACK on established conn.
tcp-tsopt-notallowed	TCP timestamp not allowed.
tcp-winscale-no-syn	TCP Window scale on non-SYN.
tcp_xmit_partial	TCP retransmission partial.
tfw-no-mgmt-ip-config	No management IP address configured for TFW.
unable-to-add-flow	Flow hash full.
unable-to-create-flow	Out of flow cache memory.
unimplemented	Slow path unimplemented.
unsupport-ipv6-hdr	Unsupported IPV6.
unsupported-ip-version	Unsupported IP version.

Examples

To enable packet capture, enter the following:

```
hostname(config)# capture captest interface inside
hostname(config)# capture captest interface outside
```

On a web browser, the capture contents for a capture named “mycapture” can be viewed at the following location:

```
https://171.69.38.95/capture/mycapture/pcap
```

To download a libpcap file (used in web browsers such as Internet Explorer or Netscape Navigator) to a local machine, enter the following:

```
https://171.69.38.95/capture/http/pcap
```

This example shows that the traffic is captured from an outside host at 171.71.69.234 to an inside HTTP server:

```
hostname(config)# access-list http permit tcp host 10.120.56.15 eq http host 171.71.69.234
hostname(config)# access-list http permit tcp host 171.71.69.234 host 10.120.56.15 eq http
hostname(config)# capture http access-list http packet-length 74 interface inside
```

This example shows how to capture ARP packets:

```
hostname(config)# capture arp ethernet-type arp interface outside
```

This example creates a WebVPN capture designated *hr*, which is configured to capture HTTP traffic for user2 visiting website *wwwin.abcd.com/hr/people*:

```
hostname# capture hr type webvpn user user2 url http://wwwin.abcd.com/hr/people  
WebVPN capture started.  
  capture name    hr  
  user name       user2  
  url             /http/0/wwwin.abcd.com/hr/people  
hostname#
```

Related Commands

Command	Description
clear capture	Clears the capture buffer.
copy capture	Copies a capture file to a server.
show capture	Displays the capture configuration when no options are specified.

cd

To change the current working directory to the one specified, use the **cd** command in privileged EXEC mode.

cd [**disk0:** | **disk1:** | **flash:**] [*path*]

Syntax Description

disk0:	Specifies the internal Flash memory, followed by a colon.
disk1:	Specifies the removable, external Flash memory card, followed by a colon.
flash:	Specifies the internal Flash memory, followed by a colon. In the ASA 5500 series, the flash keyword is aliased to disk0 .
<i>path</i>	(Optional) The absolute path of the directory to change to.

Defaults

If you do not specify a directory, the directory is changed to the root directory.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

This example shows how to change to the “config” directory:

```
hostname# cd flash:/config/
```

Related Commands

Command	Description
pwd	Displays the current working directory.

certificate

To add the indicated certificate, use the **certificate** command in crypto ca certificate chain mode. When you use this command, the security appliance interprets the data included with it as the certificate in hexadecimal format. A **quit** string indicates the end of the certificate.

To delete the certificate, use the **no** form of the command.

certificate [**ca** | **ra-encrypt** | **ra-sign** | **ra-general**] *certificate-serial-number*

no certificate *certificate-serial-number*

Syntax Description

<i>certificate-serial-number</i>	Specifies the serial number of the certificate in hexadecimal format ending with the word quit.
ca	Indicates that the certificate is a certificate authority (CA) issuing certificate.
ra-encrypt	Indicates that the certificate is a registration authority (RA) key encipherment certificate used in SCEP.
ra-general	Indicates that the certificate is a registration authority (RA) certificate used for digital signing and key encipherment in SCEP messaging.
ra-sign	Indicates that the certificate is an registration authority (RA) digital signature certificate used in SCEP messaging.

Defaults

This command has no default values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Certificate chain configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

A certificate authority (CA) is an authority in a network that issues and manages security credentials and public key for message encryption. As part of a public key infrastructure, a CA checks with a registration authority (RA) to verify information provided by the requestor of a digital certificate. If the RA verifies the requestor's information, the CA can then issue a certificate.

Examples

This example enters ca trustpoint mode for a trustpoint named central, then enters crypto ca certificate chain mode for central, and adds a CA certificate with a serial number 29573D5FF010FE25B45:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# crypto ca certificate chain central
hostname(ca-cert-chain)# certificate ca 29573D5FF010FE25B45
 30820345 308202EF A0030201 02021029 572A3FF2 96EF854F D0D6732F E25B4530
 0D06092A 864886F7 0D010105 05003081 8F311630 1406092A 864886F7 0D010901
 16076140 622E636F 6D310B30 09060355 04061302 55533116 30140603 55040813
 0D6D6173 73616368 75736574 74733111 300F0603 55040713 08667261 6E6B6C69
 6E310E30 0C060355 040A1305 63697363 6F310F30 0D060355 040B1306 726F6F74
 6F75311C 301A0603 55040313 136D732D 726F6F74 2D736861 2D30362D 32303031
 301E170D 30313036 32363134 31313430 5A170D32 32303630 34313430 3133305A
 30818F31 16301406 092A8648 86F70D01 09011607 6140622E 636F6D31 0B300906
 03550406 13025553 31163014 06035504 08130D6D 61737361 63687573 65747473
 3111300F 06035504 07130866 72616E6B 6C696E31 0E300C06 0355040A 13056369
 73636F31 0F300D06 0355040B 1306726F 6F746F75 311C301A 06035504 0313136D
 732D726F 6F742D73 68612D30 362D3230 3031305C 300D0609 2A864886 F70D0101
 01050003 4B003048 024100AA 3EB9859B 8670A6FB 5E7D2223 5C11BCFE 48E6D3A8
 181643ED CF7E75EE E77D83DF 26E51876 97D8281E 9F58E4B0 353FDA41 29FC791B
 1E14219C 847D19F4 A51B7B02 03010001 A3820123 3082011F 300B0603 551D0F04
 04030201 C6300F06 03551D13 0101FF04 05300301 01FF301D 0603551D 0E041604
 14E0D412 3ACC96C2 FBF651F3 3F66C0CE A62AB63B 323081CD 0603551D 1F0481C5
 3081C230 3EA03CA0 3A86386C 6461703A 2F2F7732 6B616476 616E6365 64737276
 2F436572 74456E72 6F6C6C2F 6D732D72 6F6F742D 7368612D 30362D32 3030312E
 63726C30 3EA03CA0 3A863868 7474703A 2F2F7732 6B616476 616E6365 64737276
 2F436572 74456E72 6F6C6C2F 6D732D72 6F6F742D 7368612D 30362D32 3030312E
 63726C30 40A03EA0 3C863A66 696C653A 2F2F5C5C 77326B61 6476616E 63656473
 72765C43 65727445 6E726F6C 6C5C6D73 2D726F6F 742D7368 612D3036 2D323030
 312E6372 6C301006 092B0601 04018237 15010403 02010130 0D06092A 864886F7
 0D010105 05000341 0056221E 03F377B9 E6900BF7 BCB3568E ADBA146F 3B8A71F3
 DF9EB96C BB1873B2 B6268B7C 0229D8D0 FFB40433 C8B3CB41 0E4D212B 2AEEDC77
 BEA3C1FE 5EE2AB6D 91
quit
```

Related Commands

Command	Description
clear configure crypto map	Clears all configuration for all crypto maps
show running-config crypto map	Displays the crypto map configuration.
crypto ca certificate chain	Enters certificate crypto ca certificate chain mode.
crypto ca trustpoint	Enters ca trustpoint mode.
show running-config crypto map	Displays all configuration for all the crypto maps

chain

To enable sending of a certificate chain, use the **chain** command in tunnel-group ipsec-attributes configuration mode. This action includes the root certificate and any subordinate CA certificates in the transmission. To return this command to the default, use the **no** form of this command.

chain

no chain

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting for this command is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group ipsec attributes configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute to all tunnel-group types.

Examples

The following example entered in config-ipsec configuration mode, enables sending a chain for an IPSec LAN-to-LAN tunnel group with the IP address of 209.165.200.225, which includes the root certificate and any subordinate CA certificates:

```
hostname(config)# tunnel-group 209.165.200.225 type IPSec_L2L
hostname(config)# tunnel-group 209.165.200.225 ipsec-attributes
hostname(config-ipsec)# chain
hostname(config-ipsec)#
```

Related Commands	Command	Description
	clear configure tunnel-group	Clears all configured tunnel groups.
	show running-config tunnel-group	Shows the indicated certificate map entry.
	tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

changeto

To change between security contexts and the system, use the **changeto** command in privileged EXEC mode.

changeto {**system** | **context** *name*}

Syntax Description

context <i>name</i>	Changes to the context with the specified name.
system	Changes to the system execution space.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If you log into the system execution space or the admin context, you can change between contexts and perform configuration and monitoring tasks within each context. The “running” configuration that you edit in configuration mode, or that is used in the **copy** or **write** commands, depends on which execution space you are in. When you are in the system execution space, the running configuration consists only of the system configuration; when you are in a context execution space, the running configuration consists only of that context. For example, you cannot view all running configurations (system plus all contexts) by entering the **show running-config** command. Only the current configuration appears.

Examples

The following example changes between contexts and the system in privileged EXEC mode:

```
hostname/admin# changeto system
hostname# changeto context customerA
hostname/customerA#
```

The following example changes between the system and the admin context in interface configuration mode. When you change between execution spaces, and you are in a configuration submode, the mode changes to the global configuration mode in the new execution space.

```
hostname(config-if)# changeto context admin
hostname/admin(config)#
```

Related Commands

Command	Description
admin-context	Sets a context to be the admin context.
context	Creates a security context in the system configuration and enters context configuration mode.
show context	Shows a list of contexts (system execution space) or information about the current context.

checkheaps

To configure checkheaps verification intervals, use the **checkheaps** command in global configuration mode. To set the value to the default, use the **no** form of this command. Checkheaps is a periodic process that verifies the sanity of the heap memory buffers (dynamic memory is allocated from the system heap memory region) and the integrity of the code region.

checkheaps {**check-interval** | **validate-checksum**} *seconds*

no checkheaps {**check-interval** | **validate-checksum**} [*seconds*]

Syntax Description

check-interval	Sets the buffer verification interval. The buffer verification process checks the sanity of the heap (allocated and freed memory buffers). During each invocation of the process, the security appliance checks the entire heap, validating each memory buffer. If there is a discrepancy, the security appliance issues either an “allocated buffer error” or a “free buffer error.” If there is an error, the security appliance dumps traceback information when possible and reloads.
validate-checksum	Sets the code space checksum validation interval. When the security appliance first boots up, the security appliance calculates a hash of the entire code. Later, during the periodic check, the security appliance generates a new hash and compares it to the original. If there is a mismatch, the security appliance issues a “text checksum checkheaps error.” If there is an error, the security appliance dumps traceback information when possible and reloads.
<i>seconds</i>	Sets the interval in seconds between 1 and 2147483.

Defaults

The default intervals are 60 seconds each.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example sets the buffer allocation interval to 200 seconds and the code space checksum interval to 500 seconds:

```
hostname(config)# checkheaps check-interval 200
hostname(config)# checkheaps validate-checksum 500
```

Related Commands

Command	Description
show checkheaps	Shows checkheaps statistics.

check-retransmission

To prevent against TCP retransmission style attacks, use the **check-retransmission** command in tcp-map configuration mode. To remove this specification, use the **no** form of this command.

check-retransmission

no check-retransmission

Syntax Description

This command has no arguments or keywords.

Defaults

The default is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Tcp-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **tcp-map** command is used along with the Modular Policy Framework infrastructure. Define the class of traffic using the **class-map** command and customize the TCP inspection with **tcp-map** commands. Apply the new TCP map using the **policy-map** command. Activate TCP inspection with **service-policy** commands.

Use the **tcp-map** command to enter tcp-map configuration mode. To prevent against TCP retransmission style attacks that arise from end-system interpretation of inconsistent retransmissions, use the **check-retransmission** command in tcp-map configuration mode.

The security appliance will make efforts to verify if the data in retransmits are the same as the original. If the data doesn't match, then the connection is dropped by the security appliance. When this feature is enabled, packets on the TCP connection are only allowed in order. For more details, see the **queue-limit** command.

Examples

The following example enables the TCP check-retransmission feature on all TCP flows:

```
hostname(config)# access-list TCP extended permit tcp any any
hostname(config)# tcp-map tmap
hostname(config-tcp-map)# check-retransmission
hostname(config)# class-map cmap
hostname(config-cmap)# match access-list TCP
hostname(config)# policy-map pmap
```

```
hostname(config-pmap)# class cmap
hostname(config-pmap)# set connection advanced-options tmap
hostname(config)# service-policy pmap global
```

Related Commands

Command	Description
class	Specifies a class map to use for traffic classification.
help	Shows syntax help for the policy-map , class , and description commands.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
set connection	Configures connection values.
tcp-map	Creates a TCP map and allows access to tcp-map configuration mode.

checksum-verification

To enable or disable TCP checksum verification, use the **checksum-verification** command in tcp-map configuration mode. To remove this specification, use the **no** form of this command.

checksum-verification

no checksum-verification

Syntax Description

This command has no arguments or keywords.

Defaults

Checksum verification is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Tcp-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **tcp-map** command is used along with the Modular Policy Framework infrastructure. Define the class of traffic using the **class-map** command and customize the TCP inspection with **tcp-map** commands. Apply the new TCP map using the **policy-map** command. Activate TCP inspection with **service-policy** commands.

Use the **tcp-map** command to enter tcp-map configuration mode. Use the **checksum-verification** command in tcp-map configuration mode to enable TCP checksum verification. If the check fails, the packet is dropped.

Examples

The following example enables TCP checksum verification on TCP connections from 10.0.0.0 to 20.0.0.0:

```
hostname(config)# access-list TCP1 extended permit tcp 10.0.0.0 255.0.0.0 20.0.0.0 255.0.0.0
hostname(config)# tcp-map tmap
hostname(config-tcp-map)# checksum-verification

hostname(config)# class-map cmap
hostname(config-cmap)# match access-list TCP1

hostname(config)# policy-map pmap
hostname(config-pmap)# class cmap
```

```
hostname(config-pmap)# set connection advanced-options tmap
```

```
hostname(config)# service-policy pmap global
```

Related Commands

Command	Description
class	Specifies a class map to use for traffic classification.
help	Shows syntax help for the policy-map , class , and description commands.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
set connection	Configures connection values.
tcp-map	Creates a TCP map and allows access to tcp-map configuration mode.

class (policy-map)

To assign a class-map to a policy for traffic classification, use the **class** command in policy-map mode. To remove a class-map specification for a policy map, use the **no** form of this command.

class *classmap-name*

no class *classmap-name*

Syntax Description

classmap-name The name for the class-map. The name can be up to 40 characters long.

Defaults

By default, “class class-default” always exists at the end of a policy map.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Policy-map	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Including the class-default, up to 63 class commands can be configured in a policy map.

The name “class-default” is a reserved name for default class, and it always exists; that is, you can include it in your configuration, but you cannot reconfigure or remove it using CLI. See the description of the **class-map** command for more information.

Use the **class** command to enter class mode, in which you can enter the following commands:

set connection

inspect

ips

priority

police

See the individual command descriptions for detailed information.

Examples

The following is an example of the class command in policy-map mode; note the change in the prompt:

```
hostname(config)# class-map localclass1
hostname(config-cmap)# match any
hostname(config-cmap)# exit
hostname(config)# policy-map localpolicy1
```

```
hostname(config-pmap)# class localclass1
hostname(config-pmap-c)# priority
hostname(config-pmap-c)# exit
```

The following is an example of a **policy-map** command, with its **class** commands, for a connection policy that limits connections to an HTTP server to a maximum of 256:

```
hostname(config)# access-list myhttp permit tcp any host 10.1.1.1
hostname(config)# class-map myhttp

hostname(config-cmap)# match access-list myhttp
hostname(config-cmap)# exit

hostname(config)# policy-map global-policy
hostname(config-pmap)# description This policy map defines a policy concerning connection
to http server.
hostname(config-pmap)# class myhttp
hostname(config-pmap-c)# set connection conn-max 256
```

The following is an example of a **policy-map** command, with its **class** commands, for the outside interface (defined in the **service-policy** command). The **class-map** command specifies a class of traffic that has a destination IP address of 192.168.10.10:

```
hostname(config)# class-map outside-voip
hostname(config-cmap)# match dscp af11
hostname(config-cmap)# exit

hostname(config)# policy-map outside-policy
hostname(config-pmap)# description This policy map defines policies for the outside
interface.
hostname(config-pmap)# class outside-voip
hostname(config-pmap-c)# priority
hostname(config-pmap-c)# exit
hostname(config-pmap)# exit
hostname(config)# service-policy outside-policy interface outside
```

Related Commands

Command	Description
clear configure policy-map	Removes all policy-map configuration, except for any policy-map that is in use in a service-policy command.
policy-map	Configures a policy; that is, an association of one or more traffic classes, each with one or more actions.
show running-config policy-map	Displays all current policy-map configurations.

class-map

To classify traffic for an interface when using Modular Policy Framework to configure a security feature, use the **class-map** command in global configuration mode. To delete a class map, use the **no** form of this command.

class-map *class_map_name*

no class-map *class_map_name*

Syntax Description

<i>class_map_name</i>	Text for the class map name; the text can be up to 40 characters in length. The name space for class-map is local to a security context. Therefore, the same name may be used in multiple security contexts. The maximum number of class-maps per security context is 255.

Defaults

The default class, class-default, always exists and cannot be configured or removed using the CLI. A default class, when used in a policy map, means “all other traffic.”. The definition of class-default is:

```
class-map class-default
  match any
```

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **class-map** command allows you to define a traffic class when using Modular Policy Framework to configure a security feature. Modular Policy Framework provides a consistent and flexible way to configure security appliance features in a manner similar to Cisco IOS software QoS CLI. Use the **class-map**, **policy-map**, and **service-policy** global configuration commands to configure a security feature using Modular Policy Framework.

Define a traffic class using the **class-map** global configuration command. Then create a policy map by associating the traffic class with one or more actions using the **policy-map** global configuration command. Finally, create a security policy by associating the policy map with one or more interfaces using the **service-policy** command.

A traffic class map contains, at most, one **match** command (with the exception of the **match tunnel-group** and **match default-inspection-traffic** commands). The **match** command identifies the traffic included in the traffic class. When a packet is matched against a class-map, the match result is either a match or a no match.

Use the **class-map** command to enter class-map configuration mode. From class-map configuration mode, you can define the traffic to include in the class using the **match** command. The following commands are available in class-map configuration mode:

description	Specifies a description for the class-map.
match access-list	Specifies the name of an access-list to be used as match criteria. When a packet does not match an entry in the access-list, the match result is a no-match. When a packet matches an entry in an access-list, and if it is a permit entry, the match result is a match. Otherwise, if it matches a deny access-list entry, the match result is no-match.
match port	Specifies to match traffic using a TCP/UDP destination port.
match precedence	Specifies to match the precedence value represented by the TOS byte in the IP header.
match dscp	Specifies to match the IETF-defined DSCP value in the IP header.
match rtp	Specifies to match an RTP port.
match tunnel-group	Specifies to match security related tunnel groups.
match flow ip destination-address	Specifies to match the IP destination address.
match default-inspection-traffic	Specifies to match default traffic for the inspect commands.

Examples

The following example shows how to define a traffic class of all TCP traffic to port 21 using a class map:

```
hostname(config)# class-map ftp-port
hostname(config-cmap)# match port tcp eq 21
```

Related Commands

Command	Description
clear configure class-map	Removes all of the traffic map definitions.
policy-map	Creates a policy map by associating the traffic class with one or more actions.
service-policy	Creates a security policy by associating the policy map with one or more interfaces.
show running-config class-map	Displays the information about the class map configuration.

clear aaa local user fail-attempts

To reset the number of failed user authentication attempts to zero without modifying the user's locked-out status, use the **clear aaa local user fail-attempts** command in privileged EXEC mode.

clear aaa local user authentication fail-attempts {username *name* | all}

Syntax Description

all	Resets the failed-attempts counter to 0 for all users.
<i>name</i>	Specifies a specific username for which the failed-attempts counter is reset to 0.
username	Indicates that the following parameter is a username, for which the failed-attempts counter is reset to 0.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use this command when a user fails authentication a few times, but you want to reset the counter to zero, for example, when the configuration has recently been modified.

After the configured number of failed authentication attempts, the user is locked out of the system and cannot successfully log in until either a system administrator unlocks the username or the system reboots.

The number of failed attempts resets to zero and the lockout status resets to No when the user successfully authenticates or when the security appliance reboots.

Locking or unlocking a username results in a syslog message.

A system administrator with a privilege level of 15 cannot be locked out.

Examples

The following example shows use of the **clear aaa local user authentication fail-attempts** command to reset the failed-attempts counter to 0 for the username anyuser:

```
hostname(config)# clear aaa local user authentication fail-attempts username anyuser
hostname(config)#
```

The following example shows use of the **clear aaa local user authentication fail-attempts** command to reset the failed-attempts counter to 0 for all users:

```
hostname(config)# clear aaa local user authentication fail-attempts all
hostname(config)#
```

Related Commands

Command	Description
aaa local authentication attempts max-fail	Configures a limit on the number of failed user authentication attempts allowed.
clear aaa local user logout	Resets the number of failed user authentication attempts to zero without modifying the user's locked-out status.
show aaa local user [locked]	Shows the list of usernames that are currently locked.

clear aaa local user logout

To clear the lockout status of the specified users and set their failed-attempts counter to 0, use the **clear aaa local user logout** command in privileged EXEC mode.

clear aaa local user logout {username *name* | all}

Syntax Description

all	Resets the failed-attempts counter to 0 for all users.
<i>name</i>	Specifies a specific username for which the failed-attempts counter is reset to 0.
username	Indicates that the following parameter is a username, for which the failed-attempts counter is reset to 0.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can specify a single user by using the **username** option or all users with the **all** option.

This command affects only the status of users that are locked out.

The administrator cannot be locked out of the device.

Locking or unlocking a username results in a syslog message.

Examples

The following example shows use of the **clear aaa local user logout** command to clear the lockout condition and reset the failed-attempts counter to 0 for the username anyuser:

```
hostname(config)# clear aaa local user logout username anyuser
hostname(config)#
```

Related Commands	Command	Description
	aaa local authentication attempts max-fail	Configures a limit on the number of failed user authentication attempts allowed.
	clear aaa local user fail-attempts	Resets the number of failed user authentication attempts to zero without modifying the user's locked-out status.
	show aaa local user [locked]	Shows the list of usernames that are currently locked.

clear aaa-server statistics

To reset the statistics for AAA servers, use the **clear aaa-server statistics** command in privileged EXEC mode.

clear aaa-server statistics [**LOCAL** | *groupname* [**host** *hostname*] | **protocol** *protocol*]

Syntax Description

LOCAL	(Optional) Clears statistics for the LOCAL user database.
<i>groupname</i>	(Optional) Clears statistics for servers in a group.
host <i>hostname</i>	(Optional) Clears statistics for a particular server in the group.
protocol <i>protocol</i>	(Optional) Clears statistics for servers of the specified protocol: • kerberos • ldap • nt • radius • sdi • tacacs+

Defaults

Remove all AAA-server statistics across all groups.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was modified to adhere to CLI guidelines. In the protocol values, nt replaces the older nt-domain , and sdi replaces the older rsa-ace .

Examples

The following command shows how to reset the AAA statistics for a specific server in a group:

```
hostname(config)# clear aaa-server statistics svrgrp1 host 1.2.3.4
```

The following command shows how to reset the AAA statistics for an entire server group:

```
hostname(config)# clear aaa-server statistics svrgrp1
```

The following command shows how to reset the AAA statistics for all server groups:

```
hostname(config)# clear aaa-server statistics
```

The following command shows how to reset the AAA statistics for a particular protocol (in this case, TACACS+):

```
hostname(config)# clear aaa-server statistics protocol tacacs+
```

Related Commands	Command	Description
	aaa-server protocol	Specifies and manages the grouping of AAA server connection data.
	clear configure aaa-server	Removes all non-default aaa server groups or clear the specified group
	show aaa-server	Displays AAA server statistics.
	show running-config aaa-server	Displays the current AAA server configuration values.

clear access-group

To remove access groups from all the interfaces, use the **clear access-group** command.

clear access-group

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Examples The following example shows how to remove all access groups:

```
hostname(config)# clear access-group
```

Related Commands	Command	Description
	access-group	Binds an access list to an interface.
	show running-config access-group	Displays the current access group configuration.

clear access-list

To clear an access-list counter, use the **clear access-list** command in global configuration mode.

clear access-list [*id*] **counters**

Syntax Description	counters	Clears access list counters.
	<i>id</i>	(Optional) Name or number of an access list.

Defaults All the access list counters are cleared.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines When you enter the **clear access-list** command, all the access list counters are cleared if you do not specify an *id*.

Examples The following example shows how to clear a specific access list counter:

```
hostname# clear access-list inbound counters
```

Related Commands	Command	Description
	access-list extended	Adds an access list to the configuration and configures policy for IP traffic through the firewall.
	access-list standard	Adds an access list to identify the destination IP addresses of OSPF routes, which can be used in a route map for OSPF redistribution.
	clear configure access-list	Clears an access list from the running configuration.
	show access-list	Displays the access list entries by number.
	show running-config access-list	Displays the access list configuration that is running on the security appliance.

clear arp statistics

To clear ARP statistics, use the **clear arp statistics** command in privileged EXEC mode.

clear arp statistics

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Examples The following example clears all ARP statistics:

```
hostname# clear arp statistics
```

Related Commands	Command	Description
	arp	Adds a static ARP entry.
	arp-inspection	For transparent firewall mode, inspects ARP packets to prevent ARP spoofing.
	show arp statistics	Shows ARP statistics.
	show running-config arp	Shows the current configuration of the ARP timeout.

clear asp drop

To clear accelerated security path drop statistics, use the **clear asp drop** command in privileged EXEC mode.

clear asp drop [*flow type* | *frame type*]

Syntax Description

flow	(Optional) Clears the dropped flow statistics.
frame	(Optional) Clears the dropped packet statistics.
<i>type</i>	(Optional) Clears the dropped flow or packets statistics for a particular process. See “ Usage Guidelines ” for a list of types.

Defaults

By default, this command clears all drop statistics.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Process types include the following:

```
acl-drop
audit-failure
closed-by-inspection
conn-limit-exceeded
fin-timeout
flow-reclaimed
fo-primary-closed
fo-standby
fo_rep_err
host-removed
inspect-fail
ips-fail-close
ips-request
ipsec-spoof-detect
loopback
mcast-entry-removed
mcast-intrf-removed
mgmt-lockdown
nat-failed
nat-rpf-failed
need-ike
```

```
no-ipv6-ipsec
non_tcp_syn
out-of-memory
parent-closed
pinhole-timeout
recurse
reinject-punt
reset-by-ips
reset-in
reset-ooout
shunned
syn-timeout
tcp-fins
tcp-intecept-no-response
tcp-intercept-kill
tcp-intercept-unexpected
tcpnorm-invalid-syn
tcpnorm-rexmit-bad
tcpnorm-win-variation
timeout
tunnel-pending
tunnel-torn-down
xlate-removed
```

Examples

The following example clears all drop statistics:

```
hostname# clear asp drop
```

Related Commands

Command	Description
show asp drop	Shows the accelerated security path counters for dropped packets.

clear asp table

To clear the hit counters either in asp arp or classify tables, or both, use the **clear asp table** command in privileged EXEC mode.

clear asp table [arp | classify]

Syntax Description

arp	clears the hits counters in asp arp table only.
classify	clears the hits counters in asp classify tables only

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.2(4)	This command was introduced.

Usage Guidelines

There are only two options arp and classify having hits in the **clear asp table** command

Examples

The following example clears all drop statistics:

```
hostname# clear asp table
```

```
Warning: hits counters in asp arp and classify tables are cleared, which might impact the
hits statistic of other modules and output of other "show" commands! hostname#clear asp
table arp
```

```
Warning: hits counters in asp arp table are cleared, which might impact the hits statistic
of other modules and output of other "show" commands! hostname#clear asp table classify
```

```
Warning: hits counters in classify tables are cleared, which might impact the hits
statistic of other modules and output of other "show" commands! hostname(config)# clear
asp table
```

```
Warning: hits counters in asp tables are cleared, which might impact the hits statistics
of other modules and output of other "show" commands! hostname# sh asp table arp
```

```
Context: single_vf, Interface: inside 10.1.1.11 Active 00e0.8146.5212 hits 0
```

```
Context: single_vf, Interface: identity :: Active 0000.0000.0000 hits 0 0.0.0.0 Active
0000.0000.0000 hits 0
```

Related Commands

Command	Description
show asp table arp	Shows the contents of the accelerated security path, which might help you troubleshoot a problem.

clear blocks

To reset the packet buffer counters such as the low watermark and history information, use the **clear blocks** command in privileged EXEC mode.

clear blocks

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines Resets the low watermark counters to the current available blocks in each pool. Also clears the history information stored during the last buffer allocation failure.

Examples The following example clears the blocks:

```
hostname# clear blocks
```

Command	Description
blocks	Increases the memory assigned to block diagnostics
show blocks	Shows the system buffer utilization.

clear capture

To clear the capture buffer, use the **clear capture** *capture_name* command.

clear capture *capture_name*

Syntax Description

capture_name Name of the packet capture.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged Mode	•	•	•	•	•

Command History

Release	Modification
2.2(1)	Support for this command was introduced on the security appliance.

Usage Guidelines

The shortened form of the **clear capture** (for example, **cl cap** or **clear cap**) is not supported to prevent accidental destruction of all the packet captures.

Examples

This example shows how to clear the capture buffer for the capture buffer “trudy”:

```
hostname(config)# clear capture trudy
```

Related Commands

Command	Description
capture	Enables packet capture capabilities for packet sniffing and network fault isolation.
show capture	Displays the capture configuration when no options are specified.

clear configure

To clear the running configuration, use the **clear configure** command in global configuration mode.

```
clear configure {primary | secondary | all | command}
```

Syntax Description	command	Clears the configuration for a specified command. For more information, see individual entries in this guide for each clear configure <i>command</i> command.
	primary	Clears commands related to connectivity, including the following commands: - tftp-server - shun - route - ip address - mtu - failover - monitor-interface - boot
	secondary	Clears commands not related to connectivity (that are cleared using the primary keyword).
	all	Clears the entire running configuration.

Defaults	No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines When you enter this command in a security context, you clear only the context configuration. If you enter this command in the system execution space, you clear the system running configuration as well as all context running configurations. Because you cleared all context entries in the system configuration (see the **context** command), the contexts are no longer running, and you cannot change to a context execution space.

Before clearing the configuration, make sure you save any changes to the **boot config** command (which specifies the startup configuration location) to the startup configuration; if you changed the startup configuration location only in the running configuration, then when you restart, the configuration loads from the default location.

Examples

The following example clears the entire running configuration:

```
hostname(config)# clear configure all
```

Related Commands

Command	Description
configure http	Merges a configuration file from the specified HTTP(S) URL with the running configuration.
configure memory	Merges the startup configuration with the running configuration.
configure net	Merges a configuration file from the specified TFTP URL with the running configuration.
configure factory-default	Adds commands you enter at the CLI to the running configuration.
show running-config	Shows the running configuration.

clear configure aaa

To clear the aaa configuration, use the **clear configure aaa** command in global configuration mode. The **clear configure aaa** command removes the AAA command statements from the configuration.

clear configure aaa

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
7.0	This command was modified for consistency within the CLI.

Usage Guidelines This command also resets the AAA parameters to their default values, if any.
There is no undo.

Examples `hostname(config)# clear configure aaa`

Command	Description
aaa accounting	Enable, disable, or view the keeping of records about which network services a user has accessed.
aaa authentication	Enable or view LOCAL, TACACS+, or RADIUS user authentication, on a server designated by the aaa-server command, or ASDM user authentication
aaa authorization	Enable or disable user authorization for a LOCAL or a TACACS+ server designated by the aaa-server command, or for ASDM user authentication.
show running-config aaa	Display the AAA configuration.

clear configure aaa-server

To remove all AAA server groups or to clear the specified group, use the **clear configure aaa-server** command in global configuration mode.

clear configure aaa-server [*server-tag*]

clear configure aaa-server [*server-tag*] **host** *server-ip*

Syntax Description

<i>server-ip</i>	The IP address of the AAA server.
<i>server-tag</i>	(Optional) Symbolic name of the server group to be cleared.

Defaults

Remove all AAA server groups.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

You can specify a particular AAA server group or, by default, all AAA server groups.

Use the **host** keyword to specify a particular server within a server group.

This command also resets the AAA server parameters to their default values, if any.

Examples

```
hostname(config)# aaa-server svrgrp1 protocol sdi
hostname(config)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server)# timeout 9
hostname(config-aaa-server)# retry 7
hostname(config-aaa-server)# sdi-version sdi-5
hostname(config-aaa-server)# exit
```

Given the preceding configuration, the following command shows how to remove a specific server from a group:

```
hostname(config)# clear config aaa-server svrgrp1 host 1.2.3.4
```

The following command shows how to remove a server group:

```
hostname(config)# clear config aaa-server svrgrp1
```

The following command shows how to remove all server groups:

```
hostname(config)# clear config aaa-server
```

Related Commands

Command	Description
aaa-server host	Specifies and manages host-specific AAA server connection data.
aaa-server protocol	Allows you to configure AAA server parameters that are group-specific and common to all hosts.
show running-config aaa	Display the current maximum number of concurrent proxy connections allowed per user, along with other AAA configuration values.

clear configure access-group

To remove access groups from all the interfaces, use the **clear configure access-group** command.

clear configure access-group

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History	Release	Modification
	7.0	Added keyword configure .

Examples The following example shows how to remove all access groups:

```
hostname(config)# clear configure access-group
```

Related Commands	Command	Description
	access-group	Binds an access list to an interface.
	show running-config access-group	Displays the current access group configuration.

clear configure access-list

To clear an access list from the running configuration, use the **clear configure access list** command in global configuration mode.

clear configure access-list [*id*]

Syntax Description	<i>id</i> (Optional) Name or number of an access list.

Defaults	All the access lists are cleared from the running configuration.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines	The clear configure access-list command automatically unbinds an access list from a crypto map command or interface. The unbinding of an access list from a crypto map command can lead to a condition that discards all packets because the crypto map commands referencing the access list are incomplete. To correct the condition, either define other access-list commands to complete the crypto map commands or remove the crypto map commands that pertain to the access-list command. Refer to the crypto map client command for more information.

Examples	This example shows how to clear the access lists from the running configuration:

```
hostname(config)# clear configure access-list
```

Related Commands	Command	Description
	access-list extended	Adds an access list to the configuration and configures policy for IP traffic through the firewall.
	access-list standard	Adds an access list to identify the destination IP addresses of OSPF routes, which can be used in a route map for OSPF redistribution.
	clear access-list	Clears access list counters.

Command	Description
show access-list	Displays counters for an access list.
show running-config access-list	Displays the access list configuration running on the security appliance.

clear configure alias

To remove all **alias** commands from the configuration, use the **clear configure alias** command in global configuration mode.

clear configure alias

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	•	•

Release	Modification
Preexisting	This command was preexisting.

Command History

Examples This example shows how to remove all **alias** commands from the configuration:

```
hostname(config)# clear configure alias
```

Command	Description
alias	Translates one address into another.
show running-config alias	Displays the overlapping addresses with dual NAT commands in the configuration.

Related Commands

clear configure arp-inspection

To clear the ARP inspection configuration, use the **clear configure arp-inspection** command in global configuration mode.

clear configure arp-inspection

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	—	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples The following example clears the ARP inspection configuration:

```
hostname# clear configure arp-inspection
```

Related Commands	Command	Description
	arp	Adds a static ARP entry.
	arp-inspection	For transparent firewall mode, inspects ARP packets to prevent ARP spoofing.
	firewall transparent	Sets the firewall mode to transparent.
	show arp statistics	Shows ARP statistics.
	show running-config arp	Shows the current configuration of the ARP timeout.

clear configure asdm

To remove all **asdm** commands from the running configuration, use the **clear configure asdm** command in global configuration mode.

clear configure asdm [**location** | **group** | **image**]

Syntax Description

group	(Optional) Clears only the asdm group commands from the running configuration.
image	(Optional) Clears only the asdm image command from the running configuration.
location	(Optional) Clears only the asdm location commands from the running configuration.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was changed from the clear pdm command to the clear configure asdm command.

Usage Guidelines

To view the **asdm** commands in the running configuration, use the **show running-config asdm** command.

Clearing the **asdm image** command from the configuration disables ASDM access. Clearing the **asdm location** and **asdm group** commands from the configuration causes ASDM to regenerate those commands the next time ASDM is accessed, but may disrupt active ASDM sessions.



Note

On security appliances running in multiple context mode, the **clear configure asdm image** command is only available in the system execution space, while the **clear configure asdm group** and **clear configure asdm location** commands are only available in the user contexts.

Examples

The following example clears the **asdm group** commands from the running configuration:

```
hostname(config)# clear configure asdm group
```

```
hostname(config)#
```

Related Commands

Command	Description
asdm group	Used by ASDM to associate object group names with interfaces.
asdm image	Specifies the ASDM image file.
asdm location	Used by ASDM to record IP address to interface associations.
show running-config asdm	Displays the asdm commands in the running configuration.

clear configure auth-prompt

To remove the previously specified authentication prompt challenge text and revert to the default value, if any, use the **clear configure auth-prompt** command in global configuration mode.

clear configure auth-prompt

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	—	—	•

Release	Modification
7.0	This command was modified to conform with CLI standards.

Usage Guidelines After you clear the authentication prompt, the prompt users see when they log in depends on the protocol they use:

- Users who log in using HTTP see HTTP Authentication.
- Users who log in using FTP see FTP Authentication.
- Users who log in using Telnet see no prompt.

Examples This example shows how to clear the auth-prompt:

```
hostname(config)# clear configure auth-prompt
```

Related Commands	auth-prompt	Sets the user authorization prompts.
	show running-config auth-prompt	Displays the user authorization prompts.

clear configure banner

To remove all the banners, use the **clear configure banner** command in global configuration mode.

clear configure banner

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History	Release	Modification
	2.2(1)	This command was introduced.

Examples This example shows how to clear banners:

```
hostname(config)# clear configure banner
```

Related Commands	Command	Description
	banner	Configures the session, login, or message-of-the-day banner.
	show running-config banner	Displays all banners.

clear configure ca certificate map

To remove all certificate map entries or to remove a specified certificate map entry, use the **clear configure ca configure map** command in global configuration mode.

clear configure ca certificate map [*sequence-number*]

Syntax Description

sequence-number (Optional) Specifies a number for the certificate map rule you are removing. The range is 1 through 65535.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example removes all certificate map entries.

```
hostname(config)# clear configure ca certificate map
hostname(config)#
```

Related Commands

Command	Description
crypto ca certificate map	Enters CA certificate map mode.

clear configure class-map

To remove all class maps, use the **clear configure class-map** command in global configuration mode.

clear configure class-map

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History	Release	Modification
	7.0	Added keyword configure .

Usage Guidelines To clear the class map for a specific class map name, use the **no** form of the **class-map** command.

Examples The following example shows how to clear all configured class-maps:
 hostname(config)# **clear configure class-map**

Related Commands	Command	Description
	class-map	Applies a traffic class to an interface.
	show running-config class-map	Displays the information about the class map configuration.

clear configure clock

To clear the clock configuration, use the **clear configure clock** command in global configuration mode.

clear configure clock

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	•

Release	Modification
7.0	This command was changed from clear clock .

Command History

Usage Guidelines This command clears all **clock** configuration commands. The **clock set** command is not a configuration command, so this command does not reset the clock. To reset the clock, you need to set a new time for the **clock set** command.

Examples The following example clears all clock commands:

```
hostname# clear configure clock
```

Command	Description
clock set	Manually sets the time.
clock summer-time	Sets the date range to show daylight savings time.
clock timezone	Sets the time zone.

Related Commands

clear configure command-alias

To remove all non-default command aliases, use the **clear configure command-alias** command in global configuration mode.

clear configure command-alias

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Release	Modification
7.0	This command was introduced.

Usage Guidelines This command has no usage guidelines.

Examples The following example shows how to remove all non-default command aliases:

```
hostname(config)# clear configure command-alias
```

Command	Description
command-alias	Creates a command alias.
show running-config command-alias	Displays all non-default command aliases.

clear configure console

To reset the console connection settings to defaults, use the **clear configure console** command in global configuration mode.

clear configure console

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Release	Modification
7.0	This command was introduced.

Examples The following example shows how to reset the console connection settings to defaults:

```
hostname(config)# clear configure console
```

Related Commands	Command	Description
	console timeout	Sets the idle timeout for a console connection to the security appliance.
	show running-config console timeout	Displays the idle timeout for a console connection to the security appliance.

clear configure context

To clear all context configurations in the system configuration, use the **clear configure context** command in global configuration mode.

clear configure context [noconfirm]

Syntax Description

noconfirm (Optional) Removes all contexts without prompting you for confirmation. This option is useful for automated scripts.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command lets you remove all contexts, including the admin context. The admin context cannot be removed using the **no context** command, but can be removed using the **clear configure context** command.

Examples

The following example removes all contexts from the system configuration, and does not confirm the deletion:

```
hostname(config)# clear configure context noconfirm
```

Related Commands

Command	Description
admin-context	Sets the admin context.
changeto	Changes between contexts or the system execution space.
context	Creates a security context in the system configuration and enters context configuration mode.

Command	Description
mode	Sets the context mode to single or multiple.
show context	Shows a list of contexts (system execution space) or information about the current context.

clear configure crypto

To remove the entire crypto configuration, including IPsec, crypto maps, dynamic crypto maps, CA trustpoints, all certificates, certificate map configurations, and ISAKMP, use the **clear configure crypto** command in global configuration. To remove specific configurations, use this command with keywords as shown in the syntax. Take caution when using this command.

clear configure crypto [**ca** | **dynamic-map** | **ipsec** | **isakmp** | **map**]

Syntax Description

ca	Removes certification authority policy.
dynamic-map	Removes dynamic crypto map configuration.
ipsec	Removes IPsec configuration.
isakmp	Removes ISAKMP configuration.
map	Removes crypto map configuration.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example issued in global configuration mode, removes all of the crypto configuration from the security appliance:

```
hostname(config)# clear configure crypto
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto dynamic-map	Clears all or specified crypto dynamic maps from the configuration.
clear configure crypto map	Clears all or specified crypto maps from the configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
show running-config crypto	Displays the entire crypto configuration, including IPsec, crypto maps, dynamic crypto maps, and ISAKMP.

clear configure crypto ca trustpoint

To remove all trustpoints from the configuration, use the **clear configure crypto ca trustpoint** command in global configuration.

clear configure crypto ca trustpoint

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Command History

Examples The following example entered in global configuration mode, removes all trustpoints from the configuration:

```
hostname(config)# clear configure crypto ca trustpoint
hostname(config)#
```

Command	Description
crypto ca trustpoint	Enters the trustpoint subconfiguration level for the indicated trustpoint.

Related Commands

clear configure crypto dynamic-map

To remove all or specified crypto dynamic maps from the configuration, use the **clear configure crypto dynamic-map** command in global configuration.

clear configure crypto dynamic-map *dynamic-map-name* *dynamic-seq-num*

Syntax Description

<i>dynamic-map-name</i>	Specifies the name of a specific crypto dynamic map.
<i>dynamic-seq-num</i>	Specifies the sequence number of the crypto dynamic map.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example entered in global configuration mode, removes the crypto dynamic map mymaps with sequence number 3 from the configuration:

```
hostname(config)# clear configure crypto dynamic-map mymaps 3
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto map	Clears the configuration of all or specified crypto maps.
show running-config crypto map	Displays all the active configuration for all dynamic crypto maps.
show running-config crypto map	Displays all the active configuration for all crypto maps.

clear configure crypto map

To remove all or specified crypto maps from the configuration, use the **clear configure crypto map** command in global configuration.

clear configure crypto map *map-name seq-num*

Syntax Description

<i>map-name</i>	Specifies the name of a specific crypto map.
<i>seq-num</i>	Specifies the sequence number of the crypto map.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example entered in global configuration mode, removes the crypto map mymaps with sequence number 3 from the configuration:

```
hostname(config)# clear configure crypto map mymaps 3
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto dynamic-map	Clears the configuration of all or specified crypto dynamic maps.
crypto map interface	Applies a crypto map to an interface.
show running-config crypto map	Displays the active configuration for all crypto maps.
	Displays the active configuration for all dynamic crypto maps.

clear configure dhcpd

To clear all of the DHCP server commands, binding, and statistics, use the **clear configure dhcpd** command in global configuration mode.

clear configure dhcpd

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
7.0	This command was changed from clear dhcpd to clear configure dhcpd .

Usage Guidelines The **clear configure dhcpd** command clears all of the **dhcpd** commands, bindings, and statistical information. To clear only the statistic counters or binding information, use the **clear dhcpd** command.

Examples The following example shows how to clear all **dhcpd** commands:

```
hostname(config)# clear configure dhcpd
```

Related Commands	Command	Description
	clear dhcpd	Clears the DHCP server bindings and statistic counters.
	show running-config dhcpd	Displays the current DHCP server configuration.

clear configure dhcprelay

To clear all of the DHCP relay configuration, use the **clear configure dhcprelay** command in global configuration mode.

clear configure dhcprelay

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	•	—

Release	Modification
7.0	This command was changed from clear dhcprelay to clear configure dhcprelay .

Usage Guidelines The **clear configure dhcprelay** command clears the DHCP relay statistics and configuration. To clear only the DHCP statistic counters, use the **clear dhcprelay statistics** command.

Examples The following example shows how to clear the DHCP relay configuration:

```
hostname(config)# clear configure dhcprelay
```

Related Commands	Command	Description
	clear dhcprelay statistics	Clears the DHCP relay agent statistic counters.
	debug dhcprelay	Displays debug information for the DHCP relay agent.
	show dhcprelay statistics	Displays DHCP relay agent statistic information.
	show running-config dhcprelay	Displays the current DHCP relay agent configuration.

clear configure dns

To clear all DNS commands, use the **clear configure dns** command in global configuration mode.

clear configure dns

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following example clears all DNS commands:

```
hostname(config)# clear configure dns
```

Related Commands	Command	Description
	show running-config dns-server-group	Shows the currently running DNS configuration.

clear configure established

To remove all established commands, use the **clear configure established** command in global configuration mode.

clear configure established

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Release	Modification
7.0	The keyword configure was added.

Usage Guidelines To remove an established connection created by the **established** command, enter the **clear xlate** command.

Examples This example shows how to remove established commands:

```
hostname(config)# clear configure established
```

Command	Description
established	Permits return connections on ports that are based on an established connection.
show running-config established	Displays the allowed inbound connections that are based on established connections.
clear xlate	Clears the current translation and connection slot information.

clear configure failover

To remove **failover** commands from the configuration and restore the defaults, use the **clear configure failover** command in global configuration mode.

clear configure failover

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History	Release	Modification
	7.0	Command was changed from clear failover to clear configure failover .

Usage Guidelines This command clears all **failover** commands from the running configuration and restores the defaults. If you use the **all** keyword with the **show running-config failover** command, you will see the default failover configuration.

The **clear configure failover** command is not available in a security context in multiple configuration mode; you must enter the command in the system execution space.

Examples The following example clears all failover commands from the configuration:

```
hostname(config)# clear configure failover
hostname(config)# show running-configuration failover
no failover
```

Related Commands	Command	Description
	show running-config failover	Displays the failover commands in the running configuration.

clear configure filter

To clear URL, FTP, and HTTPS filtering configuration, use the **clear configure filter** command in global configuration mode.

clear configure filter

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **clear configure filter** command clears the URL, FTP, and HTTPS filtering configuration.

Examples

The following example clears the URL, FTP, and HTTPS filtering configuration:

```
hostname# clear configure filter
```

Related Commands

Commands	Description
filter ftp	Identifies the FTP traffic to be filtered by a URL filtering server.
filter https	Identifies the HTTPS traffic to be filtered by a Websense server.
filter url	Directs traffic to a URL filtering server.
show running-config filter	Displays the filtering configuration.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

clear configure fips

To clear the system or module FIPS configuration information stored in NVRAM, use the **clear configure fips** command.

clear configure fips

Syntax Description

fips FIPS-2 compliance information

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	—	—	•	—	—

Command History

Release	Modification
7.0(4)	This command was introduced.

Examples

```
sw8-ASA(config)# clear configure fips
```

Related Commands

Command	Description
crashinfo console disable	Disables the reading, writing and configuration of crash write info to flash.
fips enable	Enables or disablea policy-checking to enforce FIPS compliance on the system or module.
fips self-test poweron	Executes power-on self-tests.
show crashinfo console	Reads, writes, and configures crash write to flash.
show running-config fips	Displays the FIPS configuration that is running on the security appliance.

clear configure firewall

To set the firewall mode to the default routed mode, use the **clear configure firewall** command in global configuration mode.

clear configure firewall

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples The following example sets the firewall mode to the default:

```
hostname(config)# clear configure firewall
```

Related Commands

Command	Description
arp	Adds a static ARP entry.
firewall transparent	Sets the firewall mode to transparent.
show arp statistics	Shows ARP statistics.
show running-config arp	Shows the current configuration of the ARP timeout.

clear configure fixup

To clear the fixup configuration, use the **clear configure fixup** command in global configuration mode.

clear configure fixup

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **clear configure fixup** command removes the fixup configuration.

Examples

The following example clears the fixup configuration:

```
hostname# clear configure fixup
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
policy-map	Associates a class map with specific security actions.

clear configure fragment

To reset all the IP fragment reassembly configurations to defaults, use the **clear configure fragment** command in global configuration mode.

clear configure fragment [*interface*]

Syntax Description

interface (Optional) Specifies the security appliance interface.

Defaults

If an *interface* is not specified, the command applies to all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	The configure keyword and optional <i>interface</i> argument were added. The command was also separated into two commands, clear fragment and clear configure fragment , to separate clearing of the configuration data from the operational data.

Usage Guidelines

The **clear configure fragment** command resets all the IP fragment reassembly configurations to defaults. In addition, the the **chain**, **size**, and **timeout** keywords are reset to their default values, which are as follows:

- **chain** is 24 packets
- **size** is 200
- **timeout** is 5 seconds

Examples

This example shows how to reset all the IP fragment reassembly configurations to defaults:

```
hostname(config)# clear configure fragment
```

Related Commands

Command	Description
clear fragment	Clears the operational data of the IP fragment reassembly module.
fragment	Provides additional management of packet fragmentation and improves compatibility with NFS.

Command	Description
show fragment	Displays the operational data of the IP fragment reassembly module.
show running-config fragment	Displays the IP fragment reassembly configuration.

clear configure ftp

To clear the FTP configuration, use the **clear configure ftp** command in global configuration mode.

clear configure ftp

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **clear configure ftp** command clears the FTP configuration.

Examples

The following example clears the FTP configuration:

```
hostname# clear configure filter
```

Related Commands

Commands	Description
filter ftp	Identifies the FTP traffic to be filtered by a URL filtering server.
filter https	Identifies the HTTPS traffic to be filtered by a Websense server.
filter url	Directs traffic to a URL filtering server.
show running-config filter	Displays the filtering configuration.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

clear configure ftp-map

To clear the FTP map configuration, use the **clear configure ftp-map** command in global configuration mode.

clear configure ftp-map

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **clear configure ftp-map** command removes the FTP map configuration.

Examples

The following example clears the FTP map configuration:

```
hostname# clear configure ftp-map
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
ftp-map	Defines an FTP map and enables FTP map configuration mode.
inspect ftp	Applies a specific FTP map to use for application inspection.
request-command deny	Specifies FTP commands to disallow.

clear configure global

To remove the **global** commands from the configuration, use the **clear configure global** command in global configuration mode.

clear configure global

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	•	—

Release	Modification
7.0	Added keyword configure .

Command History

Examples The following example shows how to remove the **global** commands from the configuration:

```
hostname(config)# clear configure global
```

Command	Description
global	Creates entries from a pool of global addresses.
show running-config global	Displays the global commands in the configuration.

Related Commands

clear configure group-policy

To remove the configuration for a particular group policy, use the **clear configure group-policy** command in global configuration mode, and append the name of the group policy. To remove all group-policy commands from the configuration except the default group policy, use this command without arguments.

clear configure group-policy [*name*]

Syntax Description

<i>name</i>	Specifies the name of the group policy.

Defaults

Remove all group-policy commands from the configuration, except the default group policy.

Command Modes

The following table shows the modes in which you can enter the command:

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to clear the configuration for the group policy named FirstGroup.

```
hostname(config)# clear configure group-policy FirstGroup
```

Related Commands

Command	Description
group-policy	Creates, edits, or removes a group policy.
group-policy attributes	Enters group-policy attributes mode, which lets you configure AVPs for a specified group policy.
show running-config group-policy	Displays the running configuration for a particular group policy or for all group policies.

clear configure gtp-map

To clear GTP map configuration, use the **clear configure gtp-map** command in global configuration mode.

clear configure gtp-map

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **clear configure gtp -map** command removes the GTP map configuration.

Examples

The following example clears GTP map configuration:

```
hostname# clear configure gtp-map
```

Related Commands

Commands	Description
clear service-policy inspect gtp	Clears global GTP statistics.
debug gtp	Displays detailed information about GTP inspection.
gtp-map	Defines a GTP map and enables GTP map configuration mode.
inspect gtp	Applies a specific GTP map to use for application inspection.
show service-policy inspect gtp	Displays the GTP configuration.

clear configure http

To disable the HTTP server and to remove configured hosts that can access the HTTP server, use the **clear configure http** command in global configuration mode.

clear configure http

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to clear the HTTP configuration.

```
hostname(config)# clear configure http
```

Related Commands

Command	Description
http	Specifies hosts that can access the HTTP server by IP address and subnet mask. Specifies the security appliance interface through which the host accesses the HTTP server.
http authentication-certificate	Requires authentication via certificate from users who are establishing HTTPS connections to the security appliance.
http redirect	Specifies that the security appliance redirect HTTP connections to HTTPS.
http server enable	Enables the HTTP server.
show running-config http	Displays the hosts that can access the HTTP server, and whether or not the HTTP server is enabled.

clear configure http-map

To clear HTTP map configuration, use the **clear configure http-map** command in global configuration mode.

clear configure http-map

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **clear configure http-map** command removes the HTTP map configuration.

Examples

The following example clears the HTTP map configuration:

```
hostname# clear configure http-map
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug http-map	Displays detailed information about traffic associated with an HTTP map.
http-map	Defines an HTTP map for configuring enhanced HTTP inspection.
inspect http	Applies a specific HTTP map to use for application inspection.
policy-map	Associates a class map with specific security actions.

clear configure icmp

To clear the configured access rules for ICMP traffic, use the **clear configure icmp** command in global configuration mode.

clear configure icmp

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **clear configure icmp** command clears the configured access rules for ICMP traffic.

Examples

The following example clears the clear configured access rules for ICMP traffic:

```
hostname# clear configure icmp
```

Related Commands

Commands	Description
clear configure icmp	Clears the ICMP configuration.
debug icmp	Enables the display of debug information for ICMP.
show icmp	Displays ICMP configuration.
timeout icmp	Configures the idle timeout for ICMP.

clear configure imap4s

To remove all IMAP4S commands from the configuration, reverting to default values, use the **clear configure imap4s** command in global configuration mode.

clear configure imap4s

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Examples The following example shows how to remove the IMAP4S configuration:

```
hostname(config)# clear configure imap4s
hostname(config)#
```

Related Commands	Command	Description
	show running-config imap4s	Displays the running configuration for IMAP4S.
	imap4s	Creates or edits an IMAP4S e-mail proxy configuration.

clear configure interface

To clear the interface configuration, use the **clear configure interface** command in global configuration mode.

clear configure interface [*physical_interface*[.*subinterface*] | *mapped_name* | *interface_name*]

Syntax Description

<i>interface_name</i>	(Optional) Identifies the interface name set with the nameif command.
<i>mapped_name</i>	(Optional) In multiple context mode, identifies the mapped name if it was assigned using the allocate-interface command.
<i>physical_interface</i>	(Optional) Identifies the interface ID, such as gigabitethernet0/1 . See the interface command for accepted values.
<i>subinterface</i>	(Optional) Identifies an integer between 1 and 4294967293 designating a logical subinterface.

Defaults

If you do not specify an interface, the security appliance clears all interface configuration.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was changed from clear interface . This command was also modified to include the new interface numbering scheme.

Usage Guidelines

When you clear the interface configuration for main physical interfaces, the security appliance uses the default settings.

You cannot use the interface name in the system execution space, because the **nameif** command is only available within a context. Similarly, if you mapped the interface ID to a mapped name using the **allocate-interface** command, you can only use the mapped name in a context.

Examples

The following example clears the GigabitEthernet0/1 configuration:

```
hostname(config)# clear configure interface gigabitethernet0/1
```

The following example clears the inside interface configuration:

```
hostname(config)# clear configure interface inside
```

The following example clears the int1 interface configuration in a context. “int1” is a mapped name.

```
hostname/contexta(config)# clear configure interface int1
```

The following example clears all interface configuration.

```
hostname(config)# clear configure interface
```

Related Commands

Command	Description
allocate-interface	Assigns interfaces and subinterfaces to a security context.
clear interface	Clears counters for the show interface command.
interface	Configures an interface and enters interface configuration mode.
show interface	Displays the runtime status and statistics of interfaces.

clear configure ip

To clear all IP addresses set by the **ip address** command, use the **clear configure ip** command in global configuration mode.

clear configure ip

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
1.1(1)	Support for this command was introduced.

Command History

Usage Guidelines In transparent firewall mode, this command clears the management IP address.

If you want to stop all current connections that use the old IP addresses, enter the **clear xlate** command. Otherwise, the connections time out as usual.

Examples The following example clears all IP addresses:

```
hostname(config)# clear configure ip
```

Command	Description
allocate-interface	Assigns interfaces and subinterfaces to a security context.
clear configure interface	Clears all configuration for an interface.
interface	Configures an interface and enters interface configuration mode.
ip address	Sets the IP address for the interface.
show running-config interface	Displays the interface configuration.

Related Commands

clear configure ip audit

To clear the entire audit policy configuration, use the **clear configure ip audit** command in global configuration mode.

clear configure ip audit [configuration]

Syntax Description	configuration (Optional) You can enter this keyword, but the effect is the same without it.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was changed from clear ip audit .

Examples	The following example clears all ip audit commands:

```
hostname# clear configure ip audit
```

Related Commands	Command	Description
	ip audit attack	Sets the default actions for packets that match an attack signature.
	ip audit info	Sets the default actions for packets that match an informational signature.
	ip audit interface	Assigns an audit policy to an interface.
	ip audit name	Creates a named audit policy that identifies the actions to take when a packet matches an attack signature or an informational signature.
	ip audit signature	Disables a signature.

clear configure ip local pool

To remove IP address pools, use the **clear configure ip local pool** command in global configuration mode.

clear ip local pool [*poolname*]

Syntax Description

poolname (Optional) Specifies the name of the IP address pool.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example removes all IP address pools from the running configuration:

```
hostname(config)# clear config ip local pool
hostname(config)#
```

Related Commands

Command	Description
clear configure ip local pool	Removes all ip local pools.
ip local pool	Configures an IP address pool.

clear configure ip verify reverse-path

To clear the **ip verify reverse-path** configuration, use the **clear configure ip verify reverse-path** command in global configuration mode.

clear configure ip verify reverse-path

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was changed from clear ip verify reverse-path .

Examples The following example clears the **ip verify reverse-path** configuration for all interfaces:

```
hostname(config)# clear configure ip verify reverse-path
```

Related Commands	Command	Description
	clear ip verify statistics	Clears the Unicast RPF statistics.
	ip verify reverse-path	Enables the Unicast Reverse Path Forwarding feature to prevent IP spoofing.
	show ip verify statistics	Shows the Unicast RPF statistics.
	show running-config ip verify reverse-path	Shows the ip verify reverse-path configuration.

clear configure ipv6

To clear the global IPv6 commands from the running configuration, use the **clear configure ipv6** command in global configuration mode.

clear configure ipv6 [**route** | **access-list**]

Syntax Description

route	(Optional) Clears the commands that statically define routes in the IPv6 routing table from the running configuration.
access-list	(Optional) Clears the IPv6 access list commands from the running configuration.

Defaults

Without keywords, this command clears all IPv6 commands from the running configuration.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command only clears the global IPv6 commands from the running configuration; it does not clear the IPv6 commands entered in interface configuration mode.

Examples

The following example shows how to clear statically defined IPv6 routes from the IPv6 routing table:

```
hostname(config)# clear configure ipv6 route
hostname(config)#
```

Related Commands

Command	Description
ipv6 route	Defines a static route in the IPv6 routing table.
show ipv6 route	Displays the contents of the IPv6 routing table.
show running-config ipv6	Displays the IPv6 commands in the running configuration.

clear configure isakmp

To remove all of the ISAKMP configuration, use the **clear configure isakmp** command in global configuration mode.

clear configure isakmp

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Examples The following example issued in global configuration mode, removes all of the ISAKMP configuration from the security appliance:

```
hostname(config)# clear configure isakmp
hostname(config)#
```

Related Commands	Command	Description
	clear configure isakmp policy	Clears all ISAKMP policy configuration.
	isakmp enable	Enables ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance.
	show isakmp stats	Displays runtime statistics.
	show isakmp sa	Displays IKE runtime SA database with additional information.
	show running-config isakmp	Displays all the active configuration.

clear configure isakmp policy

To remove all of the ISAKMP policy configuration, use the **clear configure isakmp policy** command in global configuration mode.

clear configure isakmp policy *priority*

Syntax Description

priority Specifies the priority of the ISAKMP priority to be cleared.

Defaults

No default behaviour or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example removes the ISAKMP policy with priority 3 from the configuration:

```
hostname(config)# clear configure isakmp policy 3
hostname(config)#
```

Related Commands

Command	Description
isakmp enable	Enables ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance.
show isakmp stats	Displays runtime statistics.
show isakmp sa	Displays IKE runtime SA database with additional information.
show running-config isakmp	Displays all the active configuration.

clear configure logging

To clear the logging configuration, use the **clear configure logging** command in global configuration mode.

clear configure logging [**disabled** | **level** | **rate-limit**]

Syntax Description

disabled	(Optional) Indicates that all disabled system log messages should be re-enabled. When you use this option, no other logging configuration is cleared.
level	(Optional) Indicates that the severity level assignments for system log messages should be reset to their default values. When you use this option, no other logging configuration is cleared.
rate-limit	(Optional) Resets the logging rate limit.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.
7.0(4)	The rate-limit keyword was introduced.

Usage Guidelines

You can use the **show running-config logging** command to view all logging configuration. If you use the **clear configure logging** command without either the **disabled** or **level** keyword, all logging configuration is cleared.

Examples

The following example shows how to clear logging configuration. The output of the **show logging** command indicates that all logging features are disabled.

```
hostname(config)# clear configure logging
hostname(config)# show logging
Syslog logging: disabled
  Facility: 20
  Timestamp logging: disabled
  Standby logging: disabled
  Deny Conn when Queue Full: disabled
  Console logging: disabled
  Monitor logging: disabled
```

```
Buffer logging: disabled
Trap logging: disabled
History logging: disabled
Device ID: disabled
Mail logging: disabled
ASDM logging: disabled
```

Related Commands

Command	Description
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

clear configure mac-address-table

To clear the **mac-address-table static** and **mac-address-table aging-time** configuration, use the **clear configure mac-address-table** command in global configuration mode.

clear configure mac-address-table

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	—	•	•	•	—

Release	Modification
7.0	This command was introduced.

Examples The following example clears the **mac-address-table static** and **mac-address-table aging-time** configuration:

```
hostname# clear configure mac-address-table
```

Related Commands	Command	Description
	firewall transparent	Sets the firewall mode to transparent.
	mac-address-table aging-time	Sets the timeout for dynamic MAC address entries.
	mac-address-table static	Adds static MAC address entries to the MAC address table.
	mac-learn	Disables MAC address learning for an interface.
	show mac-address-table	Shows the MAC address table, including dynamic and static entries.

clear configure mac-learn

To clear the **mac-learn** configuration, use the **clear configure mac-learn** command in global configuration mode.

clear configure mac-learn

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	—	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples The following example clears the **mac-learn** configuration:

```
hostname# clear configure mac-learn
```

Related Commands	Command	Description
	firewall transparent	Sets the firewall mode to transparent.
	mac-address-table static	Adds static MAC address entries to the MAC address table.
	mac-learn	Disables MAC address learning for an interface.
	show mac-address-table	Shows the MAC address table, including dynamic and static entries.

clear configure mac-list

To remove the indicated list of MAC addresses, previously specified the **mac-list** command, use the **clear configure mac-list** command in global configuration mode:

clear configure mac-list *id*

Syntax Description

id A MAC address list name.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was modified to conform with CLI standards.

Usage Guidelines

To remove a list of MAC addresses, use the **clear mac-list** command.

Examples

The following example shows how to clear a MAC address list:

```
hostname(config)# clear configure mac-list firstmaclist
```

Related Commands

Command	Description
mac-list	Adds a list of MAC addresses using a first-match search.
show running-config mac-list	Displays the MAC addresses in the MAC address list indicated by the <i>id</i> value.

clear configure management-access

To remove the configuration of an internal interface for management access of the security appliance, use the **clear configure management-access** command in global configuration mode.

clear configure management-access

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History	Release	Modification
	7.0	The keyword configure was added.

Usage Guidelines The **management-access** command lets you define an internal management interface using the IP address of the firewall interface specified in *mgmt_if*. (The interface names are defined by the **nameif** command and displayed in quotes, “ ”, in the output of the **show interface** command.) The **clear configure management-access** command removes the configuration of the internal management interface specified with the **management-access** command.

Examples The following example removes the configuration of an internal interface for management access of the security appliance:

```
hostname(config)# clear configure management-access
```

Related Commands	Command	Description
	management-access	Configures an internal interface for management access.
	show running-config management-access	Displays the name of the internal interface configured for management access.

clear configure mgcp-map

To clear the MGCP map configuration, use the **clear configure mgcp-map** command in global configuration mode.

clear configure mgcp-map

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **clear configure mgcp-map** clears the MGCP map configuration.

Examples

The following example clears clear the MGCP map configuration:

```
hostname# clear configure mgcp-map
```

Related Commands

Commands	Description
debug mgcp	Enables MGCP debug information.
mgcp-map	Defines an MGCP map and enables MGCP map configuration mode.
show conn	Displays the connection state for different connection types.
show mgcp	Displays information about MGCP sessions established through the security appliance.
timeout	Sets the maximum idle time duration for different protocols and session types.

clear configure mroute

To remove the **mroute** commands from the running configuration, use the **clear configure mroute** command in global configuration mode.

clear configure mroute

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following example shows how to remove the **mroute** commands from the configuration:

```
hostname(config)# clear configure mroute
hostname(config)#
```

Related Commands	Command	Description
	mroute	Configures a static multicast route.
	show mroute	Displays IPv4 multicast routing table.
	show running-config mroute	Displays the mroute commands in the running configuration.

clear configure mtu

To clear the configured maximum transmission unit values on all interfaces, use the **clear configure mtu** command in global configuration mode.

clear configure mtu

Syntax Description

This command has no arguments or keywords.

Defaults

Using the **clear configure mtu command** sets the maximum transmission unit to the default of 1500 for all ethernet interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	—	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example clears the current maximum transmission unit values on all interfaces:

```
hostname(config)# clear configure mtu
```

Related Commands

Command	Description
mtu	Specifies the maximum transmission unit for an interface.
show running-config mtu	Displays the current maximum transmission unit block size.

clear configure multicast-routing

To remove the **multicast-routing** command from the running configuration, use the **clear configure multicast-routing** command in global configuration mode.

clear configure multicast-routing

Syntax Description There are no keywords or arguments for this command.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Usage Guidelines The **clear configure multicast-routing** command removes the **multicast-routing** from the running configuration. The **no multicast-routing** command also removes the multicast-routing command from the running configuration.

Examples The following example shows how to remove the **multicast-routing** command from the running configuration:

```
hostname(config)# clear configure multicast-routing
```

Command	Description
multicast-routing	Enables multicast routing on the security appliance.

clear configure name

To clear the list of names from the configuration, use the **clear configure name** command in global configuration mode.

clear configure name

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
7.0	The keyword configure was added.

Usage Guidelines This command has no usage guidelines.

Examples The following example shows how to clear the name list:

```
hostname(config)# clear configure name
```

Command	Description
name	Associates a name with an IP address.
show running-config name	Displays the list of names associated with IP addresses.

clear configure nat

To remove the NAT configuration, use the **clear configure nat** command in privileged EXEC mode.

clear configure nat

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Release	Modification
7.0	Added keyword configure .

Usage Guidelines The following applies to transparent firewall mode:



Note

In transparent firewall mode, only NAT id 0 is valid.

Examples The following example shows how to remove the NAT configuration:

```
hostname(config)# clear configure nat
```

Related Commands	Command	Description
	nat	Associates a network with a pool of global IP addresses.
	show running-config nat	Displays a pool of global IP addresses that are associated with the network.

clear configure ntp

To clear the NTP configuration, use the **clear configure ntp** command in global configuration mode.

clear configure ntp

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	•

Release	Modification
7.0	This command was changed from clear ntp .

Command History

Examples The following example clears all **ntp** commands:

```
hostname# clear configure ntp
```

Command	Description
ntp authenticate	Enables NTP authentication.
ntp authentication-key	Sets the NTP authentication key.
ntp server	Identifies an NTP server to set the time on the security appliance.
ntp trusted-key	Specifies the NTP trusted key.
show running-config ntp	Shows the NTP configuration.

Related Commands

clear configure object-group

To remove all the **object group** commands from the configuration, use the **clear configure object-group** command in global configuration mode.

clear configure object-group [{ **protocol** | **service** | **icmp-type** | **network** }]

Syntax Description

icmp-type	(Optional) Clears all ICMP groups.
network	(Optional) Clears all network groups.
protocol	(Optional) Clears all protocol groups.
service	(Optional) Clears all service groups.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example shows how to remove all the **object-group** commands from the configuration:

```
hostname(config)# clear configure object-group
```

Related Commands

Command	Description
group-object	Adds network object groups.
network-object	Adds a network object to a network object group.
object-group	Defines object groups to optimize your configuration.
port-object	Adds a port object to a service object group.
show running-config object-group	Displays the current object groups.

clear configure passwd

To clear the login password configuration and restore the default setting of “cisco,” use the **clear configure passwd** command in global configuration mode.

clear configure {passwd | password}

Syntax Description

passwd | password You can enter either command; they are aliased to each other.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was changed from clear passwd .

Examples

The following example clears the login password and restores it to the default of “cisco”:

```
hostname(config)# clear configure passwd
```

Related Commands

Command	Description
enable	Enters privileged EXEC mode.
enable password	Sets the enable password.
passwd	Sets the login password.
show curpriv	Shows the currently logged in username and the user privilege level.
show running-config passwd	Shows the login password in encrypted form.

clear configure pim

To clear all of the global **pim** commands from the running configuration, use the **clear configure pim** command in global configuration mode.

clear configure pim

Syntax Description There are no keywords or arguments for this command.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Command History

Usage Guidelines The **clear configure pim** command clears all of the **pim** commands from the running configuration. To clear PIM traffic counters and topology information, use the **clear pim counters** and the **clear pim topology** commands.

The **clear configure pim** command only clears the **pim** commands entered in global configuration mode; it does not clear the interface-specific **pim** commands.

Examples The following example shows how to clear all **pim** commands from the running configuration:

```
hostname(config)# clear configure pim
```

Command	Description
clear pim topology	Clears the PIM topology table.
clear pim counters	Clears the PIM traffic counters.
show running-config pim	Displays the pim commands in the running configuration.

Related Commands

clear configure policy-map

To remove the policy-map specification from the configuration, use the **clear configure policy-map** command in global configuration mode.

clear configure policy-map

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
7.0	This command was introduced.

Examples This example shows the **clear configure policy-map** command:

```
hostname(config)# clear configure policy-map
```

Related Commands	Command	Description
	policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
	show running-config policy-map	Displays the entire policy configuration.

clear configure pop3s

To remove all POP3S commands from the configuration, reverting to default values, use the **clear configure pop3s** command in global configuration mode.

clear configure pop3s

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following example shows how to remove the POP3S configuration:

```
hostname(config)# clear configure pop3s
hostname(config)#
```

Related Commands	Command	Description
	show running-config pop3s	Displays the running configuration for POP3S.
	pop3s	Creates or edits a POP3S e-mail proxy configuration.

clear configure port-forward

To remove a configured set of applications that WebVPN users access over forwarded TCP ports, use the **clear configure port-forward** command in global configuration mode. To remove all configured applications, use this command without the *listname* argument. To remove only the applications for a specific list, use this command with that *listname*.

clear configure port-forward [*listname*]

Syntax Description

<i>listname</i>	Groups the set of applications (forwarded TCP ports) WebVPN users can access. Maximum 64 characters.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to remove the portforwarding list called *SalesGroupPorts*.

```
hostname(config)# clear configure port-forward SalesGroupPorts
```

Related Commands

Command	Description
port-forward	Use this command in webvpn configuration mode to configure the set of applications that WebVPN users can access.
port-forward	Use this command in webvpn mode to enable WebVPN application access for a user or group policy.
show running-configuration port-forward	Displays the current set of configured port-forward commands.

clear configure prefix-list

To remove the **prefix-list** commands from the running configuration, use the **clear configure prefix-list** command in global configuration mode.

clear configure prefix-list [*prefix-list-name*]

Syntax Description

prefix-list-name (Optional) The name of a prefix list. When a prefix list name is specified, only the commands for that prefix list are removed from the configuration.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was changed from clear prefix-list to clear configure prefix-list .

Usage Guidelines

The **clear configure prefix-list** command removes the **prefix-list** commands and the **prefix-list description** commands from the running configuration. If a prefix list name is specified, then the **prefix-list** command and **prefix-list description** command, if present, for that prefix list only are removed from the running configuration.

This command does not remove the **no prefix-list sequence** command from the running configuration.

Examples

The following example removes all **prefix-list** commands from the running configuration for a prefix list named MyPrefixList:

```
hostname# clear configure prefix-list MyPrefixList
```

Related Commands

Command	Description
show running-config prefix-list	Displays the prefix-list commands in the running configuration.

clear configure priority-queue

To remove the priority queue specification from the configuration, use the **clear configure priority-queue** command in global configuration mode.

clear configure priority queue *interface-name*

Syntax Description

<i>interface-name</i>	Specifies the name of the interface for which you want to show the priority queue details

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

This example shows the use of the **clear configure priority-queue** command to remove the priority-queue configuration on the interface named test:

```
hostname(config)# clear configure priority-queue test
```

Related Commands

Command	Description
priority-queue	Configures priority queueing on an interface.
show running-config priority-queue	Displays the current priority-queue configuration for the named interface.

clear configure privilege

To remove the configured privilege levels for commands, use the **clear configure privilege** command in global configuration mode.

clear configure privilege

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was modified to conform to CLI guidelines.

Usage Guidelines There is no undo.

Examples This example shows how to reset the configured privilege levels for the commands:

```
hostname(config)# clear configure privilege
```

Related Commands	Command	Description
	privilege	Configures the command privilege levels.
	show curpriv	Displays current privilege level
	show running-config privilege	Displays privilege levels for commands.

clear configure rip

To clear the **rip** commands from the running configuration, use the **clear configure rip** command in global configuration mode.

clear configure rip

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Release	Modification
7.0	This command was changed from clear rip to clear configure rip .

Usage Guidelines The **clear configure rip** command removes all **rip** commands from the configuration. Use the **no** form of the commands to clear specific commands.

Examples The following example clears all RIP commands from the running configuration:

```
hostname(config)# clear configure rip
```

Command	Description
debug rip	Displays debug information for RIP.
rip	Configures RIP on the specified interface.
show running-config rip	Displays the RIP commands in the running configuration.

clear configure route

To remove the **route** commands from the configuration that do not contain the **connect** keyword, use the **clear configure route** command in global configuration mode.

clear configure route [*interface_name* *ip_address* [*netmask* *gateway_ip*]]

Syntax Description

<i>gateway_ip</i>	(Optional) Specifies the IP address of the gateway router (the next hop address for this route).
<i>interface_name</i>	(Optional) Internal or external network interface name.
<i>ip_address</i>	(Optional) Internal or external network IP address.
<i>netmask</i>	(Optional) Specifies a network mask to apply to the <i>ip_address</i> .

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	Added keyword configure .

Usage Guidelines

Use **0.0.0.0** to specify a default route. You can abbreviate the 0.0.0.0 IP address as **0** and the 0.0.0.0 *netmask* as **0**.

Examples

The following example shows how to remove the **route** commands from the configuration that do not contain the **connect** keyword:

```
hostname(config)# clear configure route
```

Related Commands

Command	Description
route	Specifies a static or default route for the an interface.
show route	Displays route information.
show running-config route	Displays configured routes.

clear configure route-map

To remove all of the route maps, use the **clear configure route-map** command in global configuration mode.

clear configure route-map

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines Use the **clear configure route-map** command in global configuration mode to remove all **route-map** commands in the configuration. The **route-map** command is used to configure conditions of redistributing the routes from one routing protocol into another routing protocol.

To remove individual **route-map** commands, use the **no route-map** command.

Examples The following example shows how to remove the conditions of redistributing routes from one routing protocol into another routing protocol:

```
hostname(config)# clear configure route-map
```

Related Commands	Command	Description
	route-map	Defines the conditions for redistributing routes from one routing protocol into another.
	show running-config route-map	Displays the information about the route map configuration.

clear configure router

To clear all router commands from the running configuration, use the **clear configure router** command in global configuration mode.

clear configure router [*ospf id*]

Syntax Description

<i>id</i>	The OSPF process ID.
ospf	Specifies that only OSPF commands are removed from the configuration.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was changed from the clear router command to the clear configure router command.

Examples

The following example clears all OSPF commands associated with OSPF process 1 from the running configuration:

```
hostname(config)# clear configure router ospf 1
hostname(config)#
```

Related Commands

Command	Description
show running-config router	Displays the commands in the global router configuration.

clear configure service-policy

To clear the service policy configuration for enabled policies, use the **clear configure service-policy** command in privileged EXEC mode.

clear configure service-policy

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
PIX Version 7.0	This command was introduced.

Examples

The following is an example of the **clear service-policy** command:

```
hostname(config)# clear configure service-policy
```

Related Commands

Command	Description
show service-policy	Displays the service policy.
show running-config service-policy	Displays the service policies configured in the running configuration.
service-policy	Configures the service policy.
clear service-policy	Clears service policy statistics.

clear configure smtps

To remove all SMTPS commands from the configuration, reverting to default values, use the **clear configure smtps** command in global configuration mode.

clear configure smtps

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following example shows how to remove the SMTPS configuration:

```
hostname(config)# clear configure smtps
hostname(config)#
```

Related Commands	Command	Description
	show running-configuration smtps	Displays the running configuration for SMTPS.
	smtps	Creates or edits an SMTPS e-mail proxy configuration

clear configure snmp-map

To clear the SNMP map configuration, use the **clear configure snmp-map** command in global configuration mode.

clear configure snmp-map

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **clear configure snmp-map** command removes the SNMP map configuration.

Examples

The following example clears the SNMP map configuration:

```
hostname# clear configure snmp-map
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
deny version	Disallows traffic using a specific version of SNMP.
inspect snmp	Enable SNMP application inspection.
snmp-map	Defines an SNMP map and enables SNMP map configuration mode.

clear configure snmp-server

To disable the Simple Network Management Protocol (SNMP) server, use the **clear configure snmp-server** command in global configuration mode.

clear configure snmp-server

Syntax Description This command has no arguments or keywords.

Defaults This command has no default settings.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Release	Modification
7.0	Support for this command was introduced on the security appliance.

Examples This example shows how to disable the SNMP server:

```
hostname #clear snmp-server
```

Command	Description
snmp-server	Provides the security appliance event information through SNMP.
show snmp-server statistics	Displays information about the SNMP server configuration.

clear configure ssh

To clear all SSH commands from the running configuration, use the **clear configure ssh** command in global configuration mode.

clear configure ssh

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
7.0	This command was changed from the clear ssh command to the clear configure ssh command.

Usage Guidelines This command clears all SSH commands from the configuration. To clear specific commands, use the **no** form of those commands.

Examples The following example clears all SSH commands from the configuration:

```
hostname(config)# clear configure ssh
```

Command	Description
show running-config ssh	Displays the current SSH commands in the running configuration.
ssh	Allows SSH connectivity to the security appliance from the specified client or network.
ssh scopy enable	Enables a secure copy server on the security appliance.
ssh timeout	Sets the timeout value for idle SSH sessions.
ssh version	Restricts the security appliance to using either SSH Version 1 or SSH Version 2.

clear configure ssl

To remove all SSL commands from the configuration, reverting to default values, use the **clear config ssl** command in global configuration mode.

clear config ssl

Defaults

By default:

- Both the SSL client and SSL server versions are **any**.
- SSL encryption is 3des-sha1 | des-sha1 | rc4-md5, in that order.
- There is no trust point association; the security appliance uses the default RSA key-pair certificate.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to use the **clear config ssl** command:

```
hostname(config)# clear config ssl
```

Related Commands

Command	Description
show running-config ssl	Displays the current set of configured ssl commands.
ssl client-version	Specifies the SSL/TLS protocol version the security appliance uses when acting as a client.
ssl server-version	Specifies the SSL/TLS protocol version the security appliance uses when acting as a server
ssl trust-point	Specifies the certificate trust point that represents the SSL certificate for an interface

clear configure static

To remove all the **static** commands from the configuration, use the **clear configure static** command in global configuration mode.

clear configure static

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
7.0	The keyword configure was added.

Command History

Examples This example shows how to remove all the **static** commands from the configuration:

```
hostname(config)# clear configure static
```

Command	Description
show running-config static	Displays all static commands in the configuration.
static	Configures a persistent one-to-one address translation rule by mapping a local IP address to a global IP address.

Related Commands

clear configure sunrpc-server

To clear the remote processor call services from the security appliance, use the **clear configure sunrpc-server** command in global configuration mode.

clear configure sunrpc-server [**active**]

Syntax Description	active	(Optional) Identifies the SunRPC services that are currently active on the security appliance.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines	The sunrpc-server command displays the configured router ospf commands.



Note

If the highest-level IP address on the security appliance is a private address, this address is sent in hello packets and database definitions. To prevent this action, set the **router-id** *ip_address* to a global address.

Examples	The following example shows how to clear the SunRPC services from the security appliance: hostname(config)# clear configure sunrpc-server active

Related Commands	Command	Description
	sunrpc-server	Creates the SunRPC services table.
	show running-config sunrpc-server	Displays the information about the SunRPC configuration.

clear configure sysopt

To clear the configuration for all **sysopt** commands, use the **clear configure sysopt** command in global configuration mode.

clear configure sysopt

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
7.0	This command was changed from clear sysopt .

Examples The following example clears all **sysopt** command configuration:

```
hostname(config)# clear configure sysopt
```

Related Commands	Command	Description
	show running-config sysopt	Shows the sysopt command configuration.
	sysopt connection permit-ipsec	Permits any packets that come from an IPSec tunnel without checking any ACLs for interfaces.
	sysopt connection tcpmss	Overrides the maximum TCP segment size or ensures that the maximum is not less than a specified size.
	sysopt connection timewait	Forces each TCP connection to linger in a shortened TIME_WAIT state after the final normal TCP close-down sequence.
	sysopt nodnsalias	Disables alteration of the DNS A record address when you use the alias command.

clear configure tcp-map

To clear tcp-map configuration, use the **clear configure tcp-map** command in global configuration mode.

clear configure tcp-map

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following example shows how to clear the TCP map configuration:

```
hostname(config)# clear configure tcp-map
```

Related Commands	Command	Description
	tcp-map	Creates a TCP map and allows access to tcp-map configuration mode.
	show running-config tcp-map	Displays the information about the TCP map configuration.

clear configure telnet

To remove the Telnet connection and idle timeout from the configuration, use the **clear configure telnet** command in global configuration mode.

clear configure telnet

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
7.0	The keyword configure was added.

Examples This example shows how to remove the Telnet connection and the idle timeout from the security appliance configuration:

```
hostname(config)# clear configure telnet
```

Related Commands	Command	Description
	show running-config telnet	Displays the current list of IP addresses that are authorized to use Telnet connections to the security appliance.
	telnet	Adds Telnet access to the console and sets the idle timeout.

clear configure terminal

To clear the terminal display width setting, use the **clear configure terminal** command in global configuration mode.

clear configure terminal

Syntax Description This command has no keywords or arguments.

Defaults The default display width is 80 columns.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Release	Modification
7.0	The configure keyword was added.

Command History

Examples The following example clears the display width:

```
hostname# clear configure terminal
```

Command	Description
terminal	Sets the terminal line parameters.
terminal width	Sets the terminal display width.
show running-config terminal	Displays the current terminal settings.

Related Commands

clear configure timeout

To restore the default idle time durations in the configuration, use the **clear configure timeout** command in global configuration mode.

clear configure timeout

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
Preexisting	This command was preexisting.

Examples This example shows how to remove the maximum idle time durations from the configuration:

```
hostname(config)# clear configure timeout
```

Command	Description
show running-config timeout	Displays the timeout value of the designated protocol.
timeout	Sets the maximum idle time duration.

clear configure tunnel-group

To remove all or specified tunnel groups from the configuration, use the **clear config tunnel-group** command in global configuration.

clear config tunnel-group [*name*]

Syntax Description

name (Optional) Specifies the name of a tunnel group.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example entered in global configuration mode, removes the toengineering tunnel group from the configuration:

```
hostname(config)# clear config tunnel-group toengineering
hostname(config)#
```

Related Commands

Command	Description
show running-config tunnel-group	Displays information about all or selected tunnel-groups.
tunnel-group	Enters tunnel-group subconfiguration mode for the specified type.

clear configure url-block

To clear clears URL pending block buffer and long URL support configuration, use the **clear configure url-block** command in global configuration mode.

clear configure url-block

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **clear configure url-block** command clears URL pending block buffer and long URL support configuration.

Examples

The following example clears URL pending block buffer and long URL support configuration:

```
hostname# clear configure url-block
```

Related Commands

Commands	Description
clear url-block block statistics	Clears the block buffer usage counters.
show url-block	Displays information about the URL cache, which is used for buffering URLs while waiting for responses from an N2H2 or Websense filtering server.
url-block	Manage the URL buffers used for web server responses.
url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

clear configure url-cache

To clear the URL cache, use the **clear configure url-cache** command in global configuration mode.

clear configure url-cache

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **clear configure url-cache** command clears the URL cache.

Examples

The following example clears the URL cache:

```
hostname# clear configure url-cache
```

Related Commands

Commands	Description
clear url-cache statistics	Removes url-cache command statements from the configuration.
filter url	Directs traffic to a URL filtering server.
show url-cache statistics	Displays information about the URL cache, which is used for buffering URLs while waiting for responses from an N2H2 or Websense filtering server.
url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
url-server	Identifies an N2H2 or Websense server for use with the scsc command.

clear configure url-list

To remove a configured set of URLs that WebVPN users can access, use the **clear configure url-list** command in global configuration mode. To remove all configured URLs, use this command without the *listname* argument. To remove only the URLs for a specific list, use this command with that *listname*.

clear configure url-list [*listname*]

Syntax Description

listname Groups the set of URLs WebVPN users can access. Maximum 64 characters.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to remove the URL list called *Marketing URLs*.

```
hostname(config)# clear configure url-list Marketing URLs
```

Related Commands

Command	Description
show running-configuration url-list	Displays the current set of configured url-list commands.
url-list	Use this command in global configuration mode to configure the set of URLs that WebVPN users can access.
url-list	Use this command in webvpn mode that you access from group-policy or username mode to enable WebVPN URL access for a specific group policy or user.

clear configure url-server

To clear the URL filtering server configuration, use the **clear configure url-server** command in global configuration mode.

clear configure url-server

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **clear configure url-server** command clears the URL filtering server configuration.

Examples

The following example URL filtering server configuration:

```
hostname# clear configure url-server
```

Related Commands

Commands	Description
clear url-server	Clears the URL filtering server statistics.
show url-server	Displays information about the URL cache, which is used for buffering URLs while waiting for responses from an N2H2 or Websense filtering server.
url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
url-block	Manages the URL buffers used for web server responses while waiting for a filtering decision from the filtering server.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

clear configure username

To clear the username database, use the **clear configure username** command. To clear the configuration for a particular user, use this command and append the username.

clear configure username [*name*]

Syntax Description

name (Optional) Provides the name of the user.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The internal user authentication database consists of the users entered with the username command. The login command uses this database for authentication.

Examples

The following example shows how to clear the configuration for the user named anyuser:

```
hostname(config)# clear configure username anyuser
```

Related Commands

Command	Description
show running-config username	Displays the running configuration for a particular user or for all users.
username	Adds a user to the security appliance database.
username attributes	Lets you configure AVPs for specific users.

clear configure virtual

To remove the authentication virtual server from the configuration, use the **clear configure virtual** command in global configuration mode.

clear configure virtual

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	—	—	•

Release	Modification
7.0	This command was modified to conform to CLI guidelines.

Usage Guidelines There is no undo.

Examples This example shows the **clear configure virtual** command:

```
hostname(config)# clear configure virtual
```

Command	Description
show running-config virtual	Displays the IP address for the authentication virtual server.
virtual http	Allows separate authentication with the security appliance and with the HTTP server.
virtual telnet	Authenticates users with the virtual Telnet server for traffic types for which the security appliance does not supply an authentication prompt.

clear configure vpn-load-balancing

To remove the previously specified VPN load-balancing configuration, thus disabling VPN load-balancing, use the **clear configure vpn load-balancing** command in global configuration mode.

clear configure vpn load-balancing

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Release	Modification
7.0	This command was introduced

Usage Guidelines The **clear configure vpn load-balancing** command also clears the following related commands: **cluster encryption**, **cluster ip address**, **cluster key**, **cluster port**, **nat**, **participate**, and **priority**.

Examples The following command removes vpn load-balancing configuration statements from the configuration:

```
hostname(config)# clear configure vpn load-balancing
```

Related Commands	show running-config vpn load-balancing	Displays the current VPN load-balancing configuration.
	vpn load-balancing	Enters vpn load-balancing mode.

clear conn

To clear a specific connection or multiple connections, use the **clear conn** command in privileged EXEC mode. This command supports IPv4 and IPv6 addresses.

```
clear conn [all] [protocol {tcp | udp}] [address src_ip[-src_ip] [netmask mask]]
           [port src_port[-src_port]] [address dest_ip[-dest_ip] [netmask mask]]
           [port dest_port[-dest_port]]
```

Syntax Description

address	(Optional) Clears connections with the specified source or destination IP address.
all	(Optional) Clears all connections that are to the device or from the device, in addition to through-traffic connections.
<i>dest_ip</i>	(Optional) Specifies the destination IP address (IPv4 or IPv6). To specify a range, separate the IP addresses with a dash (-), For example: 10.1.1.1-10.1.1.5
<i>dest_port</i>	(Optional) Specifies the destination port number. To specify a range, separate the port numbers with a dash (-), For example: 1000-2000
netmask <i>mask</i>	(Optional) Specifies a subnet mask for use with the given IP address.
port	(Optional) Clears connections with the specified source or destination port.
protocol { tcp udp }	(Optional) Clears connections with the protocol tcp or udp .
<i>src_ip</i>	(Optional) Specifies the source IP address (IPv4 or IPv6). To specify a range, separate the IP addresses with a dash (-), For example: 10.1.1.1-10.1.1.5
<i>src_port</i>	(Optional) Specifies the source port number. To specify a range, separate the port numbers with a dash (-), For example: 1000-2000

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0(8)	This command was introduced.

Usage Guidelines

When the security appliance creates a pinhole to allow secondary connections, this is shown as an incomplete conn by the **show conn** command. To clear this incomplete conn use the **clear conn** command.

Examples

The following example shows all connections, and then clears the management connection between 10.10.10.108:4168 and 10.0.8.112:22:

```
hostname# show conn all
TCP mgmt 10.10.10.108:4168 NP Identity Ifc 10.0.8.112:22, idle 0:00:00, bytes 3084, flags
UOB
```

```
hostname# clear conn address 10.10.10.108 port 4168 address 10.0.8.112 port 22
```

Related Commandss

Commands	Description
clear local-host	Clears all connections by a specific local host or all local hosts.
clear xlate	Clears a NAT session, and any connections using NAT.
show conn	Shows connection information.
show local-host	Displays the network states of local hosts.
show xlate	Shows NAT sessions.

clear console-output

To remove the currently captured console output, use the **clear console-output** command in privileged EXEC mode.

clear console-output

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
Preexisting	This command was preexisting.

Examples The following example shows how to remove the currently captured console output:

```
hostname# clear console-output
```

Command	Description
show console-output	Displays the captured console output.

clear counters

To clear the protocol stack counters, use the **clear counters** command in global configuration mode.

clear counters [**all** | **context** *context-name* | **summary** | **top** *N*] [**detail**] [**protocol** *protocol_name* [:*counter_name*]] [**threshold** *N*]

Syntax Description

all	(Optional) Clears all filter details.
context <i>context-name</i>	(Optional) Specifies the context name.
<i>:counter_name</i>	(Optional) Specifies a counter by name.
detail	(Optional) Clears detailed counters information.
protocol <i>protocol_name</i>	(Optional) Clears the counters for the specified protocol.
summary	(Optional) Clears the counter summary.
threshold <i>N</i>	(Optional) Clears the counters at or above the specified threshold. The range is 1 through 4294967295.
top <i>N</i>	(Optional) Clears the counters at or above the specified threshold. The range is 1 through 4294967295.

Defaults

clear counters summary detail

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

This example shows how to clear the protocol stack counters:

```
hostname(config)# clear counters
```

Related Commands

Command	Description
show counters	Displays the protocol stack counters.

clear crashinfo

To delete the contents of the crash file in Flash memory, enter the **clear crashinfo** command in privileged EXEC mode.

clear crashinfo

Syntax Description This command has no arguments or keywords.

Defaults No default behaviors or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Release	Modification
Preexisting	This command was preexisting.

Command History

Usage Guidelines This command has no usage guidelines.

Examples The following command shows how to delete the crash file:

```
hostname# clear crashinfo
```

Related Commands	crashinfo force	Forces a crash of the security appliance.
	crashinfo save disable	Disables crash information from writing to Flash memory.
	crashinfo test	Tests the ability of the security appliance to save crash information to a file in Flash memory.
	show crashinfo	Displays the contents of the crash file stored in Flash memory.

clear crypto accelerator statistics

To clear the the global and accelerator-specific statistics from the crypto accelerator MIB, use the **clear crypto accelerator statistics** command in global configuration and privileged EXEC modes.

clear crypto accelerator statistics

Syntax Description

This command has no keywords or variables.

Defaults

No default behavior or values.

Command Modes

The following table shows the mode in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example entered in global configuration mode, displays crypto accelerator statistics:

```
hostname(config)# clear crypto accelerator statistics
hostname(config)#
```

Related Commands

Command	Description
clear crypto protocol statistics	Clears the protocol-specific statistics in the crypto accelerator MIB.
show crypto accelerator statistics	Displays the global and accelerator-specific statistics in the crypto accelerator MIB.
show crypto protocol statistics	Displays the protocol-specific statistics from the crypto accelerator MIB.

clear crypto ca crls

To remove the CRL cache of all CRLs associated with a specified trustpoint or to remove the CRL cache of all CRLs, use the **clear crypto ca crls** command in global configuration.

clear crypto ca crls [*trustpointname*]

Syntax Description	<i>trustpointname</i>	(Optional) The name of a trustpoint. If you do not specify a name, this command clears all CRLs cached on the system.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	

Command History	Release	Modification
	7.0	This command was introduced.

Examples	The following example issued in global configuration mode, removes all of the CRL cache from all CRLs from the security appliance:

```
hostname(config)# clear crypto ca crls
hostname(config)#
```

Related Commands	Command	Description
	crypto ca crl request	Downloads the CRL based on the CRL configuration of the trustpoint.
	show crypto ca crls	Displays all cached CRLs or CRLs cached for a specified trustpoint.

clear [crypto] ipsec sa

To remove the IPsec SA counters, entries, crypto maps or peer connections, use the **clear [crypto] ipsec sa** command in global configuration mode. To clear all IPsec SAs, use this command without arguments.

clear [crypto] ipsec sa [**counters** | **entry** {*hostname* | *IP address*} {**esp** | **ah**} {*SPI*} | **map** {*map name*} | **peer** {*hostname* | *IP address*}]

Be careful when using this command.

Syntax Description

ah	Authentication header.
counters	Clears all IPsec per SA statistics.
entry	Deletes the tunnel that matches the specified IP address/hostname, protocol and SPI value.
esp	Encryption security protocol.
<i>hostname</i>	Identified a hostname assigned to an IP address.
<i>IP address</i>	Identifies an IP address.
map	Deletes all tunnels associated with the specified crypto map as identified by map name.
<i>map name</i>	An alphanumeric string that identifies a crypto map. Max 64 characters.
peer	Deletes all IPsec SAs to a peer as identified by the specified hostname or IP address.
<i>SPI</i>	Identifies the Security Parameters Index (a hexadecimal number).

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example, issued in global configuration mode, removes all of the IPsec SAs from the security appliance:

```
hostname(config)# clear ipsec sa
```

```
hostname(config)#
```

The next example, issued in global configuration mode, deletes SAs with a peer IP address of 10.86.1.1.

```
hostname(config)# clear ipsec peer 10.86.1.1
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto map	Clears all or specified crypto maps from the configuration.
clear configure isakmp	Clears all ISAKMP policy configuration.
show ipsec sa	Displays information about IPSec SAs, including counters, entry, map name, peer IP address and hostname.
show running-config crypto	Displays the entire crypto configuration, including IPSec, crypto maps, dynamic crypto maps, and ISAKMP.

clear crypto protocol statistics

To clear the protocol-specific statistics in the crypto accelerator MIB, use the **clear crypto protocol statistics** command in global configuration or privileged EXEC modes.

clear crypto protocol statistics *protocol*

Syntax Description

protocol

Specifies the name of the protocol for which you want to clear statistics. Protocol choices are as follows:

ikev1—Internet Key Exchange version 1.

ipsec—IP Security Phase-2 protocols.

ssl—Secure Socket Layer.

other—Reserved for new protocols.

all—All protocols currently supported.

In online help for this command, other protocols may appear that will be supported in future releases.

Defaults

No default behavior or values.

Command Modes

The following table shows the mode in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example entered in global configuration mode, clears all crypto accelerator statistics:

```
hostname(config)# clear crypto protocol statistics all
hostname(config)#
```

Related Commands

Command	Description
clear crypto accelerator statistics	Clears the global and accelerator-specific statistics in the crypto accelerator MIB.

Command	Description
show crypto accelerator statistics	Displays the global and accelerator-specific statistics from the crypto accelerator MIB.
show crypto protocol statistics	Displays the protocol-specific statistics in the crypto accelerator MIB.

clear dhcpd

To clear the DHCP server bindings and statistics, use the **clear dhcp** command.

clear dhcpd { **binding** [*IP_address*] | **statistics** }

Syntax Description

binding	Clears all the client address bindings.
<i>IP_address</i>	Clears the binding for the specified IP address.
statistics	Clears statistical information counters.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If you include the optional IP address in the **clear dhcpd binding** command, only the binding for that IP address is cleared.

To clear all of the DHCP server commands, use the **clear configure dhcpd** command.

Examples

The following example shows how to clear the **dhcpd** statistics:

```
hostname(config)# clear dhcpd statistics
```

Related Commands

Command	Description
clear configure dhcpd	Removes all DHCP server settings.
show dhcpd	Displays DHCP binding, statistic, or state information.

clear dhcprelay statistics

To clear the DHCP relay statistic counters, use the **clear dhcprelay statistics** command in privileged EXEC mode.

clear dhcprelay statistics

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines The **clear dhcprelay statistics** command only clears the DHCP relay statistic counters. To clear the entire DHCP relay configuration, use the **clear configure dhcprelay** command.

Examples The following example shows how to clear the DHCP relay statistics:

```
hostname# clear dhcprelay statistics
hostname#
```

Related Commands	Command	Description
	clear configure dhcprelay	Removes all DHCP relay agent settings.
	debug dhcprelay	Displays debug information for the DHCP relay agent.
	show dhcprelay statistics	Displays DHCP relay agent statistic information.
	show running-config dhcprelay	Displays the current DHCP relay agent configuration.

clear dns-hosts cache

To clear the DNS cache, use the **clear dns-hosts cache** command in privileged EXEC mode. This command does not clear static entries you added with the **name** command.

clear dns-hosts cache

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	This command was introduced.

Examples The following example clears the DNS cache:

```
hostname# clear dns-hosts cache
```

Related Commands	Command	Description
	dns domain-lookup	Enables the security appliance to perform a name lookup.
	dns name-server	Configures a DNS server address.
	dns retries	Specifies the number of times to retry the list of DNS servers when the security appliance does not receive a response.
	dns timeout	Specifies the amount of time to wait before trying the next DNS server.
	show dns-hosts	Shows the DNS cache.

clear failover statistics

To clear the failover statistic counters, use the **clear failover statistics** command in privileged EXEC mode.

clear failover statistics

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
Preexisting	This command was introduced.

Command History

Usage Guidelines This command clears the statistics displayed with the **show failover statistics** command and the counters in the Stateful Failover Logical Update Statistics section of the **show failover** command output. To remove the failover configuration, use the **clear configure failover** command.

Examples The following example shows how to clear the failover statistic counters:

```
hostname# clear failover statistics
hostname#
```

Command	Description
debug fover	Displays failover debug information.
show failover	Displays information about the failover configuration and operational statistics.

Related Commands

clear fragment

To clear the operational data of the IP fragment reassembly module, enter the **clear fragment** command in privileged EXEC mode. This command clears either the currently queued fragments that are waiting for reassembly (if the **queue** keyword is entered) or clears all IP fragment reassembly statistics (if the **statistics** keyword is entered). The statistics are the counters, which tell how many fragments chains were successfully reassembled, how many chains failed to be reassembled, and how many times the maximum size was crossed resulting in overflow of the buffer.

clear fragment { **queue** | **statistics** } [*interface*]

Syntax Description

<i>interface</i>	(Optional) Specifies the security appliance interface.
queue	Clears the IP fragment reassembly queue.
statistics	Clears the IP fragment reassembly statistics.

Defaults

If an *interface* is not specified, the command applies to all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	The command was separated into two commands, clear fragment and clear configure fragment , to separate clearing of the configuration data from the operational data.

Examples

This example shows how to clear the operational data of the IP fragment reassembly module:

```
hostname# clear fragment queue
```

Related Commands

Command	Description
clear configure fragment	Clears the IP fragment reassembly configuration and resets the defaults.
fragment	Provides additional management of packet fragmentation and improves compatibility with NFS.
show fragment	Displays the operational data of the IP fragment reassembly module.
show running-config fragment	Displays the IP fragment reassembly configuration.

clear gc

To remove the garbage collection process statistics, use the **clear gc** command in privileged EXEC mode.

clear gc

Syntax Description This command has no arguments or keywords.

Defaults No default behaviors or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Release	Modification
7.0	This command was introduced.

Examples The following example shows how to remove the garbage collection process statistics:

```
hostname# clear gc
```

Command	Description
show gc	Displays the garbage collection process statistics.

clear igmp counters

To clear all IGMP counters, use the **clear igmp counters** command in privileged EXEC mode.

clear igmp counters [*if_name*]

Syntax Description

if_name The interface name, as specified by the **nameif** command. Including an interface name with this command causes only the counters for the specified interface to be cleared.

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example clears the IGMP statistical counters:

```
hostname# clear igmp counters
```

Related Commands

Command	Description
clear igmp group	Clears discovered groups from the IGMP group cache.
clear igmp traffic	Clears the IGMP traffic counters.

clear igmp group

To clear discovered groups from the IGMP group cache, use the **clear igmp** command in privileged EXEC mode.

clear igmp group [*group* | *interface name*]

Syntax Description

<i>group</i>	IGMP group address. Specifying a particular group removes the specified group from the cache.
<i>interface name</i>	Interface name, as specified by the namif command. When specified, all groups associated with the interface are removed.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If you do not specify a group or an interface, all groups are cleared from all interfaces. If you specify a group, only the entries for that group are cleared. If you specify an interface, then all groups on that interface are cleared. If you specify both a group and an interface, only the specified groups on the specified interface are cleared.

This command does not clear statically configured groups.

Examples

The following example shows how to clear all discovered IGMP groups from the IGMP group cache:

```
hostname# clear igmp
```

Related Commands

Command	Description
clear igmp counters	Clears all IGMP counters.
clear igmp traffic	Clears the IGMP traffic counters.

clear igmp traffic

To clear the IGMP traffic counters, use the **clear igmp traffic** command in privileged EXEC mode.

clear igmp traffic

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following example clears the IGMP statistical traffic counters:

```
hostname# clear igmp traffic
```

Related Commands	Command	Description
	clear igmp group	Clears discovered groups from the IGMP group cache.
	clear igmp counters	Clears all IGMP counters.

clear interface

To clear interface statistics, use the **clear interface** command in privileged EXEC mode.

clear interface [*physical_interface* [.*subinterface*] | *mapped_name* | *interface_name*]

Syntax Description

<i>interface_name</i>	(Optional) Identifies the interface name set with the nameif command.
<i>mapped_name</i>	(Optional) In multiple context mode, identifies the mapped name if it was assigned using the allocate-interface command.
<i>physical_interface</i>	(Optional) Identifies the interface ID, such as gigabitethernet0/1 . See the interface command for accepted values.
<i>subinterface</i>	(Optional) Identifies an integer between 1 and 4294967293 designating a logical subinterface.

Defaults

By default, this command clears all interface statistics.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If an interface is shared among contexts, and you enter this command within a context, the security appliance clears only statistics for the current context. If you enter this command in the system execution space, the security appliance clears the combined statistics.

You cannot use the interface name in the system execution space, because the **nameif** command is only available within a context. Similarly, if you mapped the interface ID to a mapped name using the **allocate-interface** command, you can only use the mapped name in a context.

Examples

The following example clears all interface statistics:

```
hostname# clear interface
```

Related Commands

Command	Description
clear configure interface	Clears the interface configuration.
interface	Configures an interface and enters interface configuration mode.
show interface	Displays the runtime status and statistics of interfaces.
show running-config interface	Displays the interface configuration.

clear ip audit count

To clear the count of signature matches for an audit policy, use the **clear ip audit count** command in privileged EXEC mode.

clear ip audit count [**global** | **interface** *interface_name*]

Syntax Description

global	(Default) Clears the number of matches for all interfaces.
interface <i>interface_name</i>	(Optional) Clears the number of matches for the specified interface.

Defaults

If you do not specify a keyword, this command clears the matches for all interfaces (**global**).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example clears the count for all interfaces:

```
hostname# clear ip audit count
```

Related Commands

Command	Description
ip audit interface	Assigns an audit policy to an interface.
ip audit name	Creates a named audit policy that identifies the actions to take when a packet matches an attack signature or an informational signature.
show ip audit count	Shows the count of signature matches for an audit policy.
show running-config ip audit attack	Shows the configuration for the ip audit attack command.

clear ip verify statistics

To clear the Unicast RPF statistics, use the **clear ip verify statistics** command in privileged EXEC mode. See the **ip verify reverse-path** command to enable Unicast RPF.

clear ip verify statistics [**interface** *interface_name*]

Syntax Description

interface Sets the interface on which you want to clear Unicast RPF statistics.
interface_name

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example clears the Unicast RPF statistics:

```
hostname# clear ip verify statistics
```

Related Commands

Command	Description
clear configure ip verify reverse-path	Clears the ip verify reverse-path configuration.
ip verify reverse-path	Enables the Unicast Reverse Path Forwarding feature to prevent IP spoofing.
show ip verify statistics	Shows the Unicast RPF statistics.
show running-config ip verify reverse-path	Shows the ip verify reverse-path configuration.

clear ipsec sa

To clear IPsec SAs entirely or based on specified parameters, use the **clear ipsec sa** command in global configuration and privileged EXEC modes. You can also use an alternate form: **clear crypto ipsec sa**.

clear ipsec sa [**counters** | **entry** *peer-addr protocol spi* | **peer** *peer-addr* | **map** *map-name*]

Syntax Description

counters	(Optional) Clears all counters.
entry	(Optional) Clears IPsec SAs for a specified IPsec peer, protocol and SPI.
map <i>map-name</i>	(Optional) Clears IPsec SAs for the specified crypto map.
peer	(Optional) Clears IPsec SAs for a specified peer.
<i>peer-addr</i>	Specifies the IP address of an IPsec peer.
<i>protocol</i>	Specifies an IPsec protocol: esp or ah .
<i>spi</i>	Specifies an IPsec SPI.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example, entered in global configuration mode, clears all IPsec SA counters:

```
hostname(config)# clear ipsec sa counters
hostname(config)#
```

Related Commands

Command	Description
show ipsec sa	Displays IPsec SAs based on specified parameters.
show ipsec stats	Displays global IPsec statistics from the IPsec flow MIB.

clear ipv6 access-list counters

To clear the IPv6 access list statistical counters, use the **clear ipv6 access-list counters** command in privileged EXEC mode.

clear ipv6 access-list *id* **counters**

Syntax Description

id The IPv6 access list identifier.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to clear the statistical data for the IPv6 access list 2:

```
hostname# clear ipv6 access-list 2 counters
hostname#
```

Related Commands

Command	Description
clear configure ipv6	Clears the ipv6 access-list commands from the current configuration.
ipv6 access-list	Configures an IPv6 access list.
show ipv6 access-list	Displays the ipv6 access-list commands in the current configuration.

clear ipv6 neighbors

To clear the IPv6 neighbor discovery cache, use the **clear ipv6 neighbors** command in privileged EXEC mode.

clear ipv6 neighbors

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines This command deletes all discovered IPv6 neighbor from the cache; it does not remove static entries.

Examples The following example deletes all entries, except static entries, in the IPv6 neighbor discovery cache:

```
hostname# clear ipv6 neighbors
hostname#
```

Related Commands	Command	Description
	ipv6 neighbor	Configures a static entry in the IPv6 discovery cache.
	show ipv6 neighbor	Displays IPv6 neighbor cache information.

clear ipv6 traffic

To reset the IPv6 traffic counters, use the **clear ipv6 traffic** command in privileged EXEC mode.

clear ipv6 traffic

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Release	Modification
7.0	This command was introduced.

Usage Guidelines Using this command resets the counters in the output from the show ipv6 traffic command.

Examples The following example resets the IPv6 traffic counters. The output from the **ipv6 traffic** command shows that the counters are reset:

```
hostname# clear ipv6 traffic
hostname# show ipv6 traffic
IPv6 statistics:
  Rcvd: 1 total, 1 local destination
        0 source-routed, 0 truncated
        0 format errors, 0 hop count exceeded
        0 bad header, 0 unknown option, 0 bad source
        0 unknown protocol, 0 not a router
        0 fragments, 0 total reassembled
        0 reassembly timeouts, 0 reassembly failures
  Sent: 1 generated, 0 forwarded
        0 fragmented into 0 fragments, 0 failed
        0 encapsulation failed, 0 no route, 0 too big
  Mcast: 0 received, 0 sent

ICMP statistics:
  Rcvd: 1 input, 0 checksum errors, 0 too short
        0 unknown info type, 0 unknown error type
  unreachable: 0 routing, 0 admin, 0 neighbor, 0 address, 0 port
  parameter: 0 error, 0 header, 0 option
        0 hopcount expired, 0 reassembly timeout, 0 too big
```



```

0 echo request, 0 echo reply
0 group query, 0 group report, 0 group reduce
0 router solicit, 0 router advert, 0 redirects
0 neighbor solicit, 1 neighbor advert
Sent: 1 output
  unreachable: 0 routing, 0 admin, 0 neighbor, 0 address, 0 port
  parameter: 0 error, 0 header, 0 option
  0 hopcount expired, 0 reassembly timeout, 0 too big
  0 echo request, 0 echo reply
  0 group query, 0 group report, 0 group reduce
  0 router solicit, 0 router advert, 0 redirects
  0 neighbor solicit, 1 neighbor advert

UDP statistics:
  Rcvd: 0 input, 0 checksum errors, 0 length errors
        0 no port, 0 dropped
  Sent: 0 output

TCP statistics:
  Rcvd: 0 input, 0 checksum errors
  Sent: 0 output, 0 retransmitted

```

Related Commands

Command	Description
show ipv6 traffic	Displays IPv6 traffic statistics.

clear isakmp sa

To remove all of the IKE runtime SA database, use the **clear isakmp sa** command in global configuration or privileged EXEC mode.

clear isakmp sa

Syntax Description This command has no keywords or arguments.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•		•		
Privileged EXEC	•		•		

Command History

Release	Modification
7.0	This command was introduced.

Examples The following example removes the IKE runtime SA database from the configuration:

```
hostname(config)# clear isakmp sa
hostname(config)#
```

Related Commands	Command	Description
	clear isakmp sa	Clears the IKE runtime SA database.
	isakmp enable	Enables ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance.
	show isakmp stats	Displays runtime statistics.
	show isakmp sa	Displays IKE runtime SA database with additional information.
	show running-config isakmp	Displays all the active ISAKMP configuration.

clear local-host

To release network connections from local hosts displayed by entering the **show local-host** command, use the **clear local-host** command in privileged EXEC mode.

clear local-host [*ip_address*] [**all**]

Syntax Description

all	(Optional) Specifies to clear the local hosts state-made connections, including to the security appliance and from the security appliance.
<i>ip_address</i>	(Optional) Specifies the local host IP address.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **clear local-host** command releases the cleared hosts from the license limit. You can see the number of hosts that are counted toward the license limit by entering the **show local-host** command.



Caution

Clearing the network state of a local host stops all network connections and xlates that are associated with the local hosts.

Examples

The following example shows how the **clear local-host** command clears the information about the local hosts:

```
hostname# clear local-host 10.1.1.15
```

After the information is cleared, nothing more displays until the hosts reestablish their connections.

Related Commands

Command	Description
show local-host	Displays the network states of local hosts.

clear logging asdm

To clear the ASDM logging buffer, use the **clear logging asdm** command in privileged EXEC mode.

clear logging asdm

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	7.0	This command was changed from the show pdm logging command to the show asdm log command.

Usage Guidelines ASDM syslog messages are stored in a separate buffer from the security appliance syslog messages. Clearing the ASDM logging buffer only clears the ASDM syslog messages, it does not clear the security appliance system messages. To view the ASDM syslog messages, use the **show asdm log** command.

Examples The following example clears the ASDM logging buffer:

```
hostname(config)# clear logging asdm
hostname(config)#
```

Related Commands	Command	Description
	show asdm log_sessions	Displays the contents of the ASDM logging buffer.

clear logging buffer

To clear the logging buffer, use the **clear logging buffer** command in global configuration mode.

clear logging buffer

Syntax Description This command has no arguments or keywords.

Defaults This command has no default settings.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Release	Modification
7.0	Support for this command was introduced on the security appliance.

Examples This example shows how to disable the SNMP server:

```
hostname #clear logging buffer
```

Related Commands	Command	Description
	logging buffered	Configures logging.
	show logging	Displays logging information.

clear mac-address-table

To clear dynamic MAC address table entries , use the **clear mac-address-table** command in privileged EXEC mode.

clear mac-address-table [*interface_name*]

Syntax Description	<i>interface_name</i> (Optional) Clears the MAC address table entries for the selected interface.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	—	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples	The following example clears the dynamic MAC address table entries:

```
hostname# clear mac-address-table
```

Related Commands	Command	Description
	arp	Adds a static ARP entry.
	firewall transparent	Sets the firewall mode to transparent.
	mac-address-table aging-time	Sets the timeout for dynamic MAC address entries.
	mac-learn	Disables MAC address learning.
	show mac-address-table	Shows MAC address table entries.

clear memory delayed-free-poisoner

To clear the delayed free-memory poisoner tool queue and statistics, use the **clear memory delayed-free-poisoner** command in privileged EXEC mode.

clear memory delayed-free-poisoner

Syntax Description This command has no arguments or keywords.

Defaults No default behaviors or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines The **clear memory delayed-free-poisoner** command returns all memory held in the delayed free-memory poisoner tool queue to the system without validation and clears the related statistical counters.

Examples The following example clears the delayed free-memory poisoner tool queue and statistics:

```
hostname# clear memory delayed-free-poisoner
```

Command	Description
memory delayed-free-poisoner enable	Enables the delayed free-memory poisoner tool.
memory delayed-free-poisoner validate	Forces validation of the delayed free-memory poisoner tool queue.
show memory delayed-free-poisoner	Displays a summary of the delayed free-memory poisoner tool queue usage.

clear memory profile

To clear the memory buffers held by the memory profiling function, use the **clear memory profile** command in privileged EXEC configuration mode.

clear memory profile [peak]

Syntax Description

peak (Optional) Clears the contents of the peak memory buffer.

Defaults

Clears the current “in use” profile buffer by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **clear memory profile** command releases the memory buffers held by the profiling function and therefore requires that profiling stop before it is cleared.

Examples

The following example clears the memory buffers held by the profiling function:

```
hostname# clear memory profile
```

Related Commands

Command	Description
memory profile enable	Enables the monitoring of memory usage (memory profiling).
memory profile text	Configures a text range of memory to profile.
show memory profile	Displays information about the memory usage (profiling) of the security appliance.

clear memory tracking

To clear all currently gathered information, use the **clear memory tracking** command in privileged EXEC configuration mode.

clear memory tracking

Syntax Description This command has no arguments or keywords.

Defaults No default behaviors or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	—	•	•

Release	Modification
7.0(8)	This command was introduced.

Usage Guidelines The **clear memory tracking** command clears all currently gathered information.

Examples The following example clears the memory tracking function:

```
hostname# clear memory tracking
```

Command	Description
memory tracking enable	Tracks heap memory request.
show memory tracking	Shows currently allocated memory.
show memory tracking address	Lists the size, location, and topmost caller function of each currently allocated piece memory tracked by the tool.
show memory tracking dump	This command shows the size, location, partial callstack, and a memory dump of the given memory address.

clear mfib counters

To clear MFIB router packet counters, use the **clear mfib counters** command in privileged EXEC mode.

clear mfib counters [*group* [*source*]]

Syntax Description

<i>group</i>	(Optional) IP address of the multicast group.
<i>source</i>	(Optional) IP address of the multicast route source. This is a unicast IP address in four-part dotted-decimal notation.

Defaults

When this command is used with no arguments, route counters for all routes are cleared.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example clears all MFIB route counters:

```
hostname# clear mfib route counters
```

Related Commands

Command	Description
show mfib count	Displays MFIB route and packet count data.

clear module recover

To clear the AIP SSM recovery network settings set in the **hw-module module recover** command, use the **clear module recover** command in privileged EXEC mode.

clear module 1 recover

Syntax Description	1	Specifies the slot number, which is always 1.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Examples	The following example clears the recovery settings for the AIP SSM: hostname# clear module 1 recover

Related Commands	Command	Description
	hw-module module recover	Recovers an AIP SSM by loading a recovery image from a TFTP server.
	hw-module module reset	Shuts down an SSM and performs a hardware reset.
	hw-module module reload	Reloads the AIP SSM software.
	hw-module module shutdown	Shuts down the SSM software in preparation for being powered off without losing configuration data.
	show module	Shows SSM information.

clear ospf

To clear OSPF process information, use the **clear ospf** command in privileged EXEC mode.

clear ospf [*pid*] { **process** | **counters** [**neighbor** [*neighbor-intf*] [*neighbor-id*]] }

Syntax Description

counters	Clears the OSPF counters.
neighbor	Clears the OSPF neighbor counters.
<i>neighbor-intf</i>	(Optional) Clears the OSPF interface router designation.
<i>neighbor-id</i>	(Optional) Clears the OSPF neighbor router ID.
<i>pid</i>	(Optional) Internally used identification parameter for an OSPF routing process; valid values are from 1 to 65535.
process	Clears the OSPF routing process.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

This command does not remove any part of the configuration. Use the **no** form of the configuration commands to clear specific commands from the configuration or use the **clear configure router ospf** command to remove all global OSPF commands from the configuration.



Note

The **clear configure router ospf** command does not clear OSPF commands entered in interface configuration mode.

Examples

The following example shows how to clear the OSPF process counters:

```
hostname# clear ospf process
```

Related Commands

Command	Description
clear configure router	Clears all global router commands from the running configuration.

clear pim counters

To clear the PIM traffic counters, use the **clear pim counters** command in privileged EXEC mode.

clear pim counters

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Command History

Usage Guidelines This command only clears the traffic counters. To clear the PIM topology table, use the **clear pim topology** command.

Examples The following example clears the PIM traffic counters:

```
hostname# clear pim counters
```

Command	Description
clear pim reset	Forces MRIB synchronization through reset.
clear pim topology	Clears the PIM topology table.
show pim traffic	Displays the PIM traffic counters.

Related Commands

clear pim reset

To force MRIB synchronization through reset, use the **clear pim reset** command in privileged EXEC mode.

clear pim reset

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Usage Guidelines All information from the topology table is cleared and the MRIB connection is reset. This command can be used to synchronize state between the PIM topology table and the MRIB database.

Examples The following example clears the topology table and resets the MRIB connection:

```
hostname# clear pim reset
```

Command	Description
clear pim counters	Clears PIM counters and statistics.
clear pim topology	Clears the PIM topology table.
clear pim counters	Clears PIM traffic counters.

clear pim topology

To clear the PIM topology table, use the **clear pim topology** command in privileged EXEC mode.

clear pim topology [*group*]

Syntax Description	<i>group</i>	(Optional) Specifies the multicast group address or name to be deleted from the topology table.

Defaults	Without the optional <i>group</i> argument, all entries are cleared from the topology table.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	This command clears existing PIM routes from the PIM topology table. Information obtained from the MRIB table, such as IGMP local membership, is retained. If a multicast group is specified, only those group entries are cleared.

Examples	The following example clears the PIM topology table:

```
hostname# clear pim topology
```

Related Commands	Command	Description
	clear pim counters	Clears PIM counters and statistics.
	clear pim reset	Forces MRIB synchronization through reset.
	clear pim counters	Clears PIM traffic counters.

clear priority-queue statistics

To clear the priority-queue statistics counters for an interface or for all configured interfaces, use the **clear priority-queue statistics** command in either global configuration or privileged EXEC mode.

clear priority-queue statistics [*interface-name*]

Syntax Description

interface-name (Optional) Specifies the name of the interface for which you want to show the best-effort and low-latency queue details.

Defaults

If you omit the interface name, this command clears the priority-queue statistics for all configured interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

This example shows the use of the **clear priority-queue statistics** command in privileged EXEC mode to remove the priority queue statistics for the interface named “test”.

```
hostname# clear priority-queue statistics test
hostname#
```

Related Commands

Command	Description
clear configure priority-queue	Removes the priority-queue configuration from the named interface.
priority-queue	Configures priority queueing on an interface.
show priority-queue statistics	Shows the priority queue statistics for a specified interface or for all interfaces.
show running-config priority-queue	Shows the current priority-queue configuration on the named interface.

clear resource usage

To clear resource usage statistics, use the **clear resource usage** command in privileged EXEC mode.

clear resource usage [**context** *context_name* | **all** | **summary**] [**resource** {*resource_name* | **all**}]

Syntax Description

context <i>context_name</i>	(Multiple mode only) Specifies the context name for which you want to clear statistics. Specify all for all contexts.
resource <i>resource_name</i>	Clears the usage of a specific resource. Specify all (the default) for all resources. Resources include the following types: • conns—TCP or UDP connections between any two hosts, including connections between one host and multiple other hosts. • hosts—Hosts that can connect through the security appliance. • ipsec—(Single mode only) IPSec sessions • ssh—SSH sessions. • telnet—Telnet sessions. • xlates—NAT translations.
summary	(Multiple mode only) Clears the combined context statistics.

Defaults

For multiple context mode, the default context is **all**, which clears resource usage for every context. For single mode, the context name is ignored and all resource statistics are cleared.

The default resource name is **all**, which clears all resource types.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example clears all resource usage statistics:

```
hostname# clear resource usage
```

Related Commands	Command	Description
	context	Adds a security context.
	show resource types	Shows a list of resource types.
	show resource usage	Shows the resource usage of the security appliance.

clear route

To remove dynamically learned routes from the configuration, use the **clear route** command in privileged EXEC mode.

clear route [*interface_name*]

Syntax Description

interface_name (Optional) Internal or external network interface name.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example shows how to remove dynamically learned routes:

hostname# **clear route**

Related Commands

Command	Description
route	Specifies a static or default route for the an interface.
show route	Displays route information.
show running-config route	Displays configured routes.

clear service-policy

To clear operational data or statistics (if any) for enabled policies, use the **clear service-policy** command in global configuration mode.

clear service-policy [**global** | **interface** *intf* | **inspect**]

Syntax Description

global	(Optional) Clears the statistics of the global service policy.
interface	(Optional) Clears the service policy statistics of a specific interface.
<i>intf</i>	The interface name defined in the nameif command.
inspect	Clears inspect service policy statistics.

Defaults

By default, this command clears all the statistics for all enabled service policies.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If an interface name is specified, the policy-map only applies to the interface. The interface name is defined in the **nameif** command, and an interface policy-map overrides a global policy-map. Only one policy-map is allowed per interface.

Only one global policy is allowed.

Examples

The following example shows the syntax of the **clear service-policy** command:

```
hostname(config)# clear service-policy outside_security_map outside
```

Related Commands

Command	Description
show service-policy	Displays the service policy.
show running-config service-policy	Displays the service policies configured in the running configuration.

Command	Description
clear configure service-policy	Clears service policy configurations.
service-policy	Configures service policies.

clear service-policy inspect gtp

To clear global GTP statistics, use the **clear service-policy inspect gtp** command in privileged EXEC mode.

```
clear service-policy inspect gtp { pdp-context [all | apn ap_name | imsi IMSI_value | ms-addr IP_address | tid tunnel_ID | version version_num ] | requests | statistics [gsn IP_address] }
```

Syntax Description

all	Clears all GTP PDP contexts.
apn	(Optional) Clears the PDP contexts based on the APN specified.
<i>ap_name</i>	Identifies the specific access point name.
gsn	(Optional) Identifies the GPRS support node, which is the interface between the GPRS wireless data network and other networks.
gtp	(Optional) Clears the service policy for GTP.
imsi	(Optional) Clears the PDP contexts based on the IMSI specified.
<i>IMSI_value</i>	Hexadecimal value that identifies the specific IMSI.
interface	(Optional) Identifies a specific interface.
<i>int</i>	Identifies the interface for which information will be cleared.
<i>IP_address</i>	IP address for which statistics will be cleared.
ms-addr	(Optional) Clears PDP contexts based on the MS Address specified.
pdp-context	(Optional) Identifies the Packet Data Protocol context.
requests	(Optional) Clears GTP requests.
statistics	(Optional) Clears GTP statistics for the inspect gtp command.
tid	(Optional) Clears the PDP contexts based on the TID specified.
<i>tunnel_ID</i>	Hexadecimal value that identifies the specific tunnel.
version	(Optional) Clears the PDP contexts based on the GTP version.
<i>version_num</i>	Specifies the version of the PDP context. The valid range is 0 to 255.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The Packet Data Protocol context is identified by the tunnel ID, which is a combination of IMSI and NSAPI. A GTP tunnel is defined by two associated PDP Contexts in different GSN nodes and is identified with a tunnel ID. A GTP tunnel is necessary to forward packets between an external packet data network and a mobile station (MS) user.

Examples

The following example clears GTP statistics:

```
hostname# clear service-policy inspect gtp statistics
```

Related Commands

Commands	Description
debug gtp	Displays detailed information about GTP inspection.
gtp-map	Defines a GTP map and enables GTP map configuration mode.
inspect gtp	Applies a GTP map to use for application inspection.
show service-policy inspect gtp	Displays the GTP configuration.
show running-config gtp-map	Shows the GTP maps that have been configured.

clear shun

To disable all the shuns that are currently enabled and clear the shun statistics, use the **clear shun** command in privileged EXEC mode.

clear shun [*statistics*]

Syntax Description

statistics (Optional) Clears the interface counters only.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
1.1(1)	This command was introduced.

Examples

The following example shows how to disable all the shuns that are currently enabled and clear the shun statistics:

```
hostname(config)# clear shun
```

Related Commands

Command	Description
shun	Enables a dynamic response to an attacking host by preventing new connections and disallowing packets from any existing connection.
show shun	Displays the shun information.

clear sunrpc-server active

To clear the pinholes opened by Sun RPC application inspection, use the **clear sunrpc-server active** command in global configuration mode.

clear sunrpc-server active

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Use the **clear sunrpc-server active** command to clear the pinholes opened by Sun RPC application inspection that allow service traffic, such as NFS or NIS, to pass through the security appliance.

Examples

The following example shows how to clear the SunRPC services table:

```
hostname(config)# clear sunrpc-server
```

Related Commands

Command	Description
clear configure sunrpc-server	Clears the Sun remote processor call services from the security appliance.
inspect sunrpc	Enables or disables Sun RPC application inspection and configures the port used.
show running-config sunrpc-server	Displays information about the SunRPC services configuration.
show sunrpc-server active	Displays information about active Sun RPC services.

clear traffic

To reset the counters for transmit and receive activity, use the **clear traffic** command in privileged EXEC mode.

clear traffic

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
Preexisting	This command was preexisting.

Command History

Usage Guidelines The **clear traffic** command resets the counters for transmit and receive activity that is displayed with the **show traffic** command. The counters indicate the number of packets and bytes moving through each interface since the last clear traffic command was entered or since the security appliance came online. And the number of seconds indicate the duration the security appliance has been online since the last reboot.

Examples The following example shows the **clear traffic** command:

```
hostname# clear traffic
```

Command	Description
show traffic	Displays the counters for transmit and receive activity.

Related Commands

clear uauth

To delete all the cached authentication and authorization information for a user or for all users, use the **clear uauth** command in privileged EXEC mode.

clear uauth [*username*]

Syntax Description

username (Optional) Specifies, by username, the user authentication information to remove.

Defaults

Omitting username deletes the authentication and authorization information for all users.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **clear uauth** command deletes the AAA authorization and authentication caches for one user or for all users, which forces the user or users to reauthenticate the next time that they create a connection.

This command is used with the **timeout** command.

Each user host IP address has an authorization cache attached to it. If the user attempts to access a service that has been cached from the correct host, the security appliance considers it preauthorized and immediately proxies the connection. Once you are authorized to access a website, for example, the authorization server is not contacted for each image as it is loaded (assuming the images come from the same IP address). This process significantly increases performance and reduces the load on the authorization server.

The cache allows up to 16 address and service pairs for each user host.



Note

When you enable Xauth, an entry is added to the uauth table (as shown by the **show uauth** command) for the IP address that is assigned to the client. However, when using Xauth with the Easy VPN Remote feature in Network Extension Mode, the IPSec tunnel is created from network to network, so that the users behind the firewall cannot be associated with a single IP address. For this reason, a uauth entry cannot be created upon completion of Xauth. If AAA authorization or accounting services are required, you can enable the AAA authentication proxy to authenticate users behind the firewall. For more information on AAA authentication proxies, see the AAA commands.

Use the **timeout uauth** command to specify how long the cache should be kept after the user connections become idle. Use the **clear uauth** command to delete all the authorization caches for all the users, which will cause them to have to reauthenticate the next time that they create a connection.

Examples

This example shows how to cause the user “Lee” to reauthenticate:

```
hostname(config)# clear uauth lee
```

Related Commands

Command	Description
aaa authentication	Enable, disable, or view LOCAL, TACACS+ or RADIUS user authentication (on a server designated by the aaa-server command).
aaa authorization	Enable, disable, or view TACACS+ or RADIUS user authorization (on a server designated by the aaa-server command).
show uauth	Display current user authentication and authorization information.
timeout	Set the maximum idle time duration.

clear url-block block statistics

To clear the block buffer usage counters, use the **clear url-block block statistics** command in privileged EXEC mode.

clear url-block block statistics

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines The **clear url-block block statistics** command clears the block buffer usage counters, except for the `Current number of packets held (global) counter`.

Examples The following example clears the URL block statistics and displays the status of the counters after clearing:

```
hostname# clear url-block block statistics
hostname# show url-block block statistics

URL Pending Packet Buffer Stats with max block 0
-----
Cumulative number of packets held: | 0
Maximum number of packets held (per URL): | 0
Current number of packets held (global): | 38
Packets dropped due to
| exceeding url-block buffer limit: | 0
| HTTP server retransmission: | 0
Number of packets released back to client: | 0
```

Related Commands

Commands	Description
filter url	Directs traffic to a URL filtering server.
show url-block	Displays information about the URL cache, which is used for buffering URLs while waiting for responses from an N2H2 or Websense filtering server.
url-block	Manage the URL buffers used for web server responses.
url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

clear url-cache statistics

To remove **url-cache** command statements from the configuration, use the **clear url-cache** command in privileged EXEC mode.

clear url-cache statistics

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines The **clear url-cache** command removes **url-cache** statistics from the configuration.

Using the URL cache does not update the Websense accounting logs for Websense protocol Version 1. If you are using Websense protocol Version 1, let Websense run to accumulate logs so you can view the Websense accounting information. After you get a usage profile that meets your security needs, enter the **url-cache** command to increase throughput. Accounting logs are updated for Websense protocol Version 4 and for N2H2 URL filtering while using the **url-cache** command.

Examples The following example clears the URL cache statistics:

```
hostname# clear url-cache statistics
```

Commands	Description
filter url	Directs traffic to a URL filtering server.
show url-cache statistics	Displays information about the URL cache, which is used for buffering URLs while waiting for responses from an N2H2 or Websense filtering server.
url-block	Manages the URL buffers used for web server responses while waiting for a filtering decision from the filtering server.

url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

clear url-server

To clear URL filtering server statistics, use the **clear url-server** command in privileged EXEC mode.

clear url-server statistics

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines The **clear url-server** command removes URL filtering server statistics from the configuration.

Examples The following example clears the URL server statistics:

```
hostname# clear url-server statistics
```

Related Commands	Commands	Description
	filter url	Directs traffic to a URL filtering server.
	show url-server	Displays information about the URL cache, which is used for buffering URLs while waiting for responses from an N2H2 or Websense filtering server.
	url-block	Manages the URL buffers used for web server responses while waiting for a filtering decision from the filtering server.
	url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
	url-server	Identifies an N2H2 or Websense server for use with the filter command.

clear xlate

To clear current translation and connection information, use the **clear xlate** command in privileged EXEC mode.

```
clear xlate [global ip1[-ip2] [netmask mask]] [local ip1[-ip2] [netmask mask]]
               [gport port1[-port2]] [lport port1[-port2]] [interface if_name] [state state]
```

Syntax Description

global <i>ip1</i> [- <i>ip2</i>]	(Optional) Clears the active translations by global IP address or range of addresses.
gport <i>port1</i> [- <i>port2</i>]	(Optional) Clears the active translations by the global port or range of ports.
interface <i>if_name</i>	(Optional) Displays the active translations by interface.
local <i>ip1</i> [- <i>ip2</i>]	(Optional) Clears the active translations by local IP address or range of addresses.
lport <i>port1</i> [- <i>port2</i>]	(Optional) Clears the active translations by local port or range of ports.
netmask <i>mask</i>	(Optional) Specifies the network mask to qualify the global or local IP addresses.
state <i>state</i>	(Optional) Clears the active translations by state. You can enter one or more of the following states: • static—specifies static translations. • portmap—specifies PAT global translations. • norandomseq—specifies a nat or static translation with the norandomseq setting. • identity—specifies nat 0 identity address translations. When specifying more than one state, separate the states with a space.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **clear xlate** command clears the contents of the translation slots (“xlate” refers to the translation slot). Translation slots can persist after key changes have been made. Always use the **clear xlate** command after adding, changing, or removing the **aaa-server**, **access-list**, **alias**, **global**, **nat**, **route**, or **static** commands in your configuration.

An xlate describes a NAT or PAT session. These sessions can be viewed with the **show xlate** command with the **detail** option. There are two types of xlates: static and dynamic.

A static xlate is a persistent xlate that is created using the **static** command. The **clear xlate** command does not clear for a host in a static entry. Static xlates can only be removed by removing the **static** command from the configuration; the **clear xlate** does not remove the static translation rule. If you remove a **static** command from the configuration, preexisting connections that use the static rule can still forward traffic. Use the **clear local-host** to deactivate these connections.

A dynamic xlate is an xlate that is created on demand with traffic processing (through the **nat** or **global** command). The **clear xlate** removes dynamic xlates and their associated connections. You can also use the **clear local-host** command to clear the xlate and associated connections. If you remove a **nat** or a **global** command from the configuration, the dynamic xlate and associated connections may remain active. Use the **clear xlate** or the **clear local-host** command to remove these connections.

Examples

The following example shows how to clear the current translation and connection slot information:

```
hostname# clear xlate global
```

Related Commands

Command	Description
clear local-host	Clears local host network information.
clear uauth	Clears cached user authentication and authorization information.
show conn	Displays all active connections.
show local-host	Displays the local host network information.
show xlate	Displays the current translation information.

client-access-rule

To configure rules that limit the remote access client types and versions that can connect via IPSec through the security appliance, use the **client-access-rule** command in group-policy configuration mode. To delete a rule, use the **no** form of this command.

To delete all rules, use the **no client-access-rule command** with only the priority argument. This deletes all configured rules, including a null rule created by issuing the **client-access-rule none** command.

When there are no client access rules, users inherit any rules that exist in the default group policy. To prevent users from inheriting client access rules, use the **client-access-rule none** command. The result of doing so is that all client types and versions can connect.

client-access-rule *priority* {**permit** | **deny**} **type** *type* **version** *version* | **none**

no client-access-rule *priority* [{**permit** | **deny**} **type** *type* **version** *version*]

Syntax Description

deny	Denies connections for devices of a particular type and/or version.
none	Allows no client access rules. Sets client-access-rule to a null value, thereby allowing no restriction. Prevents inheriting a value from a default or specified group policy.
permit	Permits connections for devices of a particular type and/or version.
priority	Determines the priority of the rule. The rule with the lowest integer has the highest priority. Therefore, the rule with the lowest integer that matches a client type and/or version is the rule that applies. If a lower priority rule contradicts, the security appliance ignores it.
type <i>type</i>	Identifies device types via free-form strings, for example VPN 3002. A string must match exactly its appearance in the show vpn-sessiondb remote display, except that you can use the * character as a wildcard.
version <i>version</i>	Identifies the device version via free-form strings, for example 7.0. A string must match exactly its appearance in the show vpn-sessiondb remote display, except that you can use the * character as a wildcard.

Defaults

By default, there are no access rules.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Construct rules according to these caveats:

- If you do not define any rules, the security appliance permits all connection types.
- When a client matches none of the rules, the security appliance denies the connection. This means that if you define a deny rule, you must also define at least one permit rule, or the security appliance denies all connections.
- For both software and hardware clients, type and version must match exactly their appearance in the **show vpn-sessiondb remote** display.
- The * character is a wildcard, which you can use multiple times in each rule. For example, **client-access-rule 3 deny type * version 3.*** creates a priority 3 client access rule that denies all client types running release versions 3.x software.
- You can construct a maximum of 25 rules per group policy.
- There is a limit of 255 characters for an entire set of rules.
- You can use n/a for clients that do not send client type and/or version.

Examples

The following example shows how to create client access rules for the group policy named FirstGroup. These rules permit VPN Clients running software version 4.1, while denying all VPN 3002 hardware clients:

```
hostname(config)# group-policy FirstGroup attributes  
hostname(config-group-policy)# client-access-rule 1 d t VPN3002 v *  
hostname(config-group-policy)# client-access-rule 2 p * v 4.1
```

client-firewall

To set personal firewall policies that the security appliance pushes to the VPN Client during IKE tunnel negotiation, use the **client-firewall** command in group-policy configuration mode. To delete a firewall policy, use the **no** form of this command.

When there are no firewall policies, users inherit any that exist in the default or other group policy. To prevent users from inheriting such firewall policies, use the **client-firewall none** command.

client-firewall none

client-firewall opt | req custom vendor-id *num* product-id *num* policy AYT | {CPP acl-in *ACL* acl-out *ACL*} [description *string*]

client-firewall opt | req zonelabs-zonealarm policy AYT | {CPP acl-in *ACL* acl-out *ACL*}

client-firewall opt | req zonelabs-zonealarmpro policy AYT | {CPP acl-in *ACL* acl-out *ACL*}

client-firewall opt | req zonelabs-zonealarmpro policy AYT | {CPP acl-in *ACL* acl-out *ACL*}

client-firewall opt | req cisco-integrated acl-in *ACL* acl-out *ACL*

client-firewall opt | req sygate-personal

client-firewall opt | req sygate-personal-pro

client-firewall opt | req sygate-security-agent

client-firewall opt | req networkice-blackice

client-firewall opt | req cisco-security-agent

Syntax Description

acl-in <ACL>	Provides the policy the client uses for inbound traffic
acl-out <ACL>	Provides the policy the client uses for outbound traffic
AYT	Specifies that the client PC firewall application controls the firewall policy. The security appliance checks to make sure the firewall is running. It asks, "Are You There?" If there is no response, the security appliance tears down the tunnel.
cisco-integrated	Specifies Cisco Integrated firewall type.
cisco-security-agent	Specifies Cisco Intrusion Prevention Security Agent firewall type
CPP	Specifies Policy Pushed as source of the VPN Client firewall policy
custom	Specifies Custom firewall type.
description <string>	Describes the firewall.
networkice-blackice	Specifies Network ICE Black ICE firewall type
none	Indicates that there is no client firewall policy. Sets a firewall policy with a null value, thereby disallowing one. Prevents inheriting a firewall policy from a default or specified group policy.
opt	Indicates an optional firewall type.
product-id	Identifies the firewall product
req	Indicates a required firewall type

sygate-personal	Specifies Sygate Personal firewall type
sygate-personal-pro	Specifies Sygate Personal Pro firewall type
sygate-security-agent	Specifies Sygate Security Agent firewall type
vendor-id	Identifies the firewall vendor
zonelabs-zonealarm	Specifies Zone Labs Zone Alarm firewall type
zonelabs-zonealarmorpro policy	Specifies Zone Labs Zone Alarm or Pro firewall type
zonelabs-zonealarmpro policy	Specifies Zone Labs Zone Alarm Pro firewall type

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Only one instance of this command can be configured.

Examples

The following example shows how to set a client firewall policy that requires Cisco Intrusion Prevention Security Agent for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# client-firewall req cisco-security-agent
```

client-update

To configure and change client update parameters, use the **client-update** command in tunnel-group ipsec-attributes configuration mode. If the client is already running a software version on the list of revision numbers, it does not need to update its software. If the client is not running a software version on the list, it should update. You can specify up to 4 of these client update entries.

To disable a client update, use the **no** form of this command.

client-update *type* {**url** *url-string*} {**rev-nums** *rev-nums*}

no client-update [*type*]

Syntax Description

rev-nums <i>rev-nums</i>	Specifies the software or firmware images for this client. Enter up to 4, separated by commas.
<i>type</i>	Specifies the operating systems to notify of a client update. The list of operating systems comprises the following: - Windows: all windows-based platforms - WIN9X: Windows 95, Windows 98, and Windows ME platforms - WinNT: Windows NT 4.0, Windows 2000, and Windows XP platforms - vpn3002: VPN 3002 hardware client
url <i>url-string</i>	Specifies the URL for the software/firmware image. This URL must point to a file appropriate for this client.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Tunnel-group ipsec attributes configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute to IPSec remote-access tunnel-group type only.

Examples

The following example entered in config-ipsec configuration mode, configures client update parameters for the remote-access tunnel-group remotegrp. It designates the revision number, 4.6.1 and the URL for retrieving the update, which is https://support/updates.

```
hostname(config)# tunnel-group remotegrp type ipsec_ra
hostname(config)# tunnel-group remotegrp ipsec-attributes
hostname(config-ipsec)# client-update type windows url https://support/updates/ rev-nums
4.6.1
hostname(config-ipsec)#
```

Related Commands

Command	Description
clear configure tunnel-group	Clears all configured tunnel groups.
show running-config tunnel-group	Shows the indicated certificate map entry.
tunnel-group-map enable	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

clock set

To manually set the clock on the security appliance, use the **clock set** command in privileged EXEC mode.

clock set *hh:mm:ss {month day | day month} year*

Syntax Description

<i>day</i>	Sets the day of the month, from 1 to 31. You can enter the day and month as april 1 or as 1 april , for example, depending on your standard date format.
<i>hh:mm:ss</i>	Sets the hour, minutes, and seconds in 24-hour time. For example, set 20:54:00 for 8:54 pm.
<i>month</i>	Sets the month. Depending on your standard date format, you can enter the day and month as april 1 or as 1 april .
<i>year</i>	Sets the year using four digits, for example, 2004 . The year range is 1993 to 2035.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If you have not entered any **clock** configuration commands, the default time zone for the **clock set** command is UTC. If you change the time zone after you enter the **clock set** command using the **clock timezone** command, the time automatically adjusts to the new time zone. However, if you enter the **clock set** command after you establish the time zone with the **clock timezone** command, then enter the time appropriate for the new time zone and not for UTC. Similarly, if you enter the **clock summer-time** command after the **clock set** command, the time adjusts for daylight saving. If you enter the **clock set** command after the **clock summer-time** command, enter the correct time for daylight saving.

This command sets the time in the hardware chip, and does not save the time in the configuration file. This time endures reboots. Unlike the other **clock** commands, this command is a privileged EXEC command. To reset the clock, you need to set a new time for the **clock set** command.

Examples

The following example sets the time zone to MST, the daylight saving time to the default period in the U.S., and the current time for MDT to 1:15 p.m. on July 27, 2004:

```
hostname(config)# clock timezone MST -7
hostname(config)# clock summer-time MDT recurring
hostname(config)# exit
hostname# clock set 13:15:0 jul 27 2004
hostname# show clock
13:15:00.652 MDT Tue Jul 27 2004
```

The following example sets the clock to 8:15 on July 27, 2004 in the UTC time zone, and then sets the time zone to MST and the daylight saving time to the default period in the U.S. The end time (1:15 in MDT) is the same as the previous example.

```
hostname# clock set 20:15:0 jul 27 2004
hostname# configure terminal
hostname(config)# clock timezone MST -7
hostname(config)# clock summer-time MDT recurring
hostname# show clock
13:15:00.652 MDT Tue Jul 27 2004
```

Related Commands

Command	Description
clock summer-time	Sets the date range to show daylight saving time.
clock timezone	Sets the time zone.
show clock	Shows the current time.

clock summer-time

To set the date range for daylight saving time for the display of the security appliance time, use the **clock summer-time** command in global configuration mode. To disable the daylight saving time dates, use the **no** form of this command.

clock summer-time *zone* **recurring** [*week weekday month hh:mm week weekday month hh:mm*]
[*offset*]

no clock summer-time [*zone recurring [week weekday month hh:mm week weekday month hh:mm]*]
[*offset*]

clock summer-time *zone* **date** {*day month | month day*} *year hh:mm {day month | month day} year*
hh:mm [*offset*]

no clock summer-time [*zone date {day month | month day} year hh:mm {day month | month day}*]
year hh:mm [*offset*]

Syntax Description

date	Specifies the start and end dates for daylight saving time as a specific date in a specific year. If you use this keyword, you need to reset the dates every year.
<i>day</i>	Sets the day of the month, from 1 to 31. You can enter the day and month as April 1 or as 1 April , for example, depending on your standard date format.
<i>hh:mm</i>	Sets the hour and minutes in 24-hour time.
<i>month</i>	Sets the month as a string. For the date command, you can enter the day and month as April 1 or as 1 April , for example, depending on your standard date format.
<i>offset</i>	(Optional) Sets the number of minutes to change the time for daylight saving time. By default, the value is 60 minutes.
recurring	Specifies the start and end dates for daylight saving time, in the form of a day and time of the month, and not a specific date in a year. This keyword lets you set a recurring date range that you do not need to alter yearly. If you do not specify any dates, the security appliance uses the default date range for the United States: 2:00 a.m. on the first Sunday in April to 2:00 a.m. on the last Sunday in October.
<i>week</i>	(Optional) Specifies the week of the month as an integer between 1 and 4 or as the words first or last . For example, if the day might fall in the partial fifth week, then specify last .
<i>weekday</i>	(Optional) Specifies the day of the week: Monday , Tuesday , Wednesday , and so on.
<i>year</i>	Sets the year using four digits, for example, 2004 . The year range is 1993 to 2035.
<i>zone</i>	Specifies the time zone as a string, for example, PDT for Pacific Daylight Time. When the security appliance shows the daylight saving time according to the date range you set with this command, the time zone changes to the value you set here. See the clock timezone to set the base time zone to a zone other than UTC.

Defaults

The default offset is 60 minutes.

The default recurring date range is from 2:00 a.m. on the first Sunday in April to 2:00 a.m. on the last Sunday in October.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

For the Southern Hemisphere, the security appliance accepts the start month to be later in the year than the end month, for example, from October to March.

Examples

The following example sets the daylight saving date range for Australia:

```
hostname(config)# clock summer-time PDT recurring last Sunday October 2:00 last Sunday March 2:00
```

Some countries start daylight saving on a specific date. In the following example, daylight saving time is configured to start on April 1, 2004, at 3 a.m. and end on October 1, 2004, at 4 a.m.

```
hostname(config)# clock summer-time UTC date 1 April 2004 3:00 1 October 2004 4:00
```

Related Commands

Command	Description
clock set	Manually sets the clock on the security appliance.
clock timezone	Sets the time zone.
ntp server	Identifies an NTP server.
show clock	Shows the current time.

clock timezone

To set the time zone for the security appliance clock, use the **clock timezone** command in global configuration mode. To set the time zone back to the default of UTC, use the **no** form of this command. The **clock set** command or the time derived from an NTP server sets the time in UTC. You must set the time zone as an offset of UTC using this command.

clock timezone *zone* [-]*hours* [*minutes*]

no clock timezone [*zone* [-]*hours* [*minutes*]]

Syntax Description

<i>zone</i>	Specifies the time zone as a string, for example, PST for Pacific Standard Time.
[-] <i>hours</i>	Sets the number of hours of offset from UTC. For example, PST is -8 hours.
<i>minutes</i>	(Optional) Sets the number of minutes of offset from UTC.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To set daylight saving time, see the **clock summer-time** command.

Examples

The following example sets the time zone to Pacific Standard Time, which is -8 hours from UTC:

```
hostname(config)# clock timezone PST -8
```

Related Commands

Command	Description
clock set	Manually sets the clock on the security appliance.
clock summer-time	Sets the date range to show daylight saving time.

Command	Description
ntp server	Identifies an NTP server.
show clock	Shows the current time.

cluster encryption

To enable encryption for messages exchanged on the virtual load-balancing cluster, use the **cluster encryption** command in VPN load-balancing mode. To disable encryption, use the **no** form of this command.

cluster encryption

no cluster encryption



Note

VPN load balancing requires an active 3DES/AES license. The security appliance checks for the existence of this crypto license before enabling load balancing. If it does not detect an active 3DES or AES license, the security appliance prevents the enabling of load balancing and also prevents internal configuration of 3DES by the load balancing system unless the license permits this usage.

Syntax Description

This command has no arguments or variables.

Defaults

Encryption is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
VPN load-balancing mode	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command turns encryption on or off for messages exchanged on the virtual load-balancing cluster. Before configuring the **cluster encryption** command, you must have first used the **vpn load-balancing** command to enter VPN load-balancing mode. You must also use the **cluster key** command to configure the cluster shared-secret key before enabling cluster encryption.



Note

When using encryption, you must first configure the command **isakmp enable inside**, where *inside* designates the load-balancing inside interface. If isakmp is not enabled on the load-balancing inside interface, you will get an error message when you try to configure cluster encryption.

Examples

The following is an example of a VPN load-balancing command sequence that includes a **cluster encryption** command that enables encryption for the virtual load-balancing cluster:

```
hostname(config)# interface GigabitEthernet 0/1
hostname(config-if)# ip address 209.165.202.159 255.255.255.0
hostname(config)# nameif test
hostname(config)# interface GigabitEthernet 0/2
hostname(config-if)# ip address 209.165.201.30 255.255.255.0
hostname(config)# nameif foo
hostname(config)# vpn load-balancing
hostname(config-load-balancing)# interface lbpublic test
hostname(config-load-balancing)# interface lbprivate foo
hostname(config-load-balancing)# cluster ip address 209.165.202.224
hostname(config-load-balancing)# cluster key 123456789
hostname(config-load-balancing)# cluster encryption
hostname(config-load-balancing)# participate
```

Related Commands

Command	Description
cluster key	Specifies the shared-secret key for the cluster.
vpn load-balancing	Enters VPN load-balancing mode.

cluster ip address

To set the IP address of the virtual load-balancing cluster, use the **cluster ip address** command in VPN load-balancing mode. To remove the IP address specification, use the **no** form of this command.

cluster ip address *ip-address*

no cluster ip address [*ip-address*]

Syntax Description

ip-address The IP address that you want to assign to the virtual load-balancing cluster.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
VPN load-balancing mode	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must first use the **vpn load-balancing** command to enter VPN load-balancing mode and configure the interface to which the virtual cluster IP address refers.

The cluster ip address must be on the same subnet as the interface for which you are configuring the virtual cluster.

In the **no** form of the command, if you specify the optional *ip-address* value, it must match the existing cluster IP address before the **no cluster ip address** command can be completed.

Examples

The following is an example of a VPN load-balancing command sequence that includes a **cluster ip address** command that sets the IP address of the virtual load-balancing cluster to 209.165.202.224:

```
hostname(config)# interface GigabitEthernet 0/1
hostname(config-if)# ip address 209.165.202.159 255.255.255.0
hostname(config)# nameif test
hostname(config)# interface GigabitEthernet 0/2
hostname(config-if)# ip address 209.165.201.30 255.255.255.0
hostname(config)# nameif foo
hostname(config)# vpn load-balancing
hostname(config-load-balancing)# interface lbpublic test
hostname(config-load-balancing)# interface lbprivate foo
hostname(config-load-balancing)# cluster ip address 209.165.202.224
```

```
hostname(config-load-balancing)# participate
```

Related Commands

Command	Description
interface	Sets the interfaces of the device.
nameif	Assigns a name to an interface.
vpn load-balancing	Enters VPN load-balancing mode.

cluster key

To set the shared secret for IPSec site-to-site tunnel exchanges on the virtual load-balancing cluster, use the **cluster key** command in VPN load-balancing mode. To remove this specification, use the **no** form of this command.

cluster key *shared-secret*

no cluster key [*shared-secret*]

Syntax Description

shared-secret A string defining the shared secret for the VPN load-balancing cluster.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
VPN load-balancing mode	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must first use the **vpn load-balancing** command to enter VPN load-balancing mode. The secret defined in the **cluster key** command is also used for cluster encryption.

You must use the **cluster key** command to configure the shared secret before enabling cluster encryption.

If you specify a value for *shared-secret* in the **no cluster key** form of the command, the shared secret value must match the existing configuration.

Examples

The following is an example of a VPN load-balancing command sequence that includes a **cluster key** command that sets the shared secret of the virtual load-balancing cluster to 123456789:

```
hostname(config)# interface GigabitEthernet 0/1
hostname(config-if)# ip address 209.165.202.159 255.255.255.0
hostname(config)# nameif test
hostname(config)# interface GigabitEthernet 0/2
hostname(config-if)# ip address 209.165.201.30 255.255.255.0
hostname(config)# nameif foo
hostname(config)# vpn load-balancing
hostname(config-load-balancing)# interface lbpublic test
hostname(config-load-balancing)# interface lbprivate foo
hostname(config-load-balancing)# cluster ip address 209.165.202.224
```

```
hostname(config-load-balancing)# cluster key 123456789  
hostname(config-load-balancing)# cluster encryption  
hostname(config-load-balancing)# participate
```

Related Commands

Command	Description
vpn load-balancing	Enters VPN load-balancing mode.

cluster port

To set the UDP port for the virtual load-balancing cluster, use the **cluster port** command in VPN load-balancing mode. To remove the port specification, use the **no** form of this command.

cluster port *port*

no cluster port [*port*]

Syntax Description

port The UDP port that you want to assign to the virtual load-balancing cluster.

Defaults

The default cluster port is 9023.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
VPN load-balancing mode	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must first use the **vpn load-balancing** command to enter VPN load-balancing mode.

You can specify any valid UDP port number. The range is 1-65535.

If you specify a value for *port* in the **no cluster port** form of the command, the port number specified must match the existing configured port number.

Examples

The following is an example of a VPN load-balancing command sequence that includes a **cluster port address** command that sets the UDP port for the virtual load-balancing cluster to 9023:

```
hostname(config)# interface GigabitEthernet 0/1
hostname(config-if)# ip address 209.165.202.159 255.255.255.0
hostname(config)# nameif test
hostname(config)# interface GigabitEthernet 0/2
hostname(config-if)# ip address 209.165.201.30 255.255.255.0
hostname(config)# nameif foo
hostname(config)# vpn load-balancing
hostname(config-load-balancing)# interface lbpublic test
hostname(config-load-balancing)# interface lbprivate foo
hostname(config-load-balancing)# cluster ip address 209.165.202.224
hostname(config-load-balancing)# cluster port 9023
hostname(config-load-balancing)# participate
```


Related Commands

Command	Description
vpn load-balancing	Enters VPN load-balancing mode.

command-alias

To create an alias for a command, use the **command-alias** command in global configuration mode. To remove the alias, use the **no** form of this command. When you enter the command alias, the original command is invoked. You might want to create command aliases to provide shortcuts for long commands, for example.

command-alias *mode command_alias original_command*

no command-alias *mode command_alias original_command*

Syntax Description

<i>mode</i>	Specifies the command mode in which you want to create the command alias, for example exec (for user and privileged EXEC modes), configure , or interface .
<i>command_alias</i>	Specifies the new name you want for an existing command.
<i>original_command</i>	Specifies the existing command or command with its keywords for which you want to create the command alias.

Defaults

By default, the following user EXEC mode aliases are configured:

h for **help**

lo for **logout**

p for **ping**

s for **show**

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines

You can create an alias for the first part of any command and still enter the additional keywords and arguments as normal.

When you use CLI help, command aliases are indicated by an asterisk (*), and displayed in the following format:

*command-alias=original-command

For example, the **lo** command alias displays along with other privileged EXEC mode commands that start with “lo,” as follows:

```
hostname# lo?
*lo=logout login logout
```

You can use the same alias in different modes. For example, you can use “happy” in privileged EXEC mode and configuration mode to alias different commands, as follows:

```
hostname(config)# happy?

configure mode commands/options:
*happy="username crichton password test"

exec mode commands/options:
*happy=enable
```

To list only commands and omit aliases, begin your input line with a space. Also, to circumvent command aliases, use a space before entering the command. In the following example, the alias happy is not shown, because there is a space before the happy? command.

```
hostname(config)# alias exec test enable
hostname(config)# exit
hostname# happy?
ERROR: % Unrecognized command
```

As with commands, you can use CLI help to display the arguments and keywords that can follow a command alias.

You must enter the complete command alias. Shortened aliases are not accepted. In the following example, the parser does not recognize the command hap as indicating the alias happy:

```
hostname# hap
% Ambiguous command: "hap"
```

Examples

The following example shows how to create a command alias named “save” for the **copy running-config startup-config** command:

```
hostname(config)# command-alias exec save copy running-config startup-config
hostname(config)# exit
hostname# save
```

```
Source filename [running-config]?
Cryptochecksum: 50d131d9 8626c515 0c698f7f 613ae54e
```

```
2209 bytes copied in 0.210 secs
hostname#
```

Related Commands

Command	Description
clear configure command-alias	Clears all non-default command aliases.
show running-config command-alias	Displays all non-default command aliases configured.

command-queue

To specify the maximum number of MGCP commands that are queued while waiting for a response, use the **command-queue** command in MGCP map configuration mode. To remove the configuration, use the **no** form of this command.

command-queue *limit*

no command-queue *limit*

Syntax Description

limit Specifies the maximum number of commands to queue, from 1 to 2147483647.

Defaults

This command is disabled by default.

The default for the MGCP command queue is 200.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
MGCP map configuration	•	•	•	•	No

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **command-queue** command to specify the maximum number of MGCP commands that are queued while waiting for a response. The range of allowed values is from 1 to 4294967295. The default is 200. When the limit has been reached and a new command arrives, the command that has been in the queue for the longest time is removed.

Examples

The following example limits the MGCP command queue to 150 commands:

```
hostname(config)# mgcp-map mgcp_policy
hostname(config-mgcp-map)#command-queue 150
```

Related Commands

Commands	Description
debug mgcp	Enables the display of debug information for MGCP.
mgcp-map	Defines an MGCP map and enables MGCP map configuration mode.
show mgcp	Displays MGCP configuration and session information.

Commands	Description
timeout mgcp	Configures the idle timeout after which an MGCP media connection will be closed.
timeout mgcp-pat	Configures the idle timeout after which an MGCP PAT xlate will be removed.

compatible rfc1583

To restore the method that is used to calculate the summary route costs per RFC 1583, use the **compatible rfc1583** command in router configuration mode. To disable RFC 1583 compatibility, use the **no** form of this command.

compatible rfc1583

no compatible rfc1583

Syntax Description

This command has no arguments or keywords.

Defaults

This command is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Only the **no** form of this command appears in the configuration.

Examples

The following example shows how to disable RFC 1583-compatible route summary cost calculation:

```
hostname(config-router)# no compatible rfc1583
hostname(config-router)#
```

Related Commands

Command	Description
router ospf	Enters router configuration mode.
show running-config router	Displays the commands in the global router configuration.

config-register

To set the configuration register value that is used the next time you reload the security appliance, use the **config-register** command in global configuration mode. To set the value back to the default, use the **no** form of this command. This command is only supported on the ASA 5500 adaptive security appliance. The configuration register value determines which image to boot from as well as other boot parameters.

config-register *hex_value*

no config-register

Syntax Description

hex_value

Sets the configuration register value as a hexadecimal number from 0x0 to 0xFFFFFFFF. This number represents 32 bits and each hexadecimal character represents 4 bits. Each bit controls a different characteristic. However, bits 32 through 20 are either reserved for future use, cannot be set by the user, or are not currently used by the security appliance; therefore, you can ignore the three characters that represent those bits, because they are always set to 0. The relevant bits are represented by 5 hexadecimal characters: 0xnnnnn.

You do not need to include preceding 0s. You do need to include trailing 0s. For example, 0x2001 is equivalent to 0x02001; but 0x10000 requires all the zeros. See [Table 3-1](#) for more information about available values for the relevant bits.

Defaults

The default value is 0x1, which boots from the local image and startup configuration.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The five characters are numbered from 0 to 4 from right to left, which is standard for hexadecimal and binary numbers. You can select one value for each character, and mix and match values as appropriate. For example, you can select either 0 or 2 for character number 3. Some values take priority if they conflict with other values. For example, if you set 0x2011, which sets the security appliance to both boot

from the TFTP server and to boot from the local image, the security appliance boots from the TFTP server. Because this value also stipulates that if the TFTP boot fails, the security appliance should boot directly into ROMMON, then the action that specifies to boot from the default image is ignored.

A value of 0 means no action unless otherwise specified.

Table 3-1 lists the actions associated with each hexadecimal character; choose one value for each character:

Table 3-1 Configuration Register Values

Prefix	Hexadecimal Character Numbers 4, 3, 2, 1, and 0				
0x	0	0	0 ¹	0 ²	0 ²
	1	2		1	1
	Disables the 10 second ROMMON countdown during startup. Normally, you can press Escape during the countdown to enter ROMMON.	If you set the security appliance to boot from a TFTP server, and the boot fails, then this value boots directly into ROMMON.		Boots from the TFTP server image as specified in the ROMMON Boot Parameters (which is the same as the boot system tftp command, if present). This value takes precedence over a value set for character 1.	Boots the image specified by the first boot system local_flash command. If that image does not load, the security appliance tries to boot each image specified by subsequent boot system commands until it boots successfully.
					3, 5, 7, 9
					Boots the image specified by a particular boot system local_flash command. Value 3 boots the image specified in the first boot system command, value 5 boots the second image, and so on.
					If the image does not boot successfully, the security appliance does not attempt to fall back to other boot system command images (this is the difference between using value 1 and value 3). However, the security appliance has a failsafe feature that in the event of a boot failure attempts to boot from any image found in the root directory of internal Flash memory. If you do not want the failsafe feature to take effect, store your images in a different directory than root.
				4³	2, 4, 6, 8
				Ignores the startup configuration and loads the default configuration.	From ROMMON, if you enter the boot command without any arguments, then the security appliance boots the image specified by a particular boot system local_flash command. Value 3 boots the image specified in the first boot system command, value 5 boots the second image, and so on. This value does not automatically boot an image.
				5	
				Performs both actions above.	

1. Reserved for future use.
2. If character numbers 0 and 1 are not set to automatically boot an image, then the security appliance boots directly into ROMMON.
3. If you disable password recovery using the **service password-recovery** command, then you cannot set the configuration register to ignore the startup configuration.

The configuration register value is not replicated to a standby unit, but the following warning is displayed when you set the configuration register on the active unit:

WARNING The configuration register is not synchronized with the standby, their values may not match.

You can also set the configuration register value in ROMMON using the **confreg** command.

Examples

The following example sets the configuration register to boot from the default image:

```
hostname(config)# config-register 0x1
```

Related Commands

Command	Description
boot	Sets the boot image and startup configuration.
service password-recovery	Enables or disables password recovery.

configure factory-default

To restore the configuration to the factory default, use the **configure factory-default** command in global configuration mode. The factory default configuration is the configuration applied by Cisco to new security appliances. This command is not supported on all platforms; see the CLI help for the **configure** command to confirm if the command is supported (enter **configure ?** at the global configuration prompt). The factory default configuration automatically configures an interface for management so you can connect to it using ASDM, with which you can then complete your configuration.

configure factory-default [*ip_address* [*mask*]]

Syntax Description	<i>ip_address</i>	Sets the IP address of the management interface, instead of using the default address, 192.168.1.1. If your platform includes a dedicated management interface, then this IP address applies to that interface. If your platform includes only data interfaces, then this address applies to the Ethernet 1 interface.
	<i>mask</i>	Sets the subnet mask of the interface. If you do not set a mask, the security appliance uses the mask appropriate for the IP address class.

Defaults	The default IP address and mask are 192.168.1.1 and 255.255.255.0.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•		•		

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines

The **configure factory-default** command configures the minimum commands required to connect to the security appliance using ASDM. This command is available only for routed firewall mode; transparent mode does not support IP addresses for interfaces, and setting the interface IP address is one of the actions this command takes. This command is also only available in single context mode; a security appliance with a cleared configuration does not have any defined contexts to automatically configure using this command.

This command clears the current running configuration and then configures several commands. The configured interface depends on your platform. For a platform with a dedicated management interface, the interface is named “management.” For other platforms, the configured interface is Ethernet 1 and named “inside.”

The following commands apply to the dedicated management interface, Management 0/0 (for a platform without a dedicated management interface, the interface is Ethernet 1):

```
interface management 0/0
  ip address 192.168.1.1 255.255.255.0
  nameif management
  security-level 100
  no shutdown
asdm logging informational 100
asdm history enable
http server enable
http 192.168.1.0 255.255.255.0 management
dhcpd address 192.168.1.2-192.168.1.254 management
dhcpd lease 3600
dhcpd ping_timeout 750
dhcpd enable management
```

If you set the IP address in the **configure factory-default** command, then the **http** command uses the subnet you specify. Similarly, the **dhcpd address** command range consists of addresses within the subnet that you specify.

After you restore the factory default configuration, save it to internal Flash memory using the **copy running-config startup-config** command. The **copy** command saves the running configuration to the default location for the startup configuration, even if you previously configured the **boot config** command to set a different location; when the configuration was cleared, this path was also cleared.



Note

This command also clears the **boot system** command, if present, along with the rest of the configuration. The **boot system** command lets you boot from a specific image, including an image on the external Flash memory card. The next time you reload the security appliance after restoring the factory configuration, it boots from the first image in internal Flash memory; if you do not have an image in internal Flash memory, the security appliance does not boot.

To configure additional settings that are useful for a full configuration, see the **setup** command.

Examples

The following example resets the configuration to the factory default, assigns the IP address 10.1.1.1 to the interface, and then saves the new configuration as the startup configuration:

```
hostname(config)# configure factory-default 10.1.1.1 255.255.255.0
Based on the inside IP address and mask, the DHCP address
pool size is reduced to 253 from the platform limit 256
```

```
WARNING: The boot system configuration will be cleared.
The first image found in disk0:/ will be used to boot the
system on the next reload.
Verify there is a valid image on disk0:/ or the system will
not boot.
```

```
Begin to apply factory-default configuration:
Clear all configuration
...
hostname(config)#
hostname(config)# copy running-config startup-config
```

Related Commands

Command	Description
boot system	Sets the software image from which to boot.
clear configure	Clears the running configuration.
copy running-config startup-config	Copies the running configuration to the startup configuration.
setup	Prompts you to configure basic settings for the security appliance.
show running-config	Shows the running configuration.

configure http

To merge a configuration file from an HTTP(S) server with the running configuration, use the **configure http** command in global configuration mode. This command supports IPv4 and IPv6 addresses.

configure http[s]://[user[:password]@]server[:port]/[path/]filename

Syntax Description

:password	(Optional) For HTTP(S) authentication, specifies the password.
:port	(Optional) Specifies the port. For HTTP, the default is 80. For HTTPS, the default is 443.
@	(Optional) If you enter a name and/or a password, precedes the server IP address with an at sign (@).
filename	Specifies the configuration filename.
http[s]	Specifies either HTTP or HTTPS.
path	(Optional) Specifies a path to the filename.
server	Specifies the server IP address or name. For IPv6 server addresses, if you specify the port, then you must enclose the IP address in brackets so that the colons in the IP address are not mistaken for the colon before the port number. For example, enter the following address and port: [fe80::2e0:b6ff:fe01:3b7a]:8080
user	(Optional) For HTTP(S) authentication, specifies the username.

Defaults

For HTTP, the default port is 80. For HTTPS, the default port is 443.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

A merge adds all commands from the new configuration to the running configuration, and overwrites any conflicting commands with the new versions. For example, if a command allows multiple instances, the new commands are added to the existing commands in the running configuration. If a command allows only one instance, the new command overwrites the command in the running configuration. A merge never removes commands that exist in the running configuration but are not set in the new configuration.

This command is the same as the **copy http running-config** command. For multiple context mode, that command is only available in the system execution space, so the **configure http** command is an alternative for use within a context.

Examples

The following example copies a configuration file from an HTTPS server to the running configuration:

```
hostname(config)# configure https://user1:pa$$w0rd@10.1.1.1/configs/newconfig.cfg
```

Related Commands

Command	Description
clear configure	Clears the running configuration.
configure memory	Merges the startup configuration with the running configuration.
configure net	Merges a configuration file from the specified TFTP URL with the running configuration.
configure factory-default	Adds commands you enter at the CLI to the running configuration.
show running-config	Shows the running configuration.

configure memory

To merge the startup configuration with the running configuration, use the **configure memory** command in global configuration mode.

configure memory

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines A merge adds all commands from the new configuration to the running configuration, and overwrites any conflicting commands with the new versions. For example, if a command allows multiple instances, the new commands are added to the existing commands in the running configuration. If a command allows only one instance, the new command overwrites the command in the running configuration. A merge never removes commands that exist in the running configuration but are not set in the new configuration.

If you do not want to merge the configurations, you can clear the running configuration, which disrupts any communications through the security appliance, and then enter the **configure memory** command to load the new configuration.

This command is equivalent to the **copy startup-config running-config** command.

For multiple context mode, a context startup configuration is at the location specified by the **config-url** command.

Examples The following example copies the startup configuration to the running configuration:

```
hostname(config)# configure memory
```

Related Commands	Command	Description
	clear configure	Clears the running configuration.
	configure http	Merges a configuration file from the specified HTTP(S) URL with the running configuration.
	configure net	Merges a configuration file from the specified TFTP URL with the running configuration.
	configure factory-default	Adds commands you enter at the CLI to the running configuration.
	show running-config	Shows the running configuration.

configure net

To merge a configuration file from a TFTP server with the running configuration, use the **configure net** command in global configuration mode. This command supports IPv4 and IPv6 addresses.

configure net [*server*:*filename*] | :*filename*]

Syntax Description

<i>:filename</i>	Specifies the path and filename. If you already set the filename using the tftp-server command, then this argument is optional. If you specify the filename in this command as well as a name in the tftp-server command, the security appliance treats the tftp-server command filename as a directory, and adds the configure net command filename as a file under the directory. To override the tftp-server command value, enter a slash in front of the path and filename. The slash indicates that the path is not relative to the tftpboot directory, but is an absolute path. The URL generated for this file includes a double slash (//) in front of the filename path. If the file you want is in the tftpboot directory, you can include the path for the tftpboot directory in the filename path. If you specified the TFTP server address using the tftp-server command, you can enter the filename alone preceded by a colon (:).
<i>server</i> :	Sets the TFTP server IP address or name. This address overrides the address you set in the tftp-server command, if present. For IPv6 server addresses, you must enclose the IP address in brackets so that the colons in the IP address are not mistaken for the colon before the filename. For example, enter the following address: [fe80::2e0:b6ff:fe01:3b7a] The default gateway interface is the highest security interface; however, you can set a different interface name using the tftp-server command.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

A merge adds all commands from the new configuration to the running configuration, and overwrites any conflicting commands with the new versions. For example, if a command allows multiple instances, the new commands are added to the existing commands in the running configuration. If a command allows only one instance, the new command overwrites the command in the running configuration. A merge never removes commands that exist in the running configuration but are not set in the new configuration.

This command is the same as the **copy tftp running-config** command. For multiple context mode, that command is only available in the system execution space, so the **configure net** command is an alternative for use within a context.

Examples

The following example sets the server and filename in the **tftp-server** command, and then overrides the server using the **configure net** command. The same filename is used.

```
hostname(config)# tftp-server inside 10.1.1.1 configs/config1
hostname(config)# configure net 10.2.2.2:
```

The following example overrides the server and the filename. The default path to the filename is /tftpboot/configs/config1. The /tftpboot/ part of the path is included by default when you do not lead the filename with a slash (/). Because you want to override this path, and the file is also in tftpboot, include the tftpboot path in the **configure net** command.

```
hostname(config)# tftp-server inside 10.1.1.1 configs/config1
hostname(config)# configure net 10.2.2.2:/tftpboot/oldconfigs/config1
```

The following example sets the server only in the **tftp-server** command. The **configure net** command specifies only the filename.

```
hostname(config)# tftp-server inside 10.1.1.1
hostname(config)# configure net :configs/config1
```

Related Commands

Command	Description
configure http	Merges a configuration file from the specified HTTP(S) URL with the running configuration.
configure memory	Merges the startup configuration with the running configuration.
show running-config	Shows the running configuration.
tftp-server	Sets a default TFTP server and path for use in other commands.
write net	Copies the running configuration to a TFTP server.

configure terminal

To configure the running configuration at the command line, use the **configure terminal** command in privileged EXEC mode. This command enters global configuration mode, which lets you enter commands that change the configuration.

configure terminal

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples The following example enters global configuration mode:

```
hostname# configure terminal
hostname(config)#
```

Related Commands	Command	Description
	clear configure	Clears the running configuration.
	configure http	Merges a configuration file from the specified HTTP(S) URL with the running configuration.
	configure memory	Merges the startup configuration with the running configuration.
	configure net	Merges a configuration file from the specified TFTP URL with the running configuration.
	show running-config	Shows the running configuration.

config-url

To identify the URL from which the system downloads the context configuration, use the **config-url** command in context configuration mode.

config-url *url*

Syntax Description

<i>url</i>	Sets the context configuration URL. All remote URLs must be accessible from the admin context. See the following URL syntax: • disk0:<i>/[path]/filename</i> For the ASA 5500 series adaptive security appliance, this URL indicates the internal Flash memory. You can also use flash instead of disk0; they are aliased. • disk1:<i>/[path]/filename</i> For the ASA 5500 series adaptive security appliance, this URL indicates the external Flash memory card. • flash:<i>/[path]/filename</i> This URL indicates the internal Flash memory. • ftp:<i>//[user[:password]@]server[:port]/[path]/filename[;type=xx]</i> The type can be one of the following keywords: – ap—ASCII passive mode – an—ASCII normal mode – ip—(Default) Binary passive mode – in—Binary normal mode • http[s]:<i>//[user[:password]@]server[:port]/[path]/filename</i> • tftp:<i>//[user[:password]@]server[:port]/[path]/filename[;int=interface_name]</i> Specify the interface name if you want to override the route to the server address.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Context configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines**Note**

When you add a context URL, the system immediately loads the context so that it is running.

Enter the **allocate-interface** command(s) before you enter the **config-url** command. The security appliance must assign interfaces to the context before it loads the context configuration; the context configuration might include commands that refer to interfaces (**interface**, **nat**, **global**...). If you enter the **config-url** command first, the security appliance loads the context configuration immediately. If the context contains any commands that refer to interfaces, those commands fail.

The filename does not require a file extension, although we recommend using “.cfg”.

The admin context file must be stored on the internal Flash memory.

If you download a context configuration from an HTTP or HTTPS server, you cannot save changes back to these servers using the **copy running-config startup-config** command. You can, however, use the **copy tftp** command to copy the running configuration to a TFTP server.

If the system cannot retrieve the context configuration file because the server is unavailable, or the file does not yet exist, the system creates a blank context that is ready for you to configure with the command-line interface.

To change the URL, reenter the **config-url** command with a new URL.

The security appliance merges the new configuration with the current running configuration. Reentering the same URL also merges the saved configuration with the running configuration. A merge adds any new commands from the new configuration to the running configuration. If the configurations are the same, no changes occur. If commands conflict or if commands affect the running of the context, then the effect of the merge depends on the command. You might get errors, or you might have unexpected results. If the running configuration is blank (for example, if the server was unavailable and the configuration was never downloaded), then the new configuration is used. If you do not want to merge the configurations, you can clear the running configuration, which disrupts any communications through the context, and then reload the configuration from the new URL.

Examples

The following example sets the admin context to be “administrator,” creates a context called “administrator” on the internal Flash memory, and then adds two contexts from an FTP server:

```
hostname(config)# admin-context administrator
hostname(config)# context administrator
hostname(config-ctx)# allocate-interface gigabitethernet0/0.1
hostname(config-ctx)# allocate-interface gigabitethernet0/1.1
hostname(config-ctx)# config-url flash:/admin.cfg

hostname(config-ctx)# context test
hostname(config-ctx)# allocate-interface gigabitethernet0/0.100 int1
hostname(config-ctx)# allocate-interface gigabitethernet0/0.102 int2
hostname(config-ctx)# allocate-interface gigabitethernet0/0.110-gigabitethernet0/0.115
int3-int8
hostname(config-ctx)# config-url ftp://user1:passw0rd@10.1.1.1/configlets/test.cfg

hostname(config-ctx)# context sample
hostname(config-ctx)# allocate-interface gigabitethernet0/1.200 int1
hostname(config-ctx)# allocate-interface gigabitethernet0/1.212 int2
```

```
hostname(config-ctx)# allocate-interface gigabitethernet0/1.230-gigabitethernet0/1.235
int3-int8
hostname(config-ctx)# config-url ftp://user1:passw0rd@10.1.1.1/configlets/sample.cfg
```

Related Commands

Command	Description
allocate-interface	Allocates interfaces to a context.
context	Creates a security context in the system configuration and enters context configuration mode.
show context	Shows a list of contexts (system execution space) or information about the current context.

console timeout

To set the idle timeout for a console connection to the security appliance, use the **console timeout** command in global configuration mode. To disable, use the **no** form of this command.

console timeout *number*

no console timeout [*number*]

Syntax Description

number Specifies the idle time in minutes (0 through 60) after which the console session ends.

Defaults

The default timeout is 0, which means the console session will not time out.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **console timeout** command sets the timeout value for any authenticated, enable mode, or configuration mode user session to the security appliance. The **console timeout** command does not alter the Telnet or SSH timeouts; these access methods maintain their own timeout values.

The **no console timeout** command resets the console timeout value to the default timeout of 0, which means that the console will not time out.

Examples

The following example shows how to set the console timeout to 15 minutes:

```
hostname(config)# console timeout 15
```

Related Commands

Command	Description
clear configure console	Restores the default console connection settings.
show running-config console timeout	Displays the idle timeout for a console connection to the security appliance.

content-length

To restrict HTTP traffic based on the length of the HTTP message body, use the **content-length** command in HTTP map configuration mode, which is accessible using the **http-map** command. To remove this command, use the **no** form of this command.

content-length { **min** *bytes* [**max** *bytes*] | **max** *bytes* } **action** { **allow** | **reset** | **drop** } [**log**]

no content-length { **min** *bytes* [**max** *bytes*] | **max** *bytes* } **action** { **allow** | **reset** | **drop** } [**log**]

Syntax Description

action	Specifies the action taken when a message fails this inspection.
allow	Allows the message.
bytes	Specifies the number of bytes. The permitted range is 1 to 65535 for the min option and 1 to 50000000 for the max option.
drop	Closes the connection.
log	(Optional) Generates a syslog.
max	(Optional) Specifies the maximum content length allowed.
min	Specifies the minimum content length allowed.
reset	Sends a TCP reset message to client and server.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
HTTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

After enabling the **content-length** command, the security appliance only allows messages within the configured range and otherwise takes the specified action. Use the **action** keyword to cause the security appliance to reset the TCP connection and create a syslog entry.

Examples

The following example restricts HTTP traffic to messages 100 bytes or larger and not exceeding 2000 bytes. If a message is outside this range, the security appliance resets the TCP connection and creates a syslog entry.

```
hostname(config)# http-map inbound_http
hostname(config-http-map)# content-length min 100 max 2000 action reset log
hostname(config-http-map)# exit
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
http-map	Defines an HTTP map for configuring enhanced HTTP inspection.
debug appfw	Displays detailed information about traffic associated with enhanced HTTP inspection.
inspect http	Applies a specific HTTP map to use for application inspection.
policy-map	Associates a class map with specific security actions.

content-type-verification

To restrict HTTP traffic based on the content type of the HTTP message, use the **content-type-verification** command, in HTTP map configuration mode, which is accessible using the **http-map** command. To disable this feature, use the **no** form of the command.

content-type-verification [**match-req-rsp**] **action** {**allow** | **reset** | **drop**} [**log**]

no content-type-verification [**match-req-rsp**] **action** {**allow** | **reset** | **drop**} [**log**]

Syntax Description

action	Specifies the action taken when a message fails command inspection.
allow	Allows the message.
drop	Closes the connection.
log	(Optional) Generates a syslog message.
match-req-rsp	(Optional) Verifies that the content-type field in the HTTP response matches the accept field in the corresponding HTTP request message.
reset	Sends a TCP reset message to client and server.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
HTTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced

Usage Guidelines

This command enables the following checks:

- Verifies that the value of the header content-type is in the internal list of supported content types,
- Verifies that the header content-type matches the actual content in the data or entity body portion of the message.
- The **match-req-rsp** keyword enables an additional check that verifies the content-type field in the HTTP response matches the **accept** field in the corresponding HTTP request message.

If the message fails any of the above checks, the security appliance takes the configured action.

The following is the list of supported content types.

audio/*	audio/basic	video/x-msvideo
audio/mpeg	audio/x-adpcm	audio/midi
audio/x-ogg	audio/x-wav	audio/x-aiff
application/octet-stream	application/pdf	application/msword
application/vnd.ms-excel	application/vnd.ms-powerpoint	application/postscript
application/x-java-arching	application/x-msn-messenger	application/x-gzip
image	application/x-java-xm	application/zip
image/jpeg	image/cgf	image/gif
image/x-3ds	image/png	image/tiff
image/x-portable-bitmap	image/x-bitmap	image/x-niff
text/*	image/x-portable-greymap	image/x-xpm
text/plain	text/css	text/html
text/xmcd	text/richtext	text/sgml
video/-flc	text/xml	video/*
video/sgi	video/mpeg	video/quicktime
video/x-mng	video/x-avi	video/x-fli

Some content-types in this list may not have a corresponding regular expression (magic number) so they cannot be verified in the body portion of the message. When this case occurs, the HTTP message will be allowed.

Examples

The following example restricts HTTP traffic based on the content type of the HTTP message. If a message contains an unsupported content type, the security appliance resets the TCP connection and creates a syslog entry.

```
hostname(config)# http-map inbound_http
hostname(config-http-map)# content-type-verification match-req-rsp reset log
hostname(config-http-map)# exit
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
http-map	Defines an HTTP map for configuring enhanced HTTP inspection.
debug appfw	Displays detailed information about traffic associated with enhanced HTTP inspection.
inspect http	Applies a specific HTTP map to use for application inspection.
policy-map	Associates a class map with specific security actions.

context

To create a security context in the system configuration and enter context configuration mode, use the **context** command in global configuration mode. To remove a context, use the **no** form of this command. In context configuration mode, you can identify the configuration file URL and interfaces that a context can use.

context *name*

no context *name* [**noconfirm**]

Syntax Description

<i>name</i>	Sets the name as a string up to 32 characters long. This name is case sensitive, so you can have two contexts named “customerA” and “CustomerA,” for example. You can use letters, digits, or hyphens, but you cannot start or end the name with a hyphen. “System” or “Null” (in upper or lower case letters) are reserved names, and cannot be used.
noconfirm	(Optional) Removes the context without prompting you for confirmation. This option is useful for automated scripts.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If you do not have an admin context (for example, if you clear the configuration) then the first context you add must be the admin context. To add an admin context, see the **admin-context** command. After you specify the admin context, you can enter the **context** command to configure the admin context.

You can only remove a context by editing the system configuration. You cannot remove the current admin context using the **no** form of this command; you can only remove it if you remove all contexts using the **clear configure context** command.

Examples

The following example sets the admin context to be “administrator,” creates a context called “administrator” on the internal Flash memory, and then adds two contexts from an FTP server:

```

hostname(config)# admin-context administrator
hostname(config)# context administrator
hostname(config-ctx)# allocate-interface gigabitethernet0/0.1
hostname(config-ctx)# allocate-interface gigabitethernet0/1.1
hostname(config-ctx)# config-url flash:/admin.cfg

hostname(config-ctx)# context test
hostname(config-ctx)# allocate-interface gigabitethernet0/0.100 int1
hostname(config-ctx)# allocate-interface gigabitethernet0/0.102 int2
hostname(config-ctx)# allocate-interface gigabitethernet0/0.110-gigabitethernet0/0.115
int3-int8
hostname(config-ctx)# config-url ftp://user1:passw0rd@10.1.1.1/configlets/test.cfg

hostname(config-ctx)# context sample
hostname(config-ctx)# allocate-interface gigabitethernet0/1.200 int1
hostname(config-ctx)# allocate-interface gigabitethernet0/1.212 int2
hostname(config-ctx)# allocate-interface gigabitethernet0/1.230-gigabitethernet0/1.235
int3-int8
hostname(config-ctx)# config-url ftp://user1:passw0rd@10.1.1.1/configlets/sample.cfg

```

Related Commands

Command	Description
allocate-interface	Assigns interfaces to a context.
changeto	Changes between contexts and the system execution space.
config-url	Specifies the location of the context configuration.
join-failover-group	Assigns a context to a failover group.
show context	Shows context information.

copy

To copy a file from one location to another, use the **copy** command.

copy [/options] {url | local:[path] | running-config | startup-config} {running-config | startup-config | url | local:[path]}

no copy [/options] {url | local:[path] | running-config | startup-config} {running-config | startup-config | url | local:[path]}

Syntax Description	
<i>/options</i>	Options used for the copy command. • noconfirm Copies the file without a confirmation prompt. • pcap Specifies the defaults of the preconfigured TFTP server.
<i>url</i>	Sets the context configuration URL. All remote URLs must be accessible from the admin context. See the following URL syntax: • disk0:/[path]/filename This option is only available for the ASA platform, and indicates the internal Flash memory. You can also use flash instead of disk0; they are aliased. • disk1:/[path]/filename This option is only available for the ASA platform, and indicates the external Flash memory card. • flash:/[path]/filename This option indicates the internal Flash card. For the ASA platform, flash is an alias for disk0. • ftp://[user[:password]@]server[:port]/[path]/filename[;type=xx] The type can be one of the following keywords: – ap—ASCII passive mode – an—ASCII normal mode – ip—(Default) Binary passive mode – in—Binary normal mode • http[s]://[user[:password]@]server[:port]/[path]/filename • tftp://[user[:password]@]server[:port]/[path]/filename[;int=interface_name] Specify the interface name if you want to override the route to the server address.
<i>path</i>	Pathname that indicates the last component of the path to the file on the server.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged mode	•	•	•	•	•

Command History

Release	Modification
7.0	Support for this command was introduced.

Usage Guidelines

The security appliance must know how to reach the location (specified by the *tftp_pathname* argument) through its routing table information. This information is determined by the **ip address** command, the **route** command, or the RIP, depending upon the configuration. The *tftp_pathname* can include any directory names in addition to the last component of the path to the file on the server.

The *pathname* can include any directory names in addition to the last component of the path to the file on the server. The pathname cannot contain spaces. If a directory name has spaces, set the directory in the TFTP server instead of in the **copy tftp flash** command

Examples

This example shows how to copy a file from the disk to a TFTP server:

```
hostname(config)# copy disk0:my_context/my_context.cfg
tftp://10.7.0.80/my_context/my_context.cfg
```

This example shows how to copy a file from one location on the disk to another location on the disk. The name of the destination file can be either the name of the source file or a different name.

```
hostname(config)# copy disk0:my_context.cfg disk0:my_context/my_context.cfg
```

This example shows how to copy an image or an ASDM file from the disk to the Flash partition:

```
hostname(config)# copy tftp://10.7.0.80/asa700.bin disk0:asa700.bin
hostname(config)# copy tftp://10.7.0.80/asdm700.bin disk0:asdm700.bin
```

This example shows how to copy a file from the disk to the startup configuration or a running configuration:

```
hostname(config)# copy disk:my_context/my_context.cfg startup-config
hostname(config)# copy disk:my_context/my_context.cfg running-config
```

Related Commands

Command	Description
copy capture	Copies a capture file to a TFTP server.

copy capture

To copy a capture file to a server, use the **copy capture** command in privileged EXEC mode.

copy [/noconfirm] [/pcap] **capture:** [context_name/]buffer_name url

Syntax Description	
/noconfirm	Copies the file without a confirmation prompt.
/pcap	Copies the packet capture as raw data.
buffer_name	Unique name that identifies the capture.
context_name/	Copies a packet capture defined in a security context.
url	Specifies the destination to copy the packet capture file. See the following URL syntax: disk0:/[path/]filename This option is only available for the ASA 5500 series adaptive security appliance, and indicates the internal Flash card. You can also use flash instead of disk0; they are aliased. disk1:/[path/]filename This option is only available for the ASA 5500 series adaptive security appliance, and indicates the external Flash card. flash:/[path/]filename This option indicates the internal Flash card. For the ASA 5500 series adaptive security appliance, flash is an alias for disk0. ftp://[user[:password]@]server[:port]/[path/]filename[;type=xx] The type can be one of the following keywords: ap—ASCII passive mode an—ASCII normal mode ip—(Default) Binary passive mode in—Binary normal mode http[s]://[user[:password]@]server[:port]/[path/]filename tftp://[user[:password]@]server[:port]/[path/]filename[;int=interface_name] Specify the interface name if you want to override the route to the server address. The pathname cannot contain spaces. If a pathname has spaces, set the path in the tftp-server command instead of in the copy tftp command.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0(1)	This command was introduced.

Examples

The following example shows the prompts that are provided when you enter the **copy capture** command without specifying the full path:

```
hostname(config)# copy capture:abc tftp
Address or name of remote host [171.68.11.129]?
Source file name [username/cdisk]?
copying capture to tftp://171.68.11.129/username/cdisk:
[yes|no|again]? y
!!!!!!!!!!!!!!
```

You can specify the full path as follows:

```
hostname(config)# copy capture:abc tftp:171.68.11.129/tftpboot/abc.cap
```

If the TFTP server is already configured, the location or filename can be unspecified as follows:

```
hostname(config)# tftp-server outside 171.68.11.129 tftp/cdisk
hostname(config)# copy capture:abc tftp:/tftp/abc.cap
```

Related Commands

Command	Description
capture	Enables packet capture capabilities for packet sniffing and network fault isolation.
clear capture	Clears the capture buffer.
show capture	Displays the capture configuration when no options are specified.

crashinfo console disable

To read, write, and configure crash write to flash, use the **crashinfo console disable** command.

crashinfo console disable

[no] crashinfo console disable

Syntax Description

disable Suppresses console output in the event of a crash.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0(4)	This command was introduced.

Usage Guidelines

This command lets you suppress crashinfo from being output to the console. The crashinfo may contain sensitive information that is not appropriate for viewing by all users connected to the device. In conjunction with this command, you should also ensure crashinfo is written to flash, which can be examined after the device reboots. This command effects output for crashinfo and checkheaps, which is saved to flash and should be sufficient for troubleshooting.

Examples

```
hostname(config)# crashinfo console disable
```

Related Commands

Command	Description
clear configure fips	Clears the system or module FIPS configuration information stored in NVRAM.
fips enable	Enables or disables policy-checking to enforce FIPS compliance on the system or module.
fips self-test poweron	Executes power-on self-tests.

Command	Description
show crashinfo console	Reads, writes, and configures crash write to flash.
show running-config fips	Displays the FIPS configuration that is running on the FWSM.

crashinfo force

To force the security appliance to crash, use the **crashinfo force** command in privileged EXEC mode.

crashinfo force [**page-fault** | **watchdog**]

Syntax Description

page-fault	(Optional) Forces a crash of the security appliance as a result of a page fault.
watchdog	(Optional) Forces a crash of the security appliance as a result of watchdogging.

Defaults

The security appliance saves the crash information file to Flash memory by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

You can use the **crashinfo force** command to test the crash output generation. In the crash output, there is nothing that differentiates a real crash from a crash resulting from the **crashinfo force page-fault** or **crashinfo force watchdog** command (because these are real crashes). The security appliance reloads after the crash dump is complete.



Caution

Do not use the **crashinfo force** command in a production environment. The **crashinfo force** command crashes the security appliance and forces it to reload.

Examples

The following example shows the warning that displays when you enter the **crashinfo force page-fault** command:

```
hostname# crashinfo force page-fault
WARNING: This command will force the XXX to crash and reboot.
Do you wish to proceed? [confirm]:
```

If you enter a carriage return (by pressing the Return or Enter key on your keyboard), “y”, or “Y” the security appliance crashes and reloads; any of these responses are interpreted as confirmation. Any other character is interpreted as a **no**, and the security appliance returns to the command-line prompt.

Related Commands

clear crashinfo	Clears the contents of the crash information file.
crashinfo save disable	Disables crash information from writing to Flash memory.
crashinfo test	Tests the ability of the security appliance to save crash information to a file in Flash memory.
show crashinfo	Displays the contents of the crash information file.

crashinfo save disable

To disable crash information from writing to Flash memory, use the **crashinfo save** command in global configuration mode.

crashinfo save disable

no crashinfo save disable

Syntax Description

This command has no default arguments or keywords.

Defaults

The security appliance saves the crash information file to Flash memory by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	The crashinfo save enable command was deprecated and is no longer a valid option. Use the no crashinfo save disable command instead.

Usage Guidelines

Crash information writes to Flash memory first, and then to your console.



Note

If the security appliance crashes during startup, the crash information file is not saved. The security appliance must be fully initialized and running first, before it can save crash information to Flash memory.

Use the **no crashinfo save disable** command to re-enable saving the crash information to Flash memory.

Examples

```
hostname(config)# crashinfo save disable
```

Related Commands

clear crashinfo	Clears the contents of the crash file.
crashinfo force	Forces a crash of the security appliance.

crashinfo test	Tests the ability of the security appliance to save crash information to a file in Flash memory.
show crashinfo	Displays the contents of the crash file.

crashinfo test

To test the ability of the security appliance to save crash information to a file in Flash memory, use the **crashinfo test** command in global configuration mode.

crashinfo test

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If a previous crash information file already exists in Flash memory, that file is overwritten.



Note

Entering the **crashinfo test** command does not crash the security appliance.

Examples

The following example shows the output of a crash information file test.

```
hostname(config)# crashinfo test
```

Related Commands

clear crashinfo	Deletes the contents of the crash file.
crashinfo force	Forces the security appliance to crash.
crashinfo save disable	Disables crash information from writing to Flash memory.
show crashinfo	Displays the contents of the crash file.

crl

To specify CRL configuration options, use the **crl** command in **crypto ca trustpoint** configuration mode.

crl { required | optional | nocheck }

Syntax Description

required	The required CRL must be available for a peer certificate to be validated.
optional	The security appliance can still accept the peer certificate if the required CRL is not available.
nocheck	Directs the security appliance not to perform CRL checking.

Defaults

The default value is **nocheck**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters **crypto ca trustpoint** configuration mode for **trustpoint central**, and requires that a CRL be available for a peer certificate to be validated for **trustpoint central**:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# crl required
hostname(ca-trustpoint)#
```

Related Commands

Command	Description
clear configure crypto ca trustpoint	Removes all trustpoints.
crypto ca trustpoint	Enters trustpoint submode.
crl configure	Enters crl configuration mode.

crl configure

To enter CRL configuration configuration mode, use the **crl configure** command in crypto ca trustpoint configuration mode.

crl configure

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters crl configuration mode within trustpoint central:

```
hostname<config># crypto ca trustpoint central
hostname<ca-trustpoint># crl configure
hostname<ca-crl>#
```

Related Commands

Command	Description
clear configure crypto ca trustpoint	Removes all trustpoints.
crypto ca trustpoint	Enters trustpoint submode.

crypto ca authenticate

To install and authenticate the CA certificates associated with a trustpoint, use the **crypto ca authenticate** command in global configuration mode. To remove the CA certificate, use the **no** form of this command.

crypto ca authenticate *trustpoint* [**fingerprint** *hexvalue*] [**nointeractive**]

no crypto ca authenticate *trustpoint*

Syntax Description

fingerprint	Specifies a hash value consisting of alphanumeric characters the security appliance uses to authenticate the CA certificate. If a fingerprint is provided, the security appliance compares it to the computed fingerprint of the CA certificate and accepts the certificate only if the two values match. If there is no fingerprint, the security appliance displays the computed fingerprint and asks whether to accept the certificate.
<i>hexvalue</i>	Identifies the hexadecimal value of the fingerprint.
nointeractive	Obtains the CA certificate for this trustpoint using no interactive mode; intended for use by the device manager only. In this case, if there is no fingerprint, the security appliance accepts the certificate without question.
<i>trustpoint</i>	Specifies the trustpoint from which to obtain the CA certificate. Maximum name length is 128 characters.

Defaults

This command has no default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced

Usage Guidelines

If the trustpoint is configured for SCEP enrollment, the CA certificate is downloaded through SCEP. If not, the security appliance prompts you to paste the base-64 formatted CA certificate onto the terminal.

The invocations of this command do not become part of the running configuration.

Examples

In the following example, the security appliance requests the certificate of the CA. The CA sends its certificate and the security appliance prompts the administrator to verify the certificate of the CA by checking the CA certificate fingerprint. The security appliance administrator should verify the fingerprint value displayed against a known, correct value. If the fingerprint displayed by the security appliance matches the correct value, you should accept the certificate as valid.

```
hostname(config)# crypto ca authenticate myca
Certificate has the following attributes:
Fingerprint: 0123 4567 89AB CDEF 0123
Do you accept this certificate? [yes/no] y#
hostname(config)#
```

In the next example, the trustpoint tp9 is configured for terminal-based (manual) enrollment. In this case the security appliance prompts the administrator to paste the CA certificate to the terminal. After displaying the fingerprint of the certificate, the security appliance prompts the administrator to confirm that the certificate should be retained.

```
hostname(config)# crypto ca authenticate tp9
Enter the base 64 encoded CA certificate.
End with a blank line or the word "quit" on a line by itself
```

```
MIIDjCCAvEgAwIBAgIQejIaQ3SJRIBMHcvDdgOsKTANBgkqhkiG9w0BAQUFADBA
MQswCQYDVQQGEwJVUzELMAkGA1UECBMCTUEExETAPBgNVBACETCEZyYW5rbGluMREw
DwYDVQQDEwhtCm1hbnNDQTAeFw0wMjEwMTcxODE5MTJhFw0wNjEwMjEwMTJhMDha
MEAxChAJBgNVBAYTA1VTMQswCQYDVQQIEwJNQTERMA8GA1UEBxMIRnJhbmtsaW4x
ETAPBgNVBAMTCEJyaWFuc0NBMIgfMA0GCSqGSIb3DQEBAQUAA4GNADCBiQKBgQCD
jXEPvNnkZD1bKzahbTHuRot1T8KRUBCP5aWKfqViKJENzI2GnAheArazaAcc4Eaz
LDnpuyyqa0j5LA3MI577MoN1/n11018fbpqOf9eVDPJdKYTvtZ/X3vJgnEjTOWyz
T0pXxhdU1b/jgqVE740vKBzU7A2yoQ2hMYzwVbGkewIDAQABo4IBhzCCAYMwEwYJ
KwYBBAGCNxQCBAYeBABDAEEwCwYDVR0PBAQDAgFGMA8GA1UdEwEB/wQFMAMBAf8w
HQYDVR0OBBYEFBhr3holowFDmniI3FBwKpSEucdtMIIBGwYDVR0fBIIBEjCCAQ4w
gcaggcOggcCGb1sZGFwOi8vL0NOPUJyaWFuc0NBLENOPWJyaWFuLXcyay1zdnIs
Q049Q0RQLENOPVB1YmxpYyUyMETleSUyMFN1cnZpY2VzLENOPVN1cnZpY2VzLENO
PUNvbmZpZ3VyYXRpb24sREM9YnJpYW5wZGMSREM9YmRzLERDPWNvbT9jZXJ0aWZp
Y2F0ZVJldm9jYXRpb25MaXN0P2Jhc2U/b2JqZWN0Y2xhc3M9Y1JMRGlzdHJpYnV0
aW9uUG9pbmQwQ6BBoD+GPWh0dHA6Ly9icmlhbi13Mmstc3ZyLmJyaWFucGRjLmJk
cy5jb20vQ2VydeVucm9sbC9Ccm1hbnNDQS5jcmmwEAYJKwYBBAGCNxUBBAMCAQEW
DQYJKoZIhvcNAQEFBQADgYEA dLhc4Za3AbMjRq66xH1qJWxKUzd4nE9wOrhGgA1r
j4B/Hv2K1gUie34xGqu9OpwqvJgpp/vCU12CiykblYdSDy/PxN4KtR9Xd1JDQMbu5
f20AYqCG5vpPWavCgmgtLcdwKa3ps1YSWGkhWmSchHHSiGgla3tevYVwhHNPA4mWo
7sQ=
```

```
Certificate has the following attributes:
Fingerprint: 21B598D5 4A81F3E5 0B24D12E 3F89C2E4
% Do you accept this certificate? [yes/no]: yes
Trustpoint CA certificate accepted.
% Certificate successfully imported
hostname(config)#
```

Related Commands

Command	Description
crypto ca enroll	Starts enrollment with a CA.
crypto ca import certificate	Installs a certificate received from a CA in response to a manual enrollment request. Also used to import PKS12 data to a trustpoint.
crypto ca trustpoint	Enters the trustpoint submode for the indicated trustpoint.

crypto ca certificate chain

To enter certificate chain configuration mode for the indicated trustpoint, use the **crypto ca certificate chain** command in global configuration mode. To return to global configuration mode, use the **no** form of the command or use the **exit** command.

crypto ca certificate chain *trustpoint*

Syntax Description

trustpoint Specifies the trustpoint for configuring the certificate chain.

Defaults

This command has no default values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters CA certificate chain submode for trustpoint central:

```
hostname<config># crypto ca certificate chain central
hostname<config-cert-chain>#
```

Related Commands

Command	Description
clear configure crypto ca trustpoint	Removes all trustpoints.

crypto ca certificate map

To enter CA certificate map mode, use the **crypto ca configuration map** command in global configuration mode. Executing this command places you in ca-certificate-map mode. Use this group of commands to maintain a prioritized list of certificate mapping rules. The sequence number orders the mapping rules.

To remove a crypto CA configuration map rule, use the **no** form of the command.

crypto ca certificate map *sequence-number*

no crypto ca certificate map [*sequence-number*]

Syntax Description

sequence-number Specifies a number for the certificate map rule you are creating. The range is 1 through 65535. You can use this number when creating a tunnel-group-map, which maps a tunnel group to a certificate map rule.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Issuing this command places the security appliance in CA certificate map configuration mode where you can configure rules based on the certificate's issuer and subject distinguished names (DNs). The general form of these rules is as follows:

DN match-criteria match-value

DN is either *subject-name* or *issuer-name*. DNs are defined in the ITU-T X.509 standard. For a list of certificate fields, see Related Commands.

match-criteria comprise the following expressions or operators:

attr <i>tag</i>	Limits the comparison to a specific DN attribute, such as common name (CN).
co	Contains
eq	Equal

nc	Does not contain
ne	Not equal

The DN matching expressions are case insensitive.

Examples

The following example enters CA certificate map mode with a sequence number of 1 (rule # 1) and specifies that the common name(CN) attribute of the subject-name must match Pat:

```
hostname(config)# crypto ca certificate map 1
hostname(ca-certificate-map)# subject-name attr cn eq pat
hostname(ca-certificate-map)#
```

The following example enters CA certificate map mode with a sequence number of 1 and specifies that the subject-name contain the value cisco anywhere within it:

```
hostname(config)# crypto ca certificate map 1
hostname(ca-certificate-map)# subject-name co cisco
hostname(ca-certificate-map)#
```

Related Commands+

Command	Description
issuer-name	Indicates that rule entry is applied to the issuer DN of the IPSec peer certificate.
subject-name (crypto ca certificate map)	Indicates that rule entry is applied to the subject DN of the IPSec peer certificate.
tunnel-group-map enable	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

crypto ca crl request

To request a CRL based on the configuration parameters of the specified trustpoint, use the **crypto ca crl request** command in Crypto ca trustpoint configuration mode.

crypto ca crl request *trustpoint*

Syntax Description

trustpoint Specifies the trustpoint. Maximum number of characters is 128.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Invocations of this command do not become part of the running configuration.

Examples

The following example requests a CRL based on the trustpoint named central:

```
hostname(config)# crypto ca crl request central
hostname(config)#
```

Related Commands

Command	Description
crl configure	Enters crl configure mode.

crypto ca enroll

To start the enrollment process with the CA, use the **crypto ca enroll** command in global configuration mode. For this command to execute successfully, the trustpoint must have been configured correctly.

crypto ca enroll *trustpoint* [**noconfirm**]

Syntax Description

noconfirm	(Optional) Suppresses all prompts. Enrollment options that might have been prompted for must be pre-configured in the trustpoint. This option is for use in scripts, ASDM, or other such non-interactive needs.
<i>trustpoint</i>	Specifies the name of the trustpoint to enroll with. Maximum number of characters is 128.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

When the trustpoint is configured for SCEP enrollment, the security appliance displays a CLI prompt immediately and displays status messages to the console asynchronously. When the trustpoint is configured for manual enrollment, the security appliance writes a base-64-encoded PKCS10 certification request to the console and then displays the CLI prompt.

This command generates interactive prompts that vary depending on the configured state of the referenced trustpoint.

Examples

The following example enrolls for an identity certificate with trustpoint tp1 using SCEP enrollment. The security appliance prompts for information not stored in the trustpoint configuration.

```
hostname(config)# crypto ca enroll tp1
%
% Start certificate enrollment ..
% Create a challenge password. You will need to verbally provide this
% password to the CA Administrator in order to revoke your certificate.
% For security reasons your password will not be saved in the configuration.
% Please make a note of it.
Password:
Re-enter password:
```

```
% The fully-qualified domain name in the certificate will be: xyz.example.com
% The subject name in the certificate will be: xyz.example.com
% Include the router serial number in the subject name? [yes/no]: no
% Include an IP address in the subject name? [no]: no
Request certificate from CA [yes/no]: yes
% Certificate request sent to Certificate authority.
% The certificate request fingerprint will be displayed.
% The 'show crypto ca certificate' command will also show the fingerprint.

hostname(config)#
```

The next command shows manual enrollment of a CA certificate.

```
hostname(config)# crypto ca enroll tp1

% Start certificate enrollment ..
% The fully-qualified domain name in the certificate will be: xyz.example.com
% The subject name in the certificate will be: wb-2600-3.example.com
if serial number not set in trustpoint, prompt:
% Include the router serial number in the subject name? [yes/no]: no
If ip-address not configured in trustpoint:
% Include an IP address in the subject name? [no]: yes
Enter Interface name or IP Address[]: 1.2.3.4
Display Certificate Request to terminal? [yes/no]: y
Certificate Request follows:
MIIBFTCBwAIBADA6MTgwFAYJKoZIhvcNAQkIEwcxLjIuMy40MCAGCSqGSIB3DQEEJ
AhYTd2ItMjYwMC0zLmNpc2NvLmNvbTBcMA0GCSqGSIB3DQEBAQUAA0sAMEgCQQDT
IdvHa4D5wXZ+40sKQV7Uek1E+CC6hm/LRN3p5ULW1KF6bxhA3Q5CQfh4jDxobn+A
Y8GoeceulS2Zb+mvgNvjAgMBAAGgITAfBgkqhkiG9w0BCQ4xExAQMA4GA1UdDwEB
/wQEAwIFoDANBgkqhkiG9w0BAQQFAANBACDhnrEGBVtltG7hp8x6Wz/dgY+ouWcA
1zy7QpdGhb1du2P81RYn+8pWRA43cikXMTem4yEkZhLjDUgv9t+R9c=

---End - This line not part of the certificate request---

Redisplay enrollment request? [yes/no]: no
hostname(config)#
```

Related Commands

Command	Description
crypto ca authenticate	Obtains the CA certificate for this trustpoint.
crypto ca import pkcs12	Installs a certificate received from a CA in response to a manual enrollment request. Also used to import PKS12 data to a trustpoint.
crypto ca trustpoint	Enters the trustpoint submode for the indicated trustpoint.

crypto ca export

To export in PKCS12 format the keys and certificates associated with a trustpoint configuration, use the **crypto ca export** command in global configuration mode.

crypto ca export *trustpoint* **pkcs12** *passphrase*

Syntax Description

passphrase	Specifies the passphrase used to encrypt the PKCS12 file for export.
pkcs12	Specifies the public key cryptography standard to use in exporting the trustpoint configuration.
trustpoint	Specifies the name of the trustpoint whose certificate and keys are to be exported. When you export, if the trustpoint uses RSA keys, the exported key pair is assigned the same name as the trustpoint.

Defaults

This command has no default values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Invocations of this command do not become part of the active configuration. The PKCS12 data is written to the terminal.

Examples

The following example exports PKCS12 data for trustpoint central using xxyyzz as the passcode:

```
hostname (config)# crypto ca export central pkcs12 xxyyzz
```

Exported pkcs12 follows:

```
[ PKCS12 data omitted ]
```

```
---End - This line not part of the pkcs12---
```

```
hostname (config)#
```

Related Commands	Command	Description
	crypto ca import pkcs12	Installs a certificate received from a CA in response to a manual enrollment request. Also used to import PKS12 data to a trustpoint.
	crypto ca authenticate	Obtains the CA certificate for this trustpoint.
	crypto ca enroll	Starts enrollment with a CA.
	crypto ca trustpoint	Enters the trustpoint submode for the indicated trustpoint.

crypto ca import

To install a certificate received from a CA in response to a manual enrollment request or to import the certificate and key pair for a trustpoint using PKCS12 data, use the **crypto ca import** command in global configuration mode. The security appliance prompts you to paste the text to the terminal in base 64 format.

crypto ca import *trustpoint* **certificate** [**nointeractive**]

crypto ca import *trustpoint* **pkcs12** *passphrase* [**nointeractive**]

Syntax Description

<i>trustpoint</i>	Specifies the trustpoint with which to associate the import action. Maximum number of characters is 128. If you import PKCS12 data and the trustpoint uses RSA keys, the imported key pair is assigned the same name as the trustpoint.
<i>certificate</i>	Tells the security appliance to import a certificate from the CA represented by the trustpoint.
pkcs12	Tells the security appliance to import a certificate and key pair for a trustpoint, using PKCS12 format.
<i>passphrase</i>	Specifies the passphrase used to decrypt the PKCS12 data.
nointeractive	(Optional) Imports a certificate using nointeractive mode. This suppresses all prompts. This option for use in scripts, ASDM, or other such non-interactive needs.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example manually imports a certificate for the trustpoint Main:

```
hostname (config)# crypto ca import Main certificate
% The fully-qualified domain name in the certificate will be:
securityappliance.example.com
```

```
Enter the base 64 encoded certificate.
End with a blank line or the word "quit" on a line by itself
[ certificate data omitted ]
```

```
quit
INFO: Certificate successfully imported
hostname (config)#
```

The following example manually imports PKCS12 data to trustpoint central:

```
hostname (config)# crypto ca import central pkcs12

Enter the base 64 encoded pkcs12.
End with a blank line or the word "quit" on a line by itself:
[ PKCS12 data omitted ]
quit
INFO: Import PKCS12 operation completed successfully
hostname (config)#
```

Related Commands

Command	Description
crypto ca export	Exports a trustpoint certificate and key pair in PKCS12 format.
crypto ca authenticate	Obtains the CA certificate for a trustpoint.
crypto ca enroll	Starts enrollment with a CA.
crypto ca trustpoint	Enters the trustpoint submode for the indicated trustpoint.

crypto ca trustpoint

To enter the trustpoint submode for the specified trustpoint, use the **crypto ca trustpoint** command in global configuration mode. To remove the specified trustpoint, use the **no** form of this command. This command manages trustpoint information. A trustpoint represents a CA identity and possibly a device identity, based on a certificate issued by the CA. The commands within the trustpoint sub mode control CA-specific configuration parameters which specify how the security appliance obtains the CA certificate, how the security appliance obtains its certificate from the CA, and the authentication policies for user certificates issued by the CA.

crypto ca trustpoint *trustpoint-name*

no crypto ca trustpoint *trustpoint-name* [**noconfirm**]

Syntax Description

noconfirm	Suppresses all interactive prompting
<i>trustpoint- name</i>	Identifies the name of the trustpoint to manage. The maximum name length is 128 characters.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **crypto ca trustpoint** command to declare a CA. Issuing this command puts you in Crypto ca trustpoint configuration mode.

You can specify characteristics for the trustpoint using the following commands listed alphabetically in this command reference guide:

- **crl required | optional | nocheck**—Specifies CRL configuration options.
- **crl configure**—Enters CRL configuration submode (see **crl**).
- **default enrollment**—Returns all enrollment parameters to their system default values. Invocations of this command do not become part of the active configuration.
- **enrollment retry period**—Specifies a retry period in minutes for automatic (SCEP) enrollment.
- **enrollment retry count**—Specifies a maximum number of permitted retries for automatic (SCEP) enrollment.

- **enrollment terminal**—Specifies cut and paste enrollment with this trustpoint.
- **enrollment url** *url*—Specifies automatic enrollment (SCEP) to enroll with this trustpoint and configures the enrollment URL (*url*).
- **fqdn** *fqdn*—During enrollment, asks the CA to include the specified fully-qualified distinguished name (FQDN) in the Subject Alternative Name extension of the certificate.
- **email** *address*—During enrollment, asks the CA to include the specified email address in the Subject Alternative Name extension of the certificate.
- **subject-name** *X.500 name*—During enrollment, asks the CA to include the specified subject DN in the certificate.
- **serial-number**—During enrollment, asks the CA to include the security appliance's serial number in the certificate.
- **ip-addr** *ip-address*—During enrollment, asks the CA to include the IP address of the security appliance in the certificate.
- **password** *string*—Specifies a challenge phrase that is registered with the CA during enrollment. The CA typically uses this phrase to authenticate a subsequent revocation request.
- **keypair** *name*—Specifies the key pair whose public key is to be certified.
- **id-cert-issuer**—Indicates whether the system accepts peer certificates issued by the CA associated with this trustpoint.
- **accept-subordinates**—Indicates whether CA certificates subordinate to the CA associated with the trustpoint are accepted if delivered during phase one IKE exchange when not previously installed on the device.
- **support-user-cert-validation**—If enabled, the configuration settings to validate a remote user certificate can be taken from this trustpoint, provided that this trustpoint is authenticated to the CA that issued the remote certificate. This option applies to the configuration data associated with the subcommands **crl required** | **optional** | **nocheck** and all settings in the CRL sub mode.
- **exit**—Leaves the submode.

Examples

The following example enters CA trustpoint mode for managing a trustpoint named central:

```
hostname(config)# crypto ca trustpoint central  
hostname(ca-trustpoint)#
```


Related Commands

Command	Description
clear configure crypto ca trustpoint	Removes all trustpoints.
crypto ca authenticate	Obtains the CA certificate for this trustpoint.
crypto ca certificate map	Enters crypto CA certificate map mode. Defines certificate-based ACLs.
crypto ca crl request	Requests a CRL based on configuration parameters of specified trustpoint.
crypto ca import	Installs a certificate received from a CA in response to a manual enrollment request. Also used to import PKS12 data to a trustpoint.

crypto dynamic-map match address

See the **crypto map match address** command for additional information about this command.

crypto dynamic-map *dynamic-map-name* *dynamic-seq-num* **match address** *acl_name*

no crypto dynamic-map *dynamic-map-name* *dynamic-seq-num* **match address** *acl_name*

Syntax Description

<i>acl-name</i>	Identifies the access-list to be matched for the dynamic crypto map entry.
<i>dynamic-map-name</i>	Specifies the name of the dynamic crypto map set.
<i>dynamic-seq-num</i>	Specifies the sequence number that corresponds to the dynamic crypto map entry.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example shows the use of the **crypto dynamic-map** command to match address of an access list named **aclist1**:

```
hostname(config)# crypto dynamic-map mymap 10 match address aclist1
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto dynamic-map	Clears all configuration for all the dynamic crypto maps.
show running-config crypto dynamic-map	Displays all configuration for all the dynamic crypto maps.

crypto dynamic-map set nat-t-disable

To disable NAT-T for connections based on this crypto map entry, use the **crypto dynamic-map set nat-t-disable** command in global configuration mode. To enable NAT-T for this crypto map entry, use the **no** form of this command.

crypto dynamic-map *dynamic-map-name* *dynamic-seq-num* **set nat-t-disable**

no crypto dynamic-map *dynamic-map-name* *dynamic-seq-num* **set nat-t-disable**

Syntax Description

<i>dynamic-map-name</i>	Specifies the name of the crypto dynamic map set.
<i>dynamic-seq-num</i>	Specifies the number you assign to the crypto dynamic map entry.

Defaults

The default setting is off.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines

Use the **isakmp nat-traversal** command to globally enable NAT-T. Then you can use the **crypto dynamic-map set nat-t-disable** command to disable NAT-T for specific crypto map entries.

Examples

The following command disables NAT-T for the crypto dynamic map named mymap:

```
hostname(config)# crypto dynamic-map mymap 10 set nat-t-disable
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto dynamic-map	Clears all configuration for all the dynamic crypto maps.
show running-config crypto dynamic-map	Displays all configuration for all the dynamic crypto maps.

crypto dynamic-map set peer

See the **crypto map set peer** command for additional information about this command.

crypto dynamic-map *dynamic-map-name* *dynamic-seq-num* **set peer** *ip_address* | *hostname*

no crypto dynamic-map *dynamic-map-name* *dynamic-seq-num* **set peer** *ip_address* | *hostname*

Syntax Description

<i>dynamic-map-name</i>	Specifies the name of the dynamic crypto map set.
<i>dynamic-seq-num</i>	Specifies the sequence number that corresponds to the dynamic crypto map entry.
<i>ip_address</i>	Identifies the peer in the dynamic crypto map entry by IP address, as defined by the name command.
<i>hostname</i>	Identifies the peer in the dynamic crypto map entry by hostname, as defined by the name command.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example shows setting a peer for a dynamic-map named mymap to the IP address 10.0.0.1:

```
hostname(config)# crypto dynamic-map mymap 10 set peer 10.0.0.1
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto dynamic-map	Clears all configuration for all the dynamic crypto maps.
show running-config crypto dynamic-map	Displays all configuration for all the dynamic crypto maps.

crypto dynamic-map set pfs

See the **crypto map set pfs** command for additional information about this command.

crypto dynamic-map *dynamic-map-name dynamic-seq-num* **set pfs** [**group1** | **group2** | **group5** | **group 7**]

no crypto dynamic-map *dynamic-map-name dynamic-seq-num* **set pfs** [**group1** | **group2** | **group5** | **group 7**]

Syntax Description

<i>dynamic-map-name</i>	Specifies the name of the dynamic crypto map set.
<i>dynamic-seq-num</i>	Specifies the sequence number that corresponds to the dynamic crypto map entry.
group1	Specifies that IPsec should use the 768-bit Diffie-Hellman prime modulus group when performing the new Diffie-Hellman exchange.
group2	Specifies that IPsec should use the 1024-bit Diffie-Hellman prime modulus group when performing the new Diffie-Hellman exchange.
group5	Specifies that IPsec should use the 1536-bit Diffie-Hellman prime modulus group when performing the new Diffie-Hellman exchange.
group7	Specifies that IPsec should use group7 (ECC) where the elliptical curve field size is 163-bits, for example, with the movianVPN client.
set pfs	Configures IPsec to ask for perfect forward secrecy (PFS) when requesting new security associations for this dynamic crypto map entry or configures IPsec to require PFS when receiving requests for new security associations.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0(1)	This command was modified to add Diffie-Hellman group 7.

Usage Guidelines

The **crypto dynamic-map** commands, such as **match address**, **set peer**, and **set pfs** are described with the **crypto map** commands. If the peer initiates the negotiation and the local configuration specifies PFS, the peer must perform a PFS exchange or the negotiation fails. If the local configuration does not specify a group, the security appliance assumes a default of group2. If the local configuration does not specify PFS, it accepts any offer of PFS from the peer.

When interacting with the Cisco VPN Client, the security appliance does not use the PFS value, but instead uses the value negotiated during Phase 1.

Examples

The following example specifies that PFS should be used whenever a new security association is negotiated for the crypto dynamic-map mymap 10. The group specified is group 2:

```
hostname(config)# crypto dynamic-map mymap 10 set pfs group2
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto dynamic-map	Clears all configuration for all the dynamic crypto maps.
show running-config crypto dynamic-map	Displays all configuration for all the dynamic crypto maps.

crypto dynamic-map set reverse route

See the **crypto map set reverse-route** command for additional information about this command.

crypto dynamic-map *dynamic-map-name* *dynamic-seq-num* **set reverse route**

no crypto dynamic-map *dynamic-map-name* *dynamic-seq-num* **set reverse route**

Syntax Description

<i>dynamic-map-name</i>	Specifies the name of the crypto map set.
<i>dynamic-seq-num</i>	Specifies the number you assign to the crypto map entry.

Defaults

The default value for this command is off.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0(1)	This command was introduced.

Examples

The following command enables RRI for the crypto dynamic-map named mymap:

```
hostname(config)# crypto dynamic-map mymap 10 set reverse route
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto dynamic-map	Clears all configuration for all the dynamic crypto maps.
show running-config crypto dynamic-map	Displays all configuration for all the dynamic crypto maps.

crypto map set security-association lifetime

To override (for a particular crypto map entry) the global lifetime value, which is used when negotiating IPSec security associations, use the **crypto map set security-association lifetime** command in global configuration mode. To reset a crypto map entry's lifetime value to the global value, use the **no** form of this command.

crypto map *map-name seq-num* **set security-association lifetime** {**seconds** *seconds* |
kilobytes *kilobytes*}

no crypto map *map-name seq-num* **set security-association lifetime** {**seconds** *seconds* |
kilobytes *kilobytes*}

Syntax Description

<i>kilobytes</i>	Specifies the volume of traffic (in kilobytes) that can pass between peers using a given security association before that security association expires. The default is 4,608,000 kilobytes.
<i>map-name</i>	Specifies the name of the crypto map set.
<i>seconds</i>	Specifies the number of seconds a security association will live before it expires. The default is 28,800 seconds (eight hours).
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.

Defaults

The default number of kilobytes is 4,608,000; the default number of seconds is 28,800.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The crypto map's security associations are negotiated according to the global lifetimes.

IPSec security associations use shared secret keys. These keys and their security associations time out together.

Assuming that the particular crypto map entry has lifetime values configured, when the security appliance requests new security associations during security association negotiation, it specifies its crypto map lifetime values in the request to the peer; it uses these values as the lifetime of the new security associations. When the security appliance receives a negotiation request from the peer, it uses the smaller of the lifetime values proposed by the peer or the locally configured lifetime values as the lifetime of the new security associations.

There are two lifetimes: a “timed” lifetime and a “traffic-volume” lifetime. The session keys/security association expires after the first of these lifetimes is reached. You can specify both with one command.

**Note**

The security appliance lets you change crypto map, dynamic map, and ipsec settings on the fly. If you do so, the security appliance brings down only the connections affected by the change. If you change an existing access-list associated with a crypto map, specifically by deleting an entry within the access-list, the result is that only the associated connection is brought down. Connections based on other entries in the access-list are not affected.

To change the timed lifetime, use the **crypto map set security-association lifetime seconds** command. The timed lifetime causes the keys and security association to time out after the specified number of seconds have passed.

Examples

The following command, entered in global configuration mode, specifies a security association lifetime in seconds and kilobytes for crypto map mymap

```
hostname(config)# crypto map mymap 10 set security-association lifetime seconds 1400  
kilobytes 3000000  
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto map	Clears all configuration for all crypto maps.
show running-config crypto map	Displays the crypto map configuration.

crypto dynamic-map set transform-set

See the **crypto map set transform-set** command for additional information about this command.

crypto dynamic-map *dynamic-map-name* *dynamic-seq-num* **set transform-set**
transform-set-name1 [... *transform-set-name9*]

no crypto dynamic-map *dynamic-map-name* *dynamic-seq-num* **set transform-set**
transform-set-name1 [... *transform-set-name9*]

Syntax Description

<i>dynamic-map-name</i>	Specifies the name of the dynamic crypto map set.
<i>dynamic-seq-num</i>	Specifies the sequence number that corresponds to the dynamic crypto map entry.
<i>transform-set-name1</i> <i>transform-set-name9</i>	Identifies the transform set to be used with the dynamic crypt map entry (the names of transform sets defined using the crypto ipsec command).



Note

The **crypto map set transform-set** command is required for dynamic crypto map entries. All you need in the entry is a transform set.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following command specifies two transform sets (tfset1 and tfset2) for the crypto dynamic-map mymap:

```
hostname(config)# crypto dynamic-map mymap 10 set transform-set tfset1 tfset2
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto dynamic-map	Clears all configuration for all the dynamic crypto maps.
show running-config crypto dynamic-map	Displays all configuration for all the dynamic crypto maps.

crypto ipsec df-bit

To configure DF-bit policy for IPSec packets, use the **crypto ipsec df-bit** command in global configuration mode.

crypto ipsec df-bit [**clear-df** | **copy-df** | **set-df**] *interface*

Syntax Description

clear-df	(Optional) Specifies that the outer IP header will have the DF bit cleared and that the security appliance may fragment the packet to add the IPSec encapsulation.
copy-df	(Optional) Specifies that the security appliance will look in the original packet for the outer DF bit setting.
set-df	(Optional) Specifies that the outer IP header will have the DF bit set; however, the security appliance may fragment the packet if the original packet had the DF bit cleared.
<i>interface</i>	Specifies an interface name.

Defaults

This command is disabled by default. If this command is enabled without a specified setting, the security appliance uses the **copy-df** setting as default.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The DF bit with IPSec tunnels feature lets you specify whether the security appliance can clear, set, or copy the Don't Fragment (DF) bit from the encapsulated header. The DF bit within the IP header determines whether a device is allowed to fragment a packet.

Use the **crypto ipsec df-bit** command in global configuration mode to configure the security appliance to specify the DF bit in an encapsulated header.

When encapsulating tunnel mode IPSec traffic, use the **clear-df** setting for the DF bit. This setting lets the device send packets larger than the available MTU size. Also this setting is appropriate if you do not know the available MTU size.

Examples

The following example, entered in global configuration mode, specifies sets the IPSec DF policy to **clear-df**:

```
hostname(config)# crypto ipsec df-bit clear-df inside
hostname(config)#
```

Related Commands

Command	Description
crypto ipsec fragmentation	Configures the fragmentation policy for IPSec packets.
show crypto ipsec df-bit	Displays the DF-bit policy for a specified interface.
show crypto ipsec fragmentation	Displays the fragmentation policy for a specified interface.

crypto ipsec fragmentation

To configure the fragmentation policy for IPSec packets, use the **crypto ipsec fragmentation** command in global configuration mode.

crypto ipsec fragmentation {**after-encryption** | **before-encryption**} *interface*

Syntax Description

after-encryption	Specifies the security appliance to fragment IPSec packets that are close to the maximum MTU size after encryption (disables pre-fragmentation).
before-encryption	Specifies the security appliance to fragment IPSec packets that are close to the maximum MTU size before encryption (enables pre-fragmentation).
<i>interface</i>	Specifies an interface name.

Defaults

This feature is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

When a packet is near the size of the MTU of the outbound link of the encrypting security appliance, and it is encapsulated with IPSec headers, it is likely to exceed the MTU of the outbound link. This causes packet fragmentation after encryption, which makes the decrypting device reassemble in the process path. Pre-fragmentation for IPSec VPNs increases the decrypting device's performance by letting it operate in the high performance CEF path instead of the process path.

Pre-fragmentation for IPSec VPNs lets an encrypting device predetermine the encapsulated packet size from information available in transform sets, which are configured as part of the IPSec SA. If the device predetermines that the packet will exceed the MTU of the output interface, the device fragments the packet before encrypting it. This avoids process level reassembly before decryption and helps improve decryption performance and overall IPSec traffic throughput.

Examples

The following example, entered in global configuration mode, enables pre-fragmentation for IPSec packets globally on the device:

```
hostname(config)# crypto ipsec fragmentation before-encryption inside
hostname(config)#
```

The following example, entered in global configuration mode, disables pre-fragmentation for IPSec packets on the interface:

```
hostname(config)# crypto ipsec fragmentation after-encryption inside  
hostname(config)#
```

Related Commands

Command	Description
crypto ipsec df-bit	Configures the DF-bit policy for IPSec packets.
show crypto ipsec fragmentation	Displays the fragmentation policy for IPSec packets.
show crypto ipsec df-bit	Displays the DF-bit policy for a specified interface.

crypto ipsec security-association lifetime

To configure global lifetime values, use the **crypto ipsec security-association lifetime** command in global configuration mode. To reset a crypto ipsec entry's lifetime value to the default value, use the **no** form of this command.

crypto ipsec security-association lifetime {seconds *seconds* | kilobytes *kilobytes*}

no crypto ipsec security-association lifetime {seconds *seconds* | kilobytes *kilobytes*}

Syntax Description

<i>kilobytes</i>	Specifies the volume of traffic (in kilobytes) that can pass between peers using a given security association before that security association expires. The range is 10 to 2147483647 kbytes. The default is 4,608,000 kilobytes.
<i>seconds</i>	Specifies the number of seconds a security association will live before it expires. The range is 120 to 214783647 seconds. The default is 28,800 seconds (eight hours).
token	Indicate a token-based server for user authentication is used.

Defaults

The default number of kilobytes is 4,608,000; the default number of seconds is 28,800.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
1.1(1)	This command was introduced.

Usage Guidelines

The **crypto ipsec security-association lifetime** command changes global lifetime values used when negotiating IPSec security associations.

IPSec security associations use shared secret keys. These keys and their security associations time out together.

Assuming that the particular crypto map entry has no lifetime values configured, when the security appliance requests new security associations during negotiation, it specifies its global lifetime value in the request to the peer; it uses this value as the lifetime of the new security associations. When the security appliance receives a negotiation request from the peer, it uses the smaller of the lifetime value proposed by the peer or the locally configured lifetime value as the lifetime of the new security associations.

There are two lifetimes: a “timed” lifetime and a “traffic-volume” lifetime. The security association expires after the first of these lifetimes is reached.

The security appliance lets you change crypto map, dynamic map, and ipsec settings on the fly. If you do so, the security appliance brings down only the connections affected by the change. If you change an existing access-list associated with a crypto map, specifically by deleting an entry within the access-list, the result is that only the associated connection is brought down. Connections based on other entries in the access-list are not affected.

To change the global timed lifetime, use the **crypto ipsec security-association lifetime seconds** command. The timed lifetime causes the security association to time out after the specified number of seconds have passed.

To change the global traffic-volume lifetime, use the **crypto ipsec security-association lifetime kilobytes** command. The traffic-volume lifetime causes the security association to time out after the specified amount of traffic (in kilobytes) has been protected by the security associations' key.

Shorter lifetimes can make it harder to mount a successful key recovery attack, because the attacker has less data encrypted under the same key to work with. However, shorter lifetimes require more CPU processing time for establishing new security associations.

The security association (and corresponding keys) expires according to whichever occurs sooner, either after the number of seconds has passed or after the amount of traffic in kilobytes has passed.

Examples

The following example specifies a global timed lifetime for security associations:

```
hostname(config)# crypto ipsec-security association lifetime seconds 240
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto map	Clears all IPSec configuration (i.e. global lifetimes and transform sets).
show running-config crypto map	Displays all configuration for all the crypto maps.

crypto ipsec transform-set

To define a transform set, use the **crypto ipsec transform-set** command in global configuration mode. With this command, you identify the IPSec encryption and hash algorithms to be used by the transform set. Use the **no** form of this command to remove a transform set.

crypto ipsec *map-name seq-num* **transform-set** *transform-set-name* *transform1* [*transform2*]

no crypto ipsec *map-name seq-num* **transform-set** *transform-set-name*

Syntax Description

esp-aes	Specifying this option means that IPSec messages protected by this transform are encrypted using AES with a 128-bit key.
esp-aes-192	Specifying this option means that IPSec messages protected by this transform are encrypted using AES with a 192-bit key.
esp-aes-256	Specifying this option means that IPSec messages protected by this transform are encrypted using AES with a 256-bit key.
esp-des	Specifying this option means that IPSec messages protected by this transform with encryption using 56-bit DES-CBC.
esp-3des	Specifying this option means that IPSec messages protected by this transform are encrypted using the Triple DES algorithm.
esp-none	Specifying this option means that IPSec messages do not use HMAC authentication.
esp-null	Specifying this option means that IPSec messages are not encrypted using the IPSec security protocol (ESP) only.
esp-md5-hmac	Specifying this option means that IPSec messages protected by this transform are using MD5/HMAC-128 as the hash algorithm.
esp-sha-hmac	Specifying this option means that IPSec messages protected by this transform are using SHA/HMAC-160 as the hash algorithm.
<i>map-name</i>	Specifies the name of the crypto map set.
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.
<i>transform1</i> , <i>transform2</i>	Specifies up to two transforms. Transforms define the IPSec security protocol(s) and algorithm(s). Each transform represents an IPSec security protocol (ESP), plus the algorithm to use, either [esp-aes esp-aes-192 esp-aes-256 esp-des esp-3des esp-null] or [esp-md5-hmac esp-sha-hmac] as defined in this syntax table.
<i>transform-set-name</i>	Specifies the name of the transform set to create or modify.
token	Indicate a token-based server for user authentication is used.

Defaults

The default encryption algorithm is esp-3des (Triple DES).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
1.1(1)	This command was introduced.

Usage Guidelines

A transform set specifies one or two IPSec security protocols and specifies which algorithms to use with the selected security protocol. During the IPSec security association negotiation, the peers agree to use a particular transform set when protecting a particular data flow.

IPSec messages can be protected by a transform set using AES with a 128-bit key, 192-bit key, or 256-bit key.

Due to the large key sizes provided by AES, ISAKMP negotiation should use Diffie-Hellman group 5 instead of group 1 or group 2. To do this, use the **isakmp policy priority group 5** command.

You can configure multiple transform sets, and then specify one or more of these transform sets in a crypto map entry. The transform set defined in the crypto map entry in the IPSec security association negotiation protects the data flows specified by that crypto map entry's access list. During the negotiation, the peers search for a transform set that is the same at both peers. When the security appliance finds such a transform set, it applies it to the protected traffic as part of both peer's IPSec security associations.

Each transform-set represents an algorithm to use for encryption or authentication. When the particular transform set is used during negotiations for IPSec security associations, the entire transform set (the combination of protocols, algorithms, and other settings) must match a transform set at the remote peer.

In a transform set, you can specify just an ESP encryption transform or both an ESP encryption transform and an ESP authentication transform.

Examples of acceptable transform combinations are as follows:

- **esp-des**
- **esp-des** and **esp-md5-hmac**

If one or more transforms are specified in the **crypto ipsec transform-set** command for an existing transform set, the specified transforms replace the existing transforms for that transform set.

Examples

The following example configures two transform sets: one named t1, using DES for encryption and SHA/HMAC-160 as the hash algorithm, and the other named standard, using AES 192 for encryption and MD5/HMAC-128 as the hash algorithm:

```
hostname(config)# crypto ipsec transform-set t1 esp-des esp-sha-hmac
hostname(config)# crypto ipsec transform-set standard esp-aes-192 esp-md5-hmac
hostname(config)
```

Related Commands	Command	Description
	clear configure crypto	Clears all ipsec configuration (i.e. global lifetimes and transform sets).
	show running-config crypto map	Displays all configuration for all the crypto maps.

crypto ipsec transform-set mode transport

To specify IPSec transport mode for the transform set, use the **crypto ipsec transform-set mode transport** command in global configuration mode. Use the **no** form of this command to remove the IPSec transport mode from the transform set.

crypto ipsec transform-set *transform-set-name* **mode transport**

no crypto ipsec transform-set *transform-set-name* **mode transport**

Syntax Description

mode transport	Specifies the transform set to accept transport mode requests in addition to the tunnel mode request.
<i>transform-set-name</i>	Specifies the name of the transform set to create or modify.
token	Indicate a token-based server for user authentication is used.

Defaults

The default mode is tunnel mode.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

This command specifies IPSec transport mode for a transform set. The default is tunnel mode. Tunnel mode is automatically enabled for a transform set.

Examples

The following example configures a transform set named transet5 that uses Triple DES for encryption, MD5/HMAC-128 for a hash algorithm, and then specifies IPSec transport mode for the transform set transet5:

```
hostname(config)# crypto ipsec transform-set transet5 esp-3des esp-md5-hmac
hostname(config)# crypto ipsec transform-set transet5 mode transport
hostname(config)#
```

Related Commands	Command	Description
	clear configure crypto	Clears all ipsec configuration (i.e. global lifetimes and transform sets).
	clear configure crypto map	Clears all crypto maps.
	show running-config crypto map	Displays all configuration for all the crypto maps.

crypto key generate dsa

To generate DSA key pairs for identity certificates, use the **crypto key generate dsa** command in global configuration mode.

crypto key generate dsa {**label** *key-pair-label*} [**modulus** *size*] [**noconfirm**]

Syntax Description

label <i>key-pair-label</i>	Specifies the name to be associated with the key pair(s); maximum label length is 128 characters. DSA requires a label.
modulus <i>size</i>	Specifies the modulus size of the key pair(s): 512, 768, 1024. The default modulus size is 1024.
noconfirm	Suppresses all interactive prompting.

Defaults

The default modulus size is 1024.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **crypto key generate dsa** command to generate DSA key pairs to support SSL, SSH, and IPSec connections. The generated key pairs are identified by labels that you provide as part of the command syntax. If you do not provide a label, the security appliance displays an error message.



Note

When generating DSA keys, you may encounter a delay. On a Cisco PIX 515E Firewall, this delay may extend up to few minutes.

Examples

The following example, entered in global configuration mode, generates an DSA key pair with the label mypubkey:

```
hostname(config)# crypto key generate dsa label mypubkey
INFO: The name for the keys will be: mypubkey
hostname(config)#
```

The following example, entered in global configuration mode, inadvertently attempts to generate a duplicate DSA key pair with the label mypubkey:

```
hostname(config)# crypto key generate dsa label mypubkey
```

crypto key generate dsa

```
WARNING: You already have dSA keys defined named mypubkey
Do you really want to replace them? [yes/no] no
ERROR: Failed to create new DSA keys named mypubkey
hostname(config)#
```

Related Commands

Command	Description
crypto key zeroize	Removes the DSA key pairs.
show crypto key mypubkey	Displays the DSA key pairs.

crypto key generate rsa

To generate RSA key pairs for identity certificates, use the **crypto key generate rsa** command in global configuration mode.

```
crypto key generate rsa [usage-keys | general-keys] [label key-pair-label] [modulus size]
[noconfirm]
```

Syntax Description

general-keys	Generates a single pair of general purpose keys. This is the default key-pair type.
label <i>key-pair-label</i>	Specifies the name to be associated with the key pair(s). This key pair must be uniquely labeled. If you attempt to create another key pair with the same label, the security appliance displays an warning message. If no label is provided when the key is generated, the key pair is statically named <Default-RSA-Key>.
modulus <i>size</i>	Specifies the modulus size of the key pair(s): 512, 768, 1024, and 2048. The default modulus size is 1024.
noconfirm	Suppresses all interactive prompting.
usage-keys	Generates two key pairs, one for signature use and one for encryption use. This implies that two certificates for the corresponding identity are required.

Defaults

The default key-pair type is **general key**. The default modulus size is 1024.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **crypto key generate rsa** command to generate RSA key pairs to support SSL, SSH, and IPSec connections. The generated key pairs are identified by labels that you can provide as part of the command syntax. Trustpoints that do not reference a key pair can use the default one <Default-RSA-Key>. SSH connections always use this key. This does not affect SSL, since SSL generates its own cert/key dynamically, unless a trustpoint has one configured.

Examples

The following example, entered in global configuration mode, generates an RSA key pair with the label mypubkey:

```
hostname(config)# crypto key generate rsa label mypubkey
INFO: The name for the keys will be: mypubkey
Keypair generation process
hostname(config)#
```

The following example, entered in global configuration mode, inadvertently attempts to generate a duplicate RSA key pair with the label mypubkey:

```
hostname(config)# crypto key generate rsa label mypubkey
WARNING: You already have RSA keys defined named mypubkey
Do you really want to replace them? [yes/no] no
ERROR: Failed to create new RSA keys named mypubkey
hostname(config)#
```

The following example, entered in global configuration mode, generates an RSA key pair with the default label:

```
hostname(config)# crypto key generate rsa
INFO: The name for the keys will be: <Default-RSA-Key>
Keypair generation process begin. Please wait...
hostname(config)#
```

Related Commands

Command	Description
crypto key zeroize	Removes RSA key pairs.
show crypto key mypubkey	Displays the RSA key pairs.

crypto key zeroize

To remove the key pairs of the indicated type (rsa or dsa), use the **crypto key zeroize** command in global configuration mode.

crypto key zeroize {rsa | dsa} [*label key-pair-label*] [**default**] [**noconfirm**]

Syntax Description

default	Removes RSA key pairs with no labels. This keyword is legal only with RSA key pairs.
dsa	Specifies DSA as the key type.
label <i>key-pair-label</i>	Removes the key pairs of the indicated type (rsa or dsa). If you do not provide a label, the security appliance removes all key pairs of the indicated type.
noconfirm	Suppresses all interactive prompting.
rsa	Specifies RSA as the key type.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example, entered in global configuration mode, removes all RSA key pairs:

```
hostname(config)# crypto key zeroize rsa
WARNING: All RSA keys will be removed.
WARNING: All router certs issued using these keys will also be removed.

Do you really want to remove these keys? [yes/no] y
hostname(config)#
```

Related Commands

Command	Description
crypto key generate dsa	Generates DSA key pairs for identity certificates.
crypto key generate rsa	Generate RSA key pairs for identity certificates.

crypto map interface

Use the **crypto map interface** command in global configuration mode to apply a previously defined crypto map set to an interface. Use the **no** form of this command to remove the crypto map set from the interface.

crypto map *map-name* **interface** *interface-name*

no crypto map *map-name* **interface** *interface-name*

Syntax Description

<i>interface-name</i>	Specifies the interface for the security appliance to use for establishing tunnels with VPN peers. If ISAKMP is enabled, and you are using a certificate authority (CA) to obtain certificates, this should be the interface with the address specified in the CA certificates.
<i>map-name</i>	Specifies the name of the crypto map set.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Use this command to assign a crypto map set to any active security appliance interface. The security appliance supports IPSec termination on any and all active interfaces. You must assign a crypto map set to an interface before that interface can provide IPSec services.

You can assign only one crypto map set to an interface. If multiple crypto map entries have the same *map-name* but a different *seq-num*, they are part of the same set and are all applied to the interface. The security appliance evaluates the crypto map entry with the lowest *seq-num* first.

**Note**

The security appliance lets you change crypto map, dynamic map, and ipsec settings on the fly. If you do so, the security appliance brings down only the connections affected by the change. If you change an existing access-list associated with a crypto map, specifically by deleting an entry within the access-list, the result is that only the associated connection is brought down. Connections based on other entries in the access-list are not affected.

**Note**

Every static crypto map must define three parts: an access list, a transform set, and an IPsec peer. If one of these is missing, the crypto map is incomplete and the security appliance moves on to the next entry. However, if the crypto map matches on the access-list but not on either or both of the other two requirements, this security appliance drops the traffic.

Use the **show running-config crypto map** command to ensure that every crypto map is complete. To fix an incomplete crypto map, remove the crypto map, add the missing entries, and reapply it.

Examples

The following example, entered in global configuration mode, assigns the crypto map set named mymap to the outside interface. When traffic passes through the outside interface, the security appliance evaluates it against all the crypto map entries in the mymap set. When outbound traffic matches an access list in one of the mymap crypto map entries, the security appliance forms a security association using that crypto map entry's configuration.

```
hostname(config)# crypto map mymap interface outside
```

The following example shows the minimum required crypto map configuration:

```
hostname(config)# crypto map mymap 10 ipsec-isakmp
hostname(config)# crypto map mymap 10 match address 101
hostname(config)# crypto map mymap set transform-set my_t_set1
hostname(config)# crypto map mymap set peer 10.0.0.1
```

Related Commands

Command	Description
clear configure crypto map	Clears all configuration for all crypto maps.
show running-config crypto map	Displays the crypto map configuration.

crypto map ipsec-isakmp dynamic

To require a given crypto map entry to refer to a pre-existing dynamic crypto map, use the **crypto map ipsec-isakmp dynamic** command in global configuration mode. Use the **no** form of this command to remove the cross reference.

Use the **crypto dynamic-map** command to create dynamic crypto map entries. After you create a dynamic crypto map set, use the **crypto map ipsec-isakmp dynamic** command to add the dynamic crypto map set to a static crypto map.

crypto map *map-name seq-num ipsec-isakmp dynamic dynamic-map-name*

no crypto map *map-name seq-num ipsec-isakmp dynamic dynamic-map-name*

Syntax Description

<i>dynamic-map-name</i>	Specifies the name of the crypto map entry that refers to a pre-existing dynamic crypto map.
ipsec-isakmp	Indicates that IKE establishes the IPSec security associations for this crypto map entry.
<i>map-name</i>	Specifies the name of the crypto map set.
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was modified to remove the ipsec-manual keyword.

Usage Guidelines

After you define crypto map entries, you can use the **crypto map interface** command to assign the dynamic crypto map set to interfaces.

Dynamic crypto maps provide two functions: filtering/classifying traffic to protect, and defining the policy to apply to that traffic. The first use affects the flow of traffic on an interface; the second affects the negotiation performed (via IKE) on behalf of that traffic.

IPSec dynamic crypto maps identify the following:

- The traffic to protect
- IPSec peer(s) with which to establish a security association
- Transform sets to use with the protected traffic

- How to use or manage keys and security associations

A crypto map set is a collection of crypto map entries, each with a different sequence number (seq-num) but the same map name. Therefore, for a given interface, you could have certain traffic forwarded to one peer with specified security applied to that traffic, and other traffic forwarded to the same or a different peer with different IPsec security applied. To accomplish this you create two crypto map entries, each with the same map name, but each with a different sequence number.

The number you assign as the seq-num argument should not be arbitrary. This number ranks multiple crypto map entries within a crypto map set. A crypto map entry with a lower seq-num is evaluated before a map entry with a higher seq-num; that is, the map entry with the lower number has a higher priority.

**Note**

When you link the crypto map to a dynamic crypto map, you must specify the dynamic crypto map. This links the crypto map to an existing dynamic crypto map that was previously defined using the **crypto dynamic-map** command. Now any changes you make to the crypto map entry after it has been converted, will not take affect. For example, a change to the set peer setting does not take effect. However, the security appliance stores the change while it is up. When the dynamic crypto map is converted back to the crypto map, the change is effective and appears in the output of the **show running-config crypto map** command. The security appliance maintains these settings until it reboots.

Examples

The following command, entered in global configuration mode, configures the crypto map mymap to refer to a dynamic crypto map named test.

```
hostname(config)# crypto map mymap ipsec-isakmp dynamic test
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto map	Clears all configuration for all crypto maps.
show running-config crypto map	Displays the crypto map configuration.

crypto map match address

To assign an access list to a crypto map entry, use the **crypto map match address** command in global configuration mode. Use the **no** form of this command to remove the access list from a crypto map entry.

crypto map *map-name* *seq-num* **match address** *acl_name*

no crypto map *map-name* *seq-num* **match address** *acl_name*

Syntax Description

<i>acl_name</i>	Specifies the name of the encryption access list. This name should match the name argument of the named encryption access list being matched.
<i>map-name</i>	Specifies the name of the crypto map set.
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

This command is required for all static crypto maps. If you are defining a dynamic crypto map (with the **crypto dynamic-map** command), this command is not required but is strongly recommended.

Use the **access-list** command to define the access lists.

The security appliance uses the access lists to differentiate the traffic to protect with IPSec crypto from the traffic that does not need protection. It protects outbound packets that match a permit ACE, and ensures that inbound packets that match a permit ACE have protections.

When the security appliance matches a packet to a deny statement, it skips the evaluation of the packet against the remaining access control entries (ACEs) in the crypto map, and resumes evaluation of the packet against the ACEs in the next crypto map in sequence. *Cascading ACLs* involves the use of deny ACEs to bypass evaluation of the remaining ACEs in an ACL, and the resumption of evaluation of traffic against the ACL assigned to the next crypto map in the crypto map set. Because you can associate each crypto map with different IPSec settings, you can use deny ACEs to exclude special traffic from further evaluation in the corresponding crypto map, and match the special traffic to permit statements in another crypto map to provide or require different security.

**Note**

The crypto access list does not determine whether to permit or deny traffic through the interface. An access list applied directly to the interface with the **access-group** command makes that determination.

**Note**

In transparent mode, the destination address should be the IP address of the security appliance, the management address. Only tunnels to the security appliance are allowed in transparent mode.

Related Commands

Command	Description
clear configure crypto map	Clears all configuration for all crypto maps.
show running-config crypto map	Displays the crypto map configuration.

crypto map set connection-type

To specify the connection type for the Backup Site-to-Site feature for this crypto map entry, use the **crypto map set connection-type** command in global configuration mode. Use the **no** form of this command to return to the default setting.

crypto map *map-name seq-num* **set connection-type** {**answer-only** | **originate-only** | **bidirectional**}

no crypto map *map-name seq-num* **set connection-type** {**answer-only** | **originate-only** | **bidirectional**}

Syntax Description

answer-only	Indicates that this peer can only respond to inbound IKE connections for Site-to-Site connections based on this crypto map entry. It cannot originate connection requests.
bidirectional	Indicates that this peer can accept and originate connections based on this crypto map entry. This is the default connection type for all Site-to-Site connections.
map-name	Specifies the name of the crypto map set.
originate-only	Indicates that this peer can only originate connections based on this crypto map entry. It cannot accept inbound connections.
seq-num	Specifies the number you assign to the crypto map entry.
set connection-type	Specifies the connection type for the Backup Site-to-Site feature for this crypto map entry. There are three types of connections: answer-only, originate-only, and bidirectional.

Defaults

The default setting is bidirectional.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

*In transparent firewall mode, you can see this command but the answer-only value cannot be set to anything other than answer-only for crypto map entries that are part of a crypto map that has been attached to the interface.

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example, entered in global configuration mode, configures the crypto map mymap and sets the connection-type to bidirectional.

```
hostname(config)# crypto map mymap 10 set connection-type bidirectional
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto map	Clears all configuration for all crypto maps.
show running-config crypto map	Displays the crypto map configuration.

crypto map set inheritance

To set the granularity (single or multiple) of security associations generated for this crypto map entry, use the **set inheritance** command in global configuration mode. To remove the inheritance setting for this crypto map entry, use the no form of this command.

crypto map *map-name seq-num set inheritance {data | rule}*

no crypto map *map-name seq-num set inheritance {data | rule}*

Syntax Description

data	Specifies one tunnel for every address pair within the address ranges specified in the rule.
<i>map-name</i>	Specifies the name of the crypto map set.
rule	Specifies one tunnel for each ACL entry associated with this crypto map. Default.
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.
set inheritance	Specifies the type of inheritance: data or rule . Inheritance allows a single security association (SA) to be generated for each security policy database (SPD) rule or multiple security SAs for each address pair in the range.

Defaults

Default value is **rule**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command works only when the security appliance is initiating the tunnel, not when responding to a tunnel. Using the data setting may create a large number of IPSec SAs. This consumes memory and results in fewer overall tunnels. You should use the data setting only for extremely security-sensitive applications.

Examples

The following example, entered in global configuration mode, configures the crypto map mymap and sets the inheritance type to data.

```
hostname(config)# crypto map mymap 10 set inheritance data
hostname(config)#
```

Related Commands	Command	Description
	clear configure crypto map	Clears all configuration for all crypto maps.
	show running-config crypto map	Displays the crypto map configuration.

crypto map set nat-t-disable

To disable NAT-T for connections based on this crypto map entry, use the **crypto map set nat-t-disable** command in global configuration mode. To enable NAT-T for this crypto map entry, use the **no** form of this command.

crypto map *map-name seq-num* **set nat-t-disable**

no crypto map *map-name seq-num* **set nat-t-disable**

Syntax Description

<i>map-name</i>	Specifies the name of the crypto map set.
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.

Defaults

The default setting for this command is not on (therefore NAT-T is enabled by default).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **isakmp nat-traversal** command to globally enable NAT-T. Then you can use the **crypto map set nat-t-disable** command to disable NAT-T for specific crypto map entries.

Examples

The following command, entered in global configuration mode, disables NAT-T for the crypto map entry named mymap.

```
hostname(config)# crypto map mymap 10 set nat-t-disable
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto map	Clears all configuration for all crypto maps.
isakmp nat-traversal	Enables NAT-T for all connections.
show running-config crypto map	Displays the crypto map configuration.

crypto map set peer

To specify an IPSec peer in a crypto map entry, use the **crypto map set peer** command in global configuration mode. Use the **no** form of this command to remove an IPSec peer from a crypto map entry.

```
crypto map map-name seq-num set peer {ip_address | hostname} {...ip_address | hostname10}
```

```
no crypto map map-name seq-num set peer {ip_address | hostname} {...ip_address | hostname10}
```

Syntax Description

<i>hostname</i>	Specifies a peer by its host name as defined by the security appliance name command.
<i>ip_address</i>	Specifies a peer by its IP address.
<i>map-name</i>	Specifies the name of the crypto map set.
peer	Specifies an IPSec peer in a crypto map entry either by hostname or IP address.
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was modified to allow up to 10 peer addresses.

Usage Guidelines

This command is required for all static crypto maps. If you are defining a dynamic crypto map (with the **crypto dynamic-map** command), this command is not required, and in most cases is not used because, in general, the peer is unknown.

For LAN-to-LAN connections, you can use multiple peers only with originator-only connection type. Configuring multiple peers is equivalent to providing a fallback list. For each tunnel, the security appliance attempts to negotiate with the first peer in the list. If that peer does not respond, the security appliance works its way down the list until either a peer responds or there are no more peers in the list. You can set up multiple peers only when using the backup LAN-to-LAN feature (that is, when the crypto map is originate-only type).

Examples

The following example, entered in global configuration mode, shows a crypto map configuration using IKE to establish the security associations. In this example, you can set up a security association to either the peer at 10.0.0.1 or the peer at 10.0.0.2.

```
hostname(config)# crypto map mymap 10 ipsec-isakmp
hostname(config)# crypto map mymap 10 match address 101
hostname(config)# crypto map mymap 10 set transform-set my_t_set1
hostname(config)# crypto map mymap 10 set peer 10.0.0.1 10.0.0.2
```

Related Commands

Command	Description
clear configure crypto map	Clears all configuration for all crypto maps.
show running-config crypto map	Displays the crypto map configuration.

crypto map set pfs

Use the **crypto map set pfs** command in global configuration mode to set IPsec to ask for perfect forward secrecy (PFS) when requesting new security associations for this crypto map entry or that IPsec requires PFS when receiving requests for new security associations. To specify that IPsec should not request PFS, use the **no** form of this command.

crypto map *map-name seq-num* **set pfs** [**group1** | **group2** | **group5** | **group7**]

no crypto map *map-name seq-num* **set pfs** [**group1** | **group2** | **group5** | **group7**]

Syntax Description

group1	Specifies that IPsec should use the 768-bit Diffie-Hellman prime modulus group when performing the new Diffie-Hellman exchange.
group2	Specifies that IPsec should use the 1024-bit Diffie-Hellman prime modulus group when performing the new Diffie-Hellman exchange.
group5	Specifies that IPsec should use the 1536-bit Diffie-Hellman prime modulus group when performing the new Diffie-Hellman exchange.
group7	Specifies that IPsec should use group7 (ECC) where the elliptical curve field size is 163-bits, for example, with the movianVPN client.
<i>map-name</i>	Specifies the name of the crypto map set.
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.

Defaults

By default PFS is not set.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was modified to add Diffie-Hellman group 7.

Usage Guidelines

With PFS, every time a new security association is negotiated, a new Diffie-Hellman exchange occurs, which requires additional processing time. PFS adds another level of security because if one key is ever cracked by an attacker, only the data sent with that key is compromised.

During negotiation, this command causes IPsec to request PFS when requesting new security associations for the crypto map entry. If the **set pfs** statement does not specify a group, the security appliance sends the default (group2).

If the peer initiates the negotiation and the local configuration specifies PFS, the peer must perform a PFS exchange or the negotiation fails. If the local configuration does not specify a group, the security appliance assumes a default of group2. If the local configuration specifies group2, group5, or group7, that group must be part of the peer's offer or the negotiation fails.

For a negotiation to succeed PFS has to be set on both ends. If set, the groups have to be an exact match; The security appliance does not accept just any offer of PFS from the peer.

The 1536-bit Diffie-Hellman prime modulus group, group5, provides more security than group1, or group2, but requires more processing time than the other groups.

Diffie-Hellman Group 7 generates IPSec SA keys, where the elliptical curve field size is 163 bits. You can use this option with any encryption algorithm. This option is intended for use with the movianVPN client, but you can use it with any peers that support Group 7 (ECC).

When interacting with the Cisco VPN Client, the security appliance does not use the PFS value, but instead uses the value negotiated during Phase 1.

Examples

The following example, entered in global configuration mode, specifies that PFS should be used whenever a new security association is negotiated for the crypto map "mymap 10":

```
hostname(config)# crypto map mymap 10 ipsec-isakmp
hostname(config)# crypto map mymap 10 set pfs group2
```

Related Commands

Command	Description
clear isakmp sa	Deletes the active IKE security associations.
clear configure crypto map	Clears all configuration for all crypto maps.
show running-config crypto map	Displays the crypto map configuration.
tunnel-group	Configures tunnel-groups and their parameters.

crypto map set phase1 mode

To specify the IKE mode for phase 1 when initiating a connection to either main or aggressive, use the **crypto map set phase1mode** command in global configuration mode. To remove the setting for phase 1 IKE negotiations, use the **no** form of this command. Including a Diffie-Hellman group with aggressive mode is optional. If one is not included, the security appliance uses group 2.

```
crypto map map-name seq-num set phase1mode {main | aggressive [group1 | group2 | group5 | group7]}
```

```
no crypto map map-name seq-num set phase1mode {main | aggressive [group1 | group2 | group5 | group7]}
```

Syntax Description

aggressive	Specifies aggressive mode for phase one IKE negotiations
group1	Specifies that IPsec should use the 768-bit Diffie-Hellman prime modulus group when performing the new Diffie-Hellman exchange.
group2	Specifies that IPsec should use the 1024-bit Diffie-Hellman prime modulus group when performing the new Diffie-Hellman exchange.
group5	Specifies that IPsec should use the 1536-bit Diffie-Hellman prime modulus group when performing the new Diffie-Hellman exchange.
group7	Specifies that IPsec should use group7 (ECC) where the elliptical curve field size is 163-bits, for example, with the movianVPN client.
main	Specifies main mode for phase one IKE negotiations.
<i>map-name</i>	Specifies the name of the crypto map set.
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.

Defaults

Default phase one mode is **main**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command works only in initiator mode; not in responder mode.

Examples

The following example, entered in global configuration mode, configures the crypto map my map and sets the phase one mode to aggressive, using group 2.

```
hostname(config)# crypto map mymap 10 set phase1mode aggressive group2
hostname(config)#
```

Related Commands

Command	Description
clear isakmp sa	Delete the active IKE security associations.
clear configure crypto map	Clears all configuration for all crypto maps.
show running-config crypto map	Displays the crypto map configuration.

crypto map set reverse-route

To enable RRI for any connection based on this crypto map entry, use the **crypto map set reverse-route** command in global configuration mode. To disable reverse route injection for any connection based this crypto map entry, use the **no** form of this command.

crypto map *map-name seq-num set reverse-route*

no crypto map *map-name seq-num set reverse-route*

Syntax Description

<i>map-name</i>	Specifies the name of the crypto map set.
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.

Defaults

The default setting for this command is off.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The security appliance can automatically add static routes to the routing table and announce these routes to its private network or border routers using OSPF.

Examples

The following example, entered in global configuration mode, enables RRI for the crypto map named mymap.

```
hostname(config)# crypto map mymap 10 set reverse-route
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto map	Clears all configuration for all crypto maps.
show running-config crypto map	Displays the crypto map configuration.

crypto map set security-association lifetime

To override (for a particular crypto map entry) the global lifetime value, which is used when negotiating IPSec security associations, use the **crypto map set security-association lifetime** command in global configuration mode. To reset a crypto map entry's lifetime value to the global value, use the **no** form of this command.

crypto map *map-name seq-num* **set security-association lifetime** {seconds *seconds* | kilobytes *kilobytes*}

no crypto map *map-name seq-num* **set security-association lifetime** {seconds *seconds* | kilobytes *kilobytes*}

Syntax Description

<i>kilobytes</i>	Specifies the volume of traffic (in kilobytes) that can pass between peers using a given security association before that security association expires. The default is 4,608,000 kilobytes.
<i>map-name</i>	Specifies the name of the crypto map set.
<i>seconds</i>	Specifies the number of seconds a security association will live before it expires. The default is 28,800 seconds (eight hours).
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.

Defaults

The default number of kilobytes is 4,608,000; the default number of seconds is 28,800.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The crypto map's security associations are negotiated according to the global lifetimes.

IPSec security associations use shared secret keys. These keys and their security associations time out together.

Assuming that the particular crypto map entry has lifetime values configured, when the security appliance requests new security associations during security association negotiation, it specifies its crypto map lifetime values in the request to the peer; it uses these values as the lifetime of the new security associations. When the security appliance receives a negotiation request from the peer, it uses the smaller of the lifetime values proposed by the peer or the locally configured lifetime values as the lifetime of the new security associations.

There are two lifetimes: a “timed” lifetime and a “traffic-volume” lifetime. The session keys/security association expires after the first of these lifetimes is reached. You can specify both with one command.

**Note**

The security appliance lets you change crypto map, dynamic map, and ipsec settings on the fly. If you do so, the security appliance brings down only the connections affected by the change. If you change an existing access-list associated with a crypto map, specifically by deleting an entry within the access-list, the result is that only the associated connection is brought down. Connections based on other entries in the access-list are not affected.

To change the timed lifetime, use the **crypto map set security-association lifetime seconds** command. The timed lifetime causes the keys and security association to time out after the specified number of seconds have passed.

Examples

The following command, entered in global configuration mode, specifies a security association lifetime in seconds and kilobytes for crypto map mymap

```
hostname(config)# crypto map mymap 10 set security-association lifetime seconds 1400  
kilobytes 3000000  
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto map	Clears all configuration for all crypto maps.
show running-config crypto map	Displays the crypto map configuration.

crypto map set transform-set

To specify the transform sets to use with the crypto map entry, use the **crypto map set transform-set** command in global configuration mode. Use the **no** form of this command to remove the specified transform sets from a crypto map entry.

crypto map *map-name seq-num set transform-set transform-set-name1*
[... *transform-set-name9*]

no crypto map *map-name seq-num set transform-set transform-set-name1*
[... *transform-set-name9*]

Syntax Description

<i>map-name</i>	Specifies the name of the crypto map set.
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.
<i>transform-set-name1</i> <i>transform-set-name9</i>	Specifies the name(s) of the transform set(s), defined using the crypto ipsec transform-set command, to use for the crypto map. For an ipsec-isakmp or dynamic crypto map entry, you can specify up to nine transform sets.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

This command is required for all crypto map entries.

If the local security appliance initiates the negotiation, the transform sets are presented to the peer in the order specified in the **crypto map** command statement. If the peer initiates the negotiation, the local security appliance accepts the first transform set that matches one of the transform sets specified in the crypto map entry.

The first matching transform set that is found at both peers is used for the security association. If no match is found, IPSec does not establish a security association. The traffic is dropped because there is no security association to protect the traffic.

If you want to change the list of transform sets, respecify the new list of transform sets to replace the old list. This change is applied only to **crypto map** command statements that reference this transform set.

Any transform sets included in a **crypto map** command statement must previously have been defined using the **crypto ipsec transform-set** command.

Examples

The following example, entered in global configuration mode, specifies two transform sets (tfset1 and tfset2) for the crypto map mymap.

```
hostname(config)# crypto map mymap 10 set transform-set tfset1 tfset2
hostname(config)#
```

The following example, entered in global configuration mode, shows the minimum required crypto map configuration when the security appliance uses IKE to establish the security associations:

```
hostname(config)# crypto map mymap 10 ipsec-isakmp
hostname(config)# crypto map mymap 10 match address 101
hostname(config)# crypto map mymap set transform-set my_t_set1
hostname(config)# crypto map mymap set peer 10.0.0.1
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto map	Clears all configuration for all crypto maps.
crypto ipsec transform-set	Configures a transform-set.
show running-config crypto map	Displays the crypto map configuration.

crypto map set trustpoint

To specify the trustpoint that identifies the certificate to send for authentication during Phase 1 negotiations for the crypto map entry, use the **crypto map set trustpoint** command in global configuration mode. Use the **no** form of this command to remove a trustpoint from a crypto map entry.

crypto map *map-name seq-num set trustpoint trustpoint-name [chain]*

no crypto map *map-name seq-num set trustpoint trustpoint-name [chain]*

Syntax Description

chain	(Optional) Sends a certificate chain. A CA certificate chain includes all CA certificates in a hierarchy of certificates from the root certificate to the identity certificate. The default value is disable (no chain).
<i>map-name</i>	Specifies the name of the crypto map set.
<i>seq-num</i>	Specifies the number you assign to the crypto map entry.
<i>trustpoint-name</i>	Identifies the certificate to be sent during Phase 1 negotiations. The default is none.

Defaults

The default value is none.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This crypto map command is valid only for initiating a connection. For information on the responder side, see the **tunnel-group** commands.

Examples

The following example, entered in global configuration mode, specifies a trustpoint named tpoint1 for crypto map mymap and includes the chain of certificates.

```
hostname(config)# crypto map mymap 10 set trustpoint tpoint1 chain
hostname(config)#
```

Related Commands

Command	Description
clear configure crypto map	Clears all configuration for all crypto maps.
show running-config crypto map	Displays the crypto map configuration.
tunnel-group	Configures tunnel groups.



D through F Commands

debug aaa

To show debug messages for AAA, use the **debug aaa** command in privileged EXEC mode. To stop showing AAA messages, use the **no** form of this command.

debug aaa [**accounting** | **authentication** | **authorization** | **internal** | **vpn** [*level*]]

no debug aaa

Syntax Description

accounting	(Optional) Show debug messages for accounting only.
authentication	(Optional) Show debug messages for authentication only.
authorization	(Optional) Show debug messages for authorization only.
internal	(Optional) Show debug messages for AAA functions supported by the local database only.
<i>level</i>	(Optional) Specifies the debug level. Valid with the vpn keyword only.
vpn	(Optional) Show debug messages for VPN-related AAA functions only.

Defaults

The default *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was modified to include new keywords.

Usage Guidelines

The **debug aaa** command displays detailed information about AAA activity. The **no debug all** or **undebug all** commands turn off all enabled debugs.

Examples

The following example enables debugging for AAA functions supported by the local database:

```
hostname(config)# debug aaa internal
debug aaa internal enabled at level 1
hostname(config)# uap allocated. remote address: 10.42.15.172, Session_id: 2147483841
uap freed for user . remote address: 10.42.15.172, session id: 2147483841
```

Related Commands

Command	Description
show running-config aaa	Displays running configuration related to AAA.

debug arp

To show debug messages for ARP, use the **debug arp** command in privileged EXEC mode. To stop showing debug messages for ARP, use the **no** form of this command.

debug arp

no debug arp

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for ARP:

```
hostname# debug arp
```

Related Commands

Command	Description
arp	Adds a static ARP entry.
show arp statistics	Shows ARP statistics.
show debug	Shows all enabled debuggers.

debug arp-inspection

To show debug messages for ARP inspection, use the **debug arp-inspection** command in privileged EXEC mode. To stop showing debug messages for ARP inspection, use the **no** form of this command.

debug arp-inspection

no debug arp-inspection

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	—	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for ARP inspection:

```
hostname# debug arp-inspection
```

Related Commands

Command	Description
arp	Adds a static ARP entry.
arp-inspection	For transparent firewall mode, inspects ARP packets to prevent ARP spoofing.
show debug	Shows all enabled debuggers.

debug asdm history

To view debug information for ASDM, use the **debug asdm history** command in privileged EXEC mode.

debug asdm history *level*

Syntax Description

level (Optional) Specifies the debug level.

Defaults

The default *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was changed from the debug pdm history command to the debug asdm history command.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables level 1 debugging of ASDM:

```
hostname# debug asdm history
debug asdm history enabled at level 1

hostname#
```

Related Commands

Command	Description
show asdm history	Displays the contents of the ASDM history buffer.

debug cmgr

To show debug messages about the SSM card manager, use the **debug cmgr** command in privileged EXEC mode. To stop showing debug messages for the card manager, use the **no** form of this command.

debug cmgr [*level*]

no debug cmgr [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for the card manager:

```
hostname# debug cmgr
```

Related Commands

Command	Description
hw-module module recover	Recovers an AIP SSM by loading a recovery image from a TFTP server.
hw-module module reset	Shuts down an AIP SSM and performs a hardware reset.
hw-module module reload	Reloads the AIP SSM software.

Command	Description
hw-module module shutdown	Shuts down the AIP SSM software in preparation for being powered off without losing configuration data.
show module	Shows SSM information.

debug context

To show debug messages when you add or delete a security context, use the **debug context** command in privileged EXEC mode. To stop showing debug messages for contexts, use the **no** form of this command.

debug context [*level*]

no debug context [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for context management:

```
hostname# debug context
```

Related Commands

Command	Description
context	Creates a security context in the system configuration and enters context configuration mode.
show context	Shows context information.
show debug	Shows all enabled debuggers.

debug cplane

To show debug messages about the control plane that connects internally to an SSM, use the **debug cplane** command in privileged EXEC mode. To stop showing debug messages for the control plane, use the **no** form of this command.

debug cplane [*level*]

no debug cplane [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for the control plane:

```
hostname# debug cplane
```

Related Commands

Command	Description
hw-module module recover	Recovers an intelligent SSM by loading a recovery image from a TFTP server.
hw-module module reset	Shuts down an SSM and performs a hardware reset.
hw-module module reload	Reloads the intelligent SSM software.

Command	Description
hw-module module shutdown	Shuts down the SSM software in preparation for being powered off without losing configuration data.
show module	Shows SSM information.

debug crypto ca

To show debug messages for PKI activity (used with CAs), use the **debug crypto ca** command in privileged EXEC mode. To stop showing debug messages for PKI, use the **no** form of this command.

debug crypto ca [**messages** | **transactions**] [*level*]

no debug crypto ca [**messages** | **transactions**] [*level*]

Syntax Description

messages	(Optional) Shows only debug messages for PKI input and output messages.
transactions	(Optional) Shows only debug messages for PKI transactions.
<i>level</i>	(Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number. Level 1 (the default) shows messages only when errors occur. Level 2 shows warnings. Level 3 shows informational messages. Levels 4 and up show additional information for troubleshooting.

Defaults

By default, this command shows all debug messages. The default level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for PKI:

```
hostname# debug crypto ca
```

Related Commands

Command	Description
debug crypto engine	Shows debug messages for the crypto engine.
debug crypto ipsec	Shows debug messages for IPSec.
debug crypto isakmp	Shows debug messages for ISAKMP.

debug crypto engine

To show debug messages for the crypto engine, use the **debug crypto engine** command in privileged EXEC mode. To stop showing debug messages for the crypto engine, use the **no** form of this command.

debug crypto engine [*level*]

no debug crypto engine [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for the crypto engine:

```
hostname# debug crypto engine
```

Related Commands

Command	Description
debug crypto ca	Shows debug messages for the CA.
debug crypto ipsec	Shows debug messages for IPsec.
debug crypto isakmp	Shows debug messages for ISAKMP.

debug crypto ipsec

To show debug messages for IPSec, use the **debug crypto ipsec** command in privileged EXEC mode. To stop showing debug messages for IPSec, use the **no** form of this command.

debug crypto ipsec [*level*]

no debug crypto ipsec [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for IPSec:

```
hostname# debug crypto ipsec
```

Related Commands

Command	Description
debug crypto ca	Shows debug messages for the CA.
debug crypto engine	Shows debug messages for the crypto engine.
debug crypto isakmp	Shows debug messages for ISAKMP.

debug crypto isakmp

To show debug messages for ISAKMP, use the **debug crypto isakmp** command in privileged EXEC mode. To stop showing debug messages for ISAKMP, use the **no** form of this command.

debug crypto isakmp [**timers**] [*level*]

no debug crypto isakmp [**timers**] [*level*]

Syntax Description

timers	(Optional) Shows debug messages for ISAKMP timer expiration.
<i>level</i>	(Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number. Level 1 (the default) shows messages only when errors occur. Levels 2 through 7 show additional information. Level 254 shows decrypted ISAKMP packets in a human readable format. Level 255 shows hexadecimal dumps of decrypted ISAKMP packets.

Defaults

The default level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for ISAKMP:

```
hostname# debug crypto isakmp
```

Related Commands

Command	Description
debug crypto ca	Shows debug messages for the CA.
debug crypto engine	Shows debug messages for the crypto engine.
debug crypto ipsec	Shows debug messages for IPSec.

debug ctiqbe

To show debug messages for CTIQBE application inspection, use the **debug ctiqbe** command in privileged EXEC mode. To stop showing debug messages for CTIQBE application inspection, use the **no** form of this command.

debug ctiqbe [*level*]

no debug ctiqbe [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug ctiqbe** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for CTIQBE application inspection:

```
hostname# debug ctiqbe
```

Related Commands

Command	Description
inspect ctique	Enables CTIQBE application inspection.
show ctique	Displays information about CTIQBE sessions established through the security appliance.
show conn	Displays the connection state for different connection types.
timeout	Sets the maximum idle time duration for different protocols and session types.

debug dhcpc

To enable debugging of the DHCP client, use the **debug dhcpc** command in privileged EXEC mode. To disable debugging, use the **no debug dhcpc** form of this command.

debug dhcpc {**detail** | **packet** | **error**} [*level*]

no debug dhcpc {**detail** | **packet** | **error**} [*level*]

Syntax Description

detail	Displays detail event information that is associated with the DHCP client.
error	Displays error messages that are associated with the DHCP client.
<i>level</i>	(Optional) Specifies the debug level. Valid valuse range from 1 to 255.
packet	Displays packet information that is associated with the DHCP client.

Defaults

The default debug level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Displays DHCP client debug information.

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example shows how to enable debugging for the DHCP client:

```
hostname# debug dhcpc detail 5
debug dhcpc detail enabled at level 5
```

Related Commands

Command	Description
show ip address dhcp	Displays detailed information about the DHCP lease for an interface.
show running-config interface	Displays the running configuration of the specified interface.

debug dhcpd

To enable debugging of the DHCP server, use the **debug dhcpd** command in privileged EXEC mode. To disable debugging, use the **no** form of this command.

debug dhcpd {event | packet} [*level*]

no debug dhcpd {event | packet} [*level*]

Syntax Description

event	Displays event information that is associated with the DHCP server.
<i>level</i>	(Optional) Specifies the debug level. Valid valuse range from 1 to 255.
packet	Displays packet information that is associated with the DHCP server.

Defaults

The default debug level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **debug dhcpd event** command displays event information about the DHCP server. The **debug dhcpd packet** command displays packet information about the DHCP server.

Use the **no** form of the **debug dhcpd** commands to disable debugging.

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following shows an example of enabling DHCP event debugging:

```
hostname# debug dhcpd event
debug dhcpd event enabled at level 1
```

Related Commands

Command	Description
show dhcpd	Displays DHCP binding, statistic, or state information.
show running-config dhcpd	Displays the current DHCP server configuration.

debug dhcprelay

To enable debugging of the DHCP relay server, use the **debug dhcprelay** command in privileged EXEC mode. To disable debugging, use the **no** form of this command.

debug dhcprelay {event | packet | error} [level]

no debug dhcprelay {event | packet | error} [level]

Syntax Description

error	Displays error messages that are associated with the DHCP relay agent.
event	Displays event information that is associated with the DHCP relay agent.
<i>level</i>	(Optional) Specifies the debug level. Valid valuse range from 1 to 255.
packet	Displays packet information that is associated with the DHCP relay agent.

Defaults

The default debug level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example shows how to enable debugging for DHCP relay agent error messages:

```
hostname# debug dhcprelay error
debug dhcprelay error enabled at level 1
```

Related Commands	Command	Description
	clear configure dhcprelay	Removes all DHCP relay agent settings.
	clear dhcprelay statistics	Clears the DHCP relay agent statistic counters.
	show dhcprelay statistics	Displays DHCP relay agent statistic information.
	show running-config dhcprelay	Displays the current DHCP relay agent configuration.

debug disk

To display file system debug information, use the **debug disk** command in privileged EXEC mode. To disable the display of debug information, use the **no** form of this command.

debug disk { **file** | **file-verbose** | **filesystem** } [*level*]

no debug disk { **file** | **file-verbose** | **filesystem** }

Syntax Description

file	Enables file-level disk debug messages.
file-verbose	Enables verbose file-level disk debug messages
filesystem	Enables file system debug messages.
<i>level</i>	(Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables file-level disk debug messages. The **show debug** command reveals that file-level disk debug messages are enabled. The **dir** command causes several debug messages.

```
hostname# debug disk file
debug disk file enabled at level 1
hostname# show debug
debug vpn-sessiondb enabled at level 1
hostname# dir
```

```

IFS: Opening: file flash:/, flags 1, mode 0
IFS: Opened: file flash:/ as fd 3
IFS: Getdent: fd 3
IFS: Getdent: fd 3
IFS: Getdent: fd 3
IFS: Getdent: fd 3

Directory of flash:/
IFS: Close: fd 3
IFS: Opening: file flash:/, flags 1, mode 0

4      -rw-  5124096      14:42:27 Apr 04 2005  cdisk.binIFS: Opened: file flash:/ as fd 3

9      -rw-  5919340      14:53:39 Apr 04 2005  ASDMIFS: Getdent: fd 3

11     drw-   0           15:18:56 Apr 21 2005  syslog
IFS: Getdent: fd 3
IFS: Getdent: fd 3
IFS: Getdent: fd 3
IFS: Close: fd 3

16128000 bytes total (5047296 bytes free)

```

Related Commands

Command	Description
show debug	Displays current debug configuration.

debug dns

To show debug messages for DNS, use the **debug dns** command in privileged EXEC mode. To stop showing debug messages for DNS, use the **no** form of this command.

debug dns [**resolver** | **all**] [*level*]

no debug dns [**resolver** | **all**] [*level*]

Syntax Description

<i>level</i>	(Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.
resolver	(Optional) Shows only DNS resolver messages.
all	(Default) Shows all messages, including messages about the DNS cache.

Defaults

The default level is 1. If you do not specify any keywords, the security appliance shows all messages.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for DNS:

```
hostname# debug dns
```

Related Commands

Command	Description
class-map	Defines the traffic class to which to apply security actions.
inspect dns	Enables DNS application inspection.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

debug entity

To display management information base (MIB) debug information, use the **debug entity** command in privileged EXEC mode. To disable the display of debug information, use the **no** form of this command.

debug entity [*level*]

no debug entity

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables MIB debug messages. The **show debug** command reveals that MIB debug messages are enabled.

```
hostname# debug entity
debug entity enabled at level 1
hostname# show debug
debug entity enabled at level 1
hostname#
```

Related Commands

Command	Description
show debug	Displays current debug configuration.

debug fixup

To display detailed information about application inspection, use the **debug fixup** command in privileged EXEC mode. To disable debugging, Use the **no** form of this command.

debug fixup

no debug fixup

Defaults

All options are enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **debug fixup** command displays detailed information about application inspection. The **no debug all** or **undebug all** commands turn off all enabled debugs.

Examples

The following example enables the display of detailed information about application inspection:

```
hostname# debug fixup
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
inspect protocol	Enables application inspection for specific protocols.
policy-map	Associates a class map with specific security actions.

debug fover

To display failover debug information, use the **debug fover** command in privileged EXEC mode. To disable the display of debug information, use the **no** form of this command.

debug fover { **cable** | **fail** | **fmsg** | **ifc** | **open** | **rx** | **rxdump** | **rxip** | **switch** | **sync** | **tx** | **txdump** | **txip** | **verify** }

no debug fover { **cable** | **fail** | **fmsg** | **ifc** | **open** | **rx** | **rxdump** | **rxip** | **switch** | **sync** | **tx** | **txdump** | **txip** | **verify** }

Syntax Description

cable	Failover LAN status or serial cable status.
fail	Failover internal exception.
fmsg	Failover message.
ifc	Network interface status trace.
open	Failover device open.
rx	Failover message receive.
rxdump	Failover receive message dump (serial console only).
rxip	IP network failover packet receive.
switch	Failover switching status.
sync	Failover configuration/command replication.
tx	Failover message transmit.
txdump	Failover transmit message dump (serial console only).
txip	IP network failover packet transmit.
verify	Failover message verify.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was modified. It includes additional debug keywords.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example shows how to display debug information for failover command replication:

```
hostname# debug fover sync  
fover event trace on
```

Related Commands

Command	Description
show failover	Displays information about the failover configuration and operational statistics.

debug fsm

To display FSM debug information, use the **debug fsm** command in privileged EXEC mode. To disable the display of debug information, use the **no** form of this command.

debug fsm [*level*]

no debug fsm

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables FSM debug messages. The **show debug** command reveals that FSM debug messages are enabled.

```
hostname# debug fsm
debug fsm  enabled at level 1
hostname# show debug
debug fsm  enabled at level 1
hostname#
```

Related Commands

Command	Description
show debug	Displays current debug configuration.

debug ftp client

To show debug messages for FTP, use the **debug ftp client** command in privileged EXEC mode. To stop showing debug messages for FTP, use the **no** form of this command.

debug ftp client [*level*]

no debug ftp client [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug ftp client** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for FTP:

```
hostname# debug ftp client
```


Related Commands

Command	Description
copy	Uploads or downloads image files or configuration files to or from an FTP server.
ftp mode passive	Configures the mode for FTP sessions.
show running-config ftp mode	Displays FTP client configuration.

debug generic

To display miscellaneous debug information, use the **debug generic** command in privileged EXEC mode. To disable the display of miscellaneous debug information, use the **no** form of this command.

debug generic [*level*]

no debug generic

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables miscellaneous debug messages. The **show debug** command reveals that miscellaneous debug messages are enabled.

```
hostname# debug generic
debug generic enabled at level 1
hostname# show debug
debug generic enabled at level 1
hostname#
```

Related Commands

Command	Description
show debug	Displays current debug configuration.

debug gtp

To display detailed information about GTP inspection, use the **debug gtp** command in privileged EXEC mode. To disable debugging, Use the **no** form of this command.

debug gtp [**error** | **event** | **ha** | **parser**]

no debug gtp [**error** | **event** | **ha** | **parser**]

Syntax Description

error	(Optional) Displays debug information on errors encountered while processing the GTP message.
event	(Optional) Displays debug information on GTP events.
ha option	(Optional) Debugs information on GTP HA events.
parser	(Optional) Displays debug information for parsing the GTP messages.

Defaults

All options are enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **debug gtp** command displays detailed information about GTP inspection. The **no debug all** or **undebug all** commands turn off all enabled debugs.



Note

GTP inspection requires a special license.

Examples

The following example enables the display of detailed information about GTP inspection:

```
hostname# debug gtp
```

Related Commands	Commands	Description
	clear service-policy inspect gtp	Clears global GTP statistics.
	gtp-map	Defines a GTP map and enables GTP map configuration mode.
	inspect gtp	Applies a GTP map to use for application inspection.
	show service-policy inspect gtp	Displays the GTP configuration.
	show running-config gtp-map	Shows the GTP maps that have been configured.

debug h323

To show debug messages for H.323, use the **debug h323** command in privileged EXEC mode. To stop showing debug messages for H.323, use the **no** form of this command.

debug h323 {h225 | h245 | ras} [asn | event]

no debug h323 {h225 | h245 | ras} [asn | event]

Syntax Description

h225	Specifies H.225 signaling.
h245	Specifies H.245 signaling.
ras	Specifies the registration, admission, and status protocol.
asn	(Optional) Displays the output of the decoded protocol data units (PDU)s.
event	(Optional) Displays the events of the H.245 signaling or turns on both traces.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug h323** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for H.225 signaling

```
hostname# debug h323 h225
```

Related Commands

Command	Description
inspect h323	Enables H.323 application inspection.
show h225	Displays information for H.225 sessions established across the security appliance.
show h245	Displays information for H.245 sessions established across the security appliance by endpoints using slow start.
show h323-ras	Displays information for H.323 RAS sessions established across the security appliance.
timeout h225 h323	Configures idle time after which an H.225 signalling connection or an H.323 control connection will be closed.

debug http

To display detailed information about HTTP traffic, use the **debug http** command in privileged EXEC mode. To disable debugging, Use the **no** form of this command.

debug http [*level*]

no debug http [*level*]

Syntax Description	<i>level</i>	(Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults The default for *level* is 1.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines The **debug http** command displays detailed information about HTTP traffic. The **no debug all** or **undebug all** commands turn off all enabled debugs.

Examples The following example enables the display of detailed information about HTTP traffic:

```
hostname# debug http
```

Related Commands	Commands	Description
	http	Specifies hosts that can access the HTTP server internal to the security appliance.
	http-proxy	Configures an HTTP proxy server.
	http redirect	Redirects HTTP traffic to HTTPS.
	http server enable	Enables the security appliance HTTP server.

debug http-map

To show debug messages for HTTP application inspection maps, use the **debug http-map** command in privileged EXEC mode. To stop showing debug messages for HTTP application inspection, use the **no** form of this command.

debug http-map

no debug http-map

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug http-map** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for HTTP application inspection:

```
hostname# debug http-map
```

Related Commands

Command	Description
class-map	Defines the traffic class to which to apply security actions.
debug appfw	Displays detailed information about HTTP application inspection.
http-map	Defines an HTTP map for configuring enhanced HTTP inspection.
inspect http	Applies a specific HTTP map to use for application inspection.
policy-map	Associates a class map with specific security actions.

debug icmp

To display detailed information about ICMP inspection, use the **debug icmp** command in privileged EXEC mode. To disable debugging, Use the **no** form of this command.

debug icmp trace [*level*]

no debug icmp trace [*level*]

Syntax Description	trace	Displays debug information about ICMP trace activity.
	<i>level</i>	(Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults All options are enabled.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines The **debug icmp** command displays detailed information about ICMP inspection. The **no debug all** or **undebug all** commands turn off all enabled debugs.

Examples The following example enables the display of detailed information about ICMP inspection:

```
hostname# debug icmp
```

Related Commands	Commands	Description
	clear configure icmp	Clears the ICMP configuration.
	icmp	Configures access rules for ICMP traffic that terminates at a security appliance interface.
	show conn	Displays the state of connections through the security appliance for different protocols and session types.

Commands	Description
show icmp	Displays ICMP configuration.
timeout icmp	Configures idle timeout for ICMP.

debug igmp

To display IGMP debug information, use the **debug igmp** command in privileged EXEC mode. To stop the display of debug information, use the **no** form of this command.

debug igmp [**group** *group_id* | **interface** *if_name*]

no debug igmp [**group** *group_id* | **interface** *if_name*]

Syntax Description

group <i>group_id</i>	Displays IGMP debug information for the specified group.
interface <i>if_name</i>	Display IGMP debug information for the specified interface.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following is sample output from the **debug igmp** command:

```
hostname#debug igmp
```

```
IGMP debugging is on
IGMP: Received v2 Query on outside from 192.168.3.2
IGMP: Send v2 general Query on dmz
IGMP: Received v2 Query on dmz from 192.168.4.1
IGMP: Send v2 general Query on outside
IGMP: Received v2 Query on outside from 192.168.3.1
IGMP: Send v2 general Query on inside
IGMP: Received v2 Query on inside from 192.168.1.1
IGMP: Received v2 Report on inside from 192.168.1.6 for 224.1.1.1
IGMP: Updating EXCLUDE group timer for 224.1.1.1
```

Related Commands	Command	Description
	show igmp groups	Displays the multicast groups with receivers that are directly connected to the security appliance and that were learned through IGMP.
	show igmp interface	Displays multicast information for an interface.

debug ils

To show debug messages for ILS, use the **debug ils** command in privileged EXEC mode. To stop showing debug messages for ILS, use the **no** form of this command.

debug ils [*level*]

no debug ils [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug ils** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for ILS application inspection:

```
hostname# debug ils
```

Related Commands

Command	Description
class-map	Defines the traffic class to which to apply security actions.
inspect ils	Enables ILS application inspection.

Command	Description
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

debug imagemgr

To display Image Manager debug information, use the **debug imagemgr** command in privileged EXEC mode. To disable the display of debug information, use the **no** form of this command.

debug imagemgr [*level*]

no debug imagemgr

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables Image Manager debug messages. The **show debug** command reveals that Image Manager debug messages are enabled.

```
hostname# debug imagemgr
debug imagemgr enabled at level 1
hostname# show debug
debug imagemgr enabled at level 1
hostname#
```


Related Commands

Command	Description
show debug	Displays current debug configuration.

debug ipsec-over-tcp

To display IPSec-over-TCP debug information, use the **debug ipsec-over-tcp** command in privileged EXEC mode. To disable the display of debug information, use the **no** form of this command.

debug ipsec-over-tcp [*level*]

no debug ipsec-over-tcp

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables IPSec-over-TCP debug messages. The **show debug** command reveals that IPSec-over-TCP debug messages are enabled.

```
hostname# debug ipsec-over-tcp
debug ipsec-over-tcp  enabled at level 1
hostname# show debug
debug ipsec-over-tcp  enabled at level 1
hostname#
```

Related Commands

Command	Description
show debug	Displays current debug configuration.

debug ipsec-pass-thru

To show debug messages for ipsec-pass-thru, use the **debug ipsec-pass-thru** command in privileged EXEC mode. To stop showing debug messages for DNS, use the **no** form of this command.

debug ipsec-pass-thru *level*

no debug ipsec-pass-thru

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default level is 1. If you do not specify any keywords, the security appliance shows all messages.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0(5)	This command was introduced.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for DNS:

```
hostname# debug ipsec-pass-thru
```

Related Commands

Command	Description
inspect	Enables IPSec pass-thru application inspection.
ipsec-pass-thru	

debug ipv6

To display ipv6 debug messages, use the **debug ipv6** command in privileged EXEC mode. To stop the display of debug messages, use the **no** form of this command.

debug ipv6 {icmp | interface | nd | packet | routing}

no debug ipv6 {icmp | interface | nd | packet | routing}

Syntax Description

icmp	Displays debug messages for IPv6 ICMP transactions, excluding ICMPv6 neighbor discovery transactions.
interface	Displays debug information for IPv6 interfaces.
nd	Displays debug messages for ICMPv6 neighbor discovery transactions.
packet	Displays debug messages for IPv6 packets.
routing	Displays debug messages for IPv6 routing table updates and route cache updates.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following is sample output for the **debug ipv6 icmp** command:

```
hostname# debug ipv6 icmp
13:28:40:ICMPv6:Received ICMPv6 packet from 2000:0:0:3::2, type 136
13:28:45:ICMPv6:Received ICMPv6 packet from FE80::203:A0FF:FED6:1400, type 135
13:28:50:ICMPv6:Received ICMPv6 packet from FE80::203:A0FF:FED6:1400, type 136
13:28:55:ICMPv6:Received ICMPv6 packet from FE80::203:A0FF:FED6:1400, type 135
```

Related Commands	Command	Description
	ipv6 icmp	Defines access rules for ICMP messages that terminate on a security appliance interface.
	ipv6 address	Configures an interface with an IPv6 address or addresses.
	ipv6 nd dad attempts	Defines the number of neighbor discovery attempts performed during duplicate address detection.
	ipv6 route	Defines a static entry in the IPv6 routing table.

debug iua-proxy

To display individual user authentication (IUA) proxy debug information, use the **debug iua-proxy** command in privileged EXEC mode. To disable the display of debug information, use the **no** form of this command.

debug iua-proxy [*level*]

no debug iua-proxy

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables IUA-proxy debug messages. The **show debug** command reveals that IUA-proxy debug messages are enabled.

```
hostname# debug iua-proxy
debug iua-proxy enabled at level 1
hostname# show debug
debug iua-proxy enabled at level 1
hostname#
```

 debug iua-proxy**Related Commands**

Command	Description
show debug	Displays current debug configuration.

debug kerberos

To display Kerberos authentication debug information, use the **debug kerberos** command in privileged EXEC mode. To disable the display of debug information, use the **no** form of this command.

debug kerberos [*level*]

no debug kerberos

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables Kerberos debug messages. The **show debug** command reveals that Kerberos debug messages are enabled.

```
hostname# debug kerberos
debug kerberos  enabled at level 1
hostname# show debug
debug kerberos  enabled at level 1
hostname#
```

 debug kerberos**Related Commands**

Command	Description
show debug	Displays current debug configuration.

debug ldap

To display LDAP debug information, use the **debug ldap** command in privileged EXEC mode. To disable the display of debug information, use the **no** form of this command.

debug ldap [*level*]

no debug ldap

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables LDAP debug messages. The **show debug** command reveals that LDAP debug messages are enabled.

```
hostname# debug ldap
debug ldap enabled at level 1
hostname# show debug
debug ldap enabled at level 1
hostname#
```

Related Commands

Command	Description
show debug	Displays current debug configuration.

debug mac-address-table

To show debug messages for the MAC address table, use the **debug mac-address-table** command in privileged EXEC mode. To stop showing debug messages for the MAC address table, use the **no** form of this command.

debug mac-address-table [*level*]

no debug mac-address-table [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	—	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for the MAC address table:

```
hostname# debug mac-address-table
```

Related Commands

Command	Description
mac-address-table aging-time	Sets the timeout for dynamic MAC address entries.
mac-address-table static	Adds static MAC address entries to the MAC address table.
mac-learn	Disables MAC address learning.

Command	Description
show debug	Shows all enabled debuggers.
show mac-address-table	Shows MAC address table entries.

debug menu

To display detailed debug information for specific features, use the **debug menu** command in privileged EXEC mode.

debug menu



Caution

The **debug menu** command should be used only under the supervision of Cisco technical support staff.

Syntax Description

This command should be used only under the supervision of Cisco technical support staff.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

This command should be used only under the supervision of Cisco technical support staff.

Related Commands

Command	Description
show debug	Displays current debug configuration.

debug mfib

To display MFIB debug information, use the **debug mfib** command in privileged EXEC mode. To stop displaying debug information, use the **no** form of this command.

debug mfib {**db** | **init** | **mrrib** | **pak** | **ps** | **signal**} [*group*]

no debug mfib {**db** | **init** | **mrrib** | **pak** | **ps** | **signal**} [*group*]

Syntax Description

db	(Optional) Displays debug information for route database operations.
<i>group</i>	(Optional) IP address of the multicast group.
init	(Optional) Displays system initialization activity.
mrrib	(Optional) Displays debug information for communication with MRIB.
pak	(Optional) Displays debug information for packet forwarding operations.
ps	(Optional) Displays debug information for process switching operations.
signal	(Optional) Displays debug information for MFIB signaling to routing protocols.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example displays MFIB database operation debug information:

```
hostname# debug mfib db
MFIB IPv4 db debugging enabled
```


Related Commands

Command	Description
show mfib	Displays MFIB forwarding entries and interfaces.

debug mgcp

To display detailed information about MGCP application inspection, use the **debug mgcp** command in privileged EXEC mode. To disable debugging, Use the **no** form of this command.

debug mgcp {messages | parser | sessions}

no debug mgcp {messages | parser | sessions}

messages	Displays debug information about MGCP messages.
parser	Displays debug information for parsing MGCP messages.
sessions	Displays debug information about MGCP sessions.

Defaults

All options are enabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **debug mgcp** command displays detailed information about mgcp inspection. The **no debug all** or **undebug all** commands turn off all enabled debugs.

Examples

The following example enables the display of detailed information about MGCP application inspection:

```
hostname# debug mgcp
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
inspect mgcp	Enables MGCP application inspection.
mgcp-map	Defines an MGCP map and enables MGCP map configuration mode.
show mgcp	Displays information about MGCP sessions established through the security appliance.
show conn	Displays the connection state for different connection types.

debug module-boot

To show debug messages about the SSM booting process, use the **debug module-boot** command in privileged EXEC mode. To stop showing debug messages for the SSM booting process, use the **no** form of this command.

debug module-boot [*level*]

no debug module-boot [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for the SSM booting process:

```
hostname# debug module-boot
```

Related Commands

Command	Description
hw-module module recover	Recovers an intelligent SSM by loading a recovery image from a TFTP server.
hw-module module reset	Shuts down an SSM and performs a hardware reset.
hw-module module reload	Reloads the intelligent SSM software.

Command	Description
hw-module module shutdown	Shuts down the SSM software in preparation for being powered off without losing configuration data.
show module	Shows SSM information.

debug mrib

To display MRIB debug information, use the **debug mrib** command in privileged EXEC mode. To stop the display of debug information, use the **no** form of this command.

debug mrib { **client** | **io** | **route** [*group*] | **table** }

no debug mrib { **client** | **io** | **route** [*group*] | **table** }

Syntax Description

client	Enables debugging for MRIB client management activity.
io	Enables debugging of MRIB I/O events.
route	Enables debugging of MRIB routing entry activity.
<i>group</i>	Enables debugging of MRIB routing entry activity for the specified group.
table	Enables debugging of MRIB table management activity.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example shows how to enable debugging of MRIB I/O events:

```
hostname# debug mrib io
IPv4 MRIB io debugging is on
```

Related Commands

Command	Description
show mrib client	Displays information about the MRIB client connections.
show mrib route	Displays MRIB table entries.

debug ntdomain

To display NT domain authentication debug information, use the **debug ntdomain** command in privileged EXEC mode. To disable the display of NT domain debug information, use the **no** form of this command.

debug ntdomain [*level*]

no debug ntdomain

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables NT domain debug messages. The **show debug** command reveals that NT domain debug messages are enabled.

```
hostname# debug ntdomain
debug ntdomain  enabled at level 1
hostname# show debug
debug ntdomain  enabled at level 1
hostname#
```

 debug ntdomain**Related Commands**

Command	Description
show debug	Displays current debug configuration.

debug ntp

To show debug messages for NTP, use the **debug ntp** command in privileged EXEC mode. To stop showing debug messages for NTP, use the **no** form of this command.

debug ntp {**adjust** | **authentication** | **events** | **loopfilter** | **packets** | **params** | **select** | **sync** | **validity**}

no debug ntp {**adjust** | **authentication** | **events** | **loopfilter** | **packets** | **params** | **select** | **sync** | **validity**}

Syntax Description

adjust	Shows messages about NTP clock adjustments.
authentication	Shows messages about NTP authentication.
events	Shows messages about NTP events.
loopfilter	Shows messages about NTP loop filter.
packets	Shows messages about NTP packets.
params	Shows messages about NTP clock parameters.
select	Shows messages about NTP clock selection.
sync	Shows messages about NTP clock synchronization.
validity	Shows messages about NTP peer clock validity.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for NTP:

```
hostname# debug ntp events
```

Related Commands	Command	Description
	ntp authenticate	Enables NTP authentication.
	ntp server	Identifies an NTP server.
	show debug	Shows all enabled debuggers.
	show ntp associations	Shows the NTP servers with which the security appliance is associated.
	show ntp status	Shows the status of the NTP association.

debug ospf

To display debug information about the OSPF routing processes, use the **debug ospf** command in privileged EXEC mode.

debug ospf [**adj** | **database-timer** | **events** | **flood** | **lsa-generation** | **packet** | **retransmission** | **spf** | **external** | **inter** | **intra**] | **tree**]

no debug ospf [**adj** | **database-timer** | **events** | **flood** | **lsa-generation** | **packet** | **retransmission** | **spf** | **external** | **inter** | **intra**] | **tree**]

Syntax Description

adj	(Optional) Enables the debugging of OSPF adjacency events.
database-timer	(Optional) Enables the debugging of OSPF timer events.
events	(Optional) Enables the debugging of OSPF events.
external	(Optional) Limits SPF debugging to external events.
flood	(Optional) Enables the debugging of OSPF flooding.
inter	(Optional) Limits SPF debugging to inter-area events.
intra	(Optional) Limits SPF debugging to intra-area events.
lsa-generation	(Optional) Enables the debugging of OSPF summary LSA generation.
packet	(Optional) Enables the debugging of received OSPF packets.
retransmission	(Optional) Enables the debugging of OSPF retransmission events.
spf	(Optional) Enables the debugging of OSPF shortest path first calculations. You can limit the SPF debug information by using the external , inter , and intra keywords.
tree	(Optional) Enables the debugging of OSPF database events.

Defaults

Displays all OSPF debug information if no keyword is provided.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following is sample output from the **debug ospf events** command:

```
hostname# debug ospf events
ospf event debugging is on

OSPF:hello with invalid timers on interface Ethernet0
hello interval received 10 configured 10
net mask received 255.255.255.0 configured 255.255.255.0
dead interval received 40 configured 30
```

Related Commands

Command	Description
show ospf	Displays general information about the OSPF routing process.

debug parser cache

To display CLI parser debug information, use the **debug parser cache** command in privileged EXEC mode. To disable the display of CLI parser debug information, use the **no** form of this command.

debug parser cache [*level*]

no debug parser cache

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables CLI parser debug messages. The **show debug** command reveals the current debug configuration. The CLI parser debug messages appear before and after the output of the **show debug** command.

```
hostname# debug parser cache
debug parser cache enabled at level 1
hostname# show debug
parser cache: try to match 'show debug' in exec mode
debug parser cache enabled at level 1
parser cache: hit at index 8
hostname#
```

 debug parser cache**Related Commands**

Command	Description
show debug	Displays current debug configuration.

debug pim

To display PIM debug information, use the **debug pim** command in privileged EXEC mode. To stop displaying debug information, use the **no** form of this command.

debug pim [**df-election** [**interface** *if_name* | **rp** *rp*] | **group** *group* | **interface** *if_name* | **neighbor**]

no debug pim [**df-election** [**interface** *if_name* | **rp** *rp*] | **group** *group* | **interface** *if_name* | **neighbor**]

Syntax Description

df-election	(Optional) Displays debug messages for PIM bidirectional DF-election message processing.
group <i>group</i>	(Optional) Displays debug information for the specified group. The value for <i>group</i> can be one of the following: - Name of the multicast group, as defined in the DNS hosts table or with the domain ipv4 host command. - IP address of the multicast group. This is a multicast IP address in four-part dotted-decimal notation.
interface <i>if_name</i>	(Optional) When used with the df-election keyword, it limits the DF election debug display to information for the specified interface. When used without the df-election keyword, displays PIM error messages for the specified interface. Note The debug pim interface command does not display PIM protocol activity messages; it only displays error messages. To see debug information for PIM protocol activity, use the debug pim command without the interface keyword. You can use the group keyword to limit the display to the specified multicast group.
neighbor	(Optional) Displays only the sent/received PIM hello messages.
rp <i>rp</i>	(Optional) Can be either one of the following: - Name of the RP, as defined in the Domain Name System (DNS) hosts table or with the domain ipv4 host command. - IP address of the RP. This is a multicast IP address in four-part dotted-decimal notation.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Logs PIM packets received and transmitted and also PIM-related events.

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following is sample output from the **debug pim** command:

```
hostname# debug pim
PIM: Received Join/Prune on Ethernet1 from 172.24.37.33
PIM: Received Join/Prune on Ethernet1 from 172.24.37.33
PIM: Received Join/Prune on Tunnel0 from 10.3.84.1
PIM: Received Join/Prune on Ethernet1 from 172.24.37.33
PIM: Received Join/Prune on Ethernet1 from 172.24.37.33
PIM: Received RP-Reachable on Ethernet1 from 172.16.20.31
PIM: Update RP expiration timer for 224.2.0.1
PIM: Forward RP-reachability packet for 224.2.0.1 on Tunnel0
PIM: Received Join/Prune on Ethernet1 from 172.24.37.33
PIM: Prune-list (10.221.196.51/32, 224.2.0.1)
PIM: Set join delay timer to 2 seconds for (10.221.0.0/16, 224.2.0.1) on Ethernet1
PIM: Received Join/Prune on Ethernet1 from 172.24.37.6
PIM: Received Join/Prune on Ethernet1 from 172.24.37.33
PIM: Received Join/Prune on Tunnel0 from 10.3.84.1
PIM: Join-list: (*, 224.2.0.1) RP 172.16.20.31
PIM: Add Tunnel0 to (*, 224.2.0.1), Forward state
PIM: Join-list: (10.0.0.0/8, 224.2.0.1)
PIM: Add Tunnel0 to (10.0.0.0/8, 224.2.0.1), Forward state
PIM: Join-list: (10.4.0.0/16, 224.2.0.1)
PIM: Prune-list (172.24.84.16/28, 224.2.0.1) RP-bit set RP 172.24.84.16
PIM: Send Prune on Ethernet1 to 172.24.37.6 for (172.24.84.16/28, 224.2.0.1), RP
PIM: For RP, Prune-list: 10.9.0.0/16
PIM: For RP, Prune-list: 10.16.0.0/16
PIM: For RP, Prune-list: 10.49.0.0/16
PIM: For RP, Prune-list: 10.84.0.0/16
PIM: For RP, Prune-list: 10.146.0.0/16
PIM: For 10.3.84.1, Join-list: 172.24.84.16/28
PIM: Send periodic Join/Prune to RP via 172.24.37.6 (Ethernet1)
```

Related Commands

Command	Description
show pim group-map	Displays group-to-protocol mapping table.
show pim interface	Displays interface-specific information for PIM.
show pim neighbor	Displays entries in the PIM neighbor table.

debug pix pkt2pc

To show debug messages that trace packets sent to the uauth code and that trace the event where the uauth proxy session is cut through to the data path, use the **debug pix pkt2pc** command in privileged EXEC mode. To stop showing debug messages, use the **no** form of this command.

debug pix pkt2pc

no debug pix pkt2pc

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages that trace packets sent to the uauth code and that trace the event where the uauth proxy session is cut through to the data path:

```
hostname# debug pix pkt2pc
```

Related Commands

Command	Description
debug pix process	Shows debug messages for xlate and secondary connections processing.
show debug	Shows all enabled debuggers.

debug pix process

To show debug messages for xlate and secondary connections processing, use the **debug pix process** command in privileged EXEC mode. To stop showing debug messages, use the **no** form of this command.

debug pix process

no debug pix process

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for xlate and secondary connections processing:

```
hostname# debug pix process
```

Related Commands

Command	Description
debug pix pkt2pc	Shows debug messages that trace packets sent to the uauth code and that trace the event where the uauth proxy session is cut through to the data path.
show debug	Shows all enabled debuggers.

debug pptp

To show debug messages for PPTP, use the **debug pptp** command in privileged EXEC mode. To stop showing debug messages for PPTP, use the **no** form of this command.

debug pptp [*level*]

no debug pptp [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug pptp** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for PPTP application inspection:

```
hostname# debug pptp
```

Related Commands

Command	Description
class-map	Defines the traffic class to which to apply security actions.
inspect pptp	Enables PPTP application inspection.

Command	Description
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

debug radius

To show debug messages for AAA, use the **debug radius** command in privileged EXEC mode. To stop showing RADIUS messages, use the **no** form of this command.

debug radius [**all** | **decode** | **session** | **user** *username*]]

no debug radius

Syntax Description

all	(Optional) Show RADIUS debugging messages for all users and sessions, including decoded RADIUS messages.
decode	(Optional) Show decoded content of RADIUS messages. Content of all RADIUS packets display, including hexadecimal values and the decoded, eye-readable versions of these values.
session	(Optional) Show session-related RADIUS messages. Packet types for sent and received RADIUS messages display but not the packet content.
user	(Optional) Show RADIUS debugging messages for a specific user.
<i>username</i>	Specifies the user whose messages you want to see. Valid with the user keyword only.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **debug radius** command displays detailed information about RADIUS messaging between the security appliance and a RADIUS AAA server. The **no debug all** or **undebug all** commands turn off all enabled debugs.

Examples

The following example shows decoded RADIUS messages, which happen to be accounting packets:

```
hostname(config)# debug radius decode
hostname(config)# RADIUS packet decode (accounting request)
```

```
-----
```

```

Raw packet data (length = 216).....
i
Parsed packet data.....
Radius: Code = 4 (0x04)
Radius: Identifier = 105 (0x69)
Radius: Length = 216 (0x00D8)
Radius: Vector: 842E0E99F44C00C05A0A19AB88A81312
Radius: Type = 40 (0x28) Acct-Status-Type
Radius: Length = 6 (0x06)
Radius: Value (Hex) = 0x2
Radius: Type = 5 (0x05) NAS-Port
Radius: Length = 6 (0x06)
Radius: Value (Hex) = 0x1
Radius: Type = 4 (0x04) NAS-IP-Address
Radius: Length = 6 (0x06)
Radius: Value (IP Address) = 10.1.1.1 (0x0A010101)
Radius: Type = 14 (0x0E) Login-IP-Host
Radius: Length = 6 (0x06)
Radius: Value (IP Address) = 10.2.0.50 (0xD0FE1291)
Radius: Type = 16 (0x10) Login-TCP-Port
Radius: Length = 6 (0x06)
Radius: Value (Hex) = 0x50
Radius: Type = 44 (0x2C) Acct-Session-Id
Radius: Length = 12 (0x0C)
Radius: Value (String) =
30 78 31 33 30 31 32 39 66 65 | 0x130129fe
Radius: Type = 1 (0x01) User-Name
Radius: Length = 9 (0x09)
Radius: Value (String) =
62 72 6f 77 73 65 72 | browser
Radius: Type = 46 (0x2E) Acct-Session-Time
Radius: Length = 6 (0x06)
Radius: Value (Hex) = 0x0
Radius: Type = 42 (0x2A) Acct-Input-Octets
Radius: Length = 6 (0x06)
Radius: Value (Hex) = 0x256D
Radius: Type = 43 (0x2B) Acct-Output-Octets
Radius: Length = 6 (0x06)
Radius: Value (Hex) = 0x3E1
Radius: Type = 26 (0x1A) Vendor-Specific
Radius: Length = 30 (0x1E)
Radius: Vendor ID = 9 (0x00000009)
Radius: Type = 1 (0x01) Cisco-AV-pair
Radius: Length = 24 (0x18)
Radius: Value (String) =
69 70 3a 73 6f 75 72 63 65 2d 69 70 3d 31 30 2e | ip:source-ip=10.
31 2e 31 2e 31 30 | 1.1.10
Radius: Type = 26 (0x1A) Vendor-Specific
Radius: Length = 27 (0x1B)
Radius: Vendor ID = 9 (0x00000009)
Radius: Type = 1 (0x01) Cisco-AV-pair
Radius: Length = 21 (0x15)
Radius: Value (String) =
69 70 3a 73 6f 75 72 63 65 2d 70 6f 72 74 3d 33 | ip:source-port=3
34 31 33 | 413
Radius: Type = 26 (0x1A) Vendor-Specific
Radius: Length = 40 (0x28)
Radius: Vendor ID = 9 (0x00000009)
Radius: Type = 1 (0x01) Cisco-AV-pair
Radius: Length = 34 (0x22)
Radius: Value (String) =
69 70 3a 64 65 73 74 69 6e 61 74 69 6f 6e 2d 69 | ip:destination-i
70 3d 32 30 38 2e 32 35 34 2e 31 38 2e 31 34 35 | p=10.2.0.50
Radius: Type = 26 (0x1A) Vendor-Specific

```

```
Radius: Length = 30 (0x1E)
Radius: Vendor ID = 9 (0x00000009)
Radius: Type = 1 (0x01) Cisco-AV-pair
Radius: Length = 24 (0x18)
Radius: Value (String) =
69 70 3a 64 65 73 74 69 6e 61 74 69 6f 6e 2d 70 | ip:destination-p
6f 72 74 3d 38 30 | ort=80
```

Related Commands

Command	Description
show running-config	Displays the configuration that is running on the security appliance.

debug rip

To display debug information for RIP, use the **debug rip** command in privileged EXEC mode. To disable the debug information display, use the **no** form of this command.

debug rip

no debug rip

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables level 1 debugging of RIP:

```
hostname# debug rip
debug rip enabled at level 1

hostname#
```

Related Commands

Command	Description
clear configure rip	Clears all RIP commands from the running configuration.

Command	Description
rip	Configures RIP on the specified interface.
show running-config rip	Displays the RIP commands in the running configuration.

debug rtsp

To show debug messages for RTSP application inspection, use the **debug rtsp** command in privileged EXEC mode. To stop showing debug messages for RTSP application inspection, use the **no** form of this command.

debug rtsp [*level*]

no debug rtsp [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug rtsp** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for RTSP application inspection:

```
hostname# debug rtsp
```

Related Commands

Command	Description
class-map	Defines the traffic class to which to apply security actions.
inspect rtsp	Enables RTSP application inspection.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

debug sdi

To display SDI authentication debug information, use the **debug sdi** command in privileged EXEC mode. To disable the display of SDI debug information, use the **no** form of this command.

debug sdi [*level*]

no debug sdi

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables SDI debug messages. The **show debug** command reveals that SDI debug messages are enabled.

```
hostname# debug sdi
debug sdi  enabled at level 1
hostname# show debug
debug sdi  enabled at level 1
hostname#
```

Related Commands

Command	Description
show debug	Displays current debug configuration.

debug sequence

To add a sequence number to the beginning of all debug messages, use the **debug sequence** command in privileged EXEC mode. To disable the use of debug sequence numbers, use the **no** form of this command.

debug sequence [*level*]

no debug sequence

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The defaults are as follows:

- Debug message sequence numbers are disabled.
- The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables sequence numbers in debug messages. The **debug parser cache** command enables CLI parser debug messages. The **show debug** command reveals the current debug configuration. The CLI parser debug messages shown include sequence numbers before each message.

```
hostname# debug sequence
debug sequence enabled at level 1
hostname# debug parser cache
debug parser cache enabled at level 1
```

```
hostname# show debug
0: parser cache: try to match 'show debug' in exec mode
debug parser cache enabled at level 1
debug sequence enabled at level 1
1: parser cache: hit at index 8
hostname#
```

Related Commands

Command	Description
show debug	Displays current debug configuration.

debug session-command

To show debug messages for a session to an SSM, use the **debug session-command** command in privileged EXEC mode. To stop showing debug messages for sessions, use the **no** form of this command.

debug session-command [*level*]

no debug session-command [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default level is 1.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Using **debug** commands might slow down traffic on busy networks.

Examples

The following example enables debug messages for sessions:

```
hostname# debug session-command
```

Related Commands

Command	Description
session	Sessions to an SSM.

debug sip

To show debug messages for SIP application inspection, use the **debug sip** command in privileged EXEC mode. To stop showing debug messages for SIP application inspection, use the **no** form of this command.

debug sip [*level*]

no debug sip [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug sip** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for SIP application inspection:

```
hostname# debug sip
```

Related Commands

Command	Description
class-map	Defines the traffic class to which to apply security actions.
inspect sip	Enables SIP application inspection.

Command	Description
show conn	Displays the connection state for different connection types.
show sip	Displays information about SIP sessions established through the security appliance.
timeout	Sets the maximum idle time duration for different protocols and session types.

debug skinny

To show debug messages for SCCP (Skinny) application inspection, use the **debug skinny** command in privileged EXEC mode. To stop showing debug messages for SCCP application inspection, use the **no** form of this command.

debug skinny [*level*]

no debug skinny [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug skinny** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for SCCP application inspection:

```
hostname# debug skinny
```

Related Commands	Command	Description
	class-map	Defines the traffic class to which to apply security actions.
	inspect skinny	Enables SCCP application inspection.
	show skinny	Displays information about SCCP sessions established through the security appliance.
	show conn	Displays the connection state for different connection types.
	timeout	Sets the maximum idle time duration for different protocols and session types.

debug smtp

To show debug messages for SMTP/ESMTP application inspection, use the **debug smtp** command in privileged EXEC mode. To stop showing debug messages for SMTP/ESMTP application inspection, use the **no** form of this command.

debug smtp [*level*]

no debug smtp [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug smtp** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for SMTP/ESMTP application inspection:

```
hostname# debug smtp
```

Related Commands	Command	Description
	class-map	Defines the traffic class to which to apply security actions.
	inspect esmtp	Enables ESMTP application inspection.
	policy-map	Associates a class map with specific security actions.
	service-policy	Applies a policy map to one or more interfaces.
	show conn	Displays the connection state for different connection types, including SMTP.

debug sqlnet

To show debug messages for SQL*Net application inspection, use the **debug sqlnet** command in privileged EXEC mode. To stop showing debug messages for SQL*Net application inspection, use the **no** form of this command.

debug sqlnet [*level*]

no debug sqlnet [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug sqlnet** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for SQL*Net application inspection:

```
hostname# debug sqlnet
```

Related Commands

Command	Description
class-map	Defines the traffic class to which to apply security actions.
inspect sqlnet	Enables SQL*Net application inspection.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.
show conn	Displays the connection state for different connection types, including SQL*Net.

debug ssh

To display debug information and error messages associated with SSH, use the **debug ssh** command in privileged EXEC mode. To disable the display of debug information, use the **no** form of this command.

debug ssh [*level*]

no debug ssh [*level*]

Syntax Description	<i>level</i> (Optional) Specifies an optional level of debug.

Defaults	The default <i>level</i> is 1.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines	Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use debug commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use debug commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased debug command processing overhead will affect system use.

Examples	The following is sample output from the debug ssh 255 command:

```
hostname# debug ssh 255
debug ssh enabled at level 255
SSH2 0: send: len 64 (includes padlen 17)
SSH2 0: done calc MAC out #239
SSH2 0: send: len 32 (includes padlen 7)
SSH2 0: done calc MAC out #240
SSH2 0: send: len 64 (includes padlen 15)
SSH2 0: done calc MAC out #241
SSH2 0: send: len 32 (includes padlen 16)
SSH2 0: done calc MAC out #242
SSH2 0: send: len 64 (includes padlen 7)
SSH2 0: done calc MAC out #243
SSH2 0: send: len 64 (includes padlen 18)
SSH2 0: done calc MAC out #244
```

```

SSH2 0: send: len 64 (includes padlen 8)
SSH2 0: done calc MAC out #245
SSH2 0: send: len 64 (includes padlen 18)
SSH2 0: done calc MAC out #246
SSH2 0: send: len 64 (includes padlen 7)
SSH2 0: done calc MAC out #247
SSH2 0: send: len 64 (includes padlen 18)
SSH2 0: done calc MAC out #248
SSH2 0: send: len 64 (includes padlen 7)
SSH2 0: done calc MAC out #249
SSH2 0: send: len 64 (includes padlen 18)
SSH2 0: done calc MAC out #250
SSH2 0: send: len 64 (includes padlen 8)
SSH2 0: done calc MAC out #251
SSH2 0: send: len 64 (includes padlen 18)
SSH2 0: done calc MAC out #252
SSH2 0: send: len 64 (includes padlen 7)
SSH2 0: done calc MAC out #253
SSH2 0: send: len 64 (includes padlen 18)
SSH2 0: done calc MAC out #254
SSH2 0: send: len 64 (includes padlen 8)
SSH2 0: done calc MAC out #255
SSH2 0: send: len 64 (includes padlen 18)
SSH2 0: done calc MAC out #256
SSH2 0: send: len 64 (includes padlen 7)
SSH2 0: done calc MAC out #257
SSH2 0: send: len 64 (includes padlen 18)
SSH2 0: done calc MAC out #258

```

Related Commands

Command	Description
clear configure ssh	Clears all SSH commands from the running configuration.
show running-config ssh	Displays the current SSH commands in the running configuration.
show ssh sessions	Displays information about active SSH sessions to the security appliance.
ssh	Allows SSH connectivity to the security appliance from the specified client or network.

debug ssl

To display SSL debug information, use the **debug ssl** command in privileged EXEC mode. To disable the display of SSL debug information, use the **no** form of this command.

debug ssl {cipher | device} [level]

no debug ssl {cipher | device}

Syntax Description

cipher	Display information about the cipher negotiation between the HTTP server and the client.
device	Displays information about the SSL device including session initiation and ongoing status.
<i>level</i>	(Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables SSL debug messages, specifically for cipher negotiation. The **show debug** command reveals that SSL debug messages are enabled.

```
hostname# debug ssl cipher
debug ssl cipher enabled at level 1
hostname# show debug
debug ssl cipher enabled at level 1
hostname#
```

Related Commands	Command	Description
	show debug	Displays current debug configuration.

debug sunrpc

To show debug messages for RPC application inspection, use the **debug sunrpc** command in privileged EXEC mode. To stop showing debug messages for RPC application inspection, use the **no** form of this command.

debug sunrpc [*level*]

no debug sunrpc [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug sunrpc** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for RPC application inspection:

```
hostname# debug sunrpc
```

Related Commands	Command	Description
	class-map	Defines the traffic class to which to apply security actions.
	inspect sunrpc	Enables Sun RPC application inspection.
	policy-map	Associates a class map with specific security actions.
	show conn	Displays the connection state for different connection types, including RPC.
	timeout	Sets the maximum idle time duration for different protocols and session types.

debug tacacs

To display TACACS+ debug information, use the **debug tacacs** command in privileged EXEC mode. To disable the display of TACACS+ debug information, use the **no** form of this command.

debug tacacs [**session** | **user** *username*]

no debug tacacs [**session** | **user** *username*]

Syntax Description

session	Displays session-related TACACS+ debug messages.
user	Displays user-specific TACACS+ debug messages. You can display TACACS+ debug messages for only one user at a time.
<i>username</i>	Specifies the user whose TACACS+ debug messages you want to view.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables TACACS+ debug messages. The **show debug** command reveals that TACACS+ debug messages are enabled.

```
hostname# debug tacacs user admin342
hostname# show debug
debug tacacs user admin342
hostname#
```

Related Commands

Command	Description
show debug	Displays current debug configuration.

debug tcp-map

To show debug messages for TCP application inspection maps, use the **debug tcp-map** command in privileged EXEC mode. To stop showing debug messages for TCP application inspection, use the **no** form of this command.

debug tcp-map

no debug tcp-map

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables debug messages for TCP application inspection maps. The **show debug** command reveals that debug messages for TCP application inspection maps are enabled.

```
hostname# debug tcp-map
debug tcp-map enabled at level 1.
hostname# show debug
debug tcp-map enabled at level 1.
hostname#
```

Related Commands

Command	Description
show debug	Displays current debug configuration.

debug timestamps

To add timestamp information to the beginning of all debug messages, use the **debug timestamps** command in privileged EXEC mode. To disable the use of debug timestamps, use the **no** form of this command.

debug timestamps [*level*]

no debug timestamps

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The defaults are as follows:

- Debug timestamp information is disabled.
- The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables timestamps in debug messages. The **debug parser cache** command enables CLI parser debug messages. The **show debug** command reveals the current debug configuration. The CLI parser debug messages shown include timestamps before each message.

```
hostname# debug timestamps
debug timestamps enabled at level 1
hostname# debug parser cache
debug parser cache enabled at level 1
```

 debug timestamps

```
hostname# show debug
1982769.770000000: parser cache: try to match 'show debug' in exec mode
1982769.770000000: parser cache: hit at index 8
hostname#
```

Related Commands

Command	Description
show debug	Displays current debug configuration.

debug vpn-sessiondb

To display VPN-session database debug information, use the **debug vpn-sessiondb** command in privileged EXEC mode. To disable the display of VPN-session database debug information, use the **no** form of this command.

debug vpn-sessiondb [*level*]

no debug vpn-sessiondb

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Because debugging output is assigned high priority in the CPU process, it can render the system unusable. For this reason, use **debug** commands only to troubleshoot specific problems or during troubleshooting sessions with Cisco technical support staff. Moreover, it is best to use **debug** commands during periods of lower network traffic and fewer users. Debugging during these periods decreases the likelihood that increased **debug** command processing overhead will affect system use.

Examples

The following example enables VPN-session database debug messages. The **show debug** command reveals that VPN-session database debug messages are enabled.

```
hostname# debug vpn-sessiondb
debug vpn-sessiondb enabled at level 1
hostname# show debug
debug vpn-sessiondb enabled at level 1
hostname#
```

 debug vpn-sessiondb**Related Commands**

Command	Description
show debug	Displays current debug configuration.

debug xdmcp

To show debug messages for XDMCP application inspection, use the **debug xdmcp** command in privileged EXEC mode. To stop showing debug messages for XDMCP application inspection, use the **no** form of this command.

debug xdmcp [*level*]

no debug xdmcp [*level*]

Syntax Description

level (Optional) Sets the debug message level to display, between 1 and 255. The default is 1. To display additional messages at higher levels, set the level to a higher number.

Defaults

The default value for *level* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To see the current debug command settings, enter the **show debug** command. To stop the debug output, enter the **no debug** command. To stop all debug messages from being displayed, enter the **no debug all** command.



Note

Enabling the **debug xdmcp** command may slow down traffic on busy networks.

Examples

The following example enables debug messages at the default level (1) for XDMCP application inspection:

```
hostname# debug xdmcp
```

Related Commands	Command	Description
	class-map	Defines the traffic class to which to apply security actions.
	inspect xdmcp	Enables XDMCP application inspection.
	policy-map	Associates a class map with specific security actions.
	service-policy	Applies a policy map to one or more interfaces.

default

To restore default settings for the **time-range** command **absolute** and **periodic** keywords, use the **default** command in time-range configuration mode.

default { **absolute** | **periodic** *days-of-the-week time to* [*days-of-the-week*] *time* }

Syntax Description

absolute	Defines an absolute time when a time range is in effect.
days-of-the-week	(Optional) The first occurrence of this argument is the starting day or day of the week that the associated time range is in effect. The second occurrence is the ending day or day of the week the associated statement is in effect. This argument is any single day or combinations of days: Monday, Tuesday, Wednesday, Thursday, Friday, Saturday, and Sunday. Other possible values are: - daily—Monday through Sunday - weekdays—Monday through Friday - weekend—Saturday and Sunday If the ending days of the week are the same as the starting days of the week, you can omit them.
periodic	Specifies a recurring (weekly) time range for functions that support the time-range feature.
time	Specifies the time in the format HH:MM. For example, 8:00 is 8:00 a.m. and 20:00 is 8:00 p.m.
to	Entry of the to keyword is required to complete the range “from start-time to end-time.”

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Time-range configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If the end days-of-the-week value is the same as the start value, you can omit them.

If a **time-range** command has both **absolute** and **periodic** values specified, then the **periodic** commands are evaluated only after the **absolute start** time is reached, and are not further evaluated after the **absolute end** time is reached.

The time-range feature relies on the system clock of the security appliance; however, the feature works best with NTP synchronization.

Examples

The following example shows how to restore the default behavior of the **absolute** keyword:

```
hostname(config-time-range)# default absolute
```

Related Commands

Command	Description
absolute	Defines an absolute time when a time range is in effect.
periodic	Specifies a recurring (weekly) time range for functions that support the time-range feature.
time-range	Defines access control to the security appliance based on time.

default (crl configure)

To return all CRL parameters to their system default values, use the **default** command in crl configure configuration mode. The crl configure configuration mode is accessible from the crypto ca trustpoint configuration mode. These parameters are used only when the LDAP server requires them.

default

Syntax Description This command has no arguments or keywords.

Defaults No default behaviors or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Crl configure configuration	•		•		

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines Invocations of this command do not become part of the active configuration.

Examples The following example enters ca-crl configuration mode, and returns CRL command values to their defaults:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# crl configure
hostname(ca-crl)# default
hostname(ca-crl)#
```

Related Commands	Command	Description
	crl configure	Enters crl configure configuration mode.
	crypto ca trustpoint	Enters trustpoint configuration mode.
	protocol ldap	Specifies LDAP as a retrieval method for CRLs.

default (time-range)

To restore default settings for the **absolute** and **periodic** commands, use the **default** command in time-range configuration mode.

default { **absolute** | **periodic** *days-of-the-week time to [days-of-the-week] time* }

Syntax Description

absolute	Defines an absolute time when a time range is in effect.
days-of-the-week	The first occurrence of this argument is the starting day or day of the week that the associated time range is in effect. The second occurrence is the ending day or day of the week the associated statement is in effect. This argument is any single day or combinations of days: Monday, Tuesday, Wednesday, Thursday, Friday, Saturday, and Sunday. Other possible values are: • daily—Monday through Sunday • weekdays—Monday through Friday • weekend—Saturday and Sunday If the ending days of the week are the same as the starting days of the week, you can omit them.
periodic	Specifies a recurring (weekly) time range for functions that support the time-range feature.
time	Specifies the time in the format HH:MM. For example, 8:00 is 8:00 a.m. and 20:00 is 8:00 p.m.
to	Entry of the to keyword is required to complete the range “from start-time to end-time.”

Defaults

There are no default settings for this command.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Time-range configuration	•	•	•	•	

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If the end days-of-the-week value is the same as the start value, you can omit them.

If a **time-range** command has both **absolute** and **periodic** values specified, then the **periodic** commands are evaluated only after the **absolute start** time is reached, and are not further evaluated after the **absolute end** time is reached.

The time-range feature relies on the system clock of the security appliance; however, the feature works best with NTP synchronization.

Examples

The following example shows how to restore the default behavior of the **absolute** keyword:

```
hostname(config-time-range)# default absolute
```

Related Commands

Command	Description
absolute	Defines an absolute time when a time range is in effect.
periodic	Specifies a recurring (weekly) time range for functions that support the time-range feature.
time-range	Defines access control to the security appliance based on time.

default enrollment

To return all enrollment parameters to their system default values, use the **default enrollment** command in crypto ca trustpoint configuration mode.

default enrollment

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Invocations of this command do not become part of the active configuration.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and returns all enrollment parameters to their default values within trustpoint central:

```
hostname<config># crypto ca trustpoint central
hostname<ca-trustpoint># default enrollment
hostname<ca-trustpoint>#
```

Related Commands

Command	Description
clear configure crypto ca trustpoint	Removes all trustpoints.
crl configure	Enters crl configuration mode.
crypto ca trustpoint	Enters trustpoint configuration mode.

default-domain

To set a default domain name for users of the group policy, use the **default-domain** command in group-policy configuration mode. To delete a domain name, use the **no** form of this command.

To prevent users from inheriting a domain name, use the **default-domain none** command.

The security appliance passes the default domain name to the IPSec client to append to DNS queries that omit the domain field. This domain name applies only to tunneled packets. When there are no default domain names, users inherit the default domain name in the default group policy.

default-domain {**value** *domain-name* | **none**}

no default-domain [*domain-name*]

Syntax Description

none	Indicates that there is no default domain name. Sets a default domain name with a null value, thereby disallowing a default domain name. Prevents inheriting a default domain name from a default or specified group policy.
value <i>domain-name</i>	Identifies the default domain name for the group.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can use only alphanumeric characters, hyphens (-), and periods (.) in default domain names.

Examples

The following example shows how to set a default domain name of FirstDomain for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# default-domain value FirstDomain
```

Related Commands

Command	Description
split-dns	Provides a list of domains to be resolved through the split tunnel.
split-tunnel-network-list	Identifies the access list the security appliance uses to distinguish networks that require tunneling and those that do not.
split-tunnel-policy	Lets an IPSec client conditionally direct packets over an IPSec tunnel in encrypted form, or to a network interface in cleartext form

default-group-policy

To specify the set of attributes that the user inherits by default, use the **default-group-policy** command in tunnel-group general-attributes configuration mode. To eliminate a default group policy name, use the **no** form of this command.

default-group-policy *group-name*

no default-group-policy *group-name*

Syntax Description

group-name Specifies the name of the default group.

Defaults

The default group name is DfltGrpPolicy.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group general attributes configuration	•		•		

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The default group policy DfltGrpPolicy comes with the initial configuration of the security appliance. You can apply this attribute to all tunnel-group types.

Examples

The following example entered in config-general configuration mode, specifies a set of attributes for users to inherit by default for an IPSec LAN-to-LAN tunnel group named standard-policy. This set of commands defines the accounting server, the authentication server, the authorization server and the address pools.

```
hostname(config)# tunnel-group standard-policy type ipsec-ra
hostname(config)# tunnel-group standard-policy general-attributes
hostname(config-general)# default-group-policy first-policy
hostname(config-general)# accounting-server-group aaa-server123
hostname(config-general)# address-pool (inside) addrpool11 addrpool12 addrpool13
hostname(config-general)# authentication-server-group aaa-server456
hostname(config-general)# authorization-server-group aaa-server78
hostname(config-general)#
```

Related Commands	Command	Description
	clear-configure tunnel-group	Clears all configured tunnel groups.
	group-policy	Creates or edits a group policy
	show running-config tunnel group	Shows the tunnel group configuration for all tunnel groups or for a particular tunnel group.
	tunnel-group-map default group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

default-group-policy (webvpn)

To specify the name of the group policy to use when the WebVPN or e-mail proxy configuration does not specify a group policy, use the **default-group-policy** command. WebVPN, IMAP4S, POP3S, and SMTPS sessions require either a specified or a default group policy. For WebVPN, use this command in webvpn mode. For e-mail proxy, use this command in the applicable e-mail proxy mode. To remove the attribute from the configuration, use the **no** version of this command.

default-group-policy *groupname*

no default-group-policy

Syntax Description

groupname	Identifies the previously configured group policy to use as the default group policy. Use the group-policy command in configuration mode to configure a group policy.

Defaults

A default group policy, named *DfltGrpPolicy*, always exists on the security appliance. This **default-group-policy** command lets you substitute a group policy that you create as the default group policy for WebVPN and e-mail proxy sessions. An alternative is to edit the *DfltGrpPolicy*.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	—	•	—	—
Imap4s	•	—	•	—	—
Pop3s	•	—	•	—	—
Smtps	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can edit, but not delete the system DefaultGroupPolicy. It has the following AVPs:

Attribute	Default Value
wins-server	none
dns-server	none
dhcp-network-scope	none
vpn-access-hours	unrestricted
vpn-simultaneous-logins	3

Attribute	Default Value
vpn-idle-timeout	30 minutes
vpn-session-timeout	none
vpn-filter	none
vpn-tunnel-protocol	WebVPN
ip-comp	disable
re-xauth	disable
group-lock	none
pfs	disable
client-access-rules	none
banner	none
password-storage	disabled
ipsec-udp	disabled
ipsec-udp-port	0
backup-servers	keep-client-config
split-tunnel-policy	tunnelall
split-tunnel-network-list	none
default-domain	none
split-dns	none
intercept-dhcp	disable
client-firewall	none
secure-unit-authentication	disabled
user-authentication	disabled
user-authentication-idle-timeout	none
ip-phone-bypass	disabled
leap-bypass	disabled
nem	disabled
webvpn attributes:	
filter	none
functions	disabled
homepage	none
html-content-filter	none
port-forward	disabled
port-forward-name	none
url-list	mpme

Examples

The following example shows how to specify a default group policy called WebVPN7 for WebVPN:

```
hostname(config)# webvpn
hostname(config-webvpn)# default-group-policy WebVPN7
```

default-idle-timeout

To set a default idle timeout value for WebVPN users, use the **default-idle-timeout** command in webvpn mode. To remove the default idle timeout value from the configuration and reset the default, use the **no** form of this command.

The default idle timeout prevents stale sessions.

default-idle-timeout *seconds*

no default-idle-timeout

Syntax Description

seconds	Specifies the number of seconds for the idle time out. The minimum is 60 seconds, maximum is 1 day (86400 seconds).

Defaults

1800 seconds (30 minutes).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The security appliance uses the value you set here if there is no idle timeout defined for a user, if the value is 0, or if the value does not fall into the valid range.

We recommend that you set this command to a short time period. This is because a browser set to disable cookies (or one that prompts for cookies and then denies them) can result in a user not connecting but nevertheless appearing in the sessions database. If the maximum number of connections permitted is set to one (**vpn-simultaneous-logins** command), the user cannot log back in because the database indicates that the maximum number of connections already exists. Setting a low idle timeout removes such phantom sessions quickly, and lets a user log in again.

Examples

The following example shows how to set the default idle timeout to 1200 seconds (20 minutes):

```
hostname(config)# webvpn
hostname(config-webvpn)# default-idle-timeout 1200
```

Related Commands

Command	Description
vpn-simultaneous-logins	Sets the maximum number of simultaneous VPN sessions permitted. Use in group-policy or username mode.

default-information originate

To generate a default external route into an OSPF routing domain, use the **default-information originate** command in router configuration mode. To disable this feature, use the **no** form of this command.

default-information originate [**always**] [**metric** *value*] [**metric-type** {**1** | **2**}] [**route-map** *name*]

no default-information originate [[**always**] [**metric** *value*] [**metric-type** {**1** | **2**}] [**route-map** *name*]]

Syntax Description

always	(Optional) Always advertises the default route regardless of whether the software has a default route.
metric <i>value</i>	(Optional) Specifies the OSPF default metric value from 0 to 16777214.
metric-type { 1 2 }	(Optional) External link type associated with the default route advertised into the OSPF routing domain. Valid values are as follows: 1—Type 1 external route. 2—Type 2 external route.
route-map <i>name</i>	(Optional) Name of the route map to apply.

Defaults

The default values are as follows:

- metric** *value* is 1.
- metric-type** is 2.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Using the **no** form of this command with optional keywords and arguments only removes the optional information from the command. For example, entering **no default-information originate metric 3** removes the **metric 3** option from the command in the running configuration. To remove the complete command from the running configuration, use the **no** form of the command without any options: **no default-information originate**.

Examples

The following example shows how to use the **default-information originate** command with an optional metric and metric type:

```
hostname(config-router)# default-information originate always metric 3 metric-type 2  
hostname(config-router)#
```

Related Commands

Command	Description
router ospf	Enters router configuration mode.
show running-config router	Displays the commands in the global router configuration.

delete

To delete a file in the disk partition, use the **delete** command in privileged EXEC mode.

delete [/noconfirm] [/recursive] [disk0: | disk1: | flash:]*filename*

Syntax Description

/noconfirm	(Optional) Specifies not to prompt for confirmation.
/recursive	(Optional) Deletes the specified file recursively in all subdirectories.
disk0:	(Optional) Specifies the internal Flash memory, followed by a colon.
disk1:	(Optional) Specifies the external Flash memory card, followed by a colon.
<i>filename</i>	Specifies the name of the file to delete.
flash:	Specifies the nonremovable internal Flash, followed by a colon. In the ASA 5500 series, the flash keyword is aliased to disk0 .

Defaults

If you do not specify a directory, the directory is the current working directory by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The file is deleted from the current working directory if a path is not specified. Wildcards are supported when deleting files. When deleting files, you are prompted with the filename and you must confirm the deletion.

The following example shows how to delete a file named *test.cfg* in the current working directory:

```
hostname# delete test.cfg
```

Related Commands

Command	Description
cd	Changes the current working directory to the one specified.
rmdir	Removes a file or directory.
show file	Displays the specified file.

deny version

To deny a specific version of SNMP traffic, use the **deny version** command in SNMP map configuration mode, which is accessible by entering the **snmp-map** command from global configuration mode. To disable this command, use the **no** version of the command.

deny version *version*

deny version *version*

Syntax Description

<i>version</i>	Specifies the version of SNMP traffic that the security appliance drops. The permitted values are 1 , 2 , 2c , and 3 .

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
SNMP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **deny version** command to restrict SNMP traffic to specific versions of SNMP. Earlier versions of SNMP were less secure so restricting SNMP traffic to Version 2 may be specified by your security policy. You use the **deny version** command within an SNMP map, which you configure using the **snmp-map** command. After creating the SNMP map, you enable the map using the **inspect snmp** command and then apply it to one or more interfaces using the **service-policy** command.

Examples

The following example shows how to identify SNMP traffic, define a SNMP map, define a policy, and apply the policy to the outside interface:

```
hostname(config)# access-list snmp-acl permit tcp any any eq 161
hostname(config)# access-list snmp-acl permit tcp any any eq 162
hostname(config)# class-map snmp-port
hostname(config-cmap)# match access-list snmp-acl
hostname(config-cmap)# exit
hostname(config)# snmp-map inbound_snmp
hostname(config-snmp-map)# deny version 1
hostname(config-snmp-map)# exit
hostname(config)# policy-map inbound_policy
hostname(config-pmap)# class snmp-port
```

```
hostname(config-pmap-c)# inspect snmp inbound_snmp
hostname(config-pmap-c)# exit
hostname(config-pmap)# exit
hostname(config)# service-policy inbound_policy interface outside
```

Related Commands	Commands	Description
	class-map	Defines the traffic class to which to apply security actions.
	inspect snmp	Enable SNMP application inspection.
	policy-map	Associates a class map with specific security actions.
	snmp-map	Defines an SNMP map and enables SNMP map configuration mode.
	service-policy	Applies a policy map to one or more interfaces.

description

To add a description for a named configuration unit (for example, for a context or for an object group), use the **description** command in various configuration modes. To remove the description, use the **no** form of this command. The description adds helpful notes in your configuration.

description *text*

no description

Syntax Description

<i>text</i>	Sets the description as a text string up to 200 characters in length. If you want to include a question mark (?) in the string, you must type Ctrl-V before typing the question mark so you do not inadvertently invoke CLI help.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Class-map configuration	•	•	•	•	—
Context configuration	•	•	—	—	•
Gtp-map configuration	•	•	•	•	—
Interface configuration	•	•	•	•	•
Object-group configuration	•	•	•	•	—
Policy-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was added to several new configuration modes.

Examples

The following example adds a description to the “Administration” context configuration:

```
hostname(config)# context administrator
hostname(config-context)# description This is the admin context.
hostname(config-context)# allocate-interface gigabitethernet0/0.1
hostname(config-context)# allocate-interface gigabitethernet0/1.1
hostname(config-context)# config-url flash://admin.cfg
```

Related Commands	Command	Description
	class-map	Identifies traffic to which you apply actions in the policy-map command.
	context	Creates a security context in the system configuration and enters context configuration mode.
	gtp-map	Controls parameters for the GTP inspection engine.
	interface	Configures an interface and enters interface configuration mode.
	object-group	Identifies traffic to include in the access-list command.
	policy-map	Identifies actions to apply to traffic identified by the class-map command.

dhcp-network-scope

To specify the range of IP addresses the security appliance DHCP server should use to assign addresses to users of this group policy, use the **dhcp-network-scope** command in group-policy configuration mode. To remove the attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a value from another group policy. To prevent inheriting a value, use the **dhcp-network-scope none** command.

dhcp-network-scope {*ip_address*} | none

no dhcp-network-scope

Syntax Description

<i>ip_address</i>	Specifies the IP subnetwork the DHCP server should use to assign IP addresses to users of this group policy.
none	Sets the DHCP subnetwork to a null value, thereby allowing no IP addresses. Prevents inheriting a value from a default or specified group policy.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to set an IP subnetwork of 10.10.85.0 for the group policy named First Group:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# dhcp-network-scope 10.10.85.0
```

dhcp-server

To configure support for DHCP servers that assign IP addresses to clients as a VPN tunnel is established, use the **dhcp-server** command in tunnel-group general-attributes configuration mode. To return this command to the default, use the **no** form of this command.

dhcp-server *hostname1* [...*hostname10*]

no dhcp-server *hostname*

Syntax Description

<i>hostname1</i>	Specifies the IP address of the DHCP server. You can specify up to 10
<i>...hostname10</i>	DHCP servers.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group general attributes configuration	•		•		

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute to IPSec remote access tunnel-group types only.

Examples

The following command entered in config-general configuration mode, adds three DHCP servers (dhcp1, dhcp2, and dhcp3) to the IPSec remote-access tunnel group remotegrp:

```
hostname(config)# tunnel-group remotegrp type ipsec_ra
hostname(config)# tunnel-group remotegrp general
hostname(config-general)# default-group-policy remotegrp
hostname(config-general)# dhcp-server dhcp1 dhcp2 dhcp3
hostname(config-general)
```

Related Commands

Command	Description
clear-configure	Clears all configured tunnel groups.
tunnel-group	

Command	Description
show running-config tunnel group	Shows the tunnel group configuration for all tunnel groups or for a particular tunnel group.
tunnel-group-map default group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

dhcpd address

To define the IP address pool used by the DHCP server, use the **dhcpd address** command in global configuration mode. To remove an existing DHCP address pool, use the **no** form of this command.

dhcpd address *IP_address1*[-*IP_address2*] *interface_name*

no dhcpd address *interface_name*

Syntax Description

<i>interface_name</i>	Interface the address pool is assigned to.
<i>IP_address1</i>	Start address of the DHCP address pool.
<i>IP_address2</i>	End address of the DHCP address pool.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **dhcpd address** *ip1*[-*ip2*] *interface_name* command specifies the DHCP server address pool. The address pool of a security appliance DHCP server must be within the same subnet of the security appliance interface on which it is enabled, and you must specify the associated security appliance interface using *interface_name*.

The size of the address pool is limited to 256 addresses per pool on the security appliance. If the address pool range is larger than 253 addresses, the netmask of the security appliance interface cannot be a Class C address (for example, 255.255.255.0) and needs to be something larger, for example, 255.255.254.0.

DHCP clients must be physically connected to the subnet of the security appliance DHCP server interface.

The **dhcpd address** command cannot use interface names with a “-” (dash) character because the “-” character is interpreted as a range specifier instead of as part of the object name.

The **no dhcpd address** *interface_name* command removes the DHCP server address pool that you configured for the specified interface.

Refer to the *Cisco Security Appliance Command Line Configuration Guide* for information on how to implement the DHCP server feature into the security appliance.

Examples

The following example shows how to use the **dhcpd address**, **dhcpd dns**, and **dhcpd enable interface_name** commands to configure an address pool and DNS server for the DHCP clients on the **dmz** interface of the security appliance:

```
hostname(config)# dhcpd address 10.0.1.100-10.0.1.108 dmz
hostname(config)# dhcpd dns 209.165.200.226
hostname(config)# dhcpd enable dmz
```

The following example shows how to configure a DHCP server on the inside interface. It uses the **dhcpd address** command to assign a pool of 10 IP addresses to the DHCP server on that interface.

```
hostname(config)# dhcpd address 10.0.1.101-10.0.1.110 inside
hostname(config)# dhcpd dns 198.162.1.2 198.162.1.3
hostname(config)# dhcpd wins 198.162.1.4
hostname(config)# dhcpd lease 3000
hostname(config)# dhcpd ping_timeout 1000
hostname(config)# dhcpd domain example.com
hostname(config)# dhcpd enable inside
```

Related Commands

Command	Description
clear configure dhcpd	Removes all DHCP server settings.
dhcpd enable	Enables the DHCP server on the specified interface.
show dhcpd	Displays DHCP binding, statistic, or state information.
show running-config dhcpd	Displays the current DHCP server configuration.

dhcpd auto_config

To enable the security appliance to automatically configure DNS, WINS and domain name values for the DHCP server based on the values obtained from an interface running a DHCP client, use the **dhcpd auto_config** command in global configuration mode. To discontinue the automatic configuration of DHCP parameters, use the **no** form of this command.

dhcpd auto_config *client_if_name*

no dhcpd auto_config *client_if_name*

Syntax Description

<i>client_if_name</i>	Specifies the interface running the DHCP client that supplies the DNS, WINS, and domain name parameters.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If you specify DNS, WINS, or domain name parameters using the CLI commands, then the CLI-configured parameters overwrite the parameters obtained by automatic configuration.

Examples

The following example shows how to configure DHCP on the inside interface. The **dhcpd auto_config** command is used to pass DNS, WINS, and domain information obtained from the DHCP client on the outside interface to the DHCP clients on the inside interface.

```
hostname(config)# dhcpd address 10.0.1.101-10.0.1.110 inside
hostname(config)# dhcpd autoconfig outside
hostname(config)# dhcpd enable inside
```

Related Commands

Command	Description
clear configure dhcpd	Removes all DHCP server settings.
dhcpd enable	Enables the DHCP server on the specified interface.

Command	Description
show ip address dhcp server	Displays detailed information about the DHCP options provided by a DHCP server to an interface acting as a DHCP client.
show running-config dhcpd	Displays the current DHCP server configuration.

dhcpd dns

To define the DNS servers for DHCP clients, use the **dhcpd dns** command in global configuration mode. To clear defined servers, use the **no** form of this command.

dhcpd dns *dnsip1* [*dnsip2*]

no dhcpd dns [*dnsip1* [*dnsip2*]]

Syntax Description

<i>dnsip1</i>	IP address of the primary DNS server for the DHCP client.
<i>dnsip2</i>	(Optional) IP address of the alternate DNS server for the DHCP client.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **dhcpd dns** command lets you specify the IP address or addresses of the DNS server(s) for the DHCP client. You can specify two DNS servers. The **no dhcpd dns** command lets you remove the DNS IP address(es) from the configuration.

Examples

The following example shows how to use the **dhcpd address**, **dhcpd dns**, and **dhcpd enable** *interface_name* commands to configure an address pool and DNS server for the DHCP clients on the **dmz** interface of the security appliance.

```
hostname(config)# dhcpd address 10.0.1.100-10.0.1.108 dmz
hostname(config)# dhcpd dns 192.168.1.2
hostname(config)# dhcpd enable dmz
```

Related Commands

Command	Description
clear configure dhcpd	Removes all DHCP server settings.
dhcpd address	Specifies the address pool used by the DHCP server on the specified interface.
dhcpd enable	Enables the DHCP server on the specified interface.
dhcpd wins	Defines the WINS servers for DHCP clients.
show running-config dhcpd	Displays the current DHCP server configuration.

dhcpd domain

To define the DNS domain name for DHCP clients, use the **dhcpd domain** command in global configuration mode. To clear the DNS domain name, use the **no** form of this command.

dhcpd domain *domain_name*

no dhcpd domain [*domain_name*]

Syntax Description

domain_name The DNS domain name, for example example.com.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **dhcpd domain** command lets you specify the DNS domain name for the DHCP client. The **no dhcpd domain** command lets you remove the DNS domain server from the configuration.

Examples

The following example shows how to use the **dhcpd domain** command to configure the domain name supplied to DHCP clients by the DHCP server on the security appliance:

```
hostname(config)# dhcpd address 10.0.1.101-10.0.1.110 inside
hostname(config)# dhcpd dns 198.162.1.2 198.162.1.3
hostname(config)# dhcpd wins 198.162.1.4
hostname(config)# dhcpd lease 3000
hostname(config)# dhcpd ping_timeout 1000
hostname(config)# dhcpd domain example.com
hostname(config)# dhcpd enable inside
```

Related Commands

Command	Description
clear configure dhcpd	Removes all DHCP server settings.
show running-config dhcpd	Displays the current DHCP server configuration.

dhcpd enable

To enable the DHCP server, use the **dhcpd enable** command in global configuration mode. To disable the DHCP server, use the **no** form of this command. The DHCP server provides network configuration parameters to DHCP clients. Support for the DHCP server within the security appliance means that the security appliance can use DHCP to configure connected clients.

dhcpd enable *interface*

no dhcpd enable *interface*

Syntax Description

interface Specifies the interface on which to enable the DHCP server.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **dhcpd enable interface** command lets you enable the DHCP daemon to listen for the DHCP client requests on the DHCP-enabled interface. The **no dhcpd enable** command disables the DHCP server feature on the specified interface.



Note

For multiple context mode, you cannot enable the DHCP server on an interface that is used by more than one context (a shared VLAN).

When the security appliance responds to a DHCP client request, it uses the IP address and subnet mask of the interface where the request was received as the IP address and subnet mask of the default gateway in the response.



Note

The security appliance DHCP server daemon does not support clients that are not directly connected to a security appliance interface.

Refer to the *Cisco Security Appliance Command Line Configuration Guide* for information on how to implement the DHCP server feature into the security appliance.

Examples

The following example shows how to use the **dhcpd enable** command to enable the DHCP server on the inside interface:

```
hostname(config)# dhcpd address 10.0.1.101-10.0.1.110 inside
hostname(config)# dhcpd dns 198.162.1.2 198.162.1.3
hostname(config)# dhcpd wins 198.162.1.4
hostname(config)# dhcpd lease 3000
hostname(config)# dhcpd ping_timeout 1000
hostname(config)# dhcpd domain example.com
hostname(config)# dhcpd enable inside
```

Related Commands

Command	Description
debug dhcpd	Displays debug information for the DHCP server.
dhcpd address	Specifies the address pool used by the DHCP server on the specified interface.
show dhcpd	Displays DHCP binding, statistic, or state information.
show running-config dhcpd	Displays the current DHCP server configuration.

dhcpd lease

To specify the DHCP lease length, use the **dhcpd lease** command in global configuration mode. To restore the default value for the lease, use the **no** form of this command.

dhcpd lease *lease_length*

no dhcpd lease [*lease_length*]

Syntax Description

<i>lease_length</i>	Length of the IP address lease, in seconds, granted to the DHCP client from the DHCP server; valid values are from 300 to 1048575 seconds.

Defaults

The default *lease_length* is 3600 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **dhcpd lease** command lets you specify the length of the lease, in seconds, that is granted to the DHCP client. This lease indicates how long the DHCP client can use the assigned IP address that the DHCP server granted.

The **no dhcpd lease** command lets you remove the lease length that you specified from the configuration and replaces this value with the default value of 3600 seconds.

Examples

The following example shows how to use the **dhcpd lease** command to specify the length of the lease of DHCP information for DHCP clients:

```
hostname(config)# dhcpd address 10.0.1.101-10.0.1.110 inside
hostname(config)# dhcpd dns 198.162.1.2 198.162.1.3
hostname(config)# dhcpd wins 198.162.1.4
hostname(config)# dhcpd lease 3000
hostname(config)# dhcpd ping_timeout 1000
hostname(config)# dhcpd domain example.com
hostname(config)# dhcpd enable inside
```

Related Commands	Command	Description
	clear configure dhcpd	Removes all DHCP server settings.
	show running-config dhcpd	Displays the current DHCP server configuration.

dhcpd option

To configure DHCP options, use the **dhcpd option** command in global configuration mode. To clear the option, use the **no** form of this command. You can use the **dhcpd option** command to provide TFTP server information to Cisco IP Phones and routers.

dhcpd option *code* {**ascii** *string*} | {**ip** *IP_address* [*IP_address*]} | {**hex** *hex_string*}

no dhcpd option *code*

Syntax Description

ascii	Specifies that the option parameter is an ASCII character string.
<i>code</i>	A number representing the DHCP option being set. Valid values are 0 to 255.
hex	Specifies that the option parameter is a hexadecimal string.
<i>hex_string</i>	Specifies a hexadecimal string with an even number of digits and no spaces. You do not need to use a 0x prefix.
ip	Specifies that the option parameter is an IP address. You can specify a maximum of two IP addresses with the ip keyword.
<i>IP_address</i>	Specifies a dotted-decimal IP address.
<i>string</i>	Specifies an ASCII character string without spaces.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

When a DHCP option request arrives at the security appliance DHCP server, the security appliance places the value or values that are specified by the **dhcpd option** command in the response to the client.

The **dhcpd option 66** and **dhcpd option 150** commands specify TFTP servers that Cisco IP Phones and routers can use to download configuration files. Use the commands as follows:

- **dhcpd option 66** *ascii string*, where *string* is either the IP address or hostname of the TFTP server. Only one TFTP server can be specified for option 66.

- **dhcpd option 150 ip** *IP_address* [*IP_address*], where *IP_address* is the IP address of the TFTP server. You can specify a maximum of two IP addresses for option 150.

**Note**

The **dhcpd option 66** command only takes an **ascii** parameter, and the **dhcpd option 150** only takes an **ip** parameter.

Use the following guidelines when specifying an IP address for the **dhcpd option 66 | 150** commands:

- If the TFTP server is located on the DHCP server interface, use the local IP address of the TFTP server.
- If the TFTP server is located on a less secure interface than the DHCP server interface, then general outbound rules apply. Create a group of NAT, global, and **access-list** entries for the DHCP clients, and use the actual IP address of the TFTP server.
- If the TFTP server is located on a more secure interface, then general inbound rules apply. Create a group of static and **access-list** statements for the TFTP server and use the global IP address of the TFTP server.

For information about other DHCP options, refer to RFC2132.

Examples

The following example shows how to specify a TFTP server for DHCP option 66:

```
hostname(config)# dhcpd option 66 ascii MyTftpServer
```

Related Commands

Command	Description
clear configure dhcpd	Removes all DHCP server settings.
show running-config dhcpd	Displays the current DHCP server configuration.

dhcpd ping_timeout

To change the default timeout for DHCP ping, use the **dhcpd ping_timeout** command in global configuration mode. To return to the default value, use the **no** form of this command. To avoid address conflicts, the DHCP server sends two ICMP ping packets to an address before assigning that address to a DHCP client. This command specifies the ping timeout in milliseconds.

dhcpd ping_timeout *number*

no dhcpd ping_timeout

Syntax Description

number The timeout value of the ping, in milliseconds. The minimum value is 10, the maximum is 10000. The default is 50.

Defaults

The default number of milliseconds for *number* is 50.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The security appliance waits for both ICMP ping packets to time out before assigning an IP address to a DHCP client. For example, if the default value is used, the security appliance waits for 1500 milliseconds (750 milliseconds for each ICMP ping packet) before assigning an IP address.

A long ping timeout value can adversely affect the performance of the DHCP server.

Examples

The following example shows how to use the **dhcpd ping_timeout** command to change the ping timeout value for the DHCP server:

```
hostname(config)# dhcpd address 10.0.1.101-10.0.1.110 inside
hostname(config)# dhcpd dns 198.162.1.2 198.162.1.3
hostname(config)# dhcpd wins 198.162.1.4
hostname(config)# dhcpd lease 3000
hostname(config)# dhcpd ping_timeout 1000
hostname(config)# dhcpd domain example.com
hostname(config)# dhcpd enable inside
```

Related Commands

Command	Description
clear configure dhcpd	Removes all DHCP server settings.
show running-config dhcpd	Displays the current DHCP server configuration.

dhcpd wins

To define the WINS servers for DHCP clients, use the **dhcpd wins** command in global configuration mode. To remove the WINS servers from the DHCP server, use the **no** form of this command.

dhcpd wins *server1* [*server2*]

no dhcpd wins [*server1* [*server2*]]

Syntax Description

<i>server1</i>	Specifies the IP address of the primary Microsoft NetBIOS name server (WINS server).
<i>server2</i>	(Optional) Specifies the IP address of the alternate Microsoft NetBIOS name server (WINS server).

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **dhcpd wins** command lets you specify the addresses of the WINS servers for the DHCP client. The **no dhcpd wins** command removes the WINS server IP addresses from the configuration.

Examples

The following example shows how to use the **dhcpd wins** command to specify WINS server information that is sent to DHCP clients:

```
hostname(config)# dhcpd address 10.0.1.101-10.0.1.110 inside
hostname(config)# dhcpd dns 198.162.1.2 198.162.1.3
hostname(config)# dhcpd wins 198.162.1.4
hostname(config)# dhcpd lease 3000
hostname(config)# dhcpd ping_timeout 1000
hostname(config)# dhcpd domain example.com
hostname(config)# dhcpd enable inside
```

Related Commands

Command	Description
clear configure dhcpd	Removes all DHCP server settings.
dhcpd address	Specifies the address pool used by the DHCP server on the specified interface.
dhcpd dns	Defines the DNS servers for DHCP clients.
show dhcpd	Displays DHCP binding, statistic, or state information.
show running-config dhcpd	Displays the current DHCP server configuration.

dhcprelay enable

To enable the DHCP relay agent, use the **dhcprelay enable** command in global configuration mode. To disable DHCP relay agent, use the **no** form of this command. The DHCP relay agent allows DHCP requests to be forwarded from a specified security appliance interface to a specified DHCP server.

dhcprelay enable *interface_name*

no dhcprelay enable *interface_name*

Syntax Description

<i>interface_name</i>	Name of the interface on which the DHCP relay agent accepts client requests.

Defaults

The DHCP relay agent is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

For the security appliance to start the DHCP relay agent with the **dhcprelay enable** *interface_name* command, you must have a **dhcprelay server** command already in the configuration. Otherwise, the security appliance displays an error message similar to the following:

```
DHCPRA: Warning - There are no DHCP servers configured!
No relaying can be done without a server!
Use the 'dhcprelay server <server_ip> <server_interface>' command
```

You cannot enable DHCP relay under the following conditions:

- You cannot enable DHCP relay and the DHCP relay server on the same interface.
- You cannot enable DHCP relay and a DHCP server (**dhcpd enable**) on the same interface.
- You cannot enable DHCP relay in a context at the same time as the DHCP server.
- For multiple context mode, you cannot enable DHCP relay on an interface that is used by more than one context (a shared VLAN).

The **no dhcprelay enable** *interface_name* command removes the DHCP relay agent configuration for the interface that is specified by *interface_name* only.

Examples

The following example shows how to configure the DHCP relay agent for a DHCP server with an IP address of 10.1.1.1 on the outside interface of the security appliance, client requests on the inside interface of the security appliance, and a timeout value up to 90 seconds:

```
hostname(config)# dhcprelay server 10.1.1.1 outside
hostname(config)# dhcprelay timeout 90
hostname(config)# dhcprelay enable inside
hostname(config)# show running-config dhcprelay
dhcprelay server 10.1.1.1 outside
dhcprelay enable inside
dhcprelay timeout 90
```

The following example shows how to disable the DHCP relay agent:

```
hostname(config)# no dhcprelay enable inside
hostname(config)# show running-config dhcprelay
dhcprelay server 10.1.1.1 outside
dhcprelay timeout 90
```

Related Commands

Command	Description
clear configure dhcprelay	Removes all DHCP relay agent settings.
debug dhcp relay	Displays debug information for the DHCP relay agent.
dhcprelay server	Specifies the DHCP server that the DHCP relay agent forwards DHCP requests to.
dhcprelay setroute	Defines IP address that the DHCP relay agent uses as the default router address in DHCP replies.
show running-config dhcprelay	Displays the current DHCP relay agent configuration.

dhcprelay server

To specify the DHCP server that DHCP requests are forwarded to, use the **dhcprelay server** command in global configuration mode. To remove the DHCP server from the DHCP relay configuration, use the **no** form of this command. The DHCP relay agent allows DHCP requests to be forwarded from a specified security appliance interface to a specified DHCP server.

dhcprelay server *IP_address interface_name*

no dhcprelay server *IP_address [interface_name]*

Syntax Description

<i>interface_name</i>	Name of the security appliance interface on which the DHCP server resides.
<i>IP_address</i>	The IP address of the DHCP server to which the DHCP relay agent forwards client DHCP requests.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

You can add up to four DHCP relay servers per interface. You must add at least one **dhcprelay server** command to the security appliance configuration before you can enter the **dhcprelay enable** command. You cannot configure a DHCP client on an interface that has a DHCP relay server configured.

The **dhcprelay server** command opens UDP port 67 on the specified interface and starts the DHCP relay task as soon as the **dhcprelay enable** command is added to the configuration. If there is **no dhcprelay enable** command in the configuration, then the sockets are not opened and the DHCP relay task does not start.

When you use the **no dhcprelay server** *IP_address [interface_name]* command, the interface stops forwarding DHCP packets to that server.

The **no dhcprelay server** *IP_address [interface_name]* command removes the DHCP relay agent configuration for the DHCP server that is specified by *IP_address [interface_name]* only.

Examples

The following example shows how to configure the DHCP relay agent for a DHCP server with an IP address of 10.1.1.1 on the outside interface of the security appliance, client requests on the inside interface of the security appliance, and a timeout value up to 90 seconds:

```
hostname(config)# dhcprelay server 10.1.1.1 outside
hostname(config)# dhcprelay timeout 90
hostname(config)# dhcprelay enable inside
hostname(config)# show running-config dhcprelay
dhcprelay server 10.1.1.1 outside
dhcprelay enable inside
dhcprelay timeout 90
```

Related Commands

Command	Description
clear configure dhcprelay	Removes all DHCP relay agent settings.
dhcprelay enable	Enables the DHCP relay agent on the specified interface.
dhcprelay setroute	Defines IP address that the DHCP relay agent uses as the default router address in DHCP replies.
dhcprelay timeout	Specifies the timeout value for the DHCP relay agent.
show running-config dhcprelay	Displays the current DHCP relay agent configuration.

dhcprelay setroute

To set the default gateway address in the DHCP reply, use the **dhcprelay setroute** command in global configuration mode. To remove the default router, use the **no** form of this command. This command causes the default IP address of the DHCP reply to be substituted with the address of the specified security appliance interface.

dhcprelay setroute *interface*

no dhcprelay setroute *interface*

Syntax Description

interface Configures the DHCP relay agent to change the first default IP address (in the packet sent from the DHCP server) to the address of *interface*.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **dhcprelay setroute** *interface* command lets you enable the DHCP relay agent to change the first default router address (in the packet sent from the DHCP server) to the address of *interface*.

If there is no default router option in the packet, the security appliance adds one containing the address of *interface*. This action allows the client to set its default route to point to the security appliance.

When you do not configure the **dhcprelay setroute** *interface* command (and there is a default router option in the packet), it passes through the security appliance with the router address unaltered.

Examples

The following example shows how to use the **dhcprelay setroute** command to set the default gateway in the DHCP reply from the external DHCP server to the inside interface of the security appliance:

```
hostname(config)# dhcprelay server 10.1.1.1 outside
hostname(config)# dhcprelay timeout 90
hostname(config)# dhcprelay setroute inside
hostname(config)# dhcprelay enable inside
```

Related Commands	Command	Description
	clear configure dhcprelay	Removes all DHCP relay agent settings.
	dhcprelay enable	Enables the DHCP relay agent on the specified interface.
	dhcprelay server	Specifies the DHCP server that the DHCP relay agent forwards DHCP requests to.
	dhcprelay timeout	Specifies the timeout value for the DHCP relay agent.
	show running-config dhcprelay	Displays the current DHCP relay agent configuration.

dhcprelay timeout

To set the DHCP relay agent timeout value, use the **dhcprelay timeout** command in global configuration mode. To restore the timeout value to its default value, use the **no** form of this command.

dhcprelay timeout *seconds*

no dhcprelay timeout

Syntax Description

seconds Specifies the number of seconds that are allowed for DHCP relay address negotiation.

Defaults

The default value for the dhcprelay timeout is 60 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **dhcprelay timeout** command lets you set the amount of time, in seconds, allowed for responses from the DHCP server to pass to the DHCP client through the relay binding structure.

Examples

The following example shows how to configure the DHCP relay agent for a DHCP server with an IP address of 10.1.1.1 on the outside interface of the security appliance, client requests on the inside interface of the security appliance, and a timeout value up to 90 seconds:

```
hostname(config)# dhcprelay server 10.1.1.1 outside
hostname(config)# dhcprelay timeout 90
hostname(config)# dhcprelay enable inside
hostname(config)# show running-config dhcprelay
dhcprelay server 10.1.1.1 outside
dhcprelay enable inside
dhcprelay timeout 90
```

Related Commands

Command	Description
clear configure dhcprelay	Removes all DHCP relay agent settings.
dhcprelay enable	Enables the DHCP relay agent on the specified interface.
dhcprelay server	Specifies the DHCP server that the DHCP relay agent forwards DHCP requests to.
dhcprelay setroute	Defines IP address that the DHCP relay agent uses as the default router address in DHCP replies.
show running-config dhcprelay	Displays the current DHCP relay agent configuration.

dir

To display the directory contents, use the **dir** command in privileged EXEC mode.

dir [/all] [all-fileSYSTEMS] [/recursive] [disk0: | disk1: | flash: | system:] [path]

Syntax Description

/all	(Optional) Displays all files.
all-fileSYSTEMS	(Optional) Displays the files of all fileSYSTEMS
disk0:	(Optional) Specifies the internal Flash memory, followed by a colon.
disk1:	(Optional) Specifies the external Flash memory card, followed by a colon.
/recursive	(Optional) Displays the directory contents recursively.
system:	(Optional) Displays the directory contents of the file system.
flash:	(Optional) Displays the directory contents of the default Flash partition.
path	(Optional) Specifies a specific path.

Defaults

If you do not specify a directory, the directory is the current working directory by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **dir** command without keywords or arguments displays the directory contents of the current directory.

Examples

The following example shows how to display the directory contents:

```
hostname# dir
Directory of disk0:/

1      -rw-  1519      10:03:50 Jul 14 2003    my_context.cfg
2      -rw-  1516      10:04:02 Jul 14 2003    my_context.cfg
3      -rw-  1516      10:01:34 Jul 14 2003    admin.cfg
60985344 bytes total (60973056 bytes free)
```

This example shows how to display recursively the contents of the entire file system:

```

hostname# dir /recursive disk0:
Directory of disk0:/*
 1      -rw-  1519      10:03:50 Jul 14 2003    my_context.cfg
 2      -rw-  1516      10:04:02 Jul 14 2003    my_context.cfg
 3      -rw-  1516      10:01:34 Jul 14 2003    admin.cfg
60985344 bytes total (60973056 bytes free)

```

This example shows how display the contents of the Flash partition:

```

hostname# dir flash:
Directory of disk0:/*
 1      -rw-  1519      10:03:50 Jul 14 2003    my_context.cfg
 2      -rw-  1516      10:04:02 Jul 14 2003    my_context.cfg
 3      -rw-  1516      10:01:34 Jul 14 2003    admin.cfg
60985344 bytes total (60973056 bytes free)

```

Related Commands

Command	Description
cd	Changes the current working directory to the one specified.
pwd	Displays the current working directory.
mkdir	Creates a directory.
rmdir	Removes a directory.

disable

To exit privileged EXEC mode and return to unprivileged EXEC mode, use the **disable** command in privileged EXEC mode.

disable

Syntax Description

This command has no arguments or keywords.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Use the **enable** command to enter privileged mode. The **disable** command allows you to exit privileged mode and returns you to unprivileged mode.

Examples

The following example shows how to enter privileged mode:

```
hostname> enable
hostname#
```

The following example shows how to exit privileged mode:

```
hostname# disable
hostname>
```

Related Commands

Command	Description
enable	Enables privileged EXEC mode.

distance ospf

To define OSPF route administrative distances based on route type, use the **distance ospf** command in router configuration mode. To restore the default values, use the **no** form of this command.

distance ospf [*intra-area d1*] [*inter-area d2*] [*external d3*]

no distance ospf

Syntax Description

<i>d1</i> , <i>d2</i> , and <i>d3</i>	Distance for each route types. Valid values range from 1 to 255.
external	(Optional) Sets the distance for routes from other routing domains that are learned by redistribution.
inter-area	(Optional) Sets the distance for all routes from one area to another area.
intra-area	(Optional) Sets the distance for all routes within an area.

Defaults

The default values for *d1*, *d2*, and *d3* are 110.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

You must specify at least one keyword and argument. You can enter the commands for each type of administrative distance separately, however they appear as a single command in the configuration. If you reenter an administrative distance, the administrative distance for only that route type changes; the administrative distances for any other route types remain unaffected.

The **no** form of the command does not take any keywords or arguments. Using the **no** form of the command restores the default administrative distance for all of the route types. If you want to restore the default administrative distance for a single route type when you have multiple route types configured, you can do one of the following:

- Manually set that route type to the default value.
- Use the **no** form of the command to remove the entire configuration and then re-enter the configurations for the route types you want to keep.

Examples

The following example sets the administrative distance of external routes to 150:

```
hostname(config-router)# distance ospf external 105
hostname(config-router)#
```

The following example shows how entering separate commands for each route type appears as a single command in the router configuration:

```
hostname(config-router)# distance ospf intra-area 105 inter-area 105
hostname(config-router)# distance ospf intra-area 105
hostname(config-router)# distance ospf external 105
hostname(config-router)# exit
hostname(config)# show running-config router ospf 1
!
router ospf 1
  distance ospf intra-area 105 inter-area 105 external 105
!
hostname(config)#
```

The following example shows how to set each administrative distance to 105, and then change only the external administrative distance to 150. The **show running-config router ospf** command shows how only the external route type value changed, while the other route types retained the value previously set.

```
hostname(config-router)# distance ospf external 105 intra-area 105 inter-area 105
hostname(config-router)# distance ospf external 150
hostname(config-router)# exit
hostname(config)# show running-config router ospf 1
!
router ospf 1
  distance ospf intra-area 105 inter-area 105 external 150
!
hostname(config)#
```

Related Commands

Command	Description
router ospf	Enters router configuration mode.
show running-config router	Displays the commands in the global router configuration.

dns domain-lookup

To enable the security appliance to send DNS requests to a DNS server to perform a name lookup for supported commands, use the **dns domain-lookup** command in global configuration mode. To disable DNS lookup, use the **no** form of this command.

dns domain-lookup *interface_name*

no dns domain-lookup *interface_name*

Syntax Description

interface_name Specifies the interface on which you want to enable DNS lookup. If you enter this command multiple times to enable DNS lookup on multiple interfaces, the security appliance tries each interface in order until it receives a response.

Defaults

DNS lookup is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **dns name-server** command to configure the DNS server addresses to which you want to send DNS requests. See the **dns name-server** command for a list of commands that support DNS lookup.

The security appliance maintains a cache of name resolutions that consists of dynamically learned entries. Instead of making queries to external DNS servers each time an hostname-to-IP-address translation is needed, the security appliance caches information returned from external DNS requests. The security appliance only makes requests for names that are not in the cache. The cache entries time out automatically according to the DNS record expiration, or after 72 hours, whichever comes first.

Examples

The following example enables DNS lookup on the inside interface:

```
hostname(config)# dns domain-lookup inside
```

Related Commands

Command	Description
dns name-server	Configures a DNS server address.
dns retries	Specifies the number of times to retry the list of DNS servers when the security appliance does not receive a response.
dns timeout	Specifies the amount of time to wait before trying the next DNS server.
domain-name	Sets the default domain name.
show dns-hosts	Shows the DNS cache.

dns-guard

To enable the DNS guard function, use the **dns-guard** command in global configuration mode. To disable the DNS guard feature, use the **no** form of this command.

dns-guard

no dns-guard

Defaults

This command is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0(5)	This command was introduced.

Usage Guidelines

DNS guard tears down the DNS session associated with a DNS request as soon as the DNS response is forwarded by the security appliance. DNS guard also monitors the message exchange to ensure that the ID of the DNS response matches the ID of the DNS request.

The **dns-guard** command provides the capability to turn on or off the DNS guard function when DNS inspection is not enabled (when the **inspect dns** command is not configured). This command is only effective on the interfaces without DNS inspection. When DNS inspection is effective, the DNS guard function is always performed.

DNS guard is enabled together with the **inspect dns** command or the **fixup protocol dns** in earlier versions, and remains active when the inspection is disabled. This is still the default behavior, but now you have the option to disable this function.

Examples

The following example shows how to enable DNS guard:

```
hostname(config)# dns-guard
```

The following example shows how to disable DNS guard:

```
hostname(config)# no dns-guard
```

Related Commands

Commands	Description
inspect dns	Enables the DNS inspection.
class-map	Defines the traffic class to which to apply security actions.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

dns name-server

To identify one or more DNS servers, use the **dns name-server** command in global configuration mode. To remove a server, use the **no** form of this command. The security appliance uses DNS to resolve server names in your WebVPN configuration or certificate configuration (see “[Usage Guidelines](#)” for a list of supported commands). Other features that define server names (such as AAA) do not support DNS resolution. You must enter the IP address or manually resolve the name to an IP address by using the **name** command.

dns name-server *ip_address* [*ip_address2*] [...] [*ip_address6*]

no dns name-server *ip_address* [*ip_address2*] [...] [*ip_address6*]

Syntax Description

<i>ip_address</i>	Specifies the DNS server IP address. You can specify up to six addresses as separate commands, or for convenience, up to six addresses in one command separated by spaces. If you enter multiple servers in one command, the security appliance saves each server in a separate command in the configuration. The security appliance tries each DNS server in order until it receives a response.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

To enable DNS lookup, configure the **dns domain-lookup** command. If you do not enable DNS lookup, the DNS servers are not used.

WebVPN commands that support DNS resolution include the following:

- **server (pop3s)**
- **server (imap4s)**
- **server (smtps)**
- **port-forward**
- **url-list**

Certificate commands that support DNS resolution include the following:

- **enrollment url**
- **url**

You can manually enter names and IP addresses using the **name** command.

See the **dns retries** command to set how many times the security appliance tries the list of DNS servers.

Examples

The following example adds three DNS servers:

```
hostname(config)# dns name-server 10.1.1.1 10.2.3.4 192.168.5.5
```

The security appliance saves the configuration as separate commands, as follows:

```
dns name-server 10.1.1.1
dns name-server 10.2.3.4
dns name-server 192.168.5.5
```

To add two additional servers, you can enter them as one command:

```
hostname(config)# dns name-server 10.5.1.1 10.8.3.8
hostname(config)# show running-config dns
dns name-server 10.1.1.1
dns name-server 10.2.3.4
dns name-server 192.168.5.5
dns name-server 10.5.1.1
dns name-server 10.8.3.8
...
```

Or you can enter them as two commands:

```
hostname(config)# dns name-server 10.5.1.1
hostname(config)# dns name-server 10.8.3.8
```

To delete multiple servers you can enter them as multiple commands or as one command, as follows:

```
hostname(config)# no dns name-server 10.5.1.1 10.8.3.8
```

Related Commands

Command	Description
dns domain-lookup	Enables the security appliance to perform a name lookup.
dns retries	Specifies the number of times to retry the list of DNS servers when the security appliance does not receive a response.
dns timeout	Specifies the amount of time to wait before trying the next DNS server.
domain-name	Sets the default domain name.
show dns-hosts	Shows the DNS cache.

dns retries

To specify the number of times to retry the list of DNS servers when the security appliance does not receive a response, use the **dns retries** command in global configuration mode. To restore the default setting, use the **no** form of this command.

dns retries *number*

no dns retries [*number*]

Syntax Description

number Specifies the number of retries between 0 and 10. The default is 2.

Defaults

The default number of retries is 2.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Add DNS servers using the **dns name-server** command.

Examples

The following example sets the number of retries to 0. The security appliance only tries each server one time.

```
hostname(config)# dns retries 0
```

Related Commands

Command	Description
dns domain-lookup	Enables the security appliance to perform a name lookup.
dns name-server	Configures a DNS server address.
dns timeout	Specifies the amount of time to wait before trying the next DNS server.
domain-name	Sets the default domain name.
show dns-hosts	Shows the DNS cache.

dns timeout

To specify the amount of time to wait before trying the next DNS server, use the **dns timeout** command in global configuration mode. To restore the default timeout, use the **no** form of this command.

dns timeout *seconds*

no dns timeout [*seconds*]

Syntax Description

seconds Specifies the timeout in seconds between 1 and 30. The default is 2 seconds. Each time the security appliance retries the list of servers, this timeout doubles. See the **dns retries** command to configure the number of retries.

Defaults

The default timeout is 2 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example sets the timeout to 1 second:

```
hostname(config)# dns timeout 1
```

Related Commands

Command	Description
dns name-server	Configures a DNS server address.
dns retries	Specifies the number of times to retry the list of DNS servers when the security appliance does not receive a response.
dns domain-lookup	Enables the security appliance to perform a name lookup.
domain-name	Sets the default domain name.
show dns-hosts	Shows the DNS cache.

dns-server

To set the IP address of the primary and secondary DNS servers, use the **dns-server** command in group-policy mode. To remove the attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a DNS server from another group policy. To prevent inheriting a server, use the **dns-server none** command.

dns-server {value *ip_address* [*ip_address*] | none}

no dns-server

Syntax Description

none	Sets dns-servers to a null value, thereby allowing no DNS servers. Prevents inheriting a value from a default or specified group policy.
value <i>ip_address</i>	Specifies the IP address of the primary and secondary DNS servers.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Every time you issue the **dns-server** command you overwrite the existing setting. For example, if you configure DNS server x.x.x.x and then configure DNS server y.y.y.y, the second command overwrites the first, and y.y.y.y becomes the sole DNS server. The same holds true for multiple servers. To add a DNS server rather than overwrite previously configured servers, include the IP addresses of all DNS servers when you enter this command.

Examples

The following example shows how to configure DNS servers with the IP addresses 10.10.10.15, 10.10.10.30, and 10.10.10.45 for the group policy named FirstGroup.

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# dns-server value 10.10.10.15 10.10.10.30 10.10.10.45
```


domain-name

To set the default domain name, use the **domain-name** command in global configuration mode. To remove the domain name, use the **no** form of this command. The security appliance appends the domain name as a suffix to unqualified names. For example, if you set the domain name to “example.com,” and specify a syslog server by the unqualified name of “jupiter,” then the security appliance qualifies the name to “jupiter.example.com.”

domain-name *name*

no domain-name [*name*]

Syntax Description

name Sets the domain name, up to 63 characters.

Defaults

The default domain name is default.domain.invalid.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

For multiple context mode, you can set the domain name for each context, as well as within the system execution space.

Examples

The following example sets the domain as example.com:

```
hostname(config)# domain-name example.com
```

Related Commands

Command	Description
dns domain-lookup	Enables the security appliance to perform a name lookup.
dns name-server	Configures a DNS server address.

■ domain-name

Command	Description
hostname	Sets the security appliance hostname.
show running-config domain-name	Shows the domain name configuration.

downgrade

To downgrade to a previous version of the operating system software (software image), use the **downgrade** command in privileged EXEC mode.



Caution

Do not load a previous version of software if your PIX security appliance is currently running PIX Version 7.0 or later. Loading a software image from monitor mode, on a PIX security appliance that has a PIX Version 7.0 file system, results in unpredictable behavior and is not supported. We strongly recommend that you use the **downgrade** command from a running PIX Version 7.0 image that facilitates the downgrade process.

downgrade *image_url* [**activation-key** [**flash** | *4-part_key* | *file*]] [**config** *start_config_url*]

Syntax Description

<i>4-part_key</i>	(Optional) Specifies the four-part activation key to write to the image. If you are using a five-part key, a warning with the list of features that might be lost by going back to the four-part key is generated. If the system Flash has been reformatted or erased, no default key is available for the downgrade. In that case, the CLI prompts you to enter an activation key at the command line. This is the default behavior if the activation-key keyword is not specified at the command line.
activation-key	(Optional) Specifies the activation key to use with the downgraded software image.
config	(Optional) Specifies the startup configuration file.
<i>file</i>	(Optional) Specifies the path/URL and name of the activation key file to use after the downgrade procedure completes. If the source image file is the one saved in Flash during the upgrade process, the activation key in this file is used with the downgrade.
flash	(Optional) Specifies to look in Flash memory for the four-part activation key that was used on the device prior to using a five-part activation key. This is the default behavior if the activation-key keyword is not specified at the command line.
<i>image_url</i>	Specifies the path/URL and name of the software image to downgrade to. The software image must be a version prior to 7.0.
<i>start_config_url</i>	(Optional) Specifies the path/URL and name of the configuration file to use after the downgrade procedure completes.

Defaults

If the **activation-key** keyword is not specified, the security appliance tries to use the last four-part activation key used. If the security appliance cannot find a four-part activation key in Flash, the command is rejected and an error message displays. In this case, a valid four-part activation-key must be specified at the command line next time. The default activation key or the user specified activation key is compared with the activation key currently in effect. If there is a potential loss of features by using the chosen activation key, a warning displays with the list of features that could be lost after downgrade.

The security appliance uses downgrade.cfg by default if the startup configuration file is not specified.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•		

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is not supported on Cisco ASA 5500 series security appliances.

**Caution**

A power failure during the downgrade process might corrupt the Flash memory. As a precaution, backup all data on the Flash memory to an external device prior to starting the downgrade process.

Recovering corrupt Flash memory requires direct console access. See the **format** command for more information.

Examples

The following example downgrades the software to Release 6.3.3:

```
hostname# downgrade tftp://17.13.2.25/tftpboot/mananthr/cdisk.6.3.3 activation-key
32c261f3 062afe24 c94ef2ea 0e299a3f
This command will reformat the flash and automatically reboot the system.
Do you wish to continue? [confirm]
Buffering image
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!

Buffering startup config

All items have been buffered successfully.
If the flash reformat is interrupted or fails, data in flash will be lost
and the system might drop to monitor mode.
Do you wish to continue? [confirm]
Installing the correct file system for the image and saving the buffered data
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
Flash downgrade succeeded

Rebooting....
```

Enter zero actkey:

The following example shows what happens if you enter an invalid activation key:

```
hostname# downgrade tftp://17.13.2.25/tftpboot/mananthr/cdisk.6.3.3 activation-key
0 0 0 0
This command will reformat the flash and automatically reboot the system.
Do you wish to continue? [confirm]
Buffering image
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!
Error: activation key entered is invalid.
```

Enter the file option when there is no actkey in the source image (happens if the source is in tftp server).

The following example shows what happens if you specify the activation key in the source image and it does not exist:

```
hostname# downgrade tftp://17.13.2.25/tftpboot/mananthr/cdisk.6.3.3 activation-key file
This command will reformat the flash and automatically reboot the system.
Do you wish to continue? [confirm]
Buffering image
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!
Activation key does not exist in the source image.
Please use the activation-key option to specify an activation key.
```

The following example shows how to abort the downgrade procedure at the final prompt:

```
hostname# downgrade tftp://17.13.2.25/tftpboot/mananthr/cdisk.6.3.3
This command will reformat the flash and automatically reboot the system.
Do you wish to continue? [confirm]
Buffering image
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!

Buffering startup config

All items have been buffered successfully.
If the flash reformat is interrupted or fails, data in flash will be lost
and the system might drop to monitor mode.
Do you wish to continue? [confirm] ==>typed n here>
Downgrade process terminated.
```

To downgrade, the software version must be less than 7.0. The following example shows a failed attempt at downgrading the software:

```
hostname# downgrade tftp://17.13.2.25/scratch/views/test/target/sw/cdisk
This command will reformat the flash and automatically reboot the system.
Do you wish to continue? [confirm]
Buffering image
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
```

The following example shows what happens if you specify an image and do not verify the activation key:

The following example shows what happens if the four-part activation key does not have all the features that the current five-part activation key has:

```

hostname# downgrade tftp://17.13.2.25//tftpboot/mananthr/cdisk.6.3.3
This command will reformat the flash and automatically reboot the system.
Do you wish to continue? [confirm]
Buffering image
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!
The following features available in current activation key in flash
are NOT available in 4 tuple activation key in flash:
VPN-3DES-AES
GTP/GPRS
5 Security Contexts
Failover is different:
current activation key in flash: UR(estricted)
4 tuple activation key in flash: R(estricted)
Some features might not work in the downgraded image if this key is used.
Do you wish to continue? [confirm]
Downgrade process terminated.
Please enter an activation-key in the command line.

```

Related Commands	Command	Description
	copy running-config startup-config	Saves the current running configuration to Flash memory.

drop

To drop specified GTP messages, use the **drop** command in GTP map configuration mode, which is accessed by using the **gtp-map** command. Use the **no** form to remove the command.

drop {**apn** *access_point_name* | **message** *message_id* | **version** *version*}

no drop {**apn** *access_point_name* | **message** *message_id* | **version** *version*}

Syntax Description

apn	Drops GTP messages with the specified access point name.
<i>access_point_name</i>	The text string of the APN which will be dropped.
message	Drops specific GTP messages.
<i>message_id</i>	An alphanumeric identifier for the message that you want to drop. The valid range for <i>message_id</i> is 1 to 255.
version	Drops GTP messages with the specified version.
<i>version</i>	Use 0 to identify Version 0 and 1 to identify Version 1. Version 0 of GTP uses port 2123, while Version 1 uses port 3386.

Defaults

All messages with valid message IDs, APNs, and version are inspected.
Any APN is allowed.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
GTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **drop message** command to drop specific GTP messages that you do not want to allow in your network.

Use the **drop apn** command to drop GTP messages with the specified access point. Use the **drop version** command to drop GTP messages with the specified version.

Examples

The following example drops traffic to message ID 20:

```
hostname(config)# gtp-map gtp-policy
hostname(config-gtpmap)# drop message 20
```

Related Commands	Commands	Description
	clear service-policy inspect gtp	Clears global GTP statistics.
	debug gtp	Displays detailed information about GTP inspection.
	gtp-map	Defines a GTP map and enables GTP map configuration mode.
	inspect gtp	Applies a specific GTP map to use for application inspection.
	show service-policy inspect gtp	Displays the GTP configuration.

duplex

To set the duplex of a copper (RJ-45) Ethernet interface, use the **duplex** command in interface configuration mode. To restore the duplex setting to the default, use the **no** form of this command.

duplex { auto | full | half }

no duplex

Syntax Description

auto	Auto-detects the duplex mode.
full	Sets the duplex mode to full duplex.
half	Sets the duplex mode to half duplex.

Defaults

The default is auto detect.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Interface configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was moved from a keyword of the interface command to an interface configuration mode command.

Usage Guidelines

Set the duplex mode on the physical interface only.

The **duplex** command is not available for fiber media.

If your network does not support auto detection, set the duplex mode to a specific value.

For RJ-45 interfaces on the ASA 5500 series adaptive security appliance, the default auto-negotiation setting also includes the Auto-MDI/MDIX feature. Auto-MDI/MDIX eliminates the need for crossover cabling by performing an internal crossover when a straight cable is detected during the auto-negotiation phase. Either the speed or duplex must be set to auto-negotiate to enable Auto-MDI/MDIX for the interface. If you explicitly set both the speed and duplex to a fixed value, thus disabling auto-negotiation for both settings, then Auto-MDI/MDIX is also disabled.

Examples

The following example sets the duplex mode to full duplex:

```
hostname(config)# interface gigabitethernet0/1
hostname(config-if)# speed 1000
hostname(config-if)# duplex full
```

```

hostname(config-if)# nameif inside
hostname(config-if)# security-level 100
hostname(config-if)# ip address 10.1.1.1 255.255.255.0
hostname(config-if)# no shutdown

```

Related Commands

Command	Description
clear configure interface	Clears all configuration for an interface.
interface	Configures an interface and enters interface configuration mode.
show interface	Displays the runtime status and statistics of interfaces.
show running-config interface	Shows the interface configuration.
speed	Sets the interface speed.

email

To include the indicated email address in the Subject Alternative Name extension of the certificate during enrollment, use the **email** command in crypto ca trustpoint configuration mode. To restore the default setting, use the **no** form of the command.

email *address*

no email

Syntax Description

<i>address</i>	Specifies the email address. The maximum length of <i>address</i> is 64 characters.

Defaults

The default setting is not set.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Crypto ca trustpoint configuration	•	•	•		

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and includes the email address jjh@nhf.net in the enrollment request for trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# email jjh@nhf.net
hostname(ca-trustpoint)#
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint configuration mode.

enable

To enter privileged EXEC mode, use the **enable** command in user EXEC mode.

enable [*level*]

Syntax Description

level (Optional) The privilege level between 0 and 15.

Defaults

Enters privilege level 15 unless you are using command authorization, in which case the default level depends on the level configured for your username.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The default enable password is blank. See the **enable password** command to set the password.

To use privilege levels other than the default of 15, configure local command authorization (see the **aaa authorization command** command and specify the **LOCAL** keyword), and set the commands to different privilege levels using the **privilege** command. If you do not configure local command authorization, the enable levels are ignored, and you have access to level 15 regardless of the level you set. See the **show curpriv** command to view your current privilege level.

Levels 2 and above enter privileged EXEC mode. Levels 0 and 1 enter user EXEC mode.

Enter the **disable** command to exit privileged EXEC mode.

Examples

The following example enters privileged EXEC mode:

```
hostname> enable
Password: Pa$$w0rd
hostname#
```

The following example enters privileged EXEC mode for level 10:

```
hostname> enable 10
Password: Pa$$w0rd10
hostname#
```

Related Commands

Command	Description
enable password	Sets the enable password.
disable	Exits privileged EXEC mode.
aaa authorization command	Configures command authorization.
privilege	Sets the command privilege levels for local command authorization.
show curpriv	Shows the currently logged in username and the user privilege level.

enable (webvpn)

To enable WebVPN or e-mail proxy access on a previously configured interface, use the **enable** command. For WebVPN, use this command in **webvpn** mode. For e-mail proxies (IMAP4S, POP3S, SMTPS), use this command in the applicable e-mail proxy mode. To disable WebVPN on an interface, use the **no** version of the command.

enable *ifname*

no enable

Syntax Description

ifname Identifies the previously configured interface. Use the **nameif** command to configure interfaces.

Defaults

WebVPN is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Webvpn	•	—	•	—	—
Imap4s	•	—	•	—	—
Pop3s	•	—	•	—	—
SMTPS	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to enable WebVPN on the interface named Outside:

```
hostname(config)# webvpn
hostname(config-webvpn)# enable Outside
```

The following example shows how to configure POP3S e-mail proxy on the interface named Outside:

```
hostname(config)# pop3s
hostname(config-pop3s)# enable Outside
```

enable password

To set the enable password for privileged EXEC mode, use the **enable password** command in global configuration mode. To remove the password for a level other than 15, use the **no** form of this command. You cannot remove the level 15 password.

enable password *password* [*level level*] [**encrypted**]

no enable password *level level*

Syntax Description

encrypted	(Optional) Specifies that the password is in encrypted form. The password is saved in the configuration in encrypted form, so you cannot view the original password after you enter it. If for some reason you need to copy the password to another security appliance but do not know the original password, you can enter the enable password command with the encrypted password and this keyword. Normally, you only see this keyword when you enter the show running-config enable command.
level level	(Optional) Sets a password for a privilege level between 0 and 15.
password	Sets the password as a case-sensitive string of up to 16 alphanumeric and special characters. You can use any character in the password except a question mark or a space.

Defaults

The default password is blank. The default level is 15.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The default password for enable level 15 (the default level) is blank. To reset the password to be blank, do not enter any text for the *password*.

For multiple context mode, you can create an enable password for the system configuration as well as for each context.

To use privilege levels other than the default of 15, configure local command authorization (see the **aaa authorization command** command and specify the **LOCAL** keyword), and set the commands to different privilege levels using the **privilege** command. If you do not configure local command authorization, the enable levels are ignored, and you have access to level 15 regardless of the level you set. See the **show curpriv** command to view your current privilege level.

Levels 2 and above enter privileged EXEC mode. Levels 0 and 1 enter user EXEC mode.

Examples

The following example sets the enable password to Pa\$\$w0rd:

```
hostname(config)# enable password Pa$$w0rd
```

The following example sets the enable password to Pa\$\$w0rd10 for level 10:

```
hostname(config)# enable password Pa$$w0rd10 level 10
```

The following example sets the enable password to an encrypted password that you copied from another security appliance:

```
hostname(config)# enable password jMorNbK0514fadBh encrypted
```

Related Commands

Command	Description
aaa authorization command	Configures command authorization.
enable	Enters privileged EXEC mode.
privilege	Sets the command privilege levels for local command authorization.
show curpriv	Shows the currently logged in username and the user privilege level.
show running-config enable	Shows the enable passwords in encrypted form.

enforcenextupdate

To specify how to handle the NextUpdate CRL field, use the **enforcenextupdate** command in ca-crl configuration mode. If set, this command requires CRLs to have a NextUpdate field that has not yet lapsed. If not used, the security appliance allows a missing or lapsed NextUpdate field in a CRL.

To permit a lapsed or missing NextUpdate field, use the **no** form of this command.

enforcenextupdate

no enforcenextupdate

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting is enforced (on).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
CRL configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters ca-crl configuration mode, and requires CRLs to have a NextUpdate field that has not expired for trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# crl configure
hostname(ca-crl)# enforcenextupdate
hostname(ca-crl)#
```

Related Commands

Command	Description
cache-time	Specifies a cache refresh time in minutes.
crl configure	Enters ca-crl configuration mode.
crypto ca trustpoint	Enters trustpoint configuration mode.

enrollment retry count

To specify a retry count, use the **enrollment retry count** command in Crypto ca trustpoint configuration mode. After requesting a certificate, the security appliance waits to receive a certificate from the CA. If the security appliance does not receive a certificate within the configured retry period, it sends another certificate request. The security appliance repeats the request until either it receives a response or reaches the end of the configured retry period.

To restore the default setting of the retry count, use the **no** form of the command.

enrollment retry count *number*

no enrollment retry count

Syntax Description

<i>number</i>	The maximum number of attempts to send an enrollment request. The valid range is 0, 1-100 retries.

Defaults

The default setting for *number* is 0 (unlimited).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is optional and applies only when automatic enrollment is configured.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and configures an enrollment retry count of 20 retries within trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# enrollment retry count 20
hostname(ca-trustpoint)#
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint configuration mode.

Command	Description
default enrollment	Returns enrollment parameters to their defaults.
enrollment retry period	Specifies the number of minutes to wait before resending an enrollment request.

enrollment retry period

To specify a retry period, use the **enrollment retry period** command in `crypto ca trustpoint` configuration mode. After requesting a certificate, the security appliance waits to receive a certificate from the CA. If the security appliance does not receive a certificate within the specified retry period, it sends another certificate request.

To restore the default setting of the retry period, use the **no** form of the command.

enrollment retry period *minutes*

no enrollment retry period

Syntax Description

<i>minutes</i>	The number of minutes between attempts to send an enrollment request. the valid range is 1- 60 minutes.

Defaults

The default setting is 1 minute.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is optional and applies only when automatic enrollment is configured.

Examples

The following example enters `crypto ca trustpoint` configuration mode for `trustpoint central`, and configures an enrollment retry period of 10 minutes within `trustpoint central`:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# enrollment retry period 10
hostname(ca-trustpoint)#
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint configuration mode.
default enrollment	Returns all enrollment parameters to their system default values.
enrollment retry count	Defines the number of retries to requesting an enrollment.

enrollment terminal

To specify cut and paste enrollment with this trustpoint (also known as manual enrollment), use the **enrollment terminal** command in crypto ca trustpoint configuration mode. To restore the default setting of the command, use the **no** form of the command.

enrollment terminal

no enrollment terminal

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting is off.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and specifies the cut and paste method of CA enrollment for trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# enrollment terminal
hostname(ca-trustpoint)#
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint configuration mode.
default enrollment	Returns enrollment parameters to their defaults.
enrollment retry count	Specifies the number of retries to attempt to send an enrollment request.
enrollment retry period	Specifies the number of minutes to wait before resending an enrollment request.
enrollment url	Specifies automatic enrollment (SCEP) with this trustpoint and configures the URL.

enrollment url

To specify automatic enrollment (SCEP) to enroll with this trustpoint and to configure the enrollment URL, use the **enrollment url** command in crypto ca trustpoint configuration mode. To restore the default setting of the command, use the **no** form of the command.

enrollment url *url*

no enrollment url

Syntax Description

<i>url</i>	Specifies the name of the URL for automatic enrollment. The maximum length is 1K characters (effectively unbounded).

Defaults

The default setting is off.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Crypto ca trustpoint configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and specifies SCEP enrollment at the URL https://enrollsite for trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# enrollment url https://enrollsite
hostname(ca-trustpoint)#
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint configuration mode.
default enrollment	Returns enrollment parameters to their defaults.
enrollment retry count	Specifies the number of retries to attempt to send an enrollment request.
enrollment retry period	Specifies the number of minutes to wait before resending an enrollment request.
enrollment terminal	Specifies cut and paste enrollment with this trustpoint.

erase

To erase and reformat the file system, use the **erase** command in privileged EXEC mode. This command overwrites all files and erases the file system, including hidden system files, and then reinstalls the file system.

erase [**disk0:** | **disk1:** | **flash:**]

Syntax Description

disk0:	(Optional) Specifies the internal Flash memory, followed by a colon.
disk1:	(Optional) Specifies the external, compact Flash memory card, followed by a colon.
flash:	(Optional) Specifies the internal Flash memory, followed by a colon.



Caution

Erasing the Flash memory also removes the licensing information, which is stored in Flash memory. Save the licensing information prior to erasing the Flash memory.

In the ASA 5500 series, the **flash** keyword is aliased to **disk0**.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **erase** command erases all data on the Flash memory using the 0xFF pattern and then rewrites an empty file system allocation table to the device.

To delete all visible files (excluding hidden system files), enter the **delete /recursive** command, instead of the **erase** command.



Note

On Cisco ASA 5500 series security appliances, the **erase** command destroys all user data on the disk with the 0xFF pattern. In contrast, the **format** command only resets the file system control structures. If you used a raw disk read tool, you could still see the information.

Examples

The following example erases and reformats the file system:

```
hostname# erase flash:
```

Related Commands

Command	Description
delete	Removes all visible files, excluding hidden system files.
format	Erases all files (including hidden system files) and formats the file system.

established

To permit return connections on ports that are based on an established connection, use the **established** command in global configuration mode. To disable the **established** feature, use the **no** form of this command.

established *est_protocol dport [sport] [permitto protocol port [-port]] [permitfrom protocol port[-port]]*

no established *est_protocol dport [sport] [permitto protocol port [-port]] [permitfrom protocol port[-port]]*

Syntax Description

<i>est_protocol</i>	Specifies the IP protocol (UDP or TCP) to use for the established connection lookup.
<i>dport</i>	Specifies the destination port to use for the established connection lookup.
permitfrom	(Optional) Allows the return protocol connection(s) originating from the specified port.
permitto	(Optional) Allows the return protocol connections destined to the specified port.
<i>port [-port]</i>	(Optional) Specifies the (UDP or TCP) destination port(s) of the return connection.
<i>protocol</i>	(Optional) IP protocol (UDP or TCP) used by the return connection.
<i>sport</i>	(Optional) Specifies the source port to use for the established connection lookup.

Defaults

The defaults are as follows:

- *dport*—0 (wildcard)
- *sport*—0 (wildcard)

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	The keywords to and from were removed from the CLI. Use the keywords permitto and permitfrom instead.

Usage Guidelines

The **established** command lets you permit return access for outbound connections through the security appliance. This command works with an original connection that is outbound from a network and protected by the security appliance and a return connection that is inbound between the same two devices on an external host. The **established** command lets you specify the destination port that is used for

connection lookups. This addition allows more control over the command and provides support for protocols where the destination port is known, but the source port is unknown. The **permitto** and **permitfrom** keywords define the return inbound connection.



Caution

We recommend that you always specify the **established** command with the **permitto** and **permitfrom** keywords. Using the **established** command without these keywords is a security risk because when connections are made to external systems, those system can make unrestricted connections to the internal host involved in the connection. This situation can be exploited for an attack of your internal systems.

The following potential security violations could occur if you do not use the **established** command correctly.

This example shows that if an internal system makes a TCP connection to an external host on port 4000, then the external host could come back in on any port using any protocol:

```
hostname(config)# established tcp 0 4000
```

You can specify the source and destination ports as **0** if the protocol does not specify which ports are used. Use wildcard ports (0) only when necessary.

```
hostname(config)# established tcp 0 0
```



Note

To allow the **established** command to work properly, the client must listen on the port that is specified with the **permitto** keyword.

You can use the **established** command with the **nat 0** command (where there are no **global** commands).



Note

You cannot use the **established** command with PAT.

The security appliance supports XDMCP with assistance from the **established** command.



Caution

Using XWindows system applications through the security appliance may cause security risks.

XDMCP is on by default, but it does not complete the session unless you enter the **established** command as follows:

```
hostname(config)# established tcp 0 6000 to tcp 6000 from tcp 1024-65535
```

Entering the **established** command enables the internal XDMCP-equipped (UNIX or ReflectionX) hosts to access external XDMCP-equipped XWindows servers. UDP/177-based XDMCP negotiates a TCP-based XWindows session, and subsequent TCP back connections are permitted. Because the source port(s) of the return traffic is unknown, specify the *sport* field as 0 (wildcard). The *dport* should be 6000 + *n*, where *n* represents the local display number. Use this UNIX command to change this value:

```
hostname(config)# setenv DISPLAY hostname:displaynumber.screennumber
```

The **established** command is needed because many TCP connections are generated (based on user interaction) and the source port for these connections is unknown. Only the destination port is static. The security appliance performs XDMCP fixups transparently. No configuration is required, but you must enter the **established** command to accommodate the TCP session.

Examples

This example shows a connection between two hosts using protocol A from the SRC port B destined for port C. To permit return connections through the security appliance and protocol D (protocol D can be different from protocol A), the source port(s) must correspond to port F and the destination port(s) must correspond to port E.

```
hostname(config)# established A B C permitto D E permitfrom D F
```

This example shows how a connection is started by an internal host to an external host using TCP source port 6060 and any destination port. The security appliance permits return traffic between the hosts through TCP destination port 6061 and TCP source port 6059.

```
hostname(config)# established tcp 6060 0 permitto tcp 6061 permitfrom tcp 6059
```

This example shows how a connection is started by an internal host to an external host using UDP destination port 6060 and any source port. The security appliance permits return traffic between the hosts through TCP destination port 6061 and TCP source port 1024-65535.

```
hostname(config)# established udp 0 6060 permitto tcp 6061 permitfrom tcp 1024-65535
```

This example shows how a local host 10.1.1.1 starts a TCP connection on port 9999 to a foreign host 209.165.201.1. The example allows packets from the foreign host 209.165.201.1 on port 4242 back to local host 10.1.1.1 on port 5454.

```
hostname(config)# established tcp 9999 permitto tcp 5454 permitfrom tcp 4242
```

This example shows how to allow packets from foreign host 209.165.201.1 on any port back to local host 10.1.1.1 on port 5454:

```
hostname(config)# established tcp 9999 permitto tcp 5454
```

Related Commands

Command	Description
clear configure established	Removes all established commands.
show running-config established	Displays the allowed inbound connections that are based on established connections.

exceed-mss

To allow or drop packets whose data length exceeds the TCP maximum segment size set by the peer during a three-way handshake, use the **exceed-mss** command in tcp-map configuration mode. To remove this specification, use the **no** form of this command.

exceed-mss {allow | drop}

no exceed-mss {allow | drop}

Syntax Description

allow	Allows packets that exceed the MSS.
drop	Drops packets that exceed the MSS.

Defaults

Packets are dropped by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tcp-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **tcp-map** command is used along with the Modular Policy Framework infrastructure. Define the class of traffic using the **class-map** command and customize the TCP inspection with **tcp-map** commands. Apply the new TCP map using the **policy-map** command. Activate TCP inspection with **service-policy** commands.

Use the **tcp-map** command to enter tcp-map configuration mode. Use the **exceed-mss** command in tcp-map configuration mode to drop TCP packets whose data length exceed the TCP maximum segment size set by the peer during a three-way handshake.

Examples

The following example allows flows on port 21 to send packets in excess of MSS:

```
hostname(config)# tcp-map tmap
hostname(config-tcp-map)# exceed-mss allow
hostname(config)# class-map cmap
hostname(config-cmap)# match port tcp eq ftp
hostname(config)# policy-map pmap
hostname(config-pmap)# class cmap
hostname(config-pmap)# set connection advanced-options tmap
hostname(config)# service-policy pmap global
```

Related Commands	Command	Description
	class	Specifies a class map to use for traffic classification.
	help	Shows syntax help for the policy-map , class , and description commands.
	policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
	set connection	Configures connection values.
	tcp-map	Creates a TCP map and allows access to tcp-map configuration mode.

exit

To exit the current configuration mode, or to logout from privileged or user EXEC modes, use the **exit** command.

exit

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

You can also use the key sequence **Ctrl Z** to exit global configuration (and higher) modes. This key sequence does not work with privileged or user EXEC modes.

When you enter the **exit** command in privileged or user EXEC modes, you log out from the security appliance. Use the **disable** command to return to user EXEC mode from privileged EXEC mode.

Examples

The following example shows how to use the **exit** command to exit global configuration mode, and then logout from the session:

```
hostname(config)# exit
hostname# exit

Logoff
```

The following example shows how to use the **exit** command to exit global configuration mode, and then use the **disable** command to exit privileged EXEC mode:

```
hostname(config)# exit
hostname# disable
hostname>
```

Related Commands

Command	Description
quit	Exits a configuration mode or logs out from privileged or user EXEC modes.

failover

To enable failover, use the **failover** command in global configuration mode. To disable failover, use the **no** form of this command.

failover

no failover

Syntax Description

This command has no arguments or keywords.

Defaults

Failover is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was limited to enable or disable failover in the configuration (see the failover active command).

Usage Guidelines

Use the **no** form of this command to disable failover.



Caution

All information sent over the failover and Stateful Failover links is sent in clear text unless you secure the communication with a failover key. If the security appliance is used to terminate VPN tunnels, this information includes any usernames, passwords and preshared keys used for establishing the tunnels. Transmitting this sensitive data in clear text could pose a significant security risk. We recommend securing the failover communication with a failover key if you are using the security appliance to terminate VPN tunnels.

Examples

The following example disables failover:

```
hostname(config)# no failover
hostname(config)#
```


Related Commands	Command	Description
	clear configure failover	Clears failover commands from the running configuration and restores failover default values.
	failover active	Switches the standby unit to active.
	show failover	Displays information about the failover status of the unit.
	show running-config failover	Displays the failover commands in the running configuration.

failover active

To switch a standby security appliance or failover group to the active state, use the **failover active** command in privileged EXEC mode. To switch an active security appliance or failover group to standby, use the **no** form of this command.

failover active [**group** *group_id*]

no failover active [**group** *group_id*]

Syntax Description

group *group_id* (Optional) Specifies the failover group to make active.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was modified to include failover groups.

Usage Guidelines

Use the **failover active** command to initiate a failover switch from the standby unit, or use the **no failover active** command from the active unit to initiate a failover switch. You can use this feature to return a failed unit to service, or to force an active unit offline for maintenance. If you are not using stateful failover, all active connections are dropped and must be reestablished by the clients after the failover occurs.

Switching for a failover group is available only for Active/Active failover. If you enter the **failover active** command on an Active/Active failover unit without specifying a failover group, all groups on the unit become active.

Examples

The following example switches the standby group 1 to active:

```
hostname# failover active group 1
```

Related Commands

Command	Description
failover reset	Moves a security appliance from a failed state to standby.

failover group

To configure an Active/Active failover group, use the **failover group** command in global configuration mode. To remove a failover group, use the **no** form of this command.

failover group *num*

no failover group *num*

Syntax Description

num Failover group number. Valid values are 1 or 2.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can define a maximum of 2 failover groups. The **failover group** command can only be added to the system context of devices configured for multiple context mode. You can create and remove failover groups only when failover is disabled.

Entering this command puts you in the failover group command mode. The **primary**, **secondary**, **preempt**, **replication http**, **interface-policy**, **mac address**, and **polltime interface** commands are available in the failover group configuration mode. Use the **exit** command to return to global configuration mode.



Note

The **failover polltime interface**, **failover interface-policy**, **failover replication http**, and **failover mac address** commands have no effect in Active/Active failover configurations. They are overridden by the following failover group configuration mode commands: **polltime interface**, **interface-policy**, **replication http**, and **mac address**.

When removing failover groups, you must remove failover group 1 last. Failover group 1 always contains the admin context. Any context not assigned to a failover group defaults to failover group 1. You cannot remove a failover group that has contexts explicitly assigned to it.

**Note**

If you have more than one Active/Active failover pair on the same network, it is possible to have the same default virtual MAC addresses assigned to the interfaces on one pair as are assigned to the interfaces of the other pairs because of the way the default virtual MAC addresses are determined. To avoid having duplicate MAC addresses on your network, make sure you assign each physical interface a virtual active and standby MAC address using the **mac address** command.

Examples

The following partial example shows a possible configuration for two failover groups:

```
hostname(config)# failover group 1
hostname(config-fover-group)# primary
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# exit
hostname(config)# failover group 2
hostname(config-fover-group)# secondary
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# exit
hostname(config)#
```

Related Commands

Command	Description
asr-group	Specifies an asymmetrical routing interface group ID.
interface-policy	Specifies the failover policy when monitoring detects interface failures.
join-failover-group	Assigns a context to a failover group.
mac address	Defines virtual mac addresses for the contexts within a failover group.
polltime interface	Specifies the amount of time between hello messages sent to monitored interfaces.
preempt	Specifies that a unit with a higher priority becomes the active unit after a reboot.
primary	Gives the primary unit higher priority for a failover group.
replication http	Specifies HTTP session replication for the selected failover group.
secondary	Gives the secondary unit higher priority for a failover group.

failover interface ip

To specify the IP address and mask for the failover interface and the Stateful Failover interface, use the **failover interface ip** command in global configuration mode. To remove the IP address, use the **no** form of this command.

failover interface ip *if_name ip_address mask standby ip_address*

no failover interface ip *if_name ip_address mask standby ip_address*

Syntax Description

<i>if_name</i>	Interface name for the failover or stateful failover interface.
<i>ip_address mask</i>	Specifies the IP address and mask for the failover or stateful failover interface on the primary module.
standby <i>ip_address</i>	Specifies the IP address used by the secondary module to communicate with the primary module.

Defaults

Not configured.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Failover and stateful failover interfaces are functions of Layer 3, even when the security appliance is operating in transparent firewall mode, and are global to the system.

In multiple context mode, you configure failover in the system context (except for the **monitor-interface** command).

This command must be part of the configuration when bootstrapping a security appliance for LAN failover.

Examples

The following example shows how to specify the IP address and mask for the failover interface:

```
hostname(config)# failover interface ip lanlink 172.27.48.1 255.255.255.0 standby
172.27.48.2
```

Related Commands

Command	Description
clear configure failover	Clears failover commands from the running configuration and restores failover default values.
failover lan interface	Specifies the interface used for failover communication.
failover link	Specifies the interface used for Stateful Failover.
monitor-interface	Monitors the health of the specified interface.
show running-config failover	Displays the failover commands in the running configuration.

failover interface-policy

To specify the policy for failover when monitoring detects an interface failure, use the **failover interface-policy** command in global configuration mode. To restore the default, use the **no** form of this command.

failover interface-policy *num*[%]

no failover interface-policy *num*[%]

Syntax Description

<i>num</i>	Specifies a number from 1 to 100 when used as a percentage, or 1 to the maximum number of interfaces when used as a number.
%	(Optional) Specifies that the number <i>num</i> is a percentage of the monitored interfaces.

Defaults

The defaults are as follows:

- num* is 1.
- Monitoring of physical interfaces is enabled by default; monitoring of logical interfaces is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

There is no space between the *num* argument and the optional % keyword.

If the number of failed interfaces meets the configured policy and the other security appliance is functioning properly, the security appliance will mark itself as failed and a failover may occur (if the active security appliance is the one that fails). Only interfaces that are designated as monitored by the **monitor-interface** command count towards the policy.



Note

This command applies to Active/Standby failover only. In Active/Active failover, you configure the interface policy for each failover group with the **interface-policy** command in failover group configuration mode.

Examples

The following examples show two ways to specify the failover policy:

```
hostname(config)# failover interface-policy 20%
```

```
hostname(config)# failover interface-policy 5
```

Related Commands

Command	Description
failover polltime	Specifies the unit and interface poll times.
failover reset	Restores a failed unit to an unfailed state.
monitor-interface	Specifies the interfaces being monitored for failover.
show failover	Displays information about the failover state of the unit.

failover key

To specify the key for encrypted and authenticated communication between units in a failover pair, use the **failover key** command in global configuration mode. To remove the key, use the **no** form of this command.

failover key {*secret* | *hex key*}

no failover key

Syntax Description

hex key	Specifies a hexadecimal value for the encryption key. The key must be 32 hexadecimal characters (0-9, a-f).
secret	Specifies an alphanumeric shared secret. The secret can be from 1 to 63 characters. Valid character are any combination of numbers, letters, or punctuation. The shared secret is used to generate the encryption key.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0(1)	This command was modified from failover lan key to failover key .
7.0(4)	This command was modified to include the hex key keyword and argument.

Usage Guidelines

To encrypt and authenticate failover communications between the units, you must configure both units with a shared secret or hexadecimal key. If you do not specify a failover key, failover communication is transmitted in the clear.



Note

On the PIX security appliance platform, if you are using the dedicated serial failover cable to connect the units, then communication over the failover link is not encrypted even if a failover key is configured. The failover key only encrypts LAN-based failover communication.



Caution

All information sent over the failover and Stateful Failover links is sent in clear text unless you secure the communication with a failover key. If the security appliance is used to terminate VPN tunnels, this information includes any user names, passwords and preshared keys used for establishing the tunnels.

Transmitting this sensitive data in clear text could pose a significant security risk. We recommend securing the failover communication with a failover key if you are using the security appliance to terminate VPN tunnels.

Examples

The following example shows how to specify a shared secret for securing failover communication between units in a failover pair:

```
hostname(config)# failover key abcdefg
```

The following example shows how to specify a hexadecimal key for securing failover communication between two units in a failover pair:

```
hostname(config)# failover key hex 6a1ed228381cf5c68557cb0c32e614dc
```

Related Commands

Command	Description
show running-config failover	Displays the failover commands in the running configuration.

failover lan enable

To enable lan-based failover on the PIX security appliance, use the **failover lan enable** command in global configuration mode. To disable LAN-based failover, use the **no** form of this command.

failover lan enable

no failover lan enable

Syntax Description This command has no arguments or keywords.

Defaults Not enabled.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	•

Release	Modification
Preexisting	This command was preexisting.

Command History

Usage Guidelines When LAN-based failover is disabled using the **no** form of this command, cable-based failover is used if the failover cable is installed. This command is available on the PIX security appliance only.



Caution

All information sent over the failover and Stateful Failover links is sent in clear text unless you secure the communication with a failover key. If the security appliance is used to terminate VPN tunnels, this information includes any usernames, passwords and preshared keys used for establishing the tunnels. Transmitting this sensitive data in clear text could pose a significant security risk. We recommend securing the failover communication with a failover key if you are using the security appliance to terminate VPN tunnels.

Examples The following example enables LAN-based failover:

```
hostname(config)# failover lan enable
```

Related Commands	Command	Description
	failover lan interface	Specifies the interface used for failover communication.
	failover lan unit	Specifies the LAN-based failover primary or secondary unit.
	show failover	Displays information about the failover status of the unit.
	show running-config failover	Displays the failover commands in the running configuration.

failover lan interface

To specify the interface used for failover communication, use the **failover lan interface** command in global configuration mode. To remove the failover interface, use the **no** form of this command.

failover lan interface *if_name phy_if*

no failover lan interface *if_name phy_if*

Syntax Description

<i>if_name</i>	Specifies the name of the security appliance interface dedicated to failover.
<i>phy_if</i>	Specifies the physical or logical interface port.

Defaults

Not configured.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was modified to include the <i>phy_if</i> argument.

Usage Guidelines

LAN failover requires a dedicated interface for passing failover traffic. However you can also use the LAN failover interface for the Stateful Failover link.



Note

If you use the same interface for both LAN failover and Stateful Failover, the interface needs enough capacity to handle both the LAN-based failover and Stateful Failover traffic.

You can use any unused Ethernet interface on the device as the failover interface. You cannot specify an interface that is currently configured with a name. The failover interface is not configured as a normal networking interface; it exists only for failover communications. This interface should only be used for the failover link (and optionally for the state link). You can connect the LAN-based failover link by using a dedicated switch with no hosts or routers on the link or by using a crossover Ethernet cable to link the units directly.



Note

When using VLANs, use a dedicated VLAN for the failover link. Sharing the failover link VLAN with any other VLANs can cause intermittent traffic problems and ping and ARP failures. If you use a switch to connect the failover link, use dedicated interfaces on the switch and security appliance for the failover link; do not share the interface with subinterfaces carrying regular network traffic.

On systems running in multiple context mode, the failover link resides in the system context. This interface and the state link, if used, are the only interfaces that you can configure in the system context. All other interfaces are allocated to and configured from within security contexts.

**Note**

The IP address and MAC address for the failover link do not change at failover.

The **no** form of this command also clears the failover interface IP address configuration.

This command must be part of the configuration when bootstrapping a security appliance for LAN failover.

Examples

The following example configures the failover LAN interface:

```
hostname(config)# failover lan interface folink e4
```

Related Commands

Command	Description
failover lan enable	Enables LAN-based failover on the PIX security appliance.
failover lan unit	Specifies the LAN-based failover primary or secondary unit.
failover link	Specifies the Stateful Failover interface.

failover lan unit

To configure the security appliance as either the primary or secondary unit in a LAN failover configuration, use the **failover lan unit** command in global configuration mode. To restore the default setting, use the **no** form of this command.

failover lan unit {primary | secondary}

no failover lan unit {primary | secondary}

Syntax Description

primary	Specifies the security appliance as a primary unit.
secondary	Specifies the security appliance as a secondary unit.

Defaults

Secondary.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

For Active/Standby failover, the primary and secondary designation for the failover unit refers to which unit becomes active at boot time. The primary unit becomes the active unit at boot time when the following occurs:

- The primary and secondary unit both complete their boot sequence within the first failover poll check.
- The primary unit boots before the secondary unit.

If the secondary unit is already active when the primary unit boots, the primary unit does not take control; it becomes the standby unit. In this case, you need to issue the **no failover active** command on the secondary (active) unit to force the primary unit back to active status.

For Active/Active failover, each failover group is assigned a primary or secondary unit preference. This preference determines on which unit in the failover pair the contexts in the failover group become active at startup when both units start simultaneously (within the failover polling period).

This command must be part of the configuration when bootstrapping a security appliance for LAN failover.

Examples

The following example sets the security appliance as the primary unit in LAN-based failover:

```
hostname(config)# failover lan unit primary
```

Related Commands

Command	Description
failover lan enable	Enables LAN-based failover on the PIX security appliance.
failover lan interface	Specifies the interface used for failover communication.

failover link

To specify the Stateful Failover interface, use the **failover link** command in global configuration mode. To remove the Stateful Failover interface, use the **no** form of this command.

failover link *if_name* [*phy_if*]

no failover link

Syntax Description

<i>if_name</i>	Specifies the name of the security appliance interface dedicated to Stateful Failover.
<i>phy_if</i>	(Optional) Specifies the physical or logical interface port. If the Stateful Failover interface is sharing the interface assigned for failover communication or sharing a standard firewall interface, then this argument is not required.

Defaults

Not configured.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was modified to include the <i>phy_if</i> argument.
7.0(4)	This command was modified to accept standard firewall interfaces.

Usage Guidelines

The physical or logical interface argument is required when not sharing the failover communication or a standard firewall interface.

The **failover link** command enables Stateful Failover. Enter the **no failover link** command to disable Stateful Failover. If you are using a dedicated Stateful Failover interface, the **no failover link** command also clears the Stateful Failover interface IP address configuration.

To use Stateful Failover, you must configure a Stateful Failover link to pass all state information. You have three options for configuring a Stateful Failover link:

- You can use a dedicated Ethernet interface for the Stateful Failover link.
- If you are using LAN-based failover, you can share the failover link.
- You can share a regular data interface, such as the inside interface. However, this option is not recommended.

If you are using a dedicated Ethernet interface for the Stateful Failover link, you can use either a switch or a crossover cable to directly connect the units. If you use a switch, no other hosts or routers should be on this link.

**Note**

Enable the PortFast option on Cisco switch ports that connect directly to the security appliance.

If you are using the failover link as the Stateful Failover link, you should use the fastest Ethernet interface available. If you experience performance problems on that interface, consider dedicating a separate interface for the Stateful Failover interface.

If you use a data interface as the Stateful Failover link, you will receive the following warning when you specify that interface as the Stateful Failover link:

```
***** WARNING ***** WARNING ***** WARNING ***** WARNING *****
Sharing Stateful failover interface with regular data interface is not
a recommended configuration due to performance and security concerns.
***** WARNING ***** WARNING ***** WARNING ***** WARNING *****
```

Sharing a data interface with the Stateful Failover interface can leave you vulnerable to replay attacks. Additionally, large amounts of Stateful Failover traffic may be sent on the interface, causing performance problems on that network segment.

**Note**

Using a data interface as the Stateful Failover interface is only supported in single context, routed mode.

In multiple context mode, the Stateful Failover link resides in the system context. This interface and the failover interface are the only interfaces in the system context. All other interfaces are allocated to and configured from within security contexts.

In multiple context mode, the Stateful Failover interface resides in the system context. This interface and the failover interface are the only interfaces in the system context. All other interfaces are allocated to and configured from within security contexts.

**Note**

The IP address and MAC address for the Stateful Failover link does not change at failover unless the Stateful Failover link is configured on a regular data interface.

**Caution**

All information sent over the failover and Stateful Failover links is sent in clear text unless you secure the communication with a failover key. If the security appliance is used to terminate VPN tunnels, this information includes any user names, passwords and preshared keys used for establishing the tunnels. Transmitting this sensitive data in clear text could pose a significant security risk. We recommend securing the failover communication with a failover key if you are using the security appliance to terminate VPN tunnels.

Examples

The following example shows how to specify a dedicated interface as the Stateful Failover interface. The interface in the example does not have an existing configuration.

```
hostname(config)# failover link stateful if e4
INFO: Non-failover interface config is cleared on Ethernet4 and its sub-interfaces
```

Related Commands

Command	Description
failover interface ip	Configures the IP address of the failover command and stateful failover interface.
failover lan interface	Specifies the interface used for failover communication.
mtu	Specifies the maximum transmission unit for an interface.

failover mac address

To specify the failover virtual MAC address for a physical interface, use the **failover mac address** command in global configuration mode. To remove the virtual MAC address, use the **no** form of this command.

failover mac address *phy_if active_mac standby_mac*

no failover mac address *phy_if active_mac standby_mac*

Syntax Description

<i>phy_if</i>	The physical name of the interface to set the MAC address.
<i>active_mac</i>	The MAC address assigned to the specified interface the active security appliance. The MAC address must be entered in h.h.h format, where h is a 16-bit hexadecimal number.
<i>standby_mac</i>	The MAC address assigned to the specified interface of the standby security appliance. The MAC address must be entered in h.h.h format, where h is a 16-bit hexadecimal number.

Defaults

Not configured.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **failover mac address** command lets you configure virtual MAC addresses for an Active/Standby failover pair. If virtual MAC addresses are not defined, then when each failover unit boots it uses the burned-in MAC addresses for its interfaces and exchanges those addresses with its failover peer. The MAC addresses for the interfaces on the primary unit are used for the interfaces on the active unit.

However, if both units are not brought online at the same time and the secondary unit boots first and becomes active, it uses the burned-in MAC addresses for its own interfaces. When the primary unit comes online, the secondary unit will obtain the MAC addresses from the primary unit. This change can disrupt network traffic. Configuring virtual MAC addresses for the interfaces ensures that the secondary unit uses the correct MAC address when it is the active unit, even if it comes online before the primary unit.

The **failover mac address** command is unnecessary (and therefore cannot be used) on an interface configured for LAN-based failover because the **failover lan interface** command does not change the IP and MAC addresses when failover occurs. This command has no effect when the security appliance is configured for Active/Active failover.

When adding the **failover mac address** command to your configuration, it is best to configure the virtual MAC address, save the configuration to Flash memory, and then reload the failover pair. If the virtual MAC address is added when there are active connections, then those connections stop. Also, you must write the complete configuration, including the **failover mac address** command, to the Flash memory of the secondary security appliance for the virtual MAC addressing to take effect.

If the **failover mac address** is specified in the configuration of the primary unit, it should also be specified in the bootstrap configuration of the secondary unit.

**Note**

This command applies to Active/Standby failover only. In Active/Active failover, you configure the virtual MAC address for each interface in a failover group with the **mac address** command in failover group configuration mode.

Examples

The following example configures the active and standby MAC addresses for the interface named intf2:

```
hostname(config)# failover mac address Ethernet0/2 00a0.c969.87c8 00a0.c918.95d8
```

Related Commands

Command	Description
show interface	Displays interface status, configuration, and statistics.

failover polltime

To specify the failover unit and interface poll times and unit hold time, use the **failover polltime** command in global configuration mode. To restore the default poll time, use the **no** form of this command.

failover polltime [**unit**] [**msec**] *time* [**holdtime** *time*]

failover polltime interface *time*

no failover polltime [**unit**] [**msec**] *time* [**holdtime** *time*]

no failover polltime interface *time*

Syntax Description

holdtime <i>time</i>	(Optional) Sets the time during which a unit must receive a hello message on the failover link, after which the peer unit is declared failed. Valid values range from 3 to 45 seconds.
interface <i>time</i>	Specifies the poll time for interface monitoring. Valid values range from 3 to 15 seconds.
msec	(Optional) Specifies that the time interval between messages is in milliseconds. The minimum value is 500 milliseconds.
time	Amount of time between hello messages. The maximum value is 15 seconds.
unit	(Optional) Sets how often hello messages are sent on the failover link.

Defaults

The defaults are as follows:

- The **unit** poll *time* on the security appliance is 1 second.
- The **interface** poll *time* is 15 seconds.
- The **holdtime** *time* is 45 seconds (3 times the poll time).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was changed from the failover poll command to the failover polltime command and now includes unit , interface , and holdtime keywords.

Usage Guidelines

You cannot enter a **holdtime** value that is less than 3 times the unit poll time. With a faster poll time, the security appliance can detect failure and trigger failover faster. However, faster detection can cause unnecessary switchovers when the network is temporarily congested.

When the **unit** or **interface** keywords are not specified, the poll time configured is for the unit.

You can include both **failover polltime unit** and **failover polltime interface** commands in the configuration.



Note

The **failover polltime interface** command applies to Active/Standby failover only. For Active/Active failover, use the **polltime interface** command in failover group configuration mode instead of the **failover polltime interface** command.

If a hello packet is not heard on the failover communication interface or cable during the hold time, the standby unit switches to active and the peer is considered failed. Five missed consecutive interface hello packets cause interface testing.



Note

When CTIQBE traffic is passed through a security appliance in a failover configuration, you should decrease the failover hold time on the security appliance to below 30 seconds. The CTIQBE keepalive timeout is 30 seconds and may time out before failover occurs in a failover situation. If CTIQBE times out, Cisco IP SoftPhone connections to the Cisco Call Manager are dropped, and the IP SoftPhone clients will need to reregister with the Call Manager.

Examples

The following example sets the unit poll time frequency to 3 seconds:

```
hostname(config)# failover polltime 3
```

Related Commands

Command	Description
polltime interface	Specify the interface polltime for Active/Active failover configurations.
show failover	Displays failover configuration information.

failover reload-standby

To force the standby unit to reboot, use the **failover reload-standby** command in privileged EXEC mode.

failover reload-standby

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Release	Modification
7.0	This command was introduced.

Usage Guidelines Use this command when your failover units do not synchronize. The standby unit restarts and resynchronizes to the active unit after it finishes booting.

Examples The following example shows how to use the **failover reload-standby** command on the active unit to force the standby unit to reboot:

```
hostname# failover reload-standby
```

Command	Description
write standby	Writes the running configuration to the memory on the standby unit.

failover replication http

To enable HTTP (port 80) connection replication, use the **failover replication http** command in global configuration mode. To disable HTTP connection replication, use the **no** form of this command.

failover replication http

no failover replication http

Syntax Description This command has no arguments or keywords.

Defaults Disabled.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History	Release	Modification
	Preexisting	This command was changed from failover replicate http to failover replication http .

Usage Guidelines By default, the security appliance does not replicate HTTP session information when Stateful Failover is enabled. Because HTTP sessions are typically short-lived, and because HTTP clients typically retry failed connection attempts, not replicating HTTP sessions increases system performance without causing serious data or connection loss. The **failover replication http** command enables the stateful replication of HTTP sessions in a Stateful Failover environment, but could have a negative effect on system performance.

In Active/Active failover configurations, you control HTTP session replication per failover group using the **replication http** command in failover group configuration mode.

Examples The following example shows how to enable HTTP connection replication:

```
hostname(config)# failover replication http
```

Related Commands	Command	Description
	replication http	Enables HTTP session replication for a specific failover group.
	show running-config failover	Displays the failover commands in the running configuration.

failover reset

To restore a failed security appliance to an unfailed state, use the **failover reset** command in privileged EXEC mode.

failover reset [**group** *group_id*]

Syntax Description

group	(Optional) Specifies a failover group.
<i>group_id</i>	Failover group number.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was modified to allow the optional failover group ID.

Usage Guidelines

The **failover reset** command allows you to change the failed unit or group to an unfailed state. The **failover reset** command can be entered on either unit, but we recommend that you always enter the command on the active unit. Entering the **failover reset** command at the active unit will “unfail” the standby unit.

You can display the failover status of the unit with the **show failover** or **show failover state** commands.

There is no **no** version of this command.

In Active/Active failover, entering **failover reset** resets the whole unit. Specifying a failover group with the command resets only the specified group.

Examples

The following example shows how to change a failed unit to an unfailed state:

```
hostname# failover reset
```

Related Commands

Command	Description
failover interface-policy	Specifies the policy for failover when monitoring detects interface failures.
show failover	Displays information about the failover status of the unit.

failover timeout

To specify the failover reconnect timeout value for asymmetrically routed sessions, use the **failover timeout** command in global configuration mode. To restore the default timeout value, use the **no** form of this command.

failover timeout *hh[:mm][:ss]*

no failover timeout [*hh[:mm][:ss]*]

Syntax Description

<i>hh</i>	Specifies the number of hours in the timeout value. Valid values range from -1 to 1193. By default, this value is set to 0. Setting this value to -1 disables the timeout, allowing connections to reconnect after any amount of time. Setting this value to 0, without specifying any of the other timeout values, sets the command back to the default value, which prevents connections from reconnecting. Entering no failover timeout command also sets this value to the default (0). Note When set to the default value, this command does not appear in the running configuration.
<i>mm</i>	(Optional) Specifies the number of minutes in the timeout value. Valid values range from 0 to 59. By default, this value is set to 0.
<i>ss</i>	(Optional) Specifies the number of seconds in the timeout value. Valid values range from 0 to 59. By default, this value is set to 0.

Defaults

By default, *hh*, *mm*, and *ss* are 0, which prevents connections from reconnecting.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was modified to appear in the command listing.

Usage Guidelines

This command is used in conjunction with the **static** command with the **nailed** option. The **nailed** option allows connections to be reestablished in a specified amount of time after bootup or a system goes active. The **failover timeout** command specifies that amount of time. If not configured, the connections cannot be reestablished. The **failover timeout** command does not affect the **asr-group** command.

**Note**

Adding the **nailed** option to the **static** command causes TCP state tracking and sequence checking to be skipped for the connection.

Enter the **no** form of this command restores the default value. Entering **failover timeout 0** also restores the default value. When set to the default value, this command does not appear in the running configuration.

Examples

The following example switches the standby group 1 to active:

```
hostname(config)# failover timeout 12:30
hostname(config)# show running-config failover
no failover
failover timeout 12:30:00
```

Related Commands

Command	Description
static	Configures a persistent one-to-one address translation rule by mapping a local IP address to a global IP address.

filter

To specify the name of the access list to use for WebVPN connections for this group policy or username, use the **filter** command in webvpn mode. To remove the access list, including a null value created by issuing the **filter none** command, use the **no** form of this command. The **no** option allows inheritance of a value from another group policy. To prevent inheriting filter values, use the **filter value none** command.

You configure ACLs to permit or deny various types of traffic for this user or group policy. You then use the **filter** command to apply those ACLs for WebVPN traffic.

filter { *value ACLname* | **none** }

no filter

Syntax Description

none	Indicates that there is no webvpntype access list. Sets a null value, thereby disallowing an access list. Prevents inheriting an access list from another group policy.
value <i>ACLname</i>	Provides the name of the previously configured access list.

Defaults

WebVPN access lists do not apply until you use the **filter** command to specify them.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn mode	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

WebVPN does not use ACLs defined in the **vpn-filter** command.

Examples

The following example shows how to set a filter that invokes an access list named *acl_in* for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# webvpn
hostname(config-group-webvpn)# filter acl_in
```

Related Commands	Command	Description
	access-list	Creates an access list, or uses a downloadable access list.
	webvpn	Use in group-policy configuration mode or in username configuration mode. Lets you enter webvpn mode to configure parameters that apply to group policies or usernames.
	webvpn	Use in global configuration mode. Lets you configure global settings for WebVPN.

filter activex

To remove ActiveX objects in HTTP traffic passing through the security appliance, use the **filter activex** command in global configuration mode. To remove the configuration, use the **no** form of this command.

filter activex {[*port*[-*port*] | **except** } *local_ip* *local_mask* *foreign_ip* *foreign_mask*]

no filter activex {[*port*[-*port*] | **except** } *local_ip* *local_mask* *foreign_ip* *foreign_mask*]

Syntax Description

<i>port</i>	The TCP port to which filtering is applied. Typically, this is port 21, but other values are accepted. The http or url literal can be used for port 21. The range of values permitted is 0 to 65535. For a listing of the well-known ports and their literal values, see
<i>port-port</i>	(Optional) Specifies a port range.
except	Creates an exception to a previous filter condition.
<i>local_ip</i>	The IP address of the highest security level interface from which access is sought. You can set this address to 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>local_mask</i>	Network mask of <i>local_ip</i> . You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>foreign_ip</i>	The IP address of the lowest security level interface to which access is sought. You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>foreign_mask</i>	Network mask of <i>foreign_ip</i> . Always specify a specific mask value. You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

ActiveX objects may pose security risks because they can contain code intended to attack hosts and servers on a protected network. You can disable ActiveX objects with the **filter activex** command.

ActiveX controls, formerly known as OLE or OCX controls, are components you can insert in a web page or other application. These controls include custom forms, calendars, or any of the extensive third-party forms for gathering or displaying information. As a technology, ActiveX creates many potential problems for network clients including causing workstations to fail, introducing network security problems, or being used to attack servers.

The **filteractivex** command blocks the HTML <object> commands by commenting them out within the HTML web page. ActiveX filtering of HTML files is performed by selectively replacing the <APPLET> and </APPLET> and <OBJECT CLASSID> and </OBJECT> tags with comments. Filtering of nested tags is supported by converting top-level tags to comments.



Caution

The <object> tag is also used for Java applets, image files, and multimedia objects, which will also be blocked by this command.

If the <object> or </object> HTML tags split across network packets or if the code in the tags is longer than the number of bytes in the MTU, the security appliance cannot block the tag.

ActiveX blocking does not occur when users access an IP address referenced by the **alias** command.

Examples

The following example specifies that Activex objects are blocked on all outbound connections:

```
hostname(config)# filteractivex 80 0 0 0 0
```

This command specifies that the ActiveX object blocking applies to web traffic on port 80 from any local host and for connections to any foreign host.

Related Commands

Commands	Description
filter url	Directs traffic to a URL filtering server.
filter java	Removes Java applets from HTTP traffic passing through the security appliance.
show running-config filter	Displays filtering configuration.
url-server	Identifies anN2H2 or Websense server for use with the filter command.

filter ftp

To identify the FTP traffic to be filtered by a Websense server, use the **filter ftp** command in global configuration mode. To remove the configuration, use the **no** form of this command.

filter ftp {[*port*[-*port*] | **except** } *local_ip* *local_mask* *foreign_ip* *foreign_mask*] [**allow**]
[**interact-block**]

no filter ftp {[*port*[-*port*] | **except** } *local_ip* *local_mask* *foreign_ip* *foreign_mask*] [**allow**]
[**interact-block**]

Syntax Description

<i>port</i>	The TCP port to which filtering is applied. Typically, this is port 21, but other values are accepted. The ftp literal can be used for port 80.
<i>port-port</i>	(Optional) Specifies a port range.
except	Creates an exception to a previous filter condition.
<i>local_ip</i>	The IP address of the highest security level interface from which access is sought. You can set this address to 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>local_mask</i>	Network mask of <i>local_ip</i> . You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>foreign_ip</i>	The IP address of the lowest security level interface to which access is sought. You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>foreign_mask</i>	Network mask of <i>foreign_ip</i> . Always specify a specific mask value. You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
allow	(Optional) When the server is unavailable, let outbound connections pass through the security appliance without filtering. If you omit this option, and if the N2H2 or Websense server goes off line, the security appliance stops outbound port 80 (Web) traffic until the N2H2 or Websense server is back on line.
interact-block	(Optional) Prevents users from connecting to the FTP server through an interactive FTP program.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **filter ftp** command lets you identify the FTP traffic to be filtered by a Websense server. FTP filtering is not supported on N2H2 servers.

After enabling this feature, when a user issues an FTP GET request to a server, the security appliance sends the request to the FTP server and to the Websense server at the same time. If the Websense server permits the connection, the security appliance allows the successful FTP return code to reach the user unchanged. For example, a successful return code is “250: CWD command successful.”

If the Websense server denies the connection, the security appliance alters the FTP return code to show that the connection was denied. For example, the security appliance would change code 250 to “550 Requested file is prohibited by URL filtering policy.” Websense only filters FTP GET commands and not PUT commands).

Use the **interactive-block** option to prevent interactive FTP sessions that do not provide the entire directory path. An interactive FTP client allows the user to change directories without typing the entire path. For example, the user might enter **cd ./files** instead of **cd /public/files**. You must identify and enable the URL filtering server before using these commands.

Examples

The following example shows how to enable FTP filtering:

```
hostname(config)# url-server (perimeter) host 10.0.1.1
hostname(config)# filter ftp 21 0 0 0 0
hostname(config)# filter ftp except 10.0.2.54 255.255.255.255 0 0
```

Related Commands

Commands	Description
filter https	Identifies the HTTPS traffic to be filtered by a Websense server.
filter java	Removes Java applets from HTTP traffic passing through the security appliance.
filter url	Directs traffic to a URL filtering server.
show running-config filter	Displays filtering configuration.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

filter https

To identify the HTTPS traffic to be filtered by a Websense server, use the **filter https** command in global configuration mode. To remove the configuration, use the **no** form of this command.

filter https {[*port*[-*port*] | **except**] [*local_ip* *local_mask* *foreign_ip* *foreign_mask*] [**allow**]

no filter https {[*port*[-*port*] | **except**] [*local_ip* *local_mask* *foreign_ip* *foreign_mask*] [**allow**]

Syntax Description

<i>port</i>	The TCP port to which filtering is applied. Typically, this is port 443, but other values are accepted. The https literal can be used for port 443.
<i>port-port</i>	(Optional) Specifies a port range.
except	(Optional) Creates an exception to a previous filter condition.
<i>dest-port</i>	The destination port number.
<i>local_ip</i>	The IP address of the highest security level interface from which access is sought. You can set this address to 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>local_mask</i>	Network mask of <i>local_ip</i> . You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>foreign_ip</i>	The IP address of the lowest security level interface to which access is sought. You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>foreign_mask</i>	Network mask of <i>foreign_ip</i> . Always specify a specific mask value. You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
allow	(Optional) When the server is unavailable, let outbound connections pass through the security appliance without filtering. If you omit this option, and if the N2H2 or Websense server goes off line, the security appliance stops outbound port 443 traffic until the N2H2 or Websense server is back on line.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The security appliance supports filtering of HTTPS and FTP sites using an external Websense filtering server.

**Note**

HTTPS is not supported for the N2H2 filtering server.

HTTPS filtering works by preventing the completion of SSL connection negotiation if the site is not allowed. The browser displays an error message such as “The Page or the content cannot be displayed.”

Because HTTPS content is encrypted, the security appliance sends the URL lookup without directory and filename information.

Examples

The following example filters all outbound HTTPS connections except those from the 10.0.2.54 host:

```
hostname(config)# url-server (perimeter) host 10.0.1.1
hostname(config)# filter https 443 0 0 0 0
hostname(config)# filter https except 10.0.2.54 255.255.255.255 0 0
```

Related Commands

Commands	Description
filteractivex	Removes ActiveX objects from HTTP traffic passing through the security appliance.
filterjava	Removes Java applets from HTTP traffic passing through the security appliance.
filterurl	Directs traffic to a URL filtering server.
show running-config filter	Displays filtering configuration.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

filter java

To remove Java applets from HTTP traffic passing through the security appliance, use the **filter java** command in global configuration mode. To remove the configuration, use the **no** form of this command.

filter java {[*port*[-*port*] | **except**] [*local_ip* *local_mask* *foreign_ip* *foreign_mask*]}

no filter java {[*port*[-*port*] | **except**] [*local_ip* *local_mask* *foreign_ip* *foreign_mask*]}

Syntax Description

<i>port</i>	The TCP port to which filtering is applied. Typically, this is port 80, but other values are accepted. The http or url literal can be used for port 80.
<i>port-port</i>	(Optional) Specifies a port range.
except	(Optional) Creates an exception to a previous filter condition.
<i>local_ip</i>	The IP address of the highest security level interface from which access is sought. You can set this address to 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>local_mask</i>	Network mask of <i>local_ip</i> . You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>foreign_ip</i>	The IP address of the lowest security level interface to which access is sought. You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>foreign_mask</i>	Network mask of <i>foreign_ip</i> . Always specify a specific mask value. You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Java applets may pose security risks because they can contain code intended to attack hosts and servers on a protected network. You can remove Java applets with the **filter java** command.

The **filter java** command filters out Java applets that return to the security appliance from an outbound connection. The user still receives the HTML page, but the web page source for the applet is commented out so that the applet cannot execute.

If the applet or /applet HTML tags split across network packets or if the code in the tags is longer than the number of bytes in the MTU, the security appliance cannot block the tag. If Java applets are known to be in <object> tags, use the **filteractivex** command to remove them.

Examples

The following example specifies that Java applets are blocked on all outbound connections:

```
hostname(config)# filter java 80 0 0 0 0
```

This command specifies that the Java applet blocking applies to web traffic on port 80 from any local host and for connections to any foreign host.

The following example blocks downloading of Java applets to a host on a protected network:

```
hostname(config)# filter java http 192.168.3.3 255.255.255.255 0 0
```

This command prevents host 192.168.3.3 from downloading Java applets.

Related Commands

Commands	Description
filteractivex	Removes ActiveX objects from HTTP traffic passing through the security appliance.
filterurl	Directs traffic to a URL filtering server.
show running-config filter	Displays filtering configuration.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

filter url

To direct traffic to a URL filtering server, use the **filter url** command in global configuration mode. To remove the configuration, use the **no** form of this command.

```
filter url {[port[-port] | except } local_ip local_mask foreign_ip foreign_mask [allow]  
[cgi-truncate] [longurl-truncate | longurl-deny] [proxy-block]
```

```
no filter url {[port[-port] | except } local_ip local_mask foreign_ip foreign_mask [allow]  
[cgi-truncate] [longurl-truncate | longurl-deny] [proxy-block]
```

Syntax Description

allow	When the server is unavailable, let outbound connections pass through the security appliance without filtering. If you omit this option, and if the N2H2 or Websense server goes off line, the security appliance stops outbound port 80 (Web) traffic until the N2H2 or Websense server is back on line.
cgi_truncate	When a URL has a parameter list starting with a question mark (?), such as a CGI script, truncate the URL sent to the filtering server by removing all characters after and including the question mark.
except	Creates an exception to a previous filter condition.
<i>foreign_ip</i>	The IP address of the lowest security level interface to which access is sought. You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>foreign_mask</i>	Network mask of <i>foreign_ip</i> . Always specify a specific mask value. You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
http	Specifies port 80. You can enter http or www instead of 80 to specify port 80.)
<i>local_ip</i>	The IP address of the highest security level interface from which access is sought. You can set this address to 0.0.0.0 (or in shortened form, 0) to specify all hosts.
<i>local_mask</i>	Network mask of <i>local_ip</i> . You can use 0.0.0.0 (or in shortened form, 0) to specify all hosts.
longurl-deny	Denies the URL request if the URL is over the URL buffer size limit or the URL buffer is not available.
longurl-truncate	Sends only the originating hostname or IP address to the Websense server if the URL is over the URL buffer limit.
<i>mask</i>	Any mask.
[<i>port</i> [- <i>port</i>]]	(Optional) The TCP port to which filtering is applied. Typically, this is port 80, but other values are accepted. The http or url literal can be used for port 80. Adding a second port after a hyphen optionally identifies a range of ports.
proxy-block	Prevents users from connecting to an HTTP proxy server.
url	Filter URLs from data moving through the security appliance.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **filter url** command lets you prevent outbound users from accessing World Wide Web URLs that you designate using the N2H2 or Websense filtering application.

**Note**

The **url-server** command must be configured before issuing the **filter url** command.

The **allow** option to the **filter url** command determines how the security appliance behaves if the N2H2 or Websense server goes off line. If you use the **allow** option with the **filter url** command and the N2H2 or Websense server goes offline, port 80 traffic passes through the security appliance without filtering. Used without the **allow** option and with the server off line, the security appliance stops outbound port 80 (Web) traffic until the server is back on line, or if another URL server is available, passes control to the next URL server.

**Note**

With the **allow** option set, the security appliance now passes control to an alternate server if the N2H2 or Websense server goes off line.

The N2H2 or Websense server works with the security appliance to deny users from access to websites based on the company security policy.

Using the Websense Filtering Server

Websense protocol Version 4 enables group and username authentication between a host and a security appliance. The security appliance performs a username lookup, and then Websense server handles URL filtering and username logging.

The N2H2 server must be a Windows workstation (2000, NT, or XP), running an IFP Server, with a recommended minimum of 512 MB of RAM. Also, the long URL support for the N2H2 service is capped at 3 KB, less than the cap for Websense.

Websense protocol Version 4 contains the following enhancements:

- URL filtering allows the security appliance to check outgoing URL requests against the policy defined on the Websense server.
- Username logging tracks username, group, and domain name on the Websense server.
- Username lookup enables the security appliance to use the user authentication table to map the host's IP address to the username.

Information on Websense is available at the following website:

<http://www.websense.com/>

Configuration Procedure

Follow these steps to filter URLs:

-
Step 1	Designate an N2H2 or Websense server with the appropriate vendor-specific form of the url-server command.
Step 2	Enable filtering with the filter command.
Step 3	If needed, improve throughput with the url-cache command. However, this command does not update Websense logs, which may affect Websense accounting reports. Accumulate Websense run logs before using the url-cache command.
Step 4	Use the show url-cache statistics and the show perfmon commands to view run information.
-

Working with Long URLs

Filtering URLs up to 4 KB is supported for the Websense filtering server, and up to 1159 bytes for the N2H2 filtering server.

Use the **longurl-truncate** and **cgi-truncate** options to allow handling of URL requests longer than the maximum permitted size.

If a URL is longer than the maximum, and you do not enable the **longurl-truncate** or **longurl-deny** options, the security appliance drops the packet.

The **longurl-truncate** option causes the security appliance to send only the hostname or IP address portion of the URL for evaluation to the filtering server when the URL is longer than the maximum length permitted. Use the **longurl-deny** option to deny outbound URL traffic if the URL is longer than the maximum permitted.

Use the **cgi-truncate** option to truncate CGI URLs to include only the CGI script location and the script name without any parameters. Many long HTTP requests are CGI requests. If the parameters list is very long, waiting and sending the complete CGI request including the parameter list can use up memory resources and affect security appliance performance.

Buffering HTTP Responses

By default, when a user issues a request to connect to a specific website, the security appliance sends the request to the web server and to the filtering server at the same time. If the filtering server does not respond before the web content server, the response from the web server is dropped. This delays the web server response from the point of view of the web client.

By enabling the HTTP response buffer, replies from web content servers are buffered and the responses will be forwarded to the requesting user if the filtering server allows the connection. This prevents the delay that may otherwise occur.

To enable the HTTP response buffer, enter the following command:

```
url-block block block-buffer-limit
```

Replace *block-buffer-limit* with the maximum number of blocks that will be buffered. The permitted values are from 0 to 128, which specifies the number of 1550-byte blocks that can be buffered at one time.

Examples

The following example filters all outbound HTTP connections except those from the 10.0.2.54 host:

```
hostname(config)# url-server (perimeter) host 10.0.1.1
hostname(config)# filter url 80 0 0 0 0
hostname(config)# filter url except 10.0.2.54 255.255.255.255 0 0
```

The following example blocks all outbound HTTP connections destined to a proxy server that listens on port 8080:

```
hostname(config)# filter url 8080 0 0 0 0 proxy-block
```

Related Commands

Commands	Description
filteractivex	Removes ActiveX objects from HTTP traffic passing through the security appliance.
filterjava	Removes Java applets from HTTP traffic passing through the security appliance.
url-block	Manages the URL buffers used for web server responses while waiting for a filtering decision from the filtering server.
url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

fips enable

To enable or disable policy-checking to enforce FIPS compliance on the system or module, use the **fips enable** command, or **[no] fips enable** command.

fips enable

[no] fips enable

Syntax Description

enable	Enables or disables policy-checking to enforce FIPS compliance.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	—	—	•	—	—

Command History

Release	Modification
7.0(4)	This command was introduced.

Usage Guidelines

To run in a FIPS-compliant mode of operation, you must apply both the **fips enable** command and the proper configuration specified in the Security Policy. The internal API allows the device to migrate towards enforcing proper configuration at run-time.

When “fips enable” is present in the startup-configuration, FIPS POST will run and print the following console message:

```
Copyright (c) 1996-2005 by Cisco Systems, Inc.
Restricted Rights Legend
```

```
Use, duplication, or disclosure by the Government is subject to restrictions as set forth
in subparagraph (c) of the Commercial Computer Software - Restricted Rights clause at FAR
sec. 52.227-19 and subparagraph (c) (1) (ii) of the Rights in Technical Data and Computer
Software clause at DFARS sec. 252.227-7013.
```

```
Cisco Systems, Inc.
170 West Tasman Drive
San Jose, California 95134-1706
```

```
....
```

```
Cryptochecksum (unchanged): 6c6d2f77 ef13898e 682c9f94 9c2d5ba9
```

```
INFO: FIPS Power-On Self-Test in process. Estimated completion in 90 seconds.
```

```
.....
```

```
INFO: FIPS Power-On Self-Test complete.  
Type help or '?' for a list of available commands.  
sw8-5520>
```

Examples

```
sw8-ASA(config)# fips enable
```

Related Commands

Command	Description
clear configure fips	Clears the system or module FIPS configuration information stored in NVRAM.
crashinfo console disable	Disables the reading, writing and configuration of crash write info to flash.
fips self-test poweron	Executes power-on self-tests.
show crashinfo console	Reads, writes, and configures crash write to flash.
show running-config fips	Displays the FIPS configuration that is running on the security appliance.

fips self-test poweron

To execute power-on self-tests, use the **fips self-test poweron** command.

fips self-test poweron

Syntax Description	poweron	Executes Power-On Self-Tests.

Defaults	This command has no default settings.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	7.0(4)	This command was introduced.

Usage Guidelines	Executing this command causes the device to run all self-tests required for FIPS 140-2 compliance. Tests are comprised of: cryptographic algorithm test, software integrity test and critical functions test.

Examples	<code>sw8-5520(config)# fips self-test poweron</code>

Related Commands	Command	Description
	clear configure fips	Clears the system or module FIPS configuration information stored in NVRAM.
	crashinfo console disable	Disables the reading, writing and configuration of crash write info to flash.
	fips enable	Enables or disables policy-checking to enforce FIPS compliance on the system or module.
	show crashinfo console	Reads, writes, and configures crash write to flash.
	show running-config fips	Displays the FIPS configuration that is running on the FWSM.

firewall transparent

To set the firewall mode to transparent mode, use the **firewall transparent** command in global configuration mode. To restore routed mode, use the **no** form of this command. A transparent firewall is a Layer 2 firewall that acts like a “bump in the wire,” or a “stealth firewall,” and is not seen as a router hop to connected devices.

firewall transparent

no firewall transparent

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines For multiple context mode, you can use only one firewall mode for all contexts. You must set the mode in the system configuration. This command also appears in each context configuration for informational purposes only; you cannot enter this command in a context.

When you change modes, the security appliance clears the configuration because many commands are not supported for both modes. If you already have a populated configuration, be sure to back up your configuration before changing the mode; you can use this backup for reference when creating your new configuration.

If you download a text configuration to the security appliance that changes the mode with the **firewall transparent** command, be sure to put the command at the top of the configuration; the security appliance changes the mode as soon as it reads the command and then continues reading the configuration you downloaded. If the command is later in the configuration, the security appliance clears all the preceding lines in the configuration.

Examples The following example changes the firewall mode to transparent:

```
hostname(config)# firewall transparent
```

Related Commands	Command	Description
	arp-inspection	Enables ARP inspection, which compares ARP packets to static ARP entries.
	mac-address-table static	Adds static MAC address entries to the MAC address table.
	mac-learn	Disables MAC address learning.
	show firewall	Shows the firewall mode.
	show mac-address-table	Shows the MAC address table, including dynamic and static entries.

format

To erase all files and format the file system, use the **format** command in privileged EXEC mode. This command erases all files on the file system, including hidden system files, and reinstalls the file system.

format { **disk0**: | **disk1**: | **flash**: }

Syntax Description

disk0 :	Specifies the internal Flash memory, followed by a colon.
disk1 :	Specifies the external Flash memory card, followed by a colon.
flash :	Specifies the internal Flash memory, followed by a colon. In the ASA 5500 series, the flash keyword is aliased to disk0 .

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **format** command erases all data on the specified file system and then rewrites the FAT information to the device.



Caution

Use the **format** command with extreme caution, only when necessary to clean up corrupted Flash memory.

To delete all visible files (excluding hidden system files), enter the **delete /recursive** command, instead of the **format** command.



Note

On Cisco ASA 5500 series security appliances, the **erase** command destroys all user data on the disk with the 0xFF pattern. In contrast, the **format** command only resets the file system control structures. If you used a raw disk read tool, you could still see the information.

To repair a corrupt file system, try entering the **fsck** command before entering the **format** command.

Examples

This example shows how to format the Flash memory:

```
hostname# format flash:
```

Related Commands

Command	Description
delete	Removes all user-visible files.
erase	Deletes all files and formats the Flash memory.
fsck	Repairs a corrupt file system.

fqdn

To include the indicated FQDN in the Subject Alternative Name extension of the certificate during enrollment, use the **fqdn** command in crypto ca trustpoint configuration mode. To restore the default setting of the fqdn, use the **no** form of the command.

fqdn *fqdn*

no fqdn

Syntax Description

fqdn Specifies the fully qualified domain name. The maximum length of *fqdn* is 64 characters.

Defaults

The default setting is not to include the FQDN.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Crypto ca trustpoint configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and includes the FQDN engineering in the enrollment request for trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# fqdn engineering
hostname(ca-trustpoint)#
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint configuration mode.
default enrollment	Returns enrollment parameters to their defaults.
enrollment retry count	Specifies the number of retries to attempt to send an enrollment request.
enrollment retry period	Specifies the number of minutes to wait before trying to send an enrollment request.
enrollment terminal	Specifies cut and paste enrollment with this trustpoint.

fragment

To provide additional management of packet fragmentation and improve compatibility with NFS, use the **fragment** command in global configuration mode.

fragment {**size** | **chain** | **reassemble full** | **timeout limit**} [*interface*]

no fragment {**size** | **chain** | **reassemble full** | **timeout limit**} *interface*

Syntax Description

chain limit	Specifies the maximum number of packets into which a full IP packet can be fragmented.
<i>interface</i>	(Optional) Specifies the security appliance interface. If an interface is not specified, the command applies to all interfaces.
size limit	Sets the maximum number of packets that can be in the IP reassembly database waiting for reassembly.
reassemble full	Enables full reassembly for fragments that are routed through the device. Fragments that terminate at the device are always fully reassembled.
timeout limit	Specifies the maximum number of seconds to wait for an entire fragmented packet to arrive. The timer starts after the first fragment of a packet arrives. If all fragments of the packet do not arrive by the number of seconds specified, all fragments of the packet that were already received will be discarded.

Defaults

The defaults are as follows:

- **chain** is 24 packets
- *interface* is all interfaces
- **size** is 200
- **timeout** is 5 seconds

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was modified so that you now must choose one of the following arguments: chain , size , or timeout . You can no longer enter the fragment command without entering one of these arguments, as was supported in prior releases of the software.
	7.0.8	The keyword reassemble full was added to enable full reassembly for fragments that are routed through the device.

Usage Guidelines

By default, the security appliance accepts up to 24 fragments to reconstruct a full IP packet. Based on your network security policy, you should consider configuring the security appliance to prevent fragmented packets from traversing the security appliance by entering the **fragment chain 1 interface** command on each interface. Setting the limit to 1 means that all packets must be whole; that is, unfragmented.

If a large percentage of the network traffic through the security appliance is NFS, additional tuning might be necessary to avoid database overflow.

In an environment where the MTU size is small between the NFS server and client, such as a WAN interface, the **chain** keyword might require additional tuning. In this case, we recommend using NFS over TCP to improve efficiency.

Setting the **size limit** to a large value can make the security appliance more vulnerable to a DoS attack by fragment flooding. Do not set the **size limit** equal to or greater than the total number of blocks in the 1550 or 16384 pool.

The default values will limit DoS attacks caused by fragment flooding.

If **reassemble full** is enabled, fragments in the completed fragment set are merged into one packet. The fragments are then released.

Examples

This example shows how to prevent fragmented packets on the outside and inside interfaces:

```
hostname(config)# fragment chain 1 outside
hostname(config)# fragment chain 1 inside
```

Continue entering the **fragment chain 1 interface** command for each additional interface on which you want to prevent fragmented packets.

This example shows how to configure the fragment database on the outside interface to a maximum size of 2000, a maximum chain length of 45, and a wait time of 10 seconds:

```
hostname(config)# fragment size 2000 outside
hostname(config)# fragment chain 45 outside
hostname(config)# fragment timeout 10 outside
```

Related Commands

Command	Description
clear configure fragment	Resets all the IP fragment reassembly configurations to defaults.
clear fragment	Clears the operational data of the IP fragment reassembly module.
show fragment	Displays the operational data of the IP fragment reassembly module.
show running-config fragment	Displays the IP fragment reassembly configuration.

 fragment

ftp-map

To identify a specific map for defining the parameters for strict FTP inspection, use the **ftp-map** command in global configuration mode. To remove the map, use the **no** form of this command.

ftp-map *map_name*

no ftp-map *map_name*

Syntax Description

<i>map_name</i>	The name of the FTP map.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **ftp-map** command to identify a specific map to use for defining the parameters for strict FTP inspection. When you enter this command, the system enters the FTP map configuration mode, which lets you enter the different commands used for defining the specific map. Use the **request-command deny** command to prevent the FTP client from sending specific commands to the FTP server.

After defining the FTP map, use the **inspect ftp strict** command to enable the map. Then use the **class-map**, **policy-map**, and **service-policy** commands to define a class of traffic, to apply the **inspect** command to the class, and to apply the policy to one or more interfaces.

Examples

The following example shows how to identify FTP traffic, define an FTP map, define a policy, and apply the policy to the outside interface:

```
hostname(config)# class-map ftp-port
hostname(config-cmap)# match port tcp eq 21
hostname(config-cmap)# exit
hostname(config)# ftp-map inbound_ftp
hostname(config-ftp-map)# request-command deny put stou appe
hostname(config-ftp-map)# exit
hostname(config)# policy-map inbound_policy
hostname(config-pmap)# class ftp-port
hostname(config-pmap-c)# inspect ftp strict inbound_ftp
hostname(config-pmap-c)# exit
```

```
hostname(config-pmap)# exit  
hostname(config)# service-policy inbound_policy interface outside
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
inspect ftp	Applies a specific FTP map to use for application inspection.
mask-syst-reply	Hides the FTP server response from clients.
policy-map	Associates a class map with specific security actions.
request-command deny	Specifies FTP commands to disallow.

ftp mode passive

To set the FTP mode to passive, use the **ftp mode passive** command in global configuration mode. To reset the FTP client to active mode, use the **no** form of this command.

ftp mode passive

no ftp mode passive

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **ftp mode passive** command sets the FTP mode to passive. The security appliance can use FTP to upload or download image files or configuration files to or from an FTP server. The **ftp mode passive** command controls how the FTP client on the security appliance interacts with the FTP server.

In passive FTP, the client initiates both the control connection and the data connection. Passive mode refers to the server state, in that the server is passively accepting both the control connection and the data connection, which are initiated by the client.

In passive mode, both destination and source ports are ephemeral ports (greater than 1023). The mode is set by the client, as the client issues the **passive** command to initiate the setup of the passive data connection. The server, which is the recipient of the data connection in passive mode, responds with the port number to which it is listening for the specific connection.

Examples

The following example sets the FTP mode to passive:

```
hostname(config)# ftp mode passive
```

Related Commands

copy	Uploads or downloads image files or configuration files to or from an FTP server.

<code>debug ftp client</code>	Displays detailed information about FTP client activity.
<code>show running-config ftp mode</code>	Displays FTP client configuration.

functions

To configure file access and file browsing, MAPI Proxy, HTTP Proxy, and URL entry over WebVPN for this user or group policy, use the **functions** command in webvpn mode, which you enter from group-policy or username mode. To remove a configured function, use the **no** form of this command.

To remove all configured functions, including a null value created by issuing the **functions none** command, use the **no** form of this command without arguments. The **no** option allows inheritance of a value from another group policy. To prevent inheriting function values, use the **functions none** command.

functions { **file-access** | **file-browsing** | **file-entry** | **filter** | **http-proxy** | **url-entry** | **mapi** | **port-forward** | **none** }

no functions [**file-access** | **file-browsing** | **file-entry** | **filter** | **url-entry** | **mapi** | **port-forward**]

Syntax Description

file-access	Enables or disables file access. When enabled, the WebVPN home page lists file servers in the server list. You must enable file access to enable file browsing and/or file entry.
file-browsing	Enables or disables browsing for file servers and shares. You must enable file browsing to allow user entry of a file server.
file-entry	Enables or disables user ability to enter names of file servers.
filter	Applies a webtype ACL. When enabled, the security appliance applies the webtype ACL defined with the webvpn filter command.
http-proxy	Enables or disables the forwarding of an HTTP applet proxy to the client. The proxy is useful for technologies that interfere with proper mangling, such as Java, ActiveX, and Flash. It bypasses mangling while ensuring the continued use of the security appliance. The forwarded proxy modifies the browser's old proxy configuration automatically and redirects all HTTP and HTTPS requests to the new proxy configuration. It supports virtually all client side technologies, including HTML, CSS, JavaScript, VBScript, ActiveX, and Java. The only browser it supports is Microsoft Internet Explorer.
mapi	Enables or disables Microsoft Outlook/Exchange port forwarding.
none	Sets a null value for all WebVPN functions . Prevents inheriting functions from a default or specified group policy.
port-forward	Enables port forwarding. When enabled, the security appliance uses the port forwarding list defined with the webvpn port-forward command.
url-entry	Enables or disables user entry of URLs. When enabled, the security appliance still restricts URLs with any configured URL or network ACLs. When URL entry is disabled, the security appliance restricts WebVPN users to the URLs on the home page.

Defaults

Functions are disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn mode	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to configure file access, file browsing, and MAPI Proxy for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# webvpn
hostname(config-group-webvpn)# functions file-access file-browsing MAPI
```

Related Commands

Command	Description
webvpn	Use in group-policy configuration mode or in username configuration mode. Lets you enter webvpn mode to configure parameters that apply to group policies or usernames.
webvpn	Use in global configuration mode. Lets you configure global settings for WebVPN.



G through L Commands

gateway

To specify which group of call agents are managing a particular gateway, use the **gateway** command in MGCP map configuration mode. To remove the configuration, use the **no** form of this command.

gateway *ip_address* [*group_id*]

Syntax Description

gateway	Specifies the group of call agents that are managing a particular gateway
<i>ip_address</i>	The IP address of the gateway.
<i>group_id</i>	The ID of the call agent group, from 0 to 2147483647.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
MGCP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **gateway** command to specify which group of call agents are managing a particular gateway. The IP address of the gateway is specified with the *ip_address* option. The *group_id* option is a number from 0 to 4294967295 that must correspond with the *group_id* of the call agents that are managing the gateway. A gateway may only belong to one group.

Examples

The following example allows call agents 10.10.11.5 and 10.10.11.6 to control gateway 10.10.10.115, and allows call agents 10.10.11.7 and 10.10.11.8 to control both gateways 10.10.10.116 and 10.10.10.117:

```
hostname(config)# mgcp-map mgcp_policy
hostname(config-mgcp-map)# call-agent 10.10.11.5 101
hostname(config-mgcp-map)# call-agent 10.10.11.6 101
hostname(config-mgcp-map)# call-agent 10.10.11.7 102
hostname(config-mgcp-map)# call-agent 10.10.11.8 102
hostname(config-mgcp-map)# gateway 10.10.10.115 101
hostname(config-mgcp-map)# gateway 10.10.10.116 102
hostname(config-mgcp-map)# gateway 10.10.10.117 102
```

Related Commands	Commands	Description
	debug mgcp	Enables the display of debug information for MGCP.
	mgcp-map	Defines an MGCP map and enables MGCP map configuration mode.
	show mgcp	Displays MGCP configuration and session information.

global

To create a pool of mapped addresses for NAT, use the **global** command in global configuration mode. To remove the pool of addresses, use the **no** form of this command.

global (*mapped_ifc*) *nat_id* {*mapped_ip*[-*mapped_ip*] [**netmask** *mask*] | **interface**}

no global (*mapped_ifc*) *nat_id* {*mapped_ip*[-*mapped_ip*] [**netmask** *mask*] | **interface**}

Syntax Description

interface	Uses the interface IP address as the mapped address. Use this keyword if you want to use the interface address, but the address is dynamically assigned using DHCP.
<i>mapped_ifc</i>	Specifies the name of the interface connected to the mapped IP address network.
<i>mapped_ip</i> [- <i>mapped_ip</i>]	Specifies the mapped address(es) to which you want to translate the real addresses when they exit the mapped interface. If you specify a single address, then you configure PAT. If you specify a range of addresses, then you configure dynamic NAT. If the external network is connected to the Internet, each global IP address must be registered with the Network Information Center (NIC).
<i>nat_id</i>	Specifies an integer for the NAT ID. This ID is referenced by the nat command to associate a mapped pool with the real addresses to translate. For regular NAT, this integer is between 1 and 2147483647. For policy NAT (nat id access-list), this integer is between 1 and 65535. Do not specify a global command for NAT ID 0; 0 is reserved for identity NAT and NAT exemption, which do not use a global command.
netmask <i>mask</i>	(Optional) Specifies the network mask for the <i>mapped_ip</i> . This mask does not specify a network when paired with the <i>mapped_ip</i> ; rather, it specifies the subnet mask assigned to the <i>mapped_ip</i> when it is assigned to a host. If you want to configure a range of addresses, you need to specify <i>mapped_ip-mapped_ip</i> . If you do not specify a mask, then the default mask for the address class is used.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

For dynamic NAT and PAT, you first configure a **nat** command identifying the real addresses on a given interface that you want to translate. Then you configure a separate **global** command to specify the mapped addresses when exiting another interface (in the case of PAT, this is one address). Each **nat** command matches a **global** command by comparing the NAT ID, a number that you assign to each command.

See the **nat** command for more information about dynamic NAT and PAT.

If you change the NAT configuration, and you do not want to wait for existing translations to time out before the new NAT information is used, you can clear the translation table using **clear xlate** command. However, clearing the translation table disconnects all of the current connections.

Examples

For example, to translate the 10.1.1.0/24 network on the inside interface, enter the following command:

```
hostname(config)# nat (inside) 1 10.1.1.0 255.255.255.0
hostname(config)# global (outside) 1 209.165.201.1-209.165.201.30
```

To identify a pool of addresses for dynamic NAT as well as a PAT address for when the NAT pool is exhausted, enter the following commands:

```
hostname(config)# nat (inside) 1 10.1.1.0 255.255.255.0
hostname(config)# global (outside) 1 209.165.201.5
hostname(config)# global (outside) 1 209.165.201.10-209.165.201.20
```

To translate the lower security dmz network addresses so they appear to be on the same network as the inside network (10.1.1.0), for example, to simplify routing, enter the following commands:

```
hostname(config)# nat (dmz) 1 10.1.2.0 255.255.255.0 outside dns
hostname(config)# global (inside) 1 10.1.1.45
```

To identify a single real address with two different destination addresses using policy NAT, enter the following commands:

```
hostname(config)# access-list NET1 permit ip 10.1.2.0 255.255.255.0 209.165.201.0
255.255.255.224
hostname(config)# access-list NET2 permit ip 10.1.2.0 255.255.255.0 209.165.200.224
255.255.255.224
hostname(config)# nat (inside) 1 access-list NET1 tcp 0 2000 udp 10000
hostname(config)# global (outside) 1 209.165.202.129
hostname(config)# nat (inside) 2 access-list NET2 tcp 1000 500 udp 2000
hostname(config)# global (outside) 2 209.165.202.130
```

To identify a single real address/destination address pair that use different ports using policy NAT, enter the following commands:

```
hostname(config)# access-list WEB permit tcp 10.1.2.0 255.255.255.0 209.165.201.11
255.255.255.255 eq 80
hostname(config)# access-list TELNET permit tcp 10.1.2.0 255.255.255.0 209.165.201.11
255.255.255.255 eq 23
hostname(config)# nat (inside) 1 access-list WEB
hostname(config)# global (outside) 1 209.165.202.129
hostname(config)# nat (inside) 2 access-list TELNET
hostname(config)# global (outside) 2 209.165.202.130
```

Related Commands	Command	Description
	clear configure global	Removes global commands from the configuration.
	nat	Specifies the real addresses to translate.
	show running-config global	Displays the global commands in the configuration.
	static	Configures a one-to-one translation.

group-delimiter

To enable group-name parsing and specify the delimiter to be used when parsing group names from the user names that are received when tunnels are being negotiated, use the **group-delimiter** command in global configuration mode. To disable this group-name parsing, use the no form of this command.

group-delimiter *delimiter*

no group-delimiter

Syntax Description

delimiter Specifies the character to use as the group-name delimiter.
Valid values are: @, #, and !.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

By default, no delimiter is specified, disabling group-name parsing.

Examples

This example shows the **group-delimiter** command to change the group delimiter to the hash mark (#):

```
hostname(config)# group-delimiter #
```

Related Commands

Command	Description
show running-config group-delimiter	Displays the current group-delimiter value.
strip-group	Enables or disables strip-group processing.

group-lock

To restrict remote users to access through the tunnel group only, issue the **group-lock** command in group-policy configuration mode or username configuration mode.

To remove the **group-lock** attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a value from another group policy. To disable group-lock, use the **group-lock none** command.

Group-lock restricts users by checking if the group configured in the VPN Client is the same as the tunnel group to which the user is assigned. If it is not, the security appliance prevents the user from connecting. If you do not configure group-lock, the security appliance authenticates users without regard to the assigned group.

group-lock {**value** *tunnel-grp-name* | **none**}

no group-lock

Syntax Description

none	Sets group-lock to a null value, thereby allowing no group-lock restriction. Prevents inheriting a group-lock value from a default or specified group policy.
value <i>tunnel-grp-name</i>	Specifies the name of an existing tunnel group that the security appliance requires for the user to connect.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—
Username	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to set group lock for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# group-lock value tunnel group name
```

group-object

To add network object groups, use the **group-object** command in protocol, network, service, and icmp-type configuration modes. To remove network object groups, use the **no** form of this command.

group-object *obj_grp_id*

no group-object *obj_grp_id*

Syntax Description

obj_grp_id Identifies the object group (one to 64 characters) and can be any combination of letters, digits, and the “_”, “-”, “.” characters.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Protocol, network, service, icmp-type configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **group-object** command is used with the **object-group** command to define an object that itself is an object group. It is used in protocol, network, service, and icmp-type configuration modes. This sub-command allows logical grouping of the same type of objects and construction of hierarchical object groups for structured configuration.

Duplicate objects are allowed in an object group if they are group objects. For example, if object 1 is in both group A and group B, it is allowed to define a group C which includes both A and B. It is not allowed, however, to include a group object which causes the group hierarchy to become circular. For example, it is not allowed to have group A include group B and then also have group B include group A.

The maximum allowed levels of a hierarchical object group is 10.

Examples

The following example shows how to use the **group-object** command in network configuration mode eliminate the need to duplicate hosts:

```
hostname(config)# object-group network host_grp_1
hostname(config-network)# network-object host 192.168.1.1
hostname(config-network)# network-object host 192.168.1.2
hostname(config-network)# exit
```

```

hostname(config)# object-group network host_grp_2
hostname(config-network)# network-object host 172.23.56.1
hostname(config-network)# network-object host 172.23.56.2
hostname(config-network)# exit
hostname(config)# object-group network all_hosts
hostname(config-network)# group-object host_grp_1
hostname(config-network)# group-object host_grp_2
hostname(config-network)# exit
hostname(config)# access-list grp_1 permit tcp object-group host_grp_1 any eq ftp
hostname(config)# access-list grp_2 permit tcp object-group host_grp_2 any eq smtp
hostname(config)# access-list all permit tcp object-group all-hosts any eq w

```

Related Commands

Command	Description
clear configure object-group	Removes all the object-group commands from the configuration.
network-object	Adds a network object to a network object group.
object-group	Defines object groups to optimize your configuration.
port-object	Adds a port object to a service object group.
show running-config object-group	Displays the current object groups.

group-policy

To create or edit a group policy, use the **group-policy** command in global configuration mode. To remove a group policy from the configuration, use the **no** form of this command.

group-policy *name* {**internal** [**from** *group-policy_name*] | **external server-group** *server_group* **password** *server_password*}

no group-policy *name*

Syntax Description

external server-group <i>server_group</i>	Specifies the group policy as external and identifies the AAA server group for the security appliance to query for attributes.
from <i>group-policy_name</i>	Initializes the attributes of this internal group policy to the values of a pre-existing group policy.
internal	Identifies the group policy as internal.
<i>name</i>	Specifies the name of the group policy.
password <i>server_password</i>	Provides the password to use when retrieving attributes from the external AAA server group.

Defaults

No default behavior or values. See Usage Guidelines.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

A default group policy, named “DefaultGroupPolicy,” always exists on the security appliance. However, this default group policy does not take effect unless you configure the security appliance to use it. For configuration instructions, see the *Cisco Security Appliance Command Line Configuration Guide*.

The DefaultGroupPolicy has these AVPs:

Attribute	Default Value
wins-server	none
dns-server	none
vpn-access-hours	unrestricted

Attribute	Default Value
vpn-simultaneous-logins	3
vpn-idle-timeout	30 minutes
vpn-session-timeout	none
vpn-filter	none
vpn-tunnel-protocol	IPSec WebVPN
ip-comp	disable
re-xauth	disable
group-lock	none
pfs	disable
client-access-rules	none
banner	none
password-storage	disabled
ipsec-udp	disabled
ipsec-udp-port	10000
backup-servers	keep-client-config
split-tunnel-policy	tunnelall
split-tunnel-network-list	none
default-domain	none
split-dns	none
client-firewall	none
secure-unit-authentication	disabled
user-authentication	disabled
user-authentication-idle-timeout	none
ip-phone-bypass	disabled
leap-bypass	disabled
nem	disabled

Examples

The following example shows how to create an internal group policy with the name “FirstGroup”:

```
hostname(config)# group-policy FirstGroup internal
```

The next example shows how to create an external group policy with the name “ExternalGroup,” the AAA server group “BostonAAA,” and the password “12345678”:

```
hostname(config)# group-policy ExternalGroup external server-group BostonAAA password 12345678
```

Related Commands

Command	Description
clear configure group-policy	Removes the configuration for a particular group policy or for all group policies.

Command	Description
<code>group-policy attributes</code>	Enters group-policy attributes mode, which lets you configure AVPs for a specified group policy.
<code>show running-config group-policy</code>	Displays the running configuration for a particular group policy or for all group policies.

group-policy attributes

To enter the group-policy attributes mode, use the **group-policy attributes** command in global configuration mode. To remove all attributes from a group policy, use the **no** version of this command. The attributes mode lets you configure AVPs for a specified group policy.

group-policy *name* **attributes**

no **group-policy** *name* **attributes**

Syntax Description

name Specifies the name of the group policy.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The syntax of the commands in attributes mode have the following characteristics in common:

- The **no** form removes the attribute from the running configuration, and enables inheritance of a value from another group policy.
- The **none** keyword sets the attribute in the running configuration to a null value, thereby preventing inheritance.
- Boolean attributes have explicit syntax for enabled and disabled settings.

Examples

The following example shows how to enter group-policy attributes mode for the group policy named "FirstGroup":

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)#
```

Related Commands	Command	Description
	<code>clear configure group-policy</code>	Removes the configuration for a particular group policy or for all group policies.
	<code>group-policy</code>	Creates, edits, or removes a group policy.
	<code>show running-config group-policy</code>	Displays the running configuration for a particular group policy or for all group policies.

gtp-map

To identify a specific map to use for defining the parameters for GTP, use the **gtp-map** command in global configuration mode. To remove the map, use the **no** form of this command.

gtp-map *map_name*

no gtp-map *map_name*



Note

GTP inspection requires a special license. If you enter the **gtp-map** command on a security appliance without the required license, the security appliance displays an error message.

Syntax Description

<i>map_name</i>	The name of the GTP map.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

GPRS is a data network architecture that is designed to integrate with existing GSM networks. It offers mobile subscribers uninterrupted, packet-switched data services to corporate networks and the Internet. For an overview of GTP and how the security appliance ensures secure access over wireless networks, refer to the “Applying Application Layer Protocol Inspection” chapter in the *Cisco Security Appliance Command Line Configuration Guide*.

Use the **gtp-map** command to identify a specific map to use for defining the parameters for GTP. When you enter this command, the system enters a configuration mode that lets you enter the different commands used for defining the specific map. After defining the GTP map, you use the **inspect gtp** command to enable the map. Then you use the **class-map**, **policy-map**, and **service-policy** commands to define a class of traffic, to apply the **inspect** command to the class, and to apply the policy to one or more interfaces.

Table 5-1 GTP Map Configuration Commands

Command	Description
description	Specifies the GTP configuration map description.
drop	Specifies the message ID, APN, or GTP version to drop.
help	Displays help for GTP map configuration commands.
mcc	Specifies the three-digit Mobile Country Code (000 - 999). One or two- digit entries will be prepended with 0s
message-length	Specifies the message length min and max
permit errors	Permits packets with errors or different GTP versions.
request-queue	Specifies the maximum requests allowed in the queue.
timeout (gtp-map)	Specifies the idle timeout for the GSN, PDP context, requests, signaling connections, and tunnels.
tunnel-limit	Specifies the maximum number of tunnels allowed.

Examples

The following example shows how to use the **gtp-map** command to identify a specific map (gtp-policy) to use for defining the parameters for GTP:

```
hostname(config)# gtp-map gtp-policy
hostname(config-gtpmap)#
```

The following example shows how to use access lists to identify GTP traffic, define a GTP map, define a policy, and apply the policy to the outside interface:

```
hostname(config)# access-list gtp-acl permit udp any any eq 3386
hostname(config)# access-list gtp-acl permit udp any any eq 2123
hostname(config)# class-map gtp-traffic
hostname(config-cmap)# match access-list gtp-acl
hostname(config-cmap)# exit
hostname(config)# gtp-map gtp-policy
hostname(config-gtpmap)# request-queue 300
hostname(config-gtpmap)# permit mcc 111 mnc 222
hostname(config-gtpmap)# message-length min 20 max 300
hostname(config-gtpmap)# drop message 20
hostname(config-gtpmap)# tunnel-limit 10000
hostname(config)# policy-map inspection_policy
hostname(config-pmap)# class gtp-traffic
hostname(config-pmap-c)# inspect gtp gtp-policy
hostname(config)# service-policy inspection_policy outside
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
clear service-policy inspect gtp	Clears global GTP statistics.
debug gtp	Displays detailed information about GTP inspection.
inspect gtp	Applies a specific GTP map to use for application inspection.
show service-policy inspect gtp	Displays the GTP configuration.

help

To display help information for the command specified, use the **help** command in user EXEC mode.

help {*command* | ?}

Syntax Description

<i>command</i>	Specifies the command for which to display the CLI help.
?	Displays all commands that are available in the current privilege level and mode.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **help** command displays help information about all commands. You can see help for an individual command by entering the **help** command followed by the command name. If you do not specify a command name and enter **?** instead, all commands that are available in the current privilege level and mode display.

If you enable the **pager** command and when 24 lines display, the listing pauses, and the following prompt appears:

```
<--- More --->
```

The More prompt uses syntax similar to the UNIX **more** command as follows:

- To see another screen of text, press the **Space** bar.
- To see the next line, press the **Enter** key.
- To return to the command line, press the **q** key.

Examples

The following example shows how to display help for the **rename** command:

```
hostname# help rename
```

```
USAGE:
```

```
rename /noconfirm [{disk0:|disk1:|flash:}] <source path> [{disk0:|disk1:
```

```
|flash:}} <destination path>
```

DESCRIPTION:

```
rename          Rename a file
```

SYNTAX:

```
/noconfirm          No confirmation
{disk0:|disk1:|flash:} Optional parameter that specifies the filesystem
<source path>       Source file path
<destination path>  Destination file path
```

```
hostname#
```

The following examples shows how to display help by entering the command name and a question mark:

```
hostname(config)# enable ?
usage: enable password <pwd> [encrypted]
```

Help is available for the core commands (not the **show**, **no**, or **clear** commands) by entering **?** at the command prompt:

```
hostname(config)# ?
aaa          Enable, disable, or view TACACS+ or RADIUS
             user authentication, authorization and accounting
...
```

Related Commands

Command	Description
show version	Displays information about the operating system software.

homepage

To specify a URL for the web page that displays upon login for this WebVPN user or group policy, use the **homepage** command in webvpn mode, which you enter from group-policy or username mode. To remove a configured home page, including a null value created by issuing the **homepage none** command, use the **no** form of this command. The **no** option allows inheritance of a value from another group policy. To prevent inheriting a home page, use the **homepage none** command.

homepage {value *url-string* | none}

no homepage

Syntax Description

none	Indicates that there is no WebVPN home page. Sets a null value, thereby disallowing a home page. Prevents inheriting an home page.
value <i>url-string</i>	Provides a URL for the home page. The string must begin with either http:// or https://.

Defaults

There is no default home page.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn mode	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to specify www.example.com as the home page for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# webvpn
hostname(config-group-webvpn)# homepage value http://www.example.com
```

Related Commands

Command	Description
webvpn	Use in group-policy configuration mode or in username configuration mode. Lets you enter webvpn mode to configure parameters that apply to group policies or usernames.

hostname

To set the security appliance hostname, use the **hostname** command in global configuration mode. To restore the default hostname, use the **no** form of this command. The hostname appears as the command line prompt, and if you establish sessions to multiple devices, the hostname helps you keep track of where you enter commands.

hostname *name*

no hostname [*name*]

Syntax Description

<i>name</i>	Specifies a hostname up to 63 characters. A hostname must start and end with a letter or digit, and have as interior characters only letters, digits, or a hyphen.

Defaults

The default hostname depends on your platform.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0(1)	You can no longer use non-alphanumeric characters (other than a hyphen).

Usage Guidelines

For multiple context mode, the hostname that you set in the system execution space appears in the command line prompt for all contexts.

The hostname that you optionally set within a context does not appear in the command line, but can be used for the **banner** command **\$(hostname)** token.

Examples

The following example sets the hostname to firewall1:

```
hostname(config)# hostname firewall1
firewall1(config)#
```

Related Commands

Command	Description
banner	Sets a login, message of the day, or enable banner.
domain-name	Sets the default domain name.

html-content-filter

To filter Java, ActiveX, images, scripts, and cookies for WebVPN sessions for this user or group policy, use the **html-content-filter** command in webvpn mode, which you enter from group-policy or username mode. To remove a content filter, use the **no** form of this command. To remove all content filters, including a null value created by issuing the **html-content-filter none** command, use the **no** form of this command without arguments. The **no** option allows inheritance of a value from another group policy. To prevent inheriting an html content filter, use the **html-content-filter none** command.

html-content-filter {java | images | scripts | cookies | none}

no html-content-filter [java | images | scripts | cookies | none]

Syntax Description

cookies	Removes cookies from images, providing limited ad filtering and privacy.
images	Removes references to images (removes tags).
java	Removes references to Java and ActiveX (removes <EMBED>, <APPLET>, and <OBJECT> tags).
none	Indicates that there is no filtering. Sets a null value, thereby disallowing filtering. Prevents inheriting filtering values.
scripts	Removes references to scripting (removes <SCRIPT> tags).

Defaults

No filtering occurs.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn mode	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Using the command a second time overrides the previous setting.

Examples

The following example shows how to set filtering of JAVA and ActiveX, cookies, and images for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# webvpn
hostname(config-group-webvpn)# html-content-filter java cookies images
```

Related Commands

Command	Description
webvpn (group-policy, username)	Use in group-policy configuration mode or in username configuration mode. Lets you enter webvpn mode to configure parameters that apply to group policies or usernames.
webvpn	Use in global configuration mode. Lets you configure global settings for WebVPN.

http

To specify hosts that can access the HTTP server internal to the security appliance, use the **http** command in global configuration mode. To remove one or more hosts, use the **no** form of this command. To remove the attribute from the configuration, use the **no** form of this command without arguments.

http *ip_address subnet_mask interface_name*

no http

Syntax Description

<i>interface_name</i>	Provides the name of the security appliance interface through which the host can access the HTTP server.
<i>ip_address</i>	Provides the IP address of a host that can access the HTTP server.
<i>subnet_mask</i>	Provides the subnet mask of a host that can access the HTTP server.

Defaults

No hosts can access the HTTP server.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example shows how to allow the host with the IP address of 10.10.99.1 and the subnet mask of 255.255.255.255 access to the HTTP server via the outside interface:

```
hostname(config)# http 10.10.99.1 255.255.255.255 outside
```

The next example shows how to allow any host access to the HTTP server via the outside interface:

```
hostname(config)# http 0.0.0.0 0.0.0.0 outside
```

Related Commands

Command	Description
clear configure http	Removes the HTTP configuration: disables the HTTP server and removes hosts that can access the HTTP server.
http authentication-certificate	Requires authentication via certificate from users who are establishing HTTPS connections to the security appliance.

Command	Description
http redirect	Specifies that the security appliance redirect HTTP connections to HTTPS.
http server enable	Enables the HTTP server.
show running-config http	Displays the hosts that can access the HTTP server, and whether or not the HTTP server is enabled.

http authentication-certificate

To require authentication via certificate from users who are establishing HTTPS connections, use the **http authentication-certificate** command in global configuration mode. To remove the attribute from the configuration, use the **no** version of this command. To remove all **http authentication-certificate** commands from the configuration, use the **no** version without arguments.

The security appliance validates certificates against the PKI trust points. If a certificate does not pass validation, the security appliance closes the SSL connection.

http authentication-certificate *interface*

no http authentication-certificate [*interface*]

Syntax Description

<i>interface</i>	Specifies the interface on the security appliance that requires certificate authentication.

Defaults

HTTP certificate authentication is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can configure certificate authentication for each interface, such that connections on a trusted/inside interface do not have to provide a certificate. You can use the command multiple times to enable certificate authentication on multiple interfaces.

Validation occurs before the URL is known, so this affects both WebVPN and ASDM access.

The ASDM uses its own authentication method in addition to this value. That is, it requires both certificate and username/password authentication if both are configured, or just username/password if certificate authentication is disabled.

Examples

The following example shows how to require certificate authentication for clients connecting to the interfaces named outside and external:

```
hostname(config)# http authentication-certificate inside
hostname(config)# http authentication-certificate external
```

Related Commands

Command	Description
<code>clear configure http</code>	Removes the HTTP configuration: disables the HTTP server and removes hosts that can access the HTTP server.
<code>http</code>	Specifies hosts that can access the HTTP server by IP address and subnet mask. Specifies the security appliance interface through which the host accesses the HTTP server.
<code>http redirect</code>	Specifies that the security appliance redirect HTTP connections to HTTPS.
<code>http server enable</code>	Enables the HTTP server.
<code>show running-config http</code>	Displays the hosts that can access the HTTP server, and whether or not the HTTP server is enabled.

http redirect

To specify that the security appliance redirect HTTP connections to HTTPS, use the **http redirect** command in global configuration mode. To remove a specified http redirect command from the configuration, use the **no** version of this command. To remove all http redirect commands from the configuration, use the **no** version of this command without arguments.

http redirect *interface* [*port*]

no http redirect [*interface*]

Syntax Description

<i>interface</i>	Identifies the interface for which the security appliance should redirect HTTP requests to HTTPS.
<i>port</i>	Identifies the port the security appliance listens on for HTTP requests, which it then redirects to HTTPS. By default it listens on port 80,

Defaults

HTTP redirect is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The interface requires an access list that permits HTTP. Otherwise the security appliance does not listen to port 80, or to any other port that you configure for HTTP.

Examples

The following example shows how to configure HTTP redirect for the inside interface, keeping the default port 80:

```
hostname(config)# http redirect inside
```


Related Commands

Command	Description
clear configure http	Removes the HTTP configuration: disables the HTTP server and removes hosts that can access the HTTP server.
http	Specifies hosts that can access the HTTP server by IP address and subnet mask. Specifies the security appliance interface through which the host accesses the HTTP server.
http authentication-certificate	Requires authentication via certificate from users who are establishing HTTPS connections to the security appliance.
http server enable	Enables the HTTP server.
show running-config http	Displays the hosts that can access the HTTP server, and whether or not the HTTP server is enabled.

http server enable

To enable the security appliance HTTP server, use the **http server enable** command in global configuration mode. To disable the HTTP server, use the **no** form of this command.

http server enable

no http server enable

Defaults

The HTTP server is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example shows how to enable the HTTP server.

```
hostname(config)# http server enable
```

Related Commands

Command	Description
clear configure http	Removes the HTTP configuration: disables the HTTP server and removes hosts that can access the HTTP server.
http	Specifies hosts that can access the HTTP server by IP address and subnet mask. Specifies the security appliance interface through which the host accesses the HTTP server.
http authentication-certificate	Requires authentication via certificate from users who are establishing HTTPS connections to the security appliance.
http redirect	Specifies that the security appliance redirect HTTP connections to HTTPS.
show running-config http	Displays the hosts that can access the HTTP server, and whether or not the HTTP server is enabled.

http-map

To create an HTTP map for applying enhanced HTTP inspection parameters, use the **http-map** command in global configuration mode. To remove the command, use the **no** form of this command.

http-map *map_name*

no http-map *map_name*

Syntax Description

<i>map_name</i>	The name of the HTTP map.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced in 7.0.

Usage Guidelines

The enhanced HTTP inspection feature, which is also known as an application firewall, verifies that HTTP messages conform to RFC 2616, use RFC-defined and supported extension methods, and comply with various other criteria. This can help prevent attackers from using HTTP messages for circumventing network security policy.



Note

When you enable HTTP inspection with an HTTP map, strict HTTP inspection with the action reset and log is enabled by default. You can change the actions performed in response to inspection failure, but you cannot disable strict inspection as long as the HTTP map remains enabled.

In many cases, you can configure the criteria and how the security appliance responds when the criteria are not met. The criteria that you can apply to HTTP messages include the following:

- Does not include any method on a configurable list.
- Message body size is within configurable limits.
- Request and response message header size is within a configurable limit.
- URI length is within a configurable limit.
- The content-type in the message body matches the header.
- The content-type in the response message matches the accept-type field in the request message.

- The content-type in the message is included in a predefined internal list.
- Message meets HTTP RFC format criteria.
- Presence or absence of selected supported applications.
- Presence or absence of selected encoding types.

**Note**

The actions that you can specify for messages that fail the criteria set using the different configuration commands include **allow**, **reset**, or **drop**. In addition to these actions, you can specify to log the event or not.

Table 5-2 summarizes the configuration commands available in HTTP map configuration mode. Click on an entry to open a command page that provides the detailed syntax for each command.

Table 5-2 HTTP Map Configuration Commands

Command	Description
content-length	Enables inspection based on the length of the HTTP content.
content-type-verification	Enables inspection based on the type of HTTP content.
max-header-length	Enables inspection based on the length of the HTTP header.
max-uri-length	Enables inspection based on the length of the URI.
port-misuse	Enables port misuse application inspection.
request-method	Enables inspection based on the HTTP request method.
strict-http	Enables strict HTTP inspection.
transfer-encoding	Enables inspection based on the transfer encoding type.

Examples

The following is sample output showing how to identify HTTP traffic, define an HTTP map, define a policy, and apply the policy to the outside interface.

```
hostname(config)# class-map http-port
hostname(config-cmap)# match port tcp eq 80
hostname(config-cmap)# exit
hostname(config)# http-map inbound_http
hostname(config-http-map)# content-length min 100 max 2000 action reset log
hostname(config-http-map)# content-type-verification match-req-rsp reset log
hostname(config-http-map)# max-header-length request bytes 100 action log reset
hostname(config-http-map)# max-uri-length 100 action reset log
hostname(config-http-map)# exit
hostname(config)# policy-map inbound_policy
hostname(config-pmap)# class http-port
hostname(config-pmap-c)# inspect http inbound_http
hostname(config-pmap-c)# exit
hostname(config-pmap)# exit
hostname(config)# service-policy inbound_policy interface outside
```

This example causes the security appliance to reset the connection and create a syslog entry when it detects any traffic that contain the following:

- Messages less than 100 bytes or exceeding 2000 bytes
- Unsupported content types
- HTTP headers exceeding 100 bytes

- URIs exceeding 100 bytes

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug appfw	Displays detailed information about HTTP application inspection.
debug http-map	Displays detailed information about traffic associated with an HTTP map.
inspect http	Applies a specific HTTP map to use for application inspection.
policy-map	Associates a class map with specific security actions.

http-proxy

To configure an HTTP proxy server, use the **http-proxy** command in webvpn mode. To remove the HTTP proxy server from the configuration, use the **no** form of this command.

This is an external proxy server the security appliance uses for HTTP requests.

http-proxy *address* [*port*]

no http-proxy

Syntax Description

<i>address</i>	Specifies the IP address for the external HTTP proxy server.
<i>port</i>	Specifies the port the HTTP proxy server uses. The default port is 80, which is the port the security appliance uses if you do not supply a value.

Defaults

No HTTP proxy server is configured by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to configure an HTTP proxy server with an IP address of 10.10.10.7 using port 80:

```
hostname(config)# webvpn
hostname(config-webvpn)# http-proxy 10.10.10.7
```

https-proxy

To configure an HTTPS proxy server, use the **https-proxy** command in webvpn mode. To remove the HTTPS proxy server from the configuration, use the no form of this command.

This is an external proxy server the security appliance uses for HTTPS requests.

https-proxy *address* [*port*]

no https-proxy

Syntax Description

<i>address</i>	Specifies the IP address for the external HTTPS proxy server.
<i>port</i>	Specifies the port the HTTPS proxy server uses. The default port is 443, which is the port the security appliance uses if you do not supply a value.

Defaults

No HTTPS proxy server is configured by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to configure an HTTPS proxy server with an IP address of 10.10.10.1 using port 443:

```
hostname(config)# webvpn
hostname(config-webvpn)# https-proxy 10.10.10.1 443
```

hw-module module recover

To load a recovery software image from a TFTP server to an intelligent SSM (for example, the AIP SSM), or to configure network settings to access the TFTP server, use the **hw-module module recover** command in privileged EXEC mode. You might need to recover an SSM using this command if, for example, the SSM is unable to load a local image. This command is not available for interface SSMs (for example, the 4GE SSM).

hw-module module 1 recover {boot | stop | configure [url *tftp_url* | ip *port_ip_address* | gateway *gateway_ip_address* | vlan *vlan_id*]}

Syntax Description	1	Specifies the slot number, which is always 1.
	boot	Initiates recovery of this SSM and downloads a recovery image according to the configure settings. The SSM then reboots from the new image.
	configure	Configures the network parameters to download a recovery image. If you do not enter any network parameters after the configure keyword, you are prompted for the information.
	gateway <i>gateway_ip_address</i>	(Optional) The gateway IP address for access to the TFTP server through the SSM management interface.
	ip <i>port_ip_address</i>	(Optional) The IP address of the SSM management interface.
	stop	Stops the recovery action, and stops downloading the recovery image. The SSM boots from the original image. You must enter this command within 30 to 45 seconds after starting recovery using the hw-module module boot command. If you issue the stop command after this period, it might cause unexpected results, such as the SSM becoming unresponsive.
	url <i>tftp_url</i>	(Optional) The URL for the image on a TFTP server, in the following format: tftp://server/[path/]filename
	vlan <i>vlan_id</i>	(Optional) Sets the VLAN ID for the management interface.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines

This command is only available when the SSM is in the Up, Down, Unresponsive, or Recovery state. See the **show module** command for state information.

Examples

The following example sets the SSM to download an image from a TFTP server:

```
hostname# hw-module module 1 recover configure
Image URL [tftp://127.0.0.1/myimage]: tftp://10.1.1.1/ids-newimg
Port IP Address [127.0.0.2]: 10.1.2.10
Port Mask [255.255.255.254]: 255.255.255.0
Gateway IP Address [1.1.2.10]: 10.1.2.254
VLAN ID [0]: 100
```

The following example recovers the SSM:

```
hostname# hw-module module 1 recover boot
The module in slot 1 will be recovered. This may
erase all configuration and all data on that device and
attempt to download a new image for it.
Recover module in slot 1? [confirm]
```

Related Commands

Command	Description
debug module-boot	Shows debug messages about the SSM booting process.
hw-module module reset	Shuts down an SSM and performs a hardware reset.
hw-module module reload	Reloads the intelligent SSM software.
hw-module module shutdown	Shuts down the SSM software in preparation for being powered off without losing configuration data.
show module	Shows SSM information.

hw-module module reload

To reload an intelligent SSM software (for example, the AIP SSM), use the **hw-module module reload** command in privileged EXEC mode. This command is not available for interface SSMs (for example, the 4GE SSM).

hw-module module 1 reload

Syntax Description	1 Specifies the slot number, which is always 1.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	This command is only valid when the SSM status is Up. See the show module command for state information.
	This command differs from the hw-module module reset command, which also performs a hardware reset.

Examples	The following example reloads the SSM in slot 1: <pre>hostname# hw-module module 1 reload Reload module in slot 1? [confirm] y Reload issued for module in slot 1 %XXX-5-505002: Module in slot 1 is reloading. Please wait... %XXX-5-505006: Module in slot 1 is Up.</pre>

Related Commands	Command	Description
	debug module-boot	Shows debug messages about the SSM booting process.
	hw-module module recover	Recovers an intelligent SSM by loading a recovery image from a TFTP server.

Command	Description
hw-module module reset	Shuts down an SSM and performs a hardware reset.
hw-module module shutdown	Shuts down the SSM software in preparation for being powered off without losing configuration data.
show module	Shows SSM information.

hw-module module reset

To shut down and reset the SSM hardware, use the **hw-module module reset** command in privileged EXEC mode.

hw-module module 1 reset

Syntax Description	1 Specifies the slot number, which is always 1.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	This command is only valid when the SSM status is Up, Down, Unresponsive, or Recover. See the show module command for state information.

When the SSM is in an Up state, the **hw-module module reset** command prompts you to shut down the software before resetting.

You can recover intelligent SSMs (for example, the AIP SSM) using the **hw-module module recover** command. If you enter the **hw-module module reset** while the SSM is in a Recover state, the SSM does not interrupt the recovery process. The **hw-module module reset** command performs a hardware reset of the SSM, and the SSM recovery continues after the hardware reset. You might want to reset the SSM during recovery if the SSM hangs; a hardware reset might resolve the issue.

This command differs from the **hw-module module reload** command which only reloads the software and does not perform a hardware reset.

Examples	The following example resets an SSM in slot 1 that is in the Up state:

```
hostname# hw-module module 1 reset
The module in slot 1 should be shut down before
resetting it or loss of configuration may occur.
Reset module in slot 1? [confirm] y
Reset issued for module in slot 1
%XXX-5-505001: Module in slot 1 is shutting down. Please wait...
%XXX-5-505004: Module in slot 1 shutdown is complete.
```

```
%XXX-5-505003: Module in slot 1 is resetting. Please wait...  
%XXX-5-505006: Module in slot 1 is Up.
```

Related Commands

Command	Description
debug module-boot	Shows debug messages about the SSM booting process.
hw-module module recover	Recovers an intelligent SSM by loading a recovery image from a TFTP server.
hw-module module reload	Reloads the intelligent SSM software.
hw-module module shutdown	Shuts down the SSM software in preparation for being powered off without losing configuration data.
show module	Shows SSM information.

hw-module module shutdown

To shut down the SSM software, use the **hw-module module shutdown** command in privileged EXEC mode.

hw-module module 1 shutdown

Syntax Description	1	Specifies the slot number, which is always 1.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	Shutting down the SSM software prepares the SSM to be safely powered off without losing configuration data.
	This command is only valid when the SSM status is Up or Unresponsive. See the show module command for state information.

Examples	The following example shuts down an SSM in slot 1:
	<pre>hostname# hw-module module 1 shutdown Shutdown module in slot 1? [confirm] y Shutdown issued for module in slot 1 hostname# %XXX-5-505001: Module in slot 1 is shutting down. Please wait... %XXX-5-505004: Module in slot 1 shutdown is complete.</pre>

Related Commands	Command	Description
	debug module-boot	Shows debug messages about the SSM booting process.
	hw-module module recover	Recovers an intelligent SSM by loading a recovery image from a TFTP server.

Command	Description
hw-module module reload	Reloads the intelligent SSM software.
hw-module module reset	Shuts down an SSM and performs a hardware reset.
show module	Shows SSM information.

icmp

To configure access rules for ICMP traffic that terminates at a security appliance interface, use the **icmp** command. To remove the configuration, use the **no** form of this command.

icmp {**permit** | **deny**} *ip_address net_mask [icmp_type] if_name*

no icmp {**permit** | **deny**} *ip_address net_mask [icmp_type] if_name*

Syntax Description

deny	Deny access if the conditions are matched.
<i>icmp_type</i>	(Optional) ICMP message type (see Table 5-3).
<i>if_name</i>	The interface name.
<i>ip_address</i>	The IP address of the host sending ICMP messages to the interface.
<i>net_mask</i>	The mask to be applied to <i>ip_address</i> .
permit	Permit access if the conditions are matched.

Defaults

The default behavior of the security appliance is to allow all ICMP traffic *to* the security appliance interfaces. However, by default the security appliance does not respond to ICMP echo requests directed to a broadcast address. The security appliance also denies ICMP messages received at the outside interface for destinations on a protected interface.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was previously existing.

Usage Guidelines

The **icmp** command controls ICMP traffic that terminates on any security appliance interface. If no ICMP control list is configured, then the security appliance accepts all ICMP traffic that terminates at any interface, including the outside interface. However, by default, the security appliance does not respond to ICMP echo requests directed to a broadcast address.

The **icmp deny** command disables pinging to an interface, and the **icmp permit** command enables pinging to an interface. With pinging disabled, the security appliance cannot be detected on the network. This is also referred to as configurable proxy pinging.

Use the [access-list extended](#) or [access-group](#) commands for ICMP traffic that is routed *through* the security appliance for destinations on a protected interface.

We recommend that you grant permission for the ICMP unreachable message type (type 3). Denying ICMP unreachable messages disables ICMP Path MTU discovery, which can halt IPsec and PPTP traffic. See RFC 1195 and RFC 1435 for details about Path MTU Discovery.

If an ICMP control list is configured for an interface, then the security appliance first matches the specified ICMP traffic and then applies an implicit deny for all other ICMP traffic on that interface. That is, if the first matched entry is a permit entry, the ICMP packet continues to be processed. If the first matched entry is a deny entry or an entry is not matched, the security appliance discards the ICMP packet and generates a syslog message. An exception is when an ICMP control list is not configured; in that case, a **permit** statement is assumed.

Table 5-3 lists the supported ICMP type values.

Table 5-3 *ICMP Type Literals*

ICMP Type	Literal
0	echo-reply
3	unreachable
4	source-quench
5	redirect
6	alternate-address
8	echo
9	router-advertisement
10	router-solicitation
11	time-exceeded
12	parameter-problem
13	timestamp-request
14	timestamp-reply
15	information-request
16	information-reply
17	mask-request
18	mask-reply
31	conversion-error
32	mobile-redirect

Examples

The following example denies all ping requests and permits all unreachable messages at the outside interface:

```
hostname(config)# icmp permit any unreachable outside
```

The following example permits host 172.16.2.15 or hosts on subnet 172.22.1.0/16 to ping the outside interface:

```
hostname(config)# icmp permit host 172.16.2.15 echo-reply outside
hostname(config)# icmp permit 172.22.1.0 255.255.0.0 echo-reply outside
hostname(config)# icmp permit any unreachable outside
```

Related Commands	Commands	Description
	clear configure icmp	Clears the ICMP configuration.
	debug icmp	Enables the display of debug information for ICMP.
	show icmp	Displays ICMP configuration.
	timeout icmp	Configures the idle timeout for ICMP.

icmp-object

To add icmp-type object groups, use the **icmp-object** command in icmp-type configuration mode. To remove network object groups, use the **no** form of this command.

icmp-object *icmp_type*

no group-object *icmp_type*

Syntax Description

icmp_type Specifies an icmp-type name.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Icmp-type configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **icmp-object** command is used with the **object-group** command to define an icmp-type object. It is used in icmp-type configuration mode.

ICMP type numbers and names include:

Number	ICMP Type Name
0	echo-reply
3	unreachable
4	source-quench
5	redirect
6	alternate-address
8	echo
9	router-advertisement
10	router-solicitation
11	time-exceeded
12	parameter-problem

Number	ICMP Type Name
13	timestamp-request
14	timestamp-reply
15	information-request
16	information-reply
17	address-mask-request
18	address-mask-reply
31	conversion-error
32	mobile-redirect

Examples

The following example shows how to use the **icmp-object** command in icmp-type configuration mode:

```
hostname(config)# object-group icmp-type icmp_allowed
hostname(config-icmp-type)# icmp-object echo
hostname(config-icmp-type)# icmp-object time-exceeded
hostname(config-icmp-type)# exit
```

Related Commands

Command	Description
clear configure object-group	Removes all the object-group commands from the configuration.
network-object	Adds a network object to a network object group.
object-group	Defines object groups to optimize your configuration.
port-object	Adds a port object to a service object group.
show running-config object-group	Displays the current object groups.

id-cert-issuer

To indicate whether the system accepts peer certificates issued by the CA associated with this trustpoint, use the **id-cert-issuer** command in crypto ca trustpoint configuration mode. Use the **no** form of this command to disallow certificates that were issued by the CA associated with the trustpoint. This is useful for trustpoints that represent widely used root CAs.

id-cert-issuer

no id-cert-issuer

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting is enabled (identity certificates are accepted).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use this command to limit certificate acceptance to those issued by the subordinate certificate of a widely used root certificate. If you do not allow this feature, the security appliance rejects any IKE peer certificate signed by this issuer.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and lets an administrator accept identity certificates signed by the issuer for trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# id-cert-issuer
hostname(ca-trustpoint)#
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint submode.
default enrollment	Returns enrollment parameters to their defaults.
enrollment retry count	Specifies the number of retries to attempt to send an enrollment request.

Command	Description
enrollment retry period	Specifies the number of minutes to wait before trying to send an enrollment request.
enrollment terminal	Specifies cut and paste enrollment with this trustpoint.

igmp

To reinstate IGMP processing on an interface, use the **igmp** command in interface configuration mode. To disable IGMP processing on an interface, use the **no** form of this command.

igmp

no igmp

Syntax Description

This command has no arguments or keywords.

Defaults

Enabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Only the **no** form of this command appears in the running configuration.

Examples

The following example disables IGMP processing on the selected interface:

```
hostname(config-if)# no igmp
```

Related Commands

Command	Description
show igmp groups	Displays the multicast groups with receivers that are directly connected to the security appliance and that were learned through IGMP.
show igmp interface	Displays multicast information for an interface.

igmp access-group

To control the multicast groups that hosts on the subnet serviced by an interface can join, use the **igmp access-group** command in interface configuration mode. To disable groups on the interface, use the **no** form of this command.

igmp access-group *acl*

no igmp access-group *acl*

Syntax Description

acl Name of an IP access list. You can specify a standard or an extended access list. However, if you specify an extended access list, only the destination address is matched; you should specify **any** for the source.

Defaults

All groups are allowed to join on an interface.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was moved to interface configuration mode. Earlier versions required you to enter multicast interface configuration mode, which is no longer available.

Examples

The following example limits hosts permitted by access list 1 to join the group:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# igmp access-group 1
```

Related Commands

Command	Description
show igmp interface	Displays multicast information for an interface.

igmp forward interface

To enable forwarding of all IGMP host reports and leave messages received to the interface specified, use the **igmp forward interface** command in interface configuration mode. To remove the forwarding, use the **no** form of this command.

igmp forward interface *if-name*

no igmp forward interface *if-name*

Syntax Description

if-name Logical name of the interface.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was moved to interface configuration mode. Earlier versions required you to enter multicast interface configuration mode, which is no longer available.

Usage Guidelines

Enter this command on the input interface. This command is used for stub multicast routing and cannot be configured concurrently with PIM.

Examples

The following example forwards IGMP host reports from the current interface to the specified interface:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# igmp forward interface outside
```

Related Commands

Command	Description
show igmp interface	Displays multicast information for an interface.

igmp join-group

To configure an interface to be a locally connected member of the specified group, use the **igmp join-group** command in interface configuration mode. To cancel membership in the group, use the **no** form of this command.

igmp join-group *group-address*

no igmp join-group *group-address*

Syntax Description

group-address IP address of the multicast group.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was moved to interface configuration mode. Earlier versions required you to enter multicast interface configuration mode, which is no longer available.

Usage Guidelines

This command configures a security appliance interface to be a member of a multicast group. The **igmp join-group** command causes the security appliance to both accept and forward multicast packets destined for the specified multicast group.

To configure the security appliance to forward the multicast traffic without being a member of the multicast group, use the **igmp static-group** command.

Examples

The following example configures the selected interface to join the IGMP group 255.2.2.2:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# igmp join-group 225.2.2.2
```

Related Commands

Command	Description
igmp static-group	Configure the interface to be a statically connected member of the specified multicast group.

igmp limit

To limit the number of IGMP states on a per-interface basis, use the **igmp limit** command in interface configuration mode. To restore the default limit, use the **no** form of this command.

igmp limit *number*

no igmp limit [*number*]

Syntax Description

<i>number</i>	Number of IGMP states allowed on the interface. Valid values range from 0 to 500. The default value is 500. Setting this value to 0 prevents learned groups from being added, but manually defined memberships (using the igmp join-group and igmp static-group commands) are still permitted.

Defaults

The default is 500.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced. It replaced the igmp max-groups command.

Examples

The following example limits the number of hosts that can join on the interface to 250:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# igmp limit 250
```

Related Commands

Command	Description
igmp	Reinstates IGMP processing on an interface.
igmp join-group	Configure an interface to be a locally connected member of the specified group.
igmp static-group	Configure the interface to be a statically connected member of the specified multicast group.

igmp query-interval

To configure the frequency at which IGMP host query messages are sent by the interface, use the **igmp query-interval** command in interface configuration mode. To restore the default frequency, use the **no** form of this command.

igmp query-interval *seconds*

no igmp query-interval *seconds*

Syntax Description

seconds Frequency, in seconds, at which to send IGMP host query messages. Valid values range from 1 to 3600. The default is 125 seconds.

Defaults

The default query interval is 125 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was moved to interface configuration mode. Earlier versions required you to enter multicast interface configuration mode, which is no longer available.

Usage Guidelines

Multicast routers send host query messages to discover which multicast groups have members on the networks attached to the interface. Hosts respond with IGMP report messages indicating that they want to receive multicast packets for specific groups. Host query messages are addressed to the all-hosts multicast group, which has an address of 224.0.0.1 TTL value of 1.

The designated router for a LAN is the only router that sends IGMP host query messages:

- For IGMP Version 1, the designated router is elected according to the multicast routing protocol that runs on the LAN.
- For IGMP Version 2, the designated router is the lowest IP-addressed multicast router on the subnet.

If the router hears no queries for the timeout period (controlled by the **igmp query-timeout** command), it becomes the querier.



Caution

Changing this value may severely impact multicast forwarding.

Examples

The following example changes the IGMP query interval to 120 seconds:

```
hostname(config)# interface gigabitethernet 0/0  
hostname(config-if)# igmp query-interval 120
```

Related Commands

Command	Description
igmp	Configures the maximum response time advertised in IGMP queries.
query-max-response-time	
igmp query-timeout	Configures the timeout period before the router takes over as the querier for the interface after the previous querier has stopped querying.

igmp query-max-response-time

To specify the maximum response time advertised in IGMP queries, use the **igmp query-max-response-time** command in interface configuration mode. To restore the default response time value, use the **no** form of this command.

igmp query-max-response-time *seconds*

no igmp query-max-response-time [*seconds*]

Syntax Description

seconds Maximum response time, in seconds, advertised in IGMP queries. Valid values are from 1 to 25. The default value is 10 seconds.

Defaults

10 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was moved to interface configuration mode. Earlier versions required you to enter multicast interface configuration mode, which is no longer available.

Usage Guidelines

This command is valid only when IGMP Version 2 or 3 is running.

This command controls the period during which the responder can respond to an IGMP query message before the router deletes the group.

Examples

The following example changes the maximum query response time to 8 seconds:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# igmp query-max-response-time 8
```

Related Commands	Command	Description
	igmp query-interval	Configures the frequency at which IGMP host query messages are sent by the interface.
	igmp query-timeout	Configures the timeout period before the router takes over as the querier for the interface after the previous querier has stopped querying.

igmp query-timeout

To configure the timeout period before the interface takes over as the querier after the previous querier has stopped querying, use the **igmp query-timeout** command in interface configuration mode. To restore the default value, use the **no** form of this command.

igmp query-timeout *seconds*

no igmp query-timeout [*seconds*]

Syntax Description

<i>seconds</i>	Number of seconds that the router waits after the previous querier has stopped querying and before it takes over as the querier. Valid values are from 60 to 300 seconds. The default value is 255 seconds.

Defaults

The default query interval is 255 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command requires IGMP Version 2 or 3.

Examples

The following example configures the router to wait 200 seconds from the time it received the last query before it takes over as the querier for the interface:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# igmp query-timeout 200
```

Related Commands

Command	Description
igmp query-interval	Configures the frequency at which IGMP host query messages are sent by the interface.
igmp query-max-response-time	Configures the maximum response time advertised in IGMP queries.

igmp static-group

To configure the interface to be a statically connected member of the specified multicast group, use the **igmp static-group** command in interface configuration mode. To remove the static group entry, use the **no** form of this command.

igmp static-group *group*

no igmp static-group *group*

Syntax Description

group IP multicast group address.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

When configured with the **igmp static-group** command, the security appliance interface does not accept multicast packets destined for the specified group itself; it only forwards them. To configure the security appliance both accept and forward multicast packets for a specific multicast group, use the **igmp join-group** command. If the **igmp join-group** command is configured for the same group address as the **igmp static-group** command, the **igmp join-group** command takes precedence, and the group behaves like a locally joined group.

Examples

The following example adds the selected interface to the multicast group 239.100.100.101:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# igmp static-group 239.100.100.101
```

Related Commands

Command	Description
igmp join-group	Configures an interface to be a locally connected member of the specified group.

igmp version

To configure which version of IGMP the interface uses, use the **igmp version** command in interface configuration mode. To restore version to the default, use the **no** form of this command.

igmp version { 1 | 2 }

no igmp version [1 | 2]

Syntax Description

1	IGMP Version 1.
2	IGMP Version 2.

Defaults

IGMP Version 2.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was moved to interface configuration mode. Earlier versions required you to enter multicast interface configuration mode, which is no longer available.

Usage Guidelines

All routers on the subnet must support the same version of IGMP. Hosts can have any IGMP version (1 or 2) and the security appliance will correctly detect their presence and query them appropriately.

Some commands require IGMP Version 2, such as the **igmp query-max-response-time** and **igmp query-timeout** commands.

Examples

The following example configures the selected interface to use IGMP Version 1:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# igmp version 1
```

Related Commands	Command	Description
	igmp query-max-response-time	Configures the maximum response time advertised in IGMP queries.
	igmp query-timeout	Configures the timeout period before the router takes over as the querier for the interface after the previous querier has stopped querying.

ignore lsa mospf

To suppress the sending of syslog messages when the router receives link-state advertisement (LSA) Type 6 Multicast OSPF (MOSPF) packets, use the **ignore lsa mospf** command in router configuration mode. To restore the sending of the syslog messages, use the **no** form of this command.

ignore lsa mospf

no ignore lsa mospf

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Type 6 MOSPF packets are unsupported.

Examples

The following example cause LSA Type 6 MOSPF packets to be ignored:

```
hostname(config-router)# ignore lsa mospf
```

Related Commands

Command	Description
show running-config router ospf	Displays the OSPF router configuration.

imap4s

To enter IMAP4S configuration mode, use the **imap4s** command in global configuration mode. To remove any commands entered in IMAP4S command mode, use the **no** form of this command.

IMAP4 is a client/server protocol in which your Internet server receives and holds e-mail for you. You (or your e-mail client) can view just the heading and the sender of the letter and then decide whether to download the mail. You can also create and manipulate multiple folders or mailboxes on the server, delete messages, or search for certain parts or an entire note. IMAP requires continual access to the server during the time that you are working with your mail. IMAP4S lets you receive e-mail over an SSL connection.

imap4s

no imap4s

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to enter IMAP4S configuration mode:

```
hostname(config)# imap4s
hostname(config-imap4s)#
```

Related Commands

Command	Description
clear configure imap4s	Removes the IMAP4S configuration.
show running-config imap4s	Displays the running configuration for IMAP4S.

inspect ctiqbe

To enable CTIQBE protocol inspection, use the **inspect ctiqbe** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To disable inspection, use the **no** form of this command.

inspect ctiqbe

no inspect ctiqbe

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced in 7.0. It replaces the previously existing fixup command, which is now deprecated.

Usage Guidelines

The **inspect ctiqbe** command enables CTIQBE protocol inspection, which supports NAT, PAT, and bidirectional NAT. This enables Cisco IP SoftPhone and other Cisco TAPI/JTAPI applications to work successfully with Cisco CallManager for call setup across the security appliance.

The Telephony Application Programming Interface (TAPI) and Java Telephony Application Programming Interface (JTAPI) are used by many Cisco VoIP applications. Computer Telephony Interface Quick Buffer Encoding (CTIQBE) is used by Cisco TAPI Service Provider (TSP) to communicate with Cisco CallManager.

The following summarizes limitations that apply when using CTIQBE application inspection:

- CTIQBE application inspection does not support configurations using the **alias** command.
- Stateful Failover of CTIQBE calls is *not* supported.
- Using the **debug ctiqbe** command may delay message transmission, which may have a performance impact in a real-time environment. When you enable this debugging or logging and Cisco IP SoftPhone seems unable to complete call setup through the security appliance, increase the timeout values in the Cisco TSP settings on the system running Cisco IP SoftPhone.
- CTIQBE application inspection does *not* support CTIQBE messages fragmented in multiple TCP packets.

The following summarizes special considerations when using CTIQBE application inspection in specific scenarios:

- If two Cisco IP SoftPhones are registered with different Cisco CallManagers, which are connected to different interfaces of the security appliance, calls between these two phones will fail.
- When Cisco CallManager is located on the higher security interface compared to Cisco IP SoftPhones, if NAT or outside NAT is required for the Cisco CallManager IP address, the mapping must be static as Cisco IP SoftPhone requires the Cisco CallManager IP address to be specified explicitly in its Cisco TSP configuration on the PC.
- When using PAT or Outside PAT, if the Cisco CallManager IP address is to be translated, its TCP port 2748 must be statically mapped to the **same port** of the PAT (interface) address for Cisco IP SoftPhone registrations to succeed. The CTIQBE listening port (TCP 2748) is fixed and is not user-configurable on Cisco CallManager, Cisco IP SoftPhone, or Cisco TSP.

Inspecting Signaling Messages

For inspecting signaling messages, the **inspect ctiqbe** command often needs to determine locations of the media endpoints (for example, IP phones).

This information is used to prepare access-control and NAT state for media traffic to traverse the firewall transparently without manual configuration.

In determining these locations, the **inspect ctiqbe** command does **not** use the tunnel default gateway route. A tunnel default gateway route is a route of the form **route interface 0 0 metric tunneled**. This route overrides the default route for packets that egress from IPSec tunnels. Therefore, if the **inspect ctiqbe** command is desired for VPN traffic, do not configure the tunnel default gateway route. Instead, use other static routing or dynamic routing.

Examples

You enable the CTIQBE inspection engine as shown in the following example, which creates a class map to match CTIQBE traffic on the default port (2748). The service policy is then applied to the outside interface.

```
hostname(config)# class-map ctiqbe-port
hostname(config-cmap)# match port tcp eq 2748
hostname(config-cmap)# exit
hostname(config)# policy-map ctiqbe_policy
hostname(config-pmap)# class ctiqbe-port
hostname(config-pmap-c)# inspect ctiqbe
hostname(config-pmap-c)# exit
hostname(config)# service-policy ctiqbe_policy interface outside
```

To enable CTIQBE inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
show conn	Displays the connection state for different connection types.
show ctiqbe	Displays information regarding the CTIQBE sessions established across the security appliance. Displays information about the media connections allocated by the CTIQBE inspection engine.
timeout	Sets the maximum idle time duration for different protocols and session types.

inspect cuseeme

To enable CU-SeeMe application inspection or to change the ports to which the security appliance listens, use the **inspect cuseeme command** in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect cuseeme

no inspect cuseeme

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

The **inspect cuseeme** command provides application inspection for the CU-SeeMe application.

Use the *port* option to change the default port assignment from 389. Use the *-port* option to apply ILS inspection to a range of port numbers.

With CU-SeeMe clients, one user can connect directly to another (CU-SeeMe or other H.323 client) for person-to-person audio, video, and data collaboration. CU-SeeMe clients can conference in a mixed client environment that includes both CU-SeeMe clients and H.323-compliant clients from other vendors.

In the background, CU-SeeMe clients operate in two very different modes. When connected to another CU-SeeMe client or CU-SeeMe Conference Server, the client sends information in CU-SeeMe mode.

When connected to an H.323-compliant videoconferencing client from a different vendor, CU-SeeMe clients communicate using the H.323-standard format in H.323 mode.

CU-SeeMe is supported through H.323 inspection, as well as performing NAT on the CU-SeeMe control stream, which operates on UDP port 7648.

Examples

You enable the CU-SeeMe inspection engine as shown in the following example, which creates a class map to match CU-SeeMe traffic on the default port (7648). The service policy is then applied to the outside interface.

```
hostname(config)# class-map cuseeme-port
hostname(config-cmap)# match port tcp eq 7648
hostname(config-cmap)# exit
hostname(config)# policy-map cuseeme_policy
hostname(config-pmap)# class cuseeme-port
hostname(config-pmap-c)# inspect cuseeme
hostname(config-pmap-c)# exit
hostname(config)# service-policy cuseeme_policy interface outside
```

To enable CU-SeeMe inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

inspect dns

To enable DNS inspection (if it has been previously disabled), use the **inspect dns** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. Use the **inspect dns** command to specify the maximum DNS packet length. To disable DNS inspection, use the **no** form of this command.

inspect dns [**maximum-length** *max_pkt_length*]

no inspect dns [**maximum-length** *max_pkt_length*]

Syntax Description

maximum-length	(Optional) Specifies the maximum DNS packet length. The default is 512. If you enter the inspect dns command without the maximum-length option, DNS packet size is not checked
<i>max_pkt_length</i>	The maximum DNS packet length. Longer packets will be dropped.

Defaults

This command is enabled by default.

The default **maximum-length** for the DNS packet size is 512.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

DNS guard tears down the DNS session associated with a DNS query as soon as the DNS reply is forwarded by the security appliance. DNS guard also monitors the message exchange to ensure that the ID of the DNS reply matches the ID of the DNS query.

When DNS inspection is enabled, which it is the default, the security appliance performs the following additional tasks:

- Translates the DNS record based on the configuration completed using the **alias**, **static** and **nat** commands (DNS rewrite). Translation only applies to the A-record in the DNS reply. Therefore, reverse lookups, which request the PTR record, are not affected by DNS rewrite.

**Note**

DNS rewrite is not applicable for PAT because multiple PAT rules are applicable for each A-record and the PAT rule to use is ambiguous.

- Enforces the maximum DNS message length (the default is 512 bytes and the maximum length is 65535 bytes). Reassembly is performed as necessary to verify that the packet length is less than the maximum length configured. The packet is dropped if it exceeds the maximum length.

**Note**

If you enter the **inspect dns** command without the **maximum-length** option, DNS packet size is not checked

- Enforces a domain-name length of 255 bytes and a label length of 63 bytes.
- Verifies the integrity of the domain-name referred to by the pointer if compression pointers are encountered in the DNS message.
- Checks to see if a compression pointer loop exists.

A single connection is created for multiple DNS sessions, as long as they are between the same two hosts, and the sessions have the same 5-tuple (source/destination IP address, source/destination port, and protocol). DNS identification is tracked by *app_id*, and the idle timer for each *app_id* runs independently.

Because the *app_id* expires independently, a legitimate DNS response can only pass through the security appliance within a limited period of time and there is no resource build-up. However, if you enter the **show conn** command, you will see the idle timer of a DNS connection being reset by a new DNS session. This is due to the nature of the shared DNS connection and is by design.

How DNS Rewrite Works

When DNS inspection is enabled, DNS rewrite provides full support for NAT of DNS messages originating from any interface.

If a client on an inside network requests DNS resolution of an inside address from a DNS server on an outside interface, the DNS A-record is translated correctly. If the DNS inspection engine is disabled, the A-record is not translated.

DNS rewrite performs two functions:

- Translating a public address (the routable or “mapped” address) in a DNS reply to a private address (the “real” address) when the DNS client is on a private interface.
- Translating a private address to a public address when the DNS client is on the public interface.

As long as DNS inspection remains enabled, you can configure DNS rewrite using the **alias**, **static**, or **nat** commands. For details about the syntax and function of these commands, refer to the appropriate command page.

Examples

The following example changes the maximum DNS packet length to 1500 bytes. Although DNS inspection is enabled by default, you still need to create a traffic map to identify DNS traffic and then apply the policy map to the appropriate interface.

```
hostname(config)# class-map dns-port
hostname(config-cmap)# match port udp eq 53
hostname(config-cmap)# exit
hostname(config)# policy-map sample_policy
hostname(config-pmap)# class dns-port
```

```
hostname(config-pmap-c)# inspect dns maximum-length 1500
hostname(config-pmap-c)# exit
hostname(config)# service-policy sample_policy interface outside
```

To change the maximum DNS packet length for all interfaces, use the **global** parameter in place of **interface outside**.

The following example shows how to disable DNS:

```
hostname(config)# policy-map sample_policy
hostname(config-pmap)# class dns-port
hostname(config-pmap-c)# no inspect dns
hostname(config-pmap-c)# exit
hostname(config)# service-policy sample_policy interface outside
```

Related Commands

Commands	Description
dns-guard	Enables the DNS guard function.
class-map	Defines the traffic class to which to apply security actions.
debug dns	Enables debug information for DNS.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

inspect esmtp

To enable SMTP application inspection or to change the ports to which the security appliance listens, use the **inspect esmtp** command in class configuration mode. The class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect esmtp

no inspect esmtp

Syntax Description

This command has no arguments or keywords.

Defaults

This command is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

ESMTP application inspection provides improved protection against SMTP-based attacks by restricting the types of SMTP commands that can pass through the security appliance and by adding monitoring capabilities.

ESMTP is an enhancement to the SMTP protocol and is similar in most respects to SMTP. For convenience, the term SMTP is used in this document to refer to both SMTP and ESMTP. The application inspection process for extended SMTP is similar to SMTP application inspection and includes support for SMTP sessions. Most commands used in an extended SMTP session are the same as those used in an SMTP session but an ESMTP session is considerably faster and offers more options related to reliability and security, such as delivery status notification.

The **inspect esmtp** command includes the functionality previously provided by the **fixup smtp** command, and provides additional support for some extended SMTP commands. Extended SMTP application inspection adds support for eight extended SMTP commands, including AUTH, EHLO, ETRN, HELP, SAML, SEND, SOML and VRFY. Along with the support for seven RFC 821 commands (DATA, HELO, MAIL, NOOP, QUIT, RCPT, RSET), the security appliance supports a total of fifteen SMTP commands.

Other extended SMTP commands, such as ATRN, STARTLS, ONEX, VERB, CHUNKING, and private extensions are not supported. Unsupported commands are translated into Xs, which are rejected by the internal server. This results in a message such as “500 Command unknown: 'XXX'.” Incomplete commands are discarded.

If you enter the **inspect smtp** command, the security appliance automatically converts the command into **inspect esmtp**, which is the configuration that will be shown if you enter the **show running-config** command.

The **inspect esmtp** command changes the characters in the server SMTP banner to asterisks except for the “2”, “0”, “0” characters. Carriage return (CR) and linefeed (LF) characters are ignored.

With SMTP inspection enabled, a Telnet session used for interactive SMTP may hang if the following rules are not observed: SMTP commands must be at least four characters in length; must be terminated with carriage return and line feed; and must wait for a response before issuing the next reply.

An SMTP server responds to client requests with numeric reply codes and optional human readable strings. SMTP application inspection controls and reduces the commands that the user can use as well as the messages that the server returns. SMTP inspection performs three primary tasks:

- Restricts SMTP requests to seven basic SMTP commands and eight extended commands.
- Monitors the SMTP command-response sequence.
- Generates an audit trail—Audit record 108002 is generated when invalid character embedded in the mail address is replaced. For more information, see RFC 821.

SMTP inspection monitors the command and response sequence for the following anomalous signatures:

- Truncated commands.
- Incorrect command termination (not terminated with <CR><LR>).
- The MAIL and RCPT commands specify who are the sender and the receiver of the mail. Mail addresses are scanned for strange characters. The pipeline character | is deleted (changed to a blank space) and | are only allowed if they are used to define a mail address | must be preceded by “<”).
- Unexpected transition by the SMTP server.
- For unknown commands, the security appliance changes all the characters in the packet to X. In this case, the server will generate an error code to the client. Because of the change in the packet, the TCP checksum has to be recalculated or adjusted.
- TCP stream editing.
- Command pipelining.

Examples

You enable the SMTP inspection engine as shown in the following example, which creates a class map to match SMTP traffic on the default port (25). The service policy is then applied to the outside interface.

```
hostname(config)# class-map smtp-port
hostname(config-cmap)# match port tcp eq 25
hostname(config-cmap)# exit
hostname(config)# policy-map smtp_policy
hostname(config-pmap)# class smtp-port
hostname(config-pmap-c)# inspect esmtp
hostname(config-pmap-c)# exit
hostname(config)# service-policy smtp_policy interface outside
```

To enable SMTP inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands	Commands	Description
	class-map	Defines the traffic class to which to apply security actions.
	debug smtp	Enables debug information for SMTP.
	policy-map	Associates a class map with specific security actions.
	service-policy	Applies a policy map to one or more interfaces.
	show conn	Displays the connection state for different connection types, including SMTP.

inspect ftp

To configure the port for FTP inspection or to enable enhanced inspection, use the **inspect ftp** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect ftp [**strict** [*map_name*]]

no inspect ftp [**strict** [*map_name*]]

Syntax Description

<i>map_name</i>	The name of the FTP map.
strict	(Optional) Enables enhanced inspection of FTP traffic and forces compliance with RFC standards.



Caution

Use caution when moving FTP to a higher port. For example, if you set the FTP port to 2021, all connections that initiate to port 2021 will have their data payload interpreted as FTP commands.

Defaults

The security appliance listens to port 21 for FTP by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated. The <i>map_name</i> option was added.

Usage Guidelines

The FTP application inspection inspects the FTP sessions and performs four tasks:

- Prepares dynamic secondary data connections
- Tracks **ftp** command-response sequence
- Generates an audit trail
- NATs embedded IP addresses

FTP application inspection prepares secondary channels for FTP data transfer. The channels are allocated in response to a file upload, a file download, or a directory listing event and must be pre-negotiated. The port is negotiated through the PORT or PASV commands.

**Note**

If you disable FTP inspection engines with the **no inspect ftp** command, outbound users can start connections only in passive mode, and all inbound FTP is disabled.

Using the strict Option

The **strict** option prevents web browsers from sending embedded commands in FTP requests. Each **ftp** command must be acknowledged before a new command is allowed. Connections sending embedded commands are dropped. The **strict** option only lets an FTP server generate the 227 command and only lets an FTP client generate the PORT command. The 227 and PORT commands are checked to ensure they do not appear in an error string.

**Caution**

The use of the **strict** option may break FTP clients that do not comply with the RFC standards.

If the **strict** option is enabled, each **ftp** command and response sequence is tracked for the following anomalous activity:

- Truncated command—Number of commas in the PORT and PASV reply command is checked to see if it is five. If it is not five, then the PORT command is assumed to be truncated and the TCP connection is closed.
- Incorrect command—Checks the **ftp** command to see if it ends with <CR><LF> characters, as required by the RFC. If it does not, the connection is closed.
- Size of RETR and STOR commands—These are checked against a fixed constant. If the size is greater, then an error message is logged and the connection is closed.
- Command spoofing—The PORT command should always be sent from the client. The TCP connection is denied if a PORT command is sent from the server.
- Reply spoofing—PASV reply command (227) should always be sent from the server. The TCP connection is denied if a PASV reply command is sent from the client. This prevents the security hole when the user executes “227 xxxxx a1, a2, a3, a4, p1, p2.”
- TCP stream editing.
- Invalid port negotiation—The negotiated dynamic port value is checked to see if it is less than 1024. As port numbers in the range from 1 to 1024 are reserved for well-known connections, if the negotiated port falls in this range, then the TCP connection is freed.
- Command pipelining—The number of characters present after the port numbers in the PORT and PASV reply command is cross checked with a constant value of 8. If it is more than 8, then the TCP connection is closed.
- The security appliance replaces the FTP server response to the SYST command with a series of Xs. to prevent the server from revealing its system type to FTP clients. To override this default behavior, use the **no mask-syst-reply** command in FTP map configuration mode.

**Note**

To identify specific FTP commands that are not permitted to pass through the security appliance, identify an FTP map and use the **request-command deny** command. For details, see the **ftp-map** and the **request-command deny** command pages.

FTP Log Messages

FTP application inspection generates the following log messages:

- An Audit record 302002 is generated for each file that is retrieved or uploaded.

- The **ftp** command is checked to see if it is RETR or STOR and the retrieve and store commands are logged.
- The username is obtained by looking up a table providing the IP address.
- The username, source IP address, destination IP address, NAT address, and the file operation are logged.
- Audit record 201005 is generated if the secondary dynamic channel preparation failed due to memory shortage.

In conjunction with NAT, the FTP application inspection translates the IP address within the application payload. This is described in detail in RFC 959.

Examples

The following example identifies FTP traffic, defines an FTP map, defines a policy, enables strict FTP inspection, and applies the policy to the outside interface:

```
hostname(config)# class-map ftp-port
hostname(config-cmap)# match port tcp eq 21
hostname(config-cmap)# exit
hostname(config)# ftp-map inbound_ftp
hostname(config-inbound_ftp)# request-command deny put stou appe
hostname(config-ftp-map)# exit
hostname(config)# policy-map inbound_policy
hostname(config-pmap)# class ftp-port
hostname(config-pmap-c)# inspect ftp strict inbound_ftp
hostname(config-pmap-c)# exit
hostname(config-pmap)# exit
hostname(config)# service-policy inbound_policy interface outside
```

To enable strict FTP application inspection for all interfaces, use the **global** parameter in place of **interface outside**.



Note

Only specify the port for the FTP control connection and not the data connection. The security appliance stateful inspection engine dynamically prepares the data connection as necessary.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
mask-syst-reply	Hides the FTP server response from clients.
policy-map	Associates a class map with specific security actions.
request-command deny	Specifies FTP commands to disallow.
service-policy	Applies a policy map to one or more interfaces.

inspect gtp

To enable or disable GTP inspection or to define a GTP map for controlling GTP traffic or tunnels, use the **inspect gtp** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. Use the **no** form of this command to remove the command.

inspect gtp [*map_name*]

no inspect gtp [*map_name*]



Note

GTP inspection requires a special license. If you enter the **inspect gtp** command on a security appliance without the required license, the security appliance displays an error message.

Syntax Description

map_name (Optional) Name for the GTP map.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

GTP is the tunnelling protocol for GPRS, and helps provide secure access over wireless networks. GPRS is a data network architecture that is designed to integrate with existing GSM networks. It offers mobile subscribers uninterrupted, packet-switched data services to corporate networks and the Internet. For an overview of GTP, refer to the “Applying Application Layer Protocol Inspection” chapter in the *Cisco Security Appliance Command Line Configuration Guide*.

Use the **gtp-map** command to identify a specific map to use for defining the parameters for GTP. When you enter this command, the system enters a configuration mode that lets you enter the different commands used for defining the specific map. The actions that you can specify for messages that fail the criteria set using the different configuration mode commands include **allow**, **reset**, or **drop**. In addition to these actions, you can specify to log the event or not.

After defining the GTP map, you use the **inspect gtp** command to enable the map. Then you use the **class-map**, **policy-map**, and **service-policy** commands to define a class of traffic, to apply the **inspect** command to the class, and to apply the policy to one or more interfaces.

The string **gtp**, used as a port value, is automatically converted to the port value 3386. The well-known ports for GTP are as follows:

- 3386
- 2123

The following features are not supported in 7.0:

- NAT, PAT, Outside NAT, alias, and Policy NAT
- Ports other than 3386, 2123, and 2152
- Validating the tunneled IP packet and its contents

Inspecting Signaling Messages

For inspecting signaling messages, the **inspect gtp** command often needs to determine locations of the media endpoints (for example, IP phones).

This information is used to prepare access-control and NAT state for media traffic to traverse the firewall transparently without manual configuration.

In determining these locations, the **inspect gtp** command does **not** use the tunnel default gateway route. A tunnel default gateway route is a route of the form **route interface 0 0 metric tunneled**. This route overrides the default route for packets that egress from IPsec tunnels. Therefore, if the **inspect gtp** command is desired for VPN traffic, do not configure the tunnel default gateway route. Instead, use other static routing or dynamic routing.

Examples

The following example shows how to use access lists to identify GTP traffic, define a GTP map, define a policy, and apply the policy to the outside interface:

```
hostname(config)# access-list gtp-acl permit udp any any eq 3386
hostname(config)# access-list gtp-acl permit udp any any eq 2123
hostname(config)# class-map gtp-traffic
hostname(config)# match access-list gtp-acl
hostname(config)# gtp-map gtp-policy
hostname(config)# policy-map inspection_policy
hostname(config-pmap)# class gtp-traffic
hostname(config-pmap-c)# inspect gtp gtp-policy
hostname(config)# service-policy inspection_policy interface outside
```



Note

This example enables GTP inspection with the default values. To change the default values, refer to the **gtp-map** command page and to the command pages for each command that is entered from GTP map configuration mode.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
clear service-policy	Clears global GTP statistics.
inspect gtp	
debug gtp	Displays detailed information about GTP inspection.
service-policy	Applies a policy map to one or more interfaces.

inspect h323

To enable H.323 application inspection or to change the ports to which the security appliance listens, use the **inspect h323** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

```
inspect h323 {h225 | ras }
```

```
no inspect h323 {h225 | ras }
```

Syntax Description

h225	Enables H.225 signalling inspection.
ras	Enables RAS inspection.

Defaults

The default port assignments are as follows:

- h323 h225 1720
- h323 ras 1718-1719

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

The **inspect h323** command provides support for H.323 compliant applications such as Cisco CallManager and VocalTec Gatekeeper. H.323 is a suite of protocols defined by the International Telecommunication Union (ITU) for multimedia conferences over LANs. The security appliance supports H.323 through Version 4, including the H.323 v3 feature Multiple Calls on One Call Signaling Channel.

With H.323 inspection enabled, the security appliance supports multiple calls on the same call signaling channel, a feature introduced with H.323 Version 3. This feature reduces call setup time and reduces the use of ports on the security appliance.

The two major functions of H.323 inspection are as follows:

- NAT the necessary embedded IPv4 addresses in the H.225 and H.245 messages. Because H.323 messages are encoded in PER encoding format, the security appliance uses an ASN.1 decoder to decode the H.323 messages.

- Dynamically allocate the negotiated H.245 and RTP/RTCP connections.

How H.323 Works

The H.323 collection of protocols collectively may use up to two TCP connection and four to six UDP connections. FastStart uses only one TCP connection, and RAS uses a single UDP connection for registration, admissions, and status.

An H.323 client may initially establish a TCP connection to an H.323 server using TCP port 1720 to request Q.931 call setup. As part of the call setup process, the H.323 terminal supplies a port number to the client to use for an H.245 TCP connection. The H.245 connection is for call negotiation and media channel setup. In environments where H.323 gatekeeper is in use, the initial packet is transmitted using UDP.

H.323 inspection monitors the Q.931 TCP connection to determine the H.245 port number. If the H.323 terminals are not using FastStart, the security appliance dynamically allocates the H.245 connection based on the inspection of the H.225 messages.



Note

The H.225 connection can also be dynamically allocated when using RAS.

Within each H.245 message, the H.323 endpoints exchange port numbers that are used for subsequent UDP data streams. H.323 inspection inspects the H.245 messages to identify these ports and dynamically creates connections for the media exchange. Real-Time Transport Protocol (RTP) uses the negotiated port number, while RTP Control Protocol (RTCP) uses the next higher port number.

The H.323 control channel handles H.225 and H.245 and H.323 RAS. H.323 inspection uses the following ports.

- 1718—UDP port used for gatekeeper discovery
- 1719—UDP port used for RAS and for gatekeeper discovery
- 1720—TCP Control Port

If the ACF message from the gatekeeper goes through the security appliance, a pinhole will be opened for the H.225 connection. The H.245 signaling ports are negotiated between the endpoints in the H.225 signaling. When an H.323 gatekeeper is used, the security appliance opens an H.225 connection based on inspection of the ACF message. If the security appliance does not see the ACF message, you might need to open an access list for the well-known H.323 port 1720 for the H.225 call signaling.

The security appliance dynamically allocates the H.245 channel after inspecting the H.225 messages and then hooks up to the H.245 channel to be fixed up as well. That means whatever H.245 messages pass through the security appliance pass through the H.245 application inspection, NATing embedded IP addresses and opening the negotiated media channels.

The H.323 ITU standard requires that a TPKT header, defining the length of the message, precede the H.225 and H.245, before being passed on to the reliable connection. Because the TPKT header does not necessarily need to be sent in the same TCP packet as the H.225/H.245 message, the security appliance must remember the TPKT length to process/decode the messages properly. The security appliance keeps a data structure for each connection and that data structure contains the TPKT length for the next expected message.

If the security appliance needs to NAT any IP addresses, then it will have to change the checksum, the UUIE (user-user information element) length, and the TPKT, if included in the TCP packet with the H.225 message. If the TPKT is sent in a separate TCP packet, then the security appliance will proxy ACK that TPKT and append a new TPKT to the H.245 message with the new length.

**Note**

The security appliance does not support TCP options in the Proxy ACK for the TPKT.

Each UDP connection with a packet going through H.323 inspection is marked as an H.323 connection and will time out with the H.323 timeout as configured using the **timeout** command.

Limitations and Restrictions

The following are some of the known issues and limitations when using H.323 application inspection:

- Static PAT may not properly translate IP addresses embedded in optional fields within H.323 messages. If you experience this kind of problem, do not use static PAT with H.323.
- It has been observed that when a NetMeeting client registers with an H.323 gatekeeper and tries to call an H.323 gateway that is also registered with the H.323 gatekeeper, the connection is established but no voice is heard in either direction. This problem is unrelated to the security appliance.
- If you configure a network static where the network static is the same as a third-party netmask and address, then any outbound H.323 connection fails.

Inspecting Signaling Messages

For inspecting signaling messages, the **inspect h323** command often needs to determine locations of the media endpoints (for example, IP phones).

This information is used to prepare access-control and NAT state for media traffic to traverse the firewall transparently without manual configuration.

In determining these locations, the **inspect h323** command does **not** use the tunnel default gateway route. A tunnel default gateway route is a route of the form **route interface 0 0 metric tunneled**. This route overrides the default route for packets that egress from IPSec tunnels. Therefore, if the **inspect h323** command is desired for VPN traffic, do not configure the tunnel default gateway route. Instead, use other static routing or dynamic routing.

Examples

You enable the H.323 inspection engine as shown in the following example, which creates a class map to match H.323 traffic on the default port (1720). The service policy is then applied to the outside interface.

```
hostname(config)# class-map h323-port
hostname(config-cmap)# match port tcp eq 1720
hostname(config-cmap)# exit
hostname(config)# policy-map h323_policy
hostname(config-pmap)# class h323-port
hostname(config-pmap-c)# inspect h323
hostname(config-pmap-c)# exit
hostname(config)# service-policy h323_policy interface outside
```

To enable H.323 inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
debug h323	Enables the display of debug information for H.323.
show h225	Displays information for H.225 sessions established across the security appliance.
show h245	Displays information for H.245 sessions established across the security appliance by endpoints using slow start.

Commands	Description
show h323-ras	Displays information for H.323 RAS sessions established across the security appliance.
timeout {h225 h323}	Configures idle time after which an H.225 signalling connection or an H.323 control connection will be closed.

inspect http

To enable HTTP application inspection or to change the ports to which the security appliance listens, use the **inspect http command** in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect http [*map_name*]

no inspect http [*map_name*]

Syntax Description

map_name (Optional) The name of the HTTP map.

Defaults

The default port for HTTP is 80.

Enhanced HTTP inspection is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

The **inspect http** command protects against specific attacks and other threats that may be associated with HTTP traffic. HTTP inspection performs several functions:

- Enhanced HTTP inspection
- URL screening through N2H2 or Websense
- Java and ActiveX filtering

The latter two features are configured in conjunction with the **filter** command.

Enhanced HTTP inspection verifies that HTTP messages conform to RFC 2616, use RFC-defined methods or supported extension methods, and comply with various other criteria. In many cases, you can configure these criteria and the system response when the criteria are not met. The actions that you can specify for messages that fail the criteria set using the different configuration commands include **allow**, **reset**, or **drop**. In addition to these actions, you can specify to log the event or not.

The criteria that you can apply to HTTP messages include the following:

- Does not include any method on a configurable list.

- Specific transfer encoding method or application type.
- HTTP transaction adheres to RFC specification.
- Message body size is within configurable limits.
- Request and response message header size is within a configurable limit.
- URI length is within a configurable limit.
- The content-type in the message body matches the header.
- The content-type in the response message matches the *accept-type* field in the request message.
- The content-type in the message is included in a predefined internal list.
- Message meets HTTP RFC format criteria.
- Presence or absence of selected supported applications.
- Presence or absence of selected encoding types.

**Note**

The actions that you can specify for messages that fail the criteria set using the different configuration commands include **allow**, **reset**, or **drop**. In addition to these actions, you can specify to log the event or not.

To enable enhanced HTTP inspection, enter the **inspect http http-map** command. The rules that this applies to HTTP traffic are defined by the specific HTTP map, which you configure by entering the **http-map** command and HTTP map configuration mode commands.

**Note**

When you enable HTTP inspection with an HTTP map, strict HTTP inspection with the action reset and log is enabled by default. You can change the actions performed in response to inspection failure, but you cannot disable strict inspection as long as the HTTP map remains enabled.

Examples

The following example shows how to identify HTTP traffic, define an HTTP map, define a policy, and apply the policy to the outside interface:

```
hostname(config)# class-map http-port
hostname(config-cmap)# match port tcp eq 80
hostname(config-cmap)# exit
hostname(config)# http-map inbound_http
hostname(config-http-map)# content-length min 100 max 2000 action reset log
hostname(config-http-map)# content-type-verification match-req-rsp reset log
hostname(config-http-map)# max-header-length request bytes 100 action log reset
hostname(config-http-map)# max-uri-length 100 action reset log
hostname(config-http-map)# exit
hostname(config)# policy-map inbound_policy
hostname(config-pmap)# class http-port
hostname(config-pmap-c)# inspect http inbound_http
hostname(config-pmap-c)# exit
hostname(config-pmap)# exit
hostname(config)# service-policy inbound_policy interface outside
```

This example causes the security appliance to reset the connection and create a syslog entry when it detects any traffic that contain the following:

- Messages less than 100 bytes or exceeding 2000 bytes

- Unsupported content types
- HTTP headers exceeding 100 bytes
- URIs exceeding 100 bytes

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug appfw	Displays detailed information about HTTP application inspection.
debug http-map	Displays detailed information about traffic associated with an HTTP map.
http-map	Defines an HTTP map for configuring enhanced HTTP inspection.
policy-map	Associates a class map with specific security actions.

inspect icmp

To configure the ICMP inspection engine, use the **inspect icmp** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode.

inspect icmp

no inspect icmp

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

The ICMP inspection engine allows ICMP traffic to be inspected like TCP and UDP traffic. Without the ICMP inspection engine, we recommend that you do not allow ICMP through the security appliance in an ACL. Without stateful inspection, ICMP can be used to attack your network. The ICMP inspection engine ensures that there is only one response for each request, and that the sequence number is correct.

When ICMP inspection is disabled, which is the default configuration, ICMP echo reply messages are denied from a lower security interface to a higher security interface, even if it is in response to an ICMP echo request.

Examples

You enable the ICMP application inspection engine as shown in the following example, which creates a class map to match ICMP traffic using the ICMP protocol ID, which is 1 for IPv4 and 58 for IPv6. The service policy is then applied to the outside interface.

```
hostname(config)# class-map icmp-class
hostname(config-cmap)# match default-inspection-traffic
hostname(config-cmap)# exit
hostname(config)# policy-map icmp_policy
hostname(config-pmap)# class icmp-class
hostname(config-pmap-c)# inspect icmp
hostname(config-pmap-c)# exit
hostname(config)# service-policy icmp_policy interface outside
```

To enable ICMP inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands	Commands	Description
	class-map	Defines the traffic class to which to apply security actions.
	icmp	Configures access rules for ICMP traffic that terminates at a security appliance interface.
	policy-map	Defines a policy that associates security actions with one or more traffic classes.
	service-policy	Applies a policy map to one or more interfaces.

inspect icmp error

To enable application inspection for ICMP error messages, use the **inspect icmp error** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode.

inspect icmp error

no inspect icmp error

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

Use the **inspect icmp error** command to create xlates for intermediate hops that send ICMP error messages, based on the static/NAT configuration. By default, the security appliance hides the IP addresses of intermediate hops. However, using the **inspect icmp error** command makes the intermediate hop IP addresses visible. The security appliance overwrites the packet with the translated IP addresses.

When enabled, the ICMP error inspection engine makes the following changes to the ICMP packet:

- In the IP Header, the NAT IP is changed to the Client IP (Destination Address and Intermediate Hop Address) and the IP checksum is modified.
- In the ICMP Header, the ICMP checksum is modified due to the changes in the ICMP packet.
- In the Payload, the following changes are made:
 - Original packet NAT IP is changed to the Client IP
 - Original packet NAT port is changed to the Client Port
 - Original packet IP checksum is recalculated

When an ICMP error message is retrieved, whether ICMP error inspection is enabled or not, the ICMP payload is scanned to retrieve the five-tuple (src ip, dest ip, src port, dest port, and ip protocol) from the original packet. A lookup is performed, using the retrieved five-tuple, to determine the original address of the client and to locate an existing session associated with the specific five-tuple. If the session is not found, the ICMP error message is dropped.

Examples

You enable the ICMP error application inspection engine as shown in the following example, which creates a class map to match ICMP traffic using the ICMP protocol ID, which is 1 for IPv4 and 58 for IPv6. The service policy is then applied to the outside interface.

```
hostname(config)# class-map icmp-class
hostname(config-cmap)# match default-inspection-traffic
hostname(config-cmap)# exit
hostname(config)# policy-map icmp_policy
hostname(config-pmap)# class icmp-class
hostname(config-pmap-c)# inspect icmp error
hostname(config-pmap-c)# exit
hostname(config)# service-policy icmp_policy interface outside
```

To enable ICMP error inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
icmp	Configures access rules for ICMP traffic that terminates at a security appliance interface.
inspect icmp	Enables or disables the ICMP inspection engine.
policy-map	Defines a policy that associates security actions with one or more traffic classes.
service-policy	Applies a policy map to one or more interfaces.

inspect ils

To enable ILS application inspection or to change the ports to which the security appliance listens, use the **inspect ils** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect ils

no inspect ils

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

The **inspect ils** command provides NAT support for Microsoft NetMeeting, SiteServer, and Active Directory products that use LDAP to exchange directory information with an ILS server.

Use the *port* option to change the default port assignment from 389. Use the *-port* option to apply ILS inspection to a range of port numbers.

The security appliance supports NAT for ILS, which is used to register and locate endpoints in the ILS or SiteServer Directory. PAT cannot be supported because only IP addresses are stored by an LDAP database.

For search responses, when the LDAP server is located outside, NAT should be considered to allow internal peers to communicate locally while registered to external LDAP servers. For such search responses, xlates are searched first, and then DNAT entries to obtain the correct address. If both of these searches fail, then the address is not changed. For sites using NAT 0 (no NAT) and not expecting DNAT interaction, we recommend that the inspection engine be turned off to provide better performance.

Additional configuration may be necessary when the ILS server is located inside the security appliance border. This would require a hole for outside clients to access the LDAP server on the specified port, typically TCP 389.

Because ILS traffic only occurs on the secondary UDP channel, the TCP connection is disconnected after the TCP inactivity interval. By default, this interval is 60 minutes and can be adjusted using the **timeout** command.

ILS/LDAP follows a client/server model with sessions handled over a single TCP connection. Depending on the client's actions, several of these sessions may be created.

During connection negotiation time, a BIND PDU is sent from the client to the server. Once a successful BIND RESPONSE from the server is received, other operational messages may be exchanged (such as ADD, DEL, SEARCH, or MODIFY) to perform operations on the ILS Directory. The ADD REQUEST and SEARCH RESPONSE PDUs may contain IP addresses of NetMeeting peers, used by H.323 (SETUP and CONNECT messages) to establish the NetMeeting sessions. Microsoft NetMeeting v2.X and v3.X provides ILS support.

The ILS inspection performs the following operations:

- Decodes the LDAP REQUEST/RESPONSE PDUs using the BER decode functions
- Parses the LDAP packet
- Extracts IP addresses
- Translates IP addresses as necessary
- Encodes the PDU with translated addresses using BER encode functions
- Copies the newly encoded PDU back to the TCP packet
- Performs incremental TCP checksum and sequence number adjustment

ILS inspection has the following limitations:

- Referral requests and responses are not supported
- Users in multiple directories are not unified
- Single users having multiple identities in multiple directories cannot be recognized by NAT



Note

Because H225 call signalling traffic only occurs on the secondary UDP channel, the TCP connection is disconnected after the interval specified by the TCP **timeout** command. By default, this interval is set at 60 minutes.

Examples

You enable the ILS inspection engine as shown in the following example, which creates a class map to match ILS traffic on the default port (389). The service policy is then applied to the outside interface.

```
hostname(config)# class-map ils-port
hostname(config-cmap)# match port tcp eq 389
hostname(config-cmap)# exit
hostname(config)# policy-map ils_policy
hostname(config-pmap)# class ils-port
hostname(config-pmap-c)# inspect ils
hostname(config-pmap-c)# exit
hostname(config)# service-policy ils_policy interface outside
```

To enable ILS inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug ils	Enables debug information for ILS.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

inspect ipsec-pass-thru

To enable ESP inspection, use the **inspect ipsec-pass-thru** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect ipsec-pass-thru

no inspect ipsec-pass-thru

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0(5)	This command was introduced.

Usage Guidelines

This inspection is configured to open pinholes for ESP traffic. All ESP data flows are permitted when a forward flow exists, and there is no limit on the maximum number of connections that can be allowed. AH is not permitted. The default idle timeout for ESP data flows is by default set to 10 minutes. This inspection can be applied in all locations that other inspections can be applied, including class and match command modes.

IPSec Pass Through application inspection provides convenient traversal of ESP (IP protocol 50) traffic associated with an IKE UDP port 500 connection. It avoids lengthy access list configuration to permit ESP traffic and also provides security using timeout and max connections.

Use **class-map**, **policy-map**, and **service-policy** commands to define a class of traffic, to apply the **inspect** command to the class, and to apply the policy to one or more interfaces. The **inspect IPSec-pass-thru** command, when enabled, allows unlimited ESP traffic with a timeout of 10 minutes, which is not configurable.

NAT and non-NAT traffic is permitted. However, PAT is not supported.

Examples

The following example shows how to use an access list to identify IKE traffic, define an IPSec Pass Through policy map, and apply the policy to the outside interface:

```
hostname(config)# access-list test-udp-acl extended permit udp any any eq 500
hostname(config)# class-map test-udp-class
hostname(config-cmap)# match access-list test-udp-acl
hostname(config)# policy-map test-udp-policy
hostname(config-pmap)# class test-udp-class
```

```
hostname(config-pmap-c)# inspect ipsec-pass-thru
hostname(config)# service-policy test-udp-policy interface outside
```

To enable ESP inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

inspect mgcp

To enable MGCP application inspection or to change the ports to which the security appliance listens, use the **inspect mgcp** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect mgcp [*map_name*]

no inspect mgcp [*map_name*]

Syntax Description

map_name (Optional) The name of the MGCP map.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

To use MGCP, you usually need to configure at least two **inspect** commands: one for the port on which the gateway receives commands, and one for the port on which the Call Agent receives commands. Normally, a Call Agent sends commands to the default MGCP port for gateways, 2427, and a gateway sends commands to the default MGCP port for Call Agents, 2727.

MGCP is used for controlling media gateways from external call control elements called media gateway controllers or call agents. A media gateway is typically a network element that provides conversion between the audio signals carried on telephone circuits and data packets carried over the Internet or over other packet networks. Using NAT and PAT with MGCP lets you support a large number of devices on an internal network with a limited set of external (global) addresses.

Examples of media gateways are:

- Trunking gateways, that interface between the telephone network and a Voice over IP network. Such gateways typically manage a large number of digital circuits.
- Residential gateways, that provide a traditional analog (RJ11) interface to a Voice over IP network. Examples of residential gateways include cable modem/cable set-top boxes, xDSL devices, broad-band wireless devices.

- Business gateways, that provide a traditional digital PBX interface or an integrated soft PBX interface to a Voice over IP network.

MGCP messages are transmitted over UDP. A response is sent back to the source address (IP address and UDP port number) of the command, but the response may not arrive from the same address as the command was sent to. This can happen when multiple call agents are being used in a failover configuration and the call agent that received the command has passed control to a backup call agent, which then sends the response.

**Note**

MGCP call agents send AUEP messages to determine if MGCP end points are present. This establishes a flow through the security appliance and allows MGCP end points to register with the call agent.

Use the **call-agent** and **gateway** commands in MGCP map configuration mode to configure the IP addresses of one or more call agents and gateways. Use the **command-queue** command in MGCP map configuration mode to specify the maximum number of MGCP commands that will be allowed in the command queue at one time.

Inspecting Signaling Messages

For inspecting signaling messages, the **inspect mgcp** command often needs to determine locations of the media endpoints (for example, IP phones).

This information is used to prepare access-control and NAT state for media traffic to traverse the firewall transparently without manual configuration.

In determining these locations, the **inspect mgcp** command does **not** use the tunnel default gateway route. A tunnel default gateway route is a route of the form **route interface 0 0 metric tunneled**. This route overrides the default route for packets that egress from IPSec tunnels. Therefore, if the **inspect mgcp** command is desired for VPN traffic, do not configure the tunnel default gateway route. Instead, use other static routing or dynamic routing.

Examples

The following example shows how to identify MGCP traffic, define a MGCP map, define a policy, and apply the policy to the outside interface. This creates a class map to match MGCP traffic on the default ports (2427 and 2727). The service policy is then applied to the outside interface.

```
hostname(config)# access-list mgcp_acl permit tcp any any eq 2427
hostname(config)# access-list mgcp_acl permit tcp any any eq 2727
hostname(config)# class-map mgcp_port
hostname(config-cmap)# match access-list mgcp_acl
hostname(config-cmap)# exit
hostname(config)# mgcp-map inbound_mgcp
hostname(config-mgcp-map)# call-agent 10.10.11.5 101
hostname(config-mgcp-map)# call-agent 10.10.11.6 101
hostname(config-mgcp-map)# call-agent 10.10.11.7 102
hostname(config-mgcp-map)# call-agent 10.10.11.8 102
hostname(config-mgcp-map)# gateway 10.10.10.115 101
hostname(config-mgcp-map)# gateway 10.10.10.116 102
hostname(config-mgcp-map)# gateway 10.10.10.117 102
hostname(config-mgcp-map)# command-queue 150
hostname(config-mgcp-map)# exit
hostname(config)# policy-map inbound_policy
hostname(config-pmap)# class mgcp_port
hostname(config-pmap-c)# inspect mgcp mgcp-map inbound_mgcp
hostname(config-pmap-c)# exit
hostname(config)# service-policy inbound_policy interface outside
```

This configuration allows call agents 10.10.11.5 and 10.10.11.6 to control gateway 10.10.10.115, and allows call agents 10.10.11.7 and 10.10.11.8 to control both gateways 10.10.10.116 and 10.10.10.117. The maximum number of MGCP commands that can be queued is 150.

To enable MGCP inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug mgcp	Enables MGCP debug information.
mgcp-map	Defines an MGCP map and enables MGCP map configuration mode.
show mgcp	Displays information about MGCP sessions established through the security appliance.
timeout	Sets the maximum idle time duration for different protocols and session types.

inspect netbios

To enable NetBIOS application inspection or to change the ports to which the security appliance listens, use the **inspect netbios command** in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect netbios

no inspect netbios

Syntax Description

This command has no arguments or keywords.

Syntax Description

<i>port</i>	The port on which to enable application inspection. You can use port numbers or supported port literals. See Appendix D, “Addresses, Protocols, and Ports,” in the <i>Cisco Security Appliance Command Line Configuration Guide</i> for a list of valid port literal names.
<i>port-port</i>	Specifies a port range.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

The **inspect netbios** command enables or disables application inspection for the NetBIOS protocol.

Examples

You enable the NetBIOS inspection engine as shown in the following example, which creates a class map to match NetBIOS traffic on the default UDP ports (137 and 138). The service policy is then applied to the outside interface.

```
hostname(config)# class-map netbios-port
hostname(config-cmap)# match port udp range 137 138
hostname(config-cmap)# exit
hostname(config)# policy-map netbios_policy
```



```
hostname(config-pmap)# class netbios-port  
hostname(config-pmap-c)# inspect netbios  
hostname(config-pmap-c)# exit  
hostname(config)# service-policy netbios_policy interface outside
```

To enable NetBIOS inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

inspect pptp

To enable PPTP application inspection or to change the ports to which the security appliance listens, use the **inspect pptp** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

```
inspect pptp
```

```
no inspect pptp
```

Syntax Description

This command has no arguments or keywords.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

The Point-to-Point Tunneling Protocol (PPTP) is a protocol for tunneling PPP traffic. A PPTP session is composed of one TCP channel and usually two PPTP GRE tunnels. The TCP channel is the control channel used for negotiating and managing the PPTP GRE tunnels. The GRE tunnels carries PPP sessions between the two hosts.

When enabled, PPTP application inspection inspects PPTP protocol packets and dynamically creates the GRE connections and xlates necessary to permit PPTP traffic. Only Version 1, as defined in RFC 2637, is supported.

PAT is only performed for the modified version of GRE [RFC 2637] when negotiated over the PPTP TCP control channel. Port Address Translation is *not* performed for the unmodified version of GRE [RFC 1701, RFC 1702].

Specifically, the security appliance inspects the PPTP version announcements and the outgoing call request/response sequence. Only PPTP Version 1, as defined in RFC 2637, is inspected. Further inspection on the TCP control channel is disabled if the version announced by either side is not Version 1. In addition, the outgoing-call request and reply sequence are tracked. Connections and xlates are dynamic allocated as necessary to permit subsequent secondary GRE data traffic.

The PPTP inspection engine must be enabled for PPTP traffic to be translated by PAT. Additionally, PAT is only performed for a modified version of GRE (RFC2637) and only if it is negotiated over the PPTP TCP control channel. PAT is not performed for the unmodified version of GRE (RFC 1701 and RFC 1702).

As described in RFC 2637, the PPTP protocol is mainly used for the tunneling of PPP sessions initiated from a modem bank PAC (PPTP Access Concentrator) to the headend PNS (PPTP Network Server). When used this way, the PAC is the remote client and the PNS is the server.

However, when used for VPN by Windows, the interaction is inverted. The PNS is a remote single-user PC that initiates connection to the head-end PAC to gain access to a central network. I

Examples

You enable the PPTP inspection engine as shown in the following example, which creates a class map to match PPTP traffic on the default port (1723). The service policy is then applied to the outside interface.

```
hostname(config)# class-map pptp-port
hostname(config-cmap)# match port tcp eq 1723
hostname(config-cmap)# exit
hostname(config)# policy-map pptp_policy
hostname(config-pmap)# class pptp-port
hostname(config-pmap-c)# inspect pptp
hostname(config-pmap-c)# exit
hostname(config)# service-policy pptp_policy interface outside
```

To enable PPTP inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug pptp	Enables debug information for PPTP.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

inspect rsh

To enable RSH application inspection or to change the ports to which the security appliance listens, use the **inspect rsh** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect rsh

no inspect rsh

Syntax Description

This command has no arguments or keywords.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

The RSH protocol uses a TCP connection from the RSH client to the RSH server on TCP port 514. The client and server negotiate the TCP port number where the client listens for the STDERR output stream. RSH inspection supports NAT of the negotiated port number if necessary.

Examples

You enable the RSH inspection engine as shown in the following example, which creates a class map to match RSH traffic on the default port (514). The service policy is then applied to the outside interface.

```
hostname(config)# class-map rsh-port
hostname(config-cmap)# match port tcp eq 514
hostname(config-cmap)# exit
hostname(config)# policy-map rsh_policy
hostname(config-pmap)# class rsh-port
hostname(config-pmap-c)# inspect rsh
hostname(config-pmap-c)# exit
hostname(config)# service-policy rsh_policy interface outside
```

To enable RSH inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands	Commands	Description
	class-map	Defines the traffic class to which to apply security actions.
	policy-map	Associates a class map with specific security actions.
	service-policy	Applies a policy map to one or more interfaces.

inspect rtsp

To enable RTSP application inspection or to change the ports to which the security appliance listens, use the **inspect rtsp** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect rtsp

no inspect rtsp

Syntax Description

This command has no arguments or keywords.

Defaults

This command is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

The **inspect rtsp** command lets the security appliance pass RTSP packets. RTSP is used by RealAudio, RealNetworks, Apple QuickTime 4, RealPlayer, and Cisco IP/TV connections.



Note

For Cisco IP/TV, use RTSP TCP port 554 and TCP 8554.

RTSP applications use the well-known port 554 with TCP (rarely UDP) as a control channel. The security appliance only supports TCP, in conformity with RFC 2326. This TCP control channel is used to negotiate the data channels that will be used to transmit audio/video traffic, depending on the transport mode that is configured on the client.

The supported RDT transports are: rtp/avp, rtp/avp/udp, x-real-rdt, x-real-rdt/udp, and x-pn-tng/udp.

The security appliance parses Setup response messages with a status code of 200. If the response message is travelling inbound, the server is outside relative to the security appliance and dynamic channels need to be opened for connections coming inbound from the server. If the response message is outbound, then the security appliance does not need to open dynamic channels.

Because RFC 2326 does not require that the client and server ports must be in the SETUP response message, the security appliance will need to keep state and remember the client ports in the SETUP message. QuickTime places the client ports in the SETUP message and then the server responds with only the server ports.

Using RealPlayer

When using RealPlayer, it is important to properly configure transport mode. For the security appliance, add an **access-list** command statement from the server to the client or vice versa. For RealPlayer, change transport mode by clicking **Options>Preferences>Transport>RTSP Settings**.

If using TCP mode on the RealPlayer, select the **Use TCP to Connect to Server** and **Attempt to use TCP for all content** check boxes. On the security appliance, there is no need to configure the inspection engine.

If using UDP mode on the RealPlayer, select the **Use TCP to Connect to Server** and **Attempt to use UDP for static content** check boxes, and for live content not available via Multicast. On the security appliance, add a **inspect rtsp port** command statement.

Restrictions and Limitations

The following restrictions apply to the **inspect rtsp** command:

- The security appliance does not support multicast RTSP or RTSP messages over UDP.
- PAT is not supported with the **inspect rtsp** command.
- The security appliance does not have the ability to recognize HTTP cloaking where RTSP messages are hidden in the HTTP messages.
- The security appliance cannot perform NAT on RTSP messages because the embedded IP addresses are contained in the SDP files as part of HTTP or RTSP messages. Packets could be fragmented and the security appliance cannot perform NAT on fragmented packets.
- With Cisco IP/TV, the number of NATs the security appliance performs on the SDP part of the message is proportional to the number of program listings in the Content Manager (each program listing can have at least six embedded IP addresses).
- You can configure NAT for Apple QuickTime 4 or RealPlayer. Cisco IP/TV only works with NAT if the Viewer and Content Manager are on the outside network and the server is on the inside network.
- Media streams delivered over HTTP are not supported by RTSP application inspection. This is because RTSP inspection does not support HTTP cloaking (RTSP wrapped in HTTP).

Examples

You enable the RTSP inspection engine as shown in the following example, which creates a class map to match RTSP traffic on the default ports (554 and 8554). The service policy is then applied to the outside interface.

```
hostname(config)# access-list rtsp-acl permit tcp any any eq 554
hostname(config)# access-list rtsp-acl permit tcp any any eq 8554
hostname(config)# class-map rtsp-traffic
hostname(config-cmap)# match access-list rtsp-acl
hostname(config-cmap)# exit
hostname(config)# policy-map rtsp_policy
hostname(config-pmap)# class rtsp-traffic
hostname(config-pmap-c)# inspect rtsp
hostname(config-pmap-c)# exit
hostname(config)# service-policy rtsp_policy interface outside
```

To enable RTSP inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug rtsp	Enables debug information for RTSP.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

inspect sip

To enable SIP application inspection or to change the ports to which the security appliance listens, use the **inspect sip** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect sip

no inspect sip

Syntax Description

This command has no arguments or keywords.

Defaults

This command is disabled by default.

The default port assignment for SIP is 5060.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

SIP, as defined by the IETF, enables VoIP calls. SIP works with SDP for call signalling. SDP specifies the details of the media stream. Using SIP, the security appliance can support any SIP Voice over IP (VoIP) gateways and VoIP proxy servers. SIP and SDP are defined in the following RFCs:

- SIP: Session Initiation Protocol, RFC 2543
- SDP: Session Description Protocol, RFC 2327

To support SIP calls through the security appliance, signaling messages for the media connection addresses, media ports, and embryonic connections for the media must be inspected, because while the signaling is sent over a well-known destination port (UDP/TCP 5060), the media streams are dynamically allocated. Also, SIP embeds IP addresses in the user-data portion of the IP packet. SIP inspection applies NAT for these embedded IP addresses.

**Note**

If a remote endpoint tries to register with a SIP proxy on a network protected by the security appliance, the registration will fail under very specific conditions. These conditions are when PAT is configured for the remote endpoint, the SIP registrar server is on the outside network, and when the port is missing in the contact field in the REGISTER message sent by the endpoint to the proxy server.

Instant Messaging

Instant Messaging refers to the transfer of messages between users in near real-time. The MESSAGE/INFO methods and 202 Accept response are used to support IM as defined in the following RFCs:

- Session Initiation Protocol (SIP)-Specific Event Notification, RFC 3265
- Session Initiation Protocol (SIP) Extension for Instant Messaging, RFC 3428

MESSAGE/INFO requests can come in at any time after registration/subscription. For example, two users can be online at any time, but not chat for hours. Therefore, the SIP inspection engine opens pinholes, which will time out according to the configured SIP timeout value. This value must be configured at least five minutes longer than the subscription duration. The subscription duration is defined in the Contact Expires value and is typically 30 minutes.

Because MESSAGE/INFO requests are typically sent using a dynamically allocated port other than port 5060, they are required to go through the SIP inspection engine.

**Note**

Only the Chat feature is currently supported. Whiteboard, File Transfer, and Application Sharing are not supported. RTC Client 5.0 is not supported.

Technical Details

SIP inspection NATs the SIP text-based messages, recalculates the content length for the SDP portion of the message, and recalculates the packet length and checksum. It dynamically opens media connections for ports specified in the SDP portion of the SIP message as address/ports on which the endpoint should listen.

SIP inspection has a database with indices CALL_ID/FROM/TO from the SIP payload that identifies the call, as well as the source and destination. Contained within this database are the media addresses and media ports that were contained in the SDP media information fields and the media type. There can be multiple media addresses and ports for a session. RTP/RTCP connections are opened between the two endpoints using these media addresses/ports.

The well-known port 5060 must be used on the initial call setup (INVITE) message. However, subsequent messages may not have this port number. The SIP inspection engine opens signaling connection pinholes, and marks these connections as SIP connections. This is done for the messages to reach the SIP application and be NATed.

As a call is set up, the SIP session is considered in the “transient” state. This state remains until a Response message is received indicating the RTP media address and port on which the destination endpoint is listening. If there is a failure to receive the response messages within one minute, the signaling connection will be torn down.

Once the final handshake is made, the call state is moved to active and the signaling connection will remain until a BYE message is received.

If an inside endpoint initiates a call to an outside endpoint, a media hole is opened to the outside interface to allow RTP/RTCP UDP packets to flow to the inside endpoint media address and media port specified in the INVITE message from the inside endpoint. Unsolicited RTP/RTCP UDP packets to an inside interface will not traverse the security appliance, unless the security appliance configuration specifically allows it.

The media connections are torn down within two minutes after the connection becomes idle. This is, however, a configurable timeout and can be set for a shorter or longer period of time.

Inspecting Signaling Messages

For inspecting signaling messages, the **inspect sip** command often needs to determine locations of the media endpoints (for example, IP phones).

This information is used to prepare access-control and NAT state for media traffic to traverse the firewall transparently without manual configuration.

In determining these locations, the **inspect sip** command does **not** use the tunnel default gateway route. A tunnel default gateway route is a route of the form **route interface 0 0 metric tunneled**. This route overrides the default route for packets that egress from IPsec tunnels. Therefore, if the **inspect sip** command is desired for VPN traffic, do not configure the tunnel default gateway route. Instead, use other static routing or dynamic routing.

Examples

You enable the SIP inspection engine as shown in the following example, which creates a class map to match SIP traffic on the default port (5060). The service policy is then applied to the outside interface.

```
hostname(config)# class-map sip-port
hostname(config-cmap)# match port tcp eq 5060
hostname(config-cmap)# exit
hostname(config)# policy-map sip_policy
hostname(config-pmap)# class sip-port
hostname(config-pmap-c)# inspect sip
hostname(config-pmap-c)# exit
hostname(config)# service-policy sip_policy interface outside
```

To enable SIP inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
show sip	Displays information about SIP sessions established through the security appliance.
debug sip	Enables debug information for SIP.
show conn	Displays the connection state for different connection types.
timeout	Sets the maximum idle time duration for different protocols and session types.

inspect skinny

To enable SCCP (Skinny) application inspection or to change the ports to which the security appliance listens, use the **inspect skinny** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect skinny

no inspect skinny

Syntax Description

This command has no arguments or keywords.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

Skinny (or Simple) Client Control Protocol (SCCP) is a simplified protocol used in VoIP networks. Cisco IP Phones using SCCP can coexist in an H.323 environment. When used with Cisco CallManager, the SCCP client can interoperate with H.323-compliant terminals. Application layer functions in the security appliance recognize SCCP Version 3.3. The functionality of the application layer software ensures that all SCCP signaling and media packets can traverse the security appliance by providing NAT of the SCCP Signaling packets.

There are 5 versions of the SCCP protocol: 2.4, 3.0.4, 3.1.1, 3.2, and 3.3.2. The security appliance supports all versions through Version 3.3.2. The security appliance provides both PAT and NAT support for SCCP. PAT is necessary if you have limited numbers of global IP addresses for use by IP phones.

Normal traffic between the Cisco CallManager and Cisco IP Phones uses SCCP and is handled by SCCP inspection without any special configuration. The security appliance also supports DHCP options 150 and 66, which allow the security appliance to send the location of a TFTP server to Cisco IP Phones and other DHCP clients. For more information, see the **dhcp-server** command.

Supporting Cisco IP Phones

In topologies where Cisco CallManager is located on the higher security interface with respect to the Cisco IP Phones, if NAT is required for the Cisco CallManager IP address, the mapping must be **static** as a Cisco IP Phone requires the Cisco CallManager IP address to be specified explicitly in its configuration. An identity static entry allows the Cisco CallManager on the higher security interface to accept registrations from the Cisco IP Phones.

Cisco IP Phones require access to a TFTP server to download the configuration information they need to connect to the Cisco CallManager server.

When the Cisco IP Phones are on a lower security interface compared to the TFTP server, you must use an access list to connect to the protected TFTP server on UDP port 69. While you do need a static entry for the TFTP server, this does not have to be an "identity" static entry. When using NAT, an identity static entry maps to the same IP address. When using PAT, it maps to the same IP address and port.

When the Cisco IP Phones are on a *higher* security interface compared to the TFTP server and Cisco CallManager, no access list or static entry is required to allow the Cisco IP Phones to initiate the connection.

Restrictions and Limitations

The following are limitations that apply to the current version of PAT and NAT support for SCCP:

- PAT will not work with configurations using the **alias** command.
- Outside NAT or PAT is **not** supported.



Note

Stateful Failover of SCCP calls is now supported except for calls that are in the middle of call setup.

If the address of an internal Cisco CallManager is configured for NAT or PAT to a different IP address or port, registrations for external Cisco IP Phones will fail because the security appliance currently does not support NAT or PAT for the file content transferred via TFTP. Although the security appliance does support NAT of TFTP messages, and opens a pinhole for the TFTP file to traverse the security appliance, the security appliance cannot translate the Cisco CallManager IP address and port embedded in the Cisco IP Phone's configuration files that are being transferred using TFTP during phone registration.

Inspecting Signaling Messages

For inspecting signaling messages, the **inspect skinny** command often needs to determine locations of the media endpoints (for example, IP phones).

This information is used to prepare access-control and NAT state for media traffic to traverse the firewall transparently without manual configuration.

In determining these locations, the **inspect skinny** command does **not** use the tunnel default gateway route. A tunnel default gateway route is a route of the form **route interface 0 0 metric tunneled**. This route overrides the default route for packets that egress from IPSec tunnels. Therefore, if the **inspect skinny** command is desired for VPN traffic, do not configure the tunnel default gateway route. Instead, use other static routing or dynamic routing.

Examples

You enable the SCCP inspection engine as shown in the following example, which creates a class map to match SCCP traffic on the default port (2000). The service policy is then applied to the outside interface.

```
hostname(config)# class-map skinny-port
hostname(config-cmap)# match port tcp eq 2000
hostname(config-cmap)# exit
```

```

hostname(config)# policy-map skinny_policy
hostname(config-pmap)# class skinny-port
hostname(config-pmap-c)# inspect skinny
hostname(config-pmap-c)# exit
hostname(config)# service-policy skinny_policy interface outside

```

To enable SCCP inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug skinny	Enables SCCP debug information.
show skinny	Displays information about SCCP sessions established through the security appliance.
show conn	Displays the connection state for different connection types.
timeout	Sets the maximum idle time duration for different protocols and session types.

inspect snmp

To enable SNMP application inspection or to change the ports to which the security appliance listens, use the **inspect snmp** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect snmp *map_name*

no inspect snmp *map_name*

Syntax Description

map_name The name of the SNMP map.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **inspect snmp** command to enable SNMP inspection, using the settings configured with an SNMP map, which you create using the **snmp-map** command. Use the **deny version** command in SNMP map configuration mode to restrict SNMP traffic to a specific version of SNMP.

Earlier versions of SNMP are less secure so restricting SNMP traffic to Version 2 may be required by your security policy. To deny a specific version of SNMP, use the **deny version** command within an SNMP map, which you create using the **snmp-map** command. After configuring the SNMP map, you enable the map using the **inspect snmp** command and then apply it to one or more interfaces using the **service-policy** command.

Examples

The following example identifies SNMP traffic, defines an SNMP map, defines a policy, enables SNMP inspection, and applies the policy to the outside interface:

```
hostname(config)# access-list snmp-acl permit tcp any any eq 161
hostname(config)# access-list snmp-acl permit tcp any any eq 162
hostname(config)# class-map snmp-port
hostname(config-cmap)# match access-list snmp-acl
hostname(config-cmap)# exit
hostname(config)# snmp-map inbound_snmp
hostname(config-snmp-map)# deny version 1
```

```

hostname(config-snmp-map)# exit
hostname(config)# policy-map inbound_policy
hostname(config-pmap)# class snmp-port
hostname(config-pmap-c)# inspect snmp inbound_snmp
hostname(config-pmap-c)# exit

```

To enable strict snmp application inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
deny version	Disallows traffic using a specific version of SNMP.
snmp-map	Defines an SNMP map and enables SNMP map configuration mode.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

inspect sqlnet

To enable Oracle SQL*Net application inspection, use the **inspect sqlnet** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect sqlnet

no inspect sqlnet

Syntax Description

This command has no arguments or keywords.

Defaults

This command is enabled by default.

The default port assignment is 1521.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the previously existing fixup command, which is now deprecated.

Usage Guidelines

The SQL*Net protocol consists of different packet types that the security appliance handles to make the data stream appear consistent to the Oracle applications on either side of the security appliance.

The default port assignment for SQL*Net is 1521. This is the value used by Oracle for SQL*Net, but this value does not agree with IANA port assignments for Structured Query Language (SQL). Use the **class-map** command to apply SQL*Net inspection to a range of port numbers.

The security appliance NATs all addresses and looks in the packets for all embedded ports to open for SQL*Net Version 1.

For SQL*Net Version 2, all DATA or REDIRECT packets that immediately follow REDIRECT packets with a zero data length will be fixed up.

The packets that need fix-up contain embedded host/port addresses in the following format:

(ADDRESS=(PROTOCOL=tcp) (DEV=6) (HOST=a.b.c.d) (PORT=a))

SQL*Net Version 2 TNSFrame types (Connect, Accept, Refuse, Resend, and Marker) will not be scanned for addresses to NAT nor will inspection open dynamic connections for any embedded ports in the packet.

SQL*Net Version 2 TNSFrames, Redirect, and Data packets will be scanned for ports to open and addresses to NAT, if preceded by a REDIRECT TNSFrame type with a zero data length for the payload. When the Redirect message with data length zero passes through the security appliance, a flag will be set in the connection data Structure to expect the Data or Redirect message that follows to be NATed and ports to be dynamically opened. If one of the TNS frames in the preceding paragraph arrive after the Redirect message, the flag will be reset.

The SQL*Net inspection engine will recalculate the checksum, change IP, TCP lengths, and readjust Sequence Numbers and Acknowledgment Numbers using the delta of the length of the new and old message.

SQL*Net Version 1 is assumed for all other cases. TNSFrame types (Connect, Accept, Refuse, Resend, Marker, Redirect, and Data) and all packets will be scanned for ports and addresses. Addresses will be NATed and port connections will be opened.

Examples

You enable the SQL*Net inspection engine as shown in the following example, which creates a class map to match SQL*Net traffic on the default port (1521). The service policy is then applied to the outside interface.

```
hostname(config)# class-map sqlnet-port
hostname(config-cmap)# match port tcp eq 1521
hostname(config-cmap)# exit
hostname(config)# policy-map sqlnet_policy
hostname(config-pmap)# class sqlnet-port
hostname(config-pmap-c)# inspect sqlnet
hostname(config-pmap-c)# exit
hostname(config)# service-policy sqlnet_policy interface outside
```

To enable SQL*Net inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug sqlnet	Enables debug information for SQL*Net.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.
show conn	Displays the connection state for different connection types, including SQL*net.

inspect sunrpc

To enable Sun RPC application inspection or to change the ports to which the security appliance listens, use the **inspect sunrpc** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect sunrpc

no inspect sunrpc

Syntax Description

This command has no arguments or keywords.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the fixup command, which is now deprecated.

Usage Guidelines

To enable Sun RPC application inspection or to change the ports to which the security appliance listens, use the **inspect sunrpc** command in policy map class configuration mode, which is accessible by using the **class** command within policy map configuration mode. To remove the configuration, use the **no** form of this command.

The **inspect sunrpc** command enables or disables application inspection for the Sun RPC protocol. Sun RPC is used by NFS and NIS. Sun RPC services can run on any port on the system. When a client attempts to access a Sun RPC service on a server, it must find out which port that service is running on. It does this by querying the portmapper process on the well-known port of 111.

The client sends the Sun RPC program number of the service, and gets back the port number. From this point on, the client program sends its Sun RPC queries to that new port. When a server sends out a reply, the security appliance intercepts this packet and opens both embryonic TCP and UDP connections on that port.



Note

NAT or PAT of Sun RPC payload information is not supported.

Examples

You enable the RPC inspection engine as shown in the following example, which creates a class map to match RPC traffic on the default port (111). The service policy is then applied to the outside interface.

```
hostname(config)# class-map sunrpc-port
hostname(config-cmap)# match port tcp eq 111
hostname(config-cmap)# exit
hostname(config)# policy-map sample_policy
hostname(config-pmap)# class sunrpc-port
hostname(config-pmap-c)# inspect sunrpc
hostname(config-pmap-c)# exit
hostname(config)# service-policy sample_policy interface outside
```

To enable RPC inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
clear configure sunrpc_server	Removes the configuration performed using the sunrpc-server command.
clear sunrpc-server active	Clears the pinholes that are opened by Sun RPC application inspection for specific services, such as NFS or NIS.
show running-config sunrpc-server	Displays the information about the Sun RPC service table configuration.
sunrpc-server	Allows pinholes to be created with a specified timeout for Sun RPC services, such as NFS or NIS.
show sunrpc-server active	Displays the pinholes open for Sun RPC services.

inspect tftp

To disable TFTP application inspection, or to enable it if it has been previously disabled, use the **inspect tftp** command in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect tftp

no inspect tftp

Syntax Description

This command has no arguments or keywords.

Defaults

This command is enabled by default.

The default port assignment is 69.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the previously existing fixup command, which is now deprecated.

Usage Guidelines

Trivial File Transfer Protocol (TFTP), described in RFC 1350, is a simple protocol to read and write files between a TFTP server and client.

The security appliance inspects TFTP traffic and dynamically creates connections and translations, if necessary, to permit file transfer between a TFTP client and server. Specifically, the inspection engine inspects TFTP read request (RRQ), write request (WRQ), and error notification (ERROR).

A dynamic secondary channel and a PAT translation, if necessary, are allocated on a reception of a valid read (RRQ) or write (WRQ) request. This secondary channel is subsequently used by TFTP for file transfer or error notification.

Only the TFTP server can initiate traffic over the secondary channel, and at most one incomplete secondary channel can exist between the TFTP client and server. An error notification from the server closes the secondary channel.

TFTP inspection must be enabled if static PAT is used to redirect TFTP traffic.

Examples

You enable the TFTP inspection engine as shown in the following example, which creates a class map to match TFTP traffic on the default port (69). The service policy is then applied to the outside interface.

```
hostname(config)# class-map tftp-port
hostname(config-cmap)# match port udp eq 69
hostname(config-cmap)# exit
hostname(config)# policy-map tftp_policy
hostname(config-pmap)# class tftp-port
hostname(config-pmap-c)# inspect tftp
hostname(config-pmap-c)# exit
hostname(config)# service-policy tftp_policy interface outside
```

To enable TFTP inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

inspect xdmcp

To enable XDMCP application inspection or to change the ports to which the security appliance listens, use the **inspect xdmcp command** in class configuration mode. Class configuration mode is accessible from policy map configuration mode. To remove the configuration, use the **no** form of this command.

inspect xdmcp

no inspect xdmcp

Syntax Description

This command has no arguments or keywords.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Class configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced, replacing the previously existing fixup command, which is now deprecated.

Usage Guidelines

The **inspect xdmcp** command enables or disables application inspection for the XDMCP protocol. XDMCP is a protocol that uses UDP port 177 to negotiate X sessions, which use TCP when established. For successful negotiation and start of an XWindows session, the security appliance must allow the TCP back connection from the Xhosted computer. To permit the back connection, use the **established** command on the security appliance. Once XDMCP negotiates the port to send the display, The **established** command is consulted to verify if this back connection should be permitted.

During the XWindows session, the manager talks to the display Xserver on the well-known port 6000 *n*. Each display has a separate connection to the Xserver, as a result of the following terminal setting.

```
setenv DISPLAY Xserver:n
```

where *n* is the display number.

When XDMCP is used, the display is negotiated using IP addresses, which the security appliance can NAT if needed. XDCMP inspection does not support PAT.

Examples

You enable the XDMCP inspection engine as shown in the following example, which creates a class map to match XDMCP traffic on the default port (177). The service policy is then applied to the outside interface.

```
hostname(config)# class-map xdmcp-port
hostname(config-cmap)# match port tcp eq 177
hostname(config-cmap)# exit
hostname(config)# policy-map xdmcp_policy
hostname(config-pmap)# class xdmcp-port
hostname(config-pmap-c)# inspect xdmcp
hostname(config-pmap-c)# exit
hostname(config)# service-policy xdmcp_policy interface outside
```

To enable XDMCP inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug xdmcp	Enables debug information for XDMCP.
policy-map	Associates a class map with specific security actions.
service-policy	Applies a policy map to one or more interfaces.

intercept-dhcp

To enable DHCP Intercept, use the **intercept-dhcp enable** command in group-policy configuration mode. To disable DHCP Intercept, use the **intercept-dhcp disable** command.

To remove the intercept-dhcp attribute from the running configuration, use the **no intercept-dhcp** command. This lets users inherit a DHCP Intercept configuration from the default or other group policy.

DHCP Intercept lets Microsoft XP clients use split-tunneling with the security appliance. The security appliance replies directly to the Microsoft Windows XP client DHCP Inform message, providing that client with the subnet mask, domain name, and classless static routes for the tunnel IP address. For Windows clients prior to XP, DHCP Intercept provides the domain name and subnet mask. This is useful in environments in which using a DHCP server is not advantageous

intercept-dhcp *netmask* { **enable** | **disable** }

no intercept-dhcp

Syntax Description

disable	Disables DHCP Intercept.
enable	Enables DHCP Intercept.
<i>netmask</i>	Provides the subnet mask for the tunnel IP address.

Defaults

DHCP Intercept is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

A Microsoft XP anomaly results in the corruption of domain names if split tunnel options exceed 255 bytes. To avoid this problem, the security appliance limits the number of routes it sends to 27 to 40 routes, with the number of routes dependent on the classes of the routes.

Examples

The following example shows how to set DHCP Intercept S for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# intercept-dhcp enable
```

interface

To configure an interface and enter interface configuration mode, use the **interface** command in global configuration mode. To create a logical subinterface, use the *subinterface* argument. To remove a subinterface, use the **no** form of this command; you cannot remove a physical interface. In interface configuration mode, you can configure hardware settings, assign a name, assign a VLAN, assign an IP address, and configure many other settings.

interface {*physical_interface*[.*subinterface*] | *mapped_name*}

no interface *physical_interface.subinterface*

Syntax Description

<i>mapped_name</i>	In multiple context mode, enter the mapped name if it was assigned using the allocate-interface command.
<i>physical_interface</i>	The physical interface type, slot, and port number as <i>type[slot/port]</i>. A space between the type and slot/port is optional. The physical interface types include the following: • ethernet • gigabitethernet For the PIX 500 series security appliance, enter the type followed by the port number, for example, ethernet0. For the ASA 5500 series adaptive security appliance, enter the type followed by slot/port, for example, gigabitethernet0/1. Interfaces that are built into the chassis are assigned to slot 0, while interfaces on the 4GE SSM are assigned to slot 1. The ASA 5500 series adaptive security appliance also includes the following type: • management The management interface is a Fast Ethernet interface designed for management traffic only, and is specified as management0/0. You can, however, use it for through traffic if desired (see the management-only command). In transparent firewall mode, you can use the management interface in addition to the two interfaces allowed for through traffic. You can also add subinterfaces to the management interface to provide management in each security context for multiple context mode. See the hardware documentation that came with your model to identify the interface type, slot, and port number.
subinterface	(Optional) An integer between 1 and 4294967293 designating a logical subinterface. The maximum number of subinterfaces varies depending on your security appliance model. See the <i>Cisco Security Appliance Command Line Configuration Guide</i> for the maximum subinterfaces per platform.

Defaults

By default, the security appliance automatically generates **interface** commands for all physical interfaces.

In multiple context mode, the security appliance automatically generates **interface** commands for all interfaces allocated to the context using the **allocate-interface** command.

All physical interfaces are shut down by default. Allocated interfaces in contexts are not shut down in the configuration.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was modified to allow for new subinterface naming conventions and to change arguments to be separate commands under interface configuration mode.

Usage Guidelines

By default, all physical interfaces are shut down. You must enable the physical interface before any traffic can pass through an enabled subinterface. For multiple context mode, if you allocate a physical interface or subinterface to a context, the interfaces are enabled by default in the context. However, before traffic can pass through the context interface, you must also enable the interface in the system configuration. If you shut down an interface in the system execution space, then that interface is down in all contexts that share it.

For an enabled interface to pass traffic, configure the following interface configuration mode commands: **nameif**, and, for routed mode, **ip address**. For subinterfaces, configure the **vlan** command. The security level is 0 (lowest) by default. See the **security-level** command for default levels for some interfaces or to change from the default of 0 so interfaces can communicate with each other.

The ASA adaptive security appliance includes a dedicated management interface called Management 0/0, which is meant to support traffic to the security appliance. However, you can configure any interface to be a management-only interface using the **management-only** command. Also, for Management 0/0, you can disable management-only mode so the interface can pass through traffic just like any other interface.



Note

Transparent firewall mode allows only two interfaces to pass through traffic; however, on the ASA adaptive security appliance, you can use the dedicated management interface (either the physical interface or a subinterface) as a third interface for management traffic. The mode is not configurable in this case and must always be management-only.

If you change interface settings, and you do not want to wait for existing connections to time out before the new security information is used, you can clear the connections using the **clear local-host** command.

You cannot delete the physical interfaces using the **no** form of the **interface** command, nor can you delete the allocated interfaces within a context.

In multiple context mode, you configure physical parameters, subinterfaces, and VLAN assignments in the system configuration only. You configure other parameters in the context configuration only.

Examples

The following example configures parameters for the physical interface in single mode:

```
hostname(config)# interface gigabitethernet0/1
hostname(config-if)# speed 1000
hostname(config-if)# duplex full
hostname(config-if)# nameif inside
hostname(config-if)# security-level 100
hostname(config-if)# ip address 10.1.1.1 255.255.255.0
hostname(config-if)# no shutdown
```

The following example configures parameters for a subinterface in single mode:

```
hostname(config)# interface gigabitethernet0/1.1
hostname(config-subif)# vlan 101
hostname(config-subif)# nameif dmz1
hostname(config-subif)# security-level 50
hostname(config-subif)# ip address 10.1.2.1 255.255.255.0
hostname(config-subif)# no shutdown
```

The following example configures interface parameters in multiple context mode for the system configuration, and allocates the gigabitethernet 0/1.1 subinterface to contextA:

```
hostname(config)# interface gigabitethernet0/1
hostname(config-if)# speed 1000
hostname(config-if)# duplex full
hostname(config-if)# no shutdown
hostname(config-if)# interface gigabitethernet0/1.1
hostname(config-subif)# vlan 101
hostname(config-subif)# no shutdown
hostname(config-subif)# context contextA
hostname(config-ctx)# ...
hostname(config-ctx)# allocate-interface gigabitethernet0/1.1
```

The following example configures parameters in multiple context mode for the context configuration:

```
hostname/contextA(config)# interface gigabitethernet0/1.1
hostname/contextA(config-if)# nameif inside
hostname/contextA(config-if)# security-level 100
hostname/contextA(config-if)# ip address 10.1.2.1 255.255.255.0
hostname/contextA(config-if)# no shutdown
```

Related Commands

Command	Description
allocate-interface	Assigns interfaces and subinterfaces to a security context.
clear configure interface	Clears all configuration for an interface.
clear interface	Clears counters for the show interface command.
show interface	Displays the runtime status and statistics of interfaces.

interface (vpn load-balancing)

To specify a non-default public or private interface for VPN load-balancing in the VPN load-balancing virtual cluster, use the **interface** command in vpn load-balancing mode. To remove the interface specification and revert to the default interface, use the **no** form of this command.

interface {**lbprivate** | **lbpublic**} *interface-name*

no interface {**lbprivate** | **lbpublic**}

Syntax Description

<i>interface-name</i>	The name of the interface to be configured as the public or private interface for the VPN load-balancing cluster.
lbprivate	Specifies that this command configures the private interface for VPN load-balancing.
lbpublic	Specifies that this command configures the public interface for VPN load-balancing.

Defaults

If you omit the **interface** command, the **lbprivate** interface defaults to **inside**, and the **lbpublic** interface defaults to **outside**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
vpn load-balancing	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must have first used the **vpn load-balancing** command to enter vpn load-balancing mode.

You must also have previously used the **interface**, **ip address**, and **nameif** commands to configure and assign a name to the interface that you are specifying in this command.

The no form of this command reverts the interface to its default.

Examples

The following is an example of a **vpn load-balancing** command sequence that includes an **interface** command that specifies the public interface of the cluster as “test” one that reverts the private interface of the cluster to the default (inside):

```
hostname(config)# interface GigabitEthernet 0/1
hostname(config-if)# ip address 209.165.202.159 255.255.255.0
```

■ interface (vpn load-balancing)

```

hostname(config)# nameif test
hostname(config)# interface GigabitEthernet 0/2
hostname(config-if)# ip address 209.165.201.30 255.255.255.0
hostname(config)# nameif foo
hostname(config)# vpn load-balancing
hostname(config-load-balancing)# interface lbpublic test
hostname(config-load-balancing)# no interface lbprivate
hostname(config-load-balancing)# cluster ip address 209.165.202.224
hostname(config-load-balancing)# participate

```

Related Commands

Command	Description
vpn load-balancing	Enter VPN load-balancing mode.

interface-policy

To specify the policy for failover when monitoring detects an interface failure, use the **interface-policy** command in failover group configuration mode. To restore the default values, use the **no** form of this command.

interface-policy *num*[%]

no interface-policy *num*[%]

Syntax Description

<i>num</i>	Specifies a number from 1 to 100 when used as a percentage, or 1 to the maximum number of interfaces.
%	(Optional) Specifies that the number <i>num</i> is a percentage of the monitored interfaces.

Defaults

If the **failover interface-policy** command is configured for the unit, then the default for the **interface-policy** failover group command assumes that value. If not, then *num* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Failover group configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

There is no space between the *num* argument and the optional % keyword.

If the number of failed interfaces meets the configured policy and the other security appliance is functioning properly, the security appliance will mark itself as failed and a failover may occur (if the active security appliance is the one that fails). Only interfaces that are designated as monitored by the **monitor-interface** command count towards the policy.

Examples

The following partial example shows a possible configuration for a failover group:

```
hostname(config)# failover group 1
hostname(config-fover-group)# primary
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# interface-policy 25%
hostname(config-fover-group)# exit
hostname(config)#
```

Related Commands	Command	Description
	failover group	Defines a failover group for Active/Active failover.
	failover interface-policy	Configures the interface monitoring policy.
	monitor-interface	Specifies the interfaces being monitored for failover.

ip-address

To include the security appliance IP address in the certificate during enrollment, use the **ip-addr** command in crypto ca trustpoint configuration mode. To restore the default setting, use the **no** form of the command.

ip-address *ip-address*

no ip-address

Syntax Description

ip-address Specifies the IP address of the security appliance.

Defaults

The default setting is to not include the IP address.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and includes the security appliance IP address in the enrollment request for trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# ip-address 209.165.200.225
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint configuration mode.
default enrollment	Returns enrollment parameters to their defaults.

ip address

To set the IP address for an interface (in routed mode) or for the management address (transparent mode), use the **ip address** command. For routed mode, enter this command in interface configuration mode. In transparent mode, enter this command in global configuration mode. To remove the IP address, use the **no** form of this command. This command also sets the standby address for failover.

ip address *ip_address* [*mask*] [**standby** *ip_address*]

no ip address [*ip_address*]

Syntax Description

<i>ip_address</i>	The IP address for the interface (routed mode) or the management IP address (transparent mode).
<i>mask</i>	(Optional) The subnet mask for the IP address. If you do not set the mask, the security appliance uses the default mask for the IP address class.
standby <i>ip_address</i>	(Optional) The IP address for the standby unit for failover.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	•	—
Global configuration	—	•	•	•	—

Command History

Release	Modification
7.0	For routed mode, this command was changed from a global configuration command to an interface configuration mode command.

Usage Guidelines

In single context routed firewall mode, each interface address must be on a unique subnet. In multiple context mode, if this interface is on a shared interface, then each IP address must be unique but on the same subnet. If the interface is unique, this IP address can be used by other contexts if desired.

A transparent firewall does not participate in IP routing. The only IP configuration required for the security appliance is to set the management IP address. This address is required because the security appliance uses this address as the source address for traffic originating on the security appliance, such as system messages or communications with AAA servers. You can also use this address for remote management access. This address must be on the same subnet as the upstream and downstream routers. For multiple context mode, set the management IP address within each context.

The standby IP address must be on the same subnet as the main IP address.

Examples

The following example sets the IP addresses and standby addresses of two interfaces:

```
hostname(config)# interface gigabitethernet0/2
hostname(config-if)# nameif inside
hostname(config-if)# security-level 100
hostname(config-if)# ip address 10.1.1.1 255.255.255.0 standby 10.1.1.2
hostname(config-if)# no shutdown
hostname(config-if)# interface gigabitethernet0/3
hostname(config-if)# nameif outside
hostname(config-if)# security-level 0
hostname(config-if)# ip address 10.1.2.1 255.255.255.0 standby 10.1.2.2
hostname(config-if)# no shutdown
```

The following example sets the management address and standby address of a transparent firewall:

```
hostname(config)# ip address 10.1.1.1 255.255.255.0 standby 10.1.1.2
```

Related Commands

Command	Description
interface	Configures an interface and enters interface configuration mode.
ip address dhcp	Sets the interface to obtain an IP address from a DHCP server.
show ip address	Shows the IP address assigned to an interface.

ip address dhcp

To use DHCP to obtain an IP address for an interface, use the **ip address dhcp** command in interface configuration mode. To disable the DHCP client for this interface, use the **no** form of this command.

ip address dhcp [setroute]

no ip address dhcp

Syntax Description

setroute (Optional) Allows the security appliance to use the default route supplied by the DHCP server.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was changed from a global configuration command to an interface configuration mode command. You can also enable this command on any interface, instead of only the outside interface.

Usage Guidelines

Reenter this command to reset the DHCP lease and request a new lease.

You cannot set this command at the same time as the **ip address** command.

If you enable the **setroute** option, do not configure a default route using the **route** command.

If you do not enable the interface using the **no shutdown** command before you enter the **ip address dhcp** command, some DHCP requests might not be sent.



Note

The security appliance rejects any leases that have a timeout of less than 32 seconds.

Examples

The following example enables DHCP on the gigabitethernet0/1 interface:

```
hostname(config)# interface gigabitethernet0/1
hostname(config-if)# nameif inside
hostname(config-if)# security-level 100
hostname(config-if)# no shutdown
hostname(config-if)# ip address dhcp
```

Related Commands	Command	Description
	interface	Configures an interface and enters interface configuration mode.
	ip address	Sets the IP address for the interface or sets the management IP address for a transparent firewall.
	show ip address dhcp	Shows the IP address obtained from the DHCP server.

ip audit attack

To set the default actions for packets that match an attack signature, use the **ip audit attack** command in global configuration mode. To restore the default action (to reset the connection), use the **no** form of this command. You can specify multiple actions, or no actions.

ip audit attack [**action** [**alarm**] [**drop**] [**reset**]]

no ip audit attack

Syntax Description

action	(Optional) Specifies that you are defining a set of default actions. If you do not follow this keyword with any actions, then the security appliance takes no action. If you do not enter the action keyword, the security appliance assumes you entered it, and the action keyword appears in the configuration.
alarm	(Default) Generates a system message showing that a packet matched a signature.
drop	(Optional) Drops the packet.
reset	(Optional) Drops the packet and closes the connection.

Defaults

The default action is to send and alarm.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

You can override the action you set with this command when you configure an audit policy using the **ip audit name** command. If you do not specify the action in the **ip audit name** command, then the action you set with this command is used.

For a list of signatures, see the **ip audit signature** command.

Examples

The following example sets the default action to alarm and reset for packets that match an attack signature. The audit policy for the inside interface overrides this default to be alarm only, while the policy for the outside interface uses the default setting set with the **ip audit attack** command.

```
hostname(config)# ip audit attack action alarm reset
```

```
hostname(config)# ip audit name insidepolicy attack action alarm
hostname(config)# ip audit name outsidepolicy attack
hostname(config)# ip audit interface inside insidepolicy
hostname(config)# ip audit interface outside outsidepolicy
```

Related Commands

Command	Description
ip audit name	Creates a named audit policy that identifies the actions to take when a packet matches an attack signature or an informational signature.
ip audit info	Sets the default actions for packets that match an informational signature.
ip audit interface	Assigns an audit policy to an interface.
ip audit signature	Disables a signature.
show running-config ip audit attack	Shows the configuration for the ip audit attack command.

ip audit info

To set the default actions for packets that match an informational signature, use the **ip audit info** command in global configuration mode. To restore the default action (to generate an alarm), use the **no** form of this command. You can specify multiple actions, or no actions.

ip audit info [**action** [**alarm**] [**drop**] [**reset**]]

no ip audit info

Syntax Description

action	(Optional) Specifies that you are defining a set of default actions. If you do not follow this keyword with any actions, then the security appliance takes no action. If you do not enter the action keyword, the security appliance assumes you entered it, and the action keyword appears in the configuration.
alarm	(Default) Generates a system message showing that a packet matched a signature.
drop	(Optional) Drops the packet.
reset	(Optional) Drops the packet and closes the connection.

Defaults

The default action is to generate an alarm.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

You can override the action you set with this command when you configure an audit policy using the **ip audit name** command. If you do not specify the action in the **ip audit name** command, then the action you set with this command is used.

For a list of signatures, see the **ip audit signature** command.

Examples

The following example sets the default action to alarm and reset for packets that match an informational signature. The audit policy for the inside interface overrides this default to be alarm and drop, while the policy for the outside interface uses the default setting set with the **ip audit info** command.

```
hostname(config)# ip audit info action alarm reset
```



```
hostname(config)# ip audit name insidepolicy info action alarm drop
hostname(config)# ip audit name outsidepolicy info
hostname(config)# ip audit interface inside insidepolicy
hostname(config)# ip audit interface outside outsidepolicy
```

Related Commands

Command	Description
ip audit name	Creates a named audit policy that identifies the actions to take when a packet matches an attack signature or an informational signature.
ip audit attack	Sets the default actions for packets that match an attack signature.
ip audit interface	Assigns an audit policy to an interface.
ip audit signature	Disables a signature.
show running-config ip audit info	Shows the configuration for the ip audit info command.

ip audit interface

To assign an audit policy to an interface, use the **ip audit interface** command in global configuration mode. To remove the policy from the interface, use the **no** form of this command.

ip audit interface *interface_name* *policy_name*

no ip audit interface *interface_name* *policy_name*

Syntax Description

<i>interface_name</i>	Specifies the interface name.
<i>policy_name</i>	The name of the policy you added with the ip audit name command. You can assign an info policy and an attack policy to each interface.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example applies audit policies to the inside and outside interfaces:

```
hostname(config)# ip audit name insidepolicy1 attack action alarm
hostname(config)# ip audit name insidepolicy2 info action alarm
hostname(config)# ip audit name outsidepolicy1 attack action reset
hostname(config)# ip audit name outsidepolicy2 info action alarm
hostname(config)# ip audit interface inside insidepolicy1
hostname(config)# ip audit interface inside insidepolicy2
hostname(config)# ip audit interface outside outsidepolicy1
hostname(config)# ip audit interface outside outsidepolicy2
```

Related Commands

Command	Description
ip audit attack	Sets the default actions for packets that match an attack signature.
ip audit info	Sets the default actions for packets that match an informational signature.
ip audit name	Creates a named audit policy that identifies the actions to take when a packet matches an attack signature or an informational signature.

Command	Description
ip audit signature	Disables a signature.
show running-config ip audit interface	Shows the configuration for the ip audit interface command.

ip audit name

To create a named audit policy that identifies the actions to take when a packet matches a predefined attack signature or informational signature, use the **ip audit name** command in global configuration mode. Signatures are activities that match known attack patterns. For example, there are signatures that match DoS attacks. To remove the policy, use the **no** form of this command.

ip audit name *name* {**info** | **attack**} [**action** [**alarm**] [**drop**] [**reset**]]

no ip audit name *name* {**info** | **attack**} [**action** [**alarm**] [**drop**] [**reset**]]

Syntax Description

action	(Optional) Specifies that you are defining a set of actions. If you do not follow this keyword with any actions, then the security appliance takes no action. If you do not enter the action keyword, then the security appliance uses the default action set by the ip audit attack and ip audit info commands.
alarm	(Optional) Generates a system message showing that a packet matched a signature.
attack	Creates an audit policy for attack signatures; the packet might be part of an attack on your network, such as a DoS attack or illegal FTP commands.
drop	(Optional) Drops the packet.
info	Creates an audit policy for informational signatures; the packet is not currently attacking your network, but could be part of an information-gathering activity, such as a port sweep.
<i>name</i>	Sets the name of the policy.
reset	(Optional) Drops the packet and closes the connection.

Defaults

If you do not change the default actions using the **ip audit attack** and **ip audit info** commands, then the default action for attack signatures and informational signatures is to generate an alarm.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To apply the policy, assign it to an interface using the **ip audit interface** command. You can assign an **info** policy and an **attack** policy to each interface.

For a list of signatures, see the **ip audit signature** command.

If traffic matches a signature, and you want to take action against that traffic, use the **shun** command to prevent new connections from the offending host and to disallow packets from any existing connection.

Examples

The following example sets an audit policy for the inside interface to generate an alarm for attack and informational signatures, while the policy for the outside interface resets the connection for attacks:

```
hostname(config)# ip audit name insidepolicy1 attack action alarm
hostname(config)# ip audit name insidepolicy2 info action alarm
hostname(config)# ip audit name outsidepolicy1 attack action reset
hostname(config)# ip audit name outsidepolicy2 info action alarm
hostname(config)# ip audit interface inside insidepolicy1
hostname(config)# ip audit interface inside insidepolicy2
hostname(config)# ip audit interface outside outsidepolicy1
hostname(config)# ip audit interface outside outsidepolicy2
```

Related Commands

Command	Description
ip audit attack	Sets the default actions for packets that match an attack signature.
ip audit info	Sets the default actions for packets that match an informational signature.
ip audit interface	Assigns an audit policy to an interface.
ip audit signature	Disables a signature.
shun	Blocks packets with a specific source and destination address.

ip audit signature

To disable a signature for an audit policy, use the **ip audit signature** command in global configuration mode. To reenable the signature, use the **no** form of this command. You might want to disable a signature if legitimate traffic continually matches a signature, and you are willing to risk disabling the signature to avoid large numbers of alarms.

ip audit signature *signature_number* **disable**

no ip audit signature *signature_number*

Syntax Description

<i>signature_number</i>	Specifies the signature number to disable. See Table 5-4 for a list of supported signatures.
disable	Disables the signature.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

[Table 5-4](#) lists supported signatures and system message numbers.

Table 5-4 Signature IDs and System Message Numbers

Signature ID	Message Number	Signature Title	Signature Type	Description
1000	400000	IP options-Bad Option List	Informational	Triggers on receipt of an IP datagram where the list of IP options in the IP datagram header is incomplete or malformed. The IP options list contains one or more options that perform various network management or debugging tasks.
1001	400001	IP options-Record Packet Route	Informational	Triggers on receipt of an IP datagram where the IP option list for the datagram includes option 7 (Record Packet Route).

Table 5-4 *Signature IDs and System Message Numbers (continued)*

Signature ID	Message Number	Signature Title	Signature Type	Description
1002	400002	IP options-Timestamp	Informational	Triggers on receipt of an IP datagram where the IP option list for the datagram includes option 4 (Timestamp).
1003	400003	IP options-Security	Informational	Triggers on receipt of an IP datagram where the IP option list for the datagram includes option 2 (Security options).
1004	400004	IP options-Loose Source Route	Informational	Triggers on receipt of an IP datagram where the IP option list for the datagram includes option 3 (Loose Source Route).
1005	400005	IP options-SATNET ID	Informational	Triggers on receipt of an IP datagram where the IP option list for the datagram includes option 8 (SATNET stream identifier).
1006	400006	IP options-Strict Source Route	Informational	Triggers on receipt of an IP datagram in which the IP option list for the datagram includes option 2 (Strict Source Routing).
1100	400007	IP Fragment Attack	Attack	Triggers when any IP datagram is received with an offset value less than 5 but greater than 0 indicated in the offset field.
1102	400008	IP Impossible Packet	Attack	Triggers when an IP packet arrives with source equal to destination address. This signature will catch the so-called Land Attack.
1103	400009	IP Overlapping Fragments (Teardrop)	Attack	Triggers when two fragments contained within the same IP datagram have offsets that indicate that they share positioning within the datagram. This could mean that fragment A is being completely overwritten by fragment B, or that fragment A is partially being overwritten by fragment B. Some operating systems do not properly handle fragments that overlap in this manner and may throw exceptions or behave in other undesirable ways upon receipt of overlapping fragments, which is how the Teardrop attack works to create a DoS.
2000	400010	ICMP Echo Reply	Informational	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 0 (Echo Reply).
2001	400011	ICMP Host Unreachable	Informational	Triggers when an IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 3 (Host Unreachable).

Table 5-4 **Signature IDs and System Message Numbers (continued)**

Signature ID	Message Number	Signature Title	Signature Type	Description
2002	400012	ICMP Source Quench	Informational	Triggers when an IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 4 (Source Quench).
2003	400013	ICMP Redirect	Informational	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 5 (Redirect).
2004	400014	ICMP Echo Request	Informational	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 8 (Echo Request).
2005	400015	ICMP Time Exceeded for a Datagram	Informational	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 11 (Time Exceeded for a Datagram).
2006	400016	ICMP Parameter Problem on Datagram	Informational	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 12 (Parameter Problem on Datagram).
2007	400017	ICMP Timestamp Request	Informational	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 13 (Timestamp Request).
2008	400018	ICMP Timestamp Reply	Informational	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 14 (Timestamp Reply).
2009	400019	ICMP Information Request	Informational	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 15 (Information Request).
2010	400020	ICMP Information Reply	Informational	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 16 (ICMP Information Reply).
2011	400021	ICMP Address Mask Request	Informational	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 17 (Address Mask Request).
2012	400022	ICMP Address Mask Reply	Informational	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the type field in the ICMP header set to 18 (Address Mask Reply).

Table 5-4 Signature IDs and System Message Numbers (continued)

Signature ID	Message Number	Signature Title	Signature Type	Description
2150	400023	Fragmented ICMP Traffic	Attack	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and either the more fragments flag is set to 1 (ICMP) or there is an offset indicated in the offset field.
2151	400024	Large ICMP Traffic	Attack	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP) and the IP length > 1024.
2154	400025	Ping of Death Attack	Attack	Triggers when a IP datagram is received with the protocol field of the IP header set to 1 (ICMP), the Last Fragment bit is set, and $(IP\ offset * 8) + (IP\ data\ length) > 65535$ that is to say, the IP offset (which represents the starting position of this fragment in the original packet, and which is in 8 byte units) plus the rest of the packet is greater than the maximum size for an IP packet.
3040	400026	TCP NULL flags	Attack	Triggers when a single TCP packet with none of the SYN, FIN, ACK, or RST flags set has been sent to a specific host.
3041	400027	TCP SYN+FIN flags	Attack	Triggers when a single TCP packet with the SYN and FIN flags are set and is sent to a specific host.
3042	400028	TCP FIN only flags	Attack	Triggers when a single orphaned TCP FIN packet is sent to a privileged port (having port number less than 1024) on a specific host.
3153	400029	FTP Improper Address Specified	Informational	Triggers if a port command is issued with an address that is not the same as the requesting host.
3154	400030	FTP Improper Port Specified	Informational	Triggers if a port command is issued with a data port specified that is <1024 or >65535.
4050	400031	UDP Bomb attack	Attack	Triggers when the UDP length specified is less than the IP length specified. This malformed packet type is associated with a denial of service attempt.
4051	400032	UDP Snork attack	Attack	Triggers when a UDP packet with a source port of either 135, 7, or 19 and a destination port of 135 is detected.
4052	400033	UDP Chargen DoS attack	Attack	This signature triggers when a UDP packet is detected with a source port of 7 and a destination port of 19.
6050	400034	DNS HINFO Request	Informational	Triggers on an attempt to access HINFO records from a DNS server.

Table 5-4 Signature IDs and System Message Numbers (continued)

Signature ID	Message Number	Signature Title	Signature Type	Description
6051	400035	DNS Zone Transfer	Informational	Triggers on normal DNS zone transfers, in which the source port is 53.
6052	400036	DNS Zone Transfer from High Port	Informational	Triggers on an illegitimate DNS zone transfer, in which the source port is not equal to 53.
6053	400037	DNS Request for All Records	Attack	Triggers on a DNS request for all records.
6100	400038	RPC Port Registration	Informational	Triggers when attempts are made to register new RPC services on a target host.
6101	400039	RPC Port Unregistration	Informational	Triggers when attempts are made to unregister existing RPC services on a target host.
6102	400040	RPC Dump	Informational	Triggers when an RPC dump request is issued to a target host.
6103	400041	Proxied RPC Request	Attack	Triggers when a proxied RPC request is sent to the portmapper of a target host.
6150	400042	ypserv (YP server daemon) Portmap Request	Informational	Triggers when a request is made to the portmapper for the YP server daemon (ypserv) port.
6151	400043	ypbind (YP bind daemon) Portmap Request	Informational	Triggers when a request is made to the portmapper for the YP bind daemon (ypbind) port.
6152	400044	yppasswdd (YP password daemon) Portmap Request	Informational	Triggers when a request is made to the portmapper for the YP password daemon (yppasswdd) port.
6153	400045	ypupdated (YP update daemon) Portmap Request	Attack	Triggers when a request is made to the portmapper for the YP update daemon (ypupdated) port.
6154	400046	ypxfrd (YP transfer daemon) Portmap Request	Attack	Triggers when a request is made to the portmapper for the YP transfer daemon (ypxfrd) port.
6155	400047	mountd (mount daemon) Portmap Request	Informational	Triggers when a request is made to the portmapper for the mount daemon (mountd) port.
6175	400048	rexcd (remote execution daemon) Portmap Request	Informational	Triggers when a request is made to the portmapper for the remote execution daemon (rexcd) port.

Table 5-4 Signature IDs and System Message Numbers (continued)

Signature ID	Message Number	Signature Title	Signature Type	Description
6180	400049	rexid (remote execution daemon) Attempt	Informational	Triggers when a call to the rexd program is made. The remote execution daemon is the server responsible for remote program execution. This may be indicative of an attempt to gain unauthorized access to system resources.
6190	400050	statd Buffer Overflow	Attack	Triggers when a large statd request is sent. This could be an attempt to overflow a buffer and gain access to system resources.

Examples

The following example disables signature 6100:

```
hostname(config)# ip audit signature 6100 disable
```

Related Commands

Command	Description
ip audit attack	Sets the default actions for packets that match an attack signature.
ip audit info	Sets the default actions for packets that match an informational signature.
ip audit interface	Assigns an audit policy to an interface.
ip audit name	Creates a named audit policy that identifies the actions to take when a packet matches an attack signature or an informational signature.
show running-config ip audit signature	Shows the configuration for the ip audit signature command.

ip local pool

To configure IP address pools to be used for VPN remote access tunnels, use the **ip local pool** command in global configuration mode. To delete address pools, use the **no** form of this command.

ip local pool *poolname first-address—last-address [mask mask]*

no ip local pool *poolname*

Syntax Description

<i>first-address</i>	Specifies the starting address in the range of IP addresses.
<i>last-address</i>	Specifies the final address in the range of IP addresses.
mask <i>mask</i>	(Optional) Specifies a subnet mask for the pool of addresses.
<i>poolname</i>	Specifies the name of the IP address pool.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must supply the mask value when the IP addresses assigned to VPN clients belong to a non-standard network and the data could be routed incorrectly if you use the default mask. A typical example is when the IP local pool contains 10.10.10.0/255.255.255.0 addresses, since this is a Class A network by default. This could cause some routing issues when the VPN client needs to access different subnets within the 10 network over different interfaces. For example, if a printer, address 10.10.100.1/255.255.255.0 is available via interface 2, but the 10.10.10.0 network is available over the VPN tunnel and therefore interface 1, the VPN client would be confused as to where to route data destined for the printer. Both the 10.10.10.0 and 10.10.100.0 subnets fall under the 10.0.0.0 Class A network so the printer data may be sent over the VPN tunnel.

Examples

The following example configures an IP address pool named firstpool. The starting address is 10.20.30.40 and the ending address is 10.20.30.50. The network mask is 255.255.255.0.

```
hostname(config)# ip local pool firstpool 10.20.30.40-10.20.30.50 mask 255.255.255.0
```

Related Commands	Command	Description
	<code>clear configure ip local pool</code>	Removes all ip local pools.
	<code>show running-config ip local pool</code>	Displays the ip pool configuration. To specify a specific IP address pool, include the name in the command.

ip-comp

To enable LZS IP compression, use the **ip-comp enable** command in group-policy configuration mode. To disable IP compression, use the **ip-comp disable** command.

To remove the **ip-comp** attribute from the running configuration, use the **no** form of this command. This enables inheritance of a value from another group policy.

ip-comp {enable | disable}

no ip-comp

Syntax Description

disable	Disables IP compression.
enable	Enables IP compression.

Defaults

IP compression is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Enabling data compression might speed up data transmission rates for remote dial-in users connecting with modems.



Caution

Data compression increases the memory requirement and CPU utilization for each user session and consequently decreases the overall throughput of the security appliance. For this reason, we recommend that you enable data compression only for remote users connecting with a modem. Design a group policy specific to modem users, and enable compression only for them.

Examples

The following example shows how to enable IP compression for the group policy named “FirstGroup”:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# ip-comp enable
```

ip-phone-bypass

To enable IP Phone Bypass, use the **ip-phone-bypass enable** command in group-policy configuration mode. To disable IP Phone Bypass, use the **ip-phone-bypass disable** command. To remove the IP phone Bypass attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a value for IP Phone Bypass from another group policy.

IP Phone Bypass lets IP phones behind hardware clients connect without undergoing user authentication processes. If enabled, secure unit authentication remains in effect.

ip-phone-bypass {enable | disable}

no ip-phone-bypass

Syntax Description

disable	Disables IP Phone Bypass.
enable	Enables IP Phone Bypass.

Defaults

IP Phone Bypass is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You need to configure IP Phone Bypass only if you have enabled user authentication.

Examples

The following example shows how to enable IP Phone Bypass. for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# ip-phone-bypass enable
```

Related Commands

Command	Description
user-authentication	Requires users behind a hardware client to identify themselves to the security appliance before connecting.

ips

The ASA 5500 series adaptive security appliance supports the AIP SSM, which runs advanced IPS software that provides further security inspection either in inline mode or promiscuous mode. The security appliance diverts packets to the AIP SSM just before the packet exits the egress interface (or before VPN encryption occurs, if configured) and after other firewall policies are applied. For example, packets that are blocked by an access list are not forwarded to the AIP SSM.

To assign traffic from the security appliance to the AIP SSM, use the **ips** command in class configuration mode. To remove this command, use the **no** form of this command.

ips {inline | promiscuous} {fail-close | fail-open}

no ips {inline | promiscuous} {fail-close | fail-open}

Syntax Description

fail-close	Blocks traffic if the AIP SSM fails.
fail-open	Permits traffic if the AIP SSM fails.
inline	Directs packets to the AIP SSM; the packet might be dropped as a result of IPS operation.
promiscuous	Duplicates packets for the AIP SSM; the original packet cannot be dropped by the AIP SSM.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class configuration	•	•	—	—	•

Command History

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines

To configure the **ips** command, you must first configure the **class-map** command, **policy-map** command and the **class** command.

After you configure the security appliance to divert traffic to the AIP SSM, configure the AIP SSM inspection and protection policy, which determines how to inspect traffic and what to do when an intrusion is detected. You can either session to the AIP SSM from the security appliance (the **session** command) or you can connect directly to the AIP SSM using SSH or Telnet on its management interface. Alternatively, you can use ASDM. For more information about configuring the AIP SSM, see *Configuring the Cisco Intrusion Prevention System Sensor Using the Command Line Interface*.

Examples

The following example diverts all IP traffic to the AIP SSM in promiscuous mode, and blocks all IP traffic should the AIP SSM card fail for any reason:

```
hostname(config)# access-list IPS permit ip any any
hostname(config)# class-map my-ips-class
hostname(config-cmap)# match access-list IPS
hostname(config-cmap)# policy-map my-ips-policy
hostname(config-pmap)# class my-ips-class
hostname(config-pmap-c)# ips promiscuous fail-close
hostname(config-pmap-c)# service-policy my-ips-policy global
```

Related Commands

Command	Description
class	Specifies a class map to use for traffic classification.
class-map	Identifies traffic for use in a policy map.
clear configure policy-map	Removes all policy-map configuration, except that if a policy map is in use in a service-policy command, that policy map is not removed.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
show running-config policy-map	Displays all current policy-map configurations.

ipsec-udp

To enable IPsec over UDP, use the **ipsec-udp enable** command in group-policy configuration mode. To disable IPsec over UDP, use the **ipsec-udp disable** command. To remove the IPsec over UDP attribute from the running configuration, use the **no** form of this command. This enables inheritance of a value for IPsec over UDP from another group policy.

IPsec over UDP, sometimes called IPsec through NAT, lets a Cisco VPN Client or hardware client connect via UDP to a security appliance that is running NAT.

ipsec-udp {enable | disable}

no ipsec-udp

Syntax Description

disable	Disables IPsec over UDP.
enable	Enables IPsec over UDP.

Defaults

IPsec over UDP is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

To use IPsec over UDP, you must also configure the **ipsec-udp-port** command.

The Cisco VPN Client must also be configured to use IPsec over UDP (it is configured to use it by default). The VPN 3002 requires no configuration to use IPsec over UDP.

IPsec over UDP is proprietary, it applies only to remote-access connections, and it requires mode configuration, means the security appliance exchanges configuration parameters with the client while negotiating SAs.

Using IPsec over UDP may slightly degrade system performance.

Examples

The following example shows how to set IPsec over UDP for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# ipsec-udp enable
```

Related Commands

Command	Description
ipsec-udp-port	Specifies the port on which the security appliance listens for UDP traffic.

ipsec-udp-port

To set a UDP port number for IPSec over UDP, use the **ipsec-udp-port** command in group-policy configuration mode. To disable the UDP port, use the **no** form of this command. This enables inheritance of a value for the IPSec over UDP port from another group policy.

In IPSec negotiations, the security appliance listens on the configured port and forwards UDP traffic for that port even if other filter rules drop UDP traffic.

ipsec-udp-port *port*

no ipsec-udp-port

Syntax Description

port Identifies the UDP port number using an integer in the range 4001 through 49151.

Defaults

The default port is 10000.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can configure multiple group policies with this feature enabled, and each group policy can use a different port number.

Examples

The following example shows how to set an IPSec UDP port to port 4025 for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# ipsec-udp-port 4025
```

Related Commands

Command	Description
ipsec-udp	Lets a Cisco VPN Client or hardware client connect via UDP to a security appliance that is running NAT.

ip verify reverse-path

To enable Unicast RPF, use the **ip verify reverse-path** command in global configuration mode. To disable this feature, use the **no** form of this command. Unicast RPF guards against IP spoofing (a packet uses an incorrect source IP address to obscure its true source) by ensuring that all packets have a source IP address that matches the correct source interface according to the routing table.

ip verify reverse-path interface *interface_name*

no ip verify reverse-path interface *interface_name*

Syntax Description

interface_name The interface on which you want to enable Unicast RPF.

Defaults

This feature is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Normally, the security appliance only looks at the destination address when determining where to forward the packet. Unicast RPF instructs the security appliance to also look at the source address; this is why it is called Reverse Path Forwarding. For any traffic that you want to allow through the security appliance, the security appliance routing table must include a route back to the source address. See RFC 2267 for more information.

For outside traffic, for example, the security appliance can use the default route to satisfy the Unicast RPF protection. If traffic enters from an outside interface, and the source address is not known to the routing table, the security appliance uses the default route to correctly identify the outside interface as the source interface.

If traffic enters the outside interface from an address that is known to the routing table, but is associated with the inside interface, then the security appliance drops the packet. Similarly, if traffic enters the inside interface from an unknown source address, the security appliance drops the packet because the matching route (the default route) indicates the outside interface.

Unicast RPF is implemented as follows:

- ICMP packets have no session, so each packet is checked.

- UDP and TCP have sessions, so the initial packet requires a reverse route lookup. Subsequent packets arriving during the session are checked using an existing state maintained as part of the session. Non-initial packets are checked to ensure they arrived on the same interface used by the initial packet.

Examples

The following example enables Unicast RPF on the outside interface:

```
hostname(config)# ip verify reverse-path interface outside
```

Related Commands

Command	Description
clear configure ip verify reverse-path	Clears the ip verify reverse-path configuration.
clear ip verify statistics	Clears the Unicast RPF statistics.
show ip verify statistics	Shows the Unicast RPF statistics.
show running-config ip verify reverse-path	Shows the ip verify reverse-path configuration.

ipv6 access-list

To configure an IPv6 access list, use the **ipv6 access-list** command in global configuration mode. To remove an ACE, use the **no** form of this command. Access lists define the traffic that the security appliance allows to pass through or blocks.

```
ipv6 access-list id [line line-num] {deny | permit} {protocol | object-group protocol_obj_grp_id}
{source-ipv6-prefix/prefix-length | any | host source-ipv6-address | object-group
network_obj_grp_id} [operator {port [port] | object-group service_obj_grp_id}]
{destination-ipv6-prefix/prefix-length | any | host destination-ipv6-address | object-group
network_obj_grp_id} [{operator port [port] | object-group service_obj_grp_id}] [log [[level]]
[interval secs] | disable | default]]
```

```
no ipv6 access-list id [line line-num] {deny | permit} {protocol | object-group
protocol_obj_grp_id} {source-ipv6-prefix/prefix-length | any | host source-ipv6-address |
object-group network_obj_grp_id} [operator {port [port] | object-group
service_obj_grp_id}] {destination-ipv6-prefix/prefix-length | any | host
destination-ipv6-address | object-group network_obj_grp_id} [{operator port [port] |
object-group service_obj_grp_id}] [log [[level]] [interval secs] | disable | default]]
```

```
ipv6 access-list id [line line-num] {deny | permit} icmp6 {source-ipv6-prefix/prefix-length | any |
host source-ipv6-address | object-group network_obj_grp_id}
{destination-ipv6-prefix/prefix-length | any | host destination-ipv6-address | object-group
network_obj_grp_id} [icmp_type | object-group icmp_type_obj_grp_id] [log [[level]] [interval
secs] | disable | default]]
```

```
no ipv6 access-list id [line line-num] {deny | permit} icmp6 {source-ipv6-prefix/prefix-length |
any | host source-ipv6-address | object-group network_obj_grp_id}
{destination-ipv6-prefix/prefix-length | any | host destination-ipv6-address | object-group
network_obj_grp_id} [icmp_type | object-group icmp_type_obj_grp_id] [log [[level]] [interval
secs] | disable | default]]
```

Syntax Description

any	An abbreviation for the IPv6 prefix ::/0, indicating any IPv6 address.
default	(Optional) Specifies that a syslog message 106100 is generated for the ACE.
deny	Denies access if the conditions are matched.
<i>destination-ipv6-address</i>	The IPv6 address of the host receiving the traffic.
<i>destination-ipv6-prefix</i>	The IPv6 network address where the traffic is destined.
disable	(Optional) Disables syslog messaging.
host	Indicates that the address refers to a specific host.
icmp6	Specifies that the access rule applies to ICMPv6 traffic passing through the security appliance.

<i>icmp_type</i>	Specifies the ICMP message type being filtered by the access rule. The value can be a valid ICMP type number (from 0 to 255) or one of the following ICMP type literals: • destination-unreachable • packet-too-big • time-exceeded • parameter-problem • echo-request • echo-reply • membership-query • membership-report • membership-reduction • router-renumbering • router-solicitation • router-advertisement • neighbor-solicitation • neighbor-advertisement • neighbor-redirect Omitting the <i>icmp_type</i> argument indicates all ICMP types.
<i>icmp_type_obj_grp_id</i>	(Optional) Specifies the object group ICMP type ID.
<i>id</i>	Name or number of an access list.
interval <i>secs</i>	(Optional) Specifies the time interval at which to generate an 106100 syslog message; valid values are from 1 to 600 seconds. The default interval is 300 seconds. This value is also used as the timeout value for deleting an inactive flow.
<i>level</i>	(Optional) Specifies the syslog level for message 106100; valid values are from 0 to 7. The default level is 6 (informational).
line <i>line-num</i>	(Optional) The line number where the access rule is being inserted into the list. If you do not specify a line number, the ACE is added to the end of the access list.
log	(Optional) Specifies the logging action for the ACE. If you do not specify the log keyword or you specify the log default keyword, then message 106023 is generated when a packet is denied by the ACE. If you specify the log keyword alone or with a level or interval, then message 106100 is generated when a packet is denied by the ACE. Packets that are denied by the implicit deny at the end of an access list are not logged. You must explicitly deny packets with an ACE to enable logging.
<i>network_obj_grp_id</i>	Existing network object group identification.
object-group	(Optional) Specifies an object group.

<i>operator</i>	(Optional) Specifies the operand to compare the source IP address to the destination IP address. The <i>operator</i> compares the source IP address or destination IP address ports. Possible operands include lt for less than, gt for greater than, eq for equal, neq for not equal, and range for an inclusive range. Use the ipv6 access-list command without an operator and port to indicate all ports by default.
permit	Permits access if the conditions are matched.
<i>port</i>	(Optional) Specifies the port that you permit or deny access. When entering the <i>port</i> argument, you can specify the port by either a number in the range of 0 to 65535 or a using literal name if the <i>protocol</i> is tcp or udp. Permitted TCP literal names are aol, bgp, chargen, cifs, citrix-ica, cmd, ctiqbe, daytime, discard, domain, echo, exec, finger, ftp, ftp-data, gopher, h323, hostname, http, https, ident, irc, kerberos, klogin, kshell, ldap, ldaps, login, lotusnotes, lpd, netbios-ssn, nntp, pop2, pop3, pptp, rsh, rtsp, smtp, sqlnet, ssh, sunrpc, tacacs, talk, telnet, uucp, whois, and www. Permitted UDP literal names are biff, bootpc, bootps, cifs, discard, dnsix, domain, echo, http, isakmp, kerberos, mobile-ip, nameserver, netbios-dgm, netbios-ns, ntp, pcanywhere-status, pim-auto-rp, radius, radius-acct, rip, secureid-udp, snmp, snmptrap, sunrpc, syslog, tacacs, talk, tftp, time, who, www, and xmcp.
<i>prefix-length</i>	Indicates how many of the high-order, contiguous bits of the address comprise the IPv6 prefix (the network portion of the IPv6 address).
<i>protocol</i>	Name or number of an IP protocol; valid values are icmp , ip , tcp , or udp , or an integer in the range 1 to 254 representing an IP protocol number.
<i>protocol_obj_grp_id</i>	Existing protocol object group identification.
<i>service_obj_grp_id</i>	(Optional) Specifies the object group.
<i>source-ipv6-address</i>	The IPv6 address of the host sending the traffic.
<i>source-ipv6-prefix</i>	The IPv6 network address of the where the network traffic originated.

Defaults

When the **log** keyword is specified, the default level for syslog message 106100 is 6 (informational). The default logging interval is 300 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **ipv6 access-list** command allows you to specify if an IPv6 address is permitted or denied access to a port or protocol. Each command is called an ACE. One or more ACEs with the same access list name are referred to as an access list. Apply an access list to an interface using the **access-group** command.

The security appliance denies all packets from an outside interface to an inside interface unless you specifically permit access using an access list. All packets are allowed by default from an inside interface to an outside interface unless you specifically deny access.

The **ipv6 access-list** command is similar to the **access-list** command, except that it is IPv6-specific. For additional information about access lists, refer to the **access-list extended** command.

The **ipv6 access-list icmp** command is used to filter ICMPv6 messages that pass through the security appliance. To configure the ICMPv6 traffic that is allowed to originate and terminate at a specific interface, use the **ipv6 icmp** command.

Refer to the **object-group** command for information on how to configure object groups.

Examples

The following example will allow any host using TCP to access the 3001:1::203:A0FF:FED6:162D server:

```
hostname(config)# ipv6 access-list acl_grp permit tcp any host 3001:1::203:A0FF:FED6:162D
```

The following example uses **eq** and a port to deny access to just FTP:

```
hostname(config)# ipv6 access-list acl_out deny tcp any host 3001:1::203:A0FF:FED6:162D eq ftp
hostname(config)# access-group acl_out in interface inside
```

The following example uses **lt** to permit access to all ports less than port 2025, which permits access to the well-known ports (1 to 1024):

```
hostname(config)# ipv6 access-list acl_dmz1 permit tcp any host 3001:1::203:A0FF:FED6:162D lt 1025
hostname(config)# access-group acl_dmz1 in interface dmz1
```

Related Commands

Command	Description
access-group	Assigns an access list to an interface.
ipv6 icmp	Configures access rules for ICMP messages that terminate at an interface of the security appliance.
object-group	Creates an object group (addresses, ICMP types, and services).

ipv6 address

To enable IPv6 and configure the IPv6 addresses on an interface, use the **ipv6 address** command in interface configuration mode. To remove the IPv6 addresses, use the **no** form of this command.

ipv6 address { **autoconfig** | *ipv6-prefix/prefix-length* [**eui-64**] | *ipv6-address* **link-local** }

no ipv6 address { **autoconfig** | *ipv6-prefix/prefix-length* [**eui-64**] | *ipv6-address* **link-local** }

Syntax Description

autoconfig	Enables automatic configuration of IPv6 addresses using stateless autoconfiguration on an interface.
eui-64	(Optional) Specifies an interface ID in the low order 64 bits of the IPv6 address.
<i>ipv6-address</i>	The IPv6 link-local address assigned to the interface.
<i>ipv6-prefix</i>	The IPv6 network address assigned to the interface.
link-local	Specifies that the address is a link-local address.
<i>prefix-length</i>	Indicates how many of the high-order, contiguous bits of the address comprise the IPv6 prefix (the network portion of the IPv6 address).

Defaults

IPv6 is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Configuring an IPv6 address on an interface enables IPv6 on that interface; you do not need to use the **ipv6 enable** command after specifying an IPv6 address.

The **ipv6 address autoconfig** command is used to enable automatic configuration of IPv6 addresses on an interface using stateless autoconfiguration. The addresses are configured based on the prefixes received in Router Advertisement messages. If a link-local address has not been configured, then one is automatically generated for this interface. An error message is displayed if another host is using the link-local address.

The **ipv6 address eui-64** command is used to configure an IPv6 address for an interface. If the optional **eui-64** is specified, the EUI-64 interface ID will be used in the low order 64 bits of the address. If the value specified for the *prefix-length* argument is greater than 64 bits, the prefix bits have precedence over the interface ID. An error message will be displayed if another host is using the specified address.

The Modified EUI-64 format interface ID is derived from the 48-bit link-layer (MAC) address by inserting the hex number FFFE between the upper three bytes (OUI field) and the lower 3 bytes (serial number) of the link layer address. To ensure the chosen address is from a unique Ethernet MAC address, the next-to-lowest order bit in the high-order byte is inverted (universal/local bit) to indicate the uniqueness of the 48-bit address. For example, an interface with a MAC address of 00E0.B601.3B7A would have a 64 bit interface ID of 02E0:B6FF:FE01:3B7A.

The **ipv6 address link-local** command is used to configure an IPv6 link-local address for an interface. The *ipv6-address* specified with this command overrides the link-local address that is automatically generated for the interface. The link-local address is composed of the link-local prefix FE80::/64 and the interface ID in Modified EUI-64 format. An interface with a MAC address of 00E0.B601.3B7A would have a link-local address of FE80::2E0:B6FF:FE01:3B7A. An error message will be displayed if another host is using the specified address.

Examples

The following example assigns 3FFE:C00:0:1::576/64 as the global address for the selected interface:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# ipv6 address 3ffe:c00:0:1::576/64
```

The following example assigns an IPv6 address automatically for the selected interface:

```
hostname(config)# interface gigabitethernet 0/1
hostname(config-if)# ipv6 address autoconfig
```

The following example assigns IPv6 address 3FFE:C00:0:1::/64 to the selected interface and specifies an EUI-64 interface ID in the low order 64 bits of the address:

```
hostname(config)# interface gigabitethernet 0/2
hostname(config-if)# ipv6 address 3FFE:C00:0:1::/64 eui-64
```

The following example assigns FE80::260:3EFF:FE11:6670 as the link-level address for the selected interface:

```
hostname(config)# interface gigabitethernet 0/3
hostname(config-if)# ipv6 address FE80::260:3EFF:FE11:6670 link-local
```

Related Commands

Command	Description
debug ipv6 interface	Displays debug information for IPv6 interfaces.
show ipv6 interface	Displays the status of interfaces configured for IPv6.

ipv6 enable

To enable IPv6 processing on an interface that has not been configured with an explicit IPv6 address, use the **ipv6 enable** command in interface configuration mode. To disable IPv6 processing on an interface that has not been configured with an explicit IPv6 address, use the **no** form of this command.

ipv6 enable

no ipv6 enable

Syntax Description

This command has no arguments or keywords.

Defaults

IPv6 is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **ipv6 enable** command automatically configures an IPv6 link-local unicast address on the interface while also enabling the interface for IPv6 processing.

The **no ipv6 enable** command does not disable IPv6 processing on an interface that is configured with an explicit IPv6 address.

Examples

The following example enables IPv6 processing on the selected interface:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# ipv6 enable
```

Related Commands

Command	Description
ipv6 address	Configures an IPv6 address for an interface and enables IPv6 processing on the interface.
show ipv6 interface	Displays the usability status of interfaces configured for IPv6.

ipv6 icmp

To configure ICMP access rules for an interface, use the **ipv6 icmp** command in global configuration mode. To remove an ICMP access rule, use the **no** form of this command.

ipv6 icmp {**permit** | **deny**} {*ipv6-prefix/prefix-length* | **any** | **host** *ipv6-address*} [*icmp-type*]
if-name

no ipv6 icmp {**permit** | **deny**} {*ipv6-prefix/prefix-length* | **any** | **host** *ipv6-address*} [*icmp-type*]
if-name

Syntax Description	any	Keyword specifying any IPv6 address. An abbreviation for the IPv6 prefix <code>::/0</code> .
	deny	Prevents the specified ICMP traffic on the selected interface.
	host	Indicates that the address refers to a specific host.
	<i>icmp-type</i>	Specifies the ICMP message type being filtered by the access rule. The value can be a valid ICMP type number (from 0 to 255) or one of the following ICMP type literals: • destination-unreachable • packet-too-big • time-exceeded • parameter-problem • echo-request • echo-reply • membership-query • membership-report • membership-reduction • router-renumbering • router-solicitation • router-advertisement • neighbor-solicitation • neighbor-advertisement • neighbor-redirect
	<i>if-name</i>	The name of the interface, as designated by the nameif command, the access rule applies to.
	<i>ipv6-address</i>	The IPv6 address of the host sending ICMPv6 messages to the interface.
	<i>ipv6-prefix</i>	The IPv6 network that is sending ICMPv6 messages to the interface.
	permit	Allows the specified ICMP traffic on the selected interface.
	<i>prefix-length</i>	The length of the IPv6 prefix. This value indicates how many of the high-order, contiguous bits of the address comprise the network portion of the prefix. The slash (/) must precede the prefix length.

Defaults

If no ICMP access rules are defined, all ICMP traffic is permitted.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

ICMP in IPv6 functions the same as ICMP in IPv4. ICMPv6 generates error messages, such as ICMP destination unreachable messages and informational messages like ICMP echo request and reply messages. Additionally, ICMP packets in IPv6 are used in the IPv6 neighbor discovery process and path MTU discovery.

If there are no ICMP rules defined for an interface, all IPv6 ICMP traffic is permitted.

If there are ICMP rules defined for an interface, then the rules are processed in order on a first-match basis followed by an implicit deny all rule. For example, if the first matched rule is a permit rule, the ICMP packet is processed. If the first matched rule is a deny rule, or if the ICMP packet did not match any rule on that interface, then the security appliance discards the ICMP packet and generates a syslog message.

For this reason, the order that you enter the ICMP rules is important. If you enter a rule denying all ICMP traffic from a specific network, and then follow it with a rule permitting ICMP traffic from a particular host on that network, the host rule will never be processed. The ICMP traffic is blocked by the network rule. However, if you enter the host rule first, followed by the network rule, the host ICMP traffic will be allowed, while all other ICMP traffic from that network is blocked.

The **ipv6 icmp** command configures access rules for ICMP traffic that terminates at the security appliance interfaces. To configure access rules for pass-through ICMP traffic, refer to the **ipv6 access-list** command.

Examples

The following example denies all ping requests and permits all Packet Too Big messages (to support Path MTU Discovery) at the outside interface:

```
hostname(config)# ipv6 icmp deny any echo-reply outside
hostname(config)# ipv6 icmp permit any packet-too-big outside
```

The following example permits host 2000:0:0:4::2 or hosts on prefix 2001::/64 to ping the outside interface:

```
hostname(config)# ipv6 icmp permit host 2000:0:0:4::2 echo-reply outside
hostname(config)# ipv6 icmp permit 2001::/64 echo-reply outside
hostname(config)# ipv6 icmp permit any packet-too-big outside
```

Related Commands

Command	Description
ipv6 access-list	Configures access lists.

ipv6 nd dad attempts

To configure the number of consecutive neighbor solicitation messages that are sent on an interface during duplicate address detection, use the **ipv6 nd dad attempts** command in interface configuration mode. To return to the default number of duplicate address detection messages sent, use the **no** form of this command.

ipv6 nd dad attempts *value*

no ipv6 nd dad [*attempts value*]

Syntax Description

<i>value</i>	A number from 0 to 600. Entering 0 disables duplicate address detection on the specified interface. Entering 1 configures a single transmission without follow-up transmissions. The default value is 1 message.

Defaults

The default number of attempts is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Duplicate address detection verifies the uniqueness of new unicast IPv6 addresses before the addresses are assigned to interfaces (the new addresses remain in a tentative state while duplicate address detection is performed). Duplicate address detection uses neighbor solicitation messages to verify the uniqueness of unicast IPv6 addresses. The frequency at which the neighbor solicitation messages are sent is configured using the **ipv6 nd ns-interval** command.

Duplicate address detection is suspended on interfaces that are administratively down. While an interface is administratively down, the unicast IPv6 addresses assigned to the interface are set to a pending state.

Duplicate address detection is automatically restarted on an interface when the interface returns to being administratively up. An interface returning to administratively up restarts duplicate address detection for all of the unicast IPv6 addresses on the interface.

**Note**

While duplicate address detection is performed on the link-local address of an interface, the state for the other IPv6 addresses is still set to tentative. When duplicate address detection is completed on the link-local address, duplicate address detection is performed on the remaining IPv6 addresses.

When duplicate address detection identifies a duplicate address, the state of the address is set to **DUPLICATE** and the address is not used. If the duplicate address is the link-local address of the interface, the processing of IPv6 packets is disabled on the interface and an error message similar to the following is issued:

```
%PIX-4-DUPLICATE: Duplicate address FE80::1 on outside
```

If the duplicate address is a global address of the interface, the address is not used and an error message similar to the following is issued:

```
%PIX-4-DUPLICATE: Duplicate address 3000::4 on outside
```

All configuration commands associated with the duplicate address remain as configured while the state of the address is set to **DUPLICATE**.

If the link-local address for an interface changes, duplicate address detection is performed on the new link-local address and all of the other IPv6 address associated with the interface are regenerated (duplicate address detection is performed only on the new link-local address).

Examples

The following example configures 5 consecutive neighbor solicitation messages to be sent when duplicate address detection is being performed on the tentative unicast IPv6 address of the interface:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# ipv6 nd dad attempts 5
```

The following example disables duplicate address detection on the selected interface:

```
hostname(config)# interface gigabitethernet 0/1
hostname(config-if)# ipv6 nd dad attempts 0
```

Related Commands

Command	Description
ipv6 nd ns-interval	Configures the interval between IPv6 neighbor solicitation transmissions on an interface.
show ipv6 interface	Displays the usability status of interfaces configured for IPv6.

ipv6 nd ns-interval

To configure the interval between IPv6 neighbor solicitation retransmissions on an interface, use the **ipv6 nd ns-interval** command in interface configuration mode. To restore the default value, use the **no** form of this command.

ipv6 nd ns-interval *value*

no ipv6 nd ns-interval [*value*]

Syntax Description

<i>value</i>	The interval between IPv6 neighbor solicitation transmissions, in milliseconds. Valid values range from 1000 to 3600000 milliseconds. The default value is 1000 milliseconds.

Defaults

1000 milliseconds between neighbor solicitation transmissions.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This value will be included in all IPv6 router advertisements sent out this interface.

Examples

The following example configures an IPv6 neighbor solicitation transmission interval of 9000 milliseconds for GigabitEthernet 0/0:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# ipv6 nd ns-interval 9000
```

Related Commands

Command	Description
show ipv6 interface	Displays the usability status of interfaces configured for IPv6.

ipv6 nd prefix

To configure which IPv6 prefixes are included in IPv6 router advertisements, use the **ipv6 nd prefix** command in interface configuration mode. To remove the prefixes, use the **no** form of this command.

ipv6 nd prefix *ipv6-prefix/prefix-length* | **default** [[*valid-lifetime preferred-lifetime*] | [**at** *valid-date preferred-date*] | **infinite** | **no-advertise** | **off-link** | **no-autoconfig**]

no ipv6 nd prefix *ipv6-prefix/prefix-length* | **default** [[*valid-lifetime preferred-lifetime*] | [**at** *valid-date preferred-date*] | **infinite** | **no-advertise** | **off-link** | **no-autoconfig**]

Syntax Description

<i>at valid-date preferred-date</i>	The date and time at which the lifetime and preference expire. The prefix is valid until this specified date and time are reached. Dates are expressed in the form <i>date-valid-expire month-valid-expire hh:mm-valid-expire date-prefer-expire month-prefer-expire hh:mm-prefer-expire</i> .
default	Default values are used.
infinite	(Optional) The valid lifetime does not expire.
<i>ipv6-prefix</i>	The IPv6 network number to include in router advertisements. This argument must be in the form documented in RFC 2373 where the address is specified in hexadecimal using 16-bit values between colons.
no-advertise	(Optional) Indicates to hosts on the local link that the specified prefix is not to be used for IPv6 autoconfiguration.
no-autoconfig	(Optional) Indicates to hosts on the local link that the specified prefix cannot be used for IPv6 autoconfiguration.
off-link	(Optional) Indicates that the specified prefix is not used for on-link determination.
<i>preferred-lifetime</i>	The amount of time (in seconds) that the specified IPv6 prefix is advertised as being preferred. Valid values range from 0 to 4294967295 seconds. The maximum value represents infinity, which can also be specified with infinite . The default is 604800 (7 days).
<i>prefix-length</i>	The length of the IPv6 prefix. This value indicates how many of the high-order, contiguous bits of the address comprise the network portion of the prefix. The slash (/) must precede the prefix length.
<i>valid-lifetime</i>	The amount of time that the specified IPv6 prefix is advertised as being valid. Valid values range from 0 to 4294967295 seconds. The maximum value represents infinity, which can also be specified with infinite . The default is 2592000 (30 days).

Defaults

All prefixes configured on interfaces that originate IPv6 router advertisements are advertised with a valid lifetime of 2592000 seconds (30 days) and a preferred lifetime of 604800 seconds (7 days), and with both the “onlink” and “autoconfig” flags set.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command allows control over the individual parameters per prefix, including whether or not the prefix should be advertised.

By default, prefixes configured as addresses on an interface using the **ipv6 address** command are advertised in router advertisements. If you configure prefixes for advertisement using the **ipv6 nd prefix** command, then only these prefixes are advertised.

The **default** keyword can be used to set default parameters for all prefixes.

A date can be set to specify the expiration of a prefix. The valid and preferred lifetimes are counted down in real time. When the expiration date is reached, the prefix will no longer be advertised.

When onlink is “on” (by default), the specified prefix is assigned to the link. Nodes sending traffic to such addresses that contain the specified prefix consider the destination to be locally reachable on the link.

When autoconfig is “on” (by default), it indicates to hosts on the local link that the specified prefix can be used for IPv6 autoconfiguration.

Examples

The following example includes the IPv6 prefix 2001:200::/35, with a valid lifetime of 1000 seconds and a preferred lifetime of 900 seconds, in router advertisements sent out on the specified interface:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# ipv6 nd prefix 2001:200::/35 1000 900
```

Related Commands

Command	Description
ipv6 address	Configures an IPv6 address and enables IPv6 processing on an interface.
show ipv6 interface	Displays the usability status of interfaces configured for IPv6.

ipv6 nd ra-interval

To configure the interval between IPv6 router advertisement transmissions on an interface, use the **ipv6 nd ra-interval** command in interface configuration mode. To restore the default interval, use the **no** form of this command.

ipv6 nd ra-interval [*msec*] *value*

no ipv6 nd ra-interval [[*msec*] *value*]

Syntax Description

msec	(Optional) indicates that the value provided is in milliseconds. If this keyword is not present, the value provided is seconds.
<i>value</i>	The interval between IPv6 router advertisement transmissions. Valid values range from 3 to 1800 seconds, or from 500 to 1800000 milliseconds if the msec keyword is provided. The default is 200 seconds.

Defaults

200 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The interval between transmissions should be less than or equal to the IPv6 router advertisement lifetime if the security appliance is configured as a default router by using the **ipv6 nd ra-lifetime** command. To prevent synchronization with other IPv6 nodes, randomly adjust the actual value used to within 20 percent of the specified value.

Examples

The following example configures an IPv6 router advertisement interval of 201 seconds for the selected interface:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# ipv6 nd ra-interval 201
```

Related Commands

Command	Description
ipv6 nd ra-lifetime	Configures the lifetime of an IPv6 router advertisement.
show ipv6 interface	Displays the usability status of interfaces configured for IPv6.

ipv6 nd ra-lifetime

To configure the “router lifetime” value in IPv6 router advertisements on an interface, use the **ipv6 nd ra-lifetime** command in interface configuration mode. To restore the default value, use the **no** form of this command.

ipv6 nd ra-lifetime *seconds*

no ipv6 nd ra-lifetime [*seconds*]

Syntax Description

seconds The validity of the security appliance as a default router on this interface. Valid values range from 0 to 9000 seconds. The default is 1800 seconds. 0 indicates that the security appliance should not be considered a default router on the selected interface.

Defaults

1800 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The “router lifetime” value is included in all IPv6 router advertisements sent out the interface. The value indicates the usefulness of the security appliance as a default router on this interface.

Setting the value to a non-zero value to indicates that the security appliance should be considered a default router on this interface. The no-zero value for the “router lifetime” value should not be less than the router advertisement interval.

Setting the value to 0 indicates that the security appliance should not be considered a default router on this interface.

Examples

The following example configures an IPv6 router advertisement lifetime of 1801 seconds for the selected interface:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# ipv6 nd ra-lifetime 1801
```


Related Commands

Command	Description
ipv6 nd ra-interval	Configures the interval between IPv6 router advertisement transmissions on an interface.
show ipv6 interface	Displays the usability status of interfaces configured for IPv6.

ipv6 nd reachable-time

To configure the amount of time that a remote IPv6 node is considered reachable after a reachability confirmation event has occurred, use the **ipv6 nd reachable-time** command in interface configuration mode. To restore the default time, use the **no** form of this command.

ipv6 nd reachable-time *value*

no ipv6 nd reachable-time [*value*]

Syntax Description

<i>value</i>	The amount of time, in milliseconds, that a remote IPv6 node is considered reachable. Valid values range from 0 to 3600000 milliseconds. The default is 0.

Defaults

0 milliseconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The configured time enables detecting unavailable neighbors. Shorter configured times enable detecting unavailable neighbors more quickly; however, shorter times consume more IPv6 network bandwidth and processing resources in all IPv6 network devices. Very short configured times are not recommended in normal IPv6 operation.

Examples

The following example configures an IPv6 reachable time of 1700000 milliseconds for the selected interface:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# ipv6 nd reachable-time 1700000
```

Related Commands

Command	Description
show ipv6 interface	Displays the usability status of interfaces configured for IPv6.

ipv6 nd suppress-ra

To suppress IPv6 router advertisement transmissions on a LAN interface, use the **ipv6 nd suppress-ra** command in interface configuration mode. To reenable the sending of IPv6 router advertisement transmissions on a LAN interface, use the **no** form of this command.

ipv6 nd suppress-ra

no ipv6 nd suppress-ra

Syntax Description

This command has no arguments or keywords.

Defaults

Router advertisements are automatically sent on LAN interfaces if IPv6 unicast routing is enabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **no ipv6 nd suppress-ra** command to enable the sending of IPv6 router advertisement transmissions on non-LAN interface types (for example serial or tunnel interfaces).

Examples

The following example suppresses IPv6 router advertisements on the selected interface:

```
hostname(config)# interface gigabitethernet 0/0
hostname(config-if)# ipv6 nd suppress-ra
```

Related Commands

Command	Description
show ipv6 interface	Displays the usability status of interfaces configured for IPv6.

ipv6 neighbor

To configure a static entry in the IPv6 neighbor discovery cache, use the **ipv6 neighbor** command in global configuration mode. To remove a static entry from the neighbor discovery cache, use the **no** form of this command.

ipv6 neighbor *ipv6_address* *if_name* *mac_address*

no ipv6 neighbor *ipv6_address* *if_name* [*mac_address*]

Syntax Description

<i>if_name</i>	The internal or external interface name designated by the nameif command.
<i>ipv6_address</i>	The IPv6 address that corresponds to the local data-link address.
<i>mac_address</i>	The local data-line (hardware MAC) address.

Defaults

Static entries are not configured in the IPv6 neighbor discovery cache.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **ipv6 neighbor** command is similar to the **arp** command. If an entry for the specified IPv6 address already exists in the neighbor discovery cache—learned through the IPv6 neighbor discovery process—the entry is automatically converted to a static entry. These entries are stored in the configuration when the **copy** command is used to store the configuration.

Use the **show ipv6 neighbor** command to view static entries in the IPv6 neighbor discovery cache.

The **clear ipv6 neighbors** command deletes all entries in the IPv6 neighbor discovery cache except static entries. The **no ipv6 neighbor** command deletes a specified static entry from the neighbor discovery cache; the command does not remove dynamic entries—entries learned from the IPv6 neighbor discovery process—from the cache. Disabling IPv6 on an interface by using the **no ipv6 enable** command deletes all IPv6 neighbor discovery cache entries configured for that interface except static entries (the state of the entry changes to INCOMP [Incomplete]).

Static entries in the IPv6 neighbor discovery cache are not modified by the neighbor discovery process.

Examples

The following example adds a static entry for the an inside host with an IPv6 address of 3001:1::45A and a MAC address of 0002.7D1A.9472 to the neighbor discovery cache:

```
hostname(config)# ipv6 neighbor 3001:1::45A inside 0002.7D1A.9472
```

Related Commands

Command	Description
clear ipv6 neighbors	Deletes all entries in the IPv6 neighbor discovery cache, except static entries.
show ipv6 neighbor	Displays IPv6 neighbor cache information.

ipv6 route

To add an IPv6 route to the IPv6 routing table, use the **ipv6 route** command in global configuration mode. To remove an IPv6 default route, use the **no** form of this command.

ipv6 route *if_name* *ipv6-prefix/prefix-length* *ipv6-address* [*administrative-distance*]

no ipv6 route *if_name* *ipv6-prefix/prefix-length* *ipv6-address* [*administrative-distance*]

Syntax Description

<i>administrative-distance</i>	(Optional) The administrative distance of the route. The default value is 1, which gives static routes precedence over any other type of routes except connected routes.
<i>if_name</i>	The name of the interface the route is being configured for.
<i>ipv6-address</i>	The IPv6 address of the next hop that can be used to reach the specified network.
<i>ipv6-prefix</i>	The IPv6 network that is the destination of the static route. This argument must be in the form documented in RFC 2373 where the address is specified in hexadecimal using 16-bit values between colons.
<i>prefix-length</i>	The length of the IPv6 prefix. This value indicates how many of the high-order, contiguous bits of the address comprise the network portion of the prefix. The slash (/) must precede the prefix length.

Defaults

By default, the *administrative-distance* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **show ipv6 route** command to view the contents of the IPv6 routing table.

Examples

The following example routes packets for network 7fff::0/32 to a networking device on the inside interface at 3FFE:1100:0:CC00::1 with an administrative distance of 110:

```
hostname(config)# ipv6 route inside 7fff::0/32 3FFE:1100:0:CC00::1 110
```

Related Commands

Command	Description
debug ipv6 route	Displays debug messages for IPv6 routing table updates and route cache updates.
show ipv6 route	Displays the current contents of the IPv6 routing table.

isakmp am-disable

To disable inbound aggressive mode connections, use the **isakmp am-disable** command in global configuration mode. To enable inbound aggressive mode connections, use the **no** form of this command.

isakmp am-disable

no isakmp am-disable

Syntax Description This command has no arguments or keywords.

Defaults The default value is enabled.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Command History

Examples The following example, entered in global configuration mode, disables inbound aggressive mode connections:

```
hostname(config)# isakmp am-disable
```

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.
show running-config isakmp	Displays all the active configuration.

Related Commands

isakmp disconnect-notify

To enable disconnect notification to peers, use the **isakmp disconnect-notify** command in global configuration mode. To disable disconnect notification, use the **no** form of this command.

isakmp disconnect-notify

no isakmp disconnect-notify

Syntax Description This command has no arguments or keywords.

Defaults The default value is disabled.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Command History

Examples The following example, entered in global configuration mode, enables disconnect notification to peers:

```
hostname(config)# isakmp disconnect-notify
```

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.
show running-config isakmp	Displays all the active configuration.

Related Commands

isakmp enable

To enable ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance, use the **isakmp enable** command in global configuration mode. To disable ISAKMP on the interface, use the **no** form of this command.

isakmp enable *interface-name*

no isakmp enable *interface-name*

Syntax Description

<i>interface-name</i>	Specifies the name of the interface on which to enable or disable ISAKMP negotiation.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example, entered in global configuration mode, shows how to disable ISAKMP on the inside interface:

```
hostname(config)# no isakmp enable inside
```

Related Commands

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.
show running-config isakmp	Displays all the active configuration.

isakmp identity

To set the Phase 2 ID to be sent to the peer, use the **isakmp identity** command in global configuration mode. To return to the default setting, use the **no** form of this command.

isakmp identity {**address** | **hostname** | **key-id** *key-id-string* | **auto**}

no isakmp identity {**address** | **hostname** | **key-id** *key-id-string* | **auto**}

Syntax Description

address	Uses the IP address of the host exchanging ISAKMP identity information.
auto	Determines ISKMP negotiation by connection type; IP address for preshared key or cert DN for certificate authentication.
hostname	Uses the fully-qualified domain name of the host exchanging ISAKMP identity information (default). This name comprises the hostname and the domain name.
key-id <i>key_id_string</i>	Specifies the string used by the remote peer to look up the preshared key.

Defaults

The default ISAKMP identity is **isakmp identity hostname**.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example, entered in global configuration mode, enables ISAKMP negotiation on the interface for communicating with the IPSec peer, depending on connection type:

```
hostname(config)# isakmp identity auto
```

Related Commands

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.

Command	Description
clear isakmp sa	Clears the IKE runtime SA database.
show running-config isakmp	Displays all the active configuration.

isakmp ipsec-over-tcp

To enable IPsec over TCP, use the **isakmp ipsec-over-tcp** command in global configuration mode. To disable IPsec over TCP, use the **no** form of this command.

isakmp ipsec-over-tcp [**port** *port1...port10*]

no isakmp ipsec-over-tcp [**port** *port1...port10*]

Syntax Description

port *port1...port10* (Optional) Specifies the ports on which the device accepts IPsec over TCP connections. You can list up to 10 ports. Port numbers can be in the range 1-65535. The default port number is 10000.

Defaults

The default value is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

This example, entered in global configuration mode, enables IPsec over TCP on port 45:

```
hostname(config)# isakmp ipsec-over-tcp port 45
```

Related Commands

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.
show running-config isakmp	Displays all the active configuration.

isakmp keepalive

To configure IKE DPD, use the **isakmp keepalive** command in tunnel-group ipsec-attributes configuration mode. In every tunnel group, IKE keepalives are enabled by default with default threshold and retry values. To return the keepalive parameters to enabled with default threshold and retry values, use the **no** form of this command.

isakmp keepalive [**threshold** *seconds*] [**retry** *seconds*] [**disable**]

no isakmp keepalive disable

Syntax Description

disable	Disables IKE keepalive processing, which is enabled by default.
retry <i>seconds</i>	Specifies the interval in seconds between retries after a keepalive response has not been received. The range is 2-10 seconds. The default is 2 seconds.
threshold <i>seconds</i>	Specifies the number of seconds the peer can idle before beginning keepalive monitoring. The range is 10-3600 seconds. The default is 10 seconds for a LAN-to-LAN group, and 300 second for a remote access group.

Defaults

The default for a remote access group is a threshold of 300 seconds and a retry of 2 seconds. For a LAN-to-LAN group, the default is a threshold of 10 seconds and a retry of 2 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group ipsec attributes configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute to IPSec remote-access and IPSec LAN-to-LAN tunnel-group types only.

Examples

The following example entered in config-ipsec configuration mode, configures IKE DPD, establishes a threshold of 15, and specifies a retry interval of 10 for the IPSec LAN-to-LAN tunnel group named 209.165.200.225:

```
hostname(config)# tunnel-group 209.165.200.225 type IPSec_L2L
hostname(config)# tunnel-group 209.165.200.225 ipsec-attributes
hostname(config-ipsec)# isakmp keepalive threshold 15 retry 10
```

Related Commands	Command	Description
	<code>clear configure tunnel-group</code>	Clears all configured tunnel groups.
	<code>show running-config tunnel-group</code>	Shows the tunnel group configuration for all tunnel groups or for a particular tunnel group.
	<code>tunnel-group-map default-group</code>	Associates the certificate map entries created using the <code>crypto ca certificate map</code> command with tunnel groups.

isakmp nat-traversal

To enable NAT traversal globally, check that ISAKMP is enabled (you can enable it with the [isakmp enable](#) command) in global configuration mode and then use the **isakmp nat-traversal** command. If you have enabled NAT traversal, you can disable it with the **no** form of this command.

isakmp nat-traversal *natkeepalive*

no isakmp nat-traversal *natkeepalive*

Syntax Description

<i>natkeepalive</i>	Sets the NAT keep alive interval, from 10 to 3600 seconds. The default is 20 seconds.

Defaults

By default, NAT traversal (**isakmp nat-traversal**) is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Network Address Translation (NAT), including Port Address Translation (PAT), is used in many networks where IPsec is also used, but there are a number of incompatibilities that prevent IPsec packets from successfully traversing NAT devices. NAT traversal enables ESP packets to pass through one or more NAT devices.

The security appliance supports NAT traversal as described by Version 2 and Version 3 of the IETF “UDP Encapsulation of IPsec Packets” draft, available at <http://www.ietf.org/html.charters/ipsec-charter.html>, and NAT traversal is supported for both dynamic and static crypto maps.

This command enables NAT-T globally on the security appliance. To disable in a crypto-map entry, use the [crypto map set nat-t-disable](#) command.

Examples

The following example, entered in global configuration mode, enables ISAKMP and then enables NAT traversal with an interval of 30 seconds:

```
hostname(config)# isakmp enable
hostname(config)# isakmp nat-traversal 30
```


Related Commands

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.
show running-config isakmp	Displays all the active configuration.

isakmp policy authentication

To specify an authentication method within an IKE policy, use the **isakmp policy authentication** command in global configuration mode. IKE policies define a set of parameters for IKE negotiation. To reset the authentication method to the default value, use the **no** form of this command.

isakmp policy *priority* authentication {pre-share | dsa-sig | rsa-sig}

no isakmp policy *priority* authentication

Syntax Description

dsa-sig	Specifies DSA signatures as the authentication method.
pre-share	Specifies preshared keys as the authentication method.
priority	Uniquely identifies the IKE policy and assigns a priority to the policy. Use an integer from 1 to 65,534, with 1 being the highest priority and 65,534 the lowest.
rsa-sig	Specifies RSA signatures as the authentication method. RSA signatures provide non-repudiation for the IKE negotiation. This basically means you can prove to a third party whether you had an IKE negotiation with the peer.

Defaults

The default ISAKMP policy authentication is **pre-share**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting. DSA-Sig was added in 7.0.

Usage Guidelines

If you specify RSA signatures, you must configure the security appliance and its peer to obtain certificates from a certification authority (CA). If you specify preshared keys, you must separately configure these preshared keys within the security appliance and its peer.

Examples

The following example, entered in global configuration mode, shows use of the **isakmp policy authentication** command. This example sets the authentication method of RSA Signatures to be used within the IKE policy with the priority number of 40.

```
hostname(config)# isakmp policy 40 authentication rsa-sig
```

Related Commands

Command	Description
<code>clear configure isakmp</code>	Clears all the ISAKMP configuration.
<code>clear configure isakmp policy</code>	Clears all ISAKMP policy configuration.
<code>clear isakmp sa</code>	Clears the IKE runtime SA database.
<code>show running-config isakmp</code>	Displays all the active configuration.

isakmp policy encryption

To specify the encryption algorithm to use within an IKE policy, use the **isakmp policy encryption** command in global configuration mode. To reset the encryption algorithm to the default value, which is **des**, use the **no** form of this command.

isakmp policy *priority* encryption {aes | aes-192 | aes-256 | des | 3des}

no isakmp policy *priority* encryption {aes | aes-192 | aes-256 | des | 3des}

Syntax Description

3des	Specifies that the Triple DES encryption algorithm be used in the IKE policy.
aes	Specifies that the encryption algorithm to use in the IKE policy is AES with a 128-bit key.
aes-192	Specifies that the encryption algorithm to use in the IKE policy is AES with a 192-bit key.
aes-256	Specifies that the encryption algorithm to use in the IKE policy is AES with a 256-bit key.
des	Specifies that the encryption algorithm to use in the IKE policy is 56-bit DES-CBC.
<i>priority</i>	Uniquely identifies the Internet Key Exchange (IKE) policy and assigns a priority to the policy. Use an integer from 1 to 65,534, with 1 being the highest priority and 65,534 the lowest.

Defaults

The default ISAKMP policy encryption is **3des**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example, entered in global configuration mode, shows use of the **isakmp policy encryption** command; it sets 128-bit key AES encryption as the algorithm to be used within the IKE policy with the priority number of 25.

```
hostname(config)# isakmp policy 25 encryption aes
```

The following example, entered in global configuration mode, sets the 3DES algorithm to be used within the IKE policy with the priority number of 40.

```
hostname(config)# isakmp policy 40 encryption 3des
```

```
hostname(config)#
```

Related Commands

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.
show running-config isakmp	Displays all the active configuration.

isakmp policy group

To specify the Diffie-Hellman group for an IKE policy, use the **isakmp policy group** command in global configuration mode. IKE policies define a set of parameters to use during IKE negotiation. To reset the Diffie-Hellman group identifier to the default value, use the **no** form of this command.

isakmp policy priority group {1 | 2 | 5 | 7}

no isakmp policy priority group

Syntax Description

group 1	Specifies that the 768-bit Diffie-Hellman group be used in the IKE policy. This is the default value.
group 2	Specifies that the 1024-bit Diffie-Hellman group 2 be used in the IKE policy.
group 5	Specifies that the 1536-bit Diffie-Hellman group 5 be used in the IKE policy.
group 7	Specifies that Diffie-Hellman Group 7 be used in the IKE policy. Group 7 generates IPsec SA keys, where the elliptical curve field size is 163 bits.
priority	Uniquely identifies the Internet Key Exchange (IKE) policy and assigns a priority to the policy. Use an integer from 1 to 65,534, with 1 being the highest priority and 65,534 the lowest.

Defaults

The default group policy is group 2.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting. Group 7 was added.

Usage Guidelines

There are four group options: 768-bit (DH Group 1), 1024-bit (DH Group 2), 1536-bit (DH Group 5), and DH Group 7. The 1024-bit and 1536-bit Diffie-Hellman Groups provide stronger security, but require more CPU time to execute.



Note

The Cisco VPN Client Version 3.x or higher requires **isakmp policy** to have DH **group 2** configured. (If you have DH **group 1** configured, the Cisco VPN Client cannot connect.)

AES support is available on security appliances licensed for VPN-3DES only. Due to the large key sizes provided by AES, ISAKMP negotiation should use Diffie-Hellman (DH) **group 5** instead of **group 1** or **group 2**. This is done with the **isakmp policy priority group 5** command.

Examples

The following example, entered in global configuration mode, shows use of the **isakmp policy group** command. This example sets group 2, the 1024-bit Diffie Hellman, to be used within the IKE policy with the priority number of 40.

```
hostname(config)# isakmp policy 40 group 2
```

Related Commands

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.
show running-config isakmp	Displays all the active configuration.

isakmp policy hash

To specify the hash algorithm for an IKE policy, use the **isakmp policy hash** command in global configuration mode. IKE policies define a set of parameters to be used during IKE negotiation.

To reset the hash algorithm to the default value of SHA-1, use the **no** form of this command.

isakmp policy *priority* **hash** {md5 | sha}

no isakmp policy *priority* **hash**

Syntax Description

md5	Specifies that MD5 (HMAC variant) as the hash algorithm be used in the IKE policy.
<i>priority</i>	Uniquely identifies the Internet Key Exchange (IKE) policy and assigns a priority to the policy. Use an integer from 1 to 65,534, with 1 being the highest priority and 65,534 the lowest.
sha	Specifies that SHA-1 (HMAC variant) as the hash algorithm be used in the IKE policy.

Defaults

The default hash algorithm is SHA-1 (HMAC variant).

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

There are two hash algorithm options: SHA-1 and MD5. MD5 has a smaller digest and is considered to be slightly faster than SHA-1.

Examples

The following example, entered in global configuration mode, shows use of the **isakmp policy hash** command. This example specifies that the MD5 hash algorithm be used within the IKE policy, with the priority number of 40.

```
hostname(config)# isakmp policy 40 hash md5
```


Related Commands

Command	Description
<code>clear configure isakmp</code>	Clears all the ISAKMP configuration.
<code>clear configure isakmp policy</code>	Clears all ISAKMP policy configuration.
<code>clear isakmp sa</code>	Clears the IKE runtime SA database.
<code>show running-config isakmp</code>	Displays all the active configuration.

isakmp policy lifetime

To specify the lifetime of an IKE security association before it expires, use the **isakmp policy lifetime** command in global configuration mode. You can specify an infinite lifetime if the peer does not propose a lifetime. Use the **no** form of this command to reset the security association lifetime to the default value of 86,400 seconds (one day).

isakmp policy *priority* **lifetime** *seconds*

no isakmp policy *priority* **lifetime**

Syntax Description

<i>priority</i>	Uniquely identifies the Internet Key Exchange (IKE) policy and assigns a priority to the policy. Use an integer from 1 to 65,534, with 1 being the highest priority and 65,534 the lowest.
<i>seconds</i>	Specifies how many seconds each security association should exist before expiring. To propose a finite lifetime, use an integer from 120 to 2147483647 seconds. Use 0 seconds for infinite lifetime.

Defaults

The default value is 86,400 seconds (one day).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

When IKE begins negotiations, it seeks to agree upon the security parameters for its own session. Then the security association at each peer refers to the agreed-upon parameters. The peers retain the security association until the lifetime expires. Before a security association expires, subsequent IKE negotiations can use it, which can save time when setting up new IPSec security associations. The peers negotiate new security associations before current security associations expire.

With longer lifetimes, the security appliance sets up future IPSec security associations more quickly. Encryption strength is great enough to ensure security without using very fast rekey times, on the order of every few minutes. We recommend that you accept the default.

**Note**

If the IKE security association is set to an infinite lifetime, but the peer proposes a finite lifetime, then the negotiated finite lifetime from the peer is used.

The following example, entered in global configuration mode, shows use of the **isakmp policy lifetime** command. This example sets the lifetime of the IKE security association to 50,400 seconds (14 hours) within the IKE policy with the priority number of 40.

Examples

The following example, entered in global configuration mode, sets the lifetime of the IKE security association to 50,400 seconds (14 hours) within the IKE policy with the priority number of 40.

```
hostname(config)# isakmp policy 40 lifetime 50400
```

The following example, entered in global configuration mode, sets the IKE security association to an infinite lifetime.

```
hostname(config)# isakmp policy 40 lifetime 0
```

Related Commands

clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.
show running-config isakmp	Displays all the active configuration.

isakmp reload-wait

To enable waiting for all active sessions to voluntarily terminate before rebooting the security appliance, use the **isakmp reload-wait** command in global configuration mode. To disable waiting for active sessions to terminate and to proceed with a reboot of the security appliance, use the **no** form of this command.

isakmp reload-wait

no isakmp reload-wait

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Command History

Examples The following example, entered in global configuration mode, tells the security appliance to wait until all active sessions have terminated before rebooting.

```
hostname(config)# isakmp reload-wait
```

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.
show running-config isakmp	Displays all the active configuration.

Related Commands

issuer-name

To identify the DN from the CA certificate to be compared to the rule entry string, use the **issuer-name** command in CA certificate map configuration mode. To remove an issuer-name, use the **no** form of the command.

issuer-name [**attr tag**] {**eq** | **ne** | **co** | **nc**} *string*

no issuer-name [**attr tag**] {**eq** | **ne** | **co** | **nc**} *string*

Syntax Description

attr tag	Indicates that only the specified attribute value from the certificate DN string will be compared to the rule entry string. The tag values are as follows: DNQ = DN qualifier GENQ = Generational qualifier I = Initials GN = Given name N = Name SN = Surname IP = IP address SER = Serial number UNAME = Unstructured name EA = Email address T = Title O = Organization Name L = Locality SP = State/Province C = Country OU = Organizational unit CN = Common name
co	Specifies that the DN string or indicated attribute must be a substring in the rule entry string.
eq	Specifies that the DN string or indicated attribute must match the entire rule string.
nc	Specifies that the DN string or indicated attribute must not be a substring in the rule entry string.
ne	Specifies that the DN string or indicated attribute must not match the entire rule string.
<i>string</i>	Specifies the rule entry information.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters the CA certificate map mode for certificate map 4 and configures the issuer name as O = central:

```
hostname(config)# crypto ca certificate map 4
hostname(ca-certificate-map)# issuer-name attr o eq central
hostname(ca-certificate-map)# exit
```

Related Commands

Command	Description
crypto ca certificate map	Enters CA certificate map mode.
subject-name (crypto ca certificate map)	Identifies the DN from the CA certificate that is to be compared to the rule entry string.

join-failover-group

To assign a context to a failover group, use the **join-failover-group** command in context configuration mode. To restore the default setting, use the **no** form of this command.

join-failover-group *group_num*

no join-failover-group *group_num*

Syntax Description

group_num Specifies the failover group number.

Defaults

Failover group 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Context configuration	•	•	—	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The admin context is always assigned to failover group 1. You can use the **show context detail** command to display the failover group and context association.

Before you can assign a context to a failover group, you must create the failover group with the **failover group** command in the system context. Enter this command on the unit where the context is in the active state. By default, unassigned contexts are members of failover group 1, so if the context had not been previously assigned to a failover group, you should enter this command on the unit that has failover group 1 in the active state.

You must remove all contexts from a failover group, using the **no join-failover-group** command, before you can remove a failover group from the system.

Examples

The following example assigns a context named ctx1 to failover group 2:

```
hostname(config)# context ctx1
hostname(config-context)# join-failover-group 2
hostname(config-context)# exit
```

Related Commands	Command	Description
	context	Enters context configuration mode for the specified context.
	failover group	Defines a failover group for Active/Active failover.
	show context detail	Displays context detail information, including name, class, interfaces, failover group association, and configuration file URL.

kerberos-realm

To specify the realm name for this Kerberos server, use the **kerberos-realm** command in aaa-server host configuration mode. To remove the realm name, use the **no** form of this command:

kerberos-realm *string*

no **kerberos-realm**

Syntax Description

string A case-sensitive, alphanumeric string, up to 64 characters long. Spaces are not permitted in the string.

Note Kerberos realm names use numbers and upper-case letters only. Although the security appliance accepts lower-case letters in the *string* argument, it does not translate lower-case letters to upper-case letters. Be sure to use upper-case letters only.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Aaa-server host configuration	•	•	•	•	—

Command History

Release	Modification
7.0	Introduced in this release.

Usage Guidelines

This command is valid only for Kerberos servers.

The value of the *string* argument should match the output of the Microsoft Windows **set USERDNSDOMAIN** command when it is run on the Windows 2000 Active Directory server for the Kerberos realm. In the following example, EXAMPLE.COM is the Kerberos realm name:

```
C:\>set USERDNSDOMAIN
USERDNSDOMAIN=EXAMPLE.COM
```

The *string* argument must use numbers and upper-case letters only. The **kerberos-realm** command is case sensitive and the security appliance does not translate lower-case letters to upper-case letters.

Examples

The following sequence shows the **kerberos-realm** command to set the kerberos realm to “EXAMPLE.COM” in the context of configuring a AAA server host:

```
hostname(config)# aaa-server svrgrp1 protocol kerberos
```

```

hostname(config-aaa-server-group)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# timeout 9
hostname(config-aaa-server-host)# retry 7
hostname(config-aaa-server-host)# kerberos-realm EXAMPLE.COM
hostname(config-aaa-server-host)# exit
hostname(config)#

```

Related Commands

Command	Description
aaa-server host	Enter AAA server host configuration submode so you can configure AAA server parameters that are host-specific.
clear configure aaa-server	Remove all AAA command statements from the configuration.
show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol

key

To specify the server secret value used to authenticate the NAS to the AAA server, use the **key** command in aaa-server host mode. Aaa-server host configuration mode is accessible from aaa-server protocol configuration mode. To remove the key, use the **no** form of this command. The key (server secret) value authenticates the security appliance to the AAA server.

key *key*

no key

Syntax Description

<i>key</i>	An alphanumeric keyword, up to 127 characters long.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Aaa-server host	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The *key* value is a case-sensitive, alphanumeric keyword of up to 127 characters that is the same value as the key on the TACACS+ server. Any characters entered past 127 are ignored. The key is used between the client and the server for encrypting data between them. The key must be the same on both the client and server systems. The key cannot contain spaces, but other special characters are allowed.

This command is valid only for RADIUS and TACACS+ servers.

The **key** parameter of the **aaa-server** command in earlier PIX Firewall versions is automatically converted to the equivalent **key** command.

Examples

The following example configures a TACACS+ AAA server named “svrgrp1” on host “1.2.3.4”, sets a timeout of 9 seconds, sets a retry-interval of 7 seconds, and configures the key as “myexclusivemumblekey”.

```
hostname(config)# aaa-server svrgrp1 protocol tacacs+
hostname(config-aaa-server-group)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# timeout 9
hostname(config-aaa-server-host)# retry-interval 7
hostname(config-aaa-server-host)# key myexclusivemumblekey
```

Related Commands	Command	Description
	aaa-server host	Enters AAA server host configuration mode so you can configure AAA server parameters that are host-specific.
	clear configure aaa-server	Removes all AAA command statements from the configuration.
	show running-config aaa-server	Displays AAA server configuration.

keypair

To specify the key pair whose public key is to be certified, use the **keypair** command in crypto ca trustpoint configuration mode. To restore the default setting, use the **no** form of the command.

keypair *name*

no keypair

Syntax Description

name Specify the name of the key pair.

Defaults

The default setting is not to include the key pair.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and specifies a key pair to be certified for trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# keypair exchange
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint configuration mode.
crypto key generate dsa	Generates DSA keys.
crypto key generate rsa	Generates RSA keys.
default enrollment	Returns enrollment parameters to their defaults.

kill

To terminate a Telnet session, use the **kill** command in privileged EXEC mode.

```
kill telnet_id
```

Syntax Description

telnet_id Specifies the Telnet session ID.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **kill** command lets you terminate a Telnet session. Use the **who** command to see the Telnet session ID. When you kill a Telnet session, the security appliance lets any active commands terminate and then drops the connection without warning.

Examples

The following example shows how to terminate a Telnet session with the ID “2”. First, the **who** command is entered to display the list of active Telnet sessions. Then the **kill 2** command is entered to terminate the Telnet session with the ID “2”.

```
hostname# who
2: From 10.10.54.0

hostname# kill 2
```

Related Commands

Command	Description
telnet	Configures Telnet access to the security appliance.
who	Displays a list of active Telnet sessions.

l2tp tunnel hello

To specify the interval between hello messages on L2TP over IPSec connections, use the **l2tp tunnel hello** command in global configuration mode. To remove the command from the configuration and set the default, use the no form of the command:

l2tp tunnel hello *interval*

no l2tp tunnel hello *interval*

Syntax Description

interval Interval between hello messages in seconds. The Default is 60 seconds. The range is 10 to 300 seconds.

Defaults

The default is 60 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.2(1)	This command was introduced.

Usage Guidelines

The **l2tp tunnel hello** command enables the security appliance to detect problems with the physical layer of the L2TP connection. The default is 60 secs. If you configure it to a lower value, connections that are experiencing problems are disconnected earlier.

Examples

The following example configures the interval between hello messages to 30 seconds:

```
hostname(config)# l2tp tunnel hello 30
```

Related Commands

Command	Description
show vpn-sessiondbdetail remote filter protocol L2TPOverIPSec	Displays the details of L2TP connections.
vpn-tunnel-protocol l2tp-ipsec	Enables L2TP as a tunneling protocol for a specific tunnel group.

ldap-base-dn

To specify the location in the LDAP hierarchy where the server should begin searching when it receives an authorization request, use the **ldap-base-dn** command in aaa-server host configuration mode. Aaa-server host configuration mode is accessible from aaa-server protocol configuration mode. To remove this specification, thus resetting the search to start at the top of the list, use the **no** form of this command.

ldap-base-dn *string*

no ldap-base-dn

Syntax Description

<i>string</i>	A case-sensitive string of up to 128 characters that specifies the location in the LDAP hierarchy where the server should begin searching when it receives an authorization request; for example, OU=Cisco. Spaces are not permitted in the string, but other special characters are allowed.

Defaults

Start the search at the top of the list.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Aaa-server host	•	•	•	•	—

Command History

Release	Modification
7.0	Pre-existing command, modified for this release

Usage Guidelines

This command is valid only for LDAP servers.

Examples

The following example configures an LDAP AAA server named “srvgrp1” on host “1.2.3.4”, sets a timeout of 9 seconds, sets a retry-interval of 7 seconds, and configures the LDAP base DN as “starthere”.

```
hostname(config)# aaa-server srvgrp1 protocol ldap
hostname(config-aaa-server-group)# aaa-server srvgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# timeout 9
hostname(config-aaa-server-host)# retry 7
hostname(config-aaa-server-host)# ldap-base-dn starthere
hostname(config-aaa-server-host)# exit
```


Related Commands	Command	Description
	aaa-server host	Enters AAA server host configuration mode so you can configure AAA server parameters that are host-specific.
	ldap-scope	Specifies the extent of the search in the LDAP hierarchy that the server should make when it receives an authorization request.
	ldap-naming-attribute	Specifies the Relative Distinguished Name attribute (or attributes) that uniquely identifies an entry on the LDAP server.
	ldap-login-dn	Specifies the name of the directory object that the system should bind as.
	ldap-login-password	Specifies the password for the login DN.

ldap-defaults

To define LDAP default values, use the **ldap-defaults** command in **crl configure** configuration mode. **Crl configure** configuration mode is accessible from **crypto ca trustpoint** configuration mode. These default values are used only when the LDAP server requires them. To specify no LDAP defaults, use the **no** form of this command.

ldap-defaults *server* [*port*]

no ldap-defaults

Syntax Description

<i>port</i>	(Optional) Specifies the LDAP server port. If this parameter is not specified, the security appliance uses the standard LDAP port (389).
<i>server</i>	Specifies the IP address or domain name of the LDAP server. If one exists within the CRL distribution point, it overrides this value.

Defaults

The default setting is not set.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crl configure configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example defines LDAP default values on the default port (389):

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# crl configure
hostname(ca-crl)# ldap-defaults ldapdomain4 8389
```

Related Commands

Command	Description
crl configure	Enters ca-crl configuration mode.
crypto ca trustpoint	Enters trustpoint configuration mode.
protocol ldap	Specifies LDAP as a retrieval method for CRLs

ldap-dn

To pass a X.500 distinguished name and password to an LDAP server that requires authentication for CRL retrieval, use the **ldap-dn** command in **crl configure** configuration mode. **Crl configure** configuration mode is accessible from **crypto ca trustpoint** configuration mode. These parameters are used only when the LDAP server requires them.

To specify no LDAP DN, use the **no** form of this command.

ldap-dn *x.500-name password*

no ldap-dn

Syntax Description

<i>password</i>	Defines a password for this distinguished name. The maximum field length is 128 characters.
<i>x.500-name</i>	Defines the directory path to access this CRL database, for example: cn=crl,ou=certs,o=CAName,c=US . The maximum field length is 128 characters.

Defaults

The default setting is not on.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Crl configure configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example specifies an X.500 name **CN=admin,OU=devtest,O=engineering** and a password **xxzzyy** for **trustpoint central**:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# crl configure
hostname(ca-crl)# ldap-dn cn=admin,ou=devtest,o=engineering xxzzyy
```

Related Commands

Command	Description
crl configure	Enters crl configure configuration mode.

Command	Description
crypto ca trustpoint	Enters ca trustpoint configuration mode.
protocol ldap	Specifies LDAP as a retrieval method for CRLs.

ldap-login-dn

To specify the name of the directory object that the system should bind this as, use the **ldap-login-dn** command in aaa-server host mode. Aaa-server host configuration mode is accessible from aaa-server protocol configuration mode. To remove this specification, use the **no** form of this command.

ldap-login-dn *string*

no ldap-login-dn

Syntax Description

<i>string</i>	A case-sensitive string of up to 128 characters that specifies the name of the directory object in the LDAP hierarchy. Spaces are not permitted in the string, but other special characters are allowed.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Aaa-server host	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is valid only for LDAP servers. The maximum supported string length is 128 characters.

Some LDAP servers, including the Microsoft Active Directory server, require that the security appliance establish a handshake via authenticated binding before they will accept requests for any other LDAP operations. The security appliance identifies itself for authenticated binding by attaching a Login DN field to the user authentication request. The Login DN field describes the authentication characteristics of the security appliance. These characteristics should correspond to those of a user with administrator privileges.

For the *string* variable, enter the name of the directory object for VPN Concentrator authenticated binding, for example: cn=Administrator, cn=users, ou=people, dc=XYZ Corporation, dc=com. For anonymous access, leave this field blank.

Examples

The following example configures an LDAP AAA server named “svrgrp1” on host “1.2.3.4”, sets a timeout of 9 seconds, sets a retry-interval of 7 seconds, and configures the LDAP login DN as “myobjectname”.

```
hostname(config)# aaa-server svrgrp1 protocol ldap
```

```

hostname(config-aaa-server-group)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# timeout 9
hostname(config-aaa-server-host)# retry 7
hostname(config-aaa-server-host)# ldap-login-dn myobjectname
hostname(config-aaa-server-host)# exit

```

Related Commands

Command	Description
aaa-server host	Enters AAA server host configuration mode so you can configure AAA server parameters that are host-specific.
ldap-base-dn	Specifies the location in the LDAP hierarchy where the server should begin searching when it receives an authorization request.
ldap-login-password	Specifies the password for the login DN. This command is valid only for LDAP servers.
ldap-naming-attribute	Specifies the Relative Distinguished Name attribute (or attributes) that uniquely identifies an entry on the LDAP server.
ldap-scope	Specifies the extent of the search in the LDAP hierarchy that the server should make when it receives an authorization request.

ldap-login-password

To specify the login password for the LDAP server, use the **ldap-login-password** command in aaa-server host mode. Aaa-server host configuration mode is accessible from aaa-server protocol configuration mode. To remove this password specification, use the **no** form of this command:

ldap-login-password *string*

no ldap-login-password

Syntax Description

string A case-sensitive, alphanumeric password, up to 64 characters long. The password cannot contain space characters.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Aaa-server host	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is valid only for LDAP servers. The maximum password string length is 64 characters.

Examples

The following example configures an LDAP AAA server named “svrgrp1” on host “1.2.3.4”, sets a timeout of 9 seconds, sets a retry-interval of 7 seconds, and configures the LDAP login password as “obscurepassword”.

```
hostname(config)# aaa-server svrgrp1 protocol ldap
hostname(config)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server)# timeout 9
hostname(config-aaa-server)# retry 7
hostname(config-aaa-server)# ldap-login-password obscurepassword
hostname(config-aaa-server)# exit
hostname(config)#
```

Related Commands

Command	Description
aaa-server host	Enters AAA server host configuration mode so you can configure AAA server parameters that are host-specific.
ldap-base-dn	Specifies the location in the LDAP hierarchy where the server should begin searching when it receives an authorization request.
ldap-login-dn	Specifies the name of the directory object that the system should bind as.
ldap-naming-attribute	Specifies the Relative Distinguished Name attribute (or attributes) that uniquely identifies an entry on the LDAP server.
ldap-scope	Specifies the extent of the search in the LDAP hierarchy that the server should make when it receives an authorization request.

ldap-naming-attribute

To specify the Relative Distinguished Name attribute, use the **ldap-naming-attribute** command in aaa-server host mode. Aaa-server host configuration mode is accessible from aaa-server protocol configuration mode. To remove this specification, use the **no** form of this command:

ldap-naming-attribute *string*

no ldap-naming-attribute

Syntax Description

string The case-sensitive, alphanumeric Relative Distinguished Name attribute consisting of up to 128 characters, that uniquely identifies an entry on the LDAP server. Spaces are not permitted in the string, but other special characters are allowed.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
aaa-server host	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Enter the Relative Distinguished Name attribute that uniquely identifies an entry on the LDAP server. Common naming attributes are Common Name (cn) and User ID (uid).

This command is valid only for LDAP servers. The maximum supported string length is 128 characters.

Examples

The following example configures an LDAP AAA server named “srvgrp1” on host “1.2.3.4”, sets a timeout of 9 seconds, sets a retry-interval of 7 seconds, and configures the LDAP naming attribute as “cn”.

```
hostname(config)# aaa-server srvgrp1 protocol ldap
hostname(config-aaa-server-group)# aaa-server srvgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# timeout 9
hostname(config-aaa-server-host)# retry 7
hostname(config-aaa-server-host)# ldap-naming-attribute cn
hostname(config-aaa-server-host)# exit
```

Related Commands

Command	Description
aaa-server host	Enters AAA server host configuration mode so you can configure AAA server parameters that are host-specific.
ldap-base-dn	Specifies the location in the LDAP hierarchy where the server should begin searching when it receives an authorization request.
ldap-login-dn	Specifies the name of the directory object that the system should bind as.
ldap-login-password	Specifies the password for the login DN. This command is valid only for LDAP servers.
ldap-scope	Specifies the extent of the search in the LDAP hierarchy that the server should make when it receives an authorization request.

ldap-scope

To specify the extent of the search in the LDAP hierarchy that the server should make when it receives an authorization request, use the **ldap-scope** command in aaa-server host configuration mode.

Aaa-server host configuration mode is accessible from aaa-server protocol configuration mode. To remove this specification, use the **no** form of this command:

ldap-scope *scope*

no ldap-scope

Syntax Description

<i>scope</i>	The number of levels in the LDAP hierarchy for the server to search when it receives an authorization request. Valid values are: onelevel—Search only one level beneath the Base DN subtree—Search all levels beneath the Base DN

Defaults

The default value is **onelevel**.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Aaa-server host	•	•	•	•	—

Command History

Release	Modification
7.0	Pre-existing command, modified for this release

Usage Guidelines

Specifying the scope as **onelevel** results in a faster search, because only one level beneath the Base DN is searched. Specifying **subtree** is slower, because all levels beneath the Base DN are searched.

This command is valid only for LDAP servers.

Examples

The following example configures an LDAP AAA server named “svrgrp1” on host “1.2.3.4”, sets a timeout of 9 seconds, sets a retry-interval of 7 seconds, and configures the LDAP scope to include the subtree levels.

```
hostname(config)# aaa-server svrgrp1 protocol ldap
hostname(config-aaa-server-group)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# timeout 9
hostname(config-aaa-server-host)# retry 7
hostname(config-aaa-server-host)# ldap-scope subtree
hostname(config-aaa-server-host)# exit
```

Related Commands	Command	Description
	aaa-server host	Enters AAA server host configuration mode so you can configure AAA server parameters that are host-specific.
	ldap-base-dn	Specifies the location in the LDAP hierarchy where the server should begin searching when it receives an authorization request.
	ldap-login-dn	Specifies the name of the directory object that the system should bind as.
	ldap-login-password	Specifies the password for the login DN. This command is valid only for LDAP servers.
	ldap-naming-attribute	Specifies the Relative Distinguished Name attribute (or attributes) that uniquely identifies an entry on the LDAP server.

leap-bypass

To enable LEAP Bypass, use the **leap-bypass enable** command in group-policy configuration mode. To disable LEAP Bypass, use the **leap-bypass disable** command. To remove the LEAP Bypass attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a value for LEAP Bypass from another group policy.

LEAP Bypass lets LEAP packets from wireless devices behind a VPN hardware client travel across a VPN tunnel prior to user authentication, when enabled. This lets workstations using Cisco wireless access point devices establish LEAP authentication. Then they authenticate again per user authentication.

leap-bypass {enable | disable}

no leap-bypass

Syntax Description

disable	Disables LEAP Bypass.
enable	Enables LEAP Bypass.

Defaults

LEAP Bypass is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This feature does not work as intended if you enable interactive hardware client authentication. For further information, see the *Cisco Security Appliance Command Line Configuration Guide*.



Note

There may be security risks in allowing any unauthenticated traffic to traverse the tunnel.

Examples

The following example shows how to set LEAP Bypass for the group policy named “FirstGroup”:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# leap-bypass enable
```

Related Commands	Command	Description
	secure-unit-authentication	Requires VPN hardware clients to authenticate with a username and password each time the client initiates a tunnel.
	user-authentication	Requires users behind VPN hardware clients to identify themselves to the security appliance before connecting.

log-adj-changes

To configure the router to send a syslog message when an OSPF neighbor goes up or down, use the **log-adj-changes** command in router configuration mode. To turn off this function, use the **no** form of this command.

log-adj-changes [detail]

no log-adj-changes [detail]

Syntax Description

detail	(Optional) Sends a syslog message for each state change, not just when a neighbor goes up or down.

Defaults

This command is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **log-adj-changes** command is enabled by default; it appears in the running configuration unless removed with the **no** form of the command.

Examples

The following example disables the sending of a syslog message when an OSPF neighbor goes up or down:

```
hostname(config)# router ospf 5
hostname(config-router)# no log-adj-changes
```

Related Commands

Command	Description
router ospf	Enters router configuration mode.
show ospf	Displays general information about the OSPF routing processes.

login

To log into privileged EXEC mode using the local user database (see the `username` command) or to change user names, use the **login** command in user EXEC mode.

login

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

From user EXEC mode, you can log in to privileged EXEC mode as any username in the local database using the **login** command. The **login** command is similar to the **enable** command when you have enable authentication turned on (see the **aaa authentication console** command). Unlike enable authentication, the **login** command can only use the local username database, and authentication is always required with this command. You can also change users using the **login** command from any CLI mode.

To allow users to access privileged EXEC mode (and all commands) when they log in, set the user privilege level to 2 (the default) through 15. If you configure local command authorization, then the user can only enter commands assigned to that privilege level or lower. See the **aaa authorization command** for more information.



Caution

If you add users to the local database who can gain access to the CLI and whom you do not want to enter privileged EXEC mode, you should configure command authorization. Without command authorization, users can access privileged EXEC mode (and all commands) at the CLI using their own password if their privilege level is 2 or greater (2 is the default). Alternatively, you can use RADIUS or TACACS+ authentication, or you can set all local users to level 1 so you can control who can use the system enable password to access privileged EXEC mode.

Examples

The following example shows the prompt after you enter the **login** command:

```
hostname> login
```


Username:

Related Commands

Command	Description
aaa authorization command	Enables command authorization for CLI access.
aaa authentication console	Requires authentication for console, Telnet, HTTP, SSH, or enable command access.
logout	Logs out of the CLI.
username	Adds a user to the local database.

logging asdm

To send syslog messages to the ASDM log buffer, use the **logging asdm** command in global configuration mode. To disable logging to the ASDM log buffer, use the **no** form of this command.

logging asdm [*logging_list* | *level*]

no logging asdm [*logging_list* | *level*]

Syntax Description

<i>level</i>	Sets the maximum level for system log messages. For example, if you set the level to 3, then the security appliance generates system log messages for level 3, 2, 1, and 0. You can specify either the number or the name, as follows: • 0 or emergencies—System unusable. • 1 or alerts—Take immediate action. • 2 or critical—Critical condition. • 3 or errors—Error. • 4 or warnings—Warning. • 5 or notifications—Normal but significant condition. • 6 or informational—Information. • 7 or debugging—Debug messages, log FTP commands, and WWW URLs.
<i>logging_list</i>	Specifies the list that identifies the messages to send to the ASDM log buffer. For information about creating lists, see the logging list command.

Defaults

ASDM logging is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Before any messages are sent to the ASDM log buffer, you must enable logging using the **logging enable** command.

When the ASDM log buffer is full, security appliance deletes the oldest message to make room in the buffer for new messages. To control the number of syslog messages retained in the ASDM log buffer, use the **logging asdm-buffer-size** command.

The ASDM log buffer is a different buffer than the log buffer enabled by the **logging buffered** command.

Examples

This example shows how enable logging and send to the ASDM log buffer messages of severity levels 0, 1, and 2. It also shows how to set the ASDM log buffer size to 200 messages.

```
hostname(config)# logging enable
hostname(config)# logging asdm 2
hostname(config)# logging asdm-buffer-size 200
hostname(config)# show logging
Syslog logging: enabled
  Facility: 20
  Timestamp logging: disabled
  Standby logging: disabled
  Deny Conn when Queue Full: disabled
  Console logging: disabled
  Monitor logging: disabled
  Buffer logging: disabled
  Trap logging: disabled
  History logging: disabled
  Device ID: disabled
  Mail logging: disabled
  ASDM logging: level critical, 48 messages logged
```

Related Commands

Command	Description
clear logging asdm	Clears the ASDM log buffer of all messages it contains.
logging asdm-buffer-size	Specifies the number of ASDM messages retained in the ASDM log buffer
logging enable	Enables logging.
logging list	Creates a reusable list of message selection criteria.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging configuration.

logging asdm-buffer-size

To specify the number of syslog messages retained in the ASDM log buffer, use the **logging asdm-buffer-size** command in global configuration mode. To reset the ASDM log buffer to its default size of 100 messages, use the **no** form of this command.

logging asdm-buffer-size *num_of_msgs*

no logging asdm-buffer-size *num_of_msgs*

Syntax Description

<i>num_of_msgs</i>	Specifies the number of syslog messages that the security appliance retains in the ASDM log buffer.

Defaults

The default ASDM syslog buffer size is 100 messages.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

When the ASDM log buffer is full, security appliance deletes the oldest message to make room in the buffer for new messages. To control whether logging to the ASDM log buffer is enabled or to control the kind of syslog messages retained in the ASDM log buffer, use the **logging asdm** command.

The ASDM log buffer is a different buffer than the log buffer enabled by the **logging buffered** command.

Examples

This example shows how enable logging and send to the ASDM log buffer messages of severity levels 0, 1, and 2. It also shows how to set the ASDM log buffer size to 200 messages.

```
hostname(config)# logging enable
hostname(config)# logging asdm 2
hostname(config)# logging asdm-buffer-size 200
hostname(config)# show logging
Syslog logging: enabled
  Facility: 20
  Timestamp logging: disabled
  Standby logging: disabled
  Deny Conn when Queue Full: disabled
  Console logging: disabled
  Monitor logging: disabled
```

```
Buffer logging: disabled
Trap logging: disabled
History logging: disabled
Device ID: disabled
Mail logging: disabled
ASDM logging: level critical, 48 messages logged
```

Related Commands

Command	Description
clear logging asdm	Clears the ASDM log buffer of all messages it contains.
logging asdm	Enables logging to the ASDM log buffer.
logging enable	Enables logging.
show logging	Displays the enabled logging options.
show running-config logging	Displays the currently running logging configuration.

logging buffered

To enable the security appliance to send syslog messages to the log buffer, use the **logging buffered** command in global configuration mode. To disable logging to the log buffer, use the **no** form of this command.

logging buffered [*logging_list* | *level*]

no logging buffered [*logging_list* | *level*]

Syntax Description

<i>level</i>	Sets the maximum level for system log messages. For example, if you set the level to 3, then the security appliance generates system log messages for level 3, 2, 1, and 0. You can specify either the number or the name, as follows: • 0 or emergencies—System unusable. • 1 or alerts—Take immediate action. • 2 or critical—Critical condition. • 3 or errors—Error. • 4 or warnings—Warning. • 5 or notifications—Normal but significant condition. • 6 or informational—Information. • 7 or debugging—Debug messages, log FTP commands, and WWW URLs.
<i>logging_list</i>	Specifies the list that identifies the messages to send to the log buffer. For information about creating lists, see the logging list command.

Defaults

The defaults are as follows:

- Logging to the buffer is disabled.
- Buffer size is 4 KB.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Before any messages are sent to the log buffer, you must enable logging using the **logging enable** command.

New messages append to the end of the buffer. When the buffer fills up, the security appliance clears it and continues adding messages to it. When the log buffer is full, security appliance deletes the oldest message to make room in the buffer for new messages. You can have buffer contents automatically saved each time the contents of the buffer have “wrapped”, meaning that all the messages since the last save have been replaced by new messages. For more information, see the **logging flash-bufferwrap** and **logging ftp-bufferwrap** commands.

At any time, you can save the contents of the buffer to Flash memory. For more information, see the **logging savelog** command.

Syslog messages sent to the buffer can be viewed with the **show logging** command.

Examples

This example configures logging to the buffer for level 0 and level 1 events:

```
hostname(config)# logging buffered alerts
hostname(config)#
```

This example creates a list named notif-list with a maximum logging level of 7 and configures logging to the buffer for syslog messages identified by the notif-list list.

```
hostname(config)# logging list notif-list level 7
hostname(config)# logging buffered notif-list
hostname(config)#
```

Related Commands

Command	Description
clear logging buffer	Clears the log buffer of all syslog messages it contains.
logging buffer-size	Specifies log buffer size.
logging enable	Enables logging.
logging flash-bufferwrap	Writes the log buffer to Flash memory when the log buffer is full.
logging ftp-bufferwrap	Sends the log buffer to an FTP server when the log buffer is full.
logging list	Creates a reusable list of message selection criteria.
logging savelog	Saves the contents of the log buffer to Flash memory.
show logging	Displays the enabled logging options.
show running-config logging	Displays the currently running logging configuration.

logging buffer-size

To specify the size of the log buffer, use the **logging buffer-size** command in global configuration mode. To reset the log buffer to its default size of 4 KB of memory, use the **no** form of this command.

logging buffer-size *bytes*

no logging buffer-size *bytes*

Syntax Description

bytes Sets the amount of memory used for the log buffer, in bytes. For example, if you specify 8192, the security appliance uses 8 KB of memory for the log buffer.

Defaults

The log buffer size is 4 KB of memory.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

To see whether the security appliance is using a log buffer of a size other than the default buffer size, use the **show running-config logging** command. If the **logging buffer-size** command is not shown, then the security appliance uses a log buffer of 4 KB.

For more information about how the security appliance uses the buffer, see the **logging buffered** command.

Examples

This example enables logging, enables the logging buffer, and specifies that the security appliance uses 16 KB of memory for the log buffer:

```
hostname(config)# logging enable
hostname(config)# logging buffered
hostname(config)# logging buffer-size 16384
hostname(config)#
```


Related Commands

Command	Description
clear logging buffer	Clears the log buffer of all syslog messages it contains.
logging buffered	Enables logging to the log buffer.
logging enable	Enables logging.
logging flash-bufferwrap	Writes the log buffer to Flash memory when the log buffer is full.
logging savelog	Saves the contents of the log buffer to Flash memory.
show logging	Displays the enabled logging options.
show running-config logging	Displays the currently running logging configuration.

logging class

To configure for a message class the maximum logging level per logging destination, use the **logging class** command in global configuration mode. To remove a message class logging level configuration, use the **no** form of the command.

logging class *class destination level [destination level . . .]*

no logging class *class*

Syntax Description

<i>class</i>	Specifies the message class whose maximum logging levels per destination you are configuring. For valid values of class, see the “Usage Guidelines” section that follows.
<i>destination</i>	Specifies a logging destination for <i>class</i> . For the destination, the <i>level</i> determines the maximum logging level sent to <i>destination</i> . For valid values of <i>destination</i> , see the “Usage Guidelines” section that follows.
<i>level</i>	Sets the maximum level for system log messages. For example, if you set the level to 3, then the security appliance generates system log messages for level 3, 2, 1, and 0. You can specify either the number or the name, as follows: • 0 or emergencies—System unusable. • 1 or alerts—Take immediate action. • 2 or critical—Critical condition. • 3 or errors—Error. • 4 or warnings—Warning. • 5 or notifications—Normal but significant condition. • 6 or informational—Information. • 7 or debugging—Debug messages, log FTP commands, and WWW URLs.

Defaults

By default, the security appliance does not apply logging levels on a logging destination and message class basis. Instead, each enabled logging destination receives messages for all classes at the logging level determined by the logging list or level specified when you enabled the logging destination.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines

Valid values for *class* include the following:

- **auth**—User authentication
- **bridge**—Transparent firewall
- **ca**—PKI certificate authority
- **config**—Command interface
- **email**—Email proxy
- **ha**—Failover
- **ids**—Intrusion detection system
- **ip**—IP stack
- **np**—Network processor
- **ospf**—OSPF routing
- **rip**—RIP routing
- **session**—User session
- **snmp**—SNMP
- **sys**—System
- **vpn**—IKE and IPSec
- **vpnc**—VPN client
- **vpnfo**—VPN failover
- **vpnlb**—VPN load balancing

Valid logging destinations are as follows:

- **asdm**—To learn about this destination, see the **logging asdm** command.
- **buffered**—To learn about this destination, see the **logging buffered** command.
- **console**—To learn about this destination, see the **logging console** command.
- **history**—To learn about this destination, see the **logging history** command.
- **mail**—To learn about this destination, see the **logging mail** command.
- **monitor**—To learn about this destination, see the **logging monitor** command.
- **trap**—To learn about this destination, see the **logging trap** command.

Examples

This example specifies that, for Failover-related messages, the maximum logging level for the ASDM log buffer is 2 and the maximum logging level for the system log buffer is 7:

```
hostname(config)# logging class ha asdm 2 buffered 7
hostname(config)#
```

Related Commands	Command	Description
	logging enable	Enables logging.
	show logging	Displays the enabled logging options.
	show running-config logging	Displays the logging-related portion of the running configuration.

logging console

To enable the security appliance to display syslog messages in console sessions, use the **logging console** command in global configuration mode. To disable the display of syslog messages in console sessions, use the **no** form of this command.

logging console [*logging_list* | *level*]

no logging console



Note

We recommend that you do not use this command because it may cause many syslog messages to be dropped due to buffer overflow. For more information, see the “Usage Guidelines” section that follows.

Syntax Description

<i>level</i>	Sets the maximum level for system log messages. For example, if you set the level to 3, then the security appliance generates system log messages for level 3, 2, 1, and 0. You can specify either the number or the name, as follows: • 0 or emergencies—System unusable. • 1 or alerts—Take immediate action. • 2 or critical—Critical condition. • 3 or errors—Error. • 4 or warnings—Warning. • 5 or notifications—Normal but significant condition. • 6 or informational—Information. • 7 or debugging—Debug messages, log FTP commands, and WWW URLs.
<i>logging_list</i>	Specifies the list that identifies the messages to send to the console session. For information about creating lists, see the logging list command.

Defaults

The security appliance does not display syslog messages in console sessions by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Before any messages are sent to the console, you must enable logging using the **logging enable** command.

**Caution**

Using the **logging console** command could drastically degrade system performance. Instead, use the **logging buffered** command to start logging and the **show logging** command to see the messages. To make viewing the most current messages easier, use the **clear logging buffer** command to clear the buffer.

Examples

This example shows how to enable syslog messages of levels 0, 1, 2, and 3 to appear in console sessions:

```
hostname(config)# logging enable
hostname(config)# logging console errors
hostname(config)#
```

Related Commands

Command	Description
logging enable	Enables logging.
logging list	Creates a reusable list of message selection criteria.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

logging debug-trace

To redirect debugging messages to logs as syslog message 711001 issued at severity level 7, use the **logging debug-trace** command in global configuration mode. To stop sending debugging messages to logs, use the **no** form of this command.

logging debug-trace

no logging debug-trace

Syntax Description

This command has no arguments or keywords.

Defaults

By default, the security appliance does not include debug output in syslog messages.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Debug messages are generated as severity level 7 messages. They appear in logs with the syslog message number 711001, but do not appear in any monitoring session.

Examples

This example shows how enable logging, send log messages to the system log buffer, redirect debugging output to logs, and turn on debugging disk activity.

```
hostname(config)# logging enable
hostname(config)# logging buffered
hostname(config)# logging debug-trace
hostname(config)# debug disk filesystem
```

An example of a debug message that could appear in the logs follows:

```
%PIX-7-711001: IFS: Read: fd 3, bytes 4096
```

Related Commands

Command	Description
logging enable	Enables logging.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

logging device-id

To configure the security appliance to include a device ID in non-EMBLEM-format syslog messages, use the **logging device-id** command in global configuration mode. To disable the use of a device ID, use the **no** form of this command.

logging device-id { **context-name** | **hostname** | **ipaddress** *interface_name* | **string** *text* }

no logging device-id { **context-name** | **hostname** | **ipaddress** *interface_name* | **string** *text* }

Syntax Description

context-name	Use the name of the current context as the device ID.
hostname	Use the host name of the security appliance as the device ID.
ipaddress <i>interface_name</i>	Use as the device ID the IP address of the interface specified as <i>interface_name</i> . If you use the ipaddress keyword, syslog messages sent to an external server contain the IP address of the interface specified, regardless of which interface the security appliance uses to send the log data to the external server.
string <i>text</i>	Use as the device ID the characters contained in <i>text</i> , which can be up to 16 characters long. You cannot use white space characters or any of the following characters in <i>text</i> : • &—ampersand • '—single quote • "—double quote • <—less than • >—greater than • ?—question mark

Defaults

No default device ID is used in syslog messages.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If you use the **ipaddress** keyword, the device ID becomes the specified security appliance interface IP address, regardless of the interface from which the message is sent. This keyword provides a single, consistent device ID for all messages that are sent from the device.

Examples

This example shows how to configure a host named secappl-1:

```
hostname(config)# logging device-id hostname
hostname(config)# show logging
Syslog logging: disabled
Facility: 20
Timestamp logging: disabled
Standby logging: disabled
Console logging: disabled
Monitor logging: disabled
Buffer logging: level informational, 991 messages logged
Trap logging: disabled
History logging: disabled
Device ID: hostname "secappl-1"
```

In syslog messages, the host name secappl-1 appears at the beginning of messages, such as the following message:

```
secappl-1 %PIX-5-111008: User 'enable_15' executed the 'logging buffer-size 4096' command.
```

Related Commands

Command	Description
logging enable	Enables logging.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

logging emblem

To use the EMBLEM format for syslog messages sent to destinations other than a syslog server, use the **logging emblem** command in global configuration mode. To disable the use of EMBLEM format, use the **no** form of this command.

logging emblem

no logging emblem

Syntax Description

This command has no arguments or keywords.

Defaults

By default, the security appliance does not use EMBLEM format for syslog messages.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was changed to be independent of the logging host command.

Usage Guidelines

The **logging emblem** command lets you to enable EMBLEM-format logging for all logging destinations other than syslog servers. If you also enable the **logging timestamp** keyword, the messages with a time stamp are sent.

To enable EMBLEM-format logging for syslog servers, use the **format emblem** option with the **logging host** command.

Examples

This example shows how to enable logging and enable the use of EMBLEM-format for logging to all logging destinations except syslog servers:

```
hostname(config)# logging enable
hostname(config)# logging emblem
hostname(config)#
```

Related Commands

Command	Description
logging enable	Enables logging.

Command	Description
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

logging enable

To enable logging for all configured output locations, use the **logging enable** command in global configuration mode. To disable logging, use the **no** form of this command.

logging enable

no logging enable

Syntax Description

This command has no arguments or keywords.

Defaults

Logging is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was changed from the logging on command.

Usage Guidelines

The **logging enable** command allows you to enable or disable sending syslog messages to any of the supported logging destinations. You can stop all logging with the **no logging enable** command.

You can enable logging to individual logging destinations with the following commands:

- **logging asdm**
- **logging buffered**
- **logging console**
- **logging history**
- **logging mail**
- **logging monitor**
- **logging trap**

Examples

This example shows how to enable logging. The output of the **show logging** command illustrates how each possible logging destination must be enabled separately.

```
hostname(config)# logging enable
hostname(config)# show logging
Syslog logging: enabled
```

■ logging enable

```

Facility: 20
Timestamp logging: disabled
Standby logging: disabled
Deny Conn when Queue Full: disabled
Console logging: disabled
Monitor logging: disabled
Buffer logging: disabled
Trap logging: disabled
History logging: disabled
Device ID: disabled
Mail logging: disabled
ASDM logging: disabled

```

Related Commands

Command	Description
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

logging facility

To specify the logging facility used for messages sent to syslog servers, use the **logging facility** command in global configuration mode. To reset the logging facility to its default of 20, use the **no** form of this command.

logging facility *facility*

no logging facility

Syntax Description

facility Specifies the syslog facility; valid values are 16 through 23.

Defaults

The default facility is 20 (LOCAL4).

Command Modes

The following table shows the modes in which you can enter the command, with the exceptions noted above in the Syntax Description section:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Syslog servers file messages based on the *facility* number in the message. There are eight possible facilities, 16 (LOCAL0) through 23 (LOCAL7).

Examples

This example shows how to specify that the security appliance specify the logging facility as 16 in syslog messages. The output of the **show logging** command includes the facility being used by the security appliance.

```
hostname(config)# logging facility 16
hostname(config)# show logging
Syslog logging: enabled
  Facility: 16
  Timestamp logging: disabled
  Standby logging: disabled
  Deny Conn when Queue Full: disabled
  Console logging: disabled
  Monitor logging: disabled
  Buffer logging: disabled
  Trap logging: level errors, facility 16, 3607 messages logged
    Logging to infrastructure 10.1.2.3
```

```
History logging: disabled
Device ID: 'inside' interface IP address "10.1.1.1"
Mail logging: disabled
ASDM logging: disabled
```

Related Commands

Command	Description
logging enable	Enables logging.
logging host	Defines a syslog server.
logging trap	Enables logging to syslog servers.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

logging flash-bufferwrap

To enable the security appliance to write the log buffer to Flash memory every time the buffer is full of messages that have never been saved, use the **logging flash-bufferwrap** command in global configuration mode. To disable writing of the log buffer to Flash memory, use the **no** form of this command.

logging flash-bufferwrap

no logging flash-bufferwrap

Syntax Description

This command has no arguments or keywords.

Defaults

The defaults are as follows:

- Logging to the buffer is disabled.
- Writing the log buffer to Flash memory is disabled.
- Buffer size is 4 KB.
- Minimum free Flash memory is 3 MB.
- Maximum Flash memory allocation for buffer logging is 1 MB.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

For the security appliance to write the log buffer to Flash memory, you must enable logging to the buffer; otherwise, the log buffer never has data to be written to Flash memory. To enable logging to the buffer, use the **logging buffered** command.

While the security appliance writes log buffer contents to Flash memory, it continues storing to the log buffer continues any new event messages.

The security appliance creates log files with names that use a default time-stamp format, as follows:

LOG-YYYY-MM-DD-HHMMSS.TXT

where *YYYY* is the year, *MM* is the month, *DD* is the day of the month, and *HHMMSS* is the time in hours, minutes, and seconds.

The availability of Flash memory affects how the security appliance saves syslog messages using the **logging flash-bufferwrap** command. For more information, see the **logging flash-maximum-allocation** and the **logging flash-minimum-free** commands.

Examples

This example shows how enable logging, enable the log buffer, and enable the security appliance to write the log buffer to Flash memory:

```
hostname(config)# logging enable
hostname(config)# logging buffered
hostname(config)# logging flash-bufferwrap
hostname(config)#
```

Related Commands

Command	Description
clear logging buffer	Clears the log buffer of all syslog messages it contains.
copy	Copies a file from one location to another, including to a TFTP or FTP server.
delete	Deletes a file from the disk partition, such as saved log files.
logging buffered	Enables logging to the log buffer.
logging buffer-size	Specifies log buffer size.
logging enable	Enables logging.
logging flash-maximum-allocation	Specifies the maximum amount of Flash memory that can be used for writing log buffer contents.
logging flash-minimum-free	Specifies the minimum amount of Flash memory that must be available for the security appliance to permit writing the log buffer to Flash memory.
show logging	Displays the enabled logging options.

logging flash-maximum-allocation

To specify the maximum amount of Flash memory that the security appliance uses to store log data, use the **logging flash-maximum-allocation** command in global configuration mode. This command determines how much Flash memory is available for the **logging savelog** and **logging flash-bufferwrap** commands. To reset the maximum amount of Flash memory used for this purpose to its default size of 1 MB of Flash memory, use the **no** form of this command.

logging flash-maximum-allocation *kbytes*

no logging flash-maximum-allocation *kbytes*

Syntax Description

kbytes The largest amount of Flash memory, in kilobytes, that the security appliance can use to save log buffer data.

Defaults

The default maximum Flash memory allocation for log data is 1 MB.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If a log file to be saved by **logging savelog** or **logging flash-bufferwrap** causes Flash memory use for log files to exceed the maximum amount specified by the **logging flash-maximum-allocation** command, the security appliance deletes the oldest log files to free sufficient memory for the new log file. If there are no files to delete or if, after all old files are deleted, free memory is too small for the new log file, the security appliance fails to save the new log file.

To see whether the security appliance has a maximum Flash memory allocation of a size different than the default size, use the **show running-config logging** command. If the **logging flash-maximum-allocation** command is not shown, then the security appliance uses a maximum of 1 MB for saved log buffer data. The memory allocated is used for both the **logging savelog** and **logging flash-bufferwrap** commands.

For more information about how the security appliance uses the log buffer, see the **logging buffered** command.

Examples

This example shows how to enable logging, enable the log buffer, enable the security appliance to write the log buffer to Flash memory, with the maximum amount of Flash memory used for writing log files set to approximately 1.2 MB of memory:

```
hostname(config)# logging enable
hostname(config)# logging buffered
hostname(config)# logging flash-bufferwrap
hostname(config)# logging flash-maximum-allocation 1200
hostname(config)#
```

Related Commands

Command	Description
clear logging buffer	Clears the log buffer of all syslog messages it contains.
logging buffered	Enables logging to the log buffer.
logging enable	Enables logging.
logging flash-bufferwrap	Writes the log buffer to Flash memory when the log buffer is full.
logging flash-minimum-free	Specifies the minimum amount of Flash memory that must be available for the security appliance to permit writing the log buffer to Flash memory.
logging savelog	Saves the contents of the log buffer to Flash memory.
show logging	Displays the enabled logging options.
show running-config logging	Displays the currently running logging configuration.

logging flash-minimum-free

To specify the minimum amount of free Flash memory that must exist before the security appliance saves a new log file, use the **logging flash-minimum-free** command in global configuration mode. This command affects how much free Flash memory must exist before the security appliance saves log files created by the **logging savelog** and **logging flash-bufferwrap** commands. To reset the minimum required amount of free Flash memory to its default size of 3 MB, use the **no** form of this command.

logging flash-minimum-free *kbytes*

no logging flash-minimum-free *kbytes*

Syntax Description

kbytes The minimum amount of Flash memory, in kilobytes, that must be available before the security appliance saves a new log file.

Defaults

The default minimum free Flash memory is 3 MB.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The logging flash-minimum-free command specifies how much Flash memory the **logging savelog** and **logging flash-bufferwrap** commands must preserve at all times.

If a log file to be saved by **logging savelog** or **logging flash-bufferwrap** would cause the amount of free Flash memory to fall below the limit specified by the **logging flash-minimum-free** command, the security appliance deletes the oldest log files to ensure that the minimum amount of memory remains free after saving the new log file. If there are no files to delete or if, after all old files are deleted, free memory would still be below the limit, the security appliance fails to save the new log file.

Examples

This example shows how to enable logging, enable the log buffer, enable the security appliance to write the log buffer to Flash memory, and specify that the minimum amount of free Flash memory must be 4000 KB:

```
hostname(config)# logging enable
hostname(config)# logging buffered
hostname(config)# logging flash-bufferwrap
hostname(config)# logging flash-minimum-free 4000
```

```
hostname(config)#
```

Related Commands

Command	Description
clear logging buffer	Clears the log buffer of all syslog messages it contains.
logging buffered	Enables logging to the log buffer.
logging enable	Enables logging.
logging flash-bufferwrap	Writes the log buffer to Flash memory when the log buffer is full.
logging flash-maximum-allocation	Specifies the maximum amount of Flash memory that can be used for writing log buffer contents.
logging saveolog	Saves the contents of the log buffer to Flash memory.
show logging	Displays the enabled logging options.
show running-config logging	Displays the currently running logging configuration.

logging from-address

To specify the sender email address for syslog messages emailed by the security appliance, use the **logging from-address** command in global configuration mode. All emailed syslog messages appear to come from the address you specify. To remove the sender email address, use the **no** form of this command.

logging from-address *from-email-address*

no logging from-address *from-email-address*

Syntax Description

from-email-address Source email address, that is, the email address that syslog emails appear to come from. For example, cdb@example.com.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Sending syslog messages by email is enabled by the **logging mail** command.

The address specified with this command need not correspond to an existing email account.

Examples

To enable logging and set up the security appliance to send syslog messages by email, using the following criteria:

- Send messages that are critical, alerts, or emergencies.
- Send messages using ciscosecurityappliance@example.com as the sender's address.
- Send messages to admin@example.com
- Send messages using SMTP the primary servers pri-smtp-host and secondary server sec-smtp-host.

you would enter the following commands:

```
hostname(config)# logging enable
hostname(config)# logging mail critical
hostname(config)# logging from-address ciscosecurityappliance@example.com
```

```
hostname(config)# logging recipient-address admin@example.com
hostname(config)# smtp-server pri-smtp-host sec-smtp-host
```

Related Commands

Command	Description
logging enable	Enables logging.
logging mail	Enables the security appliance to send syslog messages by email and determines which messages are sent by email.
logging recipient-address	Specifies the email address to which emailed syslog messages are sent.
smtp-server	Configures an SMTP server.
show logging	Displays the enabled logging options.
show running-config logging	Displays the currently running logging configuration.

logging ftp-bufferwrap

To enable the security appliance to send the log buffer to an FTP server every time the buffer is full of messages that have never been saved, use the **logging ftp-bufferwrap** command in global configuration mode. To disable sending the log buffer to an FTP server, use the **no** form of this command.

logging ftp-bufferwrap

no logging ftp-bufferwrap

Syntax Description

This command has no arguments or keywords.

Defaults

The defaults are as follows:

- Logging to the buffer is disabled.
- Sending the log buffer to an FTP server is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

When you enable **logging ftp-bufferwrap**, the security appliance sends log buffer data to the FTP server you specify with the **logging ftp-server** command. While the security appliance sends log data to the FTP server, it continues storing to the log buffer continues any new event messages.

For the security appliance to send log buffer contents to an FTP server, you must enable logging to the buffer; otherwise, the log buffer never has data to be written to Flash memory. To enable logging to the buffer, use the **logging buffered** command.

The security appliance creates log files with names that use a default time-stamp format, as follows:

LOG-YYYY-MM-DD-HHMMSS.TXT

where *YYYY* is the year, *MM* is the month, *DD* is the day of the month, and *HHMMSS* is the time in hours, minutes, and seconds.

Examples

This example shows how enable logging, enable the log buffer, specify an FTP server, and enable the security appliance to write the log buffer to an FTP server. This example specifies an FTP server whose host name is logserver-352. The server can be accessed with the username logsupervisor and password 1luvMy10gs. Log files are to be stored in the /syslogs directory.

```
hostname(config)# logging enable
hostname(config)# logging buffered
hostname(config)# logging ftp-server logserver-352 /syslogs logsupervisor 1luvMy10gs
hostname(config)# logging ftp-bufferwrap
hostname(config)#
```

Related Commands

Command	Description
clear logging buffer	Clears the log buffer of all syslog messages it contains.
logging buffered	Enables logging to the log buffer.
logging buffer-size	Specifies log buffer size.
logging enable	Enables logging.
logging ftp-server	Specifies FTP server parameters for use with the logging ftp-bufferwrap command.
show logging	Displays the enabled logging options.
show running-config logging	Displays the currently running logging configuration.

logging ftp-server

To specify details about the FTP server the security appliance sends log buffer data to when **logging ftp-bufferwrap** is enabled, use the **logging ftp-server** command in global configuration mode. To remove all details about an FTP server, use the **no** form of this command.

logging ftp-server *ftp-server ftp_server path username password*

no logging ftp-server *ftp-server ftp_server path username password*

Syntax Description

<i>ftp-server</i>	External FTP server IP address or host name. Note If you specify a host name, be sure DNS is operating correctly on your network.
<i>path</i>	Directory path on the FTP server where the log buffer data is to be saved. This path is relative to the FTP root directory. For example: /security_appliances/syslogs/appliance107
<i>username</i>	A username that is valid for logging into the FTP server.
<i>password</i>	The password for the username specified.

Defaults

No FTP server is specified by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can only specify one FTP server. If a logging FTP server is already specified, using the **logging ftp-server** command replaces that FTP server configuration with the new one you enter.

The security appliance does not verify the FTP server information you specify. If you misconfigure any of the details, the security appliance fails to send log buffer data to the FTP server.

Examples

This example shows how enable logging, enable the log buffer, specify an FTP server, and enable the security appliance to write the log buffer to an FTP server. This example specifies an FTP server whose host name is logserver-352. The server can be accessed with the username logsupervisor and password 1luvMy10gs. Log files are to be stored in the /syslogs directory.

```

hostname(config)# logging enable
hostname(config)# logging buffered
hostname(config)# logging ftp-server logserver-352 /syslogs logsupervisor 1luvMy10gs
hostname(config)# logging ftp-bufferwrap
hostname(config)#

```

Related Commands

Command	Description
clear logging buffer	Clears the log buffer of all syslog messages it contains.
logging buffered	Enables logging to the log buffer.
logging buffer-size	Specifies log buffer size.
logging enable	Enables logging.
logging ftp-bufferwrap	Sends the log buffer to an FTP server when the log buffer is full.
show logging	Displays the enabled logging options.
show running-config logging	Displays the currently running logging configuration.

logging history

To enable SNMP logging and specify which messages are to be sent to SNMP servers, use the **logging history** command in global configuration mode. To disable SNMP logging, use the **no** form of this command.

logging history [*logging_list* | *level*]

no logging history

Syntax Description

<i>level</i>	Sets the maximum level for system log messages. For example, if you set the level to 3, then the security appliance generates system log messages for level 3, 2, 1, and 0. You can specify either the number or the name, as follows: • 0 or emergencies—System unusable. • 1 or alerts—Take immediate action. • 2 or critical—Critical condition. • 3 or errors—Error. • 4 or warnings—Warning. • 5 or notifications—Normal but significant condition. • 6 or informational—Information. • 7 or debugging—Debug messages, log FTP commands, and WWW URLs.
<i>logging_list</i>	Specifies the list that identifies the messages to send to the SNMP server. For information about creating lists, see the logging list command.

Defaults

The security appliance does not log to SNMP servers by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **logging history** command allows you to enable logging to an SNMP server and to set the SNMP message level or event list.

Examples

This example shows how to enable SNMP logging and specify that messages of levels 0, 1, 2, and 3 are sent to the SNMP server configured:

```
hostname(config)# logging enable
hostname(config)# snmp-server host infrastructure 10.2.3.7 trap community gam327
hostname(config)# snmp-server enable traps syslog
hostname(config)# logging history errors
hostname(config)#
```

Related Commands

Command	Description
logging enable	Enables logging.
logging list	Creates a reusable list of message selection criteria.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.
snmp-server	Specifies SNMP server details.

logging host

To define a syslog server, use the **logging host** command in global configuration mode. To remove a syslog server definition, use the **no** form of this command.

logging host *interface_name* *syslog_ip* [**tcp**/*port* | **udp**/*port*] [**format emblem**]

logging host *interface_name* *syslog_ip*

Syntax Description

format emblem	(Optional) Enables EMBLEM format logging for the syslog server.
<i>interface_name</i>	Interface on which the syslog server resides.
<i>syslog_ip</i>	The IP address of the syslog server.
tcp	Specifies that the security appliance should use TCP to send messages to the syslog server.
udp	Specifies that the security appliance should use TCP to send messages to the syslog server.
<i>port</i>	The port that the syslog server listens to for messages. Valid port values are 1025 through 65535, for either protocol.

Defaults

The defaults are as follows:

- The default port numbers are as follows:
 - UDP port is 514
 - TCP port is 1470
- The default protocol is UDP.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **logging host ip_address format emblem** command allows you to enable EMBLEM-format logging for each syslog server. EMBLEM-format logging is available for UDP syslog messages only. If you enable EMBLEM-format logging for a particular syslog host, then the messages are sent to that host. If you also enable the **logging timestamp** keyword, the messages with a time stamp are sent.

You can use multiple **logging host** commands to specify additional servers that would all receive the syslog messages. However, a server can only be specified to receive either UDP or TCP, not both.

You can display only the *port* and *protocol* values that you previously entered by using the **show running-config logging** command and finding the command in the listing—the TCP protocol is listed as 6 and the UDP protocol is listed as 17. TCP ports work only with the security appliance syslog server. The *port* must be the same port on which the syslog server listens.

Examples

This example shows how to send syslog messages of levels 0, 1, 2, and 3 to a syslog server that resides on the inside interface and uses the default protocol and port number.

```
hostname(config)# logging enable
hostname(config)# logging host inside 10.2.2.3
hostname(config)# logging trap errors
hostname(config)#
```

Related Commands

Command	Description
logging enable	Enables logging.
logging trap	Enables logging to syslog servers.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

logging list

To create a logging list to use in other commands to specify messages by various criteria (logging level, event class, and message IDs) use the **logging list** command in global configuration mode. To remove the list, use the **no** form of this command.

logging list *name* {**level** *level* [**class** *event_class*] | **message** *start_id*[-*end_id*]}

no logging list *name*

Syntax Description

class <i>event_class</i>	(Optional) Sets the class of events for syslog messages. For the level specified, only syslog messages of the class specified are identified by the command. See “Usage Guidelines” for a list of classes.
level <i>level</i>	Sets the maximum level for system log messages. For example, if you set the level to 3, then the security appliance generates system log messages for level 3, 2, 1, and 0. You can specify either the number or the name, as follows: • 0 or emergencies—System unusable. • 1 or alerts—Take immediate action. • 2 or critical—Critical condition. • 3 or errors—Error. • 4 or warnings—Warning. • 5 or notifications—Normal but significant condition. • 6 or informational—Information. • 7 or debugging—Debug messages, log FTP commands, and WWW URLs.
message <i>start_id</i> [- <i>end_id</i>]	Specified a message ID or range of IDs. To lookup the default level of a message, use the show logging command or see the <i>Cisco Security Appliance Logging Configuration and System Log Messages</i> guide.
<i>name</i>	Sets the logging list name.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	Support for this command was introduced.

Usage Guidelines

Logging commands that can use lists are the following:

- **logging asdm**
- **logging buffered**
- **logging console**
- **logging history**
- **logging mail**
- **logging monitor**
- **logging trap**

Possible values for the *event_class* include the following:

- **auth**—User authentication
- **bridge**—Transparent firewall
- **ca**—PKI certificate authority
- **config**—Command interface
- **email**—Email proxy
- **ha**—Failover
- **ids**—Intrusion detection system
- **ip**—IP stack
- **np**—Network processor
- **ospf**—OSPF routing
- **rip**—RIP routing
- **session**—User session
- **snmp**—SNMP
- **sys**—System
- **vpn**—IKE and IPSec
- **vpnc**—VPN client
- **vpnfo**—VPN failover
- **vpnlb**—VPN load balancing

Examples

This example shows how to use the logging list command:

```
hostname(config)# logging list my-list 100100-100110
hostname(config)# logging list my-list level critical
hostname(config)# logging list my-list level warning class vpn
hostname(config)# logging buffered my-list
```

The preceding example states that syslog messages that match the criteria specified will be sent to the logging buffer. The criteria specified in this example are:

1. Syslog message IDs that fall in the range of 100100 to 100110
2. All syslog messages with critical level or higher (emergency, alert, or critical)

3. All VPN class syslog messages with warning level or higher (emergency, alert, critical, error, or warning)

If a syslog message satisfies any one of these conditions, it is logged to the buffer.

**Note**

When you design list criteria, criteria can specify overlapping sets of messages. Syslog messages matching more than one criteria are logged normally.

Related Commands

Command	Description
logging enable	Enables logging.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

logging mail

To enable the security appliance to send syslog messages by email and to determine which messages are sent by email, use the **logging mail** command in global configuration mode. To disable emailing syslog messages, use the **no** form of this command.

logging mail [*logging_list* | *level*]

no logging mail [*logging_list* | *level*]

Syntax Description

<i>level</i>	Sets the maximum level for system log messages. For example, if you set the level to 3, then the security appliance generates system log messages for level 3, 2, 1, and 0. You can specify either the number or the name, as follows: • 0 or emergencies—System unusable. • 1 or alerts—Take immediate action. • 2 or critical—Critical condition. • 3 or errors—Error. • 4 or warnings—Warning. • 5 or notifications—Normal but significant condition. • 6 or informational—Information. • 7 or debugging—Debug messages, log FTP commands, and WWW URLs.
<i>logging_list</i>	Specifies the list that identifies the messages to send to the email recipient. For information about creating lists, see the logging list command.

Defaults

Logging to email is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Emailed syslog messages appear in the subject line of the emails sent.

Examples

To set up the security appliance to send syslog messages by email, using the following criteria:

- Send messages that are critical, alerts, or emergencies.
- Send messages using ciscosecurityappliance@example.com as the sender's address.
- Send messages to admin@example.com
- Send messages using SMTP the primary servers pri-smtp-host and secondary server sec-smtp-host.

you would enter the following commands:

```
hostname(config)# logging mail critical
hostname(config)# logging from-address ciscosecurityappliance@example.com
hostname(config)# logging recipient-address admin@example.com
hostname(config)# smtp-server pri-smtp-host sec-smtp-host
```

Related Commands

Command	Description
logging enable	Enables logging.
logging from-address	Specifies the email address from which emailed syslog messages appear to come.
logging list	Creates a reusable list of message selection criteria.
logging recipient-address	Specifies the email address to which emailed syslog messages are sent.
smtp-server	Configures an SMTP server.
show logging	Displays the enabled logging options.
show running-config logging	Displays the currently running logging configuration.

logging message

To specify the logging level of a syslog message, use the **logging message** command with the **level** keyword in global configuration mode. To reset the logging level of a message to its default level, use the **no** form of this command. To prevent the security appliance from generating a particular syslog message, use the **no** form of the **logging message** command (without the **level** keyword) in global configuration mode. To let the security appliance generate a particular syslog message, use the **logging message** command (without the **level** keyword). These two purposes of the **logging message** command can be used in parallel. See the “Examples” section that follows.

logging message *syslog_id* **level** *level*

no logging message *syslog_id* **level** *level*

logging message *syslog_id*

no logging message *syslog_id*

Syntax Description

level <i>level</i>	Sets the maximum level for system log messages. For example, if you set the level to 3, then the security appliance generates system log messages for level 3, 2, 1, and 0. You can specify either the number or the name, as follows: • 0 or emergencies—System unusable. • 1 or alerts—Take immediate action. • 2 or critical—Critical condition. • 3 or errors—Error. • 4 or warnings—Warning. • 5 or notifications—Normal but significant condition. • 6 or informational—Information. • 7 or debugging—Debug messages, log FTP commands, and WWW URLs.
<i>syslog_id</i>	The ID of the syslog message that you want to enable or disable or whose severity level you want to modify. To lookup the default level of a message, use the show logging command or see the <i>Cisco Security Appliance Logging Configuration and System Log Messages</i> guide.

Defaults

By default, all syslog messages are enabled and the severity levels of all messages are set to their default levels.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

You can use the **logging message** command for two purposes:

- To control whether a message is enabled or disabled.
- To control the severity level of a message.

You can use the **show logging** command to determine the level currently assigned to a message and whether the message is enabled.

Examples

The series of commands in the following example illustrates the use of the **logging message** command to control both whether a message is enabled and the severity level of the messages

```
hostname(config)# show logging message 403503
syslog 403503: default-level errors (enabled)

hostname(config)# logging message 403503 level 1
hostname(config)# show logging message 403503
syslog 403503: default-level errors, current-level alerts (enabled)

hostname(config)# no logging message 403503
hostname(config)# show logging message 403503
syslog 403503: default-level errors, current-level alerts (disabled)

hostname(config)# logging message 403503
hostname(config)# show logging message 403503
syslog 403503: default-level errors, current-level alerts (enabled)

hostname(config)# no logging message 403503 level 3
hostname(config)# show logging message 403503
syslog 403503: default-level errors (enabled)
```

Related Commands

Command	Description
clear configure logging	Clears all logging configuration or message configuration only.
logging enable	Enables logging.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

logging monitor

To enable the security appliance to display syslog messages in SSH and Telnet sessions, use the **logging monitor** command in global configuration mode. To disable the display of syslog messages in SSH and Telnet sessions, use the **no** form of this command.

logging monitor [*logging_list* | *level*]

no logging monitor

Syntax Description

<i>level</i>	Sets the maximum level for system log messages. For example, if you set the level to 3, then the security appliance generates system log messages for level 3, 2, 1, and 0. You can specify either the number or the name, as follows: • 0 or emergencies—System unusable. • 1 or alerts—Take immediate action. • 2 or critical—Critical condition. • 3 or errors—Error. • 4 or warnings—Warning. • 5 or notifications—Normal but significant condition. • 6 or informational—Information. • 7 or debugging—Debug messages, log FTP commands, and WWW URLs.
<i>logging_list</i>	Specifies the list that identifies the messages to send to the SSH or Telnet session. For information about creating lists, see the logging list command.

Defaults

The security appliance does not display syslog messages in SSH and Telnet sessions by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **logging monitor** command enables syslog messages for all sessions in the current context; however, in each session, the **terminal** command controls whether syslog messages appear in that session.

Examples

This example shows how to enable the display of syslog messages in console sessions. The use of the **errors** keyword indicates that messages of levels 0, 1, 2, and 3 should be shown in SSH and Telnet sessions. The **terminal** command enables the messages to appear in the current session.

```
hostname(config)# logging enable
hostname(config)# logging monitor errors
hostname(config)# terminal monitor
hostname(config)#
```

Related Commands

Command	Description
logging enable	Enables logging.
logging list	Creates a reusable list of message selection criteria.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.
terminal	Sets terminal line parameters.

logging permit-hostdown

To make the status of a TCP-based syslog server irrelevant to new user sessions, use the **logging permit-hostdown** command in global configuration mode. To cause the security appliance to deny new user sessions when a TCP-based syslog server is unavailable, use the **no** form of this command.

logging permit-hostdown

no logging permit-hostdown

Syntax Description

This command has no arguments or keywords.

Defaults

By default, if you have enabled logging to a syslog server that uses a TCP connection, the security appliance does not allow new network access sessions when the syslog server is unavailable for any reason.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If you are using TCP as the logging transport protocol for sending messages to a syslog server, the security appliance denies new network access sessions as a security measure if the security appliance is unable to reach the syslog server. You can use the **logging permit-hostdown** command to remove this restriction.

Examples

The following example makes the status of TCP-based syslog servers irrelevant to whether the security appliance permits new sessions. When the **show running-config logging** command includes in its output the **show running-config logging** command, the status of TCP-based syslog servers is irrelevant to new network access sessions.

```
hostname(config)# logging permit-hostdown
hostname(config)# show running-config logging
logging enable
logging trap errors
logging host infrastructure 10.1.2.3 6/1470
logging permit-hostdown
hostname(config)#
```

Related Commands	Command	Description
	logging enable	Enables logging.
	logging host	Defines a syslog server.
	logging trap	Enables logging to syslog servers.
	show logging	Displays the enabled logging options.
	show running-config logging	Displays the logging-related portion of the running configuration.

logging queue

To specify how many syslog messages the security appliance may hold in its syslog queue prior to processing them according to logging configuration, use the **logging queue** command in global configuration mode. To reset the logging queue size to the default of 512 messages, use the **no** form of this command.

logging queue *queue_size*

no logging queue *queue_size*

Syntax Description

<i>queue_size</i>	The number of syslog messages permitted in the queue used for storing syslog messages prior to processing them. Valid values are from 0 to 8192 messages. Zero means that the queue is limited only by block memory availability.

Defaults

The default queue size is 512 messages.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

When traffic is so heavy that the queue fills up, the security appliance may discard messages.

Examples

This example shows how to display the output of the **logging queue** and **show logging queue** commands:

```
hostname(config)# logging queue 0
hostname(config)# show logging queue
Logging Queue length limit : Unlimited
Current 5 msg on queue, 3513 msgs most on queue, 1 msg discard.
```

In this example, the **logging queue** command is set to 0, which means that the queue can hold as many messages as block memory availability allows. The syslog messages in the queue are processed by the security appliance in the manner dictated by logging configuration, such as sending syslog messages to mail recipients, saving them to Flash memory, and so forth.

The output of this example **show logging queue** command shows that 5 messages are queued, 3513 messages was the largest number of messages in the queue at one time since the security appliance was last booted, and that 1 message was discarded. Even though the queue was set for unlimited, the messages was discarded because no block memory was available to add the message to the queue.

Related Commands

Command	Description
logging enable	Enables logging.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

logging rate-limit

To limit the rate at which system log messages are generated, use the **logging rate-limit** command. To disable rate limiting, use the **no** form of this command.

logging rate-limit { **unlimited** | { *num* [*interval*] } } **message** *syslog_id* | **level** *severity_level*

[**no**] **logging rate-limit** [**unlimited** | { *num* [*interval*] } } **message** *syslog_id*] **level** *severity_level*

Syntax Description

unlimited	Disables rate limiting. This means that there is no limit on the logging rate.
<i>num</i>	Number of system messages that can be generated during the specified time interval. The valid range of values for <i>num</i> is 1 through 2147483647.
<i>interval</i>	(Optional) Time interval (in seconds) to use for measuring the rate at which messages are generated. The valid range of values for <i>interval</i> is 1 through 2147483647.
message	Suppresses reporting of this system log message.
<i>syslog_id</i>	ID of the system log message to be suppressed. The valid range of values for <i>syslog_id</i> is 100000-999999.
level <i>severity_level</i>	Sets the severity level above which the security appliance suppresses messages. The valid range for <i>severity_level</i> is 1 through 7.

Defaults

The default setting for *interval* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0(4)	This command was introduced.

Usage Guidelines

The system message severity levels are as follows:

- 0—System Unusable
- 1—Take Immediate Action
- 2—Critical Condition
- 3—Error Message
- 4—Warning Message

- 5—Normal but significant condition
- 6—Informational
- 7—Debug Message

Examples

The following example shows how to limit the rate of system log message generation:

```
hostname(config)# logging rate-limit 5 message 106023
hostname(config)# logging rate-limit 10 60 level 7
```

Related Commands

Command	Description
clear configure logging rate-limit	Resets the logging rate-limit setting to its default.
show logging	Shows the messages currently in the internal buffer or to shows logging configuration settings
show running-config logging rate-limit	Shows the current logging rate-limit setting.

logging recipient-address

To specify the receiving email address for syslog messages emailed by the security appliance, use the **logging recipient-address** command in global configuration mode. To remove the receiving email address, use the **no** form of this command. You can configure up to 5 recipient addresses. If you want, each recipient address can have a different message level than that specified by the **logging mail** command.

logging recipient-address *address* [**level** *level*]

no logging recipient-address *address* [**level** *level*]

Syntax Description

<i>address</i>	Specifies recipient email address when sending syslog messages by email.
level	Indicates that a logging level follows.
<i>level</i>	Sets the maximum level for system log messages. For example, if you set the level to 3, then the security appliance generates system log messages for level 3, 2, 1, and 0. You can specify either the number or the name, as follows: • 0 or emergencies—System unusable. • 1 or alerts—Take immediate action. • 2 or critical—Critical condition. • 3 or errors—Error. • 4 or warnings—Warning. • 5 or notifications—Normal but significant condition. • 6 or informational—Information. • 7 or debugging—Debug messages, log FTP commands, and WWW URLs. Note We do not recommend using a level greater than 3 with the logging recipient-address command. Higher logging levels are likely to cause dropped syslog messages due to buffer overflow. The message level specified by a logging recipient-address command overrides the message level specified by the logging mail command. For example, if a logging recipient-address command specifies a level of 7 but the logging mail command specifies a level of 3, the security appliance sends all messages to the recipient, including those of levels 4, 5, 6, and 7.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Sending syslog messages by email is enabled by the **logging mail** command.

You can configure up to 5 **logging recipient-address** commands. Each command can have a different logging level than the others. This is useful when you want more urgent messages to go to a larger number of recipients than less urgent messages are sent to.

Examples

To set up the security appliance to send syslog messages by email, using the following criteria:

- Send messages that are critical, alerts, or emergencies.
- Send messages using ciscosecurityappliance@example.com as the sender's address.
- Send messages to admin@example.com
- Send messages using SMTP the primary servers pri-smtp-host and secondary server sec-smtp-host.

you would enter the following commands:

```
hostname(config)# logging mail critical
hostname(config)# logging from-address ciscosecurityappliance@example.com
hostname(config)# logging recipient-address admin@example.com
hostname(config)# smtp-server pri-smtp-host sec-smtp-host
```

Related Commands

Command	Description
logging enable	Enables logging.
logging from-address	Specifies the email address from which emailed syslog messages appear to come.
logging mail	Enables the security appliance to send syslog messages by email and determines which messages are sent by email.
smtp-server	Configures an SMTP server.
show logging	Displays the enabled logging options.
show running-config logging	Displays the currently running logging configuration.

logging savelog

To save the log buffer to Flash memory, use the **logging savelog** command in privileged EXEC mode.

logging savelog [*savefile*]

Syntax Description

savefile

(Optional) Saved Flash memory file name. If you do not specify the file name, the security appliance, saves the file using a default time-stamp format, as follows:

LOG-YYYY-MM-DD-HHMMSS.TXT

where *YYYY* is the year, *MM* is the month, *DD* is the day of the month, and *HHMMSS* is the time in hours, minutes, and seconds.

Defaults

The defaults are as follows:

- Buffer size is 4 KB.
- Minimum free Flash memory is 3 MB.
- Maximum Flash memory allocation for buffer logging is 1 MB.
- The default log file name is described in the preceding table.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Before you can save the log buffer to Flash memory, you must enable logging to the buffer; otherwise, the log buffer never has data to be saved to Flash memory. To enable logging to the buffer, use the **logging buffered** command.



Note

The **logging savelog** command does not clear the buffer. To clear the buffer, use the **clear logging buffer** command.

Examples

This example enables logging and the log buffer, exits global configuration mode, and saves the log buffer to Flash memory, using the file name latest-logfile.txt:

```
hostname(config)# logging enable
hostname(config)# logging buffered
hostname(config)# exit
hostname# logging savelog latest-logfile.txt
hostname#
```

Related Commands

Command	Description
clear logging buffer	Clears the log buffer of all syslog messages it contains.
copy	Copies a file from one location to another, including to a TFTP or FTP server.
delete	Deletes a file from the disk partition, such as saved log files.
logging buffered	Enables logging to the log buffer.
logging enable	Enables logging.
show logging	Displays the enabled logging options.

logging standby

To enable the failover standby security appliance to send the syslog messages of this security appliance to logging destinations, use the **logging standby** command in global configuration mode. To disable syslog and SNMP logging, use the **no** form of this command.

logging standby

no logging standby

Syntax Description

This command has no arguments or keywords.

Defaults

The **logging standby** command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

You can enable **logging standby** to ensure that the syslog messages of the failover standby security appliance stay synchronized if failover occurs.



Note

Using the **logging standby** command causes twice as much traffic on shared logging destinations, such as syslog servers, SNMP servers, and FTP servers.

Examples

The following example enables the security appliance to send syslog messages to the failover standby security appliance. The output of the **show logging** command reveals that this feature is enabled.

```
hostname(config)# logging standby
hostname(config)# show logging
Syslog logging: enabled
  Facility: 20
  Timestamp logging: disabled
  Standby logging: enabled
  Deny Conn when Queue Full: disabled
  Console logging: disabled
  Monitor logging: disabled
  Buffer logging: disabled
```

```
Trap logging: disabled
History logging: disabled
Device ID: 'inside' interface IP address "10.1.1.1"
Mail logging: disabled
ASDM logging: disabled
```

Related Commands

Command	Description
failover	Enables the failover feature.
logging enable	Enables logging.
logging host	Defines a syslog server.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

logging timestamp

To specify that syslog messages should include the date and time that the messages was generated, use the **logging timestamp** command in global configuration mode. To remove the date and time from syslog messages, use the **no** form of this command.

logging timestamp

no logging timestamp

Syntax Description

This command has no arguments or keywords.

Defaults

The security appliance does not include the date and time in syslog messages by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **logging timestamp** command makes the security appliance include a timestamp in all syslog messages.

Examples

The following example enables the inclusion of timestamp information in all syslog messages:

```
hostname(config)# logging enable
hostname(config)# logging timestamp
hostname(config)#
```

Related Commands

Command	Description
logging enable	Enables logging.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

logging trap

To specify which syslog messages the security appliance sends to a syslog server, use the **logging trap** command in global configuration mode. To remove this command from the configuration, use the **no** form of this command.

logging trap [*logging_list* | *level*]

no logging trap

Syntax Description

<i>level</i>	Sets the maximum level for system log messages. For example, if you set the level to 3, then the security appliance generates system log messages for level 3, 2, 1, and 0. You can specify either the number or the name, as follows: • 0 or emergencies—System unusable. • 1 or alerts—Take immediate action. • 2 or critical—Critical condition. • 3 or errors—Error. • 4 or warnings—Warning. • 5 or notifications—Normal but significant condition. • 6 or informational—Information. • 7 or debugging—Debug messages, log FTP commands, and WWW URLs.
<i>logging_list</i>	Specifies the list that identifies the messages to send to the syslog server. For information about creating lists, see the logging list command.

Defaults

No default syslog trap is defined.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If you are using TCP as the logging transport protocol, the security appliance denies new network access sessions as a security measure if the security appliance is unable to reach the syslog server, if the syslog server is misconfigured, or if the disk is full.

UDP-based logging does not prevent the security appliance from passing traffic if the syslog server fails.

Examples

This example shows how to send syslog messages of levels 0, 1, 2, and 3 to a syslog server that resides on the inside interface and uses the default protocol and port number.

```
hostname(config)# logging enable
hostname(config)# logging host inside 10.2.2.3
hostname(config)# logging trap errors
hostname(config)#
```

Related Commands

Command	Description
logging enable	Enables logging.
logging host	Defines a syslog server.
logging list	Creates a reusable list of message selection criteria.
show logging	Displays the enabled logging options.
show running-config logging	Displays the logging-related portion of the running configuration.

login-message

To create a message that prompts WebVPN users to log in, use the **login-message** command in webvpn mode. To remove a login message from the configuration and reset the default, use the **no** form of this command. To have no login message, use the **login-message** command without a string.

login-message [*string*]

no login-message

Syntax Description

string (Optional) Specifies the HTML string for the login message. Maximum 255 characters. May contain 7-bit ASCII values and HTML tags and escape sequences.

Defaults

The default login message is “Please enter your username and password.”

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to create the WebVPN message, “Welcome to Our Company. Please enter your username and password.”:

```
hostname(config)# webvpn
hostname(config-webvpn)# login-message Welcome to Our Company. Please enter your username
and password.
```

logo

To specify a logo to display on the WebVPN login and home pages, use the **logo** command in webvpn mode. To remove a logo from the configuration and reset the default, use the **no** form of this command. To have no logo, use the **logo none** command. If the filename you specify does not exist, an error occurs. If you remove a logo file but the configuration still points to it, no logo displays.

logo {**file** *filename* | **none**}

no logo

Syntax Description

file <i>filename</i>	Specifies the filename for the logo image. Maximum length is 255 characters. File type must be JPG, PNG, or GIF, and must be less than 100 KB.
none	Indicates that there is no logo. Sets a null value, thereby disallowing a logo. Prevents inheriting a logo.

Defaults

The Cisco logo is the default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The administrator uploads this file to the security gateway. If you specify a file, and it does not exist, the security appliance generates an error.

Examples

The following example shows how to set a WebVPN logo with the filename MyCompanylogo.gif:

```
hostname(config)# webvpn
hostname(config-webvpn)# logo MyCompanylogo.gif
```

logout

To exit from the CLI, use the **logout** command in user EXEC mode.

logout

Syntax Description This command has no arguments or keywords.

Defaults No default behaviors or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines The **logout** command lets you log out of the security appliance. You can use the **exit** or **quit** commands to go back to unprivileged mode.

Examples The following example shows how to log out of the security appliance:

```
hostname> logout
```

Related Commands	Command	Description
	login	Initiates the log-in prompt.
	exit	Exits an access mode.
	quit	Exits configuration or privileged mode.

logout-message

To create a logout message that WebVPN presents to users logging out, use the **logout-message** command in webvpn mode. To remove a logout message from the configuration and reset the default, use the **no** form of this command. To have no logout message, use the **logout-message** command without a string.

logout-message [*string*]

no logout-message

Syntax Description

<i>string</i>	(Optional) Specifies the HTML string for the logout message. Maximum 255 characters. May contain 7-bit ASCII values and HTML tags and escape sequences.

Defaults

The default logout message is “Goodbye.”

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Webvpn configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to create the WebVPN logout message, “Farewell! Be careful crossing the street!”:

```
hostname(config)# logout-message Farewell! Be careful crossing the street!
```



M through R Commands

mac address

To specify the virtual MAC addresses for the active and standby units, use the **mac address** command in failover group configuration mode. To restore the default virtual MAC addresses, use the **no** form of this command.

mac address *phy_if* [*active_mac*] [*standby_mac*]

no mac address *phy_if* [*active_mac*] [*standby_mac*]

Syntax Description

<i>phy_if</i>	The physical name of the interface to set the MAC address.
<i>active_mac</i>	The virtual MAC address for the active unit. The MAC address must be entered in h.h.h format, where h is a 16-bit hexadecimal number.
<i>standby_mac</i>	The virtual MAC address for the standby unit. The MAC address must be entered in h.h.h format, where h is a 16-bit hexadecimal number.

Defaults

The defaults are as follows:

- Active unit default MAC address: 00a0.c9*physical_port_number.failover_group_id*01.
- Standby unit default MAC address: 00a0.c9*physical_port_number.failover_group_id*02.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Failover group configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If the virtual MAC addresses are not defined for the failover group, the default values are used.

If you have more than one Active/Active failover pair on the same network, it is possible to have the same default virtual MAC addresses assigned to the interfaces on one pair as are assigned to the interfaces of the other pairs because of the way the default virtual MAC addresses are determined. To avoid having duplicate MAC addresses on your network, make sure you assign each physical interface a virtual active and standby MAC address.

Examples

The following partial example shows a possible configuration for a failover group:

```
hostname(config)# failover group 1
hostname(config-fover-group)# primary
```

```
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# exit
hostname(config)# failover group 2
hostname(config-fover-group)# secondary
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# mac address e1 0000.a000.a011 0000.a000.a012
hostname(config-fover-group)# exit
hostname(config)#
```

Related Commands

Command	Description
failover group	Defines a failover group for Active/Active failover.
failover mac address	Specifies a virtual MAC address for a physical interface.

mac-address-table aging-time

To set the timeout for MAC address table entries, use the **mac-address-table aging-time** command in global configuration mode. To restore the default value of 5 minutes, use the **no** form of this command.

mac-address-table aging-time *timeout_value*

no mac-address-table aging-time

Syntax Description

<i>timeout_value</i>	The time a MAC address entry stays in the MAC address table before timing out, between 5 and 720 minutes (12 hours). 5 minutes is the default.

Defaults

The default timeout is 5 minutes.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	—	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

No usage guidelines.

Examples

The following example sets the MAC address timeout to 10 minutes:

```
hostname(config)# mac-address-timeout aging time 10
```

Related Commands

Command	Description
arp-inspection	Enables ARP inspection, which compares ARP packets to static ARP entries.
firewall transparent	Sets the firewall mode to transparent.
mac-address-table static	Adds static MAC address entries to the MAC address table.
mac-learn	Disables MAC address learning.
show mac-address-table	Shows the MAC address table, including dynamic and static entries.

mac-address-table static

To add a static entry to the MAC address table, use the **mac-address-table static** command in global configuration mode. To remove a static entry, use the **no** form of this command. Normally, MAC addresses are added to the MAC address table dynamically as traffic from a particular MAC address enters an interface. You can add static MAC addresses to the MAC address table if desired. One benefit to adding static entries is to guard against MAC spoofing. If a client with the same MAC address as a static entry attempts to send traffic to an interface that does not match the static entry, then the security appliance drops the traffic and generates a system message.

mac-address-table static *interface_name* *mac_address*

no mac-address-table static *interface_name* *mac_address*

Syntax Description

<i>interface_name</i>	The source interface.
<i>mac_address</i>	The MAC address you want to add to the table.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	—	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example adds a static MAC address entry to the MAC address table:

```
hostname(config)# mac-address-table static inside 0010.7cbe.6101
```

Related Commands

Command	Description
arp	Adds a static ARP entry.
firewall transparent	Sets the firewall mode to transparent.
mac-address-table aging-time	Sets the timeout for dynamic MAC address entries.

Command	Description
mac-learn	Disables MAC address learning.
show mac-address-table	Shows MAC address table entries.

mac-learn

To disable MAC address learning for an interface, use the **mac-learn** command in global configuration mode. To reenable MAC address learning, use the **no** form of this command. By default, each interface automatically learns the MAC addresses of entering traffic, and the security appliance adds corresponding entries to the MAC address table. You can disable MAC address learning if desired.

mac-learn *interface_name* **disable**

no mac-learn *interface_name* **disable**

Syntax Description

<i>interface_name</i>	The interface on which you want to disable MAC learning.
disable	Disables MAC learning.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	—	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example disables MAC learning on the outside interface:

```
hostname(config)# mac-learn outside disable
```

Related Commands

Command	Description
clear configure mac-learn	Sets the mac-learn configuration to the default.
firewall transparent	Sets the firewall mode to transparent.
mac-address-table static	Adds static MAC address entries to the MAC address table.
show mac-address-table	Shows the MAC address table, including dynamic and static entries.
show running-config mac-learn	Shows the mac-learn configuration.

mac-list

To specify a list of MAC addresses to be used for MAC-based authentication, use the **mac-list** command in global configuration mode. To disable the use of a list of MAC addresses, use the **no** form of this command. The **mac-list** command adds a list of MAC addresses using a first-match search.

mac-list *id* **deny** | **permit** *mac* *macmask*

no mac-list *id* **deny** | **permit** *mac* *macmask*

Syntax Description

deny	Indicates that traffic matching these criteria is <i>not</i> included in the MAC list and is subject to both authentication and authorization.
<i>id</i>	Specifies a hexadecimal MAC access list number.
<i>mac</i>	Specifies the source MAC address in 12-digit hexadecimal form; that is, nnnn.nnnn.nnnn
<i>macmask</i>	Specifies and applies the netmask to <i>mac</i> and allows the grouping of MAC addresses.
permit	Indicates that traffic matching these criteria <i>is</i> included in the MAC list and is exempt from both authentication and authorization.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To group a set of MAC addresses, enter the **mac-list** command as many times as needed with the same *id* value. Configure the MAC access list number using the **mac-list** command before using the **aaa mac-exempt** command.

Only AAA exemption is provided. Authorization is automatically exempted for MAC addresses for which authentication is exempted. Other types of AAA with **mac-list** are not supported.

Examples

The following example shows how to configure a MAC address list:

```
hostname(config)# mac-list adc permit 00a0.cp5d.0282 ffff.ffff.ffff
```

```

hostname(config)# mac-list adc deny 00a1.cp5d.0282 ffff.ffff.ffff
hostname(config)# mac-list ac permit 0050.54ff.0000 ffff.ffff.0000
hostname(config)# mac-list ac deny 0061.54ff.b440 ffff.ffff.ffff
hostname(config)# mac-list ac deny 0072.54ff.b440 ffff.ffff.ffff

```

Related Commands

Command	Description
aaa authentication	Enable, disable, or view LOCAL, TACACS+, or RADIUS user authentication, on a server designated by the aaa-server command, or ASDM user authentication.
aaa authorization	Enable or disable LOCAL or TACACS+ user authorization services.
aaa mac-exempt	Exempt a list of MAC addresses from authentication and authorization.
clear configure mac-list	Remove a list of MAC addresses previously specified the mac-list command with the indicated MAC list number.
show running-config mac-list	Display a list of MAC addresses previously specified in the mac-list command with the indicated MAC list number.

management-access

To enable access to an internal management interface of the security appliance, use the **management-access** command in global configuration mode. To disable, use the **no** form of this command.

management-access *mgmt_if*

no management-access *mgmt_if*

Syntax Description

<i>mgmt_if</i>	The name of the internal management interface.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•		•		

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **management-access** command lets you define an internal management interface using the IP address of the firewall interface specified in *mgmt_if*. (The interface names are defined by the **nameif** command and displayed in quotes, “ ”, in the output of the **show interface** command.)

The **management-access** command is supported for the following through an IPSec VPN tunnel only, and you can define only one management interface globally:

- SNMP polls to the *mgmt_if*
- HTTPS requests to the *mgmt_if*
- ASDM access to the *mgmt_if*
- Telnet access to the *mgmt_if*
- SSH access to the *mgmt_if*
- Ping to the *mgmt_if*
- Syslog polls to the *mgmt_if*
- NTP requests the *mgmt_if*

Examples

The following example shows how to configure a firewall interface named “inside” as the management access interface:

```
hostname(config)# management-access inside  
hostname(config)# show management-access  
management-access inside
```

Related Commands

Command	Description
clear configure management-access	Removes the configuration of an internal interface for management access of the security appliance.
show management-access	Displays the name of the internal interface configured for management access.

management-only

To set an interface to accept management traffic only, use the **management-only** command in interface configuration mode. To allow through traffic, use the **no** form of this command.

management-only

no management-only

Syntax Description

This command has no arguments or keywords.

Defaults

The Management 0/0 interface on the ASA 5500 series adaptive security appliance is set to management-only mode by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The ASA adaptive security appliance includes a dedicated management interface called Management 0/0, which is meant to support traffic to the security appliance. However, you can configure any interface to be a management-only interface using the **management-only** command. Also, for Management 0/0, you can disable management-only mode so the interface can pass through traffic just like any other interface.



Note

Transparent firewall mode allows only two interfaces to pass through traffic; however, on the ASA adaptive security appliance, you can use the dedicated management interface (either the physical interface or a subinterface) as a third interface for management traffic. The mode is not configurable in this case and must always be management-only.

Examples

The following example disables management-only mode on the management interface:

```
hostname(config)# interface management0/0
hostname(config-if)# no management-only
```

The following example enables management-only mode on a subinterface:

 management-only

```
hostname(config)# interface gigabitethernet0/2.1  
hostname(config-subif)# management-only
```

Related Commands

Command	Description
interface	Configures an interface and enters interface configuration mode.

mask-syst-reply

To hide the FTP server response from clients, use the **mask-syst-reply** command in FTP map configuration mode, which is accessible by using the **ftp-map** command. To remove the configuration, use the **no** form of this command.

mask-syst-reply

no mask-syst-reply

Syntax Description

This command has no arguments or keywords.

Defaults

This command is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
FTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **mask-syst-reply** command with strict FTP inspection to protect the FTP server system from clients. After enabling this command, the servers replies to the **syst** command are replaced by a series of Xs.

Examples

The following example causes the security appliance to replace the FTP server replies to the **syst** command with Xs:

```
hostname(config)# ftp-map inbound_ftp
hostname(config-ftp-map)# mask-syst-reply
hostname(config-ftp-map)# exit
```

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
functions	Defines an FTP map and enables FTP map configuration mode.
inspect ftp	Applies a specific FTP map to use for application inspection.
policy-map	Associates a class map with specific security actions.
request-command deny	Specifies FTP commands to disallow.

match access-list

To identify traffic using an access list in a class map, use the **match access-list** command in class-map configuration mode. To remove the access list, use the **no** form of this command.

match access-list {*acl-id...*}

no match access-list {*acl-id...*}

Syntax Description

<i>acl-id</i>	Specifies the name of an ACL to be used as match criteria. When a packet does not match an entry in the ACL, the match result is a no-match. When a packet matches an entry in an ACL, and if it is a permit entry, the match result is a match. Otherwise, if it matches a deny ACL entry, the match result is no-match.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **match** commands are used to identify the traffic included in the traffic class for a class map. They include different criteria to define the traffic included in a class-map. Define a traffic class using the **class-map** global configuration command as part of configuring a security feature using Modular Policy Framework. From class-map configuration mode, you can define the traffic to include in the class using the **match** command.

After a traffic class is applied to an interface, packets received on that interface are compared to the criteria defined by the **match** statements in the class map. If the packet matches the specified criteria, it is included in the traffic class and is subjected to any actions associated with that traffic class. Packets that do not match any of the criteria in any traffic class are assigned to the default traffic class.

You can specify one or more access lists to identify specific types of traffic using the **match access-list** command. The **permit** statement in an access control entry causes the traffic to be included, while a **deny** statement causes the traffic to be excluded from the traffic class map.

Examples

The following example shows how to define a traffic class using a class map and the **match access-list** command:

```
hostname(config)# access-list ftp_acl extended permit tcp any any eq 21  
hostname(config)# class-map ftp_port  
hostname(config-cmap)# match access-list ftp_acl
```

Related Commands

Command	Description
class-map	Applies a traffic class to an interface.
clear configure class-map	Removes of the traffic map definitions.
match any	Includes all traffic in the class map.
match port	Identifies a specific port number in a class map.
show running-config class-map	Displays the information about the class map configuration.

match any

To include all traffic in a class map, use the **match any** command in class-map configuration mode. To remove this specification, use the **no** form of this command.

match any

no match any

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **match** commands are used to identify the traffic included in the traffic class for a class map. They include different criteria to define the traffic included in a class-map. Define a traffic class using the **class-map** global configuration command as part of configuring a security feature using Modular Policy Framework. From class-map configuration mode, you can define the traffic to include in the class using the **match** command.

After a traffic class is applied to an interface, packets received on that interface are compared to the criteria defined by the **match** statements in the class map. If the packet matches the specified criteria, it is included in the traffic class and is subjected to any actions associated with that traffic class. Packets that do not match any of the criteria in any traffic class are assigned to the default traffic class.

All packets will be matched using the **match any** command (as in the default class map, class-default).

Examples

This example shows how to define a traffic class using a class map and the **match any** command:

```
hostname(config)# class-map cmap
hostname(config-cmap)# match any
```

Related Commands	Command	Description
	class-map	Applies a traffic class to an interface.
	clear configure class-map	Removes all of the traffic map definitions.
	match access-list	Identifies access list traffic in a class map.
	match rtp	Identifies a specific RTP port in a class map.
	show running-config class-map	Displays the information about the class map configuration.

match default-inspection-traffic

To specify default traffic for the inspect commands in a class map, use the **match default-inspection-traffic** command in class-map configuration mode. To remove this specification, use the **no** form of this command.

match default-inspection-traffic

no match default-inspection-traffic

Syntax Description

This command has no arguments or keywords.

Defaults

See the Usage Guidelines section for the default traffic of each inspection.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **match** commands are used to identify the traffic included in the traffic class for a class map. They include different criteria to define the traffic included in a class-map. Define a traffic class using the **class-map** global configuration command as part of configuring a security feature using Modular Policy Framework. From class-map configuration mode, you can define the traffic to include in the class using the **match** command.

After a traffic class is applied to an interface, packets received on that interface are compared to the criteria defined by the **match** statements in the class map. If the packet matches the specified criteria, it is included in the traffic class and is subjected to any actions associated with that traffic class. Packets that do not match any of the criteria in any traffic class are assigned to the default traffic class.

Using the **match default-inspection-traffic** command, you can match default traffic for the individual **inspect** commands. The **match default-inspection-traffic** command can be used in conjunction with one other match command, which is typically an access-list in the form of **permit ip src-ip dst-ip**.

The rule for combining a second **match** command with the **match default-inspection-traffic** command is to specify the protocol and port information using the **match default-inspection-traffic** command and specify all other information (such as IP addresses) using the second **match** command. Any protocol or port information specified in the second **match** command is ignored with respect to the **inspect** commands.

For instance, port 65535 specified in the example below is ignored:


```
hostname(config)# class-map cmap
hostname(config-cmap)# match default-inspection-traffic
hostname(config-cmap)# match port 65535
```

Default traffic for inspections are as follows:

Inspection Type	Protocol Type	Source Port	Destination Port
ctiqbe	tcp	N/A	1748
dns	udp	53	53
ftp	tcp	N/A	21
gtp	udp	2123,3386	2123,3386
h323 h225	tcp	N/A	1720
h323 ras	udp	N/A	1718-1719
http	tcp	N/A	80
icmp	icmp	N/A	N/A
ils	tcp	N/A	389
mgcp	udp	2427,2727	2427,2727
netbios	udp	137-138	N/A
rpc	udp	111	111
rsh	tcp	N/A	514
rtsp	tcp	N/A	554
sip	tcp,udp	N/A	5060
skinny	tcp	N/A	2000
smtp	tcp	N/A	25
sqlnet	tcp	N/A	1521
tftp	udp	N/A	69
xmcp	udp	177	177

Examples

The following example shows how to define a traffic class using a class map and the **match default-inspection-traffic** command:

```
hostname(config)# class-map cmap
hostname(config-cmap)# match default-inspection-traffic
```

Related Commands

Command	Description
class-map	Applies a traffic class to an interface.
clear configure class-map	Removes all of the traffic map definitions.
match access-list	Identifies access list traffic within a class map.
match any	Includes all traffic in the class map.
show running-config class-map	Displays the information about the class map configuration.

match dscp

To identify the IETF-defined DSCP value (in an IP header) in a class map, use the **match dscp** command in class-map configuration mode. To remove this specification, use the **no** form of this command.

match dscp {*values*}

no match dscp {*values*}

Syntax Description

<i>values</i>	Specifies up to eight different the IETF-defined DSCP values in the IP header. Range is 0 to 63.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Class-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **match** commands are used to identify the traffic included in the traffic class for a class map. They include different criteria to define the traffic included in a class-map. Define a traffic class using the **class-map** global configuration command as part of configuring a security feature using Modular Policy Framework. From class-map configuration mode, you can define the traffic to include in the class using the **match** command.

After a traffic class is applied to an interface, packets received on that interface are compared to the criteria defined by the **match** statements in the class map. If the packet matches the specified criteria, it is included in the traffic class and is subjected to any actions associated with that traffic class. Packets that do not match any of the criteria in any traffic class are assigned to the default traffic class.

Using the **match dscp** command, you can match the IETF-defined DSCP values in the IP header.

Examples

The following example shows how to define a traffic class using a class map and the **match dscp** command:

```
hostname(config)# class-map cmap
hostname(config-cmap)# match dscp af43 cs1 ef
```

Related Commands	Command	Description
	class-map	Applies a traffic class to an interface.
	clear configure class-map	Removes all of the traffic map definitions.
	match access-list	Identifies access list traffic within a class map.
	match port	Specifies the TCP/UDP ports as the comparison criteria for packets received on that interface.
	show running-config class-map	Displays the information about the class map configuration.

match flow ip destination-address

To specify the flow IP destination address in a class map, use the **match flow ip destination-address** command in class-map configuration mode. To remove this specification, use the **no** form of this command.

match flow ip destination-address

no match flow ip destination-address

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **match** commands are used to identify the traffic included in the traffic class for a class map. They include different criteria to define the traffic included in a class-map. Define a traffic class using the **class-map** global configuration command as part of configuring a security feature using Modular Policy Framework. From class-map configuration mode, you can define the traffic to include in the class using the **match** command.

After a traffic class is applied to an interface, packets received on that interface are compared to the criteria defined by the **match** statements in the class map. If the packet matches the specified criteria, it is included in the traffic class and is subjected to any actions associated with that traffic class. Packets that do not match any of the criteria in any traffic class are assigned to the default traffic class.

To enable flow-based policy actions on a tunnel group, use the **match flow ip destination-address** and **match tunnel-group** commands with the **class-map**, **policy-map**, and **service-policy** commands. The criteria to define flow is the destination IP address. All traffic going to a unique IP destination address is considered a flow. Policy action is applied to each flow instead of the entire class of traffic. QoS action police is applied using the **match flow ip destination-address** command. Use **match tunnel-group** to police every tunnel within a tunnel group to a specified rate.

Examples

The following example shows how to enable flow-based policing within a tunnel group and limit each tunnel to a specified rate:

```
hostname(config)# class-map cmap
hostname(config-cmap)# match tunnel-group
hostname(config-cmap)# match flow ip destination-address
hostname(config-cmap)# exit
hostname(config)# policy-map pmap
hostname(config-pmap)# class cmap
hostname(config-pmap)# police 56000
hostname(config-pmap)# exit
hostname(config)# service-policy pmap global
```

Related Commands

Command	Description
class-map	Applies a traffic class to an interface.
clear configure class-map	Removes all of the traffic map definitions.
match access-list	Identifies access list traffic within a class map.
show running-config class-map	Displays the information about the class map configuration.
tunnel-group	Creates and manages the database of connection-specific records for VPN.

match interface

To distribute any routes that have their next hop out one of the interfaces specified, use the **match interface** command in route-map configuration mode. To remove the match interface entry, use the **no** form of this command.

match interface *interface-name...*

no match interface *interface-name...*

Syntax Description

interface-name	Name of the interface (not the physical interface). Multiple interface names can be specified.

Defaults

No match interfaces are defined.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Route-map configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

An ellipsis (...) in the command syntax indicates that your command input can include multiple values for the interface-type interface-number arguments.

The **route-map global** configuration command and the **match** and **set** configuration commands allow you to define the conditions for redistributing routes from one routing protocol into another. Each **route-map** command has **match** and **set** commands that are associated with it. The **match** commands specify the match criteria—the conditions under which redistribution is allowed for the current **route-map** command. The **set** commands specify the set actions—the particular redistribution actions to perform if the criteria that is enforced by the **match** commands are met. The **no route-map** command deletes the route map.

The **match** route-map configuration command has multiple formats. You can give the **match** commands in any order. All **match** commands must “pass” to cause the route to be redistributed according to the set actions that are given with the **set** commands. The **no** forms of the **match** commands remove the specified match criteria. If there is more than one interface specified in the **match** command, then the **no match interface interface-name** can be used to remove a single interface.

A route map can have several parts. Any route that does not match at least one match clause relating to a **route-map** command is ignored. If you want to modify only some data, you must configure a second route map section and specify an explicit match.

Examples

The following example shows that the routes with their next hop outside is distributed:

```
hostname(config)# route-map name  
hostname(config-route-map)# match interface outside
```

Related Commands

Command	Description
match ip next-hop	Distributes any routes that have a next-hop router address that is passed by one of the access lists specified.
match ip route-source	Redistributes routes that have been advertised by routers and access servers at the address that is specified by the access lists.
match metric	Redistributes routes with the metric specified.
route-map	Defines the conditions for redistributing routes from one routing protocol into another.
set metric	Specifies the metric value in the destination routing protocol for a route map.

match ip address

To redistribute any routes that have a route address or match packet that is passed by one of the access lists specified, use the **match ip address** command in route-map configuration mode. To restore the default settings, use the **no** form of this command.

match ip address {*acl...*}

no match ip address {*acl...*}

Syntax Description

acl Name an access list. Multiple access lists can be specified.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Route-map configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **route-map global** configuration command and the **match** and **set** configuration commands allow you to define the conditions for redistributing routes from one routing protocol into another. Each **route-map** command has **match** and **set** commands that are associated with it. The **match** commands specify the match criteria—the conditions under which redistribution is allowed for the current **route-map** command. The **set** commands specify the set actions—the particular redistribution actions to perform if the criteria that is enforced by the **match** commands are met. The **no route-map** command deletes the route map.

Examples

The following example shows how to redistribute internal routes:

```
hostname(config)# route-map name
hostname(config-route-map)# match ip address acl_dmz1 acl_dmz2
```


Related Commands	Command	Description
	match interface	Distributes distribute any routes that have their next hop out one of the interfaces specified,
	match ip next-hop	Distributes any routes that have a next-hop router address that is passed by one of the access lists specified.
	match metric	Redistributes routes with the metric specified.
	route-map	Defines the conditions for redistributing routes from one routing protocol into another.
	set metric	Specifies the metric value in the destination routing protocol for a route map.

match ip next-hop

To redistribute any routes that have a next-hop router address that is passed by one of the access lists specified, use the **match ip next-hop** command in route-map configuration mode. To remove the next-hop entry, use the **no** form of this command.

match ip next-hop {*acl...*} | **prefix-list** *prefix_list*

no match ip next-hop {*acl...*} | **prefix-list** *prefix_list*

Syntax Description

<i>acl</i>	Name of an ACL. Multiple ACLs can be specified.
prefix-list <i>prefix_list</i>	Name of prefix list.

Defaults

Routes are distributed freely, without being required to match a next-hop address.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Route-map configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

An ellipsis (...) in the command syntax indicates that your command input can include multiple values for the *acl* argument.

The **route-map global** configuration command and the **match** and **set** configuration commands allow you to define the conditions for redistributing routes from one routing protocol into another. Each **route-map** command has **match** and **set** commands that are associated with it. The **match** commands specify the match criteria—the conditions under which redistribution is allowed for the current **route-map** command. The **set** commands specify the set actions—the particular redistribution actions to perform if the criteria that is enforced by the **match** commands are met. The **no route-map** command deletes the route map.

The **match** route-map configuration command has multiple formats. You can enter the **match** commands in any order. All **match** commands must “pass” to cause the route to be redistributed according to the set actions given with the **set** commands. The **no** forms of the **match** commands remove the specified match criteria.

When you are passing routes through a route map, a route map can have several parts. Any route that does not match at least one match clause relating to a **route-map** command is ignored. To modify only some data, you must configure a second route map section and specify an explicit match.

Examples

The following example shows how to distribute routes that have a next-hop router address passed by access list `acl_dmz1` or `acl_dmz2`:

```
hostname(config)# route-map name  
hostname(config-route-map)# match ip next-hop acl_dmz1 acl_dmz2
```

Related Commands

Command	Description
match interface	Distributes distribute any routes that have their next hop out one of the interfaces specified.
match ip next-hop	Distributes any routes that have a next-hop router address that is passed by one of the access lists specified.
match metric	Redistributes routes with the metric specified.
route-map	Defines the conditions for redistributing routes from one routing protocol into another.
set metric	Specifies the metric value in the destination routing protocol for a route map.

match ip route-source

To redistribute routes that have been advertised by routers and access servers at the address that is specified by the ACLs, use the **match ip route-source** command in the route-map configuration mode. To remove the next-hop entry, use the **no** form of this command.

match ip route-source {*acl...*} [**prefix-list** *prefix_list*]

no match ip route-source {*acl...*}

Syntax Description

<i>acl</i>	Name of an ACL. Multiple ACLs can be specified.
<i>prefix_list</i>	Name of prefix list.

Defaults

No filtering on a route source.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Route-map configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

An ellipsis (...) in the command syntax indicates that your command input can include multiple values for the access-list-name argument.

The **route-map global** configuration command and the **match** and **set** configuration commands allow you to define the conditions for redistributing routes from one routing protocol into another. Each **route-map** command has **match** and **set** commands that are associated with it. The **match** commands specify the match criteria—the conditions under which redistribution is allowed for the current **route-map** command. The **set** commands specify the set actions—the particular redistribution actions to perform if the criteria that is enforced by the **match** commands are met. The **no route-map** command deletes the route map.

The **match** route-map configuration command has multiple formats. You can enter the **match** commands in any order. All **match** commands must “pass” to cause the route to be redistributed according to the set actions given with the **set** commands. The **no** forms of the **match** commands remove the specified match criteria.

A route map can have several parts. Any route that does not match at least one match clause relating to a **route-map** command is ignored. To modify only some data, you must configure a second route map section and specify an explicit match. The next-hop and source-router address of the route are not the same in some situations.

Examples

The following example shows how to distribute routes that have been advertised by routers and access servers at the addresses specified by ACLs `acl_dmz1` and `acl_dmz2`:

```
hostname(config)# route-map name  
hostname(config-route-map)# match ip route-source acl_dmz1 acl_dmz2
```

Related Commands

Command	Description
match interface	Distributes distribute any routes that have their next hop out one of the interfaces specified.
match ip next-hop	Distributes any routes that have a next-hop router address that is passed by one of the ACLs specified.
match metric	Redistributes routes with the metric specified.
route-map	Defines the conditions for redistributing routes from one routing protocol into another.
set metric	Specifies the metric value in the destination routing protocol for a route map.

match metric

To redistribute routes with the metric specified, use the **match metric** command in route-map configuration mode. To remove the entry, use the **no** form of this command.

match metric *number*

no match metric *number*

Syntax Description

<i>number</i>	Route metric, which can be an IGRP five-part metric; valid values are from 0 to 4294967295.

Defaults

No filtering on a metric value.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Route-map configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **route-map global** configuration command and the **match** and **set** configuration commands allow you to define the conditions for redistributing routes from one routing protocol into another. Each **route-map** command has **match** and **set** commands that are associated with it. The **match** commands specify the match criteria—the conditions under which redistribution is allowed for the current **route-map** command. The **set** commands specify the set actions—the particular redistribution actions to perform if the criteria that is enforced by the **match** commands are met. The **no route-map** command deletes the route map.

The **match** route-map configuration command has multiple formats. The **match** commands can be given in any order, and all **match** commands must “pass” to cause the route to be redistributed according to the set actions given with the **set** commands. The **no** forms of the **match** commands remove the specified match criteria.

A route map can have several parts. Any route that does not match at least one match clause relating to a **route-map** command is ignored. To modify only some data, you must configure a second route map section and specify an explicit match.

Examples

The following example shows how to redistribute routes with the metric 5:

```
hostname(config)# route-map name
```

```
hostname(config-route-map)# match metric 5
```

Related Commands

Command	Description
match interface	Distributes distribute any routes that have their next hop out one of the interfaces specified,
match ip next-hop	Distributes any routes that have a next-hop router address that is passed by one of the access lists specified.
route-map	Defines the conditions for redistributing routes from one routing protocol into another.
set metric	Specifies the metric value in the destination routing protocol for a route map.

match port

To identify a specific port number in a class map, use the **match port** command in class-map configuration mode. To remove this specification, use the **no** form of this command.

```
match port {tcp | udp} {eq eq_id | range beg_id end_id}
```

```
no match port {tcp | udp} {eq eq_id | range beg_id end_id}
```

Syntax Description

eq <i>eq_id</i>	Specifies a port name.
range <i>beg_id</i> <i>end_id</i>	Specifies beginning and ending port range values (1-65535).
tcp	Specifies a TCP port.
udp	Specifies a UDP port.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Class-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **match** commands are used to identify the traffic included in the traffic class for a class map. They include different criteria to define the traffic included in a class-map. Define a traffic class using the **class-map** global configuration command as part of configuring a security feature using Modular Policy Framework. From class-map configuration mode, you can define the traffic to include in the class using the **match** command.

After a traffic class is applied to an interface, packets received on that interface are compared to the criteria defined by the **match** statements in the class map. If the packet matches the specified criteria, it is included in the traffic class and is subjected to any actions associated with that traffic class. Packets that do not match any of the criteria in any traffic class are assigned to the default traffic class.

Use the **match port** command to specify a range of ports.

Examples

The following example shows how to define a traffic class using a class map and the **match port** command:

```
hostname(config)# class-map cmap
```



```
hostname(config-cmap) # match port tcp eq 8080
```

Related Commands

Command	Description
class-map	Applies a traffic class to an interface.
clear configure class-map	Removes all of the traffic map definitions.
match access-list	Identifies access list traffic within a class map.
match any	Includes all traffic in the class map.
show running-config class-map	Displays the information about the class map configuration.

match precedence

To specify a precedence value in a class map, use the **match precedence** command in class-map configuration mode. To remove this specification, use the **no** form of this command.

match precedence *value*

no match precedence *value*

Syntax Description

value Specifies up to four precedence values separated by a space. Range is 0 to 7.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **match** commands are used to identify the traffic included in the traffic class for a class map. They include different criteria to define the traffic included in a class-map. Define a traffic class using the **class-map** global configuration command as part of configuring a security feature using Modular Policy Framework. From class-map configuration mode, you can define the traffic to include in the class using the **match** command.

After a traffic class is applied to an interface, packets received on that interface are compared to the criteria defined by the **match** statements in the class map. If the packet matches the specified criteria, it is included in the traffic class and is subjected to any actions associated with that traffic class. Packets that do not match any of the criteria in any traffic class are assigned to the default traffic class.

Use the **match precedence** command to specify the value represented by the TOS byte in the IP header.

Examples

The following example shows how to define a traffic class using a class map and the **match precedence** command:

```
hostname(config)# class-map cmap
hostname(config-cmap)# match precedence 1
```

Related Commands	Command	Description
	class-map	Applies a traffic class to an interface.
	clear configure class-map	Removes all of the traffic map definitions.
	match access-list	Identifies access list traffic within a class map.
	match any	Includes all traffic in the class map.
	show running-config class-map	Displays the information about the class map configuration.

match route-type

To redistribute routes of the specified type, use the **match route-type** command in route-map configuration mode. To remove the route type entry, use the **no** form of this command.

```
match route-type {local | internal | {external [type-1 | type-2]} | {nssa-external [type-1 | type-2]}}
```

```
no match route-type {local | internal | {external [type-1 | type-2]} | {nssa-external [type-1 | type-2]}}
```

Syntax Description

local	Locally generated BGP routes.
internal	OSPF intra-area and interarea routes or EIGRP internal routes.
external	OSPF external routes or EIGRP external routes.
type-1	(Optional) Specifies the route type 1.
type-2	(Optional) Specifies the route type 2.
nssa-external	Specifies the external NSSA.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Route-map configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **route-map** global configuration command and the **match** and **set** configuration commands allow you to define the conditions for redistributing routes from one routing protocol into another. Each **route-map** command has **match** and **set** commands that are associated with it. The **match** commands specify the match criteria—the conditions under which redistribution is allowed for the current **route-map** command. The **set** commands specify the set actions—the particular redistribution actions to perform if the criteria that is enforced by the **match** commands are met. The **no route-map** command deletes the route map.

The **match** route-map configuration command has multiple formats. You can enter the **match** commands in any order. All **match** commands must “pass” to cause the route to be redistributed according to the set actions given with the **set** commands. The **no** forms of the **match** commands remove the specified match criteria.

A route map can have several parts. Any route that does not match at least one match clause relating to a **route-map** command is ignored. To modify only some data, you must configure a second route map section and specify an explicit match.

For OSPF, the **external type-1** keywords match only type 1 external routes and the **external type-2** keywords match only type 2 external routes.

Examples

The following example shows how to redistribute internal routes:

```
hostname(config)# route-map name  
hostname(config-route-map)# match route-type internal
```

Related Commands

Command	Description
match interface	Distributes distribute any routes that have their next hop out one of the interfaces specified,
match ip next-hop	Distributes any routes that have a next-hop router address that is passed by one of the access lists specified.
match metric	Redistributes routes with the metric specified.
route-map	Defines the conditions for redistributing routes from one routing protocol into another.
set metric	Specifies the metric value in the destination routing protocol for a route map.

match rtp

To specify a UDP port range of even-number ports in a class map, use the **match rtp** command in class-map configuration mode. To remove this specification, use the **no** form of this command.

match rtp *starting_port range*

no match rtp *starting_port range*

Syntax Description

<i>starting_port</i>	Specifies lower bound of even-number UDP destination port. Range is 2000-65535
<i>range</i>	Specifies range of RTP ports. Range is 0-16383.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **match** commands are used to identify the traffic included in the traffic class for a class map. They include different criteria to define the traffic included in a class-map. Define a traffic class using the **class-map** global configuration command as part of configuring a security feature using Modular Policy Framework. From class-map configuration mode, you can define the traffic to include in the class using the **match** command.

After a traffic class is applied to an interface, packets received on that interface are compared to the criteria defined by the **match** statements in the class map. If the packet matches the specified criteria, it is included in the traffic class and is subjected to any actions associated with that traffic class. Packets that do not match any of the criteria in any traffic class are assigned to the default traffic class.

Use the **match rtp** command to match RTP ports (even UDP port numbers between the *starting_port* and the *starting_port* plus the *range*).

Examples

The following example shows how to define a traffic class using a class map and the **match rtp** command:

```
hostname(config)# class-map cmap
```

```
hostname(config-cmap) # match rtp 20000 100
```

Related Commands

Command	Description
class-map	Applies a traffic class to an interface.
clear configure class-map	Removes all of the traffic map definitions.
match access-list	Identifies access list traffic within a class map.
match any	Includes all traffic in the class map.
show running-config class-map	Displays the information about the class map configuration.

match tunnel-group

To match traffic in a class map that belongs to a previously defined tunnel-group, use the **match tunnel-group** command in class-map configuration mode. To remove this specification, use the **no** form of this command.

match tunnel-group *name*

no match tunnel-group *name*

Syntax Description

<i>name</i>	Text for the tunnel group name.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **match** commands are used to identify the traffic included in the traffic class for a class map. They include different criteria to define the traffic included in a class-map. Define a traffic class using the **class-map** global configuration command as part of configuring a security feature using Modular Policy Framework. From class-map configuration mode, you can define the traffic to include in the class using the **match** command.

After a traffic class is applied to an interface, packets received on that interface are compared to the criteria defined by the **match** statements in the class map. If the packet matches the specified criteria, it is included in the traffic class and is subjected to any actions associated with that traffic class. Packets that do not match any of the criteria in any traffic class are assigned to the default traffic class.

To enable flow-based policy actions, use the **match flow ip destination-address** and **match tunnel-group** commands with the **class-map**, **policy-map**, and **service-policy** commands. The criteria to define flow is the destination IP address. All traffic going to a unique IP destination address is considered a flow. Policy action is applied to each flow instead of the entire class of traffic. QoS action police is applied using the **police** command. Use **match tunnel-group** along with **match flow ip destination-address** to police every tunnel within a tunnel group to a specified rate.

Examples

The following example shows how to enable flow-based policing within a tunnel group and limit each tunnel to a specified rate:

```
hostname(config)# class-map cmap
hostname(config-cmap)# match tunnel-group
hostname(config-cmap)# match flow ip destination-address
hostname(config-cmap)# exit
hostname(config)# policy-map pmap
hostname(config-pmap)# class cmap
hostname(config-pmap)# police 56000
hostname(config-pmap)# exit
hostname(config)# service-policy pmap global
```

Related Commands

Command	Description
class-map	Applies a traffic class to an interface.
clear configure class-map	Removes all of the traffic map definitions.
match access-list	Identifies access list traffic within a class map.
show running-config class-map	Displays the information about the class map configuration.
tunnel-group	Creates and manages the database of connection-specific records for IPSec and L2TP,

max-failed-attempts

To specify the number of failed attempts allowed for any given server in the server group before that server is deactivated, use the **max-failed-attempts** command in AAA-server group mode. To remove this specification and revert to the default value, use the **no** form of this command:

max-failed-attempts *number*

no max-failed-attempts

Syntax Description

number An integer in the range 1-5, specifying the number of failed connection attempts allowed for any given server in the server group specified in a prior **aaa-server** command.

Defaults

The default value of *number* is 3.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
AAA-server group	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must have configured the AAA server/group before issuing this command.

Examples

```
hostname(config)# aaa-server svrgrp1 protocol tacacs+
hostname(config-aaa-server-group)# max-failed-attempts 4
```

Related Commands

Command	Description
aaa-server <i>server-tag</i> protocol <i>protocol</i>	Enters AAA server group configuration mode so you can configure AAA server parameters that are group-specific and common to all hosts in the group.

clear configure aaa-server	Removes all AAA server configuration.
show running-config aaa	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol

max-header-length

To restrict HTTP traffic based on the HTTP header length, use the **max-header-length** command in HTTP map configuration mode, which is accessible using the **http-map** command. To remove this command, use the **no** form of this command.

max-header-length {**request** *bytes* [**response** *bytes*] | **response** *bytes*} **action** {**allow** | **reset** | **drop**} [**log**]

no max-header-length {**request** *bytes* [**response** *bytes*] | **response** *bytes*} **action** {**allow** | **reset** | **drop**} [**log**]

Syntax Description

action	The action taken when a message fails this command inspection.
allow	Allow the message.
drop	Closes the connection.
bytes	Number of bytes, range is 1 to 65535.
log	(Optional) Generate a syslog.
request	Request message.
reset	Send a TCP reset message to client and server.
response	(Optional) Response message.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
HTTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

After enabling the **max-header-length** command, the security appliance only allows messages having an HTTP header within the configured limit and otherwise takes the specified action. Use the **action** keyword to cause the security appliance to reset the TCP connection and optionally create a syslog entry.

Examples

The following example restricts HTTP requests to those with HTTP headers that do not exceed 100 bytes. If a header is too large, the security appliance resets the TCP connection and creates a syslog entry.

```
hostname(config)# http-map inbound_http
hostname(config-http-map)# max-header-length request bytes 100 action log reset
hostname(config-http-map)# exit
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug appfw	Displays detailed information about traffic associated with enhanced HTTP inspection.
http-map	Defines an HTTP map for configuring enhanced HTTP inspection.
inspect http	Applies a specific HTTP map to use for application inspection.
policy-map	Associates a class map with specific security actions.

max-uri-length

To restrict HTTP traffic based on the length of the URI in the HTTP request message, use the **max-uri-length** command in HTTP map configuration mode, which is accessible using the **http-map** command. To remove this command, use the **no** form of this command.

max-uri-length *bytes* **action** { **allow** | **reset** | **drop** } [**log**]

no max-uri-length *bytes* **action** { **allow** | **reset** | **drop** } [**log**]

Syntax Description

action	The action taken when a message fails this command inspection.
allow	Allow the message.
drop	Closes the connection.
bytes	Number of bytes, range is 1 to 65535.
log	(Optional) Generate a syslog.
reset	Send a TCP reset message to client and server.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
HTTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

After enabling the **max-uri-length** command, the security appliance only allows messages having a URI within the configured limit and otherwise takes the specified action. Use the **action** keyword to cause the security appliance to reset the TCP connection and create a syslog entry.

URIs with a length less than or equal to the configured value will be allowed. Otherwise, the specified action will be taken.

Examples

The following example restricts HTTP requests to those with URIs that do not exceed 100 bytes. If a URI is too large, the security appliance resets the TCP connection and creates a syslog entry.

```
hostname(config)# http-map inbound_http
hostname(config-http-map)# max-uri-length 100 action reset log
hostname(config-http-map)# exit
```

Related Commands	Commands	Description
	class-map	Defines the traffic class to which to apply security actions.
	debug appfw	Displays detailed information about traffic associated with enhanced HTTP inspection.
	http-map	Defines an HTTP map for configuring enhanced HTTP inspection.
	inspect http	Applies a specific HTTP map to use for application inspection.
	policy-map	Associates a class map with specific security actions.

mcc

To identify the mobile country code and the mobile network code for IMSI prefix filtering, use the **mcc** command in GTP map configuration mode. To remove the configuration, use the **no** form of this command.

mcc *country_code* **mnc** *network_code*

no **mcc** *country_code* **mnc** *network_code*

Syntax Description

<i>country_code</i>	A non-zero, three-digit value identifying the mobile country code. One or two-digit entries will be prepended by 0 to create a three-digit value.
<i>network_code</i>	A two or three-digit value identifying the network code.

Defaults

By default, the security appliance does not check for valid MCC/MNC combinations.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
GTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is used for IMSI Prefix filtering. The MCC and MNC in the IMSI of the received packet is compared with the MCC/MNC configured with this command and is dropped if it does not match.

This command must be used to enable IMSI Prefix filtering. You can configure multiple instances to specify permitted MCC and MNC combinations. By default, the security appliance does not check the validity of MNC and MCC combinations, so you must verify the validity of the combinations configured. To find more information about MCC and MNC codes, see the ITU E.212 recommendation, *Identification Plan for Land Mobile Stations*.

Examples

The following example identifies traffic for IMSI Prefix filtering with an MCC of 111 and an MNC of 222:

```
hostname(config)# gtp-map gtp-policy
hostname(config-gtpmap)# mcc 111 mnc 222
```


Related Commands	Commands	Description
	clear service-policy inspect gtp	Clears global GTP statistics.
	debug gtp	Displays detailed information about GTP inspection.
	gtp-map	Defines a GTP map and enables GTP map configuration mode.
	inspect gtp	Applies a specific GTP map to use for application inspection.
	show service-policy inspect gtp	Displays the GTP configuration.

media-type

To set the media type to copper or fiber Gigabit Ethernet, use the **media-type** command in interface configuration mode. The fiber SFP connector is available on the 4GE SSM for the ASA 5500 series adaptive security appliance. To restore the media type setting to the default, use the **no** form of this command.

media-type {rj45 | sfp}

no media-type [rj45 | sfp]

Syntax Description

rj45	(Default) Sets the media type to the copper RJ-45 connector.
sfp	Sets the media type to the fiber SFP connector.

Defaults

The default is **rj45**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	•	•	—	•

Command History

Release	Modification
7.0(4)	This command was introduced.

Usage Guidelines

The **sfp** setting uses a fixed speed (1000 Mbps), so the **speed** command allows you to set whether the interface negotiates link parameters or not. The **duplex** command is not supported for **sfp**.

Examples

The following example sets the media type to SFP:

```
hostname(config)# interface gigabitethernet1/1
hostname(config-if)# media-type sfp
hostname(config-if)# nameif inside
hostname(config-if)# security-level 100
hostname(config-if)# ip address 10.1.1.1 255.255.255.0
hostname(config-if)# no shutdown
```

Related Commands

Command	Description
interface	Configures an interface and enters interface configuration mode.
show interface	Displays the runtime status and statistics of interfaces.
show running-config interface	Shows the interface configuration.
speed	Sets the interface speed.

memory caller-address

To configure a specific range of program memory for the call tracing, or caller PC, to help isolate memory problems, use the **memory caller-address** command in privileged EXEC mode. The caller PC is the address of the program that called a memory allocation primitive. To remove an address range, use the **no** form of this command.

memory caller-address *startPC endPC*

no memory caller-address

Syntax Description

<i>endPC</i>	Specifies the end address range of the memory block.
<i>startPC</i>	Specifies the start address range of the memory block.

Defaults

The actual caller PC is recorded for memory tracing.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **memory caller-address** command to isolate memory problems to a specific block of memory.

In certain cases the actual caller PC of the memory allocation primitive is a known library function that is used at many places in the program. To isolate individual places in the program, configure the start and end program address of the library function, thereby recording the program address of the caller of the library function.



Note

The security appliance might experience a temporary reduction in performance when caller-address tracing is enabled.

Examples

The following examples show the address ranges configured with the **memory caller-address** commands, and the resulting display of the **show memory-caller address** command:

```
hostname# memory caller-address 0x00109d5c 0x00109e08
hostname# memory caller-address 0x009b0ef0 0x009b0f14
hostname# memory caller-address 0x00cf211c 0x00cf4464
```

```
hostname# show memory-caller address
Move down stack frame for the addresses:
pc = 0x00109d5c-0x00109e08
pc = 0x009b0ef0-0x009b0f14
pc = 0x00cf211c-0x00cf4464
```

Related Commands

Command	Description
memory profile enable	Enables the monitoring of memory usage (memory profiling).
memory profile text	Configures a text range of memory to profile.
show memory	Displays a summary of the maximum physical memory and current free memory available to the operating system.
show memory binsize	Displays summary information about the chunks allocated for a specific bin size.
show memory profile	Displays information about the memory usage (profiling) of the security appliance.
show memory-caller address	Displays the address ranges configured on the security appliance.

memory delayed-free-poisoner enable

To enable the delayed free-memory poisoner tool, use the **memory delayed-free-poisoner enable** command in privileged EXEC mode. To disable the delayed free-memory poisoner tool, use the **no** form of this command. The delayed free-memory poisoner tool lets you monitor freed memory for changes after it has been released by an application.

memory delayed-free-poisoner enable

no memory delayed-free-poisoner enable

Syntax Description

This command has no arguments or keywords.

Defaults

The **memory delayed-free-poisoner enable** command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines

Enabling the delayed free-memory poisoner tool has a significant impact on memory usage and system performance. The command should only be used under the supervision of the Cisco TAC. It should not be run in a production environment during heavy system usage.

When you enable this tool, requests to free memory by the applications running on the security appliance are written to a FIFO queue. As each request is written to the queue, each associated byte of memory that is not required by lower-level memory management is “poisoned” by being written with the value 0xcc.

The freed memory requests remain in the queue until more memory is required by an application than is in the free memory pool. When memory is needed, the first freed memory request is pulled from the queue and the poisoned memory is validated.

If the memory is unmodified, it is returned to the lower-level memory pool and the tool reissues the memory request from the application that made the initial request. The process continues until enough memory for the requesting application is freed.

If the poisoned memory has been modified, then the system forces a crash and produces diagnostic output to determine the cause of the crash.

The delayed free-memory poisoner tool periodically performs validation on all of the elements of the queue automatically. Validation can also be started manually using the **memory delayed-free-poisoner validate** command.

The **no** form of the command causes all of the memory referenced by the requests in the queue to be returned to the free memory pool without validation and any statistical counters to be cleared.

Examples

The following example enables the delayed free-memory poisoner tool:

```
hostname# memory delayed-free-poisoner enable
```

The following is sample output when the delayed free-memory poisoner tool detects illegal memory reuse:

```
delayed-free-poisoner validate failed because a
data signature is invalid at delayfree.c:328.

heap region:      0x025b1cac-0x025b1d63 (184 bytes)
memory address:   0x025b1cb4
byte offset:      8
allocated by:     0x0060b812
freed by:         0x0060ae15

Dumping 80 bytes of memory from 0x025b1c88 to 0x025b1cd7
025b1c80:          ef cd 1c a1 e1 00 00 00 | .....
025b1c90: 23 01 1c a1 b8 00 00 00 15 ae 60 00 68 ba 5e 02 | #.....`.h.^
025b1ca0: 88 1f 5b 02 12 b8 60 00 00 00 00 00 6c 26 5b 02 | ..[...`.l&[
025b1cb0: 8e a5 ea 10 ff ff ff ff cc cc cc cc cc cc cc cc | .....
025b1cc0: cc cc cc cc cc cc cc cc cc cc cc cc cc cc cc cc | .....
025b1cd0: cc cc cc cc cc cc cc cc | .....
```

An internal error occurred. Specifically, a programming assertion was violated. Copy the error message exactly as it appears, and get the output of the show version command and the contents of the configuration file. Then call your technical support representative.

```
assertion "0" failed: file "delayfree.c", line 191
```

Table 6-1 describes the significant portion of the output.

Table 6-1 *Illegal Memory Usage Output Description*

Field	Description
heap region	The address region and size of the region of memory available for use by the requesting application. This is not the same as the requested size, which may be smaller given the manner in which the system may parcel out memory at the time the memory request was made.
memory address	The location in memory where the fault was detected.
byte offset	The byte offset is relative to the beginning of the heap region and can be used to find the field that was modified if the result was used to hold a data structure starting at this address. A value of 0 or that is larger than the heap region byte count may indicate that the problem is an unexpected value in the lower level heap package.

Table 6-1 *Illegal Memory Usage Output Description*

Field	Description
allocated by/freed by	Instruction addresses where the last malloc/calloc/realloc and free calls were made involving this particular region of memory.
Dumping...	A dump of one or two regions of memory, depending upon how close the detected fault was to the beginning of the region of heap memory. The next eight bytes after any system heap header is the memory used by this tool to hold a hash of various system header values plus the queue linkage. All other bytes in the region until any system heap trailer is encountered should be set to 0xcc.

Related Commands

Command	Description
clear memory delayed-free-poisoner	Clears the delayed free-memory poisoner tool queue and statistics.
memory delayed-free-poisoner validate	Forces validation of the elements in the delayed free-memory poisoner tool queue.
show memory delayed-free-poisoner	Displays a summary of the delayed free-memory poisoner tool queue usage.

memory delayed-free-poisoner validate

To force validation of all elements in the **memory delayed-free-poisoner** queue, use the **memory delayed-free-poisoner validate** command in privileged EXEC mode.

memory delayed-free-poisoner validate

Syntax Description This command has no arguments or keywords.

Defaults No default behaviors or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines You must enable the delayed free-memory poisoner tool using the **memory delayed-free-poisoner enable** command before issuing the **memory delayed-free-poisoner validate** command.

The **memory delayed-free-poisoner validate** command causes each element of the **memory delayed-free-poisoner** queue to be validated. If an element contains unexpected values, then the system forces a crash and produces diagnostic output to determine the cause of the crash. If no unexpected values are encountered, the elements remain in the queue and are processed normally by the tool; the **memory delayed-free-poisoner validate** command does not cause the memory in the queue to be returned to the system memory pool.



Note

The delayed free-memory poisoner tool periodically performs validation on all of the elements of the queue automatically.

Examples The following example causes all elements in the **memory delayed-free-poisoner** queue to be validated:

```
hostname# memory delayed-free-poisoner validate
```

Related Commands	Command	Description
	clear memory delayed-free-poisoner	Clears the delayed free-memory poisoner tool queue and statistics.
	memory delayed-free-poisoner enable	Enables the delayed free-memory poisoner tool.
	show memory delayed-free-poisoner	Displays a summary of the delayed free-memory poisoner tool queue usage.

memory profile enable

To enable the monitoring of memory usage (memory profiling), use the **memory profile enable** command in privileged EXEC mode. To disable memory profiling, use the **no** form of this command.

memory profile enable peak *peak_value*

no memory profile enable peak *peak_value*

Syntax Description

<i>peak_value</i>	Specifies the memory usage threshold at which a snapshot of the memory usage is saved to the peak usage buffer. The contents of this buffer could be analyzed at a later time to determine the peak memory needs of the system.

Defaults

Memory profiling is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Before enabling memory profiling, you must first configure a memory text range to profile with the **memory profile text** command.

Some memory is held by the profiling system until you enter the **clear memory profile** command. See the output of the **show memory status** command.



Note

The security appliance might experience a temporary reduction in performance when memory profiling is enabled.

The following example enables memory profiling:

```
hostname# memory profile enable
```

Related Commands	Command	Description
	memory profile text	Configures a text range of memory to profile.
	show memory profile	Displays information about the memory usage (profiling) of the security appliance.

memory profile text

To configure a program text range of memory to profile, use the **memory profile text** command in privileged EXEC mode. To disable, use the **no** form of this command.

memory profile text {*startPC endPC* | **all** *resolution*}

no memory profile text {*startPC endPC* | **all** *resolution*}

Syntax Description

all	Specifies the entire text range of the memory block.
<i>endPC</i>	Specifies the end text range of the memory block.
<i>resolution</i>	Specifies the resolution of tracing for the source text region.
<i>startPC</i>	Specifies the start text range of the memory block.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	—	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

For a small text range, a resolution of “4” normally traces the call to an instruction. For a larger text range, a coarse resolution is probably enough for the first pass and the range could be narrowed down to a set of smaller regions in the next pass.

After entering the text range with the **memory profile text** command, you must then enter the **memory profile enable** command to begin memory profiling. Memory profiling is disabled by default.



Note

The security appliance might experience a temporary reduction in performance when memory profiling is enabled.

Examples

The following example shows how to configure a text range of memory to profile, with a resolution of 4:

```
hostname# memory profile text 0x004018b4 0x004169d0 4
```

The following example displays the configuration of the text range and the status of memory profiling (OFF):

```
hostname# show memory profile
InUse profiling: OFF
Peak profiling: OFF
Profile:
0x004018b4-0x004169d0 (00000004)
```

**Note**

To begin memory profiling, you must enter the **memory profile enable** command. Memory profiling is disabled by default.

Related Commands

Command	Description
clear memory profile	Clears the buffers held by the memory profiling function.
memory profile enable	Enables the monitoring of memory usage (memory profiling).
show memory profile	Displays information about the memory usage (profiling) of the security appliance.
show memory-caller address	Displays the address ranges configured on the security appliance.

memory tracking enable

To enable the tracking of heap memory request, use the **memory tracking enable** command in privileged EXEC mode. To disable memory tracking, use the **no** form of this command.

memory tracking enable

no memory tracking enable

Syntax Description

This command has no arguments or keywords.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	•	•

Command History

Release	Modification
7.0(8)	This command was introduced.

Usage Guidelines

Use the **memory tracking enable** command to track heap memory requests. To disable memory tracking, use the **no** form of this command.

Examples

The following example enables tracking heap memory requests:

```
hostname# memory tracking enable
```

Related Commands

Command	Description
clear memory tracking	Clears all currently gathered information.
show memory tracking	Shows currently allocated memory.
show memory tracking address	Lists the size, location, and topmost caller function of each currently allocated piece memory tracked by the tool.
show memory tracking dump	This command shows the size, location, partial callstack, and a memory dump of the given memory address.
show memory tracking detail	Shows various internal details to be used in gaining insight into the tool's internal behavior.

message-length

To filter GTP packets that do not meet the configured maximum and minimum length, use the **message-length** command in GTP map configuration mode, which is accessed by using the **gtp-map** command. Use the **no** form to remove the command.

message-length *min min_bytes max max_bytes*

no message-length *min min_bytes max max_bytes*

Syntax Description

max	Specifies the maximum number of bytes allowed in the UDP payload.
<i>max_bytes</i>	The maximum number of bytes in the UDP payload. The range is from 1 to 65536
min	Specifies the minimum number of bytes allowed in the UDP payload
<i>min_bytes</i>	The minimum number of bytes in the UDP payload. The range is from 1 to 65536

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
GTP map configuration	•	•	•	•	No

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The length specified by this command is the sum of the GTP header and the rest of the message, which is the payload of the UDP packet.

Examples

The following example allows messages between 20 bytes and 300 bytes in length:

```
hostname(config)# gtp-map qtp-policy
hostname(config-gtpmap)# permit message-length min 20 max 300
```


Related Commands	Commands	Description
	clear service-policy inspect gtp	Clears global GTP statistics.
	debug gtp	Displays detailed information about GTP inspection.
	gtp-map	Defines a GTP map and enables GTP map configuration mode.
	inspect gtp	Applies a specific GTP map to use for application inspection.
	show service-policy inspect gtp	Displays the GTP configuration.

mgcp-map

To identify a specific map for defining the parameters for MGCP inspection, use the **mgcp-map** command in global configuration mode. To remove the map, use the **no** form of this command.

```
mgcp-map map_name

no mgcp-map map_name
```

Syntax Description	map_name	The name of the MGCP map. The maximum number of characters is 64.

Defaults The default for the MGCP command queue is 200.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
7.0	This command was introduced.

Usage Guidelines Use the **mgcp-map** command to identify a specific map to use for defining the parameters for MGCP inspection. When you enter this command, the system enters a configuration mode that lets you enter the different commands used for defining the specific map. After defining the MGCP map, you use the **inspect mgcp** command to enable the map. You use Modular Policy Framework to apply the **inspect** command to a defined class of traffic and to apply the policy to a specific interface. The following are the commands available in MGCP map configuration mode.

- **call-agent**—Specifies a group of call agents.
- **command-queue**—Specifies the maximum number of MGCP commands that can be queued.
- **gateway**—Specifies the group of call agents that are managing a particular gateway.
- **no**—Negates a command or sets a parameter to its default value.

Examples The following example shows how to use the **mgcp-map** command to identify a specific map (mgcp-policy) to use for defining the parameters for MGCP inspection.

```
hostname(config)# mgcp-map mgcp-policy
hostname(config-mgcp-policy)#
```

The following example shows how to identify MGCP traffic, define a MGCP map, define a policy, and apply the policy to the outside interface.

You enable the MGCP inspection engine as shown in the following example, which creates a class map to match MGCP traffic on the default port (2427). The service policy is then applied to the outside interface.

```
hostname(config)# class-map mgcp-port
hostname(config-cmap)# match port tcp eq 2427
hostname(config-cmap)# exit
hostname(config)# mgcp-map mgcp_inbound
hostname(config-mgcp-map)# call-agent 10.10.11.5 101
hostname(config-mgcp-map)# call-agent 10.10.11.6 101
hostname(config-mgcp-map)# call-agent 10.10.11.7 102
hostname(config-mgcp-map)# call-agent 10.10.11.8 102
hostname(config-mgcp-map)# gateway 10.10.10.115 101
hostname(config-mgcp-map)# gateway 10.10.10.116 102
hostname(config-mgcp-map)# gateway 10.10.10.117 102
hostname(config-mgcp-map)# command-queue 150
hostname(config)# policy-map mgcp_policy
hostname(config)# mgcp-map mgcp_
hostname(config-pmap)# class mgcp-port
hostname(config-pmap-c)# inspect mgcp mgcp_inbound
hostname(config-pmap-c)# exit
hostname(config)# service-policy mgcp_policy interface outside
```

This allows call agents 10.10.11.5 and 10.10.11.6 to control gateway 10.10.10.115, and allows call agents 10.10.11.7 and 10.10.11.8 to control both gateways 10.10.10.116 and 10.10.10.117. The maximum number of MGCP commands that can be queued is 150.

To enable MGCP inspection for all interfaces, use the **global** parameter in place of **interface outside**.

Related Commands	Commands	Description
	debug mgcp	Enables the display of debug information for MGCP.
	show mgcp	Displays MGCP configuration and session information.
	timeout mgcp	Configures the idle timeout after which an MGCP media connection will be closed.
	timeout mgcp-pat	Configures the idle timeout after which an MGCP PAT xlate will be removed.

mkdir

To create a new directory, use the **mkdir** command in privileged EXEC mode.

mkdir [/noconfirm] [disk0: | disk1: | flash:]*path*

Syntax Description

noconfirm	(Optional) Suppresses the confirmation prompt.
disk0:	(Optional) Specifies the internal Flash memory, followed by a colon.
disk1:	(Optional) Specifies the external Flash memory card, followed by a colon.
flash:	(Optional) Specifies the internal Flash memory, followed by a colon. In the ASA 5500 series, the flash keyword is aliased to disk0 .
<i>path</i>	The name and path of the directory to create.

Defaults

If you do not specify a path, the directory is created in the current working directory.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If a directory with the same name already exists, then the new directory is not created.

Examples

This example shows how to make a new directory called “backup”:

```
hostname# mkdir backup
```

Related Commands

Command	Description
cd	Changes the current working directory to the one specified.
dir	Displays the directory contents.
rmdir	Removes the specified directory.
pwd	Display the current working directory.

mode

To set the security context mode to single or multiple, use the **mode** command in global configuration mode. You can partition a single security appliance into multiple virtual devices, known as security contexts. Each context behaves like an independent device, with its own security policy, interfaces, and administrators. Multiple contexts are similar to having multiple standalone appliances. In single mode, the security appliance has a single configuration and behaves as a single device. In multiple mode, you can create multiple contexts, each with its own configuration. The number of contexts allowed depends on your license.

mode {single | multiple} [noconfirm]

Syntax Description

multiple	Sets multiple context mode.
noconfirm	(Optional) Sets the mode without prompting you for confirmation. This option is useful for automated scripts.
single	Sets the context mode to single.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

In multiple context mode, the security appliance includes a configuration for each context that identifies the security policy, interfaces, and almost all the options you can configure on a stand-alone device (see the **config-url** command to identify the context configuration location). The system administrator adds and manages contexts by configuring them in the system configuration, which, like a single mode configuration, is the startup configuration. The system configuration identifies basic settings for the security appliance. The system configuration does not include any network interfaces or network settings for itself; rather, when the system needs to access network resources (such as downloading the contexts from the server), it uses one of the contexts that is designated as the admin context.

When you change the context mode using the **mode** command, you are prompted to reboot.

The context mode (single or multiple) is not stored in the configuration file, even though it does endure reboots. If you need to copy your configuration to another device, set the mode on the new device to match using the **mode** command.

When you convert from single mode to multiple mode, the security appliance converts the running configuration into two files: a new startup configuration that comprises the system configuration, and admin.cfg that comprises the admin context (in the root directory of the internal Flash memory). The original running configuration is saved as old_running.cfg (in the root directory of the internal Flash memory). The original startup configuration is not saved. The security appliance automatically adds an entry for the admin context to the system configuration with the name “admin.”

If you convert from multiple mode to single mode, you might want to first copy a full startup configuration (if available) to the security appliance; the system configuration inherited from multiple mode is not a complete functioning configuration for a single mode device.

Not all features are supported in multiple context mode. See the *Cisco Security Appliance Command Line Configuration Guide* for more information.

Examples

The following example sets the mode to multiple:

```
hostname(config)# mode multiple
WARNING: This command will change the behavior of the device
WARNING: This command will initiate a Reboot
Proceed with change mode? [confirm] y
Convert the system configuration? [confirm] y
Flash Firewall mode: multiple

***
*** --- SHUTDOWN NOW ---
***
*** Message to all terminals:
***
***   change mode

Rebooting....

Booting system, please wait...
```

The following example sets the mode to single:

```
hostname(config)# mode single
WARNING: This command will change the behavior of the device
WARNING: This command will initiate a Reboot
Proceed with change mode? [confirm] y
Flash Firewall mode: single

***
*** --- SHUTDOWN NOW ---
***
*** Message to all terminals:
***
***   change mode

Rebooting....

Booting system, please wait...
```

Related Commands	Command	Description
	context	Configures a context in the system configuration and enters context configuration mode.
	show mode	Shows the current context mode, either single or multiple.

monitor-interface

To enable health monitoring on a specific interface, use the **monitor-interface** command in global configuration mode. To disable interface monitoring, use the **no** form of this command.

monitor-interface *if_name*

no monitor-interface *if_name*

Syntax Description

if_name Specifies the name of the interface being monitored.

Defaults

Monitoring of physical interfaces is enabled by default; monitoring of logical interfaces is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The number of interfaces that can be monitored for the security appliance is 250. Hello messages are exchanged during every interface poll frequency time period between the security appliance failover pair. The failover interface poll time is 3 to 15 seconds. For example, if the poll time is set to 5 seconds, testing begins on an interface if 5 consecutive hellos are not heard on that interface (25 seconds).

Monitored failover interfaces can have the following status:

- Unknown—Initial status. This status can also mean the status cannot be determined.
- Normal—The interface is receiving traffic.
- Testing—Hello messages are not heard on the interface for five poll times.
- Link Down—The interface or VLAN is administratively down.
- No Link—The physical link for the interface is down.
- Failed—No traffic is received on the interface, yet traffic is heard on the peer interface.

In Active/Active failover, this command is only valid within a context.

Examples

The following example enables monitoring on an interface named “inside”:

```
hostname(config)# monitor-interface inside  
hostname(config)#
```

Related Commands

Command	Description
failover interface-policy	Specifies the number or percentage of monitored interface that must fail for failover to occur.
failover polltime	Specifies the interval between hello messages on an interface (Active/Standby failover).
polltime interface	Specifies the interval between hello messages on an interface (Active/Active failover).

more

To display the contents of a file, use the **more** command.

more [/ascii | /binary | /ebcdic | **disk0:** | **disk1:** | **flash:** | **ftp:** | **http:** | **https:** | **system:** | **tftp:**]*filename*

Syntax Description

/ascii	(Optional) Displays a binary file in binary mode and an ASCII file in binary mode.
/binary	(Optional) Displays any file in binary mode.
/ebcdic	(Optional) Displays binary files in EBCDIC.
disk0:	(Optional) Displays a file on the internal Flash memory.
disk1:	(Optional) Displays a file on the external Flash memory card.
flash:	(Optional) Specifies the internal Flash memory, followed by a colon. In the ASA 5500 series, the flash keyword is aliased to disk0 .
ftp:	(Optional) Displays a file on an FTP server.
http:	(Optional) Displays a file on a web site.
https:	(Optional) Displays a file on a secure web site.
system:	(Optional) Displays the file system.
tftp:	(Optional) Displays a file on a TFTP server.
<i>filename</i>	Specifies the name of the file to display.

Defaults

ASCII mode

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **more filesystem:** command prompts you to enter the alias of the local directory or file systems.

Examples

This example shows how to display the contents of a local file named “test.cfg”:

```
hostname# more test.cfg
: Saved
: Written by enable_15 at 10:04:01 Apr 14 2005
```

```

XXX Version X.X(X)
nameif vlan300 outside security10
enable password 8Ry2YjIyt7RRXU24 encrypted
passwd 2KFQnbNIdI.2KYOU encrypted
hostname test
fixup protocol ftp 21
fixup protocol h323 H225 1720
fixup protocol h323 ras 1718-1719
fixup protocol ils 389
fixup protocol rsh 514
fixup protocol smtp 25
fixup protocol sqlnet 1521
fixup protocol sip 5060
fixup protocol skinny 2000
names
access-list deny-flow-max 4096
access-list alert-interval 300
access-list 100 extended permit icmp any any
access-list 100 extended permit ip any any
pager lines 24
icmp permit any outside
mtu outside 1500
ip address outside 172.29.145.35 255.255.0.0
no asdm history enable
arp timeout 14400
access-group 100 in interface outside
!
interface outside
!
route outside 0.0.0.0 0.0.0.0 172.29.145.1 1
timeout xlate 3:00:00
timeout conn 1:00:00 half-closed 0:10:00 udp 0:02:00 icmp 0:00:02 rpc 0:10:00 h3
23 0:05:00 h225 1:00:00 mgcp 0:05:00 sip 0:30:00 sip_media 0:02:00
timeout uauth 0:05:00 absolute
aaa-server TACACS+ protocol tacacs+
aaa-server RADIUS protocol radius
aaa-server LOCAL protocol local
snmp-server host outside 128.107.128.179
snmp-server location my_context, USA
snmp-server contact admin@my_context.com
snmp-server community public
no snmp-server enable traps
floodguard enable
fragment size 200 outside
no sysopt route dnat
telnet timeout 5
ssh timeout 5
terminal width 511
gdb enable
mgcp command-queue 0
Cryptochecksum:00000000000000000000000000000000
: end

```

Related Commands

Command	Description
cd	Changes to the specified directory.
pwd	Displays the current working directory.

mroute

To configure a static multicast route, use the **mroute** command in global configuration mode. To remove a static multicast route, use the **no** form of this command.

mroute *src smask in_if_name* [**dense** *output_if_name*] [*distance*]

no mroute *src smask in_if_name* [**dense** *output_if_name*] [*distance*]

Syntax Description

dense <i>output_if_name</i>	(Optional) The interface name for dense mode output. The dense <i>output_if_name</i> keyword and argument pair is only supported for SMR stub multicast routing (igmp forwarding).
<i>distance</i>	(Optional) The administrative distance of the route. Routes with lower distances have preference. The default is 0.
<i>in_if_name</i>	Specifies the incoming interface name for the mroute.
<i>smask</i>	Specifies the multicast source network address mask.
<i>src</i>	Specifies the IP address of the multicast source.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

This command lets you statically configure where multicast sources are located. The security appliance expects to receive multicast packets on the same interface as it would use to send unicast packets to a specific source. In some cases, such as bypassing a route that does not support multicast routing, multicast packets may take a different path than the unicast packets.

Static multicast routes are not advertised or redistributed.

Use the **show mroute** command displays the contents of the multicast route table. Use the **show running-config mroute** command to display the mroute commands in the running configuration.

Examples

The following example shows how configure a static multicast route using the **mroute** command:

```
hostname(config)# mroute 172.16.0.0 255.255.0.0 inside
```

Related Commands

Command	Description
clear configure mroute	Removes the mroute commands from the configuration.
show mroute	Displays the IPv4 multicast routing table.
show running-config mroute	Displays the mroute commands in the configuration.

mtu

To specify the maximum transmission unit for an interface, use the **mtu** command in global configuration mode. To reset the MTU block size to 1500 for Ethernet interfaces, use the **no** form of this command. This command supports IPv4 and IPv6 traffic.

mtu *interface_name* *bytes*

no mtu *interface_name* *bytes*

Syntax Description

<i>bytes</i>	Number of bytes in the MTU; valid values are from 64 to 65,535 bytes.
<i>interface_name</i>	Internal or external network interface name.

Defaults

The default *bytes* is 1500 for Ethernet interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	—	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **mtu** command lets you to set the data size that is sent on a connection. Data that is larger than the MTU value is fragmented before being sent.

The security appliance supports IP path MTU discovery (as defined in RFC 1191), which allows a host to dynamically discover and cope with the differences in the maximum allowable MTU size of the various links along the path. Sometimes, the security appliance cannot forward a datagram because the packet is larger than the MTU that you set for the interface, but the “don’t fragment” (DF) bit is set. The network software sends a message to the sending host, alerting it to the problem. The host has to fragment packets for the destination so that they fit the smallest packet size of all the links along the path.

The default MTU is 1500 bytes in a block for Ethernet interfaces (which is also the maximum). This value is sufficient for most applications, but you can pick a lower number if network conditions require it.

When using the Layer 2 Tunneling Protocol (L2TP), we recommend that you set the MTU size to 1380 to account for the L2TP header and IPSec header length.

Examples

This example shows how to specify the MTU for an interface:

```
hostname(config)# show running-config mtu  
mtu outside 1500  
mtu inside 1500  
hostname(config)# mtu inside 8192  
hostname(config)# show running-config mtu  
mtu outside 1500  
mtu inside 8192
```

Related Commands

Command	Description
clear configure mtu	Clears the configured maximum transmission unit values on all interfaces.
show running-config mtu	Displays the current maximum transmission unit block size.

multicast-routing

To enable IP multicast routing on the security appliance, use the **multicast routing** command in global configuration mode. To disable IP multicast routing, use the **no** form of this command.

multicast-routing

no multicast-routing

Syntax Description

This command has no arguments or keywords.

Defaults

The **multicast-routing** command enables PIM and IGMP on all interfaces by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **multicast-routing** command enables PIM and IGMP on all interfaces.



Note

PIM is not supported with PAT. The PIM protocol does not use ports and PAT only works with protocols that use ports.

If the security appliance is the PIM RP, use the untranslated outside address of the security appliance as the RP address.

The number of entries in the multicast routing tables are limited by the amount of RAM on the system. [Table 6-1](#) lists the maximum number of entries for specific multicast tables based on the amount of RAM on the security appliance. Once these limits are reached, any new entries are discarded.

Table 6-2 Entry Limits for Multicast Tables

Table	16 MB	128 MB	128+ MB
MFIB	1000	3000	5000
IGMP Groups	1000	3000	5000
PIM Routes	3000	7000	12000

Examples

The following example enables IP multicast routing on the security appliance:

```
hostname(config)# multicast-routing
```

Related Commands

Command	Description
igmp	Enables IGMP on an interface.
pim	Enables PIM on an interface.

name

To associate a name with an IP address, use the **name** command in global configuration mode. To disable the use of the text names but not remove them from the configuration, use the **no** form of this command.

name *ip_address name*

no name *ip_address [name]*

Syntax Description

<i>ip_address</i>	Specifies an IP address of the host that is named.
<i>name</i>	Specifies the name assigned to the IP address. Use characters a to z, A to Z, 0 to 9, a dash, and an underscore. The <i>name</i> must be 63 characters or less. Also, the <i>name</i> cannot start with a number.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To enable the association of a name with an IP address, use the **names** command. You can associate only one name with an IP address.

You must first use the **names** command before you use the **name** command. Use the **name** command immediately after you use the **names** command and before you use the **write memory** command.

The **name** command lets you identify a host by a text name and map text strings to IP addresses. The **no name** command allows you to disable the use of the text names but does not remove them from the configuration. Use the **clear configure name** command to clear the list of names from the configuration.

If you are using both ASDM and the command line to manage the security appliance, when you add a **name** command using the command line interface you should also add an **asdm location** command specifying the same IP address. If you do not, ASDM will not display the named object. For example, the following commands will cause the 10.1.1.0 network, named “finance”, to appear in the Hosts/Networks list in ASDM:

```
hostname(config)# name finance 10.1.1.0
hostname(config)# asdm location 10.1.1.0 255.255.255.0 inside
```

To disable displaying **name** values, use the **no names** command.

Both the **name** and **names** commands are saved in the configuration.

The **name** command does not support assigning a name to a network mask. For example, this command would be rejected:

```
hostname(config)# name 255.255.255.0 class-C-mask
```


Note

None of the commands in which a mask is required can process a name as an accepted network mask.

Examples

This example shows that the **names** command allows you to enable use of the **name** command. The **name** command substitutes **sa_inside** for references to 192.168.42.3 and **sa_outside** for 209.165.201.3. You can use these names with the **ip address** commands when assigning IP addresses to the network interfaces. The **no names** command disables the **name** command values from displaying. Subsequent use of the **names** command again restores the **name** command value display.

```
hostname(config)# names
hostname(config)# name 192.168.42.3 sa_inside
hostname(config)# name 209.165.201.3 sa_outside

hostname(config-if)# ip address inside sa_inside 255.255.255.0
hostname(config-if)# ip address outside sa_outside 255.255.255.224

hostname(config)# show ip address
System IP Addresses:
    inside ip address sa_inside mask 255.255.255.0
    outside ip address sa_outside mask 255.255.255.224

hostname(config)# no names
hostname(config)# show ip address
System IP Addresses:
    inside ip address 192.168.42.3 mask 255.255.255.0
    outside ip address 209.165.201.3 mask 255.255.255.224

hostname(config)# names
hostname(config)# show ip address
System IP Addresses:
    inside ip address sa_inside mask 255.255.255.0
    outside ip address sa_outside mask 255.255.255.224
```

Related Commands

Command	Description
clear configure name	Clears the list of names from the configuration.
names	Enables the association of a name with an IP address.
show running-config name	Displays the names associated with an IP address.

nameif

To provide a name for an interface, use the **nameif** command in interface configuration mode. To remove the name, use the **no** form of this command. The interface name is used in all configuration commands on the security appliance instead of the interface type and ID (such as gigabitethernet0/1), and is therefore required before traffic can pass through the interface.

nameif *name*

no nameif

Syntax Description

name Sets a name up to 48 characters in length. The name is not case-sensitive.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was changed from a global configuration command to an interface configuration mode command.

Usage Guidelines

For subinterfaces, you must assign a VLAN with the **vlan** command before you enter the **nameif** command.

You can change the name by reentering this command with a new value. Do not enter the **no** form, because that command causes all commands that refer to that name to be deleted.

Examples

The following example configures the names for two interfaces to be “inside” and “outside:”

```
hostname(config)# interface gigabitethernet0/1
hostname(config-if)# nameif inside
hostname(config-if)# security-level 100
hostname(config-if)# ip address 10.1.1.1 255.255.255.0
hostname(config-if)# no shutdown
hostname(config-if)# interface gigabitethernet0/0
hostname(config-if)# nameif outside
hostname(config-if)# security-level 0
hostname(config-if)# ip address 10.1.2.1 255.255.255.0
hostname(config-if)# no shutdown
```

Related Commands

Command	Description
clear xlate	Resets all translations for existing connections, causing the connections to be reset.
interface	Configures an interface and enters interface configuration mode.
security-level	Sets the security level for the interface.
vlan	Assigns a VLAN ID to a subinterface.

names

To enable the association of a name with an IP address, use the **names** command in global configuration mode. You can associate only one name with an IP address. To disable displaying **name** values, use the **no names** command.

names

no names

Syntax Description

This command has no arguments or keywords.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **names** command is used to enable the association of a name with an IP address that you configured with the **name** command. The order in which you enter the **name** or **names** commands is irrelevant.

Examples

The following example shows how to enable the association of a name with an IP address:

```
hostname(config)# names
```

Related Commands

Command	Description
clear configure name	Clears the list of names from the configuration.
name	Associates a name with an IP address.
show running-config name	Displays a list of names associated with IP addresses.
show running-config names	Displays the IP address-to-name conversions.

name-separator

To specify a character as a delimiter between the e-mail and VPN username and password, use the **name-separator** command in the applicable e-mail proxy mode. To revert to the default, “:”, use the **no** version of this command.

name-separator [*symbol*]

no name-separator

Syntax Description

symbol	(Optional) The character that separates the e-mail and VPN usernames and passwords. Choices are “@,” (at), “ ” (pipe), “:”(colon), “#” (hash), “,” (comma), and “;” (semi-colon).

Defaults

The default is “:” (colon).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Pop3s	•	—	•	—	—
Imap4s	•	—	•	—	—
Smtps	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The name separator must be different from the server separator.

Examples

The following example shows how to set a hash (#) as the name separator for POP3S:

```
hostname(config)# pop3s
hostname(config-pop3s)# name-separator #
```

Related Commands

Command	Description
server-separator	Separates the e-mail and server names.

nat

To identify addresses on one interface that are translated to mapped addresses on another interface, use the **nat** command in global configuration mode. This command configures dynamic NAT or PAT, where an address is translated to one of a pool of mapped addresses. To remove the **nat** command, use the **no** form of this command.

For regular dynamic NAT:

```
nat (real_ifc) nat_id real_ip [mask [dns] [outside] [[tcp] tcp_max_conns [emb_limit]
[norandomseq]]] [udp udp_max_conns]

no nat (real_ifc) nat_id real_ip [mask [dns] [outside] [[tcp] tcp_max_conns [emb_limit]
[norandomseq]]] [udp udp_max_conns]
```

For policy dynamic NAT and NAT exemption:

```
nat (real_ifc) nat_id access-list access_list_name [dns] [outside] [[tcp] tcp_max_conns
[emb_limit] [norandomseq]]] [udp udp_max_conns]

no nat (real_ifc) nat_id access-list access_list_name [dns] [outside] [[tcp] tcp_max_conns
[emb_limit] [norandomseq]]] [udp udp_max_conns]
```

Syntax Description

access-list <i>access_list_name</i>	Identifies the local addresses and destination addresses using an extended access list, also known as policy NAT. Create the access list using the access-list command. You can optionally specify the local and destination ports in the access list using the eq operator. If the NAT ID is 0, then the access list specifies addresses that are exempt from NAT. NAT exemption is not the same as policy NAT; you cannot specify the port addresses, for example. Note Access list hit counts, as shown by the show access-list command, do not increment for NAT exemption access lists.
dns	(Optional) Rewrites the A record, or address record, in DNS replies that match this command. For DNS replies traversing from a mapped interface to a real interface, the A record is rewritten from the mapped value to the real value. Inversely, for DNS replies traversing from a real interface to a mapped interface, the A record is rewritten from the real value to the mapped value. If your NAT statement includes the address of a host that has an entry in a DNS server, and the DNS server is on a different interface from a client, then the client and the DNS server need different addresses for the host; one needs the global address and one needs the local address. The translated host needs to be on the same interface as either the client or the DNS server. Typically, hosts that need to allow access from other interfaces use a static translation, so this option is more likely to be used with the static command.

<i>emb_limit</i>	(Optional) Specifies the maximum number of embryonic connections per host. The default is 0, which means unlimited embryonic connections. Limiting the number of embryonic connections protects you from a DoS attack. The security appliance uses the embryonic limit to trigger TCP Intercept, which protects inside systems from a DoS attack perpetrated by flooding an interface with TCP SYN packets. An embryonic connection is a connection request that has not finished the necessary handshake between source and destination. This option does not apply to outside NAT. The TCP intercept feature applies only to hosts or servers on a higher security level. If you set the embryonic limit for outside NAT, the embryonic limit is ignored.
<i>real_ifc</i>	Specifies the name of the interface connected to the real IP address network.
<i>real_ip</i>	Specifies the real address that you want to translate. You can use 0.0.0.0 (or the abbreviation 0) to specify all addresses.
<i>mask</i>	(Optional) Specifies the subnet mask for the real addresses. If you do not enter a mask, then the default mask for the IP address class is used.
<i>nat_id</i>	Specifies an integer for the NAT ID. For regular NAT, this integer is between 1 and 2147483647. For policy NAT (nat id access-list), this integer is between 1 and 65535. Identity NAT (nat 0) and NAT exemption (nat 0 access-list) use the NAT ID of 0. This ID is referenced by the global command to associate a global pool with the <i>real_ip</i>.
norandomseq	(Optional) Disables TCP ISN randomization protection. Each TCP connection has two ISNs: one generated by the client and one generated by the server. The security appliance randomizes the ISN of the TCP SYN passing in both the inbound and outbound directions. Randomizing the ISN of the protected host prevents an attacker from predicting the next ISN for a new connection and potentially hijacking the new session. TCP initial sequence number randomization can be disabled if required. For example: • If another in-line firewall is also randomizing the initial sequence numbers, there is no need for both firewalls to be performing this action, even though this action does not affect the traffic. • If you use eBGP multi-hop through the security appliance, and the eBGP peers are using MD5. Randomization breaks the MD5 checksum. • You use a WAAS device that requires the security appliance not to randomize the sequence numbers of connections.
outside	(Optional) If this interface is on a lower security level than the interface you identify by the matching global statement, then you must enter outside. This feature is called outside NAT or bidirectional NAT.

tcp <i>tcp_max_conns</i>	Specifies the maximum number of simultaneous TCP and UDP connections for the entire subnet. The default is 0, which means unlimited connections. (Idle connections are closed after the idle timeout specified by the timeout conn command.) This option does not apply to outside NAT. The security appliance only tracks connections from a higher security interface to a lower security interface.
udp <i>udp_max_conns</i>	(Optional) Used with the udp keyword to set the maximum number of simultaneous UDP connections the <i>real_ip</i> hosts are each allowed to use.

Defaults

The default value for *tcp_max_conns*, *emb_limit*, and *udp_max_conns* is 0 (unlimited), which is the maximum available.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

For dynamic NAT and PAT, you first configure a **nat** command identifying the real addresses on a given interface that you want to translate. Then you configure a separate **global** command to specify the mapped addresses when exiting another interface (in the case of PAT, this is one address). Each **nat** command matches a **global** command by comparing the NAT ID, a number that you assign to each command.

The security appliance translates an address when a NAT rule matches the traffic. If no NAT rule matches, processing for the packet continues. The exception is when you enable NAT control using the **nat-control** command. NAT control requires that packets traversing from a higher security interface (inside) to a lower security interface (outside) match a NAT rule, or else processing for the packet stops. NAT is not required between same security level interfaces even if you enable NAT control. You can optionally configure NAT if desired.

Dynamic NAT translates a group of real addresses to a pool of mapped addresses that are routable on the destination network. The mapped pool can include fewer addresses than the real group. When a host you want to translate accesses the destination network, the security appliance assigns it an IP address from the mapped pool. The translation is added only when the real host initiates the connection. The translation is in place only for the duration of the connection, and a given user does not keep the same IP address after the translation times out (see the **timeout xlate** command). Users on the destination network, therefore, cannot reliably initiate a connection to a host that uses dynamic NAT (or PAT, even if the connection is allowed by an access list), and the security appliance rejects any attempt to connect to a real host address directly. See the **static** command for reliable access to hosts.

Dynamic NAT has these disadvantages:

- If the mapped pool has fewer addresses than the real group, you could run out of addresses if the amount of traffic is more than expected.

Use PAT if this event occurs often, because PAT provides over 64,000 translations using ports of a single address.

- You have to use a large number of routable addresses in the mapped pool; if the destination network requires registered addresses, such as the Internet, you might encounter a shortage of usable addresses.

The advantage of dynamic NAT is that some protocols cannot use PAT. For example, PAT does not work with IP protocols that do not have a port to overload, such as GRE version 0. PAT also does not work with some applications that have a data stream on one port and the control path on another and are not open standard, such as some multimedia applications.

PAT translates multiple real addresses to a single mapped IP address. Specifically, the security appliance translates the real address and source port (real socket) to the mapped address and a unique port above 1024 (mapped socket). Each connection requires a separate translation, because the source port differs for each connection. For example, 10.1.1.1:1025 requires a separate translation from 10.1.1.1:1026.

After the connection expires, the port translation also expires after 30 seconds of inactivity. The timeout is not configurable.

PAT lets you use a single mapped address, thus conserving routable addresses. You can even use the security appliance interface IP address as the PAT address. PAT does not work with some multimedia applications that have a data stream that is different from the control path.

**Note**

For the duration of the translation, a remote host can initiate a connection to the translated host if an access list allows it. Because the address (both real and mapped) is unpredictable, a connection to the host is unlikely. However in this case, you can rely on the security of the access list.

If you enable NAT control, then inside hosts must match a NAT rule when accessing outside hosts. If you do not want to perform NAT for some hosts, then you can bypass NAT for those hosts (alternatively, you can disable NAT control). You might want to bypass NAT, for example, if you are using an application that does not support NAT. You can use the **static** command to bypass NAT, or one of the following options:

- Identity NAT (**nat 0** command)—When you configure identity NAT (which is similar to dynamic NAT), you do not limit translation for a host on specific interfaces; you must use identity NAT for connections through all interfaces. Therefore, you cannot choose to perform normal translation on real addresses when you access interface A, but use identity NAT when accessing interface B. Regular dynamic NAT, on the other hand, lets you specify a particular interface on which to translate the addresses. Make sure that the real addresses for which you use identity NAT are routable on all networks that are available according to your access lists.

For identity NAT, even though the mapped address is the same as the real address, you cannot initiate a connection from the outside to the inside (even if the interface access list allows it). Use static identity NAT or NAT exemption for this functionality.

- NAT exemption (**nat 0 access-list** command)—NAT exemption allows both translated and remote hosts to initiate connections. Like identity NAT, you do not limit translation for a host on specific interfaces; you must use NAT exemption for connections through all interfaces. However, NAT exemption does let you specify the real and destination addresses when determining the real addresses to translate (similar to policy NAT), so you have greater control using NAT exemption. However unlike policy NAT, NAT exemption does not consider the ports in the access list.

Policy NAT lets you identify real addresses for address translation by specifying the source and destination addresses in an extended access list. You can also optionally specify the source and destination ports. Regular NAT can only consider the real addresses. For example, you can translate the real address to mapped address A when it accesses server A, but translate the real address to mapped address B when it accesses server B.

When you specify the ports in policy NAT for applications that require application inspection for secondary channels (FTP, VoIP, etc.), the security appliance automatically translates the secondary ports.



Note

All types of NAT support policy NAT except for NAT exemption. NAT exemption uses an access list to identify the real addresses, but differs from policy NAT in that the ports are not considered. You can accomplish the same result as NAT exemption using **static** identity NAT, which does support policy NAT.

You can alternatively configure maximum connections, maximum embryonic connections, and TCP sequence randomization using the **set connection** commands. If you configure these settings for the same traffic using both methods, then the security appliance uses the lower limit. For TCP sequence randomization, if it is disabled using either method, then the security appliance disables TCP sequence randomization.

If you change the NAT configuration, and you do not want to wait for existing translations to time out before the new NAT information is used, you can clear the translation table using **clear xlate** command. However, clearing the translation table disconnects all of the current connections.

Examples

For example, to translate the 10.1.1.0/24 network on the inside interface, enter the following command:

```
hostname(config)# nat (inside) 1 10.1.1.0 255.255.255.0
hostname(config)# global (outside) 1 209.165.201.1-209.165.201.30
```

To identify a pool of addresses for dynamic NAT as well as a PAT address for when the NAT pool is exhausted, enter the following commands:

```
hostname(config)# nat (inside) 1 10.1.1.0 255.255.255.0
hostname(config)# global (outside) 1 209.165.201.5
hostname(config)# global (outside) 1 209.165.201.10-209.165.201.20
```

To translate the lower security dmz network addresses so they appear to be on the same network as the inside network (10.1.1.0), for example, to simplify routing, enter the following commands:

```
hostname(config)# nat (dmz) 1 10.1.2.0 255.255.255.0 outside dns
hostname(config)# global (inside) 1 10.1.1.45
```

To identify a single real address with two different destination addresses using policy NAT, enter the following commands:

```
hostname(config)# access-list NET1 permit ip 10.1.2.0 255.255.255.0 209.165.201.0
255.255.255.224
hostname(config)# access-list NET2 permit ip 10.1.2.0 255.255.255.0 209.165.200.224
255.255.255.224
hostname(config)# nat (inside) 1 access-list NET1 tcp 0 2000 udp 10000
hostname(config)# global (outside) 1 209.165.202.129
hostname(config)# nat (inside) 2 access-list NET2 tcp 1000 500 udp 2000
hostname(config)# global (outside) 2 209.165.202.130
```

To identify a single real address/destination address pair that use different ports using policy NAT, enter the following commands:

```
hostname(config)# access-list WEB permit tcp 10.1.2.0 255.255.255.0 209.165.201.11
255.255.255.255 eq 80
```

```

hostname(config)# access-list TELNET permit tcp 10.1.2.0 255.255.255.0 209.165.201.11
255.255.255.255 eq 23
hostname(config)# nat (inside) 1 access-list WEB
hostname(config)# global (outside) 1 209.165.202.129
hostname(config)# nat (inside) 2 access-list TELNET
hostname(config)# global (outside) 2 209.165.202.130

```

Related Commands

Command	Description
access-list deny-flow-max	Specifies the maximum number of concurrent deny flows that can be created.
clear configure nat	Removes the NAT configuration.
global	Creates entries from a pool of global addresses.
interface	Creates and configures an interface.
show running-config nat	Displays a pool of global IP addresses that are associated with the network.

nat (vpn load-balancing)

To set the IP address to which NAT translates the IP address of this device, use the **nat** command in VPN load-balancing mode. To disable this NAT translation, use the **no** form of this command.

nat *ip-address*

no nat [*ip-address*]

Syntax Description

ip-address The IP address to which you want this NAT to translate the IP address of this device.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
VPN load-balancing	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must first use the **vpn load-balancing** command to enter VPN load-balancing mode.

In the **no nat** form of the command, if you specify the optional *ip-address* value, the IP address must match the existing NAT IP address in the running configuration.

Examples

The following is an example of a VPN load-balancing command sequence that includes a **nat** command that sets the NAT-translated address to 192.168.10.10:

```
hostname(config)# interface GigabitEthernet 0/1
hostname(config-if)# ip address 209.165.202.159 255.255.255.0
hostname(config)# nameif test
hostname(config)# interface GigabitEthernet 0/2
hostname(config-if)# ip address 209.165.201.30 255.255.255.0
hostname(config)# nameif foo
hostname(config)# vpn load-balancing
hostname(config-load-balancing)# nat 192.168.10.10
hostname(config-load-balancing)# priority 9
hostname(config-load-balancing)# interface lbpublic test
hostname(config-load-balancing)# interface lbprivate foo
hostname(config-load-balancing)# cluster ip address 209.165.202.224
hostname(config-load-balancing)# cluster port 9023
```

```
hostname(config-load-balancing) # participate
```

Related Commands

Command	Description
vpn load-balancing	Enter VPN load-balancing mode.

nat-control

To enforce NAT control, use the **nat-control** command in global configuration mode. To disable NAT control, which allows inside hosts to communicate with outside networks without configuring a NAT rule, use the **no** form of this command.

nat-control

no nat-control

Syntax Description

This command has no arguments or keywords.

Defaults

NAT control is disabled by default (**no nat-control** command).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If **nat-control** is enabled, you must configure a NAT rule before an inside host can communicate with any outside networks. The **no nat-control** command allows inside hosts to communicate with outside networks without configuring a NAT rule. Only hosts that undergo NAT need to have a NAT rule configured.

The difference between the **no nat-control** command and the **nat 0** (identity NAT) command is that identity NAT requires that traffic be initiated from the local host. The **no nat-control** command does not have this requirement, nor does it require a static command to allow communication to inside hosts.

Disabling NAT control is similar to the same security level communication feature, which allows communication between two interfaces of the same security level without configuring a NAT rule, except that the NAT control feature is between hosts instead of interfaces.

No new NAT functionality is provided with this feature. All existing NAT functionality remains the same.



Note

In multiple context mode, the packet classifier relies on the NAT configuration in some cases to assign packets to contexts. If you do not perform NAT because NAT control is disabled, then the classifier might require changes in your network configuration.

If you want the added security of NAT control but do not want to translate inside addresses in some cases, you can apply a NAT exemption (**nat 0 access-list**) or identity NAT (**nat 0** or **static**) rule on those addresses.

When NAT control is disabled with the **no-nat control** command, and a NAT and a global command pair are configured for an interface, the real IP addresses cannot go out on other interfaces unless you define those destinations with the **nat 0 access-list** command.

For example, the following NAT is the that one you want performed when going to the outside network:

```
nat (inside) 1 0.0.0.0 0.0.0.0
global (outside) 1 209.165.201.2
```

The above configuration catches everything on the inside network, so if you do not want to translate inside addresses when they go to the DMZ, then you need to match that traffic for NAT exemption, as shown in the following example:

```
access-list EXEMPT extended permit ip any 192.168.1.0 255.255.255.0
access-list EXEMPT remark This matches any traffic going to DMZ1
access-list EXEMPT extended permit ip any 10.1.1.0 255.255.255.0
access-list EXEMPT remark This matches any traffic going to DMZ1
nat (inside) 0 access-list EXEMPT
```

Alternately, you can perform NAT translation on all interfaces:

```
nat (inside) 1 0.0.0.0 0.0.0.0
global (outside) 1 209.165.201.2
global (dmz1) 1 192.168.1.230
global (dmz2) 1 10.1.1.230
```

The following table compares the results between **nat-control** and **no nat-control**:

Condition	nat-control	no nat-control
- no inside NAT rule - no outside NAT rule	deny	continue
- inside NAT rule - no outside NAT rule (no dynamic outside NAT)	continue	continue
- inside NAT rule - no outside NAT rule (dynamic outside NAT)¹	deny	continue

1. Dynamic outside NAT is enabled at an interface if a **nat** command with the keyword **outside** is associated with the interface

Two NAT policies are used to perform address translation on each packet that traverses the security appliance, an inside NAT policy and an outside NAT policy. If the **nat-control** command is enabled, each inside address must have an inside NAT rule before communication is permitted through the security appliance. Additionally, if outside dynamic NAT is enabled on an interface, each outside address must have an outside NAT rule before communication is permitted through the security appliance.

If the **no nat-control** command is configured and no NAT policy matches, an address rewrite is not performed and processing continues. The default is NAT control disabled (**no nat-control** command).

Note: To ensure backward compatibility, the **nat-control** command is automatically enabled if the startup configuration is six or lower.

Examples

The following example enables **nat-control**:

```
hostname(config)# nat-control
```

Related Commands

Command	Description
nat	Defines an address on one interface that is translated to a global address on another interface.
show running-config nat-control	Shows the NAT configuration requirement.

nbns-server

To configure an NBNS server, use the **nbns-server** command in webvpn mode. To remove the NBNS server from the configuration, use the **no** form of this command.

The security appliance queries NBNS servers to map NetBIOS names to IP addresses. WebVPN requires NetBIOS to access or share files on remote systems.

nbns-server {*ipaddr or hostname*} [master] [timeout *timeout*] [retry *retries*]

no nbns-server

Syntax Description

hostname	Specifies the hostname for the NBNS server.
ipaddr	Specifies the IP address for the NBNS server.
master	Indicates that this is a master browser, rather than a WINS server.
retry	Indicates that a retry value follows.
retries	Specifies the number of times to retry queries to NBNS servers. The security appliance recycles through the list of servers the number of times you specify here before sending an error message. The default value is 2; the range is 1 to 10.
timeout	Indicates that a timeout value follows.
timeout	Specifies the amount of time the security appliance waits before sending the query again, to the same server if there is only one, or another server if there are multiple NBNS servers. The default timeout is 2 seconds; the range is 1 to 30 seconds.

Defaults

No NBNS server is configured by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Webvpn	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Maximum of 3 server entries. The first server you configure is the primary server, and the others are backups, for redundancy.

Use the **no** option to remove the matching entry from the configuration.

Examples

The following example shows how to configure an NBNS server that is a master browser with an IP address of 10.10.10.19, a timeout value of 10 seconds, and 8 retries. It also shows how to configure an NBNS WINS server with an IP address of 10.10.10.24, a timeout value of 15 seconds, and 8 retries.

```
hostname(config)# webvpn
hostname(config-webvpn)# nbns-server 10.10.10.19 master timeout 10 retry 8
hostname(config-webvpn)# nbns-server 10.10.10.24 timeout 15 retry 8
```

neighbor

To define a static neighbor on a point-to-point, non-broadcast network, use the **neighbor** command in router configuration mode. To remove the statically defined neighbor from the configuration, use the **no** form of this command. The **neighbor** command is used to advertise OSPF routes over VPN tunnels.

neighbor *ip_address* [*interface name*]

no neighbor *ip_address* [*interface name*]

Syntax Description

interface name	(Optional) The interface name, as specified by the nameif command, through which the neighbor can be reached.
ip_address	IP address of the neighbor router.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

One neighbor entry must be included for each known non-broadcast network neighbor. The neighbor address must be on the primary address of the interface.

The **interface** option needs to be specified when the neighbor is not on the same network as any of the directly connected interfaces of the system. Additionally, a static route must be created to reach the neighbor.

Examples

The following example defines a neighbor router with an address of 192.168.1.1:

```
hostname(config-router)# neighbor 192.168.1.1
```

Related Commands	Command	Description
	router ospf	Enters router configuration mode.
	show running-config	Displays the commands in the global router configuration.
	router	

nem

To enable network extension mode for hardware clients, use the **nem enable** command in group-policy configuration mode. To disable NEM, use the **nem disable** command. To remove the NEM attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a value from another group policy.

nem {enable | disable}

no nem

Syntax Description

disable	Disables Network Extension Mode.
enable	Enables Network Extension Mode.

Defaults

Network extension mode is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—

Usage Guidelines

Network Extension mode lets hardware clients present a single, routable network to the remote private network over the VPN tunnel. IPSec encapsulates all traffic from the private network behind the hardware client to networks behind the security appliance. PAT does not apply. Therefore, devices behind the security appliance have direct access to devices on the private network behind the hardware client over the tunnel, and only over the tunnel, and vice versa. The hardware client must initiate the tunnel, but after the tunnel is up, either side can initiate data exchange.

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to set NEM for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# nem enable
```

network area

To define the interfaces on which OSPF runs and to define the area ID for those interfaces, use the **network area** command in router configuration mode. To disable OSPF routing for interfaces defined with the address/netmask pair, use the **no** form of this command.

network *addr mask area area_id*

no network *addr mask area area_id*

Syntax Description

<i>addr</i>	IP address.
area <i>area_id</i>	Specifies the area that is to be associated with the OSPF address range. The <i>area_id</i> can be specified in either IP address format or in decimal format. When specified in decimal format, valid values range from 0 to 4294967295.
<i>mask</i>	The network mask.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

For OSPF to operate on the interface, the address of the interface must be covered by the **network area** command. If the **network area** command does not cover the IP address of the interface, it will not enable OSPF over that interface.

There is no limit to the number of **network area** commands you can use on the security appliance.

Examples

The following example enables OSPF on the 192.168.1.1 interface and assigns it to area 2:

```
hostname(config-router)# network 192.168.1.1 255.255.255.0 area 2
```


Related Commands	Command	Description
	router ospf	Enters router configuration mode.
	show running-config router	Displays the commands in the global router configuration.

network-object

To add a network object to a network object group, use the **network-object** command in network configuration mode. To remove network objects, use the **no** form of this command.

network-object host *host_addr* | *host_name*

no network-object host *host_addr* | *host_name*

network-object *net_addr netmask*

no network-object *net_addr netmask*

Syntax Description

host_addr	Host IP address (if the host name is not already defined using the name command).
host_name	Host name (if the host name is defined using the name command).
net_addr	Network address; used with <i>netmask</i> to define a subnet object.
netmask	Netmask; used with <i>net_addr</i> to define a subnet object.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Network configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **network-object** command is used with the [object-group](#) command to define a host or a subnet object in network configuration mode.

Examples

The following example shows how to use the **network-object** command in network configuration mode to create a new network object group:

```
hostname(config)# object-group network sjj_eng_ftp_servers
hostname(config-network)# network-object host sjj.eng.ftp
hostname(config-network)# network-object host 172.16.56.195
hostname(config-network)# network-object 192.168.1.0 255.255.255.224
hostname(config-network)# group-object sjc_eng_ftp_servers
hostname(config-network)# quit
```

```
hostname(config)#
```

Related Commands

Command	Description
clear configure object-group	Removes all the object-group commands from the configuration.
group-object	Adds network object groups.
object-group	Defines object groups to optimize your configuration.
port-object	Adds a port object to a service object group.
show running-config object-group	Displays the current object groups.

nt-auth-domain-controller

To specify the name of the NT Primary Domain Controller for this server, use the **nt-auth-domain-controller** command in AAA-server host mode. To remove this specification, use the **no** form of this command:

nt-auth-domain-controller *string*

no nt-auth-domain-controller

Syntax Description

<i>string</i>	Specify the name, up to 16 characters long, of the Primary Domain Controller for this server.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
AAA-server host	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is valid only for NT Authentication AAA servers. You must have first used the **aaa-server host** command to enter host configuration mode. The name in the *string* variable must match the NT entry on the server itself.

Examples

The following example configures the name of the NT Primary Domain Controller for this server as “primary1”.

```
hostname(config)# aaa-server svrgrp1 protocol nt
hostname(config-aaa-server-group)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# nt-auth-domain-controller primary1
```

Related Commands

Command	Description
aaa server host	Enters AAA server host configuration mode so you can configure AAA server parameters that are host-specific.

clear configure aaa-server	Remove all AAA command statements from the configuration.
show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol

ntp authenticate

To enable authentication with an NTP server, use the **ntp authenticate** command in global configuration mode. To disable NTP authentication, use the **no** form of this command.

ntp authenticate

no ntp authenticate

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If you enable authentication, the security appliance only communicates with an NTP server if it uses the correct trusted key in the packets (see the **ntp trusted-key** command). The security appliance also uses an authentication key to synchronize with the NTP server (see the **ntp authentication-key** command).

Examples

The following example configures the security appliance to synchronize only to systems that provide authentication key 42 in their NTP packets:

```
hostname(config)# ntp authenticate
hostname(config)# ntp authentication-key 42 md5 aNiceKey
hostname(config)# ntp trusted-key 42
```

Related Commands

Command	Description
ntp authentication-key	Sets an encrypted authentication key to synchronize with an NTP server.
ntp server	Identifies an NTP server.
ntp trusted-key	Provides a key ID for the security appliance to use in packets for authentication with an NTP server.

Command	Description
show ntp associations	Shows the NTP servers with which the security appliance is associated.
show ntp status	Shows the status of the NTP association.

ntp authentication-key

To set a key to authenticate with an NTP server, use the **ntp authentication-key** command in global configuration mode. To remove the key, use the **no** form of this command.

ntp authentication-key *key_id* **md5** *key*

no ntp authentication-key *key_id* [**md5** *key*]

Syntax Description

<i>key_id</i>	Identifies a key ID between 1 and 4294967295. You must specify this ID as a trusted key using the ntp trusted-key command.
md5	Specifies the authentication algorithm as MD5, which is the only algorithm supported.
<i>key</i>	Sets the key value as a string up to 32 characters in length.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To use NTP authentication, also configure the **ntp authenticate** command.

Examples

The following example enables authentications, identifies trusted key IDs 1 and 2, and sets authentication keys for each trusted key ID:

```
hostname(config)# ntp authenticate
hostname(config)# ntp trusted-key 1
hostname(config)# ntp trusted-key 2
hostname(config)# ntp authentication-key 1 md5 aNiceKey
hostname(config)# ntp authentication-key 2 md5 aNiceKey2
```


Related Commands

Command	Description
ntp authenticate	Enables NTP authentication.
ntp server	Identifies an NTP server.
ntp trusted-key	Provides a key ID for the security appliance to use in packets for authentication with an NTP server.
show ntp associations	Shows the NTP servers with which the security appliance is associated.
show ntp status	Shows the status of the NTP association.

ntp server

To identify an NTP server to set the time on the security appliance, use the **ntp server** command in global configuration mode. To remove the server, use the **no** form of this command. You can identify multiple servers; the security appliance uses the most accurate server. In multiple context mode, set the NTP server in the system configuration only.

ntp server *ip_address* [**key** *key_id*] [**source** *interface_name*] [**prefer**]

no ntp server *ip_address* [**key** *key_id*] [**source** *interface_name*] [**prefer**]

Syntax Description

<i>ip_address</i>	Sets the IP address of the NTP server.
key <i>key_id</i>	If you enable authentication using the ntp authenticate command, sets the trusted key ID for this server. See also the ntp trusted-key command.
source <i>interface_name</i>	Identifies the outgoing interface for NTP packets if you do not want to use the default interface in the routing table. Because the system does not include any interfaces in multiple context mode, specify an interface name defined in the admin context.
prefer	Sets this NTP server as the preferred server if multiple servers have similar accuracy. NTP uses an algorithm to determine which server is the most accurate and synchronizes to that one. If servers are of similar accuracy, then the prefer keyword specifies which of those servers to use. However, if a server is significantly more accurate than the preferred one, the security appliance uses the more accurate one. For example, the security appliance uses a server of stratum 2 over a server of stratum 3 that is preferred.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was modified to make the source interface optional.

Examples

The following example identifies two NTP servers and enables authentication for the key IDs 1 and 2:

```
hostname(config)# ntp server 10.1.1.1 key 1 prefer
hostname(config)# ntp server 10.2.1.1 key 2
hostname(config)# ntp authenticate
hostname(config)# ntp trusted-key 1
```

```
hostname(config)# ntp trusted-key 2
hostname(config)# ntp authentication-key 1 md5 aNiceKey
hostname(config)# ntp authentication-key 2 md5 aNiceKey2
```

Related Commands

Command	Description
ntp authenticate	Enables NTP authentication.
ntp authentication-key	Sets an encrypted authentication key to synchronize with an NTP server.
ntp trusted-key	Provides a key ID for the security appliance to use in packets for authentication with an NTP server.
show ntp associations	Shows the NTP servers with which the security appliance is associated.
show ntp status	Shows the status of the NTP association.

ntp trusted-key

To specify an authentication key ID to be a trusted key, which is required for authentication with an NTP server, use the **ntp trusted-key** command in global configuration mode. To remove the trusted key, use the **no** form of this command. You can enter multiple trusted keys for use with multiple servers.

ntp trusted-key *key_id*

no ntp trusted-key *key_id*

Syntax Description

key_id Sets a key ID between 1 and 4294967295.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To use NTP authentication, also configure the **ntp authenticate** command. To synchronize with a server, set the authentication key for the key ID using the **ntp authentication-key** command.

Examples

The following example enables authentications, identifies trusted key IDs 1 and 2, and sets authentication keys for each trusted key ID:

```
hostname(config)# ntp authenticate
hostname(config)# ntp trusted-key 1
hostname(config)# ntp trusted-key 2
hostname(config)# ntp authentication-key 1 md5 aNiceKey
hostname(config)# ntp authentication-key 2 md5 aNiceKey2
```

Related Commands

Command	Description
ntp authenticate	Enables NTP authentication.
ntp authentication-key	Sets an encrypted authentication key to synchronize with an NTP server.
ntp server	Identifies an NTP server.

Command	Description
show ntp associations	Shows the NTP servers with which the security appliance is associated.
show ntp status	Shows the status of the NTP association.

object-group

To define object groups that you can use to optimize your configuration, use the **object-group** command in global configuration mode. Use the **no** form of this command to remove object groups from the configuration. This command supports IPv4 and IPv6 addresses.

object-group { **protocol** | **network** | **icmp-type** } *obj_grp_id*

no object-group { **protocol** | **network** | **icmp-type** } *obj_grp_id*

object-group service *obj_grp_id* { **tcp** | **udp** | **tcp-udp** }

no object-group service *obj_grp_id* { **tcp** | **udp** | **tcp-udp** }

Syntax Description

icmp-type	Defines a group of ICMP types such as echo and echo-reply. After entering the main object-group icmp-type command, add ICMP objects to the ICMP type group with the icmp-object and the group-object commands.
network	Defines a group of hosts or subnet IP addresses. After entering the main object-group network command, add network objects to the network group with the network-object and the group-object commands.
<i>obj_grp_id</i>	Identifies the object group (one to 64 characters) and can be any combination of letters, digits, and the “_”, “-”, “.” characters.
protocol	Defines a group of protocols such as TCP and UDP. After entering the main object-group protocol command, add protocol objects to the protocol group with the protocol-object and the group-object commands.
service	Defines a group of TCP/UDP port specifications such as “eq smtp” and “range 2000 2010.” After entering the main object-group service command, add port objects to the service group with the port-object and the group-object commands.
tcp	Specifies that service group is used for TCP.
tcp-udp	Specifies that service group can be used for TCP and UDP.
udp	Specifies that service group is used for UDP.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Objects such as hosts, protocols, or services can be grouped, and then you can issue a single command using the group name to apply to every item in the group.

When you define a group with the **object-group** command and then use any security appliance command, the command applies to every item in that group. This feature can significantly reduce your configuration size.

Once you define an object group, you must use the **object-group** keyword before the group name in all applicable security appliance commands as follows:

```
hostname# show running-config object-group group_name
```

where *group_name* is the name of the group.

This example shows the use of an object group once it is defined:

```
hostname(config)# access-list access_list_name permit tcp any object-group group_name
```

In addition, you can group **access list** command arguments:

Individual Arguments	Object Group Replacement
<i>protocol</i>	object-group <i>protocol</i>
<i>host and subnet</i>	object-group <i>network</i>
<i>service</i>	object-group <i>service</i>
<i>icmp_type</i>	object-group <i>icmp_type</i>

You can group commands hierarchically; an object group can be a member of another object group.

To use object groups, you must do the following:

- Use the **object-group** keyword before the object group name in all commands as follows:

```
hostname(config)# access-list acl permit tcp object-group remotes object-group locals
object-group eng_svc
```

where *remotes* and *locals* are sample object group names.

- The object group must be nonempty.
- You cannot remove or empty an object group if it is currently being used in a command.

After you enter a main **object-group** command, the command mode changes to its corresponding mode. The object group is defined in the new mode. The active mode is indicated in the command prompt format. For example, the prompt in the configuration terminal mode appears as follows:

```
hostname(config)#
```

where *hostname* is the name of the security appliance.

However, when you enter the **object-group** command, the prompt appears as follows:

```
hostname(config-type)#
```

where *hostname* is the name of the security appliance, and *type* is the object-group type.

Use the **exit**, **quit**, or any valid config-mode commands such as **access-list** to close an **object-group** mode and exit the **object-group** main command.

The **show running-config object-group** command displays all defined object groups by their *grp_id* when the **show running-config object-group grp_id** command is entered, and by their group type when you enter the **show running-config object-group grp_type** command. When you enter the **show running-config object-group** command without an argument, all defined object groups are shown.

Use the **clear configure object-group** command to remove a group of previously defined **object-group** commands. Without an argument, the **clear configure object-group** command lets you to remove all defined object groups that are not being used in a command. The *grp_type* argument removes all defined object groups that are not being used in a command for that group type only.

You can use all other security appliance commands in an object-group mode, including the **show running-config** and **clear configure** commands.

Commands within the object-group mode appear indented when displayed or saved by the **show running-config object-group**, **write**, or **config** commands.

Commands within the object-group mode have the same command privilege level as the main command.

When you use more than one object group in an **access-list** command, the elements of all object groups that are used in the command are linked together, starting with the elements of the first group with the elements of the second group, then the elements of the first and second groups together with the elements of the third group, and so on.

The starting position of the description text is the character right after the white space (a blank or a tab) following the **description** keyword.

Examples

The following example shows how to use the **object-group icmp-type** mode to create a new icmp-type object group:

```
hostname(config)# object-group icmp-type icmp-allowed
hostname(config-icmp-type)# icmp-object echo
hostname(config-icmp-type)# icmp-object time-exceeded
hostname(config-icmp-type)# exit
```

The following example shows how to use the **object-group network** command to create a new network object group:

```
hostname(config)# object-group network sjc_eng_ftp_servers
hostname(config-network)# network-object host sjc.eng.ftp.servcers
hostname(config-network)# network-object host 172.23.56.194
hostname(config-network)# network-object 192.1.1.0 255.255.255.224
hostname(config-network)# exit
```

The following example shows how to use the **object-group network** command to create a new network object group and map it to an existing object-group:

```
hostname(config)# object-group network sjc_ftp_servers
hostname(config-network)# network-object host sjc.ftp.servers
hostname(config-network)# network-object host 172.23.56.195
hostname(config-network)# network-object 193.1.1.0 255.255.255.224
hostname(config-network)# group-object sjc_eng_ftp_servers
hostname(config-network)# exit
```

The following example shows how to use the **object-group protocol** mode to create a new protocol object group:

```
hostname(config)# object-group protocol proto_grp_1
hostname(config-protocol)# protocol-object udp
```



```
hostname(config-protocol)# protocol-object ipsec
hostname(config-protocol)# exit

hostname(config)# object-group protocol proto_grp_2
hostname(config-protocol)# protocol-object tcp
hostname(config-protocol)# group-object proto_grp_1
hostname(config-protocol)# exit
```

The following example shows how to use the **object-group service** mode to create a new port (service) object group:

```
hostname(config)# object-group service eng_service tcp
hostname(config-service)# group-object eng_www_service
hostname(config-service)# port-object eq ftp
hostname(config-service)# port-object range 2000 2005
hostname(config-service)# exit
```

The following example shows how to add and remove a text description to an object group:

```
hostname(config)# object-group protocol protos1
hostname(config-protocol)# description This group of protocols is for our internal network

hostname(config-protocol)# show running-config object-group id protos1
object-group protocol protos1
description: This group of protocols is for our internal network

hostname(config-protocol)# no description
hostname(config-protocol)# show running-config object-group id protos1
object-group protocol protos1
```

The following example shows how to use the **group-object** mode to create a new object group that consists of previously defined objects:

```
hostname(config)# object-group network host_grp_1
hostname(config-network)# network-object host 192.168.1.1
hostname(config-network)# network-object host 192.168.1.2
hostname(config-network)# exit

hostname(config)# object-group network host_grp_2
hostname(config-network)# network-object host 172.23.56.1
hostname(config-network)# network-object host 172.23.56.2
hostname(config-network)# exit

hostname(config)# object-group network all_hosts
hostname(config-network)# group-object host_grp_1
hostname(config-network)# group-object host_grp_2
hostname(config-network)# exit

hostname(config)# access-list grp_1 permit tcp object-group host_grp_1 any eq ftp
hostname(config)# access-list grp_2 permit tcp object-group host_grp_2 any eq smtp
hostname(config)# access-list all permit tcp object-group all_hosts any eq www
```

Without the **group-object** command, you need to define the *all_hosts* group to include all the IP addresses that have already been defined in *host_grp_1* and *host_grp_2*. With the **group-object** command, the duplicated definitions of the hosts are eliminated.

The following examples show how to use object groups to simplify the access list configuration:

```
hostname(config)# object-group network remote
hostname(config-network)# network-object host kqk.suu.dri.ixx
hostname(config-network)# network-object host kqk.suu.pyl.gnl

hostname(config)# object-group network locals
hostname(config-network)# network-object host 172.23.56.10
```

```

hostname(config-network)# network-object host 172.23.56.20
hostname(config-network)# network-object host 172.23.56.194
hostname(config-network)# network-object host 172.23.56.195

hostname(config)# object-group service eng_svc ftp
hostname(config-service)# port-object eq www
hostname(config-service)# port-object eq smtp
hostname(config-service)# port-object range 25000 25100

```

This grouping enables the access list to be configured in 1 line instead of 24 lines, which would be needed if no grouping is used. Instead, with the grouping, the access list configuration is as follows:

```

hostname(config)# access-list acl permit tcp object-group remote object-group locals
object-group eng_svc

```

**Note**

The **show running-config object-group** and **write** commands allow you to display the access list as configured with the object group names. The **show access-list** command displays the access list entries that are expanded out into individual entries without their object groupings.

Related Commands

Command	Description
clear configure object-group	Removes all the object group commands from the configuration.
group-object	Adds network object groups.
network-object	Adds a network object to a network object group.
port-object	Adds a port object to a service object group.
show running-config object-group	Displays the current object groups.

ospf authentication

To enable the use of OSPF authentication, use the **ospf authentication** command in interface configuration mode. To restore the default authentication stance, use the **no** form of this command.

ospf authentication [**message-digest** | **null**]

no ospf authentication

Syntax Description

message-digest	(Optional) Specifies to use OSPF message digest authentication.
null	(Optional) Specifies to not use OSPF authentication.

Defaults

By default, OSPF authentication is not enabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Before using the **ospf authentication** command, configure a password for the interface using the **ospf authentication-key** command. If you use the **message-digest** keyword, configure the message-digest key for the interface with the **ospf message-digest-key** command.

For backward compatibility, authentication type for an area is still supported. If the authentication type is not specified for an interface, the authentication type for the area will be used (the area default is null authentication).

When this command is used without any options, simple password authentication is enabled.

Examples

The following example shows how to enable simple password authentication for OSPF on the selected interface:

```
hostname(config-if)# ospf authentication
hostname(config-if)#
```

Related Commands	Command	Description
	ospf authentication-key	Specifies the password used by neighboring routing devices.
	ospf message-digest-key	Enables MD5 authentication and specifies the MD5 key.

ospf authentication-key

To specify the password used by neighboring routing devices, use the **ospf authentication-key** command in interface configuration mode. To remove the password, use the **no** form of this command.

ospf authentication-key *password*

no ospf authentication-key

Syntax Description

<i>password</i>	Assigns an OSPF authentication password for use by neighboring routing devices. The password must be less than 9 characters. You can include blank space between two characters. Spaces at the beginning or end of the password are ignored.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The password created by this command is used as a key that is inserted directly into the OSPF header when routing protocol packets are originated. A separate password can be assigned to each network on a per-interface basis. All neighboring routers on the same network must have the same password to be able to exchange OSPF information.

Examples

The following example shows how to specify a password for OSPF authentication:

```
hostname(config-if)# ospf authentication-key ThisMyPW
```

Related Commands

Command	Description
area authentication	Enables OSPF authentication for the specified area.
ospf authentication	Enables the use of OSPF authentication.

ospf cost

To specify the cost of sending a packet through the interface, use the **ospf cost** command in interface configuration mode. To reset the interface cost to the default value, use the **no** form of this command.

ospf cost *interface_cost*

no ospf cost

Syntax Description

<i>interface_cost</i>	The cost (a link-state metric) of sending a packet through an interface. This is an unsigned integer value from 0 to 65535. 0 represents a network that is directly connected to the interface, and the higher the interface bandwidth, the lower the associated cost to send packets across that interface. In other words, a large cost value represents a low bandwidth interface and a small cost value represents a high bandwidth interface. The OSPF interface default cost on the security appliance is 10. This default differs from Cisco IOS software, where the default cost is 1 for fast Ethernet and Gigabit Ethernet and 10 for 10BaseT. This is important to take into account if you are using ECMP in your network.

Defaults

The default *interface_cost* is 10.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **ospf cost** command lets you explicitly specify the cost of sending a packet on an interface. The *interface_cost* parameter is an unsigned integer value from 0 to 65535.

The **no ospf cost** command allows you to reset the path cost to the default value.

Examples

The following example show how to specify the cost of sending a packet on the selected interface:

```
hostname(config-if)# ospf cost 4
```

Related Commands

Command	Description
<code>show running-config interface</code>	Displays the configuration of the specified interface.

ospf database-filter

To filter out all outgoing LSAs to an OSPF interface during synchronization and flooding, use the **ospf database-filter** command in interface configuration mode. To restore the LSAs, use the **no** form of this command.

ospf database-filter all out

no ospf database-filter all out

Syntax Description

all out	Filters all outgoing LSAs to an OSPF interface.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **ospf database-filter** command filters outgoing LSAs to an OSPF interface. The **no ospf database-filter all out** command restores the forwarding of LSAs to the interface.

Examples

The following example shows how to use the **ospf database-filter** command to filter outgoing LSAs:

```
hostname(config-if)# ospf database-filter all out
```

Related Commands

Command	Description
show interface	Displays interface status information.

ospf dead-interval

To specify the interval before neighbors declare a router down, use the **ospf dead-interval** command in interface configuration mode. To restore the default value, use the **no** form of this command.

ospf dead-interval *seconds*

no ospf dead-interval

Syntax Description

seconds The length of time during which no hello packets are seen. The default for *seconds* is four times the interval set by the **ospf hello-interval** command (which ranges from 1 to 65535).

Defaults

The default value for *seconds* is four times the interval set by the **ospf hello-interval** command.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **ospf dead-interval** command lets you set the dead interval before neighbors to declare the router down (the length of time during which no hello packets are seen). The *seconds* argument specifies the dead interval and must be the same for all nodes on the network. The default for *seconds* is four times the interval set by the **ospf hello-interval** command from 1 to 65535.

The **no ospf dead-interval** command lets restores the default interval value.

Examples

The following example sets the OSPF dead interval to 1 minute:

```
hostname(config-if)# ospf dead-interval 60
```

Related Commands

Command	Description
ospf hello-interval	Specifies the interval between hello packets sent on an interface.
show ospf interface	Displays OSPF-related interface information.

ospf hello-interval

To specify the interval between hello packets sent on an interface, use the **ospf hello-interval** command in interface configuration mode. To return the hello interval to the default value, use the **no** form of this command.

ospf hello-interval *seconds*

no ospf hello-interval

Syntax Description

seconds Specifies the interval between hello packets that are sent on the interface; valid values are from 1 to 65535 seconds.

Defaults

The default value for **hello-interval** *seconds* is 10 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

This value is advertised in the hello packets. The smaller the hello interval, the faster topological changes will be detected, but more routing traffic will ensue. This value must be the same for all routers and access servers on a specific network.

Examples

The following example sets the OSPF hello interval to 5 seconds:

```
hostname(config-if)# ospf hello-interval 5
```

Related Commands

Command	Description
ospf dead-interval	Specifies the interval before neighbors declare a router down.
show ospf interface	Displays OSPF-related interface information.

ospf message-digest-key

To enable OSPF MD5 authentication, use the **ospf message-digest-key** command in interface configuration mode. To remove an MD5 key, use the **no** form of this command.

ospf message-digest-key *key-id* **md5** *key*

no ospf message-digest-key

Syntax Description

<i>key-id</i>	Enables MD5 authentication and specifies the numerical authentication key ID number; valid values are from 1 to 255.
md5 <i>key</i>	Alphanumeric password of up to 16 bytes. You can include spaces between key characters. Spaces at the beginning or end of the key are ignored. MD5 authentication verifies the integrity of the communication, authenticates the origin, and checks for timeliness.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **ospf message-digest-key** command lets you enable MD5 authentication. The **no** form of the command let you remove an old MD5 key. *key_id* is a numerical identifier from 1 to 255 for the authentication key. *key* is an alphanumeric password of up to 16 bytes. MD5 verifies the integrity of the communication, authenticates the origin, and checks for timeliness.

Examples

The following example shows how to specify an MD5 key for OSPF authentication:

```
hostname(config-if)# ospf message-digest-key 3 md5 ThisIsMyMd5Key
```

Related Commands	Command	Description
	area authentication	Enables OSPF area authentication.
	ospf authentication	Enables the use of OSPF authentication.

ospf mtu-ignore

To disable OSPF maximum transmission unit (MTU) mismatch detection on receiving database packets, use the **ospf mtu-ignore** command in interface configuration mode. To restore MTU mismatch detection, use the **no** form of this command.

ospf mtu-ignore

no ospf mtu-ignore

Syntax Description

This command has no arguments or keywords.

Defaults

By default, **ospf mtu-ignore** is enabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

OSPF checks whether neighbors are using the same MTU on a common interface. This check is performed when neighbors exchange Database Descriptor (DBD) packets. If the receiving MTU in the DBD packet is higher than the IP MTU configured on the incoming interface, OSPF adjacency will not be established. The **ospf mtu-ignore** command disables OSPF MTU mismatch detection on receiving DBD packets. It is enabled by default.

Examples

The following example shows how to disable the **ospf mtu-ignore** command:

```
hostname(config-if)# ospf mtu-ignore
```

Related Commands

Command	Description
show interface	Displays interface status information.

ospf network point-to-point non-broadcast

To configure the OSPF interface as a point-to-point, non-broadcast network, use the **ospf network point-to-point non-broadcast** command in interface configuration mode. To remove this command from the configuration, use the **no** form of this command. The **ospf network point-to-point non-broadcast** command lets you to transmit OSPF routes over VPN tunnels.

ospf network point-to-point non-broadcast

no ospf network point-to-point non-broadcast

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

When the interface is specified as point-to-point, the OSPF neighbors have to be manually configured; dynamic discovery is not possible. To manually configure OSPF neighbors, use the **neighbor** command in router configuration mode.

When an interface is configured as point-to-point, the following restrictions apply:

- You can define only one neighbor for the interface.
- You need to define a static route pointing to the crypto endpoint.
- The interface cannot form adjacencies unless neighbors are configured explicitly.
- If OSPF over the tunnel is running on the interface, regular OSPF with an upstream router cannot be run on the same interface.
- You should bind the crypto-map to the interface before specifying the OSPF neighbor to ensure that the OSPF updates are passed through the VPN tunnel. If you bind the crypto-map to the interface after specifying the OSPF neighbor, use the **clear local-host all** command to clear OSPF connections so the OSPF adjacencies can be established over the VPN tunnel.

Examples

The following example shows how to configure the selected interface as a point-to-point, non-broadcast interface:

```
hostname(config-if)# ospf network point-to-point non-broadcast  
hostname(config-if)#
```

Related Commands

Command	Description
neighbor	Specifies manually configured OSPF neighbors.
show interface	Displays interface status information.

ospf priority

To change the OSPF router priority, use the **ospf priority** command in interface configuration mode. To restore the default priority, use the **no** form of this command.

ospf priority *number*

no ospf priority [*number*]

Syntax Description

number Specifies the priority of the router; valid values are from 0 to 255.

Defaults

The default value for *number* is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

When two routers attached to a network both attempt to become the designated router, the one with the higher router priority takes precedence. If there is a tie, the router with the higher router ID takes precedence. A router with a router priority set to zero is ineligible to become the designated router or backup designated router. Router priority is configured only for interfaces to multiaccess networks (in other words, not to point-to-point networks).

Examples

The following example shows how to change the OSPF priority on the selected interface:

```
hostname(config-if)# ospf priority 4
hostname(config-if)#
```

Related Commands

Command	Description
show ospf interface	Displays OSPF-related interface information.

ospf retransmit-interval

To specify the time between LSA retransmissions for adjacencies belonging to the interface, use the **ospf retransmit-interval** command in interface configuration mode. To restore the default value, use the **no** form of this command.

ospf retransmit-interval *seconds*

no ospf retransmit-interval [*seconds*]

Syntax Description

<i>seconds</i>	Specifies the time between LSA retransmissions for adjacent routers belonging to the interface; valid values are from 1 to 65535 seconds.

Defaults

The default value of **retransmit-interval** *seconds* is 5 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

When a router sends an LSA to its neighbor, it keeps the LSA until it receives the acknowledgment message. If the router receives no acknowledgment, it will re-send the LSA.

The setting of this parameter should be conservative, or needless retransmission will result. The value should be larger for serial lines and virtual links.

Examples

The following example shows how to change the retransmit interval for LSAs:

```
hostname(config-if)# ospf retransmit-interval 15
hostname(config-if)#
```

Related Commands

Command	Description
show ospf interface	Displays OSPF-related interface information.

ospf transmit-delay

To set the estimated time required to send a link-state update packet on the interface, use the **ospf transmit-delay** command in interface configuration mode. To restore the default value, use the **no** form of this command.

ospf transmit-delay *seconds*

no ospf transmit-delay [*seconds*]

Syntax Description

<i>seconds</i>	Sets the estimated time required to send a link-state update packet on the interface. The default value is 1 second with a range from 1 to 65535 seconds.

Defaults

The default value of *seconds* is 1 second.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

LSAs in the update packet must have their ages incremented by the amount specified in the *seconds* argument before transmission. The value assigned should take into account the transmission and propagation delays for the interface.

If the delay is not added before transmission over a link, the time in which the LSA propagates over the link is not considered. This setting has more significance on very low-speed links.

Examples

The following example sets the transmit delay to 3 seconds for the selected interface:

```
hostname(config-if)# ospf retransmit-delay 3
hostname(config-if)#
```

Related Commands

Command	Description
show ospf interface	Displays OSPF-related interface information.

outstanding

To limit the number of unauthenticated e-mail proxy sessions, use the **outstanding** command in the applicable e-mail proxy mode. To remove the attribute from the configuration, use the **no** version of this command, which permits an unlimited number of unauthenticated sessions. Use this command to limit DOS attacks on the e-mail ports.

E-mail proxy connections have three states:

1. A new e-mail connection enters the “unauthenticated” state.
2. When the connection presents a username, it enters the “authenticating” state.
3. When the security appliance authenticates the connection, it enters the “authenticated” state.

If the number of connections in the unauthenticated state exceeds the configured limit, the security appliance terminates the oldest unauthenticated connection, preventing overload. It does not terminate authenticated connections.

outstanding {*number*}

no outstanding

Syntax Description

number	The number of unauthenticated sessions permitted. The range is from 1 to 1000.

Defaults

The default is 20.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Pop3s	•	•	—	—	•
Imap4s	•	•	—	—	•
Smtps	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to set a limit of 12 unauthenticated sessions for POP3S e-mail proxy.

```
hostname(config)# pop3s
hostname(config-pop3s)# outstanding 12
```

participate

To force the device to participate in the virtual load-balancing cluster, use the **participate** command in VPN load-balancing mode. To remove a device from participation in the cluster, use the **no** form of this command.

participate

no participate

Syntax Description

This command has no arguments or keywords.

Defaults

The default behavior is that the device does not participate in the vpn load-balancing cluster.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
VPN load-balancing	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must first configure the interface using the **interface** and **nameif** commands, and use the **vpn load-balancing** command to enter VPN load-balancing mode. You must also have previously configured the cluster IP address using the **cluster ip** command and configured the interface to which the virtual cluster IP address refers.

This command forces this device to participate in the virtual load-balancing cluster. You must explicitly issue this command to enable participation for a device.

All devices that participate in a cluster must share the same cluster-specific values: ip address, encryption settings, encryption key, and port.



Note

When using encryption, you must have previously configured the command **isakmp enable inside**, where *inside* designates the load-balancing inside interface. If isakmp is not enabled on the load-balancing inside interface, you get an error message when you try to configure cluster encryption.

If isakmp was enabled when you configured the **cluster encryption** command, but was disabled before you configured the **participate** command, you get an error message when you enter the **participate** command, and the local device will not participate in the cluster.

Examples

The following is an example of a VPN load-balancing command sequence that includes a **participate** command that enables the current device to participate in the vpn load-balancing cluster:

```
hostname(config)# interface GigabitEthernet 0/1
hostname(config-if)# ip address 209.165.202.159 255.255.255.0
hostname(config)# nameif test
hostname(config)# interface GigabitEthernet 0/2
hostname(config-if)# ip address 209.165.201.30 255.255.255.0
hostname(config)# nameif foo
hostname(config)# vpn load-balancing
hostname(config-load-balancing)# interface lbpublic test
hostname(config-load-balancing)# interface lbprivate foo
hostname(config-load-balancing)# cluster ip address 209.165.202.224
hostname(config-load-balancing)# participate
hostname(config-load-balancing)#
```

Related Commands

Command	Description
vpn load-balancing	Enter VPN load-balancing mode.

passwd

To set the login password, use the **passwd** command in global configuration mode. To set the password back to the default of “cisco,” use the **no** form of this command. You are prompted for the login password when you access the CLI as the default user using Telnet or SSH. After you enter the login password, you are in user EXEC mode.

```
{ passwd | password } password [encrypted]
```

```
no { passwd | password } password
```

Syntax Description

encrypted	(Optional) Specifies that the password is in encrypted form. The password is saved in the configuration in encrypted form, so you cannot view the original password after you enter it. If for some reason you need to copy the password to another security appliance but do not know the original password, you can enter the passwd command with the encrypted password and this keyword. Normally, you only see this keyword when you enter the show running-config passwd command.
passwd password	You can enter either command; they are aliased to each other.
<i>password</i>	Sets the password as a case-sensitive string of up to 80 characters. The password must not contains spaces.

Defaults

The default password is “cisco.”

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

This login password is for the default user. If you configure CLI authentication per user for Telnet or SSH using the **aaa authentication console** command, then this password is not used.

Examples

The following example sets the password to Pa\$\$w0rd:

```
hostname(config)# passwd Pa$$w0rd
```

The following example sets the password to an encrypted password that you copied from another security appliance:

```
hostname(config)# passwd jMorNbK0514fadBh encrypted
```

Related Commands

Command	Description
clear configure passwd	Clears the login password.
enable	Enters privileged EXEC mode.
enable password	Sets the enable password.
show curpriv	Shows the currently logged in username and the user privilege level.
show running-config passwd	Shows the login password in encrypted form.

password (crypto ca trustpoint)

To specify a challenge phrase that is registered with the CA during enrollment, use the **password** command in crypto ca trustpoint configuration mode. The CA typically uses this phrase to authenticate a subsequent revocation request. To restore the default setting, use the **no** form of the command.

password *string*

no password

Syntax Description

string Specifies the name of the password as a character string. The first character cannot be a number. The string can contain any alphanumeric characters, including spaces, up to 80 characters. You cannot specify the password in the format number-space-anything. The space after the number causes problems. For example, “hello 21” is a legal password, but “21 hello” is not. The password checking is case sensitive. For example, the password “Secret” is different from the password “secret”.

Defaults

The default setting is to not include a password.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command lets you specify the revocation password for the certificate before actual certificate enrollment begins. The specified password is encrypted when the updated configuration is written to NVRAM by the security appliance.

If this command is enabled, you will not be prompted for a password during certificate enrollment.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and includes a challenge phrase registered with the CA in the enrollment request for trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# password zzxxyy
hostname(ca-trustpoint)#
```


Related Commands	Command	Description
	crypto ca trustpoint	Enters trustpoint configuration mode.
	default enrollment	Returns enrollment parameters to their defaults.

password-prompt

To configure the prompt that requests the password for initial login to WebVPN, use the **password-prompt** command in webvpn mode. To revert to the default, “Password:,” use the **no** form of this command.

password-prompt [*prompt*]

no password-prompt

Syntax Description

prompt	(Optional) Specifies the string that prompts users to enter a password. Maximum 16 characters.

Defaults

The default prompt is “Password:”

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Webvpn	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to configure the password prompt, “Enter Password:”

```
hostname(config)# webvpn
hostname(config-webvpn)# password-prompt Enter Password:
```

password-storage

To let users store their login passwords on the client system, use the **password-storage enable** command in group-policy configuration mode or username configuration mode. To disable password storage, use the **password-storage disable** command.

To remove the password-storage attribute from the running configuration, use the **no** form of this command. This enables inheritance of a value for password-storage from another group policy.

password-storage {enable | disable}

no password-storage

Syntax Description

disable	Disables password storage.
enable	Enables password storage.

Defaults

Password storage is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Group-policy	•	—	•	—	—
Username	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Enable password storage only on systems that you know to be in secure sites.

This command has no bearing on interactive hardware client authentication or individual user authentication for hardware clients.

Examples

The following example shows how to enable password storage for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# password-storage enable
```

peer-id-validate

To specify whether to validate the identity of the peer using the peer's certificate, use the **peer-id-validate** command in tunnel-group ipsec-attributes mode. To return to the default value, use the **no** form of this command.

peer-id-validate *option*

no peer-id-validate

Syntax Description

<i>option</i>	Specifies one of the following options:
	• req: required • cert: if supported by certificate • nocheck: do not check

Defaults

The default setting for this command is **req**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group ipsec attributes	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute to all tunnel-group types.

Examples

The following example entered in config-ipsec configuration mode, requires validating the peer using the identity of the peer's certificate for the IPSec LAN-to-LAN tunnel group named 209.165.200.225:

```
hostname(config)# tunnel-group 209.165.200.225 type IPSec_L2L
hostname(config)# tunnel-group 209.165.200.225 ipsec-attributes
hostname(config-ipsec)# peer-id-validate req
hostname(config-ipsec)#
```

Related Commands

Command	Description
clear configure tunnel-group	Clears all configured tunnel groups.
show running-config tunnel-group	Shows the configuration for the indicated tunnel group or for all tunnel groups.
tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

perfmon

To display performance information, use the **perfmon** command in privileged EXEC mode.

perfmon { **verbose** | **interval** *seconds* | **quiet** | **settings** }

Syntax Description

verbose	Displays performance monitor information at the security appliance console.
interval <i>seconds</i>	Specifies the number of seconds before the performance display is refreshed on the console.
quiet	Disables the performance monitor displays.
settings	Displays the interval and whether it is quiet or verbose.

Defaults

The *seconds* is 120 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	

Command History

Release	Modification
7.0	Support for this command was introduced on the security appliance.

Usage Guidelines

The **perfmon** command allows you to monitor the performance of the security appliance. Use the **show perfmon** command to display the information immediately. Use the **perfmon verbose** command to display the information every 2 minutes continuously. Use the **perfmon interval** *seconds* command with the **perfmon verbose** command to display the information continuously every number of seconds that you specify.

An example of the performance information is displayed as follows:

PERFMON STATS:	Current	Average
Xlates	33/s	20/s
Connections	110/s	10/s
TCP Conns	50/s	42/s
WebSns Req	4/s	2/s
TCP Fixup	20/s	15/s
HTTP Fixup	5/s	5/s
FTP Fixup	7/s	4/s
AAA Authen	10/s	5/s

AAA Author	9/s	5/s
AAA Account	3/s	3/s

This information lists the number of translations, connections, Websense requests, address translations (called “fixups”), and AAA transactions that occur each second.

Examples

This example shows how to display the performance monitor statistics every 30 seconds on the security appliance console:

```
hostname(config)# perfmon interval 120
hostname(config)# perfmon quiet
hostname(config)# perfmon settings
interval: 120 (seconds)
quiet
```

Related Commands

Command	Description
show perfmon	Displays performance information.

periodic

To specify a recurring (weekly) time range for functions that support the time-range feature, use the **periodic** command in time-range configuration mode. To disable, use the **no** form of this command.

periodic *days-of-the-week time to [days-of-the-week] time*

no periodic *days-of-the-week time to [days-of-the-week] time*

Syntax Description

days-of-the-week (Optional) The first occurrence of this argument is the starting day or day of the week that the associated time range is in effect. The second occurrence is the ending day or day of the week the associated statement is in effect.

This argument is any single day or combinations of days: Monday, Tuesday, Wednesday, Thursday, Friday, Saturday, and Sunday. Other possible values are:

- **daily**—Monday through Sunday
- **weekdays**—Monday through Friday
- **weekend**—Saturday and Sunday

If the ending days of the week are the same as the starting days of the week, you can omit them.

time Specifies the time in the format HH:MM. For example, 8:00 is 8:00 a.m. and 20:00 is 8:00 p.m.

to Entry of the **to** keyword is required to complete the range “from start-time to end-time.”

Defaults

If a value is not entered with the **periodic** command, access to the security appliance as defined with the **time-range** command is in effect immediately and always on.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Time-range configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

To implement a time-based ACL, use the **time-range** command to define specific times of the day and week. Then use the with the **access-list extended time-range** command to bind the time range to an ACL.

The **periodic** command is one way to specify when a time range is in effect. Another way is to specify an absolute time period with the **absolute** command. Use either of these commands after the **time-range** global configuration command, which specifies the name of the time range. Multiple **periodic** entries are allowed per **time-range** command.

If the end days-of-the-week value is the same as the start value, you can omit them.

If a **time-range** command has both **absolute** and **periodic** values specified, then the **periodic** commands are evaluated only after the **absolute start** time is reached, and are not further evaluated after the **absolute end** time is reached.

The time-range feature relies on the system clock of the security appliance; however, the feature works best with NTP synchronization.

Examples

Some examples follow:

If you want:	Enter this:
Monday through Friday, 8:00 a.m. to 6:00 p.m. only	periodic weekdays 8:00 to 18:00
Every day of the week, from 8:00 a.m. to 6:00 p.m. only	periodic daily 8:00 to 18:00
Every minute from Monday 8:00 a.m. to Friday 8:00 p.m.	periodic monday 8:00 to friday 20:00
All weekend, from Saturday morning through Sunday night	periodic weekend 00:00 to 23:59
Saturdays and Sundays, from noon to midnight	periodic weekend 12:00 to 23:59

The following example shows how to allow access to the security appliance on Monday through Friday, 8:00 a.m. to 6:00 p.m. only:

```
hostname(config-time-range)# periodic weekdays 8:00 to 18:00
hostname(config-time-range)#
```

The following example shows how to allow access to the security appliance on specific days (Monday, Tuesday, and Friday), 10:30 a.m. to 12:30 p.m.:

```
hostname(config-time-range)# periodic Monday Tuesday Friday 10:30 to 12:30
hostname(config-time-range)#
```

Related Commands

Command	Description
absolute	Defines an absolute time when a time range is in effect.
access-list extended	Configures a policy for permitting or denying IP traffic through the security appliance.
default	Restores default settings for the time-range command absolute and periodic keywords.
time-range	Defines access control to the security appliance based on time.

permit errors

To allow invalid GTP packets or packets that otherwise would fail parsing and be dropped, use the **permit errors** command in GTP map configuration mode, which is accessed by using the **gtp-map** command. Use the **no** form of this command to remove the command.

permit errors

no permit errors

Syntax Description

This command has no arguments or keywords.

Defaults

By default, all invalid packets or packets that failed, during parsing, are dropped.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
GTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **permit errors** command in GTP map configuration mode to allow any packets that are invalid or encountered an error during inspection of the message to be sent through the security appliance instead of being dropped.

Examples

The following example permits traffic containing invalid packets or packets that failed, during parsing:

```
hostname(config)# gtp-map gtp-policy
hostname(config-gtpmap)# permit errors
```

Related Commands

Commands	Description
clear service-policy	Clears global GTP statistics.
inspect gtp	
gtp-map	Defines a GTP map and enables GTP map configuration mode.
inspect gtp	Applies a specific GTP map to use for application inspection.

Commands	Description
permit response	Supports load-balancing GSNs.
show service-policy inspect gtp	Displays the GTP configuration.

permit response

To support load-balancing GSNs, use the **permit response** command in GTP map configuration mode, which is accessed by using the **gtp-map** command. The permit response command supports load-balancing GSNs by allowing GTP responses from a different GSN than the response was sent to. Use the **no** form of this command to remove the command.

permit response to-object-group *to_obj_group_id* **from-object-group** *from_obj_group_id*

no permit response to-object-group *to_obj_group_id* **from-object-group** *from_obj_group_id*

Syntax Description

from-object-group <i>from_obj_group_id</i>	Specifies the name of the object-group configured with the object-group command which can send responses to the set of GSNs in the object-group specified by the <i>to_obj_group_id</i> argument. The security appliance supports only object-groups containing network-objects with IPv4 addresses. IPv6 addresses are currently not supported with GTP.
to-object-group <i>to_obj_group_id</i>	Specifies the name of the object-group configured with the object-group command which can receive responses from the set of GSNs in the object-group specified by the <i>from_obj_group_id</i> argument. The security appliance supports only object-groups containing network-objects with IPv4 addresses. IPv6 addresses are currently not supported with GTP.

Defaults

By default, the security appliance drops GTP responses from GSNs other than the host to which the request was sent.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
GTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0(4)	This command was introduced.

Usage Guidelines

Use the **permit response** command in GTP map configuration mode to support load-balancing GSNs. The **permit response** command configures the GTP map to allow GTP responses from a different GSN than the response was sent to.

You identify the pool of load-balancing GSNs as a network object. Likewise, you identify the SGSN as a network object. If the GSN responding belongs to the same object group as the GSN that the GTP request was sent to and if the SGSN is in a object group that the responding GSN is permitted to send a GTP response to, the security appliance permits the response.

Examples

The following example permits GTP responses from any host on the 192.168.32.0 network to the host with the IP address 192.168.112.57:

```
hostname(config)# object-group network gsnpool32
hostname(config-network)# network-object 192.168.32.0 255.255.255.0
hostname(config)# object-group network sgsn1
hostname(config-network)# network-object host 192.168.112.57
hostname(config-network)# exit
hostname(config)# gtp-map gtp-policy
hostname(config-gtpmap)# permit response to-object-group sgsn1 from-object-group gsnpool32
```

Related Commands

Commands	Description
clear service-policy inspect gtp	Clears global GTP statistics.
gtp-map	Defines a GTP map and enables GTP map configuration mode.
inspect gtp	Applies a specific GTP map to use for application inspection.
permit errors	Allow invalid GTP packets.
show service-policy inspect gtp	Displays the GTP configuration.

pfs

To enable PFS, use the **pfs enable** command in group-policy configuration mode. To disable PFS, use the **pfs disable** command. To remove the PFS attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a value for PFS from another group policy.

In IPsec negotiations, PFS ensures that each new cryptographic key is unrelated to any previous key.

pfs {enable | disable}

no pfs

Syntax Description

disable	Disables PFS.
enable	Enables PFS.

Defaults

PFS is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The PFS setting on the VPN Client and the security appliance must match.

Examples

The following example shows how to set PFS for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# pfs enable
```

pim

To re-enable PIM on an interface, use the **pim** command in interface configuration mode. To disable PIM, use the **no** form of this command.

pim

no pim

Syntax Description

This command has no arguments or keywords.

Defaults

The **mcast-routing** command enables PIM on all interfaces by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **mcast-routing** command enables PIM on all interfaces by default. Only the **no** form of the **pim** command is saved in the configuration.



Note

PIM is not supported with PAT. The PIM protocol does not use ports and PAT only works with protocols that use ports.

Examples

The following example disables PIM on the selected interface:

```
hostname(config-if)# no pim
```

Related Commands

Command	Description
mcast-routing	Enables multicast routing on the security appliance.

pim accept-register

To configure the security appliance to filter PIM register messages, use the **pim accept-register** command in global configuration mode. To remove the filtering, use the **no** form of this command.

pim accept-register {**list** *acl* | **route-map** *map-name*}

no pim accept-register

Syntax Description

list <i>acl</i>	Specifies an access list name or number. Use only standard host ACLs with this command; extended ACLs are not supported.
route-map <i>map-name</i>	Specifies a route-map name. Use standard host ACLs in the referenced route-map; extended ACLs are not supported.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is used to prevent unauthorized sources from registering with the RP. If an unauthorized source sends a register message to the RP, the security appliance will immediately send back a register-stop message.

Examples

The following example restricts PIM register messages to those from sources defined in the access list named “no-ssm-range”:

```
hostname(config)# pim accept-register list no-ssm-range
```

Related Commands

Command	Description
multicast-routing	Enables multicast routing on the security appliance.

pim dr-priority

To configure the neighbor priority on the security appliance used for designated router election, use the **pim dr-priority** command in interface configuration mode. To restore the default priority, use the **no** form of this command.

pim dr-priority *number*

no pim dr-priority

Syntax Description

<i>number</i>	A number from 0 to 4294967294. This number is used to determine the priority of the device when determining the designated router. Specifying 0 prevents the security appliance from becoming the designated router.

Defaults

The default value is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The device with the largest priority value on an interface becomes the PIM designated router. If multiple devices have the same designated router priority, then the device with the highest IP address becomes the DR. If a device does not include the DR-Priority Option in hello messages, it is regarded as the highest-priority device and becomes the designated router. If multiple devices do not include this option in their hello messages, then the device with the highest IP address becomes the designated router.

Examples

The following example sets the DR priority for the interface to 5:

```
hostname(config-if)# pim dr-priority 5
```

Related Commands

Command	Description
multicast-routing	Enables multicast routing on the security appliance.

pim hello-interval

To configure the frequency of the PIM hello messages, use the **pim hello-interval** command in interface configuration mode. To restore the hello-interval to the default value, use the **no** form of this command.

pim hello-interval *seconds*

no pim hello-interval [*seconds*]

Syntax Description

<i>seconds</i>	The number of seconds that the security appliance waits before sending a hello message. Valid values range from 1 to 3600 seconds. The default value is 30 seconds.

Defaults

30 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example sets the PIM hello interval to 1 minute:

```
hostname(config-if)# pim hello-interval 60
```

Related Commands

Command	Description
multicast-routing	Enables multicast routing on the security appliance.

pim join-prune-interval

To configure the PIM join/prune interval, use the **pim join-prune-interval** command in interface configuration mode. To restore the interval to the default value, use the **no** form of this command.

pim join-prune-interval *seconds*

no pim join-prune-interval [*seconds*]

Syntax Description	<i>seconds</i>	The number of seconds that the security appliance waits before sending a join/prune message. Valid values range from 10 to 600 seconds. 60 seconds is the default.

Defaults	60 seconds

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following example sets the PIM join/prune interval to 2 minutes:

```
hostname(config-if)# pim join-prune-interval 120
```

Related Commands	Command	Description
	mcast-routing	Enables multicast routing on the security appliance.

pim old-register-checksum

To allow backward compatibility on a rendezvous point (RP) that uses old register checksum methodology, use the **pim old-register-checksum** command in global configuration mode. To generate PIM RFC-compliant registers, use the **no** form of this command.

pim old-register-checksum

no pim old-register-checksum

Syntax Description

This command has no arguments or keywords.

Defaults

The security appliance generates PIM RFC-compliant registers.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The security appliance software accepts register messages with checksum on the PIM header and only the next 4 bytes rather than using the Cisco IOS method—accepting register messages with the entire PIM message for all PIM message types. The **pim old-register-checksum** command generates registers compatible with Cisco IOS software.

Examples

The following example configures the security appliance to use the old checksum calculations:

```
hostname(config)# pim old-register-checksum
```

Related Commands

Command	Description
multicast-routing	Enables multicast routing on the security appliance.

pim rp-address

To configure the address of a PIM rendezvous point (RP), use the **pim rp-address** command in global configuration mode. To remove an RP address, use the **no** form of this command.

pim rp-address *ip_address* [*acl*] [**bidir**]

no pim rp-address *ip_address*

Syntax Description

<i>acl</i>	(Optional) The name or number of a standard access list that defines which multicast groups the RP should be used with. Do not use a host ACL with this command.
bidir	(Optional) Indicates that the specified multicast groups are to operate in bidirectional mode. If the command is configured without this option, the specified groups operate in PIM sparse mode.
<i>ip_address</i>	IP address of a router to be a PIM RP. This is a unicast IP address in four-part dotted-decimal notation.

This command has no arguments or keywords.

Defaults

No PIM RP addresses are configured.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

All routers within a common PIM sparse mode (PIM-SM) or bidir domain require knowledge of the well-known PIM RP address. The address is statically configured using this command.



Note

The security appliance does not support Auto-RP; you must use the **pim rp-address** command to specify the RP address.

You can configure a single RP to serve more than one group. The group range specified in the access list determines the PIM RP group mapping. If the an access list is not specified, the RP for the group is applied to the entire IP multicast group range (224.0.0.0/4).

**Note**

The security appliance always advertises the bidir capability in the PIM hello messages regardless of the actual bidir configuration.

Examples

The following example sets the PIM RP address to 10.0.0.1 for all multicast groups:

```
hostname(config)# pim rp-address 10.0.0.1
```

Related Commands

Command	Description
pim accept-register	Configures candidate RPs to filter PIM register messages.

pim spt-threshold infinity

To change the behavior of the last hop router to always use the shared tree and never perform a shortest-path tree (SPT) switchover, use the **pim spt-threshold infinity** command in global configuration mode. To restore the default value, use the **no** form of this command.

pim spt-threshold infinity [group-list *acl*]

no pim spt-threshold

Syntax Description

group-list *acl* (Optional) Indicates the source groups restricted by the access list. The *acl* argument must specify a standard ACL; extended ACLs are not supported.

Defaults

The last hop PIM router switches to the shortest-path source tree by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If the **group-list** keyword is not used, this command applies to all multicast groups.

Examples

The following example causes the last hop PIM router to always use the shared tree instead of switching to the shortest-path source tree:

```
hostname(config)# pim spt-threshold infinity
```

Related Commands

Command	Description
mcast-routing	Enables multicast routing on the security appliance.

ping

To determine if other IP addresses are visible from the security appliance, use the **ping** command in privileged EXEC mode.

ping [*if_name*] *host* [**data pattern**] [**repeat count**] [**size bytes**] [**timeout seconds**] [**validate**]

Syntax Description

data pattern	(Optional) Specifies the 16-bit data pattern in hexadecimal.
<i>host</i>	Specifies the IPv4 or IPv6 address or name of the host to ping.
<i>if_name</i>	(Optional) Specifies the interface name, as configured by the nameif command, by which the <i>host</i> is accessible. If not supplied, then the <i>host</i> is resolved to an IP address and then the routing table is consulted to determine the destination interface.
repeat count	(Optional) Specifies the number of times to repeat the ping request.
size bytes	(Optional) Specifies the datagram size in bytes.
timeout seconds	(Optional) Specifies the the number of seconds to wait before timing out the ping request.
validate	(Optional) Specifies to validate reply data.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **ping** command allows you to determine if the security appliance has connectivity or if a host is available on the network. If the security appliance has connectivity, ensure that the **icmp permit any interface** command is configured. This configuration is required to allow the security appliance to respond and accept messages generated from the **ping** command. The **ping** command output shows if the response was received. If a host is not responding, when you enter the **ping** command, a message similar to the following displays:

```
hostname(config)# ping 10.1.1.1
Sending 5, 100-byte ICMP Echos to 10.1.1.1, timeout is 2 seconds:
?????
Success rate is 0 percent (0/5)
```


Use the **show interface** command to ensure that the security appliance is connected to the network and is passing traffic. The address of the specified *if_name* is used as the source address of the ping.

If you want internal hosts to ping external hosts, you must do one of the following:

- Create an ICMP **access-list** command for an echo reply; for example, to give ping access to all hosts, use the **access-list acl_grp permit icmp any any** command and bind the **access-list** command to the interface that you want to test using the **access-group** command.
- Configure the ICMP inspection engine using the **inspect icmp** command. For example, adding the **inspect icmp** command to the **class default_inspection** class for the global service policy allows echo replies through the security appliance for echo requests initiated by internal hosts.

You can also perform an extended ping, which allows you to enter the keywords one line at a time.

If you are pinging through the security appliance between hosts or routers, but the pings are not successful, use the **capture** command to monitor the success of the ping.

The security appliance **ping** command does not require an interface name. If you do not specify an interface name, the security appliance checks the routing table to find the address that you specify. You can specify an interface name to indicate through which interface the ICMP echo requests are sent.

Examples

The following example shows how to determine if other IP addresses are visible from the security appliance:

```
hostname# ping 171.69.38.1
Sending 5, 100-byte ICMP Echos to 171.69.38.1, timeout is 2 seconds:
!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/10 ms
```

The following is an example of an extended ping:

```
hostname# ping
Interface: outside
Target IP address: 171.69.38.1
Repeat count: [5]
Datagram size: [100]
Timeout in seconds: [2]
Extended commands [n]:
Sweep range of sizes [n]:
Sending 5, 100-byte ICMP Echos to 171.69.38.1, timeout is 2 seconds:
!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/10 ms
```

Related Commands

Command	Description
capture	Captures packets at an interface
icmp	Configures access rules for ICMP traffic that terminates at an interface.
show interface	Displays information about the VLAN configuration.

police

To apply strict scheduling priority for this class, use the **police** command in class mode. To remove the rate-limiting requirement, use the **no** form of this command.

police [**output**] *conform-rate* {*conform-burst* | **conform-action** {**drop** | **transmit**} | **exceed-action** {**drop** | **transmit**}}

no police

Syntax Description

conform-action	The action to take when the rate is less than the conform-burst value.
<i>conform-burst</i>	A value in the range 1000-512000000, specifying the maximum number of instantaneous bytes allowed in a sustained burst before throttling to the conforming rate value.
<i>conform-rate</i>	The rate limit for this traffic flow; this is a value in the range 8000-2000000000, specifying the maximum speed (bits per second) allowed.
drop	Drop the packet.
exceed-action	Take this action when the rate is between the conform-rate value and the conform-burst value.
output	Enables policing of traffic flowing in the output direction.
transmit	Transmit the packet.

Defaults

No default behavior or variables.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class	—	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must have configured the **policy-map** command and the **class** command before issuing the **police** command.



Note

The **police** command merely enforces the maximum speed and burst rate, forcing them to the conforming rate value. It does not enforce the **conform-action** or the **exceed-action** specification if these are present.

Policing traffic in the inbound direction is not supported.

You cannot enable both priority and policing together.

If a service policy is applied or removed from an interface that has existing VPN client/LAN-to-LAN or non-tunneled traffic already established, the QoS policy is not applied or removed from the traffic stream. To apply or remove the QoS policy for such connections, you must clear (that is, drop) the connections and re-establish them.

Examples

The following is an example of a **police** command that sets the conform rate to 100,000 bits per second, a burst value of 2,000,000 bytes, and specifies that traffic that exceeds the burst rate will be dropped:

```
hostname(config)# policy-map localpolicy1
hostname(config-pmap)# class firstclass class
hostname(config-pmap-c)# police 100000 20000 exceed-action drop
hostname(config-pmap-c)# class class-default
hostname(config-pmap-c)# police 1000000 200000 exceed-action drop
hostname(config-pmap-c)# exit
```

Related Commands

class	Specifies a class-map to use for traffic classification.
clear configure policy-map	Remove all policy-map configuration, except that if a policy-map is in use in a service-policy command, that policy-map is not removed.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
show running-config policy-map	Display all current policy-map configurations.

policy

To specify the source for retrieving the CRL, use the **policy** command in ca-crl configuration mode.

policy {static | cdp | both}

Syntax Description

both	Specifies that if obtaining a CRL using the CRL distribution point fails, retry using static CDPs up to a limit of five.
cdp	Uses the CDP extension embedded within the certificate being checked. In this case, the security appliance retrieves up to five CRL distribution points from the CDP extension of the certificate being verified and augments their information with the configured default values, if necessary. If the security appliance attempt to retrieve a CRL using the primary CDP fails, it retries using the next available CDP in the list. This continues until either the security appliance retrieves a CRL or exhausts the list.
static	Uses up to five static CRL distribution points. If you specify this option, specify also the LDAP or HTTP URLs with the protocol command.

Defaults

The default setting is **cdp**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
CRL configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters ca-crl configuration mode, and configures CRL retrieval to occur using the CRL distribution point extension in the certificate being checked or if that fails, to use static CDPs:

```
hostname(configure)# crypto ca trustpoint central
hostname(ca-trustpoint)# crl configure
hostname(ca-crl)# policy both
hostname(ca-crl)#
```

Related Commands

Command	Description
crl configure	Enters ca-crl configuration mode.
crypto ca trustpoint	Enters trustpoint configuration mode.
url	Creates and maintains a list of static URLs for retrieving CRLs.

policy-map

To configure a policy, use the **policy-map** command in global configuration mode. To remove a policy, use the **no** form of this command.

policy-map *name*

no policy-map *name*

Syntax Description

name The name for this policy-map. The name can be up to 40 characters long.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced in this release.

Usage Guidelines

A **policy-map** command configures a policy, which is an association of a traffic class with one or more security-related actions. A traffic class is a set of traffic that is identifiable by its packet content. For example, TCP traffic with a port value of 23 can be classified as a Telnet traffic class. A policy consists of a **class** command and its associated actions. A policy map can specify multiple policies. A **service-policy** command activates a policy map globally on all interfaces or on a single targeted interface.

The **policy-map** command lets you classify traffic and then apply feature-specific actions to it.

The maximum number of policy maps is 64.

Use the **policy-map** command to enter policy-map mode, in which you can enter **class** and **description** commands. See the individual command descriptions for detailed information.

The order in which different types of actions in a policy-map are performed is independent of the order in which the actions appear in these command descriptions.

Examples

The following is an example of the **policy-map** command; note the change in the prompt:

```
hostname(config)# policy-map localpolicy1
hostname(config-pmap)#
```

The following is an example of a **policy-map** command for connection policy:

```
hostname(config)# access-list http-server permit tcp any host 10.1.1.1
hostname(config)# class-map http-server

hostname(config-cmap)# match access-list http-server
hostname(config-cmap)# exit

hostname(config)# policy-map global-policy global
hostname(config-pmap)# description This policy map defines a policy concerning connection
to http server.
hostname(config-pmap)# class http-server
hostname(config-pmap-c)# set connection conn-max 256
```

The following is an example of a **policy-map** command for the “outside” interface:

```
hostname(config)# class-map outside-voip
hostname(config-cmap)# match ip rtp 2000 100
hostname(config-cmap)# exit

hostname(config)# policy-map outside-policy
hostname(config-pmap)# description This policy map defines policies for the outside
interface.
hostname(config-pmap)# class outside-voip
hostname(config-pmap-c)# priority
hostname(config-pmap-c)# exit
hostname(config-pmap)#
```

Related Commands

Command	Description
class	Specifies a class-map for traffic classification.
clear configure policy-map	Remove all policy-map configuration, except that if a policy-map is in use in a service-policy command, that policy-map is not removed.
description	Specifies a description for the policy-map.
help policy-map	Shows syntax help for the policy-map command.
show running-config policy-map	Display all current policy-map configurations.

polltime interface

To specify the interval between hello packets on the interface, use the **polltime interface** command in failover group configuration mode. To restore the default value, use the **no** form of this command.

polltime interface *time*

no polltime interface *time*

Syntax Description

<i>time</i>	Amount of time between hello messages.

Defaults

The default is 15 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Failover group configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **polltime interface** command to change the frequency that hello packets are sent out on an interfaces associated with the current failover group. with a faster poll time, the security appliance can detect failure and trigger failover faster. However, faster detection can cause unnecessary switchovers when the network is temporarily congested.

Five missed consecutive interface hello packets cause interface testing.

This command is available for Active/Active failover only.

Examples

The following partial example shows a possible configuration for a failover group:

```
hostname(config)# failover group 1
hostname(config-fover-group)# primary
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# polltime interface 20
hostname(config-fover-group)# exit
hostname(config)#
```

Related Commands

Command	Description
failover group	Defines a failover group for Active/Active failover.
failover polltime	Configures the time between hello packets on monitored interfaces.

pop3s

To enter POP3S configuration mode, use the **pop3s** command in global configuration mode. To remove any commands entered in POP3S command mode, use the **no** version of this command.

POP3 is a client/server protocol in which your Internet server receives and holds e-mail for you. Periodically, you (or your client e-mail receiver) check your mail-box on the server and download any mail. This standard protocol is built into most popular e-mail products. POP3S lets you receive e-mail over an SSL connection.

pop3s

no pop3

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to enter POP3S configuration mode:

```
hostname(config)# pop3s
hostname(config-pop3s)#
```

Related Commands

Command	Description
clear configure pop3s	Removes the POP3S configuration.
show running-config pop3s	Displays the running configuration for POP3S.

port

To specify the port an e-mail proxy listens to, use the **port** command in the applicable e-mail proxy command mode. To revert to the default value, use the **no** version of this command.

port {*portnum*}

no port

Syntax Description

portnum	The port for the e-mail proxy to use. To avoid conflicts with local TCP services, use port numbers in the range 1024 to 65535.

Defaults

The default ports for e-mail proxies are as follows:

E-mail Proxy	Default Port
IMAP4S	993
POP3S	995
SMTPS	988

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Pop3s	•	—	•	—	—
Imap4s	•	—	•	—	—
Smtps	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

To avoid conflicts with local TCP services, use port numbers in the range 1024 to 65535.

Examples

The following example shows how to set port 1066 for the IMAP4S e-mail proxy:

```
hostname(config)# imap4s
hostname(config-imap4s)# port 1066
```

port-forward

To configure the set of applications that WebVPN users can access over forwarded TCP ports, use the **port-forward** command in global configuration mode. To configure access to multiple applications, use this command with the same *listname* multiple times, once for each application. To remove an entire configured list, use the **no port-forward listname** command. To remove a configured application, use the **no port-forward listname localport** command (you need not include the *remoteserver* and *remoteport* parameters).

port-forward {*listname localport remoteserver remoteport description*}

no port-forward *listname*

no port-forward *listname localport*

Syntax Description

<i>description</i>	Provides the application name or short description that displays on the end user Port Forwarding Java applet screen. Maximum 64 characters.
<i>listname</i>	Groups the set of applications (forwarded TCP ports) WebVPN users can access. Maximum 64 characters.
<i>localport</i>	Specifies the local port that listens for TCP traffic for an application. You can use a local port number only once for a <i>listname</i> .
<i>remoteport</i>	Specifies the port to connect to for this application on the remote server.
<i>remoteserver</i>	Provides the DNS name or IP address of the remote server for an application. We recommend using DNS names. For more information, see the <i>Cisco Security Appliance Command Line Configuration Guide</i> .

Defaults

There is no default port forwarding list.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration mode	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

To allow access to particular TCP port forwarding applications for a specific user or group policy, use the *listname* you create here with the **port-forward** command in webvpn mode.

Examples

The following example shows how to create a portforwarding list called *SalesGroupPorts* that provides access to IMAP4S e-mail, SMTPS e-mail, DDTS, and Telnet. The following table provides values that the example uses for each application.

Application	Local Port	Server DNS Name	Remote Port	Description
IMAP4S e-mail	143	IMAP4Sserver	20143	Get Mail
SMTPS e-mail	25	SMTPSserver	20025	Send Mail
DDTS over SSH	22	DDTSserver	20022	DDTS over SSH
Telnet	23	Telnetserver	20023	Telnet

```
hostname(config)# port-forward SalesGroupPorts 143 IMAP4Sserver 20143 Get Mail
hostname(config)# port-forward SalesGroupPorts 25 SMTPSserver 20025 Send Mail
hostname(config)# port-forward SalesGroupPorts 22 DDTSserver 20022 DDTS over SSH
hostname(config)# port-forward SalesGroupPorts 23 Telnetserver 20023 Telnet
```

Related Commands

Command	Description
clear configuration port-forward [listname]	Removes all port forwarding commands from the configuration. If you include the listname, the security appliance removes only the commands for that list.
port-forward	Use this command in webvpn mode to enable WebVPN application access for a user or group policy.
show running-config port-forward	Displays the current set of configured port-forward commands.
webvpn	Use in group-policy configuration mode or in username configuration mode. Lets you enter webvpn mode to configure parameters that apply to group policies or usernames.
webvpn	Use in global configuration mode. Lets you configure global settings for WebVPN.

port-forward (webvpn)

To enable WebVPN application access for this user or group policy, use the **port-forward** command in webvpn mode, which you enter from group-policy or username mode. To remove the port forwarding attribute from the configuration, including a null value created by issuing the **port-forward none** command, use the **no** form of this command. The **no** option allows inheritance of a list from another group policy. To prevent inheriting a port forwarding list, use the **port-forward none** command.

port-forward { **value** *listname* | **none** }

no port-forward

Syntax Description

none	Indicates that there is no filtering. Sets a null value, thereby disallowing a filtering. Prevents inheriting filtering values.
value <i>listname</i>	Identifies the list of applications WebVPN users can access. Use the port-forward command in configuration mode to define the list.

Defaults

Port forwarding is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn mode	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Using the command a second time overrides the previous setting.

Before you can use the **port-forward** command in webvpn mode to enable application access, you must define a list of applications that you want users to be able to use in a WebVPN connection. Use the **port-forward** command in global configuration mode to define this list.

Examples

The following example shows how to set a portforwarding list called *ports1* for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# webvpn
hostname(config-group-webvpn)# port-forward value ports1
```

Related Commands	Command	Description
	clear configuration port-forward [<i>listname</i>]	Removes all port forwarding commands from the configuration. If you include the listname, the security appliance removes only the commands for that list.
	port-forward	Use this command in configuration mode to define applications, or forwarded ports, that WebVPN users can access.
	show running-config port-forward	Displays the current set of configured port-forward commands.
	webvpn	Use in group-policy configuration mode or in username configuration mode. Lets you enter webvpn mode to configure parameters that apply to group policies or usernames.
	webvpn	Use in global configuration mode. Lets you configure global settings for WebVPN.

port-forward-name

To configure the display name that identifies TCP port forwarding to end users for a particular user or group policy, use the **port-forward-name** command in webvpn mode, which you enter from group-policy or username mode. To delete the display name, including a null value created by using the **port-forward-name none** command, use the no form of the command. The **no** option restores the default name, “Application Access.” To prevent a display name, use the **port-forward none** command.

port-forward-name {value *name* | none}

no port-forward-name

Syntax Description

none	Indicates that there is no display name. Sets a null value, thereby disallowing a display name. Prevents inheriting a value.
value <i>name</i>	Describes port forwarding to end users. Maximum of 255 characters.

Defaults

The default name is “Application Access.”

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to set the name, “Remote Access TCP Applications,” for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# webvpn
hostname(config-group-webvpn)# port-forward-name value Remote Access TCP Applications
```

Related Commands

Command	Description
webvpn	Use in group-policy configuration mode or in username configuration mode. Lets you enter webvpn mode to configure parameters that apply to group policies or usernames.
webvpn	Use in global configuration mode. Lets you configure global settings for WebVPN.

port-misuse

To restrict HTTP traffic by specifying a restricted application category, use the **port-misuse** command in HTTP map configuration mode, which is accessible using the **http-map** command. To disable this feature, use the **no** form of the command.

port-misuse {im | p2p | tunneling | default} action {allow | reset | drop} [log]

no port-misuse {im | p2p | tunneling | default} action {allow | reset | drop} [log]

Syntax Description

action	Specifies the action taken when an application in the configured category is detected.
allow	Allows the message.
default	Specifies the default action taken by the security appliance when the traffic contains a supported request method that is not on a configured list.
im	Restricts traffic in the instant messaging application category. The applications checked for are Yahoo Messenger, AIM, and MSN IM.
log	(Optional) Generates a syslog.
p2p	Restricts traffic in the peer-to-peer application category. The Kazaa application is checked.
reset	Sends a TCP reset message to client and server.
tunneling	Restricts traffic in the tunneling application category. The applications checked for are: HTTPPort/HTTHost, GNU Httptunnel, GotoMyPC, Firethru, and Http-tunnel.com Client.

Defaults

This command is disabled by default. When the command is enabled and a supported application category is not specified, the default action is to allow the connection without logging. To change the default action, use the **default** keyword and specify a different default action.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
HTTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

When you enable the **port-misuse** command, the security appliance applies the specified action to HTTP connections for each supported and configured application category.

The security appliance applies the **default** action to all traffic that does *not* match the application categories on the configured list. The preconfigured **default** action is to **allow** connections without logging.

For example, given the preconfigured default action, if you specify one or more application categories with the action of **drop** and **log**, the security appliance drops connections containing the configured application categories, logs each connection, and allows all connections for the other supported application types.

If you want to configure a more restrictive policy, change the default action to **drop** (or **reset**) and **log** (if you want to log the event). Then configure each permitted application type with the **allow** action.

Enter the **port-misuse** command once for each setting you wish to apply. You use one instance of the **port-misuse** command to change the default action and one instance to add each application category to the list of configured application types.



Caution

These inspections require searches in the entity body of the HTTP message and may affect the performance of the security appliance.

When you use the **no** form of the command to remove an application category from the list of configured application types, any characters in the command line after the application category keyword are ignored.

Examples

The following example provides a permissive policy, using the preconfigured default, which allows all supported application types that are not specifically prohibited.

```
hostname(config)# http-map inbound_http
hostname(config-http-map)# port-misuse p2p drop log
hostname(config-http-map)# exit
```

In this case, only connections in the peer-to-peer category are dropped and the events is logged.

The following example provides a restrictive policy, with the default action changed to reset the connection and to log the event for any application type that is not specifically allowed.

```
hostname(config)# http-map inbound_http
hostname(config-http-map)# port-misuse default action reset log
hostname(config-http-map)# port-misuse im allow
hostname(config-http-map)# exit
```

In this case, only the Instant Messenger application is allowed. When HTTP traffic for the other supported applications is received, the security appliance resets the connection and creates a syslog entry.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
<code>debug appfw</code>	Displays detailed information about traffic associated with enhanced HTTP inspection.
http-map	Defines an HTTP map for configuring enhanced HTTP inspection.
inspect http	Applies a specific HTTP map to use for application inspection.
policy-map	Associates a class map with specific security actions.

port-object

To add a port object to a service object group, use the **port-object** command in service configuration mode. To remove port objects, use the **no** form of this command.

port-object eq *service*

no port-object eq *service*

port-object range *begin_service end_service*

no port-object range *begin_service end_service*

Syntax Description

begin_service	Specifies the decimal number or name of a TCP or UDP port that is the beginning value for a range of services. This value must be between 0 and 65535.
end_service	Specifies the decimal number or name of a TCP or UDP port that is the ending value for a range of services. This value must be between 0 and 65535.
eq service	Specifies the decimal number or name of a TCP or UDP port for a service object.
range	Specifies a range of ports (inclusive).

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Service configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **port-object** command is used with the [object-group](#) command to define an object that is either a specific service (port) or a range of services (ports) in service configuration mode.

If a name is specified for a TCP or UDP service, it must be one of the supported TCP or/and UDP names, and must be consistent with the protocol type of the object group. For instance, for a protocol types of tcp, udp, and tcp-udp, the names must be a valid TCP service name, a valid UDP service name, or a valid TCP and UDP service name, respectively.

If a number is specified, translation to its corresponding name (if one exists) based on the protocol type will be made when showing the object.

The following service names are supported:

Table 6-1

TCP	UDP	TCP and UDP
bgp	biff	discard
chargen	bootpc	domain
cmd	bootps	echo
daytime	dnsix	pim-auto-rp
exec	nameserver	sunrpc
finger	mobile-ip	syslog
ftp	netbios-ns	tacacs
ftp-data	netbios-dgm	talk
gopher	ntp	
ident	rip	
irc	snmp	
h323	snmptrap	
hostname	tftp	
http	time	
klogin	who	
kshell	xmcp	
login	isakmp	
lpd		
nnntp		
pop2		
pop3		
smtp		
sqlnet		
telnet		
uucp		
whois		
www		

Examples

This example shows how to use the **port-object** command in service configuration mode to create a new port (service) object group:

```
hostname(config)# object-group service eng_service tcp
hostname(config-service)# port-object eq smtp
hostname(config-service)# port-object eq telnet
hostname(config)# object-group service eng_service udp
```

```

hostname(config-service)# port-object eq snmp
hostname(config)# object-group service eng_service tcp-udp
hostname(config-service)# port-object eq domain
hostname(config-service)# port-object range 2000 2005
hostname(config-service)# quit

```

Related Commands

Command	Description
clear configure object-group	Removes all the object-group commands from the configuration.
group-object	Adds network object groups.
network-object	Adds a network object to a network object group.
object-group	Defines object groups to optimize your configuration.
show running-config object-group	Displays the current object groups.

preempt

To cause the unit to become active on boot if it has the higher priority, use the **preempt** command in failover group configuration mode. To remove the preemption, use the **no** form of this command.

preempt [*delay*]

no preempt [*delay*]

Syntax Description

seconds The wait time, in seconds, before the peer is preempted. Valid values are from 1 to 1200 seconds.

Defaults

By default, there is no delay.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Failover group configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Assigning a primary or secondary priority to a failover group specifies which unit the failover group becomes active on when both units boot simultaneously (within a unit polltime). However, if one unit boots before the other, then both failover groups become active on that unit. When the other unit comes online, any failover groups that have the second unit as a priority do not become active on the second unit unless the failover group is configured with the **preempt** command or is manually forced to the other unit with the **no failover active** command. If the failover group is configured with the **preempt** command, the failover group automatically becomes active on the designated unit.



Note

If Stateful Failover is enabled, the preemption is delayed until the connections are replicated from the unit on which the failover group is currently active.

Examples

The following example configures failover group 1 with the primary unit as the higher priority and failover group 2 with the secondary unit as the higher priority. Both failover groups are configured with the **preempt** command with a wait time of 100 seconds, so the groups will automatically become active on their preferred unit 100 seconds after the units become available.

```
hostname(config)# failover group 1
```

```

hostname(config-fover-group)# primary
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# exit
hostname(config)# failover group 2
hostname(config-fover-group)# secondary
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# mac-address e1 0000.a000.a011 0000.a000.a012
hostname(config-fover-group)# exit
hostname(config)#

```

Related Commands

Command	Description
failover group	Defines a failover group for Active/Active failover.
primary	Gives the primary unit in a failover pair priority for the failover group being configured.
secondary	Gives the secondary unit in a failover pair priority for the failover group being configured.

prefix-list

To create an entry in a prefix list for ABR type 3 LSA filtering, use the **prefix-list** command in global configuration mode. To remove a prefix list entry, use the **no** form of this command.

```
prefix-list prefix-list-name [seq seq_num] {permit | deny} network/len [ge min_value] [le max_value]
```

```
no prefix-list prefix-list-name [seq seq_num] {permit | deny} network/len [ge min_value] [le max_value]
```

Syntax Description

/	A required separator between the <i>network</i> and <i>len</i> values.
deny	Denies access for a matching condition.
ge <i>min_value</i>	(Optional) Specifies the minimum prefix length to be matched. The value of the <i>min_value</i> argument must be greater than the value of the <i>len</i> argument and less than or equal to the <i>max_value</i> argument, if present.
le <i>max_value</i>	(Optional) Specifies the maximum prefix length to be matched. The value of the <i>max_value</i> argument must be greater than or equal to the value of the <i>min_value</i> argument, if present, or greater than the value of the <i>len</i> argument if the <i>min_value</i> argument is not present.
<i>len</i>	The length of the network mask. Valid values are from 0 to 32.
<i>network</i>	The network address.
permit	Permits access for a matching condition.
<i>prefix-list-name</i>	The name of the prefix list. The prefix-list name cannot contain spaces.
seq <i>seq_num</i>	(Optional) Applies the specified sequence number to the prefix list being created.

Defaults

If you do not specify a sequence number, the first entry in a prefix list is assigned a sequence number of 5, and the sequence number for each subsequent entry is increased by 5.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **prefix-list** commands are ABR type 3 LSA filtering commands. ABR type 3 LSA filtering extends the capability of an ABR that is running OSPF to filter type 3 LSAs between different OSPF areas. Once a prefix list is configured, only the specified prefixes are sent from one area to another area. All other prefixes are restricted to their OSPF area. You can apply this type of area filtering to traffic going into or coming out of an OSPF area, or to both the incoming and outgoing traffic for that area.

When multiple entries of a prefix list match a given prefix, the entry with the lowest sequence number is used. The security appliance begins the search at the top of the prefix list, with the entry with the lowest sequence number. Once a match is made, the security appliance does not go through the rest of the list. For efficiency, you may want to put the most common matches or denials near the top of the list by manually assigning them a lower sequence number.

By default, the sequence numbers are automatically generated. They can be suppressed with the **no prefix-list sequence-number** command. Sequence numbers are generated in increments of 5. The first sequence number generated in a prefix list would be 5. The next entry in that list would have a sequence number of 10, and so on. If you specify a value for an entry, and then do not specify values for subsequent entries, the generated sequence numbers are increased from the specified value in increments of 5. For example, if you specify that the first entry in the prefix list has a sequence number of 3, and then add two more entries without specifying a sequence number for the additional entries, the automatically generated sequence numbers for those two entries would be 8 and 13.

You can use the **ge** and **le** keywords to specify the range of the prefix length to be matched for prefixes that are more specific than the *network/len* argument. Exact match is assumed when neither the **ge** or **le** keywords are specified. The range is from *min_value* to 32 if only the **ge** keyword is specified. The range is from *len* to *max_value* if only the **le** keyword is specified.

The value of the *min_value* and *max_value* arguments must satisfy the following condition:

$$len < min\_value \leq max\_value \leq 32$$

Use the **no** form of the command to remove specific entries from the prefix list. Use the **clear configure prefix-list** command to remove a prefix list. The **clear configure prefix-list** command also removes the associated **prefix-list description** command, if any, from the configuration.

Examples

The following example denies the default route 0.0.0.0/0:

```
hostname(config)# prefix-list abc deny 0.0.0.0/0
```

The following example permits the prefix 10.0.0.0/8:

```
hostname(config)# prefix-list abc permit 10.0.0.0/8
```

The following example shows how to accept a mask length of up to 24 bits in routes with the prefix 192/8:

```
hostname(config)# prefix-list abc permit 192.168.0.0/8 le 24
```

The following example shows how to deny mask lengths greater than 25 bits in routes with a prefix of 192/8:

```
hostname(config)# prefix-list abc deny 192.168.0.0/8 ge 25
```

The following example shows how to permit mask lengths from 8 to 24 bits in all address space:

```
hostname(config)# prefix-list abc permit 0.0.0.0/0 ge 8 le 24
```

The following example shows how to deny mask lengths greater than 25 bits in all address space:

```
hostname(config)# prefix-list abc deny 0.0.0.0/0 ge 25
```


The following example shows how to deny all routes with a prefix of 10/8:

```
hostname(config)# prefix-list abc deny 10.0.0.0/8 le 32
```

The following example shows how to deny all masks with a length greater than 25 bits for routes with a prefix of 192.168.1/24:

```
hostname(config)# prefix-list abc deny 192.168.1.0/24 ge 25
```

The following example shows how to permit all routes with a prefix of 0/0:

```
hostname(config)# prefix-list abc permit 0.0.0.0/0 le 32
```

Related Commands

Command	Description
clear configure prefix-list	Removes the prefix-list commands from the running configuration.
prefix-list description	Lets you to enter a description for a prefix list.
prefix-list sequence-number	Enables prefix list sequence numbering.
show running-config prefix-list	Displays the prefix-list commands in the running configuration.

prefix-list description

To add a description to a prefix list, use the **prefix-list description** command in global configuration mode. To remove a prefix list description, use the **no** form of this command.

prefix-list *prefix-list-name* **description** *text*

no prefix-list *prefix-list-name* **description** [*text*]

Syntax Description

<i>prefix-list-name</i>	The name of a prefix list.
<i>text</i>	The text of the prefix list description. You can enter a maximum of 80 characters.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

You can enter **prefix-list** and **prefix-list description** commands in any order for a particular prefix list name; you do not need to create the prefix list before entering a prefix list description. The **prefix-list description** command will always appear on the line before the associated prefix list in the configuration, no matter what order you enter the commands.

If you enter a **prefix-list description** command for a prefix list entry that already has a description, the new description replaces the original description.

You do not need to enter the text description when using the **no** form of this command.

Examples

The following example adds a description for a prefix list named MyPrefixList. The **show running-config prefix-list** command shows that although the prefix list description has been added to the running configuration, the prefix-list itself has not been configured.

```
hostname(config)# prefix-list MyPrefixList description A sample prefix list description
hostname(config)# show running-config prefix-list
```

```
!
prefix-list MyPrefixList description A sample prefix list description
```

!

Related Commands	Command	Description
	clear configure prefix-list	Removes the prefix-list commands from the running configuration.
	prefix-list	Defines a prefix list for ABR type 3 LSA filtering.
	show running-config prefix-list	Displays the prefix-list commands in the running configuration.

prefix-list sequence-number

To enable prefix list sequence numbering, use the **prefix-list sequence-number** command in global configuration mode. To disable prefix list sequence numbering, use the **no** form of this command.

prefix-list sequence-number

Syntax Description

This command has no arguments or keywords.

Defaults

Prefix list sequence numbering is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Only the **no** form of this command appears in the configuration. When the **no** form of this command is in the configuration, the sequence numbers, including the manually configured ones, are removed from the **prefix-list** commands in the configuration and new prefix lists entries are not assigned a sequence number.

When prefix list sequence numbering is enabled, all prefix list entries are assigned sequence numbers using the default numbering method (starting with 5 and incrementing each number by 5). If a sequence number was manually assigned to a prefix list entry before numbering was disabled, the manually assigned number is restored. Sequence numbers that are manually assigned while automatic numbering is disabled are also restored, even though they are not displayed while numbering is disabled.

Examples

The following example disables prefix list sequence numbering:

```
hostname(config)# no prefix-list sequence-number
```

Related Commands

Command	Description
prefix-list	Defines a prefix list for ABR type 3 LSA filtering.
show running-config prefix-list	Displays the prefix-list commands in the running configuration.

pre-shared-key

To specify a preshared key to support IKE connections based on preshared keys, use the **pre-shared-key** command in tunnel-group ipsec-attributes configuration mode. To return to the default value, use the **no** form of this command.

pre-shared-key *key*

no pre-shared-key

Syntax Description

key Specifies an alphanumeric key between 1 and 128 characters.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group ipsec attributes configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute to all tunnel-group types.

Examples

The following command entered in config-ipsec configuration mode, specifies the preshared key XYZX to support IKE connections for the IPsec LAN-to-LAN tunnel group named 209.165.200.225:

```
hostname(config)# tunnel-group 209.165.200.225 type IPSec_L2L
hostname(config)# tunnel-group 209.165.200.225 ipsec-attributes
hostname(config-ipsec)# pre-shared-key xyzx
hostname(config-ipsec)#
```

Related Commands

Command	Description
clear configure tunnel-group	Clears all configured tunnel groups.
show running-config tunnel-group	Shows the indicated certificate map entry.
tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

primary

To give the primary unit higher priority for a failover group, use the **primary** command in failover group configuration mode. To restore the default value, use the **no** form of this command.

primary

no primary

Syntax Description

This command has no arguments or keywords.

Defaults

If **primary** or **secondary** is not specified for a failover group, the failover group defaults to **primary**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Failover group configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Assigning a primary or secondary priority to a failover group specifies which unit the failover group becomes active on when both units boot simultaneously (within a unit polltime). If one unit boots before the other, then both failover groups become active on that unit. When the other unit comes online, any failover groups that have the second unit as a priority do not become active on the second unit unless the failover group is configured with the **preempt** command or is manually forced to the other unit with the **no failover active** command.

Examples

The following example configures failover group 1 with the primary unit as the higher priority and failover group 2 with the secondary unit as the higher priority. Both failover groups are configured with the **preempt** command, so the groups will automatically become active on their preferred unit as the units become available.

```
hostname(config)# failover group 1
hostname(config-fover-group)# primary
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# exit
hostname(config)# failover group 2
hostname(config-fover-group)# secondary
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# mac-address e1 0000.a000.a011 0000.a000.a012
hostname(config-fover-group)# exit
```

```
hostname(config)#
```

Related Commands

Command	Description
failover group	Defines a failover group for Active/Active failover.
preempt	Forces the failover group to become active on its preferred unit when the unit becomes available.
secondary	Gives the secondary unit a higher priority than the primary unit.

priority

To apply strict scheduling priority for this class, use the **priority** command in class mode. To remove the priority requirement, use the **no** form of this command.

priority

no priority

Syntax Description

This command has no parameters or variables.

Defaults

No default behavior or variables.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class	—	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must have configured the **policy-map** command and the **class** command before issuing the **priority** command.

Examples

The following is an example of the **priority** command in policy-map mode:

```
hostname(config)# policy-map localpolicy1
hostname(config-pmap)# class firstclass
hostname(config-pmap-c)# priority
hostname(config-pmap-c)# class class-default
hostname(config-pmap-c)# exit
```

Related Commands

class	Specifies a class-map to use for traffic classification.
clear configure policy-map	Remove all policy-map configuration, except that if a policy-map is in use in a service-policy command, that policy-map is not removed.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
show running-config policy-map	Display all current policy-map configurations.

priority (vpn load balancing)

To set the priority of the local device participating in the virtual load-balancing cluster, use the **priority** command in VPN load-balancing mode. To revert to the default priority specification, use the **no** form of this command.

priority *priority*

no priority

Syntax Description

priority The priority, in the range of 1 to 10, that you want to assign to this device.

Defaults

The default priority depends on the model number of the device:

Model Number	Default Priority
5520	5
5540	7

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
VPN load-balancing	—	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must first use the **vpn load-balancing** command to enter VPN load-balancing mode.

This command sets the priority of the local device participating in the virtual load-balancing cluster.

The priority must be an integer in the range of 1 (lowest) to 10 (highest).

The priority is used in the master-election process as one way to determine which of the devices in a VPN load-balancing cluster becomes the master or primary device for the cluster. See *Cisco Security Appliance Command Line Configuration Guide* for details about the master-election process.

The **no** form of the command reverts the priority specification to the default value.

Examples

The following is an example of a VPN load-balancing command sequence that includes a **priority** command that sets the priority of the current device to 9:

```
hostname(config)# interface GigabitEthernet 0/1
```

■ priority (vpn load balancing)

```

hostname(config-if)# ip address 209.165.202.159 255.255.255.0
hostname(config)# nameif test
hostname(config)# interface GigabitEthernet 0/2
hostname(config-if)# ip address 209.165.201.30 255.255.255.0
hostname(config)# nameif foo
hostname(config)# vpn load-balancing
hostname(config-load-balancing)# priority 9
hostname(config-load-balancing)# interface lbpublic test
hostname(config-load-balancing)# interface lbprivate foo
hostname(config-load-balancing)# cluster ip address 209.165.202.224
hostname(config-load-balancing)# participate

```

Related Commands

Command	Description
vpn load-balancing	Enter VPN load-balancing mode.

priority-queue

To configure priority queuing on an interface, use the `priority-queue` command in global configuration mode. To remove this specification, use the **no** form of this command.

priority-queue *interface-name*

no priority queue *interface-name*

Syntax Description

<i>interface-name</i>	Specifies the name of the physical interface on which you want to enable priority queuing.

Defaults

By default, priority queuing is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	—	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The security appliance allows two classes of traffic: low-latency queuing (LLQ) for higher priority, latency sensitive traffic (such as voice and video) and best-effort, the default, for all other traffic. The security appliance recognizes priority traffic and enforces appropriate Quality of Service (QoS) policies. You can configure the size and depth of the priority queue to fine-tune the traffic flow.

For priority queuing to occur, you must create a priority queue for a named, physical interface. To create the priority queue, use the **priority-queue** command in global configuration mode. In general, you can apply one **priority-queue** command to each physical interface defined by the **nameif** command. You cannot apply a **priority-queue** command to a VLAN interface, except on an ASA 5505 security appliance. On the ASA 5500, you configure the **nameif** command under a VLAN interface, so you must apply the **priority-queue** command there as well.

The **priority-queue** command enters priority-queue mode, as shown by the prompt. In priority-queue mode, you can configure the maximum number of packets allowed in the transmit queue at any given time (**tx-ring-limit** command) and the number of packets of either type (priority or best -effort) allowed to be buffered before dropping packets (**queue-limit** command).

The tx-ring-limit and the queue-limit values that you specify affect both the higher priority low-latency queue and the best-effort queue. The tx-ring-limit is the number of either type of packets allowed into the driver before the driver pushes back to the queues sitting in front of the interface to let them buffer packets until the congestion clears. In general, you can adjust these two parameters to optimize the flow of low-latency traffic.

Because queues are not of infinite size, they can fill and overflow. When a queue is full, any additional packets cannot get into the queue and are dropped. This is *tail drop*. To avoid having the queue fill up, you can use the **queue-limit** command to increase the queue buffer size.

**Note**

The upper limit of the range of values for the **queue-limit** and **tx-ring-limit** commands is determined dynamically at run time. To view this limit, enter **help** or **?** on the command line. The key determinant is the memory needed to support the queues and the memory available on the device. The queues must not exceed the available memory. The theoretical maximum number of packets is 2147483647 (that is, up to line speed at full duplex).

If a service policy is applied or removed from an interface that has existing VPN client/LAN-to-LAN or non-tunneled traffic already established, the QoS policy is not applied or removed from the traffic stream. To apply or remove the QoS policy for such connections, you must clear (that is, drop) the connections and re-establish them.

You cannot enable both priority and policing together.

Examples

The following example configures a priority queue for the interface named test, specifying a queue limit of 30,000 packets and a transmit queue limit of 256 packets.

```
hostname(config)# priority-queue test
hostname(priority-queue)# queue-limit 30000
hostname(priority-queue)# tx-ring-limit 256
```

Related Commands

Command	Description
queue-limit	Specifies the maximum number of packets that can be enqueued to a priority queue before it drops data.
tx-ring-limit	Sets the maximum number of packets that can be queued at any given time in the Ethernet transmit driver.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
clear configure priority-queue	Removes the current priority queue configuration.
show running-config [all] priority-queue	Shows the current priority queue configuration. If you specify the all keyword, this command displays all the current priority queue, queue-limit, and tx-ring-limit configuration values.

privilege

To configure the command privilege levels, use the **privilege** command in global configuration mode. To disallow the configuration, use the **no** form of this command.

privilege [**show** | **clear** | **configure**] **level** *level* [**mode** { **enable** | **configure** }] **command** *command*

no privilege [**show** | **clear** | **configure**] **level** *level* [**mode** { **enable** | **configure** }] **command** *command*

Syntax Description

clear	(Optional) Sets the privilege level for the clear command corresponding to the command specified.
command <i>command</i>	Specifies the command on which to set the privilege level.
configure	(Optional) Sets the privilege level for the command specified.
level <i>level</i>	Specifies the privilege level; valid values are from 0 to 15.
mode enable	(Optional) Indicates that the level is for the enable mode of the command.
mode configure	(Optional) Indicates that the level is for the configure mode of the command.
show	(Optional) Sets the privilege level for the show command corresponding to the command specified.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **privilege** command lets you set user-defined privilege levels for the security appliance commands. In particular, this command is useful for setting different privilege levels for related configuration, show, and clear commands. Make sure that you verify privilege level changes in your commands with your security policies before using the new privilege levels.

When commands and users have privilege levels set, the two are compared to determine if a given user can execute a given command. If the user's privilege level is lower than the privilege level of the command, the user is prevented from executing the command.

To change between privilege levels, use the **login** command to access another privilege level and the appropriate **logout**, **exit**, or **quit** command to exit that level.

The **mode enable** and **mode configure** keywords are for commands with both enable and configure modes.

Lower privilege level numbers are lower privilege levels.


Note

The **aaa authentication** and **aaa authorization** commands need to include any new privilege levels that you define before you can use them in your AAA server configuration.

Examples

This example shows how to set the privilege level “5” for an individual user as follows:

```
username intern1 password pass1 privilege 5
```

This example shows how to define a set of **show** commands with the privilege level “5” as follows:

```
hostname(config)# privilege show level 5 command alias
hostname(config)# privilege show level 5 command apply
hostname(config)# privilege show level 5 command arp
hostname(config)# privilege show level 5 command auth-prompt
hostname(config)# privilege show level 5 command blocks
```

This example shows how to apply privilege level 11 to a complete AAA authorization configuration:

```
hostname(config)# privilege configure level 11 command aaa
hostname(config)# privilege configure level 11 command aaa-server
hostname(config)# privilege configure level 11 command access-group
hostname(config)# privilege configure level 11 command access-list
hostname(config)# privilege configure level 11 command activation-key
hostname(config)# privilege configure level 11 command age
hostname(config)# privilege configure level 11 command alias
hostname(config)# privilege configure level 11 command apply
```

Related Commands

Command	Description
clear configure privilege	Remove privilege command statements from the configuration.
show curpriv	Display current privilege level.
show running-config privilege	Display privilege levels for commands.

protocol http

To specify HTTP as a permitted distribution point protocol for retrieving a CRL, use the **protocol http** command in ca-crl configuration mode. Subject to permission, the content of the CRL distribution point determines the retrieval method (HTTP, LDAP, and/or SCEP).

To remove HTTP as the permitted method of CRL retrieval, use the **no** form of this command.

protocol http

no protocol http

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting is to permit HTTP.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
CRL configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If you use this command, be sure to assign HTTP rules to the public interface filter.

Examples

The following example enters ca-crl configuration mode, and permits HTTP as a distribution point protocol for retrieving a CRL for trustpoint central:

```
hostname(configure)# crypto ca trustpoint central
hostname(ca-trustpoint)# crl configure
hostname(ca-crl)# protocol http
hostname(ca-crl)#
```

Related Commands

Command	Description
crl configure	Enters ca-crl configuration mode.
crypto ca trustpoint	Enters trustpoint configuration mode.
protocol ldap	Specifies LDAP as a retrieval method for CRLs.
protocol scep	Specifies SCEP as a retrieval method for CRLs.

protocol ldap

To specify LDAP as a distribution point protocol for retrieving a CRL, use the **protocol ldap** command in ca-crl configuration mode. Subject to permission, the content of the CRL distribution point determines the retrieval method (HTTP, LDAP, and/or SCEP).

To remove the LDAP protocol as the permitted method of CRL retrieval, use the **no** form of this command.

protocol ldap

no protocol ldap

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting is to permit LDAP.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
CRL configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters ca-crl configuration mode, and permits LDAP as a distribution point protocol for retrieving a CRL for trustpoint central:

```
hostname(configure)# crypto ca trustpoint central
hostname(ca-trustpoint)# crl configure
hostname(ca-crl)# protocol ldap
hostname(ca-crl)#
```

Related Commands

Command	Description
crl configure	Enters ca-crl configuration mode.
crypto ca trustpoint	Enters trustpoint configuration mode.
protocol http	Specifies HTTP as a retrieval method for CRLs
protocol scep	Specifies SCEP as a retrieval method for CRLs

protocol scep

To specify SCEP as a distribution point protocol for retrieving a CRL, use the **protocol scep** command in **crl configure** mode. Subject to permission, the content of the CRL distribution point determines the retrieval method (HTTP, LDAP, and/or SCEP).

To remove the SCEP protocol as the permitted method of CRL retrieval, use the **no** form of this command.

protocol scep

no protocol scep

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting is to permit SCEP.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
CRL configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters **ca-crl** configuration mode, and permits SCEP as a distribution point protocol for retrieving a CRL for trustpoint central:

```
hostname(configure)# crypto ca trustpoint central
hostname(ca-trustpoint)# crl configure
hostname(ca-crl)# protocol scep
hostname(ca-crl)#
```

Related Commands

Command	Description
crl configure	Enters ca-crl configuration mode.
crypto ca trustpoint	Enters trustpoint configuration mode.
protocol http	Specifies HTTP as a retrieval method for CRLs
protocol ldap	Specifies LDAP as a retrieval method for CRLs

protocol-object

To add a protocol object to a protocol object group, use the **protocol-object** command in protocol configuration mode. To remove port objects, use the **no** form of this command.

protocol-object *protocol*

no protocol-object *protocol*

Syntax Description

protocol Protocol name or number.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Protocol configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **protocol-object** command is used with the [object-group](#) command to define a protocol object in protocol configuration mode.

You can specify an IP protocol name or number using the *protocol* argument. The udp protocol number is 17, the tcp protocol number is 6, and the egp protocol number is 47.

Examples

The following example shows how to define protocol objects:

```
hostname(config)# object-group protocol proto_grp_1
hostname(config-protocol)# protocol-object udp
hostname(config-protocol)# protocol-object tcp
hostname(config-protocol)# exit
hostname(config)# object-group protocol proto_grp
hostname(config-protocol)# protocol-object tcp
hostname(config-protocol)# group-object proto_grp_1
hostname(config-protocol)# exit
hostname(config)#
```

Related Commands

Command	Description
clear configure object-group	Removes all the object group commands from the configuration.
group-object	Adds network object groups.
network-object	Adds a network object to a network object group.
object-group	Defines object groups to optimize your configuration.
show running-config object-group	Displays the current object groups.

pwd

To display the current working directory, use the **pwd** command in privileged EXEC mode.

pwd

Syntax Description

This command has no arguments or keywords.

Defaults

The root directory (/) is the default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is similar in functionality to the **dir** command.

Examples

The following example shows how to display the current working directory:

```
hostname# pwd
disk0:/
hostname# pwd
flash:
```

Related Commands

Command	Description
cd	Changes the current working directory to the one specified.
dir	Displays the directory contents.
more	Displays the contents of a file.

queue-limit (priority-queue)

To specify the depth of the priority queues, use the **queue-limit** command in priority-queue mode. To remove this specification, use the **no** form of this command.

queue-limit *number-of-packets*

no queue-limit *number-of-packets*

Syntax Description

number-of-packets Specifies the maximum number of low-latency or normal priority packets that can be queued (that is, buffered) before the interface begins dropping packets. See the Usage Notes section for the range of possible values.

Defaults

The default queue limit is 1024 packets.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Priority-queue	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The security appliance allows two classes of traffic: low-latency queuing (LLQ) for higher priority, latency sensitive traffic (such as voice and video) and best-effort, the default, for all other traffic. The security appliance recognizes priority traffic and enforces appropriate Quality of Service (QoS) policies. You can configure the size and depth of the priority queue to fine-tune the traffic flow.

You must use the **priority-queue** command to create the priority queue for an interface before priority queuing takes effect. You can apply one **priority-queue** command to any interface that can be defined by the **nameif** command.

The **priority-queue** command enters priority-queue mode, as shown by the prompt. In priority-queue mode, you can configure the maximum number of packets allowed in the transmit queue at any given time (**tx-ring-limit** command) and the number of packets of either type (priority or best -effort) allowed to be buffered before dropping packets (**queue-limit** command).



Note

You *must* configure the **priority-queue** command in order to enable priority queueing for the interface.

The tx-ring-limit and the queue-limit that you specify affect both the higher priority low-latency queue and the best-effort queue. The tx-ring-limit is the number of either type of packets allowed into the driver before the driver pushes back to the queues sitting in front of the interface to let them buffer packets until the congestion clears. In general, you can adjust these two parameters to optimize the flow of low-latency traffic.

Because queues are not of infinite size, they can fill and overflow. When a queue is full, any additional packets cannot get into the queue and are dropped. This is *tail drop*. To avoid having the queue fill up, you can use the **queue-limit** command to increase the queue buffer size.

**Note**

The upper limit of the range of values for the **queue-limit** and **tx-ring-limit** commands is determined dynamically at run time. To view this limit, enter **help** or **?** on the command line. The key determinant is the memory needed to support the queues and the memory available on the device. The queues must not exceed the available memory. The theoretical maximum number of packets is 2147483647.

Examples

The following example configures a priority queue for the interface named test, specifying a queue limit of 30,000 packets and a transmit queue limit of 256 packets.

```
hostname(config)# priority-queue test
hostname(priority-queue)# queue-limit 30000
hostname(priority-queue)# tx-ring-limit 256
```

Related Commands

Command	Description
clear configure priority-queue	Removes the current priority queue configuration on the named interface.
priority-queue	Configures priority queuing on an interface.
show priority-queue statistics	Shows the priority-queue statistics for the named interface.
show running-config [all] priority-queue	Shows the current priority queue configuration. If you specify the all keyword, this command displays all the current priority queue, queue-limit, and tx-ring-limit configuration values.
tx-ring-limit	Sets the maximum number of packets that can be queued at any given time in the Ethernet transmit driver.

queue-limit (tcp-map)

To configure the maximum number of out-of-order packets that can be queued on a TCP stream, use the **queue-limit** command in tcp-map configuration mode. To remove this specification, use the **no** form of this command.

queue-limit *pkt_num*

no queue-limit *pkt_num*

Syntax Description

<i>pkt_num</i>	Specifies the maximum number of out-of-order packets that can be queued for a TCP connection before they are dropped. For ASA, the range is 0 to 250 with the default being 0. For PIX, the packet number is 3 and cannot be changed.

Defaults

The default maximum number of packets is 0 for the ASA platform. For PIX, the number is 3 and cannot be changed.

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Tcp-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines

The **tcp-map** command is used along with the Modular Policy Framework infrastructure. Define the class of traffic using the **class-map** command and customize the TCP inspection with **tcp-map** commands. Apply the new tcp map using the **policy-map** command. Activate TCP inspection with **service-policy** commands.

Use the **tcp-map** command to enter tcp-map configuration mode. Use the **queue-limit** command in tcp-map configuration mode to enable TCP packet ordering on any TCP connection or change the queue limit for connections that are ordered by default.

Packets will be ordered on TCP connections if any of the following features have been enabled: inspect, IDS feature, or TCP check-retransmission. The default packet queue limit for connections that are ordered is two per flow. For all other TCP connections, packets are forwarded as received, including out-of-order packets. To enable TCP packet ordering on any TCP connection or change the queue limit for connections that are ordered, use the **queue-limit** command. Enabling this feature results in out-of-order packets being queued until they can be forwarded or a fixed amount of time. Hence, memory usage is increased due to packet buffering.

Examples

The following example shows how to enable TCP packet ordering on all telnet connections:

```
hostname(config)# tcp-map tmap
hostname(config-tcp-map)# queue-limit 8
hostname(config)# class-map cmap
hostname(config-cmap)# match port tcp eq telnet
hostname(config)# policy-map pmap
hostname(config-pmap)# class cmap
hostname(config-pmap)# set connection advanced-options tmap
hostname(config)# service-policy pmap global
```

Related Commands

Command	Description
class-map	Specifies a class map to use for traffic classification.
help	Shows syntax help for the policy-map , class , and description commands.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
set connection	Configures connection values.
tcp-map	Creates a TCP map and allows access to tcp-map configuration mode.

quit

To exit the current configuration mode, or to logout from privileged or user EXEC modes, use the **quit** command.

quit

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC	•	•	•	•	•

Release	Modification
Preexisting	This command was preexisting.

Command History

Usage Guidelines You can also use the key sequence **Ctrl Z** to exit global configuration (and higher) modes. This key sequence does not work with privileged or user EXEC modes.

When you enter the **quit** command in privileged or user EXEC modes, you log out from the security appliance. Use the **disable** command to return to user EXEC mode from privileged EXEC mode.

Examples The following example shows how to use the **quit** command to exit global configuration mode, and then logout from the session:

```
hostname(config)# quit
hostname# quit

Logoff
```

The following example shows how to use the **quit** command to exit global configuration mode, and then use the **disable** command to exit privileged EXEC mode:

```
hostname(config)# quit
hostname# disable
hostname>
```

Related Commands

Command	Description
exit	Exits a configuration mode or logs out from privileged or user EXEC modes.

radius-common-pw

To specify a common password to be used for all users who are accessing this RADIUS authorization server through this security appliance, use the **radius-common-pw** command in AAA-server host mode. To remove this specification, use the **no** form of this command:

radius-common-pw *string*

no radius-common-pw

Syntax Description

<i>string</i>	A case-sensitive, alphanumeric keyword of up to 127 characters to be used as a common password for all authorization transactions with this RADIUS server.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
AAA-server host	•	•	•	•	—

Command History

Release	Modification
7.0	Introduced in this release.

Usage Guidelines

This command is valid only for RADIUS authorization servers.

The RADIUS authorization server requires a password and username for each connecting user. The security appliance provides the username automatically. You enter the password here. The RADIUS server administrator must configure the RADIUS server to associate this password with each user authorizing to the server via this security appliance. Be sure to provide this information to your RADIUS server administrator.

If you do not specify a common user password, each user's password is his or her own username. For example, a user with the username "jsmith" would enter "jsmith". If you are using usernames for the common user passwords, as a security precaution do not use this RADIUS server for authorization anywhere else on your network.



Note

This field is essentially a space-filler. The RADIUS server expects and requires it, but does not use it. Users do not need to know it.

Examples

The following example configures a RADIUS AAA server group named “svrgrp1” on host “1.2.3.4”, sets the timeout interval to 9 seconds, sets the retry interval to 7 seconds, and configures the RADIUS common password as “allauthpw”.

```
hostname(config)# aaa-server svrgrp1 protocol radius
hostname(config-aaa-server-group)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# timeout 9
hostname(config-aaa-server-host)# retry 7
hostname(config-aaa-server-host)# radius-common-pw allauthpw
hostname(config-aaa-server-host)# exit
hostname(config)#
```

Related Commands

Command	Description
aaa-server host	Enter AAA server host configuration mode so you can configure AAA server parameters that are host-specific.
clear configure aaa-server	Remove all AAA command statements from the configuration.
show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol

radius-with-expiry

To have the security appliance use MS-CHAPv2 to negotiate a password update with the user during authentication, use the **radius-with-expiry** command in tunnel-group ipsec-attributes configuration mode. The security appliance ignores this command if RADIUS authentication has not been configured.

To return to the default value, use the **no** form of this command.

radius-with-expiry

no radius-with-expiry

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting for this command is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group ipsec attributes configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute to IPSec remote-access tunnel-group type only.

Examples

The following example entered in config-ipsec configuration mode, configures Radius with Expiry for the remote-access tunnel group named remotegrp:

```
hostname(config)# tunnel-group remotegrp type ipsec_ra
hostname(config)# tunnel-group remotegrp ipsec-attributes
hostname(config-ipsec)# radius-with-expiry
hostname(config-ipsec)#
```

Related Commands

Command	Description
clear configure tunnel-group	Clears all configured tunnel groups.

Command	Description
show running-config tunnel-group	Shows the indicated certificate map entry.
tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

reactivation-mode

To specify the method (reactivation policy) by which failed servers in a group are reactivated, use the **reactivation-mode** command in AAA-server group mode. To remove this specification, use the **no** form of this command:

reactivation-mode depletion [*deadtime minutes*]

reactivation-mode timed

no reactivation-mode

Syntax Description

deadtime <i>minutes</i>	(Optional) Specifies the amount of time that elapses between the disabling of the last server in the group and the subsequent re-enabling of all servers.
depletion	Reactivates failed servers only after all of the servers in the group are inactive.
timed	Reactivates failed servers after 30 seconds of down time.

Defaults

The default reactivation mode is depletion, and the default deadtime value is 10. The supported range of values for deadtime is 0-1440 minutes.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
AAA-server group	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Each server group has an attribute that specifies the reactivation policy for its servers.

In **depletion** mode, when a server is deactivated, it remains inactive until all other servers in the group are inactive. When and if this occurs, all servers in the group are reactivated. This approach minimizes the occurrence of connection delays due to failed servers. When **depletion** mode is in use, you can also specify the **deadtime** parameter. The **deadtime** parameter specifies the amount of time (in minutes) that will elapse between the disabling of the last server in the group and the subsequent re-enabling of all servers. This parameter is meaningful only when the server group is being used in conjunction with the local fallback feature.

In **timed** mode, failed servers are reactivated after 30 seconds of down time. This is useful when customers use the first server in a server list as the primary server and prefer that it is online whenever possible. This policy breaks down in the case of UDP servers. Since a connection to a UDP server will not fail, even if the server is not present, UDP servers are put back on line blindly. This could lead to slowed connection times or connection failures if a server list contains multiple servers that are not reachable.

Accounting server groups that have simultaneous accounting enabled are forced to use the **timed** mode. This implies that all servers in a given list are equivalent.

Examples

The following example configures a TACACS+ AAA server named “srvgrp1” to use the depletion reactivation mode, with a deadtime of 15 minutes:

```
hostname(config)# aaa-server srvgrp1 protocol tacacs+
hostname(config-aaa-servers-group)# reactivation-mode depletion deadtime 15
hostname(config-aaa-server)# exit
hostname(config)#
```

The following example configures a TACACS+ AAA server named “srvgrp1” to use timed reactivation mode:

```
hostname(config)# aaa-server srvgrp2 protocol tacacs+
hostname(config-aaa-server)# reactivation-mode timed
hostname(config-aaa-server)# exit
hostname(config)#
```

Related Commands

accounting-mode	Indicates whether accounting messages are sent to a single server or sent to all servers in the group.
aaa-server protocol	Enters AAA server group configuration mode so you can configure AAA server parameters that are group-specific and common to all hosts in the group.
max-failed-attempts	Specifies the number of failures that will be tolerated for any given server in the server group before that server is deactivated.
clear configure aaa-server	Removes all AAA server configuration.
show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol

redistribute

To redistribute routes from one routing domain into another routing domain, use the **redistribute** command in router configuration mode. To remove the redistribution, use the **no** form of this command.

```
redistribute {{ ospf pid [match {internal | external [1 | 2] | nssa-external [1 | 2]} } | static |
connected } [metric metric_value] [metric-type metric_type] [route-map map_name] [tag
tag_value] [subnets]

no redistribute {{ ospf pid [match {internal | external [1 | 2] | nssa-external [1 | 2]} } | static |
connected } [metric metric_value] [metric-type metric_type] [route-map map_name] [tag
tag_value] [subnets]
```

Syntax Description	
connected	Specifies redistributing a network connected to an interface into an OSPF routing process.
external type	Specifies the OSPF metric routes that are external to a specified autonomous system; valid values are 1 or 2 .
internal type	Specifies OSPF metric routes that are internal to a specified autonomous system.
match	(Optional) Specifies the conditions for redistributing routes from one routing protocol into another.
metric <i>metric_value</i>	(Optional) Specifies the OSPF default metric value from 0 to 16777214.
metric-type <i>metric_type</i>	(Optional) The external link type associated with the default route advertised into the OSPF routing domain. It can be either of the following two values: 1 (Type 1 external route) or 2 (Type 2 external route).
nssa-external type	Specifies the OSPF metric type for routes that are external to a not-so-stubby area (NSSA); valid values are 1 or 2 .
ospf pid	Used to redistribute an OSPF routing process into the current OSPF routing process. The <i>pid</i> specifies the internally used identification parameter for an OSPF routing process; valid values are from 1 to 65535.
route-map <i>map_name</i>	(Optional) Name of the route map to apply.
static	Used to redistribute a static route into an OSPF process.
subnets	(Optional) For redistributing routes into OSPF, scopes the redistribution for the specified protocol. If not used, only classful routes are redistributed.
tag <i>tag_value</i>	(Optional) A 32-bit decimal value attached to each external route. This value is not used by OSPF itself. It may be used to communicate information between ASBRs. If none is specified, then the remote autonomous system number is used for routes from BGP and EGP; for other protocols, zero (0) is used. Valid values range from 0 to 4294967295.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

This example shows how to redistribute static routes into the current OSPF process:

```
hostname(config-router)# redistribute ospf static
```

Related Commands

Command	Description
router ospf	Enters router configuration mode.
show running-config router	Displays the commands in the global router configuration.

reload

To reboot and reload the configuration, use the **reload** command in privileged EXEC mode.

reload [**at** *hh:mm* [*month day* | *day month*]] [**cancel**] [**in** [*hh:mm*]] [**max-hold-time** [*hh:mm*]] [**noconfirm**] [**quick**] [**reason** *text*] [**save-config**]

Syntax Description

at <i>hh:mm</i>	(Optional) Schedules a reload of the software to take place at the specified time (using a 24-hour clock). If you do not specify the month and day, the reload occurs at the specified time on the current day (if the specified time is later than the current time), or on the next day (if the specified time is earlier than the current time). Specifying 00:00 schedules the reload for midnight. The reload must take place within 24 hours.
cancel	(Optional) Cancels a scheduled reload.
<i>day</i>	(Optional) Number of the day in the range from 1 to 31.
in [<i>hh:mm</i>]	(Optional) Schedules a reload of the software to take effect in the specified minutes or hours and minutes. The reload must occur within 24 hours.
max-hold-time [<i>hh:mm</i>]	(Optional) Specifies the maximum hold time the security appliance waits to notify other subsystems before a shutdown or reboot. After this time elapses, a quick (forced) shutdown/reboot occurs.
<i>month</i>	(Optional) Specifies the name of the month. Enter enough characters to create a unique string for the name of the month. For example, “Ju” is not unique because it could represent June or July, but “Jul” is unique because no other month beginning with those exact three letters.
noconfirm	(Optional) Permits the security appliance to reload without user confirmation.
quick	(Optional) Forces a quick reload, without notifying or properly shutting down all the subsystems.
reason <i>text</i>	(Optional) Specifies the reason for the reload, 1 to 255 characters. The reason text is sent to all open IPSec VPN client, terminal, console, telnet, SSH, and ASDM connections/sessions.
 Note Some applications, like isakmp, require additional configuration to send the reason text to IPSec VPN Clients. Refer to the appropriate section in the software configuration documentation for more information.	
save-config	(Optional) Saves the running configuration to memory before shutting down. If you do not enter the save-config keyword, any configuration changes that have not been saved will be lost after the reload.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was modified to add the following new arguments and keywords: <i>day</i> , <i>hh</i> , <i>mm</i> , <i>month</i> , quick , save-config , and <i>text</i> .

Usage Guidelines

The **reload** command lets you reboot the security appliance and reload the configuration from Flash.

By default, the **reload** command is interactive. The security appliance first checks whether the configuration has been modified but not saved. If so, the security appliance prompts you to save the configuration. In multiple context mode, the security appliance prompts for each context with an unsaved configuration. If you specify the **save-config** parameter, the configuration is saved without prompting you. The security appliance then prompts you to confirm that you really want to reload the system. Only a response of **y** or pressing the **Enter** key causes a reload. Upon confirmation, the security appliance starts or schedules the reload process, depending upon whether you have specified a delay parameter (**in** or **at**).

By default, the reload process operates in “graceful” (also known as “nice”) mode. All registered subsystems are notified when a reboot is about to occur, allowing these subsystems to shut down properly before the reboot. To avoid waiting until for such a shutdown to occur, specify the **max-hold-time** parameter to specify a maximum time to wait. Alternatively, you can use the **quick** parameter to force the reload process to begin abruptly, without notifying the affected subsystems or waiting for a graceful shutdown.

You can force the **reload** command to operate noninteractively by specifying the **noconfirm** parameter. In this case, the security appliance does not check for an unsaved configuration unless you have specified the **save-config** parameter. The security appliance does not prompt the user for confirmation before rebooting the system. It starts or schedules the reload process immediately, unless you have specified a delay parameter, although you can specify the **max-hold-time** or **quick** parameters to control the behavior or the reload process.

Use **reload cancel** to cancel a scheduled reload. You cannot cancel a reload that is already in progress.

**Note**

Configuration changes that are not written to the Flash partition are lost after a reload. Before rebooting, enter the **write memory** command to store the current configuration in the Flash partition.

Examples

This example shows how to reboot and reload the configuration:

```
hostname# reload
Proceed with ? [confirm] y

Rebooting...

XXX Bios VX.X
...
```

Related Commands

Command	Description
show reload	Displays the reload status of the security appliance.

remote-access threshold session-threshold-exceeded

To set threshold values, use the **remote-access threshold** command in global configuration mode. To remove threshold values, use the **no** version of this command. This command specifies the number of active remote access sessions, at which point the security appliance sends traps.

remote-access threshold session-threshold-exceeded {*threshold-value*}

no remote-access threshold session-threshold-exceeded

Syntax Description

threshold-value Specifies an integer less than or equal to the session limit the security appliance supports.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Examples

The following example shows how to set a threshold value of 1500:

```
hostname# remote-access threshold session-threshold-exceeded 1500
```

Related Commands

Command	Description
snmp-server enable trap remote-access	Enables threshold trapping.

rename

To rename a file or a directory from the source filename to the destination filename, use the **rename** command in privileged EXEC mode.

rename [/noconfirm] [disk0: | disk1: | flash:] *source-path* [disk0: | disk1: | flash:] *destination-path*

Syntax Description	/noconfirm	(Optional) Suppresses the confirmation prompt.
	<i>destination-path</i>	Specifies the path of the destination file.
	disk0:	(Optional) Specifies the internal Flash memory, followed by a colon.
	disk1:	(Optional) Specifies the external Flash memory card, followed by a colon.
	flash:	(Optional) Specifies the internal Flash memory, followed by a colon.
	<i>source-path</i>	Specifies the path of the source file.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines The **rename flash: flash:** command prompts you to enter a source and destination filename. You cannot rename a file or directory across file systems.

For example:

```
hostname# rename flash: disk1:
Source filename []? new-config
Destination filename []? old-config
%Cannot rename between filesystems
```

Examples The following example shows how to rename a file named “test” to “test1”:

```
hostname# rename flash: flash:
Source filename [running-config]? test
Destination filename [n]? test1
```

Related Commands

Command	Description
mkdir	Creates a new directory.
rmdir	Removes a directory.
show file	Displays information about the file system.

replication http

To enable HTTP connection replication for the failover group, use the **replication http** command in failover group configuration mode. To disable HTTP connection replication, use the **no** form of this command.

replication http

no replication http

Syntax Description

This command has no arguments or keywords.

Defaults

Disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Failover group configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

By default, the security appliance does not replicate HTTP session information when Stateful Failover is enabled. Because HTTP sessions are typically short-lived, and because HTTP clients typically retry failed connection attempts, not replicating HTTP sessions increases system performance without causing serious data or connection loss. The **replication http** command enables the stateful replication of HTTP sessions in a Stateful Failover environment, but could have a negative effect on system performance.

This command is available for Active/Active failover only. It provides the same functionality as the **failover replication http** command for Active/Standby failover, except for failover groups in Active/Active failover configurations.

Examples

The following example shows a possible configuration for a failover group:

```
hostname(config)# failover group 1
hostname(config-fover-group)# primary
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# replication http
hostname(config-fover-group)# exit
```

Related Commands	Command	Description
	failover group	Defines a failover group for Active/Active failover.
	failover replication http	Configures stateful failover to replicate HTTP connections.

request-command deny

To disallow specific commands within FTP requests, use the **request-command deny** command in FTP map configuration mode, which is accessible by using the **ftp-map** command. To remove the configuration, use the **no** form of this command.

```
request-command deny { appe | cdup | dele | get | help | mkd | put | rmd | rnfr | rnto | site | stou }
```

```
no request-command deny { appe | cdup | help | retr | rnfr | rnto | site | stor | stou }
```

Syntax Description

appe	Disallows the command that appends to a file.
cdup	Disallows the command that changes to the parent directory of the current working directory.
dele	Disallows the command that deletes a file on the server.
get	Disallows the client command for retrieving a file from the server.
help	Disallows the command that provides help information.
mkd	Disallows the command that makes a directory on the server.
put	Disallows the client command for sending a file to the server.
rmd	Disallows the command that deletes a directory on the server.
rnfr	Disallows the command that specifies rename-from filename.
rnto	Disallows the command that specifies rename-to filename.
site	Disallows the command that are specific to the server system. Usually used for remote administration.
stou	Disallows the command that stores a file using a unique file name.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
FTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is used for controlling the commands allowed within FTP requests traversing the security appliance when using strict FTP inspection.

Examples

The following example causes the security appliance to drop FTP requests containing **stor**, **stou**, or **appe** commands:

```
hostname(config)# ftp-map inbound_ftp
hostname(config-ftp-map)# request-command deny put stou appe
hostname(config-ftp-map)# exit
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
ftp-map	Defines an FTP map and enables FTP map configuration mode.
inspect ftp	Applies a specific FTP map to use for application inspection.
mask-syst-reply	Hides the FTP server response from clients.
policy-map	Associates a class map with specific security actions.

request-method

To restrict HTTP traffic based on the HTTP request method, use the **request-method** command in HTTP map configuration mode, which is accessible using the **http-map** command. To disable this feature, use the **no** form of the command.

```
request-method { { ext ext_methods | default } | { rfc rfc_methods | default } } action { allow | reset | drop } [log]
```

```
no request-method { ext ext_methods | rfc rfc_methods } action { allow | reset | drop } [log]
```

Syntax Description

action	Identifies the action taken when a message fails this command inspection.
allow	Allows the message.
default	Specifies the default action taken by the security appliance when the traffic contains a supported request method that is not on a configured list.
drop	Closes the connection.
ext	Specifies extension methods.
<i>ext-methods</i>	Identifies one of the extended methods you want to allow to pass through the security appliance.
log	(Optional) Generates a syslog.
reset	Sends a TCP reset message to client and server.
rfc	Specifies RFC 2616 supported methods.
<i>rfc-methods</i>	Identifies one of the RFC methods you want to allow to pass through the security appliance (see Table 6-2).

Defaults

This command is disabled by default. When the command is enabled and a supported request method is not specified, the default action is to allow the connection without logging. To change the default action, use the **default** keyword and specify a different default action.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
HTTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

When you enable the **request-method** command, the security appliance applies the specified action to HTTP connections for each supported and configured request method.

The security appliance applies the **default** action to all traffic that does *not* match the request methods on the configured list. The **default** action is to **allow** connections without logging. Given this preconfigured default action, if you specify one or more request methods with the action of **drop** and **log**, the security appliance drops connections containing the configured request methods, logs each connection, and allows all connections containing other supported request methods.

If you want to configure a more restrictive policy, change the default action to **drop** (or **reset**) and **log** (if you want to log the event). Then configure each permitted method with the **allow** action.

Enter the **request-method** command once for each setting you wish to apply. You use one instance of the **request-method** command to change the default action or to add a single request method to the list of configured methods.

When you use the **no** form of the command to remove a request method from the list of configured methods, any characters in the command line after the request method keyword are ignored.

Table 6-2 lists the methods defined in RFC 2616 that you can add to the list of configured methods:

Table 6-3 *RFC 2616 Methods*

Method	Description
connect	Used with a proxy that can dynamically switch to being a tunnel (for example SSL tunneling).
delete	Requests that the origin server delete the resource identified by the Request-URI.
get	Retrieves whatever information or object is identified by the Request-URI.
head	Identical to GET except that the server does not return a message-body in the response.
options	Represents a request for information about the communication options available on server identified by the Request-URI.
post	Request that the origin server accept the object enclosed in the request as a new subordinate of the resource identified by the Request-URI in the Request-Line.
put	Requests that the enclosed object be stored under the supplied Request-URI.
trace	Invokes a remote, application-layer loop-back of the request message.

Examples

The following example provides a permissive policy, using the preconfigured default, which allows all supported request methods that are not specifically prohibited.

```
hostname(config)# http-map inbound_http
hostname(config-http-map)# request-method rfc options drop log
hostname(config-http-map)# request-method rfc post drop log
hostname(config-http-map)# exit
```

In this example, only the **options** and **post** request methods are dropped and the events are logged.

The following example provides a restrictive policy, with the default action changed to **reset** the connection and **log** the event for any request method that is not specifically allowed.

```
hostname(config)# http-map inbound_http
hostname(config-http-map)# request-method rfc default action reset log
hostname(config-http-map)# request-method rfc get allow
```

```
hostname(config-http-map) # request-method rfc put allow  
hostname(config-http-map) # exit
```

In this case, the **get** and **put** request methods are allowed. When traffic is detected that uses any other methods, the security appliance resets the connection and creates a syslog entry.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
<code>debug appfw</code>	Displays detailed information about traffic associated with enhanced HTTP inspection.
http-map	Defines an HTTP map for configuring enhanced HTTP inspection.
inspect http	Applies a specific HTTP map to use for application inspection.
policy-map	Associates a class map with specific security actions.

request-queue

To specify the maximum number of GTP requests that will be queued waiting for a response, use the **request-queue** command in GTP map configuration mode, which is accessed by using the **gtp-map** command. Use the **no** form of this command to return this number to the default of 200.

request-queue *max_requests*

no request-queue *max_requests*

Syntax Description

<i>max_requests</i>	The maximum number of GTP requests that will be queued waiting for a response. The range values is 1 to 4294967295.

Defaults

The *max_requests* default is 200.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
GTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **gtp request-queue** command specifies the maximum number of GTP requests that are queued waiting for a response. When the limit has been reached and a new request arrives, the request that has been in the queue for the longest time is removed. The Error Indication, the Version Not Supported and the SGSN Context Acknowledge messages are not considered as requests and do not enter the request queue to wait for a response.

Examples

The following example specifies a maximum request queue size of 300 bytes:

```
hostname(config)# gtp-map gtp-policy
hostname(config-gtpmap)# request-queue-size 300
```

Related Commands

Commands	Description
clear service-policy	Clears global GTP statistics.
inspect gtp	
debug gtp	Displays detailed information about GTP inspection.

Commands	Description
gtp-map	Defines a GTP map and enables GTP map configuration mode.
inspect gtp	Applies a specific GTP map to use for application inspection.
show service-policy inspect gtp	Displays the GTP configuration.

reserved-bits

To clear reserved bits in the TCP header, or drop packets with reserved bits set, use the **reserved-bits** command in tcp-map configuration mode. To remove this specification, use the **no** form of this command.

reserved-bits {allow | clear | drop}

no reserved-bits {allow | clear | drop}

Syntax Description

allow	Allows packet with the reserved bits in the TCP header.
clear	Clears the reserved bits in the TCP header and allows the packet.
drop	Drops the packet with the reserved bits in the TCP header.

Defaults

The reserved bits are allowed by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tcp-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **tcp-map** command is used along with the Modular Policy Framework infrastructure. Define the class of traffic using the **class-map** command and customize the TCP inspection with **tcp-map** commands. Apply the new TCP map using the **policy-map** command. Activate TCP inspection with **service-policy** commands.

Use the **tcp-map** command to enter tcp-map configuration mode. Use the **reserved-bits** command in tcp-map configuration mode to remove ambiguity as to how packets with reserved bits are handled by the end host, which may lead to desynchronizing the security appliance. You can choose to clear the reserved bits in the TCP header or even drop packets with the reserved bits set.

Examples

The following example shows how to clear packets on all TCP flows with the reserved bit set:

```
hostname(config)# access-list TCP extended permit tcp any any
hostname(config)# tcp-map tmap
hostname(config-tcp-map)# reserved-bits clear
hostname(config)# class-map cmap
hostname(config-cmap)# match access-list TCP
```

```
hostname(config)# policy-map pmap
hostname(config-pmap)# class cmap
hostname(config-pmap)# set connection advanced-options tmap
hostname(config)# service-policy pmap global
```

Related Commands

Command	Description
class	Specifies a class map to use for traffic classification.
help	Shows syntax help for the policy-map , class , and description commands.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
set connection	Configures connection values.
tcp-map	Creates a TCP map and allows access to tcp-map configuration mode.

retry-interval

To configure the amount of time between retry attempts for a particular AAA server designated in a prior `aaa-server host` command, use the **retry-interval** command in AAA-server host mode. To reset the retry interval to the default value, use the **no** form of this command.

retry-interval *seconds*

no retry-interval

Syntax Description

<i>seconds</i>	Specify the retry interval (1-10 seconds) for the request. This is the time the security appliance waits before retrying a connection request.

Defaults

The default retry interval is 10 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
AAA-server host	•	•	•	•	—

Command History

Release	Modification
7.0	This command was modified to conform to CLI guidelines.

Usage Guidelines

Use the **retry-interval** command to specify or reset the number of seconds the security appliance waits between connection attempts. Use the **timeout** command to specify the length of time during which the security appliance attempts to make a connection to a AAA server.

Examples

The following examples show the **retry-interval** command in context.

```
hostname(config)# aaa-server svrgrp1 protocol radius
hostname(config-aaa-server-group)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# timeout 7
hostname(config-aaa-server-host)# retry-interval 9
hostname(config-aaa-server-host)# exit
hostname(config)#
```

Related Commands

Command	Description
aaa-server host	Enters AAA server host configuration mode so you can configure AAA server parameters that are host-specific.
clear configure aaa-server	Removes all AAA command statements from the configuration.
show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol
timeout	Specifies the length of time during which the security appliance attempts to make a connection to a AAA server.

re-xauth

To require that users reauthenticate on IKE rekey, issue the **re-xauth enable** command in group-policy configuration mode. To disable user reauthentication on IKE rekey, use the **re-xauth disable** command.

To remove the re-xauth attribute from the running configuration, use the **no** form of this command. This enables inheritance of a value for reauthentication on IKE rekey from another group policy.

re-xauth {enable | disable}

no re-xauth

Syntax Description

disable	Disables reauthentication on IKE rekey
enable	Enables reauthentication on IKE rekey

Defaults

Reauthentication on IKE rekey is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If you enable reauthentication on IKE rekey, the security appliance prompts the user to enter a username and password during initial Phase 1 IKE negotiation and also prompts for user authentication whenever an IKE rekey occurs. Reauthentication provides additional security.

If the configured rekey interval is very short, users might find the repeated authorization requests inconvenient. In this case, disable reauthentication. To check the configured rekey interval, in monitoring mode, issue the **show crypto ipsec sa** command to view the security association lifetime in seconds and lifetime in kilobytes of data.



Note

The reauthentication fails if there is no user at the other end of the connection.

Examples

The following example shows how to enable reauthentication on rekey for the group policy named FirstGroup:

```
hostname(config) #group-policy FirstGroup attributes
```

```
hostname(config-group-policy)# re-xauth enable
```

rip

To enable and change RIP settings, use the **rip** command in global configuration mode. To disable the security appliance RIP routing table updates, use the **no** form of this command.

rip *if_name* { **default** | **passive** } [**version** { **1** | **2** [**authentication** { **text** | **md5** } *key* *key_id*]]

no rip *if_name* { **default** | **passive** } [**version** { **1** | **2** [**authentication** { **text** | **md5** } *key* *key_id*]]

Syntax Description

authentication	(Optional) Enables RIP version 2 authentication.
default	Broadcast a default route on the interface.
<i>if_name</i>	The interface on which RIP is being enabled.
<i>key</i>	Key to authenticate RIP updates.
<i>key_id</i>	Key identification value; valid values range from 1 to 255.
md5	Uses MD5 for RIP message authentication.
passive	Enables passive RIP on the interface. The interface listens for RIP routing broadcasts and uses that information to populate the routing tables but does not broadcast routing updates.
text	Uses clear text for RIP message authentication (not recommended).
version	(Optional) Specifies the RIP version; valid values are 1 and 2 .

Defaults

RIP is disabled.

If you do not specify a version, RIP version 1 is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **rip** command lets you to enable the sending and receiving of RIP routing updates on an interface. You configure RIP update transmission and reception independently; you can enable transmission only, reception only, or both transmission and reception on each interface. Use the **passive** keyword with the **rip** command to enable RIP update reception. Use the **default** keyword with the **rip** command to enable the broadcast of a default route. To enable both transmission and reception of RIP updates on an

interface, you must two **rip** commands for the interface, one with the **default** keyword, enabling the sending of RIP routing updates, and one with the **passive** keyword, enabling the interface to receive RIP updates and to populate the routing table with those updates.

**Note**

The security appliance cannot pass RIP updates between interfaces.

If you specify RIP version 2, you can enable neighbor authentication and use MD5-based encryption to authenticate the RIP updates. When you enable neighbor authentication, you must ensure that the *key* and *key_id* arguments are the same as those used by neighbor devices that provide RIP version 2 updates. The *key* is a text string of up to 16 characters.

Configuring RIP Version 2 registers the multicast address 224.0.0.9 on the respective interface to be able to accept multicast RIP Version 2 updates. When RIP Version 2 is configured in passive mode, the security appliance accepts RIP Version 2 multicast updates with an IP destination of 224.0.0.9. When RIP Version 2 is configured in default mode, the security appliance transmits default route updates using an IP multicast destination of 224.0.0.9. Removing the RIP version 2 commands for an interface unregisters the multicast address from the interface card.

**Note**

Only Intel 10/100 and Gigabit interfaces support multicasting.

RIP is not supported under transparent mode. By default, the security appliance denies all RIP broadcast and multicast packets. To permit these RIP messages to pass through a security appliance operating in transparent mode you must define access list entries to permit this traffic. For example, to permit RIP version 2 traffic through the security appliance, create an access list entry like `access-list myriplist extended permit ip any host 224.0.0.9`. To permit RIP version 1 broadcasts, create an access list entry like `access-list myriplist extended permit udp any any eq rip`. Apply these access list entries to the appropriate interface using the **access-group** command.

Examples

The following example shows how to combine version 1 and version 2 commands and list the information with the **show running-config rip** command after entering the **rip** commands. The **rip** commands let you to do the following.

- Enable version 2 passive and default RIP using MD5 authentication on the outside interface to encrypt the key that is used by the security appliance and other RIP peers, such as routers.
- Enable version 1 passive RIP listening on the inside interface of the security appliance.
- Enable version 2 passive RIP listening on the dmz (demilitarized) interface of the security appliance.

```
hostname(config)# rip outside passive version 2 authentication md5 thisisakey 2
hostname(config)# rip outside default version 2 authentication md5 thisisakey 2
hostname(config)# rip inside passive
hostname(config)# rip dmz passive version 2
```

```
hostname# show running-config rip
rip outside passive version 2 authentication md5 thisisakey 2
rip outside default version 2 authentication md5 thisisakey 2
rip inside passive version 1
rip dmz passive version 2
```

The following example shows how to use the version 2 feature that passes the encryption key in text form:

```
hostname(config)# rip out default version 2 authentication text thisisakey 3
hostname# show running-config rip
```

```
rip outside default version 2 authentication text thisisakey 3
```

Related Commands

Command	Description
clear configure rip	Clears all RIP commands from the running configuration.
debug rip	Displays debug information for RIP.
show running-config rip	Displays the RIP commands in the running configuration.

rmdir

To remove the existing directory, use the **rmdir** command in privileged EXEC mode.

rmdir [/noconfirm] [disk0: | disk1: | flash:]*path*

Syntax Description

noconfirm	(Optional) Suppresses the confirmation prompt.
disk0:	(Optional) Specifies the nonremovable internal Flash memory, followed by a colon.
disk1:	(Optional) Specifies the removable external Flash memory card, followed by a colon.
flash:	(Optional) Specifies the nonremovable internal Flash, followed by a colon. In the ASA 5500 series, the flash keyword is aliased to disk0 .
<i>path</i>	(Optional) The absolute or relative path of the directory to remove.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If the directory is not empty, the **rmdir** command fails.

Examples

This example shows how to remove an existing directory named “test”:

```
hostname# rmdir test
```

Related Commands

Command	Description
dir	Displays the directory contents.
mkdir	Creates a new directory.
pwd	Displays the current working directory.
show file	Displays information about the file system.

route

To enter a static or default route for the specified interface, use the **route** command in global configuration mode. Use the **no** form of this command to remove routes from the specified interface.

route *interface_name* *ip_address* *netmask* *gateway_ip* [*metric* | **tunneled**]

no route *interface_name* *ip_address* *netmask* *gateway_ip* [*metric* | **tunneled**]

Syntax Description

<i>gateway_ip</i>	Specifies the IP address of the gateway router (the next-hop address for this route).
	Note The <i>gateway_ip</i> argument is optional in transparent mode.
<i>interface_name</i>	Internal or external network interface name.
<i>ip_address</i>	Internal or external network IP address.
<i>metric</i>	(Optional) The administrative distance for this route. Valid values range from 1 to 255. The default value is 1.
<i>netmask</i>	Specifies a network mask to apply to <i>ip_address</i> .
tunneled	Specifies route as the default tunnel gateway for VPN traffic.

Defaults

The *metric* default is 1.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Use the **route** command to enter a default or static route for an interface. To enter a default route, set *ip_address* and *netmask* to **0.0.0.0**, or use the shortened form of **0**. All routes that are entered using the **route** command are stored in the configuration when it is saved.

You can define a separate default route for tunneled traffic along with the standard default route. When you create a default route with the **tunneled** option, all encrypted traffic that arrives on the security appliance and cannot be routed using learned or static routes is sent to this route. Otherwise, if the traffic is not encrypted, the standard default route entry is used. You cannot define more than one default route with the **tunneled** option; ECMP for tunneled traffic is not supported.

Create static routes to access networks that are connected outside a router on any interface. For example, the security appliance sends all packets that are destined to the 192.168.42.0 network through the 192.168.1.5 router with this static **route** command.

```
hostname(config)# route dmz 192.168.42.0 255.255.255.0 192.168.1.5 1
```

Once you enter the IP address for each interface, the security appliance creates a CONNECT route in the route table. This entry is not deleted when you use the **clear route** or **clear configure route** commands.

If the **route** command uses the IP address from one of the interfaces on the security appliance as the gateway IP address, the security appliance will ARP for the destination IP address in the packet instead of ARPing for the gateway IP address.

Examples

The following example shows how to specify one default **route** command for an outside interface:

```
hostname(config)# route outside 0 0 209.165.201.1 1
```

The following example shows how to add these static **route** commands to provide access to the networks:

```
hostname(config)# route dmz1 10.1.2.0 255.0.0.0 10.1.1.4 1  
hostname(config)# route dmz1 10.1.3.0 255.0.0.0 10.1.1.4 1
```

Related Commands

Command	Description
clear configure route	Removes statically configured route commands.
clear route	Removes routes learned through dynamic routing protocols such as RIP.
show route	Displays route information.
show running-config route	Displays configured routes.

route-map

To define the conditions for redistributing routes from one routing protocol into another, use the **route-map** command in global configuration mode. To delete a map, use the **no** form of this command.

route-map *map_tag* [**permit** | **deny**] [*seq_num*]

no route-map *map_tag* [**permit** | **deny**] [*seq_num*]

Syntax Description

deny	(Optional) Specifies that if the match criteria are met for the route map, the route is not redistributed.
<i>map_tag</i>	Text for the route map tag; the text can be up to 57 characters in length.
permit	(Optional) Specifies that if the match criteria is met for this route map, the route is redistributed as controlled by the set actions.
<i>seq_num</i>	(Optional) Route map sequence number; valid values are from 0 to 65535. Indicates the position that a new route map will have in the list of route maps already configured with the same name.

Defaults

The defaults are as follows:

- **permit.**
- If you do not specify a *seq_num*, a *seq_num* of 10 is assigned to the first route map.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **route-map** command allows you to redistribute routes.

The **route-map** global configuration command and the **match** and **set** configuration commands define the conditions for redistributing routes from one routing protocol into another. Each **route-map** command has **match** and **set** commands that are associated with it. The **match** commands specify the match criteria that are the conditions under which redistribution is allowed for the current **route-map** command. The **set** commands specify the set actions, which are the redistribution actions to perform if the criteria enforced by the **match** commands are met. The **no route-map** command deletes the route map.

The **match route-map** configuration command has multiple formats. You can enter the **match** commands in any order, and all **match** commands must pass to cause the route to be redistributed according to the set actions given with the **set** commands. The **no** form of the **match** commands removes the specified match criteria.

Use route maps when you want detailed control over how routes are redistributed between routing processes. You specify the destination routing protocol with the **router ospf** global configuration command. You specify the source routing protocol with the **redistribute** router configuration command.

When you pass routes through a route map, a route map can have several parts. Any route that does not match at least one match clause relating to a **route-map** command is ignored; the route is not advertised for outbound route maps and is not accepted for inbound route maps. To modify only some data, you must configure a second route map section with an explicit match specified.

The *seq_number* argument is as follows:

1. If you do not define an entry with the supplied tag, an entry is created with the *seq_number* argument set to 10.
2. If you define only one entry with the supplied tag, that entry becomes the default entry for the following **route-map** command. The *seq_number* argument of this entry is unchanged.
3. If you define more than one entry with the supplied tag, an error message is printed to indicate that the *seq_number* argument is required.

If the **no route-map map-tag** command is specified (with no *seq-num* argument), the whole route map is deleted (all **route-map** entries with the same *map-tag* text).

If the match criteria are not met, and you specify the **permit** keyword, the next route map with the same *map_tag* is tested. If a route passes none of the match criteria for the set of route maps sharing the same name, it is not redistributed by that set.

Examples

The following example shows how to configure a route map in OSPF routing:

```
hostname(config)# route-map maptag1 permit 8
hostname(config-route-map)# set metric 5
hostname(config-route-map)# match metric 5
hostname(config-route-map)# show running-config route-map
route-map maptag1 permit 8
    set metric 5
    match metric 5
hostname(config-route-map)# exit
hostname(config)#
```

Related Commands

Command	Description
clear configure route-map	Removes the conditions for redistributing the routes from one routing protocol into another routing protocol.
match interface	Distributes distribute any routes that have their next hop out one of the interfaces specified,
router ospf	Starts and configures an ospf routing process.
set metric	Specifies the metric value in the destination routing protocol for a route map.
show running-config route-map	Displays the information about the route map configuration.

router-id

To use a fixed router ID, use the **router-id** command in router configuration mode. To reset OSPF to use the previous router ID behavior, use the **no** form of this command.

router-id *addr*

no router-id [*addr*]

Syntax Description

addr Router ID in IP address format.

Defaults

If not specified, the highest-level IP address on the security appliance is used as the router ID.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If the highest-level IP address on the security appliance is a private address, then this address is sent in hello packets and database definitions. To prevent this situation, use the **router-id** command to specify a global address for the router ID.

Examples

The following example sets the router ID to 192.168.1.1:

```
hostname(config-router)# router-id 192.168.1.1
hostname(config-router)#
```

Related Commands

Command	Description
router ospf	Enters router configuration mode.
show ospf	Displays general information about the OSPF routing processes.

router ospf

To start an OSPF routing process and configure parameters for that process, use the **router ospf** command in global configuration mode. To disable OSPF routing, use the **no** form of this command.

router ospf *pid*

no router ospf *pid*

Syntax Description

<i>pid</i>	Internally used identification parameter for an OSPF routing process; valid values are from 1 to 65535. The <i>pid</i> does not need to match the ID of OSPF processes on other routers.

Defaults

OSPF routing is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **router ospf** command is the global configuration command for OSPF routing processes running on the security appliance. Once you enter the **router ospf** command, the command prompt appears as (config-router)#, indicating that you are in router configuration mode.

When using the **no router ospf** command, you do not need to specify optional arguments unless they provide necessary information. The **no router ospf** command terminates the OSPF routing process specified by its *pid*. You assign the *pid* locally on the security appliance. You must assign a unique value for each OSPF routing process.

The **router ospf** command is used with the following OSPF-specific commands to configure OSPF routing processes:

- **area**—Configures a regular OSPF area.
- **compatible rfc1583**—Restores the method used to calculate summary route costs per RFC 1583.
- **default-information originate**—Generates a default external route into an OSPF routing domain.
- **distance**—Defines the OSPF route administrative distances based on the route type.
- **ignore**—Suppresses the sending of syslog messages when the router receives a link-state advertisement (LSA) for type 6 Multicast OSPF (MOSPF) packets.

- **log-adj-changes**—Configures the router to send a syslog message when an OSPF neighbor goes up or down.
- **neighbor**—Specifies a neighbor router. Used to allow adjacency to be established over VPN tunnels.
- **network**—Defines the interfaces on which OSPF runs and the area ID for those interfaces.
- **redistribute**—Configures the redistribution of routes from one routing domain to another according to the parameters specified.
- **router-id**—Creates a fixed router ID.
- **summary-address**—Creates the aggregate addresses for OSPF.
- **timers lsa-group-pacing**—OSPF LSA group pacing timer (interval between group of LSA being refreshed or max-aged).
- **timers spf**—Delay between receiving a change to the SPF calculation.

You cannot configure OSPF when RIP is configured on the security appliance.

Examples

The following example shows how to enter the configuration mode for the OSPF routing process numbered 5:

```
hostname(config)# router ospf 5
hostname(config-router)#
```

Related Commands

Command	Description
clear configure router	Clears the OSPF router commands from the running configuration.
show running-config router ospf	Displays the OSPF router commands in the running configuration.



S Commands

same-security-traffic

To permit communication between interfaces with equal security levels, use the **same-security-traffic** command in global configuration mode. To disable the same-security interfaces, use the **no** forms of this command.

same-security-traffic permit {inter-interface | intra-interface}

no same-security-traffic permit {inter-interface | intra-interface}

Syntax Description

inter-interface	Permits communication between different interfaces that have the same security level.
intra-interface	Permits communication in and out of the same interface when traffic is IPSec protected.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Allowing communication between same security interfaces provides the following benefits:

- You can configure more than 101 communicating interfaces. If you use different levels for each interface, you can configure only one interface per level (0 to 100).
- You can allow traffic to flow freely between all same security interfaces without access lists.

You can also redirect incoming client VPN traffic back out through the same interface unencrypted as well as encrypted. If you send VPN traffic back out through the same interface unencrypted, you must enable NAT for the interface so that publically routable addresses replace your private ip addresses (unless you already use public ip addresses in your local ip address pool). The following example commands apply an interface PAT rule to traffic sourced from the client ip pool:

```
hostname(config)# ip local pool clientpool 192.168.0.10-192.168.0.100
hostname(config)# global (outside) 1 interface
hostname config)# nat (outside) 1 192.168.0.0 255.255.255.0
```

When the security appliance sends encrypted VPN traffic back out this same interface, however, NAT is optional. To apply NAT to all outgoing traffic, implement only the commands above. To exempt the VPN-to-VPN traffic from NAT, add commands (to the example above) that implement NAT exemption for VPN-to-VPN traffic, such as:

```
hostname(config)# access-list nonat permit ip 192.168.0.0 255.255.255.0 192.168.0.0  
255.255.255.0  
hostname(config)# nat (outside) 0 access-list nonat
```

See the **nat** command for more information.

Examples

The following example shows how to enable the same-security interface communication:

```
hostname(config)# same-security-traffic permit inter-interface
```

Related Commands

Command	Description
show running-config same-security-traffic	Displays the same-security-traffic configuration.

sdi-pre-5-slave

To specify the IP address or name of an optional SDI AAA “slave” server to use for this host connection that uses a version of SDI prior to SDI version 5, use the **sdi-pre-5-slave** command in AAA-server host configuration mode. To remove this specification, use the **no** form of this command:

sdi-pre-5-slave *host*

no sdi-pre-5-slave

Syntax Description	<i>host</i>	Specify the name or IP address of the slave server host.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
AAA-server Host	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced

Usage Guidelines	This command is available for any host in an SDI AAA servergroup, but it is relevant only if the SDI version for the host is set to sdi-pre-5 in the sdi-version command. Prior to using this command, you must have configured the AAA server to use the SDI protocol. The sdi-pre-5-slave command lets you identify an optional secondary server that is to be used if the primary server fails. The address specified by this command must be that of a server that is configured as a “slave” to the primary SDI server. In this situation, if you are using a pre-5 version, you must configure the sdi-pre-5-slave command so that the security appliance can access the appropriate SDI configuration record that is downloaded from the server. This is not an issue with version 5 and later versions.

Examples	The following example configures the AAA SDI server group “svrgrp1” that uses an SDI version prior to SDI version 5. <pre>hostname(config)# aaa-server svrgrp1 protocol sdi hostname(config-aaa-server-group)# aaa-server svrgrp1 host 192.168.10.10 hostname(config-aaa-server-host)# sdi-version sdi-pre-5 hostname(config-aaa-server-host)# sdi-pre-5-slave 209.165.201.31 hostname(config-aaa-server-host)# exit hostname(config)#</pre>

Related Commands

Command	Description
aaa-server host	Enter AAA server host configuration mode so you can configure AAA server parameters that are host-specific.
clear configure aaa-server	Removes all AAA server configurations.
sdi-version	Specifies the version of SDI to use for this host connection.
show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol.

sdi-version

To specify the version of SDI to use for this host connection, use the **sdi-version** command in AAA-server host configuration mode. To remove this specification, use the **no** form of this command:

sdi-version *version*

no sdi-version

Syntax Description

<i>version</i>	Specify the version of SDI to use. Valid values are:
	sdi-5 – SDI version 5.0 (default)
	sdi-pre-5 – SDI versions prior to 5.0

Defaults

The default version is **sdi-5**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
AAA-server host	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced

Usage Guidelines

This command is valid only for SDI AAA servers. If you configure a secondary (failover) SDI AAA server, and if the SDI version for that server is earlier than version 5, you must also specify the **sdi-pre-5-slave** command

Examples

```
hostname(config)# aaa-server svrgrp1 protocol sdi
hostname(config-aaa-server-group)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# timeout 6
hostname(config-aaa-server-host)# retry-interval 7
hostname(config-aaa-server-host)# sdi-version sdi-5
hostname(config-aaa-server)# exit
hostname(config)#
```

Related Commands

Command	Description
aaa-server host	Enter AAA server host configuration mode so you can configure AAA server parameters that are host-specific.

clear configure aaa-server	Remove all AAA configurations.
show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol

secondary

To give the secondary unit higher priority in a failover group, use the **secondary** command in failover group configuration mode. To restore the default, use the **no** form of this command.

secondary

no secondary

Syntax Description

This command has no arguments or keywords.

Defaults

If **primary** or **secondary** is not specified for a failover group, the failover group defaults to **primary**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Failover group configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Assigning a primary or secondary priority to a failover group specifies which unit the failover group becomes active on when both units boot simultaneously (within a unit polltime). If one unit boots before the other, then both failover groups become active on that unit. When the other unit comes online, any failover groups that have the second unit as a priority do not become active on the second unit unless the failover group is configured with the **preempt** command or is manually forced to the other unit with the **no failover active** command.

Examples

The following example configures failover group 1 with the primary unit as the higher priority and failover group 2 with the secondary unit as the higher priority. Both failover groups are configured with the **preempt** command, so the groups will automatically become active on their preferred unit as the units become available.

```
hostname(config)# failover group 1
hostname(config-fover-group)# primary
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# exit
hostname(config)# failover group 2
hostname(config-fover-group)# secondary
hostname(config-fover-group)# preempt 100
hostname(config-fover-group)# mac-address e1 0000.a000.a011 0000.a000.a012
hostname(config-fover-group)# exit
```

```
hostname(config)#
```

Related Commands

Command	Description
failover group	Defines a failover group for Active/Active failover.
preempt	Forces the failover group to become active on its preferred unit when the unit becomes available.
primary	Gives the primary unit a higher priority than the secondary unit.

secondary-color

To set a secondary color for the WebVPN login, home page, and file access page, use the **secondary-color** command in webvpn mode. To remove a color from the configuration and reset the default, use the **no** form of this command.

secondary-color *[color]*

no secondary-color

Syntax Description

color	(Optional) Specifies the color. You can use a comma separated RGB value, an HTML color value, or the name of the color if recognized in HTML. - RGB format is 0,0,0, a range of decimal numbers from 0 to 255 for each color (red, green, blue); the comma separated entry indicates the level of intensity of each color to combine with the others. - HTML format is #000000, six digits in hexadecimal format; the first and second represent red, the third and fourth green, and the fifth and sixth represent blue. - Name length maximum is 32 characters

Defaults

The default secondary color is HTML #CCCCFF, a lavender shade.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The number of RGB values recommended for use is 216, many fewer than the mathematical possibilities. Many displays can handle only 256 colors, and 40 of those look differently on MACs and PCs. For best results, check published RGB tables. To find RGB tables online, enter RGB in a search engine.

Examples

The following example shows how to set an HTML color value of #5F9EAO, which is a teal shade:

```
hostname(config)# webvpn
hostname(config-webvpn)# secondary-color #5F9EAO
```

Related Commands	Command	Description
	title-color	Sets a color for the WebVPN title bar on the login, home page, and file access page

secondary-color

To set a secondary color for the WebVPN login, home page, and file access page, use the **secondary-color** command in webvpn mode. To remove a color from the configuration and reset the default, use the **no** form of this command.

secondary-color *[color]*

no secondary-color

Syntax Description

color	(Optional) Specifies the color. You can use a comma separated RGB value, an HTML color value, or the name of the color if recognized in HTML. • RGB format is 0,0,0, a range of decimal numbers from 0 to 255 for each color (red, green, blue); the comma separated entry indicates the level of intensity of each color to combine with the others. • HTML format is #000000, six digits in hexadecimal format; the first and second represent red, the third and fourth green, and the fifth and sixth represent blue. • Name length maximum is 32 characters

Defaults

The default secondary color is HTML #CCCCFF, a lavender shade.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The number of RGB values recommended for use is 216, many fewer than the mathematical possibilities. Many displays can handle only 256 colors, and 40 of those look differently on MACs and PCs. For best results, check published RGB tables. To find RGB tables online, enter RGB in a search engine.

Examples

The following example shows how to set an HTML color value of #5F9EAO, which is a teal shade:

```
hostname(config)# webvpn
hostname(config-webvpn)# secondary-color #5F9EAO
```

Related Commands

Command	Description
title-color	Sets a color for the WebVPN title bar on the login, home page, and file access page

secure-unit-authentication

To enable secure unit authentication, use the **secure-unit-authentication enable** command in group-policy configuration mode. To disable secure unit authentication, use the **secure-unit-authentication disable** command. To remove the secure unit authentication attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a value for secure unit authentication from another group policy.

Secure unit authentication provides additional security by requiring VPN hardware clients to authenticate with a username and password each time the client initiates a tunnel. With this feature enabled, the hardware client does not have a saved username and password.



Note

With this feature enabled, to bring up a VPN tunnel, a user must be present to enter the username and password.

secure-unit-authentication {enable | disable}

no secure-unit-authentication

Syntax Description

disable	Disables secure unit authentication.
enable	Enables secure unit authentication.

Defaults

Secure unit authentication is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Group policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Secure unit authentication requires that you have an authentication server group configured for the tunnel group the hardware client(s) use.

If you require secure unit authentication on the primary security appliance, be sure to configure it on any backup servers as well.

Examples

The following example shows how to enable secure unit authentication for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes  
hostname(config-group-policy)# secure-unit-authentication enable
```

Related Commands

Command	Description
ip-phone-bypass	Lets IP phones connect without undergoing user authentication. Secure unit authentication remains in effect.
leap-bypass	Lets LEAP packets from wireless devices behind a VPN hardware client travel across a VPN tunnel prior to user authentication, when enabled. This lets workstations using Cisco wireless access point devices establish LEAP authentication. Then they authenticate again per user authentication.
user-authentication	Requires users behind a hardware client to identify themselves to the security appliance before connecting.

security-level

To set the security level of an interface, use the **security-level** command in interface configuration mode. To set the security level to the default, use the **no** form of this command. The security level protects higher security networks from lower security networks by imposing additional protection between the two.

security-level *number*

no security-level

Syntax Description

<i>number</i>	An integer between 0 (lowest) and 100 (highest).

Defaults

By default, the security level is 0.

If you name an interface “inside” and you do not set the security level explicitly, then the security appliance sets the security level to 100 (see the **nameif** command). You can change this level if desired.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was moved from a keyword of the nameif command to an interface configuration mode command.

Usage Guidelines

The level controls the following behavior:

- Network access—By default, there is an implicit permit from a higher security interface to a lower security interface (outbound). Hosts on the higher security interface can access any host on a lower security interface. You can limit access by applying an access list to the interface.

For same security interfaces, there is an implicit permit for interfaces to access other interfaces on the same security level or lower.

- Inspection engines—Some inspection engines are dependent on the security level. For same security interfaces, inspection engines apply to traffic in either direction.
 - NetBIOS inspection engine—Applied only for outbound connections.
 - OraServ inspection engine—If a control connection for the OraServ port exists between a pair of hosts, then only an inbound data connection is permitted through the security appliance.

- **Filtering**—HTTP(S) and FTP filtering applies only for outbound connections (from a higher level to a lower level).

For same security interfaces, you can filter traffic in either direction.

- **NAT control**—When you enable NAT control, you must configure NAT for hosts on a higher security interface (inside) when they access hosts on a lower security interface (outside).

Without NAT control, or for same security interfaces, you can choose to use NAT between any interface, or you can choose not to use NAT. Keep in mind that configuring NAT for an outside interface might require a special keyword.

- **established** command—This command allows return connections from a lower security host to a higher security host if there is already an established connection from the higher level host to the lower level host.

For same security interfaces, you can configure **established** commands for both directions.

Normally, interfaces on the same security level cannot communicate. If you want interfaces on the same security level to communicate, see the **same-security-traffic** command. You might want to assign two interfaces to the same level and allow them to communicate if you want to create more than 101 communicating interfaces, or you want protection features to be applied equally for traffic between two interfaces; for example, you have two departments that are equally secure.

If you change the security level of an interface, and you do not want to wait for existing connections to time out before the new security information is used, you can clear the connections using the **clear local-host** command.

Examples

The following example configures the security levels for two interfaces to be 100 and 0:

```
hostname(config)# interface gigabitethernet0/0
hostname(config-if)# nameif inside
hostname(config-if)# security-level 100
hostname(config-if)# ip address 10.1.1.1 255.255.255.0
hostname(config-if)# no shutdown
hostname(config-if)# interface gigabitethernet0/1
hostname(config-if)# nameif outside
hostname(config-if)# security-level 0
hostname(config-if)# ip address 10.1.2.1 255.255.255.0
hostname(config-if)# no shutdown
```

Related Commands

Command	Description
clear local-host	Resets all connections.
interface	Configures an interface and enters interface configuration mode.
nameif	Sets the interface name.
vlan	Assigns a VLAN ID to a subinterface.

serial-number

To include the security appliance serial number in the certificate during enrollment, use the **serial-number** command in crypto ca trustpoint configuration mode. To restore the default setting, use the **no** form of the command.

serial-number

no serial-number

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting is to not include the serial number.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Crypto ca trustpoint configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and includes the security appliance serial number in the enrollment request for trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# serial-number
hostname(ca-trustpoint)#
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint configuration mode.

server

To specify a default e-mail proxy server, use the **server** command in the applicable e-mail proxy mode. To remove the attribute from the configuration, use the **no** version of this command. The security appliance sends requests to the default e-mail server when the user connects to the e-mail proxy without specifying a server. If you do not configure a default server, and a user does not specify a server, the security appliance returns an error.

server {ipaddr or hostname}

no server

Syntax Description

hostname	The DNS name of the default e-mail proxy server.
ipaddr	The IP address of the default e-mail proxy server.

Defaults

There is no default e-mail proxy server by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Pop3s	•	•	—	—	•
Imap4s	•	•	—	—	•
Smtps	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to set a default POP3S e-mail server with an IP address. of 10.1.1.7:

```
hostname(config)# pop3s
hostname(config-pop3s)# server 10.1.1.7
```

server-port

To configure a AAA server port for a host, use the **server-port** command in AAA-server host mode. To remove the designated server port, use the **no** form of this command:

server-port *port-number*

no server-port

Syntax Description

port-number A port number in the range 0 through 65535.

Defaults

The default server ports are as follows:

- SDI—5500
- LDAP—389
- Kerberos—88
- NT—139
- TACACS+—49

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
AAA-server group	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example configures an SDI AAA server named “srvgrp1” to use server port number 8888:

```
hostname(config)# aaa-server srvgrp1 protocol sdi
hostname(config-aaa-server-group)# aaa-server srvgrp1 host 192.168.10.10
hostname(config-aaa-server-host)# server-port 8888
hostname(config-aaa-server-host)# exit
hostname(config)#
```

Related Commands

Command	Description
aaa-server host	Configures host-specific AAA server parameters.

clear configure aaa-server	Removes all AAA-server configuration.
show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol

server-separator

To specify a character as a delimiter between the e-mail and VPN server names, use **server-separator** command in the applicable e-mail proxy mode. To revert to the default, “:”, use the no form of this command.

server-separator {*symbol*}

no server-separator

Syntax Description

symbol The character that separates the e-mail and VPN server names. Choices are “@,” (at), “|” (pipe), “:” (colon), “#” (hash), “,” (comma), and “;” (semi-colon).

Defaults

The default is “@” (at).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Pop3s	•	—	•	—	—
Imap4s	•	—	•	—	—
Smtps	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The server separator must be different from the name separator.

Examples

The following example shows how to set a pipe (|) as the server separator for IMAP4S:

```
hostname(config)# imap4s
hostname(config-imap4s)# server-separator |
```

Related Commands

Command	Description
name-separator	Separates the e-mail and VPN usernames and passwords.

service

To enable system services, use the **service** command in global configuration mode. To disable system services, use the **no** form of this command.

service { **resetinbound** | **resetoutbound** } [**interface** *intf*]

no service { **resetinbound** | **resetoutbound** } [**interface** *intf*]

Syntax Description

resetinbound	Sends a reset to a denied inbound TCP packet.
resetoutbound	Sends a reset to a denied TCP packet to the outside interface.
interface	(Optional) Specifies a specific interface.
<i>intf</i>	Name of interface.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.
7.0(5)	This command was modified to include the <i>interface</i> keyword.

Usage Guidelines

The **service** command works with all inbound TCP connections to static interfaces whose access lists or uauth (user authorization) do not allow inbound connections. One use is for resetting identity request (IDENT) connections. If an inbound TCP connection is attempted and denied, you can use the **service resetinbound** command to return an RST (reset flag in the TCP header) to the source. Without the keyword, the security appliance drops the packet without returning an RST.

By default a RST is always sent to the inside host when outbound TCP traffic is denied. The keyword **resetoutbound** is used to change this default. For example, if traffic is outbound through the security appliance, and the **no service resetoutbound** command is configured globally or on that interface, we do not send RST.

With the optional **interface** keyword, the TCP reset is sent only when outbound packets are denied on that interface.

The security appliance sends a TCP RST to the host connecting inbound and stops the incoming IDENT process so that outbound e-mail can be transmitted without having to wait for IDENT to time out. The security appliance sends a syslog message stating that the incoming connection was denied. Without

entering the **service resetinbound** command, the security appliance drops packets that are denied and generates a syslog message stating that the SYN was denied. However, outside hosts keep retransmitting the SYN until the IDENT times out.

When an IDENT connection times out, the connections slow down. Perform a trace to determine that IDENT is causing the delay and then enter the **service** command.

Use the **service resetinbound** command to handle an IDENT connection through the security appliance. These methods for handling IDENT connections are ranked from most secure to the least secure:

1. Use the **service resetinbound** command.
2. Use the **established** command with the **permitto tcp 113** keyword.
3. Enter the **static** and **access-list** commands to open TCP port 113.

When using the **aaa** command, if the first attempt at authorization fails and a second attempt causes a timeout, use the **service resetinbound** command to reset the client that failed the authorization so that it will not retransmit any connections. An example authorization timeout message in Telnet is as follows:

```
Unable to connect to remote host: Connection timed out
```

The following is the expected behavior of traffic on the security appliance in regards to the reset flag.

1. If **resetinbound** is configured and if denied traffic flows from a low security interface to high security interface, then a reset is sent.
2. If **resetinbound** is configured and if denied traffic flows from an interface to another interface with the same security, then a reset is sent.
3. If **resetinbound** is not configured and if denied traffic flows from high security interface to low security interface, then a reset is sent.

If you use the **resetoutside** command, the security appliance actively resets denied TCP packets that terminate at the security appliances least-secure interface. By default, these packets are silently discarded. We recommend that you use the **resetoutside** keyword with dynamic or static interface Port Address Translation (PAT). The static interface PAT is available with security appliance version 6.0 and higher. This keyword allows the security appliance to terminate the IDENT from an external SMTP or FTP server. Actively resetting these connections avoids the 30-second timeout delay.

Examples

The following example shows how to enable system services:

```
hostname/context_name(config)# service resetinbound
```

This example shows how to enable system services on an interface called dmz1:

```
hostname/context_name(config)# service resetinbound interface dmz1
```

Related Commands

Command	Description
show running-config service	Displays the system services.

service password-recovery

To enable password recovery, use the **service password-recovery** command in global configuration mode. To disable password recovery, use the **no** form of this command. Password recovery is enabled by default, but you might want to disable it to ensure that unauthorized users cannot use the password recovery mechanism to compromise the security appliance.

service password-recovery

no service password-recovery

Syntax Description This command has no arguments or keywords.

Defaults Password recovery is enabled by default.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines On the ASA 5500 series adaptive security appliance, if you forget the passwords, you can boot the security appliance into ROMMON by pressing the **Escape** key on the terminal keyboard when prompted during startup. Then set the security appliance to ignore the startup configuration by changing the configuration register (see the **config-register** command). For example if your configuration register is the default 0x1, then change the value to 0x41 by entering the **confreg 0x41** command. After reloading the security appliance, it loads a default configuration, and you can enter privileged EXEC mode using the default passwords. Then load the startup configuration by copying it to the running configuration and reset the passwords. Finally, set the security appliance to boot as before by setting the configuration register to the original setting. For example, enter the **config-register 0x1** command in global configuration mode.

On the PIX 500 series security appliance, boot the security appliance into monitor mode by pressing the **Escape** key on the terminal keyboard when prompted during startup. Then download the PIX password tool to the security appliance, which erases all passwords and **aaa authentication** commands.

On the ASA 5500 series adaptive security appliance, the **no service password-recovery** command prevents a user from entering ROMMON with the configuration intact. When a user enters ROMMON, the security appliance prompts the user to erase all Flash file systems. The user cannot enter ROMMON without first performing this erasure. If a user chooses not to erase the Flash file system, the security appliance reloads. Because password recovery depends on using ROMMON and maintaining the

existing configuration, this erasure prevents you from recovering a password. However, disabling password recovery prevents unauthorized users from viewing the configuration or inserting different passwords. In this case, to recover the system to an operating state, load a new image and a backup configuration file, if available. The **service password-recovery** command appears in the configuration file for informational purposes only; when you enter the command at the CLI prompt, the setting is saved in NVRAM. The only way to change the setting is to enter the command at the CLI prompt. Loading a new configuration with a different version of the command does not change the setting. If you disable password recovery when the security appliance is configured to ignore the startup configuration at startup (in preparation for password recovery), then the security appliance changes the setting to boot the startup configuration as usual. If you use failover, and the standby unit is configured to ignore the startup configuration, then the same change is made to the configuration register when the **no service password recovery** command replicates to the standby unit.

On the PIX 500 series security appliance, the **no service password-recovery** command forces the PIX password tool to prompt the user to erase all Flash file systems. The user cannot use the PIX password tool without first performing this erasure. If a user chooses not to erase the Flash file system, the security appliance reloads. Because password recovery depends on maintaining the existing configuration, this erasure prevents you from recovering a password. However, disabling password recovery prevents unauthorized users from viewing the configuration or inserting different passwords. In this case, to recover the system to an operating state, load a new image and a backup configuration file, if available.

Examples

The following example disables password recovery for the ASA 5500 series adaptive security appliance:

```
hostname(config)# no service password-recovery
WARNING: Executing "no service password-recovery" has disabled the password recovery
mechanism and disabled access to ROMMON. The only means of recovering from lost or
forgotten passwords will be for ROMMON to erase all file systems including configuration
files and images. You should make a backup of your configuration and have a mechanism to
restore images from the ROMMON command line.
```

The following example disables password recovery for the PIX 500 series security appliance:

```
hostname(config)# no service password-recovery
WARNING: Saving "no service password-recovery" in the startup-config will disable password
recovery via the npdisk application. The only means of recovering from lost or forgotten
passwords will be for npdisk to erase all file systems including configuration files and
images. You should make a backup of your configuration and have a mechanism to restore
images from the Monitor Mode command line.
```

The following example for the ASA 5500 series adaptive security appliance shows when to enter ROMMON at startup and how to complete a password recovery operation.

```
Use BREAK or ESC to interrupt boot.
Use SPACE to begin boot immediately.
Boot interrupted.
```

```
Use ? for help.
rommon #0> confreg
```

```
Current Configuration Register: 0x00000001
Configuration Summary:
  boot default image from Flash
```

```
Do you wish to change this configuration? y/n [n]: n
```

```
rommon #1> confreg 0x41
```

```
Update Config Register (0x41) in NVRAM...
```

```

rommon #2> boot
Launching BootLoader...
Boot configuration file contains 1 entry.

Loading disk0:/ASA_7.0.bin... Booting...
#####
...
Ignoring startup configuration as instructed by configuration register.
Type help or '?' for a list of available commands.
hostname> enable
Password:
hostname# configure terminal
hostname(config)# copy startup-config running-config

Destination filename [running-config]?
Cryptochecksum(unchanged): 7708b94c e0e3f0d5 c94dde05 594fbee9

892 bytes copied in 6.300 secs (148 bytes/sec)
hostname(config)# enable password NewPassword
hostname(config)# config-register 0x1

```

Related Commands

Command	Description
config-register	Sets the security appliance to ignore the startup configuration when it reloads.
enable password	Sets the enable password.
password	Sets the login password.

service-policy

To activate a policy map globally on all interfaces or on a targeted interface, use the **service-policy** command in privileged EXEC mode. To disable, use the **no** form of this command. Use the **service-policy** command to enable a set of policies on an interface. In general, a **service-policy** command can be applied to any interface that can be defined by the **nameif** command.

service-policy *policymap_name* [**global** | **interface** *intf*]

no service-policy *policymap_name* [**global** | **interface** *intf*]

Syntax Description

<i>policymap_name</i>	A unique alphanumeric policy map identifier.
global	Applies the policy map to all interfaces.
interface	Applies the policy map to a specific interface
<i>intf</i>	The interface name defined in the nameif command.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If an interface name is specified, the policy-map only applies to the interface. The interface name is defined in the **nameif** command, and an interface policy-map overrides a global policy-map. Only one policy-map is allowed per interface.

Only one global policy is allowed.

Examples

The following example shows the syntax of the **service-policy** command:

```
hostname(config)# service-policy outside_security_map outside
```

Related Commands

Command	Description
show service-policy	Displays the service policy.
show running-config service-policy	Displays the service policies configured in the running configuration.
clear service-policy	Clears service policy statistics.
clear configure service-policy	Clears service policy configurations.

session

To establish a Telnet session to an AIP SSM, use the **session** command in privileged EXEC mode.

session 1

Syntax Description

1 Specifies the slot number, which is always 1.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is only available when the AIP SSM is in the Up state. See the **show module** command for state information.

To end a session, enter **exit** or **Ctrl-Shift-6** then the **X** key.

Examples

The following example sessions to an SSM in slot 1:

```
hostname# session 1
Opening command session with slot 1.
Connected to slot 1. Escape character sequence is 'CTRL-^X'.
```

Related Commands

Command	Description
debug session-command	Shows debug messages for sessions.

set connection

To specify connection values within a policy-map for a traffic class, use the **set connection** command in class mode. Use this command to specify the maximum number of simultaneous connections and to specify whether to enable or disable TCP sequence number randomization. To remove these specifications, thereby allowing unlimited connections, use the **no** form of this command.

```
set connection {conn-max | embryonic-conn-max} n random-seq# {enable | disable}
```

```
no set connection {conn-max | embryonic-conn-max} n random-seq# {enable | disable}
```

Syntax Description	conn-max <i>n</i>	The maximum number of simultaneous TCP and/or UDP connections that are allowed.
	disable	Turns off TCP sequence number randomization.
	enable	Turns on TCP sequence number randomization.
	embryonic-conn-max <i>n</i>	The maximum number of simultaneous embryonic connections allowed.
	random-seq#	Enable or disable TCP sequence number randomization. Each TCP connection has two ISNs: one generated by the client and one generated by the server. The security appliance randomizes the ISN of the TCP SYN passing in both the inbound and outbound directions. Randomizing the ISN of the protected host prevents an attacker from predicting the next ISN for a new connection and potentially hijacking the new session. TCP initial sequence number randomization can be disabled if required. For example: • If another in-line firewall is also randomizing the initial sequence numbers, there is no need for both firewalls to be performing this action, even though this action does not affect the traffic. • If you use eBGP multi-hop through the security appliance, and the eBGP peers are using MD5. Randomization breaks the MD5 checksum. • You use a WAAS device that requires the security appliance not to randomize the sequence numbers of connections.

Defaults

For both the **conn-max** and **embryonic-conn-max** parameters, the default value of *n* is 0, which allows unlimited connections.

Sequence number randomization is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must have configured the **policy-map** command and the **class** command before issuing this command.

**Note**

The **set connection** command parameters (**conn-max**, **embryonic-conn-max**, **random-seq#**) can co-exist with any **nat** or **static** command; that is, you can configure connection parameters either through the **nat/static** commands using **max-conn**, **emb_limit**, or **norandomseq** parameters, or through the MPC **set connection** command using **conn-max**, **embryonic-conn-max**, or **random-seq#** parameters. A mixed configuration is not recommended, but if one exists, it behaves in the following ways:

When a traffic class is subject to a connection limit or embryonic connection limit from both the MPC **set connection** command and the **nat/static** command, then whichever limit is reached, that limit is applied.

When a TCP traffic class is configured to have sequence number randomization disabled by either the MPC **set connection** command or the **nat/static** command, then sequence number randomization is disabled.

Examples

The following is an example of the use of the **set connection** command in class mode to configure the maximum number of simultaneous connections as 256 and to disable TCP sequence number randomization:

```
hostname(config)# policy-map localpolicy1
hostname(config-pmap)# class local_server
hostname(config-pmap-c)# set connection conn-max 256 random-seq# disable
hostname(config-pmap-c)# exit
```

Related Commands

Command	Description
class	Specifies a class-map to use for traffic classification.
clear configure policy-map	Remove all policy-map configuration, except that if a policy-map is in use in a service-policy command, that policy-map is not removed.
help policy-map	Shows syntax help for the policy-map command.

policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
show running-config policy-map	Display all current policy-map configurations.

set connection advanced-options

To specify advanced TCP connection options within a policy-map for a traffic class, use the **set connection advanced-options** command in class mode. To remove advanced TCP connection options for a traffic class within a policy map, use the **no** form of this command.

set connection advanced-options *tcp-mapname*

no set connection advanced-options *tcp-mapname*

Syntax Description

<i>tcp-mapname</i>	Name of a TCP map in which advanced TCP connection options are configured.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Class	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must have configured the **policy-map** command and the **class** command, as well as the TCP map name, before issuing this command. See the description of the **tcp-map** command for detailed information.

Examples

The following example shows the use of the **set connection advanced-options** command to specify the use of a TCP map named localmap:

```
hostname(config)# access-list http-server permit tcp any host 10.1.1.1
hostname(config)# class-map http-server
hostname(config-cmap)# match access-list http-server
hostname(config-cmap)# exit
hostname(config)# tcp-map localmap
hostname(config)# policy-map global_policy global
hostname(config-pmap)# description This policy map defines a policy concerning connection
to http server.
hostname(config-pmap)# class http-server
hostname(config-pmap-c)# set connection advanced-options localmap
```

Related Commands	Command	Description
	class	Specifies a class-map to use for traffic classification.
	class-map	Configures a traffic class by issuing at most one (with the exception of tunnel-group and default-inspection-traffic) match command, specifying match criteria, in the class-map mode.
	clear configure policy-map	Remove all policy-map configuration, except that if a policy-map is in use in a service-policy command, that policy-map is not removed.
	policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
	show running-config policy-map	Display all current policy-map configurations.

set connection timeout

To configure the timeout period, after which an idle TCP connection is disconnected, use the **set connection timeout** command in class mode. To remove the timeout, use the **no** form of this command.

set connection timeout tcp *hh[:mm[:ss]]* [**reset**]

no set connection timeout tcp

set connection timeout embryonic *hh[:mm[:ss]]*

no set connection timeout embryonic

set connection timeout half-closed *hh[:mm[:ss]]*

no set connection timeout half-closed

Syntax Description

embryonic <i>hh[:mm[:ss]]</i>	Timeout period after which a TCP embryonic (half-opened) connection is closed.
half-closed <i>hh[:mm[:ss]]</i>	The timeout period until a TCP half-closed connection is freed.
reset	Sends a TCP RST packet to both end systems after TCP idle connections are removed.
tcp <i>hh[:mm[:ss]]</i>	The idle time after which an established connection closes.

Defaults

The default **embryonic** connection timeout value is 30 seconds.

The default **half-closed** connection timeout value is 10 minutes.

The default **tcp** connection timeout value is 1 hour.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Class	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You must have configured the **policy-map** command and the **class** command before issuing this command.

A TCP connection for which a three-way handshake is not complete is an *embryonic* connection. For the **embryonic** connection timeout value, use **0:0:0** to specify that the connection never times out. Otherwise, the timeout duration must be at least 5 seconds.

When the TCP connection is in the closing state, use the half-closed parameter to configure the length of time until the connection is freed. Use **0:0:0** to specify that the connection never times out. The minimum timeout duration is 5 minutes.

The **tcp** inactive connection timeout configures the period after which an idle TCP connection in the established state is disconnected. Use **0:0:0** to specify that the connection never times out. The minimum timeout duration is 5 minutes.

The **reset** keyword is used to send a TCP RST packet to both end systems once an idle TCP connection has timed out. Some applications require a TCP RST after a timeout to perform properly.

Examples

The following is an example of a **set connection timeout** command that specifies an embryonic connection **timeout** of two minutes:

```
hostname(config)# access-list http-server permit tcp any host 10.1.1.1
hostname(config)# class-map http-server

hostname(config-cmap)# match access-list http-server
hostname(config-cmap)# exit

hostname(config)# policy-map global_policy global
hostname(config-pmap)# description This policy map defines a policy concerning connection
to http server.
hostname(config-pmap)# class http-server
hostname(config-pmap-c)# set connection timeout embryonic 00:2:00
```

Related Commands

Command	Description
class	Specifies a class-map to use for traffic classification.
clear configure policy-map	Remove all policy-map configuration, except that if a policy-map is in use in a service-policy command, that policy-map is not removed.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
set connection	Configure connection values.
show running-config policy-map	Display all current policy-map configurations.

set metric

To set the metric value for a routing protocol, use the **set metric** command in route-map configuration mode. To return to the default metric value, use the **no** form of this command.

set metric *value*

no set metric *value*

Syntax Description	<i>value</i>	Metric value.

Defaults	No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Route-map configuration	•	—	•	—	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines The **no set metric value** command allows you to return to the default metric value. In this context, the *value* is an integer from 0 to 4294967295.

Examples The following example shows how to configure a route map for OSPF routing:

```
hostname(config)# route-map maptag1 permit 8
hostname(config-route-map)# set metric 5
hostname(config-route-map)# match metric 5
hostname(config-route-map)# show route-map
route-map maptag1 permit 8
set metric 5
match metric 5
hostname(config-route-map)# exit
hostname(config)#
```


Related Commands

Command	Description
match interface	Distributes any routes that have their next hop out one of the interfaces specified,
match ip next-hop	Distributes any routes that have a next-hop router address that is passed by one of the access lists specified.
route-map	Defines the conditions for redistributing routes from one routing protocol into another.

set metric-type

To specify the type of OSPF metric routes, use the **set metric-type** command in route-map configuration mode. To return to the default setting, use the **no** form of this command.

set metric-type { type-1 | type-2 }

no set metric-type

Syntax Description

type-1	Specifies the type of OSPF metric routes that are external to a specified autonomous system.
type-2	Specifies the type of OSPF metric routes that are external to a specified autonomous system.

Defaults

The default is **type-2**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Route-map configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example shows how to configure a route map for OSPF routing:

```
hostname(config)# route-map maptag1 permit 8
hostname(config-route-map)# set metric 5
hostname(config-route-map)# match metric 5
hostname(config-route-map)# set metric-type type-2
hostname(config-route-map)# show route-map
route-map maptag1 permit 8
  set metric 5
  set metric-type type-2
  match metric 5
hostname(config-route-map)# exit
hostname(config)#
```

Related Commands

Command	Description
match interface	Distributes any routes that have their next hop out one of the interfaces specified,
route-map	Defines the conditions for redistributing routes from one routing protocol into another.
set metric	Specifies the metric value in the destination routing protocol for a route map.

setup

To configure a minimal configuration for the security appliance using interactive prompts, enter the **setup** command in global configuration mode. This configuration provides connectivity to use ASDM. See also the **configure factory-default** command to restore the default configuration.

setup

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The setup dialog automatically appears at boot time if there is no startup configuration in Flash memory.

Before you can use the **setup** command, you must have an inside interface already configured. The PIX 500 series default configuration includes an inside interface (Ethernet 1), but the ASA 550 series default configuration does not. Before using the **setup** command, enter the **interface** command for the interface you want to make inside, and then the **nameif inside** command.

In multiple context mode, you can use the **setup** command in the system execution space and for each context.

When you enter the **setup** command, you are asked for the information in [Table 7-1](#). The system **setup** command includes a subset of these prompts. If there is already a configuration for the prompted parameter, it appears in brackets so you can either accept it as the default or override it by entering something new.

Table 7-1 Setup Prompts

Prompt	Description
Pre-configure Firewall now through interactive prompts [yes]?	Enter yes or no . If you enter yes , the setup dialog continues. If no , the setup dialog stops and the global configuration prompt (hostname(config)#) appears.

Table 7-1 Setup Prompts (continued)

Firewall Mode [Routed]:	Enter routed or transparent .
Enable password:	Enter an enable password. (The password must have at least three characters.)
Allow password recovery [yes]?	Enter yes or no .
Clock (UTC):	You cannot enter anything in this field. UTC time is used by default.
Year:	Enter the year using four digits, for example, 2005. The year range is 1993 to 2035.
Month:	Enter the month using the first three characters of the month; for example, Sep for September.
Day:	Enter the day of the month, from 1 to 31.
Time:	Enter the hour, minutes, and seconds in 24-hour time format. For example, enter 20:54:44 for 8:54 p.m and 44 seconds.
Inside IP address:	Enter the IP address for the inside interface.
Inside network mask:	Enter the network mask that applies to the inside IP address. You must specify a valid network mask, such as 255.0.0.0 or 255.255.0.0.
Host name:	Enter the hostname that you want to display in the command line prompt.
Domain name:	Enter the domain name of the network on which the security appliance runs.
IP address of host running Device Manager:	Enter the IP address of the host that needs to access ASDM.
Use this configuration and write to flash?	Enter yes or no . If you enter yes , the inside interface is enabled and the requested configuration is written to the Flash partition. If you enter no , the setup dialog repeats, beginning with the first question: Pre-configure Firewall now through interactive prompts [yes]? Enter no to exit the setup dialog or yes to repeat it.

Examples

This example shows how to complete the **setup** command prompts:

```
hostname(config)# setup
Pre-configure Firewall now through interactive prompts [yes]? yes
Firewall Mode [Routed]: routed
Enable password [<use current password>]: writer
Allow password recovery [yes]? yes
Clock (UTC):
  Year: 2005
  Month: Nov
  Day: 15
  Time: 10:0:0
Inside IP address: 192.168.1.1
Inside network mask: 255.255.255.0
Host name: tech_pubs
Domain name: your_company.com
IP address of host running Device Manager: 10.1.1.1
```

The following configuration will be used:
Enable password: writer

```

Allow password recovery: yes
Clock (UTC): 20:54:44 Sep 17 2005
Firewall Mode: Routed
Inside IP address: 192.168.1.1
Inside network mask: 255.255.255.0
Host name: tech_pubs
Domain name: your_company.com
IP address of host running Device Manager: 10.1.1.1

Use this configuration and write to flash? yes

```

Related Commands

Command	Description
configure	Restores the default configuration.
factory-default	

show aaa local user

To show the list of usernames that are currently locked, or to show details about the username, use the **show aaa local user** command in global configuration mode.

show aaa local user [locked]

Syntax Description	locked (Optional) Shows the list of usernames that are currently locked.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	If you omit the optional keyword locked, the security appliance displays the failed-attempts and lockout status details for all AAA local users. You can specify a single user by using the username option or all users with the all option. This command affects only the status of users that are locked out. The administrator cannot be locked out of the device.

Examples	The following example shows use of the show aaa local user command to display the lockout status of all usernames:

This example shows the use of the **show aaa local user** command to display the number of failed authentication attempts and lockout status details for all AAA local users, after the limit has been set to 5:

```
hostname(config)# aaa local authentication attempts max-fail 5
hostname(config)# show aaa local user
Lock-time  Failed-attempts  Locked  User
-           6              Y      test
-           2              N      mona
-           1              N      cisco
-           4              N      newuser
hostname(config)#
```

This example shows the use of the **show aaa local user** command with the **lockout** keyword to display the number of failed authentication attempts and lockout status details only for any locked-out AAA local users, after the limit has been set to 5:

```
hostname(config)# aaa local authentication attempts max-fail 5
hostname(config)# show aaa local user
Lock-time  Failed-attempts  Locked  User
-          6              Y      test
hostname(config)#
```

Related Commands

Command	Description
aaa local authentication attempts max-fail	Configures the maximum number of times a user can enter a wrong password before being locked out.
clear aaa local user fail-attempts	Resets the number of failed attempts to 0 without modifying the lockout status.
clear aaa local user lockout	Clears the lockout status of the specified user or all users and sets their failed attempts counters to 0.

show aaa-server

To display AAA server statistics for AAA servers, use the **show aaa-server** command in privileged EXEC mode:

show aaa-server [**LOCAL** | *groupname* [**host** *hostname*] | **protocol** *protocol*]

Syntax Description

LOCAL	(Optional) Shows statistics for the LOCAL user database.
<i>groupname</i>	(Optional) Shows statistics for servers in a group.
host <i>hostname</i>	(Optional) Shows statistics for a particular server in the group.
protocol <i>protocol</i>	(Optional) Shows statistics for servers of the specified protocol: • kerberos • ldap • nt • radius • sdi • tacacs+

Defaults

By default, all AAA server statistics display.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	—	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

This example shows the use of the **show aaa-server** command to display statistics for a particular host in server group group1:

```
hostname(config)# show aaa-server group1 host 192.68.125.60
Server Group:          group1
Server Protocol:       RADIUS
Server Address:        192.68.125.60
Server port:           1645
Server status:         ACTIVE/FAILED. Last transaction (success) at 11:10:08 UTC  Fri Aug 22
Number of pending requests 20
Average round trip time4ms
Number of authentication requests20
```

show aaa-server

```

Number of authorization requests 0
Number of accounting requests 0
Number of retransmissions1
Number of accepts 16
Number of rejects 4
Number of challenges 5
Number of malformed responses0
Number of bad authenticators0
Number of pending requests0
Number of timeouts 0
Number of unrecognized responses0
hostname(config)#

```

This example shows the use of the **show aaa-server** command to show the statistics for all servers in a small, inactive system:

```

hostname(config)# show aaa-server
Server Group:      LOCAL
Server Protocol:   Local database
Server Address:    None
Server port:       None
Server status:     ACTIVE, Last transaction at unknown
Number of pending requests      0
Average round trip time        0ms
Number of authentication requests 0
Number of authorization requests 0
Number of accounting requests   0
Number of retransmissions       0
Number of accepts               0
Number of rejects               0
Number of challenges            0
Number of malformed responses   0
Number of bad authenticators    0
Number of timeouts             0
Number of unrecognized responses 0
hostname(config)#

```

Related Commands

show running-config aaa-server	Display statistics for all servers in the indicated server group or for a particular server.
clear aaa-server statistics	Clear the AAA server statistics.

show access-list

To display the counters for an access list, use the **show access-list** command in privileged EXEC mode.

show access-list *id*

Syntax Description	<i>id</i>	Identifies the access list.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Examples	The following is sample output from the show access-list command:

```
hostname# show access-list ac
access-list ac; 2 elements
  access-list ac line 1 permit ip any any (hitcnt=0)
  access-list ac line 2 permit tcp any any (hitcnt=0)
```

Related Commands	Command	Description
	access-list ethertype	Configures an access list that controls traffic based on its EtherType.
	access-list extended	Adds an access list to the configuration and configures policy for IP traffic through the firewall.
	clear access-list	Clears an access list counter.
	clear configure access-list	Clears an access list from the running configuration.
	show running-config access-list	Displays the current running access-list configuration.

show activation-key

To display the commands in the configuration for features that are enabled by your activation key, including the number of contexts allowed, use the **show activation-key** command in privileged EXEC mode.

show activation-key

Syntax Description This command has no arguments or keywords.

Defaults This command has no default settings.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
PIX Version 7.0	Support for this command was introduced on the security appliance.

Usage Guidelines The **show activation-key** command output indicates the status of the activation key as follows:

- If the activation key in the security appliance Flash file system is the same as the activation key running on the security appliance, then the **show activation-key** output reads as follows:
The flash activation key is the SAME as the running key.
- If the activation key in the security appliance Flash file system is different from the activation key running on the security appliance, then the **show activation-key** output reads as follows:
The flash activation key is DIFFERENT from the running key.
The flash activation key takes effect after the next reload.
- If you downgrade your activation key, the display shows that the running key (the old key) differs from the key that is stored in the Flash (the new key). When you restart, the security appliance uses the new key.
- If you upgrade your key to enable extra features, the new key starts running immediately without a restart.

- For the PIX Firewall platform, if there is any change in the failover feature (R/UR/FO) between the new key and the oldkey, it prompts for confirmation. If the user enters **n**, it aborts the change; otherwise it updates the key in the Flash file system. When you restart the security appliance uses the new key.

Examples

This example shows how to display the commands in the configuration for features that are enabled by your activation key:

```
hostname(config)# show activation-key
```

```
Serial Number: P3000000134 Running Activation Key: Oxyadayada Oxyadayada Oxyadayada
Oxyadayada Oxyadayada
```

```
License Features for this Platform:
```

```
Maximum Physical Interfaces : Unlimited
Maximum VLANs               : 50
Inside Hosts                 : Unlimited
Failover                     : Enabled
VPN-DES                      : Enabled
VPN-3DES-AES                 : Disabled
Cut-through Proxy            : Enabled
Guards                       : Enabled
URL-filtering                 : Enabled
Security Contexts            : 20
GTP/GPRS                     : Disabled
VPN Peers                    : 5000
```

```
The flash activation key is the SAME as the running key.
```

```
hostname(config)#
```

Related Commands

Command	Description
activation-key	Changes the activation key.

show admin-context

To display the context name currently assigned as the admin context, use the **show admin-context** command in privileged EXEC mode.

show admin-context

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following is sample output from the **show admin-context** command. The following example shows the admin context called “admin” and stored in the root directory of flash:

```
hostname# show admin-context
Admin: admin flash:/admin.cfg
```

Related Commands

Command	Description
admin-context	Sets the admin context.
changeto	Changes between contexts or the system execution space.
clear configure context	Removes all contexts.
mode	Sets the context mode to single or multiple.
show context	Shows a list of contexts (system execution space) or information about the current context.

show arp

To view the ARP table, use the **show arp** command in privileged EXEC mode.

show arp

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0(8)	Added dynamic ARP age to the display.

Usage Guidelines The display output shows dynamic, static, and proxy ARP entries. Dynamic ARP entries include the age of the ARP entry in seconds. Static ARP entries include a dash (-) instead of the age, and proxy ARP entries state “alias.”

Examples The following is sample output from the **show arp** command. The first entry is a dynamic entry aged 2 seconds. The second entry is a static entry, and the third entry is from proxy ARP.

```
hostname# show arp
  outside 10.86.194.61 0011.2094.1d2b 2
  outside 10.86.194.1 001a.300c.8000 -
  outside 10.86.195.2 00d0.02a8.440a alias
```

Related Commands	Command	Description
	arp	Adds a static ARP entry.
	arp-inspection	For transparent firewall mode, inspects ARP packets to prevent ARP spoofing.
	clear arp statistics	Clears ARP statistics.
	show arp statistics	Shows ARP statistics.
	show running-config arp	Shows the current configuration of the ARP timeout.

■ show arp

show arp-inspection

To view the ARP inspection setting for each interface, use the **show arp-inspection** command in privileged EXEC mode.

show arp-inspection

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	—	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples The following is sample output from the **show arp-inspection** command:

```
hostname# show arp-inspection
interface      arp-inspection      miss
-----
inside1        enabled              flood
outside        disabled              -
```

The **miss** column shows the default action to take for non-matching packets when ARP inspection is enabled, either “flood” or “no-flood.”

Related Commands

Command	Description
arp	Adds a static ARP entry.
arp-inspection	For transparent firewall mode, inspects ARP packets to prevent ARP spoofing.
clear arp statistics	Clears ARP statistics.
show arp statistics	Shows ARP statistics.
show running-config arp	Shows the current configuration of the ARP timeout.

show arp statistics

To view ARP statistics, use the `show arp statistics` command in privileged EXEC mode.

show arp statistics

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
Preexisting	This command was preexisting.

Command History

Examples The following is sample output from the `show arp statistics` command:

```
hostname# show arp statistics
  Number of ARP entries:
  ASA : 6
  Dropped blocks in ARP: 6
  Maximum Queued blocks: 3
  Queued blocks: 1
  Interface collision ARPs Received: 5
  ARP-defense Gratuitous ARPs sent: 4
  Total ARP retries: 15
  Unresolved hosts: 1
  Maximum Unresolved hosts: 2
```

Table 2 shows each field description.

Table 7-2 *show arp statistics Fields*

Field	Description
Number of ARP entries	The total number of ARP table entries.
Dropped blocks in ARP	The number of blocks that were dropped while IP addresses were being resolved to their corresponding hardware addresses.
Maximum queued blocks	The maximum number of blocks that were ever queued in the ARP module, while waiting for the IP address to be resolved.

Table 7-2 *show arp statistics Fields (continued)*

Field	Description
Queued blocks	The number of blocks currently queued in the ARP module.
Interface collision ARPs received	The number of ARP packets received at all security appliance interfaces that were from the same IP address as that of a security appliance interface.
ARP-defense gratuitous ARPs sent	The number of gratuitous ARPs sent by the security appliance as part of the ARP-Defense mechanism.
Total ARP retries	The total number of ARP requests sent by the ARP module when the address was not resolved in response to first ARP request.
Unresolved hosts	The number of unresolved hosts for which ARP requests are still being sent out by the ARP module.
Maximum unresolved hosts	The maximum number of unresolved hosts that ever were in the ARP module since it was last cleared or the security appliance booted up.

Related Commands

Command	Description
arp-inspection	For transparent firewall mode, inspects ARP packets to prevent ARP spoofing.
clear arp statistics	Clears ARP statistics and resets the values to zero.
show arp	Shows the ARP table.
show running-config arp	Shows the current configuration of the ARP timeout.

show asdm history

To display the contents of the ASDM history buffer, use the **show asdm history** command in privileged EXEC mode.

show asdm history [**view** *timeframe*] [**snapshot**] [**feature** *feature*] [**asdmclient**]

Syntax Description	
asdmclient	(Optional) Displays the ASDM history data formatted for the ASDM client.
feature <i>feature</i>	(Optional) Limits the history display to the specified feature. The following are valid values for the <i>feature</i> argument: • all—Displays the history for all features (default). • blocks—Displays the history for the system buffers. • cpu—Displays the history for CPU usage. • failover—Displays the history for failover. • ids—Displays the history for IDS. • interface <i>if_name</i>—Displays the history for the specified interface. The <i>if_name</i> argument is the name of the interface as specified by the nameif command. • memory—Displays memory usage history. • perfmon—Displays performance history. • sas—Displays the history for Security Associations. • tunnels—Displays the history for tunnels. • xlates—Displays translation slot history.
snapshot	(Optional) Displays only the last ASDM history data point.
view <i>timeframe</i>	(Optional) Limits the history display to the specified time period. Valid values for the <i>timeframe</i> argument are: • all—all contents in the history buffer (default). • 12h—12 hours • 5d—5 days • 60m—60 minutes • 10m—10 minutes

Defaults

If no arguments or keywords are specified, all history information for all features is displayed.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was changed from the show pdm history command to the show asdm history command.

Usage Guidelines

The **show asdm history** command displays the contents of the ASDM history buffer. Before you can view ASDM history information, you must enable ASDM history tracking using the **asdm history enable** command.

Examples

The following is sample output from the **show asdm history** command. It limits the output to data for the outside interface collected during the last 10 minutes.

```
hostname# show asdm history view 10m feature interface outside

Input KByte Count:
  [ 10s:12:46:41 Mar 1 2005 ] 62640 62636 62633 62628 62622 62616 62609
Output KByte Count:
  [ 10s:12:46:41 Mar 1 2005 ] 25178 25169 25165 25161 25157 25151 25147
Input KPacket Count:
  [ 10s:12:46:41 Mar 1 2005 ]   752   752   751   751   751   751   751
Output KPacket Count:
  [ 10s:12:46:41 Mar 1 2005 ]    55    55    55    55    55    55    55
Input Bit Rate:
  [ 10s:12:46:41 Mar 1 2005 ] 3397 2843 3764 4515 4932 5728 4186
Output Bit Rate:
  [ 10s:12:46:41 Mar 1 2005 ] 7316 3292 3349 3298 5212 3349 3301
Input Packet Rate:
  [ 10s:12:46:41 Mar 1 2005 ]    5    4    6    7    6    8    6
Output Packet Rate:
  [ 10s:12:46:41 Mar 1 2005 ]    1    0    0    0    0    0    0
Input Error Packet Count:
  [ 10s:12:46:41 Mar 1 2005 ]    0    0    0    0    0    0    0
No Buffer:
  [ 10s:12:46:41 Mar 1 2005 ]    0    0    0    0    0    0    0
Received Broadcasts:
  [ 10s:12:46:41 Mar 1 2005 ] 375974 375954 375935 375902 375863 375833 375794
Runts:
  [ 10s:12:46:41 Mar 1 2005 ]    0    0    0    0    0    0    0
Giants:
  [ 10s:12:46:41 Mar 1 2005 ]    0    0    0    0    0    0    0
CRC:
  [ 10s:12:46:41 Mar 1 2005 ]    0    0    0    0    0    0    0
Frames:
  [ 10s:12:46:41 Mar 1 2005 ]    0    0    0    0    0    0    0
Overruns:
  [ 10s:12:46:41 Mar 1 2005 ]    0    0    0    0    0    0    0
Underruns:
```

show asdm history

```

[ 10s:12:46:41 Mar 1 2005 ] 0 0 0 0 0 0 0
Output Error Packet Count:
[ 10s:12:46:41 Mar 1 2005 ] 0 0 0 0 0 0 0
Collisions:
[ 10s:12:46:41 Mar 1 2005 ] 0 0 0 0 0 0 0
LCOLL:
[ 10s:12:46:41 Mar 1 2005 ] 0 0 0 0 0 0 0
Reset:
[ 10s:12:46:41 Mar 1 2005 ] 0 0 0 0 0 0 0
Deferred:
[ 10s:12:46:41 Mar 1 2005 ] 0 0 0 0 0 0 0
Lost Carrier:
[ 10s:12:46:41 Mar 1 2005 ] 0 0 0 0 0 0 0
Hardware Input Queue:
[ 10s:12:46:41 Mar 1 2005 ] 128 128 128 128 128 128 128
Software Input Queue:
[ 10s:12:46:41 Mar 1 2005 ] 0 0 0 0 0 0 0
Hardware Output Queue:
[ 10s:12:46:41 Mar 1 2005 ] 0 0 0 0 0 0 0
Software Output Queue:
[ 10s:12:46:41 Mar 1 2005 ] 0 0 0 0 0 0 0
Drop KPacket Count:
[ 10s:12:46:41 Mar 1 2005 ] 0 0 0 0 0 0 0
hostname#

```

The following is sample output from the **show asdm history** command. Like the previous example, it limits the output to data for the outside interface collected during the last 10 minutes. However, in this example the output is formatted for the ASDM client.

```
hostname# show asdm history view 10m feature interface outside asdmclient
```

```

MH|IBC|10|CURFACT|0|CURVAL|0|TIME|1109703031|MAX|60|NUM|60|62439|62445|62453|62457|62464|6
2469|62474|62486|62489|62496|62501|62506|62511|62518|62522|62530|62534|62539|62542|62547|6
2553|62556|62562|62568|62574|62581|62585|62593|62598|62604|62609|62616|62622|62628|62633|6
2636|62640|62653|62657|62665|62672|62678|62681|62686|62691|62695|62700|62704|62711|62718|6
2723|62728|62733|62738|62742|62747|62751|62761|62770|62775|
MH|OBC|10|CURFACT|0|CURVAL|0|TIME|1109703031|MAX|60|NUM|60|25023|25023|25025|25025|25025|2
5026|25026|25032|25038|25044|25052|25056|25060|25064|25070|25076|25083|25087|25091|25096|2
5102|25106|25110|25114|25118|25122|25128|25133|25137|25143|25147|25151|25157|25161|25165|2
5169|25178|25321|25327|25332|25336|25341|25345|25349|25355|25359|25363|25367|25371|25375|2
5381|25386|25390|25395|25399|25403|25410|25414|25418|25422|
MH|IPC|10|CURFACT|0|CURVAL|0|TIME|1109703031|MAX|60|NUM|60|749|749|749|749|749|750|750|750
|750|750|750|750|750|750|750|750|750|750|750|751|751|751|751|751|751|751|751|751|751|7
51|751|751|751|751|752|752|752|752|752|752|752|752|752|752|752|752|752|752|753|753|753|7
753|753|753|753|753|753|753|
MH|OPC|10|CURFACT|0|CURVAL|0|TIME|1109703031|MAX|60|NUM|60|55|55|55|55|55|55|55|55|55|55|5
5|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|55|5
5|55|55|56|56|56|56|56|56|56|56|56|56|56|56|56|56|56|56|56|56|56|56|56|56|56|56|56|
MH|IBR|10|CURFACT|0|CURVAL|0|TIME|1109703031|MAX|60|NUM|60|7127|5155|6202|3545|5408|3979|4
381|9492|3033|4962|4571|4226|3760|5923|3265|6494|3441|3542|3162|4076|4744|2726|4847|4292|5
401|5166|3735|6659|3837|5260|4186|5728|4932|4515|3764|2843|3397|10768|3080|6309|5969|4472|
2780|4492|3540|3664|3800|3002|6258|5567|4044|4059|4548|3713|3265|4159|3630|8235|6934|4298|
MH|OBR|10|CURFACT|0|CURVAL|0|TIME|1109703031|MAX|60|NUM|60|82791|57|1410|588|57|639|0|4698
|5068|4992|6495|3292|3292|3352|5061|4808|5205|3931|3298|3349|5064|3439|3356|3292|3343|3349
|5067|3883|3356|4500|3301|3349|5212|3298|3349|3292|7316|116896|5072|3881|3356|3931|3298|33
49|5064|3292|3349|3292|3292|3349|5061|3883|3356|3931|3452|3356|5064|3292|3349|3292|
MH|IPR|10|CURFACT|0|CURVAL|0|TIME|1109703031|MAX|60|NUM|60|12|8|6|5|7|5|6|14|5|7|7|5|6|9|5
|8|6|5|5|7|6|5|6|5|6|7|6|8|6|6|6|8|6|7|6|4|5|19|5|8|7|6|4|7|5|6|6|5|7|8|6|6|7|5|5|7|6|9|7|
6|
MH|OPR|10|CURFACT|0|CURVAL|0|TIME|1109703031|MAX|60|NUM|60|12|0|1|0|0|0|0|4|0|2|2|0|0|0|0|
1|1|0|0|0|0|0|0|0|0|0|0|0|0|0|0|1|0|0|0|0|0|0|0|1|28|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|
|
MH|IERR|10|CURFACT|0|CURVAL|0|TIME|1109703031|MAX|60|NUM|60|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|
0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|0|

```

The following is sample output from the **show asdm history** command using the **snapshot** keyword:

```
Available 4 byte Blocks: [ 10s] : 100
Used 4 byte Blocks: [ 10s] : 0
Available 80 byte Blocks: [ 10s] : 100
Used 80 byte Blocks: [ 10s] : 0
Available 256 byte Blocks: [ 10s] : 2100
Used 256 byte Blocks: [ 10s] : 0
Available 1550 byte Blocks: [ 10s] : 7425
Used 1550 byte Blocks: [ 10s] : 1279
Available 2560 byte Blocks: [ 10s] : 40
Used 2560 byte Blocks: [ 10s] : 0
Available 4096 byte Blocks: [ 10s] : 30
Used 4096 byte Blocks: [ 10s] : 0
Available 8192 byte Blocks: [ 10s] : 60
```

```

Used 8192 byte Blocks: [ 10s] : 0
Available 16384 byte Blocks: [ 10s] : 100
Used 16384 byte Blocks: [ 10s] : 0
Available 65536 byte Blocks: [ 10s] : 10
Used 65536 byte Blocks: [ 10s] : 0
CPU Utilization: [ 10s] : 31
Input KByte Count: [ 10s] : 62930
Output KByte Count: [ 10s] : 26620
Input KPacket Count: [ 10s] : 755
Output KPacket Count: [ 10s] : 58
Input Bit Rate: [ 10s] : 24561
Output Bit Rate: [ 10s] : 518897
Input Packet Rate: [ 10s] : 48
Output Packet Rate: [ 10s] : 114
Input Error Packet Count: [ 10s] : 0
No Buffer: [ 10s] : 0
Received Broadcasts: [ 10s] : 377331
Runts: [ 10s] : 0
Giants: [ 10s] : 0
CRC: [ 10s] : 0
Frames: [ 10s] : 0
Overruns: [ 10s] : 0
Underruns: [ 10s] : 0
Output Error Packet Count: [ 10s] : 0
Collisions: [ 10s] : 0
LCOLL: [ 10s] : 0
Reset: [ 10s] : 0
Deferred: [ 10s] : 0
Lost Carrier: [ 10s] : 0
Hardware Input Queue: [ 10s] : 128
Software Input Queue: [ 10s] : 0
Hardware Output Queue: [ 10s] : 0
Software Output Queue: [ 10s] : 0
Drop KPacket Count: [ 10s] : 0
Input KByte Count: [ 10s] : 3672
Output KByte Count: [ 10s] : 4051
Input KPacket Count: [ 10s] : 19
Output KPacket Count: [ 10s] : 20
Input Bit Rate: [ 10s] : 0
Output Bit Rate: [ 10s] : 0
Input Packet Rate: [ 10s] : 0
Output Packet Rate: [ 10s] : 0
Input Error Packet Count: [ 10s] : 0
No Buffer: [ 10s] : 0
Received Broadcasts: [ 10s] : 1458
Runts: [ 10s] : 1
Giants: [ 10s] : 0
CRC: [ 10s] : 0
Frames: [ 10s] : 0
Overruns: [ 10s] : 0
Underruns: [ 10s] : 0
Output Error Packet Count: [ 10s] : 0
Collisions: [ 10s] : 63
LCOLL: [ 10s] : 0
Reset: [ 10s] : 0
Deferred: [ 10s] : 15
Lost Carrier: [ 10s] : 0
Hardware Input Queue: [ 10s] : 128
Software Input Queue: [ 10s] : 0
Hardware Output Queue: [ 10s] : 0
Software Output Queue: [ 10s] : 0
Drop KPacket Count: [ 10s] : 0
Input KByte Count: [ 10s] : 0
Output KByte Count: [ 10s] : 0

```



```
Input KPacket Count: [ 10s] : 0
Output KPacket Count: [ 10s] : 0
Input Bit Rate: [ 10s] : 0
Output Bit Rate: [ 10s] : 0
Input Packet Rate: [ 10s] : 0
Output Packet Rate: [ 10s] : 0
Input Error Packet Count: [ 10s] : 0
No Buffer: [ 10s] : 0
Received Broadcasts: [ 10s] : 0
Runts: [ 10s] : 0
Giants: [ 10s] : 0
CRC: [ 10s] : 0
Frames: [ 10s] : 0
Overruns: [ 10s] : 0
Underruns: [ 10s] : 0
Output Error Packet Count: [ 10s] : 0
Collisions: [ 10s] : 0
LCOLL: [ 10s] : 0
Reset: [ 10s] : 0
Deferred: [ 10s] : 0
Lost Carrier: [ 10s] : 0
Hardware Input Queue: [ 10s] : 128
Software Input Queue: [ 10s] : 0
Hardware Output Queue: [ 10s] : 0
Software Output Queue: [ 10s] : 0
Drop KPacket Count: [ 10s] : 0
Input KByte Count: [ 10s] : 0
Output KByte Count: [ 10s] : 0
Input KPacket Count: [ 10s] : 0
Output KPacket Count: [ 10s] : 0
Input Bit Rate: [ 10s] : 0
Output Bit Rate: [ 10s] : 0
Input Packet Rate: [ 10s] : 0
Output Packet Rate: [ 10s] : 0
Input Error Packet Count: [ 10s] : 0
No Buffer: [ 10s] : 0
Received Broadcasts: [ 10s] : 0
Runts: [ 10s] : 0
Giants: [ 10s] : 0
CRC: [ 10s] : 0
Frames: [ 10s] : 0
Overruns: [ 10s] : 0
Underruns: [ 10s] : 0
Output Error Packet Count: [ 10s] : 0
Collisions: [ 10s] : 0
LCOLL: [ 10s] : 0
Reset: [ 10s] : 0
Deferred: [ 10s] : 0
Lost Carrier: [ 10s] : 0
Hardware Input Queue: [ 10s] : 128
Software Input Queue: [ 10s] : 0
Hardware Output Queue: [ 10s] : 0
Software Output Queue: [ 10s] : 0
Drop KPacket Count: [ 10s] : 0
Available Memory: [ 10s] : 205149944
Used Memory: [ 10s] : 63285512
Xlate Count: [ 10s] : 0
Connection Count: [ 10s] : 0
TCP Connection Count: [ 10s] : 0
UDP Connection Count: [ 10s] : 0
URL Filtering Count: [ 10s] : 0
URL Server Filtering Count: [ 10s] : 0
TCP Fixup Count: [ 10s] : 0
TCP Intercept Count: [ 10s] : 0
```

show asdm history

```

HTTP Fixup Count:  [ 10s] : 0
FTP Fixup Count:   [ 10s] : 0
AAA Authentication Count: [ 10s] : 0
AAA Authorization Count: [ 10s] : 0
AAA Accounting Count:  [ 10s] : 0
Current Xlates:    [ 10s] : 0
Max Xlates:        [ 10s] : 0
ISAKMP SAs:        [ 10s] : 0
IPSec SAs:         [ 10s] : 0
L2TP Sessions:     [ 10s] : 0
L2TP Tunnels:      [ 10s] : 0
hostname#

```

Related Commands

Command	Description
asdm history enable	Enables ASDM history tracking.

show asdm image

To the current ASDM software image file, use the show **asdm image** command in privileged EXEC mode.

show asdm image

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Release	Modification
7.0	This command was changed from the show pdm image command to the show asdm image command.

Examples The following is sample output from the **show asdm image** command:

```
hostname# show asdm image

Device Manager image file, flash:/ASDM
```

Command	Description
asdm image	Specifies the current ASDM image file.

show asdm log_sessions

To display a list of active ASDM logging sessions and their associated session IDs, use the **show asdm log_sessions** command in privileged EXEC mode.

show asdm log_sessions

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	This command was introduced.

Usage Guidelines Each active ASDM session has one or more associated ASDM logging sessions. ASDM uses the logging session to retrieve syslog messages from the security appliance. Each ASDM logging session is assigned a unique session ID. You can use this session ID with the **asdm disconnect log_session** command to terminate the specified session.



Note

Because each ASDM session has at least one ASDM logging session, the output for the **show asdm sessions** and **show asdm log_sessions** may appear to be the same.

Examples The following is sample output from the **show asdm log_sessions** command:

```
hostname# show asdm log_sessions

0 192.168.1.1
1 192.168.1.2
```

Related Commands	Command	Description
	asdm disconnect log_session	Terminates an active ASDM logging session.

show asdm sessions

To display a list of active ASDM sessions and their associated session IDs, use the **show asdm sessions** command in privileged EXEC mode.

show asdm sessions

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was changed from the show pdm sessions command to the show asdm sessions command.

Usage Guidelines Each active ASDM session is assigned a unique session ID. You can use this session ID with the **asdm disconnect** command to terminate the specified session.

Examples The following is sample output from the **show asdm sessions** command:

```
hostname# show asdm sessions

0 192.168.1.1
1 192.168.1.2
```

Related Commands	Command	Description
	asdm disconnect	Terminates an active ASDM session.

show asp drop

To debug the accelerated security path dropped packets or connections, use the **show asp drop** command in privileged EXEC mode.

```
show asp drop [flow [flow_drop_reason] | frame [frame_drop_reason]]
```

Syntax Description

flow [flow_drop_reason]	(Optional) Shows the dropped flows (connections). You can specify a particular reason by using the <i>flow_drop_reason</i> argument. Valid values for the <i>flow_drop_reason</i> argument are listed in the “Usage Guidelines” section, below.
frame [frame_drop_reason]	(Optional) Shows the dropped packets. You can specify a particular reason by using the <i>frame_drop_reason</i> argument. Valid values for the <i>frame_drop_reason</i> argument are listed in the “Usage Guidelines” section, below.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0(1)	This command was introduced.
7.0(8)	Added a timestamp indicating when the counters were last cleared (see the clear asp drop command). It also displays the drop reason keywords next to the description, so you can easily use the capture asp-drop command with that keyword.

Usage Guidelines

The **show asp drop** command shows the packets or connections dropped by the accelerated security path, which might help you troubleshoot a problem. See the *Cisco Security Appliance Command Line Configuration Guide* for more information about the accelerated security path. This information is used for debugging purposes only, and the information output is subject to change. Consult Cisco TAC to help you debug your system with this command.

Table 7-3 lists valid values for the *flow_drop_reason* argument for dropped flows. Table 7-4 lists valid values for the *frame_drop_reason* argument for dropped frames.

Table 7-3 Flow Drop Reasons

Flow Drop Reason Keyword	Flow Drop Reason Display	Description
acl-drop	Flow is denied by access rule	This counter is incremented when a packet is denied by the security appliance, and flow creation is denied. The deny rule could be a default rule created when the security appliance comes up, when various features are turned on or off, when an access list is applied to an interface, or any other feature. Apart from default rule drops, a flow could be denied because of: • An access list configured on an interface • An access list configured for AAA, and AAA denied the user • Through traffic arriving at a management-only interface • Unencrypted traffic arriving on a IPSec-enabled interface • Implicit deny at the end of an access list Recommendation: Observe if one of system messages related to packet drop display. Flow drop results in the corresponding packet drop that would trigger the requisite system message. System messages: None.
audit-failure	Audit failure	A flow was freed after matching an ip audit signature that had reset as the associated action. Recommendation: If removing the flow is not the desired outcome of matching this signature, then remove the reset action from the ip audit command. System messages: None.
closed-by-inspection	Flow closed by inspection	This reason is given for closing a flow due to an error detected during application inspection. For example, if an error is detected during inspecting an H323 message, the corresponding H323 flow is closed with this reason. Recommendation: None. System messages: None.
conn-limit-exceeded	Connection limit exceeded	This reason is given for closing a flow when the connection limit has been exceeded. The connection limit is configured using the set connection conn-max command. Recommendation: None. System messages: 201011

Table 7-3 Flow Drop Reasons (continued)

Flow Drop Reason Keyword	Flow Drop Reason Display	Description
fin-timeout	FIN Timeout	This reason is given for closing a TCP flow due to expiry of half-closed timer. Recommendation: If these are valid sessions which take longer to close a TCP flow, increase the half-closed timeout. System messages: 302014
flow-reclaimed	Non-tcp/udp flow reclaimed for new request	This counter is incremented when a reclaimable flow is removed to make room for a new flow. This occurs only when the number of flows through the security appliance equals the maximum number permitted by the software imposed limit, and a new flow request is received. When this occurs, if the number of reclaimable flows exceeds the number of VPN tunnels permitted by the security appliance, then the oldest reclaimable flow is removed to make room for the new flow. All flows except the following are deemed to be reclaimable: • TCP, UDP, GRE and failover flows • ICMP flows if ICMP stateful inspection is enabled • ESP flows to the security appliance Recommendation: No action is required if this counter is incrementing slowly. If this counter is incrementing rapidly, it could mean that the security appliance is under attack and the security appliance is spending more time reclaiming and rebuilding flows. System messages: 302021
fo-primary-closed	Failover primary closed	The standby unit received a flow delete message from the active unit and terminated the flow. Recommendation: If the security appliance is running stateful failover, then this counter should increment for every replicated connection that is torn down on the standby appliance. System messages: 302014, 302016, 302018
fo-standby	Flow closed by failover standby	If a through-the-box packet arrives at the security appliance or a context that is in a standby state, then a flow is created, the packet is dropped, and the flow removed. This counter will increment each time a flow is removed in this manner. Recommendation: This counter should never be incrementing on the active security appliance or context. However, it is normal to see it increment on the standby security appliance or context. System messages: 302014, 302016, 302018

Table 7-3 Flow Drop Reasons (continued)

Flow Drop Reason Keyword	Flow Drop Reason Display	Description
fo_rep_err	Standby flow replication error	The standby unit failed to replicate a flow. Recommendation: If the security appliance is processing VPN traffic, then this counter could be constantly increasing on the standby unit because the flow could be replicated before the IKE SA information. No action is required in this case. If the appliance is not processing VPN traffic, then this indicates a software defect; turn on the debug fover fail command on the standby unit, collect the debug output, and report the problem to Cisco TAC. System messages: 302014, 302016, 302018
host-removed	Host is removed	The flow was removed in response to the clear local-host command. Recommendation: This is an information counter. System messages: 302014, 302016, 302018, 302021, 305010, 305012, 609002
inspect-fail	Inspection failure	This counter will increment when the security appliance fails to enable protocol inspection carried out by the NP for the connection. Currently, ICMP and DNS inspections are carried out by the NP. The cause could be memory allocation failure, or for ICMP error message, the security appliance not being able to find any established connection related to the frame embedded in the ICMP error message. Recommendation: Check system memory usage. For the ICMP error message, if the cause is an attack, you can deny the host using the access lists. System messages: 313005 for ICMP error.
ips-fail-close	IPS fail-close	This reason is given for terminating a flow because the AIP SSM is down and the fail-close option was used with IPS inspection. Recommendation: Check and bring up the AIP SSM. System messages: 420001
ips-request	Flow terminated by IPS	This reason is given for terminating a flow as requested by the AIP SSM. Recommendation: Check system messages and alerts on the AIP SSM. System messages: 420002

Table 7-3 Flow Drop Reasons (continued)

Flow Drop Reason Keyword	Flow Drop Reason Display	Description
ipsec-spoof-detect	IPsec spoof packet detected	This counter will increment when the security appliance receives a packet that should have been encrypted but was not. The packet matched the inner header security policy check of a configured and established IPsec connection on the security appliance but was received unencrypted. This is a security issue. Recommendation: Analyze your network traffic to determine the source of the spoofed IPsec traffic. System messages: 402117
loopback	Flow is a loopback	This reason is given for closing a flow due to the following conditions: - U-turn traffic is present on the flow. same-security-traffic permit intra-interface is not configured. Recommendation: To allow U-turn traffic on an interface, configure the interface with the same-security-traffic permit intra-interface command. System messages: None.
mcast-entry-removed	Multicast entry removed	This reason is given for one of the following cases: - A packet has arrived that matches a multicast flow, but the multicast service is no longer enabled, or was re-enabled after the flow was built. Recommendation: Reenable multicast if it is disabled. System messages: None. - The multicast entry has been deleted so the flow is being cleaned up, but the packet will be reinjected into the data path. Recommendation: None. System messages: None.
mcast-intrf-removed	Multicast interface removed	This reason is given for one of the following cases: - An output interface has been removed from the multicast entry. Recommendation: None. System messages: None. - All output interfaces have been removed from the multicast entry. Recommendation: Verify that there are no longer any receivers for this group. System messages: None.

Table 7-3 Flow Drop Reasons (continued)

Flow Drop Reason Keyword	Flow Drop Reason Display	Description
nat-failed	NAT failed	Failed to create an xlate to translate an IP or transport header. Recommendation: If NAT is not desired, disable nat-control. Otherwise, use the static, nat, or global command to configure NAT policy for the dropped flow. For dynamic NAT, ensure that each nat command is paired with at least one global command. Use show running-config nat and debug pix process to verify NAT rules. System messages: 305005, 305006, 305009, 305010, 305011, 305012
nat-rpf-failed	NAT reverse path failed	Rejected attempt to connect to a mapped host using the mapped host's real address. Recommendation: When not on the same interface as the host undergoing NAT, use the mapped address instead of the real address to connect to the host. Also, enable the appropriate inspect command if the application embeds the IP address. System messages: 305005
need-ike	Need to start IKE negotiation	This counter will increment when the security appliance receives a packet that requires encryption but has no established IPsec security association. This is generally a normal condition for LAN-to-LAN IPsec configurations. This indication will cause the security appliance to begin ISAKMP negotiations with the destination peer. Recommendation: If you have configured IPsec LAN-to-LANs on your security appliance, this indication is normal and does not indicate a problem. However, if this counter increments rapidly, it may indicate a crypto configuration error or network error preventing the ISAKMP negotiation from completing. Verify that you can communicate with the destination peer and verify your crypto configuration using the show running-config command. System messages: None.
no-ipv6-ipsec	IPsec over IPv6 unsupported	This counter will increment when the security appliance receives an IPsec ESP packet, IPsec NAT-T ESP packet, or an IPsec over UDP ESP packet encapsulated in an IPv6 header. The security appliance does not currently support any IPsec sessions encapsulated in IPv6. Recommendation: None. System messages: None.

Table 7-3 *Flow Drop Reasons (continued)*

Flow Drop Reason Keyword	Flow Drop Reason Display	Description
non_tcp_syn	non-syn TCP	This reason is given for terminating a TCP flow when the first packet is not a SYN packet. Recommendation: None. System messages: None.
out-of-memory	No memory to complete flow	This counter is incremented when the security appliance is unable to create a flow because of insufficient memory. Recommendation: Verify that the security appliance is not under attack by checking the current connections. Also verify if the configured timeout values are too large resulting in idle flows residing in memory longer. Check the free memory available by issuing the show memory command. If free memory is low, issue the show processes memory command to determine which processes are utilizing most of the memory. System messages: None.
parent-closed	Parent flow is closed	When the parent flow of a subordinating flow is closed, the subordinating flow is also closed. For example, an FTP data flow (subordinating flow) will be closed with this specific reason when its control flow (parent flow) is terminated. This reason is also given when a secondary flow (pin-hole) is closed by its controlling application. For example, when the BYE message is received, the SIP inspection engine (controlling application) will close the corresponding SIP RTP flows (secondary flow). Recommendation: None. System messages: None.
pinhole-timeout	Pinhole timeout	This counter is incremented to report that the security appliance opened a secondary flow, but no packets passed through this flow within the timeout interval, and hence it was removed. An example of a secondary flow is the FTP data channel that is created after successful negotiation on the FTP control channel. Recommendation: None. System messages: 302014, 302016
recurse	Close recursive flow	A flow was recursively freed. This reason applies to pair flows and multicast slave flows, and serves to prevent system messages being issued for each of these subordinate flows. Recommendation: None. System messages: None.

Table 7-3 Flow Drop Reasons (continued)

Flow Drop Reason Keyword	Flow Drop Reason Display	Description
reinject-punt	Flow terminated by punt action	This counter is incremented when a packet is punted to the exception path for processing by one of the enhanced services such as inspection or AAA. The servicing routine, having detected a violation in the traffic flowing on the flow, requests that the flow be dropped. The flow is immediately dropped. Recommendation: Please watch for system messages triggered by a servicing routine. Flow drop terminates the corresponding connection. System messages: None.
reset-by-ips	Flow reset by IPS	This reason is given for terminating a TCP flow as requested by the AIP SSM. Recommendation: Check system messages and alerts on the AIP SSM. System messages: 420003
reset-in	TCP Reset-I	This reason is given for closing an outbound flow (from a low-security interface to a same- or high-security interface) when a TCP reset is received on the flow. Recommendation: None. System messages: 302014
reset-out	TCP Reset-O	This reason is given for closing an inbound flow (from a high-security interface to low-security interface) when a TCP reset is received on the flow. Recommendation: None. System messages: 302014
shunned	Flow shunned	This counter will increment when a packet is received that has a source IP address that matches a host in the shun database. When a shun command is applied, it will be incremented for each existing flow that matches the shun command. Recommendation: None. System messages: 401004
syn-timeout	SYN Timeout	This reason is given for closing a TCP flow due to expiry of embryonic timer. Recommendation: If these are valid sessions that take longer to establish a connection, then increase the embryonic timeout. System messages: 302014
tcp-fins	TCP FINs	This reason is given for closing a TCP flow when TCP FIN packets are received. Recommendation: This counter will increment for each TCP connection that is terminated normally with FINs. System messages: 302014

Table 7-3 Flow Drop Reasons (continued)

Flow Drop Reason Keyword	Flow Drop Reason Display	Description
tcp-intercept-no-response	TCP intercept server no respond	SYN retransmission timeout after trying three times, once every second. Server unreachable, tearing down connection. Recommendation: Check if the server is reachable from the security appliance. System messages: None.
tcp-intercept-kill	Flow terminated by TCP Intercept	TCP intercept tore down the connection for the following reasons: 1. This is the first SYN 2. A connection is created for the SYN 3. TCP intercept replied with a SYN cookie; or TCP intercept sends a SYN to the server and the server replies with a RST after seeing a valid ACK from the client. Recommendation: TCP intercept normally does not create a connection for the first SYN, except when there are nailed rules, the packet comes over a VPN tunnel, or the next hop gateway address to reach the client is not resolved. So for the first SYN, this indicates that a connection was created. When TCP intercept receives a RST from server, it is likely that the corresponding port is closed on the server. System messages: None.
tcp-intercept-unexpected	TCP intercept unexpected state	Logic error in the TCP intercept module; this should never happen. Recommendation: Indicates memory corruption or some other logic error in the TCP intercept module. System messages: None.
tcpnorm-invalid-syn	TCP invalid SYN	This reason is given for closing a TCP flow when the SYN packet is invalid. Recommendation: The SYN packet could be invalid for a number of reasons, such as an invalid checksum or an invalid TCP header. Please use the packet capture feature to understand why the SYN packet is invalid. If you would like to allow these connections, use the tcp-map configuration to bypass checks. System messages: 302014
tcpnorm-rexmit-bad	TCP bad retransmission	This reason is given for closing a TCP flow when the check-retransmission feature is enabled, and the TCP endpoint sent a retransmission with different data from the original packet. Recommendation: The TCP endpoint may be attacking by sending different data in TCP retransmits. Please use the packet capture feature to learn more about the origin of the packet. System messages: 302014

Table 7-3 Flow Drop Reasons (continued)

Flow Drop Reason Keyword	Flow Drop Reason Display	Description
tcpnorm-win-variation	TCP unexpected window size variation	This reason is given for closing a TCP flow when the window size advertised by the TCP endpoint is drastically changed without accepting that much data. Recommendation: In order to allow this connection, use the window-variation command. System messages: 302014
timeout	Conn-timeout	This counter is incremented when a flow is closed because of the expiration of its inactivity timer. Recommendation: None. System messages: 302014, 302016, 302018, 302021
tunnel-pending	Tunnel being brought up or torn down	This counter will increment when the security appliance receives a packet matching an entry in the security policy database (i.e. crypto map) but the security association is in the process of being negotiated; its not complete yet. This counter will also increment when the security appliance receives a packet matching an entry in the security policy database but the security association has been or is in the process of being deleted. The difference between this indication and the “Tunnel has been torn down” indication is that the “Tunnel has been torn down” indication is for established flows. Recommendation: This is a normal condition when the IPSec tunnel is in the process of being negotiated or deleted. System messages: None.
tunnel-torn-down	Tunnel has been torn down	This counter will increment when the security appliance receives a packet associated with an established flow whose IPSec security association is in the process of being deleted. Recommendation: This is a normal condition when the IPSec tunnel is torn down for any reason. System messages: None
xlate-removed	Xlate Clear	The flow was removed in response to the clear xlate command or clear local-host command. Recommendation: This is an information counter. System messages: 302014, 302016, 302018, 302021, 305010, 305012, 609002

Table 7-4 lists valid values for the *frame_drop_reason* argument for dropped frames.

Table 7-4 **Frame Drop Reasons**

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
acl-drop	Flow is denied by access rule	This counter is incremented when a packet is denied by the security appliance. The deny rule could be a default rule created when the security appliance comes up, when various features are turned on or off, when an access list is applied to an interface, or any other feature. Apart from default rule drops, a flow could be denied because of: • An access list configured on an interface • An access list configured for AAA, and AAA denied the user • Through traffic arriving at a management-only interface • Unencrypted traffic arriving on a IPSec-enabled interface Recommendation: Check the access lists referenced by the following system log messages. System messages: 106023, 106100, 106004
bad-crypto	Bad crypto return in packet	This counter will increment when the security appliance attempts to perform a crypto operation on a packet, and the crypto operation fails. This is not a normal condition and could indicate possible software or hardware problems with the security appliance. Recommendation: If you are receiving many bad crypto indications, your security appliance may need servicing. You should enable system message 402123 to determine whether the crypto errors are hardware or software errors. You can also check the error counter in the global IPSec statistics with the show ipsec stats command. If the IPSec SA that is triggering these errors is known, the SA statistics from the show ipsec sa detail command will also be useful in diagnosing the problem. System messages: 402123
bad-ipsec-natt	Bad IPSEC NATT packet	This counter will increment when the security appliance receives a packet on an IPSec connection that has negotiated NAT-T, but the packet is not addressed to the NAT-T UDP destination port of 4500 or had an invalid payload length. Recommendation: Analyze your network traffic to determine the source of the NAT-T traffic. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
bad-ipsec-prot	IPSEC not AH or ESP	This counter will increment when the security appliance receives a packet on an IPsec connection that is not an AH or ESP protocol packet. This is not a normal condition. Recommendation: If you are receiving many IPsec not AH or ESP indications on your security appliance, analyze your network traffic to determine the source of the traffic. System messages: 402115
bad-ipsec-udp	Bad IPSEC UDP packet	This counter will increment when the security appliance receives a packet on an IPsec connection that has negotiated IPsec over UDP, but the packet has an invalid payload length. Recommendation: Analyze your network traffic to determine the source of the NAT-T traffic. System messages: None.
bad-tcp-cksum	Bad TCP checksum	This counter is incremented and the packet is dropped when the security appliance receives a TCP packet whose computed TCP checksum does not match the recorded checksum in TCP header. Recommendation: The packet corruption may be caused by a bad cable or noise on the line. It may also be that a TCP endpoint is sending corrupted packets, and an attack is in progress. Please use the packet capture feature to learn more about the origin of the packet. To allow packets with an incorrect TCP checksum, disable the checksum-verification feature. System messages: None
bad-tcp-flags	Bad TCP flags	This counter is incremented and the packet is dropped when the security appliance receives a TCP packet with invalid TCP flags in the TCP header. For example, a packet with both SYN and FIN TCP flags set will be dropped. Recommendation: The packet corruption may be caused by a bad cable or noise on the line. It may also be that a TCP endpoint is sending corrupted packets and an attack is in progress. Please use the packet capture feature to learn more about the origin of the packet. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
conn-limit	Connection limit reached	This reason is given for dropping a packet when the connection limit or host connection limit has been exceeded. If this is a TCP packet which is dropped during TCP connection establishment phase due to connection limit, the drop reason “TCP connection limit reached” is also reported. Recommendation: If this is incrementing rapidly, check the system messages to determine which host's connection limit is reached. The connection limit may need to be increased if the traffic is normal, or the host may be under attack. System messages: 201011
ctm-error	CTM returned error	This counter will increment when the security appliance attempts to perform a crypto operation on a packet and the crypto operation fails. This is not a normal condition and could indicate possible software or hardware problems with the security appliance. Recommendation: If you are receiving many bad crypto indications, your security appliance may need servicing. You should enable system message 402123 to determine whether the crypto errors are hardware or software errors. You can also check the error counter in the global IPSec statistics with the show ipsec stats command. If the IPSec SA that is triggering these errors is known, the SA statistics from the show ipsec sa detail command will also be useful in diagnosing the problem. System messages: 402123
dns-guard-id-not-matched	DNS Guard id not matched	This counter will increment when the identification of the DNS response message does not match any DNS queries that passed across the appliance earlier on the same connection. This counter will increment by the DNS Guard function. Recommendation: No action required if it is an intermittent event. If the cause is an attack, you can deny the host using the access lists. System messages: None.
dns-guard-out-of-app-id	DNS Guard out of app id	This counter will increment when the DNS Guard function fails to allocate a data structure to store the identification of the DNS message. Recommendation: Check the system memory usage. This event normally happens when the system runs short of memory. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
dst-l2_lookup-fail	Dst MAC L2 Lookup Failed	This counter will increment when the security appliance is configured for transparent mode, and the security appliance does a Layer 2 destination MAC address lookup that fails. Upon the lookup failure, the security appliance will begin the destination MAC discovery process and attempt to find the location of the host via ARP and/or ICMP messages. Recommendation: This is a normal condition when the security appliance is configured for transparent mode. You can also execute the show mac-address-table command to list the L2 MAC address locations currently discovered by the security appliance. System messages: None.
flow-expired	Expired flow	This counter is incremented when the security appliance tries to inject a new or cached packet belonging to a flow that has already expired. It is also incremented when the security appliance attempts to send an RST on a TCP flow that has already expired, or when a packet returns from the AIP SSM but the flow had already expired. The packet is dropped. Recommendation: If valid applications are getting preempted, investigate if a longer timeout is needed. System messages: None.
fo-standby	Dropped by standby unit	If a through-the-box packet arrives at security appliance or context in a standby state, and a flow is created, then the packet is dropped and the flow removed. This counter will increment each time a packet is dropped in this manner. Recommendation: This counter should never be incrementing on the active security appliance or context. However, it is normal to see it increment on the standby appliance or security appliance. System messages: 302014, 302016, 302018
fragment-reassembly-failed	Fragment reassembly failed	This counter is incremented when the security appliance fails to reassemble a chain of fragmented packets into a single packet. All the fragment packets in the chain are dropped. This is probably because of a failure while allocating memory for the reassembled packet. Recommendation: Use the show blocks command to monitor the current block memory. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
host-move-pkt	FP host move packet	This counter will increment when the security appliance or context is configured for transparent mode, and the source interface of a known Layer 2 MAC address is detected on a different interface. Recommendation: This indicates that a host has been moved from one interface (i.e. LAN segment) to another. This condition is normal while in transparent mode if the host has in fact been moved. However, if the host move toggles back and forth between interfaces, a network loop may be present. System messages: 412001, 412002, 322001
ifc-classify	Virtual firewall classification failed	A packet arrived on a shared interface, but failed to classify to any specific context interface. Recommendation: Use the global or static command to specify the IPv4 addresses that belong to each context interface. System messages: None.
inspect-dns-id-not-matched	DNS Inspect id not matched	This counter will increment when the identification of the DNS response message does not match any DNS queries that passed across the security appliance earlier on the same connection. Recommendation: No action required if it is an intermittent event. If the cause is an attack, you can deny the host using the access lists. System messages: None.
inspect-dns-invalid-domain-label	DNS Inspect invalid domain label	This counter will increment when the security appliance detects an invalid DNS domain name or label. DNS domain name and label is checked per RFC 1035. Recommendation: None. System messages: None.
inspect-dns-invalid-pak	DNS Inspect invalid packet	This counter will increment when the security appliance detects an invalid DNS packet. For example, a DNS packet with no DNS header, the number of DNS resource records not matching the counter in the header, etc. Recommendation: None. System messages: None.
inspect-dns-out-of-app-id	DNS Inspect out of app id	This counter will increment when the DNS inspection engine fails to allocate a data structure to store the identification of the DNS message. Recommendation: Check the system memory usage. This event normally happens when the system runs short of memory. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
inspect-dns-pak-too-long	DNS Inspect packet too long	This counter is incremented when the length of the DNS message exceeds the configured maximum allowed value. Recommendation: No action required. If DNS message length checking is not desired, enable DNS inspection without the inspect dns maximum-length option. System messages: 410001
inspect-icmp-error-different-embedded-conn	ICMP Error Inspect different embedded conn	This counter will increment when the frame embedded in the ICMP error message does not match the established connection that has been identified when the ICMP connection is created. Recommendation: No action required if it is an intermittent event. If the cause is an attack, you can deny the host using the access lists. System messages: 313005
inspect-icmp-error-no-existing-conn	ICMP Error Inspect no existing conn	This counter will increment when the security appliance is not able to find any established connection related to the frame embedded in the ICMP error message. Recommendation: No action required if it is an intermittent event. If the cause is an attack, you can deny the host using the access lists. System messages: 313005
inspect-icmp-out-of-app-id	ICMP Inspect out of app id	This counter will increment when the ICMP inspection engine fails to allocate an App ID data structure. The structure is used to store the sequence number of the ICMP packet. Recommendation: Check the system memory usage. This event normally happens when the system runs short of memory. System messages: None.
inspect-icmp-seq-num-not-matched	ICMP Inspect seq num not matched	This counter will increment when the sequence number in the ICMP echo reply message does not match any ICMP echo message that passed across the security appliance earlier on the same connection. Recommendation: No action required if it is an intermittent event. If the cause is an attack, you can deny the host using the access lists. System messages: 313004

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
inspect-icmpv6-error-invalid-pak	ICMPv6 Error Inspect invalid packet	This counter will increment when the security appliance detects an invalid frame embedded in the ICMPv6 packet. This check is the same as that on IPv6 packets. For example, an incomplete IPv6 header, a malformed IPv6 Next Header, etc. Recommendation: None. System messages: None.
inspect-icmpv6-error-no-existing-conn	ICMPv6 Error Inspect no existing conn	This counter will increment when the security appliance is not able to find any established connection related to the frame embedded in the ICMPv6 error message. Recommendation: No action required if it is an intermittent event. If the cause is an attack, you can deny the host using the access lists. System messages: 313005
intercept-unexpected	Intercept unexpected packet	The security appliance either received data from a client while waiting for a SYNACK from a server, or it received a packet that cannot be handled in a particular state of TCP intercept. Recommendation: If this drop is causing the connection to fail, please have a sniffer trace of the client- and server-side of the connection while reporting the issue. The security appliance could be under attack, and the sniffer traces or capture would help narrow down the culprit. System messages: None.
interface-down	Interface is down	This counter will increment for each packet received on an interface that is shutdown using the shutdown command. For ingress traffic, the packet is dropped after security context classification and if the interface associated with the context is shut down. For egress traffic, the packet is dropped when the egress interface is shut down. Recommendation: None. System messages: None.
invalid-app-length	Invalid app length	This counter will increment when the security appliance detects an invalid length of the Layer 7 payload in the packet. Currently, it counts the drops by the DNS Guard function only. For example, an incomplete DNS header. Recommendation: None. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
invalid-encap	Invalid encapsulation	This counter is incremented when the security appliance receives a frame belonging to an unsupported link-level protocol or if the L3 type specified in the frame is not supported by the security appliance. The packet is dropped. Recommendation: Verify that directly-connected hosts have proper link-level protocol settings. System messages: None.
invalid-ethertype	Invalid ethertype	This counter is incremented when the fragmentation module on the security appliance receives or tries to send a fragmented packet that does not belong to IP version 4 or version 6. The packet is dropped. Recommendation: Verify the MTU of the security appliance and other devices on the connected network to determine why the security appliance is processing such fragments. System messages: None.
invalid-ip-header	Invalid IP header	This counter is incremented and the packet is dropped when the security appliance receives an IP packet whose computed checksum of the IP header does not match the recorded checksum in the header. Recommendation: The packet corruption may be caused by a bad cable or noise on the line. It may also be that a peer is sending corrupted packets and an attack is in progress. Please use the packet capture feature to learn more about the origin of the packet. System messages: None
invalid-ip-length	Invalid IP length	This counter is incremented when the security appliance receives an IPv4 or IPv6 packet in which the header length or total length fields in the IP header are not valid or do not conform to the received packet length. Recommendation: None. System messages: None.
invalid-ip-option	IP option configured drop	This counter is incremented when any unicast packet with IP options or a multicast packet with IP options that have not been configured to be accepted, is received by the security appliance. The packet is dropped. Recommendation: Investigate why a packet with IP options is being sent by the sender. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
invalid-tcp-hdr-length	Invalid tcp length	This counter is incremented when the security appliance receives a TCP packet whose size is smaller than the minimum-allowed header length or does not conform to the received packet length. Recommendation: The invalid packet could be a bogus packet being sent by an attacker. Investigate the traffic from the source in the following system message. System messages: 500003.
invalid-udp-length	Invalid udp length	This counter is incremented when the security appliance receives a UDP packet whose size as calculated from the fields in the header is different from the measured size of the packet as received from the network. Recommendation: The invalid packet could be a bogus packet being sent by an attacker. System messages: None.
ips-fail-close	IPS card is down	This counter is incremented and the packet is dropped when the AIP SSM is down and the fail-close option was used in IPS inspection. Recommendation: Check and bring up the AIP SSM. System messages: 420001
ips-request	IPS Module requested drop	This counter is incremented and the packet is dropped as requested by the AIP SSM when the packet matches a signature on the IPS engine. Recommendation: Check system messages and alerts on the AIP SSM. System messages: 420002
ipsec-clearpkt-notun	IPSEC Clear Pkt w/no tunnel	This counter will increment when the security appliance receives a packet that should have been encrypted but was not. The packet matched the inner header security policy check of a configured and established IPsec connection on the security appliance but was received unencrypted. This is a security issue. Recommendation: Analyze your network traffic to determine the source of the spoofed IPsec traffic. System messages: 402117
ipsec-ipv6	IPSEC via IPV6	This counter will increment when the security appliance receives an IPsec ESP packet, IPsec NAT-T ESP packet, or an IPsec over UDP ESP packet encapsulated in an IPv6 header. The security appliance does not currently support any IPsec sessions encapsulated in IPv6. Recommendation: None. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
ipsec-need-sa	IPSEC SA Not negotiated yet	This counter will increment when the security appliance receives a packet that requires encryption but has no established IPsec security association. This is generally a normal condition for LAN-to-LAN IPsec configurations. This indication will cause the security appliance to begin ISAKMP negotiations with the destination peer. Recommendation: If you have configured IPsec LAN-to-LAN on your security appliance, this indication is normal and does not indicate a problem. However, if this counter increments rapidly it may indicate a crypto configuration error or network error preventing the ISAKMP negotiation from completing. Verify that you can communicate with the destination peer and verify your crypto configuration using the show running-config command. System messages: None.
ipsec-spoof	IPSEC Spoof detected	This counter will increment when the security appliance receives a packet which should have been encrypted but was not. The packet matched the inner header security policy check of a configured and established IPsec connection on the security appliance but was received unencrypted. This is a security issue. Recommendation: Analyze your network traffic to determine the source of the spoofed IPsec traffic. System messages: 402117
ipsec-tun-down	IPSEC tunnel is down	This counter will increment when the security appliance receives a packet associated with an IPsec connection which is in the process of being deleted. Recommendation: This is a normal condition when the IPsec tunnel is torn down for any reason. System messages: None.

Table 7-4 *Frame Drop Reasons (continued)*

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
ipsecudp-keepalive	IPSEC/UDP keepalive message	This counter will increment when the security appliance receives an IPsec over UDP keepalive message. IPsec over UDP keepalive messages are sent from the IPsec peer to the security appliance to keep NAT/PAT flow information current in network devices between the IPsec over UDP peer and the security appliance. Note These are not industry-standard NAT-T keepalive messages that are also carried over UDP and addressed to UDP port 4500. Recommendation: If you have configured IPsec over UDP on your security appliance, this indication is normal and does not indicate a problem. If IPsec over UDP is not configured on your security appliance, analyze your network traffic to determine the source of the IPsec over UDP traffic. System messages: None.
ipv6_sp-security-failed	IPv6 slowpath security checks failed	This counter is incremented and the packet is dropped for one of the following reasons: • An IPv6 through-the-box packet has the identical source and destination address. • An IPv6 through-the-box packet has a linklocal source or destination address. • An IPv6 through-the-box packet has a multicast destination address. Recommendation: These packets could indicate malicious activity, or could be the result of a misconfigured IPv6 host. Use the packet capture feature to capture type asp packets, and use the source MAC address to identify the source. System messages: For identical source and destination address, system message 106016.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
l2_acl	FP L2 rule drop	This counter increments when the security appliance denies a packet due to an EtherType access list. The transparent mode security appliance permits the following traffic by default: - IPv4 traffic is allowed through the transparent firewall automatically from a higher security interface to a lower security interface, without an access list. Note For Layer 3 traffic travelling from a low to a high security interface, an extended access list is required on the low security interface. - ARPs are allowed through the transparent firewall in both directions without an access list. ARP traffic can be controlled by ARP inspection. In routed mode, some types of traffic cannot pass through the security appliance even if you allow it in an access list. The transparent firewall, however, can allow almost any traffic through using either an extended access list (for IP traffic) or an EtherType access list (for non-IP traffic). Note The transparent mode security appliance does not pass CDP packets or IPv6 packets, or any packets that do not have a valid EtherType greater than or equal to 0x600. For example, you cannot pass IS-IS packets. An exception is made for BPDUs, which are supported. Packets permitted by EtherType access lists might still be dropped by an extended access list. The EtherType access list only supports EtherTypes and not Layer 2 destination MAC addresses. The following destination MAC addresses are allowed through the transparent firewall. Any MAC address not on this list is dropped. - TRUE broadcast destination MAC address equal to FFFF.FFFF.FFFF - IPv4 multicast MAC addresses from 0100.5E00.0000 to 0100.5EFE.FFFF - BPDU multicast address equal to 0100.0CCC.CCCD - Appletalk multicast MAC addresses from 0900.0700.0000 to 0900.07FF.FFFF Recommendation: If your non-IP packets are dropped by the security appliance, you can configure an EtherType access list to permit the Layer 2 traffic. System log messages: 106026, 106027

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
l2_same-lan-port	L2 Src/Dst same LAN port	This counter will increment when the security appliance or context is configured for transparent mode, and the security appliance determines that the destination interface's L2 MAC address is the same as its ingress interface. Recommendation: This is a normal condition when the security appliance or context is configured for transparent mode. Since the security appliance interface is operating in promiscuous mode, the security appliance or context receives all packets on the local LAN segment. System messages: None.
loopback-buffer-full	Loopback buffer full	This counter is incremented and the packet is dropped when packets are sent from one context of the security appliance to another context through a shared interface, and there is no buffer space in the loopback queue. Recommendation: Check the system CPU to make sure it is not overloaded. System messages: None.
lu-invalid-pkt	Invalid LU packet	The standby unit received a corrupted Logical Update packet. Recommendation: The packet corruption could be caused by a bad cable, interface card, line noise, or software defect. If the interface appears to be functioning properly, then report the problem to Cisco TAC. System messages: None.
natt-keepalive	NAT-T keepalive message	This counter will increment when the security appliance receives an IPsec NAT-T keepalive message. NAT-T keepalive messages are sent from the IPsec peer to the security appliance to keep NAT/PAT flow information current in network devices between the NAT-T IPsec peer and the security appliance. Recommendation: If you have configured IPsec NAT-T on your security appliance, this indication is normal and does not indicate a problem. If NAT-T is not configured on your security appliance, analyze your network traffic to determine the source of the NAT-T traffic. System messages: None
no-adjacency	No valid adjacency	This counter is incremented when the security appliance has tried to obtain an adjacency and could not obtain the MAC address for the next hop. The packet is dropped. Recommendation: Configure a capture for this drop reason and check if a host with the specified destination address exists on the connected network or is routable from the security appliance. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
no-mcast-entry	FP no mcast entry	This counter increments because of one of the following reasons: - A packet has arrived that matches a multicast flow, but the multicast service is no longer enabled, or was re-enabled after the flow was built. Recommendation: Reenable multicast if it is disabled. System messages: None. - A multicast entry change has been detected after a packet was punted to the CP, and the NP can no longer forward the packet since no entry is present. Recommendation: None. System messages: None.
no-mcast-intrf	FP no mcast output intrf	This counter increments because of one of the following reasons: - All output interfaces have been removed from the multicast entry. Recommendation: Verify that there are no longer any receivers for this group. System messages: None. - The multicast packet could not be forwarded. Recommendation: Verify that a flow exists for this packet. System messages: None.
no-route	No route to host	This counter is incremented when the security appliance tries to send a packet out of an interface and does not find a route for it in the routing table. Recommendation: Verify that a route exists for the destination address obtained from the generated system message. System messages: 110001
non-ip-pkt-in-routed-mode	Non-IP packet received in routed mode	This counter will increment when the security appliance receives a packet that is not an IPv4, IPv6, or ARP packet, and the security appliance or context is configured for routed mode. In normal operation such packets should be dropped. Recommendation: This indicates that a software error should be reported to the Cisco TAC. System messages: 106026, 106027

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
np-sp-invalid-spi	Invalid SPI	This counter increments when the security appliance receives an IPSec ESP packet addressed to the security appliance that specifies an SPI (security parameter index) not currently known by the security appliance. Recommendation: Occasional invalid SPI indications are common, especially during rekey processing. Many invalid SPI indications may suggest a problem or DoS attack. If you are experiencing a high rate of invalid SPI indications, analyze your network traffic to determine the source of the ESP traffic. System messages: 402114
punt-rate-limit	Punt rate limit exceeded	This counter will increment when the security appliance attempts to forward a Layer 2 packet to a rate-limited control point service routine, and the rate limit (per/second) is now being exceeded. Currently, the only Layer 2 packets destined for a control point service routine that are rate limited are ARP packets. The ARP packet rate limit is 500 ARPs per second per interface. Recommendation: Analyze your network traffic to determine the reason behind the high rate of ARP packets. System messages: 322002, 322003
queue-removed	Queued packet dropped	When the QoS configuration is changed or removed, the existing packets in the output queues awaiting transmission are dropped and this counter is incremented. Recommendation: Under normal conditions, this may be seen when the QoS configuration has been changed by the user. If this occurs when no changes to the QoS configuration were performed, please contact Cisco TAC. System messages: None.
rate-exceeded	QoS rate exceeded	This counter is incremented when rate-limiting (policing) is configured on an egress interface, and the egress traffic rate exceeds the burst rate configured. The counter is incremented for each packet dropped. Recommendation: Investigate and determine why the rate of traffic leaving the interface is higher than the configured rate. This may be normal, or could be an indication of virus or attempted attack. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
rpf-violated	Reverse-path verify failed	This counter is incremented when ip verify reverse-path is configured on an interface and the security appliance receives a packet for which the route lookup of the source IP did not yield the same interface as the one on which the packet was received. Recommendation: Trace the source of traffic based on the source IP printed in the system message below, and investigate why it is sending spoofed traffic. System messages: 106021
security-failed	Early security checks failed	This counter is incremented and the packet is dropped when the security appliance: • Receives an IPv4 multicast packet when the packet multicast MAC address does not match the packet multicast destination IP address • Receives an IPv6 or IPv4 teardrop fragment containing either small offset or fragment overlapping • Receives an IPv4 packet that matches an IP audit signature Recommendation: Contact the remote peer administrator or escalate this issue according to your security policy. For detailed description and system messages for IP audit attack checks please refer the ip audit signature command. System messages: 106020, 400xx in case of IP audit checks
send-ctm-error	Send to CTM returned error	This counter is obsolete in the security appliance and should never increment. Recommendation: None. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
sp-security-failed	Slowpath security checks failed	This counter is incremented and the packet is dropped when the security appliance: - Is in routed mode and receives a through-the-box: - L2 broadcast packet - IPv4 packet with destination IP address equal to 0.0.0.0 - IPv4 packet with source IP address equal to 0.0.0.0 Recommendation: Determine if an external user is trying to compromise the protected network. Check for misconfigured clients. System messages: 106016 - Is in routed or transparent mode and receives a through-the-box IPv4 packet with: - The first octet of the source IP address is equal to zero - The source IP address is equal to the loopback IP address - Network part of the source IP address is equal to all 0s - The network part of the source IP address is equal to all 1s - The source IP address host part is equal to all 0s or all 1s Recommendation: Determine if an external user is trying to compromise the protected network. Check for misconfigured clients. System messages: 106016 - In routed or transparent mode and receives an IPv4 or IPv6 packet with the same source and destination IP addresses Recommendation: If this message counter is incrementing rapidly, an attack may be in progress. Use the packet capture feature to capture type asp packets, and check the source MAC address in the packet to see where they are coming from. System messages: 106017

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
tcp-3whs-failed	TCP failed 3 way handshake	This counter is incremented and the packet is dropped when security appliance receives an invalid TCP packet during the three-way handshake. For example, the SYN-ACK from a client will be dropped for this reason. Recommendation: None. System messages: None.
tcp-ack-syn-diff	TCP ACK in SYNACK invalid	This counter is incremented and the packet is dropped when the security appliance receives a SYN-ACK packet during the three-way handshake with an incorrect TCP acknowledgement number. Recommendation: None. System messages: None.
tcp-acked	TCP DUP and has been ACKed	This counter is incremented and the packet is dropped when the security appliance receives a retransmitted data packet and the data has been acknowledged by the peer TCP endpoint. Recommendation: None. System messages: None.
tcp-bad-option-len	Bad option length in TCP	This counter is incremented and the packet is dropped when the security appliance receives a TCP packet with a TCP option set, but the option length does not match the length defined for that option in the TCP RFC. Recommendation: The packet corruption may be caused by a bad cable or noise on the line. It may also be that a TCP endpoint is sending corrupted packets and an attack is in progress. Please use the packet capture feature to learn more about the origin of the packet. System messages: None.
tcp-bad-option-list	TCP option list invalid	This counter is incremented and the packet is dropped when the security appliance receives a TCP packet with a non-standard TCP header option. Recommendation: To allow such TCP packets or clear non-standard TCP header options and then allow the packet, use the tcp-options command. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
tcp-bad-sack-allow	Bad TCP SACK ALLOW option	This counter is incremented and the packet is dropped when the appliance receives a TCP packet with the selective acknowledgement option, but the SYN flag is not set. Recommendation: The packet corruption may be caused by a bad cable or noise on the line. It may also be that a TCP endpoint is sending corrupted packets and an attack is in progress. Please use the packet capture feature to learn more about the origin of the packet. System messages: None.
tcp-bad-winscale	Bad TCP window scale value	This counter is incremented and the packet is dropped when the security appliance receives a TCP packet with the window-scale option greater than 14. Recommendation: The packet corruption may be caused by a bad cable or noise on the line. It may also be that a TCP endpoint is sending corrupted packets and an attack is in progress. Please use the packet capture feature to learn more about the origin of the packet. System messages: None.
tcp-buffer-full	TCP packet buffer full	This counter is incremented and the packet is dropped when the security appliance receives an out-of-order TCP packet on a connection, and there is no buffer space to store this packet. Typically TCP packets are put into order on connections that are inspected by the security appliance or when packets are sent to an SSM for inspection. There is a default queue size, and when packets in excess of this default queue size are received they will be dropped. Recommendation: On ASA platforms the queue size could be increased using the queue-size command. System messages: None.
tcp-conn-limit	TCP Connection limit reached	This reason is given for dropping a TCP packet during the TCP connection establishment phase when the connection limit has been exceeded. The connection limit is configured using the set connection conn-max command. Recommendation: If this is incrementing rapidly, check the system messages to determine which host's connection limit is reached. The connection limit may need to be increased if the traffic is normal, or the host may be under attack. System messages: 201011
tcp-data-past-fin	TCP data send after FIN	This counter is incremented and the packet is dropped when the security appliance receives new a TCP data packet from an endpoint which had sent a FIN to close the connection. Recommendation: None. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
tcp-discarded-ooo	TCP ACK in 3 way handshake invalid	This counter is incremented and the packet is dropped when the security appliance receives a TCP ACK packet from a client during the three-way-handshake and the sequence number is not the next expected sequence number. Recommendation: None. System messages: None.
tcp-dual-open	TCP Dual open denied	This counter is incremented and the packet is dropped when the security appliance receives a TCP SYN packet from the server and an embryonic TCP connection is already open. Recommendation: None. System messages: None.
tcp-fo-drop	TCP replicated flow pak drop	This counter is incremented and the packet is dropped when the security appliance receives a TCP packet with a control flag like SYN, FIN, or RST on an established connection just after the security appliance has taken over as active unit. Recommendation: None. System messages: None.
tcp-invalid-ack	TCP invalid ACK	This counter is incremented and the packet is dropped when the security appliance receives a TCP packet with an acknowledgement number greater than the data sent by the peer TCP endpoint. Recommendation: None. System messages: None.
tcp-mss-exceeded	TCP data exceeded MSS	This counter is incremented and the packet is dropped when the security appliance receives a TCP packet with a data length greater than the MSS advertized by the peer TCP endpoint. Recommendation: To allow such TCP packets, use the exceed-mss command. System messages: 4419001
tcp-not-syn	First TCP packet not SYN	The security appliance received a non-SYN packet as the first packet of a non-intercepted and non-nailed connection. Recommendation: Under normal conditions, this may be seen when the security appliance has already closed a connection, and the client or server still believe the connection is open, and continue to transmit data. Some examples where this may occur is just after a clear local-host or clear xlate command is issued. Also, if connections have not been recently removed, and the counter is incrementing rapidly, the security appliance may be under attack. Capture a sniffer trace to help isolate the cause. System messages: 6106015

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
tcp-paws-fail	TCP packet failed PAWS test	This counter is incremented and the packet is dropped when a TCP packet with a timestamp header option fails the PAWS (Protect Against Wrapped Sequences) test. Recommendation: To allow such connections to proceed, use the tcp-options command to clear the timestamp option. System messages: None.
tcp-reserved-set	TCP reserved flags set	This counter is incremented and the packet is dropped when the security appliance receives a TCP packet with reserved flags set in TCP header. Recommendation: The packet corruption may be caused by a bad cable or noise on the line. It may also be that a TCP endpoint is sending corrupted packets and an attack is in progress. Please use the packet capture feature to learn more about the origin of the packet. To allow such TCP packets or clear reserved flags and then pass the packet, use the reserved-bits command. System messages: None
tcp-rst-syn-in-win	TCP RST/SYN in window	This counter is incremented and the packet is dropped when the security appliance receives a TCP SYN or TCP RST packet on an established connection with a sequence number within the window, but not as the next expected sequence number. Recommendation: None. System messages: None.
tcp-rstfin-ooo	TCP RST/FIN out of order	This counter is incremented and the packet is dropped when the security appliance receives a RST or a FIN packet with the incorrect TCP sequence number. Recommendation: None. System messages: None.
tcp-seq-past-win	TCP packet SEQ past window	This counter is incremented and the packet is dropped when the security appliance receives a TCP data packet with a sequence number beyond the window allowed by the peer TCP endpoint. Recommendation: None. System messages: None.
tcp-seq-syn-diff	TCP SEQ in SYN/SYNACK invalid	This counter is incremented and the packet is dropped when the security appliance receives a SYN or SYN-ACK packet during the three-way handshake with an incorrect TCP sequence number. Recommendation: None. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
tcp-syn-data	TCP SYN with data	This counter is incremented and the packet is dropped when the security appliance receives a TCP SYN packet with data. Recommendation: To allow such TCP packets use the syn-data command. System messages: None.
tcp-syn-ooo	TCP SYN on established conn	This counter is incremented and the packet is dropped when the security appliance receives a TCP SYN packet on an established TCP connection. Recommendation: None. System messages: None.
tcp-synack-data	TCP SYNACK with data	This counter is incremented and the packet is dropped when the security appliance receives a TCP SYN-ACK packet with data. Recommendation: The packet corruption may be caused by a bad cable or noise on the line. It may also be that a TCP endpoint is sending corrupted packets and an attack is in progress. Please use the packet capture feature to learn more about the origin of the packet. System messages: None.
tcp-synack-ooo	TCP SYNACK on established conn	This counter is incremented and the packet is dropped when the security appliance receives a TCP SYN-ACK packet on an established TCP connection. Recommendation: None. System messages: None.
tcp-winscale-no-syn	TCP Window scale on non-SYN	This counter is incremented and the packet is dropped when the security appliance receives a TCP packet with the window-scale TCP option without SYN flag set. Recommendation: The packet corruption may be caused by a bad cable or noise on the line. It may also be that a TCP endpoint is sending corrupted packets and an attack is in progress. Please use the packet capture feature to learn more about the origin of the packet. System messages: None.
tcp_xmit_partial	TCP retransmission partial	This counter is incremented and the packet is dropped when the check-retransmission feature is enabled, and a partial TCP retransmission was received. Recommendation: None. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
tcpnorm-rexmit-bad	TCP bad retransmission	This counter is incremented and the packet is dropped when the check-retransmission feature is enabled, and a TCP retransmission with different data from the original packet was received. Recommendation: None. System messages: None.
tcpnorm-win-variation	TCP unexpected window size variation	This counter is incremented and the packet is dropped when the window size advertised by the TCP endpoint is drastically changed without accepting that much data. Recommendation: To allow such packet, use the window-variation command. System messages: None.
tfw-no-mgmt-ip-config	No management IP address configured for TFW	This counter is incremented when the security appliance receives an IP packet in transparent mode and has no management IP address defined. The packet is dropped. Recommendation: Configure the security appliance with a management IP address and mask values. System messages: 322004
unable-to-add-flow	Flow hash full	This counter is incremented when a newly created flow is inserted into the flow hash table, and the insertion failed because the hash table was full. The flow and the packet are dropped. This is different from the counter that increments when the maximum connection limit is reached. Recommendation: This message signifies a lack of resources on the security appliance to support an operation that should have been successful. Please check if the connections in the show conn output have exceeded their configured idle timeout values. If so, contact Cisco TAC. System messages: None.

Table 7-4 Frame Drop Reasons (continued)

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
unable-to-create-flow	Flow denied due to resource limitation	This counter is incremented and the packet is dropped when flow creation fails due to a system resource limitation. The resource limit may be either: • System memory • Packet block extension memory • System connection limit The first two causes occur simultaneously with flow drop reason “No memory to complete flow.” Recommendation: • Observe if free system memory is low. • Observe if flow drop reason “No memory to complete flow” occurs. • Observe if the connection count reaches the system connection limit using the show resource usage command. System messages: None.
unexpected-packet	Unexpected packet	This counter is incremented when the security appliance in transparent mode receives a non-IP packet destined to its MAC address, but there is no corresponding service running on the security appliance to process the packet. Recommendation: Verify if the security appliance is under attack. If there are no suspicious packets, or the security appliance is not in transparent mode, this counter is most likely being incremented due to a software error. Attempt to capture the traffic that is causing the counter to increment and contact the Cisco TAC. System messages: None.

Table 7-4 **Frame Drop Reasons (continued)**

Frame Drop Reason Keyword	Frame Drop Reason Display	Description
unsupported-ipv6-hdr	Unsupported IPV6 header	This counter is incremented and the packet is dropped if an IPv6 packet is received with an unsupported IPv6 extension header. The supported IPv6 extension headers are: TCP, UDP, ICMPv6, ESP, AH, Hop Options, Destination Options, and Fragment. The IPv6 routing extension header is not supported, and any extension header not listed above is not supported. IPv6 ESP and AH headers are supported only if the packet is through-the-box. To-the-box IPv6 ESP and AH packets are not supported and will be dropped. Recommendation: This error may be due to a misconfigured host. If this error occurs repeatedly or in large numbers, it could also indicate spurious or malicious activity such as an attempted DoS attack. System messages: None.
unsupported-ip-version	Unsupported IP version	This counter is incremented when the security appliance receives an IP packet that has an unsupported version in the version field of the IP header. Specifically, if the packet does not belong to version 4 or version 6, the packet is dropped. Recommendation: Verify that other devices on the connected network are configured to send IP packets belonging to versions 4 or 6 only. System messages: None.

Examples

The following is sample output from the **show asp drop** command, with the timestamp indicating when the last time the counters were cleared:

```
hostname# show asp drop
```

```
Frame drop:
```

```
Flow is denied by configured rule (acl-drop)          3
Dst MAC L2 Lookup Failed (dst-l2_lookup-fail)       4110
L2 Src/Dst same LAN port (l2_same-lan-port)         760
Expired flow (flow-expired)                          1
```

```
Last clearing: Never
```

```
Flow drop:
```

```
Flow is denied by access rule (acl-drop)            24
NAT failed (nat-failed)                             28739
NAT reverse path failed (nat-rpf-failed)            22266
Inspection failure (inspect-fail)                   19433
```

```
Last clearing: 17:02:12 UTC Jan 17 2008 by enable_15
```

Related Commands

Command	Description
clear asp drop	Clears drop statistics for the accelerated security path.
show conn	Shows information about connections.

show asp table arp

To debug the accelerated security path ARP tables, use the **show asp table arp** command in privileged EXEC mode.

show asp table arp [**interface** *interface_name*] [**address** *ip_address* [**netmask** *mask*]]

Syntax Description

address <i>ip_address</i>	(Optional) Identifies an IP address for which you want to view ARP table entries.
interface <i>interface_name</i>	(Optional) Identifies a specific interface for which you want to view the ARP table.
netmask <i>mask</i>	(Optional) Sets the subnet mask for the IP address.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **show arp** command shows the contents of the control plane, while the **show asp table arp** command shows the contents of the accelerated security path, which might help you troubleshoot a problem. See the *Cisco Security Appliance Command Line Configuration Guide* for more information about the accelerated security path. These tables are used for debugging purposes only, and the information output is subject to change. Consult Cisco TAC to help you debug your system with this command.

Examples

The following is sample output from the **show asp table arp** command:

```
hostname# show asp table arp
```

```
Context: single_vf, Interface: inside
```

10.86.194.50	Active	000f.66ce.5d46	hits 0
10.86.194.1	Active	00b0.64ea.91a2	hits 638
10.86.194.172	Active	0001.03cf.9e79	hits 0
10.86.194.204	Active	000f.66ce.5d3c	hits 0
10.86.194.188	Active	000f.904b.80d7	hits 0

```
Context: single_vf, Interface: identity
```

```
:: Active 0000.0000.0000 hits 0
0.0.0.0 Active 0000.0000.0000 hits 50208
```

Related Commands

Command	Description
show arp	Shows the ARP table.
show arp statistics	Shows ARP statistics.

show asp table classify

To debug the accelerated security path classifier tables, use the **show asp table classify** command in privileged EXEC mode. The classifier examines properties of incoming packets, such as protocol, and source and destination address, to match each packet to an appropriate classification rule. Each rule is labeled with a classification domain that determines what types of actions are performed, such as dropping a packet or allowing it through.

show asp table classify [**hit** | **crypto** | **domain** *domain_name* | **interface** *interface_name*]

Syntax Description

crypto	(Optional) Shows the encrypt, decrypt, and ipsec tunnel flow domains only.
domain <i>domain_name</i>	(Optional) Shows entries for a specific classifier domain. See “ Usage Guidelines ” for a list of domains.
hits	(Optional) Shows classifier entries which have non-zero hits values
interface <i>interface_name</i>	(Optional) Identifies a specific interface for which you want to view the classifier table.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.
7.2(4)	Added the hits option, and the timestamp indicating when the last time the asp table counters were cleared.

Usage Guidelines

The **show asp table classifier** command shows the classifier contents of the accelerated security path, which might help you troubleshoot a problem. See the *Cisco Security Appliance Command Line Configuration Guide* for more information about the accelerated security path. These tables are used for debugging purposes only, and the information output is subject to change. Consult Cisco TAC to help you debug your system with this command.

Classifier domains include the following:

```
aaa-acct
aaa-auth
aaa-user
accounting
arp
```

```
capture
capture
conn-nailed
conn-set
ctcp
decrypt
encrypt
established
filter-activex
filter-ftp
filter-https
filter-java
filter-url
host
ids
inspect
inspect-ctiqbe
inspect-dns
inspect-dns-ids
inspect-ftp
inspect-ftp-data
inspect-gtp
inspect-h323
inspect-http
inspect-icmp
inspect-icmp-error
inspect-ils
inspect-mgcp
inspect-netbios
inspect-pptp
inspect-rsh
inspect-rtsp
inspect-sip
inspect-skinny
inspect-smtp
inspect-snmp
inspect-sqlnet
inspect-sqlnet-plus
inspect-sunrpc
inspect-tftp
inspect-xdmcp
ipsec-natt
ipsec-tunnel-flow
ipsec-user
limits
lu
mac-permit
mgmt-lockdown
mgmt-tcp-intercept
multicast
nat
nat-exempt
nat-exempt-reverse
nat-reverse
null
permit
permit-ip-option
permit-log
pim
ppp
priority-q
punt
punt-l2
punt-root
```

show asp table classify

```

qos
qos-per-class
qos-per-dest
qos-per-flow
qos-per-source
shun
tcp-intercept

```

Examples

The following is sample output from the **show asp table classify** command:

```

hostname# show asp table classify

Interface test:
in id=0x36f3800, priority=10, domain=punt, deny=false
    hits=0, user_data=0x0, flags=0x0
    src ip=0.0.0.0, mask=0.0.0.0, port=0
    dst ip=10.86.194.60, mask=255.255.255.255, port=0
in id=0x33d3508, priority=99, domain=inspect, deny=false
    hits=0, user_data=0x0, use_real_addr, flags=0x0
    src ip=0.0.0.0, mask=0.0.0.0, port=0
    dst ip=0.0.0.0, mask=0.0.0.0, port=0
in id=0x33d3978, priority=99, domain=inspect, deny=false
    hits=0, user_data=0x0, use_real_addr, flags=0x0
    src ip=0.0.0.0, mask=0.0.0.0, port=53
    dst ip=0.0.0.0, mask=0.0.0.0, port=0
...

```

The following is sample output from the **show asp table classify hits** command with a record of the last clearing hits counters:

```

Interface mgmt:
in id=0x494cd88, priority=210, domain=permit, deny=true
    hits=54, user_data=0x1, cs_id=0x0, reverse, flags=0x0, protocol=0 src ip=0.0.0.0,
    mask=0.0.0.0, port=0 dst ip=255.255.255.255, mask=255.255.255.255, port=0,
    dscp=0x0
in id=0x494d1b8, priority=112, domain=permit, deny=false
    hits=1, user_data=0x0, cs_id=0x0, reverse, flags=0x0, protocol=1 src ip=0.0.0.0,
    mask=0.0.0.0, port=0 dst ip=0.0.0.0, mask=0.0.0.0, port=0, dscp=0x0

Interface inside:
in id=0x48f1580, priority=210, domain=permit, deny=true
    hits=54, user_data=0x1, cs_id=0x0, reverse, flags=0x0, protocol=0 src ip=0.0.0.0,
    mask=0.0.0.0, port=0 dst ip=255.255.255.255, mask=255.255.255.255, port=0,
    dscp=0x0
in id=0x48f09e0, priority=1, domain=permit, deny=false
    hits=101, user_data=0x0, cs_id=0x0, l3_type=0x608 src mac=0000.0000.0000,
    mask=0000.0000.0000 dst mac=0000.0000.0000, mask=0000.0000.0000

Interface outside:
in id=0x48c0970, priority=210, domain=permit, deny=true
    hits=54, user_data=0x1, cs_id=0x0, reverse, flags=0x0, protocol=0 src ip=0.0.0.0,
    mask=0.0.0.0, port=0 dst ip=255.255.255.255, mask=255.255.255.255, port=0,
    dscp=0x0

```

Related Commands

Command	Description
show asp drop	Shows the accelerated security path counters for dropped packets.

show asp table interfaces

To debug the accelerated security path interface tables, use the **show asp table interfaces** command in privileged EXEC mode.

show asp table interfaces

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines The **show asp table interfaces** command shows the interface table contents of the accelerated security path, which might help you troubleshoot a problem. See the *Cisco Security Appliance Command Line Configuration Guide* for more information about the accelerated security path. These tables are used for debugging purposes only, and the information output is subject to change. Consult Cisco TAC to help you debug your system with this command.

Examples The following is sample output from the **show asp table interfaces** command:

```
hostname# show asp table interfaces

** Flags: 0x0001-DHCP, 0x0002-VMAC, 0x0010-Ident Ifc, 0x0020-HDB Initd,
0x0040-RPF Enabled
Soft-np interface 'dmz' is up
    context single_vf, nicnum 0, mtu 1500
    vlan 300, Not shared, seclvl 50
    0 packets input, 1 packets output
    flags 0x20

Soft-np interface 'foo' is down
    context single_vf, nicnum 2, mtu 1500
    vlan <None>, Not shared, seclvl 0
    0 packets input, 0 packets output
    flags 0x20
```

■ show asp table interfaces

```

Soft-np interface 'outside' is down
  context single_vf, nicnum 1, mtu 1500
    vlan <None>, Not shared, seclvl 50
    0 packets input, 0 packets output
    flags 0x20

Soft-np interface 'inside' is up
  context single_vf, nicnum 0, mtu 1500
    vlan <None>, Not shared, seclvl 100
    680277 packets input, 92501 packets output
    flags 0x20
...

```

Related Commands

Command	Description
interface	Configures an interface and enters interface configuration mode.
show interface	Displays the runtime status and statistics of interfaces.

show asp table routing

To debug the accelerated security path routing tables, use the **show asp table routing** command in privileged EXEC mode. This command supports IPv4 and IPv6 addresses.

show asp table routing [**input** | **output**] [**address** *ip_address* [**netmask** *mask*] |
interface *interface_name*]

Syntax Description

address <i>ip_address</i>	Sets the IP address for which you want to view routing entries. For IPv6 addresses, you can include the subnet mask as a slash (/) followed by the prefix (0 to 128). For example, enter the following: <i>fe80::2e0:b6ff:fe01:3b7a/128</i>
input	Shows the entries from the input route table.
interface <i>interface_name</i>	(Optional) Identifies a specific interface for which you want to view the routing table.
netmask <i>mask</i>	For IPv4 addresses, specifies the subnet mask.
output	Shows the entries from the output route table.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **show asp table routing** command shows the routing table contents of the accelerated security path, which might help you troubleshoot a problem. See the *Cisco Security Appliance Command Line Configuration Guide* for more information about the accelerated security path. These tables are used for debugging purposes only, and the information output is subject to change. Consult Cisco TAC to help you debug your system with this command.

Examples

The following is sample output from the **show asp table routing** command:

```
hostname# show asp table routing

in  255.255.255.255 255.255.255.255 identity
```

show asp table routing

```
in  224.0.0.9      255.255.255.255 identity
in  10.86.194.60   255.255.255.255 identity
in  10.86.195.255  255.255.255.255 identity
in  10.86.194.0    255.255.255.255 identity
in  209.165.202.159 255.255.255.255 identity
in  209.165.202.255 255.255.255.255 identity
in  209.165.201.30  255.255.255.255 identity
in  209.165.201.0   255.255.255.255 identity
in  10.86.194.0     255.255.254.0   inside
in  224.0.0.0       240.0.0.0       identity
in  0.0.0.0         0.0.0.0         inside
out  255.255.255.255 255.255.255.255 foo
out  224.0.0.0       240.0.0.0       foo
out  255.255.255.255 255.255.255.255 test
out  224.0.0.0       240.0.0.0       test
out  255.255.255.255 255.255.255.255 inside
out  10.86.194.0     255.255.254.0   inside
out  224.0.0.0       240.0.0.0       inside
out  0.0.0.0         0.0.0.0         via 10.86.194.1, inside
out  0.0.0.0         0.0.0.0         via 0.0.0.0, identity
out  ::              ::              via 0.0.0.0, identity
```

Related Commands	Command	Description
	show route	Shows the routing table in the control plane.

show asp table vpn-context

To debug the accelerated security path VPN context tables, use the **show asp table vpn-context** command in privileged EXEC mode.

show asp table vpn-context [detail]

Syntax Description	detail (Optional) Shows additional detail for the VPN context tables.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	The show asp table vpn-context command shows the VPN context contents of the accelerated security path, which might help you troubleshoot a problem. See the <i>Cisco Security Appliance Command Line Configuration Guide</i> for more information about the accelerated security path. These tables are used for debugging purposes only, and the information output is subject to change. Consult Cisco TAC to help you debug your system with this command.

Examples	The following is sample output from the show asp table vpn-context command:

```
hostname# show asp table vpn-context

VPN ID=0058070576, DECR+ESP, UP, pk=0000000000, rk=0000000000, gc=0
VPN ID=0058193920, ENCR+ESP, UP, pk=0000000000, rk=0000000000, gc=0
VPN ID=0058168568, DECR+ESP, UP, pk=0000299627, rk=0000000061, gc=2
VPN ID=0058161168, ENCR+ESP, UP, pk=0000305043, rk=0000000061, gc=1
VPN ID=0058153728, DECR+ESP, UP, pk=0000271432, rk=0000000061, gc=2
VPN ID=0058150440, ENCR+ESP, UP, pk=0000285328, rk=0000000061, gc=1
VPN ID=0058102088, DECR+ESP, UP, pk=0000268550, rk=0000000061, gc=2
VPN ID=0058134088, ENCR+ESP, UP, pk=0000274673, rk=0000000061, gc=1
VPN ID=0058103216, DECR+ESP, UP, pk=0000252854, rk=0000000061, gc=2
...
```

The following is sample output from the **show asp table vpn-context detail** command:

```
hostname# show asp table vpn-context detail
```

show asp table vpn-context

```
VPN Ctx  = 0058070576 [0x03761630]
State    = UP
Flags    = DECR+ESP
SA       = 0x037928F0
SPI      = 0xEA0F21F0
Group    = 0
Pkts     = 0
Bad Pkts = 0
Bad SPI  = 0
Spoof    = 0
Bad Crypto = 0
Rekey Pkt = 0
Rekey Call = 0

VPN Ctx  = 0058193920 [0x0377F800]
State    = UP
Flags    = ENCR+ESP
SA       = 0x037B4B70
SPI      = 0x900FDC32
Group    = 0
Pkts     = 0
Bad Pkts = 0
Bad SPI  = 0
Spoof    = 0
Bad Crypto = 0
Rekey Pkt = 0
Rekey Call = 0
...
```

Related Commands	Command	Description
	show asp drop	Shows the accelerated security path counters for dropped packets.

show blocks

To show the packet buffer utilization, use the **show blocks** command in privileged EXEC mode.

show blocks [{**address** *hex* | **all** | **assigned** | **free** | **old** | **pool size** [**summary**]} [**diagnostics** | **dump** | **header** | **packet**] | **queue history** [**detail**]]

Syntax Description

address <i>hex</i>	(Optional) Shows a block corresponding to this address, in hexadecimal.
all	(Optional) Shows all blocks.
assigned	(Optional) Shows blocks that are assigned and in use by an application.
detail	(Optional) Shows a portion (128 bytes) of the first block for each unique queue type.
dump	(Optional) Shows the entire block contents, including the header and packet information. The difference between dump and packet is that dump includes additional information between the header and the packet.
diagnostics	(Optional) Shows block diagnostics.
free	(Optional) Shows blocks that are available for use.
header	(Optional) Shows the header of the block.
old	(Optional) Shows blocks that were assigned more than a minute ago.
packet	(Optional) Shows the header of the block as well as the packet contents.
pool size	(Optional) Shows blocks of a specific size.
queue history	(Optional) Shows where blocks are assigned when the security appliance runs out of blocks. Sometimes, a block is allocated from the pool but never assigned to a queue. In that case, the location is the code address that allocated the block.
summary	(Optional) Shows detailed information about block usage sorted by the program addresses of applications that allocated blocks in this class, program addresses of applications that released blocks in this class, and the queues to which valid blocks in this class belong.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	The pool summary option was added.

Usage Guidelines

The **show blocks** command helps you determine if the security appliance is overloaded. This command lists preallocated system buffer utilization. A full memory condition is not a problem as long as traffic is moving through the security appliance. You can use the **show conn** command to see if traffic is moving. If traffic is not moving and the memory is full, there may be a problem.

You can also view this information using SNMP.

The information shown in a security context includes the system-wide information as well as context-specific information about the blocks in use and the high water mark for block usage.

See the “[Examples](#)” section for a description of the display output.

Examples

The following is sample output from the **show blocks** command in single mode:

```
hostname# show blocks
SIZE      MAX      LOW      CNT
    4      1600    1598    1599
   80       400     398     399
  256      3600    3540    3542
 1550      4716    3177    3184
16384        10        10        10
 2048      1000    1000    1000
```

[Table 7-5](#) shows each field description.

Table 7-5 *show blocks Fields*

Field	Description
SIZE	Size, in bytes, of the block pool. Each size represents a particular type. Examples are shown below.
4	Duplicates existing blocks in applications such as DNS, ISAKMP, URL filtering, uauth, TFTP, and TCP modules.
80	Used in TCP intercept to generate acknowledgment packets and for failover hello messages.
256	Used for Stateful Failover updates, syslogging, and other TCP functions. These blocks are mainly used for Stateful Failover messages. The active security appliance generates and sends packets to the standby security appliance to update the translation and connection table. In bursty traffic, where high rates of connections are created or torn down, the number of available blocks might drop to 0. This situation indicates that one or more connections were not updated to the standby security appliance. The Stateful Failover protocol catches the missing translation or connection the next time. If the CNT column for 256-byte blocks stays at or near 0 for extended periods of time, then the security appliance is having trouble keeping the translation and connection tables synchronized because of the number of connections per second that the security appliance is processing. Syslog messages sent out from the security appliance also use the 256-byte blocks, but they are generally not released in such quantity to cause a depletion of the 256-byte block pool. If the CNT column shows that the number of 256-byte blocks is near 0, ensure that you are not logging at Debugging (level 7) to the syslog server. This is indicated by the logging trap line in the security appliance configuration. We recommend that you set logging at Notification (level 5) or lower, unless you require additional information for debugging purposes.

Table 7-5 *show blocks Fields (continued)*

Field	Description
1550	Used to store Ethernet packets for processing through the security appliance. When a packet enters a security appliance interface, it is placed on the input interface queue, passed up to the operating system, and placed in a block. The security appliance determines whether the packet should be permitted or denied based on the security policy and processes the packet through to the output queue on the outbound interface. If the security appliance is having trouble keeping up with the traffic load, the number of available blocks will hover close to 0 (as shown in the CNT column of the command output). When the CNT column is zero, the security appliance attempts to allocate more blocks, up to a maximum of 8192. If no more blocks are available, the security appliance drops the packet.
16384	Only used for the 64-bit, 66-MHz Gigabit Ethernet cards (i82543). See the description for 1550 for more information about Ethernet packets.
2048	Control or guided frames used for control updates.
MAX	Maximum number of blocks available for the specified byte block pool. The maximum number of blocks are carved out of memory at bootup. Typically, the maximum number of blocks does not change. The exception is for the 256- and 1550-byte blocks, where the security appliance can dynamically create more when needed, up to a maximum of 8192.
LOW	Low-water mark. This number indicates the lowest number of this size blocks available since the security appliance was powered up, or since the last clearing of the blocks (with the clear blocks command). A zero in the LOW column indicates a previous event where memory was full.
CNT	Current number of blocks available for that specific size block pool. A zero in the CNT column means memory is full now.

The following is sample output from the **show blocks all** command:

```
hostname# show blocks all
Class 0, size 4
    Block    allocd_by    freed_by    data size    alloccnt    dup_cnt    oper location
0x01799940  0x00000000  0x00101603         0         0         0 alloc not_specified
0x01798e80  0x00000000  0x00101603         0         0         0 alloc not_specified
0x017983c0  0x00000000  0x00101603         0         0         0 alloc not_specified

...

    Found 1000 of 1000 blocks
    Displaying 1000 of 1000 blocks
```

Table 7-6 shows each field description.

Table 7-6 *show blocks all Fields*

Field	Description
Block	The block address.
allocd_by	The program address of the application that last used the block (0 if not used).
freed_by	The program address of the application that last released the block.
data size	The size of the application buffer/packet data that is inside the block.

Table 7-6 *show blocks all Fields*

Field	Description
allocnt	The number of times this block has been used since the block came into existence.
dup_cnt	The current number of references to this block if used: 0 means 1 reference, 1 means 2 references.
oper	One of the four operations that was last performed on the block: alloc, get, put, or free.
location	The application that uses the block, or the program address of the application that last allocated the block (same as the allocd_by field).

The following is sample output from the **show blocks** command in a context:

```
hostname/contexta# show blocks
  SIZE    MAX    LOW    CNT   INUSE   HIGH
    4    1600   1599   1599     0      0
   80     400    400    400     0      0
  256   3600   3538   3540     0      1
 1550   4616   3077   3085     0      0
```

The following is sample output from the **show blocks queue history** command:

```
hostname# show blocks queue history
Each Summary for User and Queue_type is followed its top 5 individual queues
Block Size: 4
Summary for User "http", Queue "tcp_unp_c_in", Blocks 1595, Queues 1396
Blk_cnt Q_cnt Last_Op Queue_Type      User      Context
    186     1 put      tcp_unp_c_in  http      contexta
    15     1 put      tcp_unp_c_in  http      contexta
    1     1 put      tcp_unp_c_in  http      contexta
    1     1 put      tcp_unp_c_in  http      contextb
    1     1 put      tcp_unp_c_in  http      contextc
Summary for User "aaa", Queue "tcp_unp_c_in", Blocks 220, Queues 200
Blk_cnt Q_cnt Last_Op Queue_Type      User      Context
    21     1 put      tcp_unp_c_in  aaa       contexta
    1     1 put      tcp_unp_c_in  aaa       contexta
    1     1 put      tcp_unp_c_in  aaa       contexta
    1     1 put      tcp_unp_c_in  aaa       contextb
    1     1 put      tcp_unp_c_in  aaa       contextc
Blk_cnt Q_cnt Last_Op Queue_Type      User      Context
   200     1 alloc    ip_rx        tcp       contexta
   108     1 get     ip_rx        udp       contexta
    85     1 free    fixup        h323_ras contextb
    42     1 put     fixup        skinny    contextb

Block Size: 1550
Summary for User "http", Queue "tcp_unp_c_in", Blocks 1595, Queues 1000
Blk_cnt Q_cnt Last_Op Queue_Type      User      Context
    186     1 put      tcp_unp_c_in  http      contexta
    15     1 put      tcp_unp_c_in  http      contexta
    1     1 put      tcp_unp_c_in  http      contexta
    1     1 put      tcp_unp_c_in  http      contextb
    1     1 put      tcp_unp_c_in  http      contextc
...
```

The following is sample output from the **show blocks queue history detail** command:

```
hostname# show blocks queue history detail
History buffer memory usage: 2136 bytes (default)
Each Summary for User and Queue type is followed its top 5 individual queues
Block Size: 4
```



```

Summary for User "http", Queue_Type "tcp_unp_c_in", Blocks 1595, Queues 1396
Blk_cnt Q_cnt Last_Op Queue_Type User Context
    186     1 put contexta
    15     1 put contexta
    1     1 put contexta
    1     1 put contextb
    1     1 put contextc

First Block information for Block at 0x....
dup_count 0, flags 0x8000000, alloc_pc 0x43ea2a,
start_addr 0xefb1074, read_addr 0xefb118c, write_addr 0xefb1193
urgent_addr 0xefb118c, end_addr 0xefb17b2
0efb1150: 00 00 00 03 47 c5 61 c5 00 05 9a 38 76 80 a3 00 | ....G.a....8v...
0efb1160: 00 0a 08 00 45 00 05 dc 9b c9 00 00 ff 06 f8 f3 | ....E.....
0efb1170: 0a 07 0d 01 0a 07 00 50 00 17 cb 3d c7 e5 60 62 | .....P...=...`b
0efb1180: 7e 73 55 82 50 18 10 00 45 ca 00 00 2d 2d 20 49 | ~sU.P...E...-- I
0efb1190: 50 20 2d 2d 0d 0a 31 30 2e 37 2e 31 33 2e 31 09 | P --..10.7.13.1.
0efb11a0: 3d 3d 3e 09 31 30 2e 37 2e 30 2e 38 30 0d 0a 0d | ==>.10.7.0.80...

Summary for User "aaa", Queue "tcp_unp_c_in", Blocks 220, Queues 200
Blk_cnt Q_cnt Last_Op Queue_Type User Context
    21     1 put contexta
    1     1 put contexta
    1     1 put contexta
    1     1 put contextb
    1     1 put contextc

First Block information for Block at 0x....
dup_count 0, flags 0x8000000, alloc_pc 0x43ea2a,
start_addr 0xefb1074, read_addr 0xefb118c, write_addr 0xefb1193
urgent_addr 0xefb118c, end_addr 0xefb17b2
0efb1150: 00 00 00 03 47 c5 61 c5 00 05 9a 38 76 80 a3 00 | ....G.a....8v...
0efb1160: 00 0a 08 00 45 00 05 dc 9b c9 00 00 ff 06 f8 f3 | ....E.....
0efb1170: 0a 07 0d 01 0a 07 00 50 00 17 cb 3d c7 e5 60 62 | .....P...=...`b
0efb1180: 7e 73 55 82 50 18 10 00 45 ca 00 00 2d 2d 20 49 | ~sU.P...E...-- I
0efb1190: 50 20 2d 2d 0d 0a 31 30 2e 37 2e 31 33 2e 31 09 | P --..10.7.13.1.
0efb11a0: 3d 3d 3e 09 31 30 2e 37 2e 30 2e 38 30 0d 0a 0d | ==>.10.7.0.80...

...

total_count: total buffers in this class

```

The following is sample output from the **show blocks pool summary** command:

```

hostname# show blocks pool 1550 summary
Class 3, size 1550

=====
total_count=1531    miss_count=0
Alloc_pc    valid_cnt    invalid_cnt
0x3b0a18    00000256    00000000
0x01ad0760 0x01acfe00 0x01acf4a0 0x01aceb40 00000000 0x00000000
0x3a8f6b    00001275    00000012
0x05006aa0 0x05006140 0x050057e0 0x05004520 00000000
0x00000000

=====
total_count=9716    miss_count=0
Freed_pc    valid_cnt    invalid_cnt
0x9a81f3    00000104    00000007
0x05006140 0x05000380 0x04fffa20 0x04ffde00 00000000 0x00000000
0x9a0326    00000053    00000033
0x05006aa0 0x050057e0 0x05004e80 0x05003260 00000000 0x00000000
0x4605a2    00000005    00000000
0x04ff5ac0 0x01e8e2e0 0x01e2eac0 0x01e17d20 00000000 0x00000000
...
=====

```

show blocks

```

        total_count=1531    miss_count=0
Queue   valid_cnt          invalid_cnt
0x3b0a18    00000256        00000000   Invalid Bad qtype
           0x01ad0760 0x01acfe00 0x01acf4a0 0x01aceb40 00000000 0x00000000
0x3a8f6b    00001275        00000000   Invalid Bad qtype
           0x05006aa0 0x05006140 0x050057e0 0x05004520 00000000
0x00000000

=====
free_cnt=8185  fails=0  actual_free=8185  hash_miss=0
      03a8d3e0 03a8b7c0 03a7fc40 03a6ff20 03a6f5c0 03a6ec60 kao-f1#

```

Table 7-7 shows each field description.

Table 7-7 *show blocks pool summary Fields*

Field	Description
total_count	The number of blocks for a given class.
miss_count	The number of blocks not reported in the specified category due to technical reasons.
Freed_pc	The program addresses of applications that released blocks in this class.
Alloc_pc	The program addresses of applications that allocated blocks in this class.
Queue	The queues to which valid blocks in this class belong.
valid_cnt	The number of blocks that are currently allocated.
invalid_cnt	The number of blocks that are not currently allocated.
Invalid Bad qtype	Either this queue has been freed and the contents are invalid or this queue was never initialized.
Valid tcp_usr_conn_inp	The queue is valid.

Related Commands

Command	Description
blocks	Increases the memory assigned to block diagnostics
clear blocks	Clears the system buffer statistics.
show conn	Shows active connections.

show bootvar

To show the boot file and configuration properties, use the **show boot** command in privileged configuration mode.

show bootvar

Syntax Description

show bootvar The system boot properties.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged Mode	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The BOOT variable specifies a list of bootable images on various devices. The CONFIG_FILE variable specifies the configuration file used during system initialization. Set these variables with the **boot system** command, and **boot config** command, respectively.

Examples

The following example, the BOOT variable contains disk0:/f1_image, which is the image booted when the system reloads. The current value of BOOT is disk0:/f1_image; disk0:/f1_backupimage. This meansboot variable has been modified with the boot system command, but the running configuration has notbeen saved with the **write memory** command. When the running config is saved, the BOOT variable and current BOOT variable will both be disk0:/f1_image; disk0:/f1_backupimage. Assuming the running configuration is saved the boot loader will attempt to load the contents of the BOOT variable, starting with disk0:/f1image, but if that is not present or invalid, it will attempt to boot disk0:1/f1_backupimage.

The CONFIG_FILE variable points to the system startup configuration. In this example it is not set, so the startup configuration file is the default specified with the **boot config** command. The current CONFIG_FILE variable may be modified with the **boot config** command and saved with the **write memory** command.

```
hostname# show bootvar
BOOT variable = disk0:/f1_image
Current BOOT variable = disk0:/f1_image; disk0:/f1_backupimage
CONFIG_FILE variable =
Current CONFIG_FILE variable =
hostname#
```

 show bootvar**Related Commands**

Command	Description
boot	Specifies the configuration file or image file used at startup.

show capture

To display the capture configuration when no options are specified, use the **show capture** command.

show capture [*capture_name*] [**access-list** *access_list_name*] [**count** *number*] [**decode**] [**detail**] [**dump**] [**packet-number** *number*]

Syntax Description

<i>capture_name</i>	(Optional) Name of the packet capture.
access-list <i>access_list_name</i>	(Optional) Displays information for packets that are based on IP or higher fields for the specific access list identification.
count <i>number</i>	(Optional) Displays the number of packets specified data.
decode	This option is useful when a capture of type isakmp is applied to an interface. All isakmp data flowing through that interface will be captured after decryption and shown with more information after decoding the fields.
detail	(Optional) Displays additional protocol information for each packet.
dump	(Optional) Displays a hexadecimal dump of the packets that are transported over the data link transport.
packet-number <i>number</i>	Starts the display at the specified packet number.

Defaults

This command has no default settings.

Command Modes

Security Context Mode: single context mode and multiple context mode

Access Location: system and context command line

Command Mode: privileged mode

Firewall Mode: routed firewall mode and transparent firewall mode

Command History

Release	Modification
PIX Version 7.0	Support for this command was introduced on the security appliance.

Usage Guidelines

If you specify the *capture_name*, then the capture buffer contents for that capture are displayed.

The **dump** keyword does not display MAC information in the hexadecimal dump.

The decoded output of the packets depend on the protocol of the packet. In [Table 7-8](#), the bracketed output is displayed when you specify the **detail** keyword.

Table 7-8 Packet Capture Output Formats

Packet Type	Capture Output Format
802.1Q	<i>HH:MM:SS.ms</i> [ether-hdr] <i>VLAN-info</i> <i>encap-ether-packet</i>
ARP	<i>HH:MM:SS.ms</i> [ether-hdr] <i>arp-type</i> <i>arp-info</i>

Table 7-8 Packet Capture Output Formats (continued)

Packet Type	Capture Output Format
IP/ICMP	<i>HH:MM:SS.ms [ether-hdr] ip-source > ip-destination: icmp: icmp-type icmp-code [checksum-failure]</i>
IP/UDP	<i>HH:MM:SS.ms [ether-hdr] src-addr.src-port dest-addr.dst-port: [checksum-info] udp payload-len</i>
IP/TCP	<i>HH:MM:SS.ms [ether-hdr] src-addr.src-port dest-addr.dst-port: tcp-flags [header-check] [checksum-info] sequence-number ack-number tcp-window urgent-info tcp-options</i>
IP/Other	<i>HH:MM:SS.ms [ether-hdr] src-addr dest-addr: ip-protocol ip-length</i>
Other	<i>HH:MM:SS.ms ether-hdr: hex-dump</i>

Examples

This example shows how to display the capture configuration:

```
hostname(config)# show capture
capture arp ethernet-type arp interface outside
capture http access-list http packet-length 74 interface inside
```

This example shows how to display the packets that are captured by an ARP capture:

```
hostname(config)# show capture arp
2 packets captured
19:12:23.478429 arp who-has 171.69.38.89 tell 171.69.38.10
19:12:26.784294 arp who-has 171.69.38.89 tell 171.69.38.10
2 packets shown
```

Related Commands

Command	Description
capture	Enables packet capture capabilities for packet sniffing and network fault isolation.
clear capture	Clears the capture buffer.
copy capture	Copies a capture file to a server.

show chardrop

To display the count of characters dropped from the serial console, use the **show chardrop** command in privileged EXEC mode.

show chardrop

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
7.0	This command was introduced.

Examples The following is sample output from the **show chardrop** command:

```
hostname# show chardrop
Chars dropped pre-TxTimeouts: 0, post-TxTimeouts: 0
```

Command	Description
show running-config	Shows the current operating configuration.

show checkheaps

To show the checkheaps statistics, use the **show checkheaps** command in privileged EXEC mode. Checkheaps is a periodic process that verifies the sanity of the heap memory buffers (dynamic memory is allocated from the system heap memory region) and the integrity of the code region.

show checkheaps

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples The following is sample output from the **show checkheaps** command:

```
hostname# show checkheaps
```

```
Checkheaps stats from buffer validation runs
```

```
-----
Time elapsed since last run      : 42 secs
Duration of last run            : 0 millisecs
Number of buffers created        : 8082
Number of buffers allocated      : 7808
Number of buffers free           : 274
Total memory in use              : 43570344 bytes
Total memory in free buffers     : 87000 bytes
Total number of runs             : 310
```

Related Commands

Command	Description
checkheaps	Sets the checkheap verification intervals.

show checksum

To display the configuration checksum, use the **show checksum** command in privileged EXEC mode.

show checksum

Syntax Description This command has no arguments or keywords.

Defaults This command has no default settings.

Command Modes The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	•	•	•	

Command History	Release	Modification
	7.0	Support for this command was introduced on the security appliance.

Usage Guidelines The **show checksum** command allows you to display four groups of hexadecimal numbers that act as a digital summary of the configuration contents. This checksum is calculated only when you store the configuration in Flash memory.

If a dot (“.”) appears before the checksum in the **show config** or **show checksum** command output, the output indicates a normal configuration load or write mode indicator (when loading from or writing to the security appliance Flash partition). The “.” shows that the security appliance is preoccupied with the operation but is not “hung up.” This message is similar to a “system processing, please wait” message.

Examples This example shows how to display the configuration or the checksum:

```
hostname(config)# show checksum
Cryptochecksum: 1a2833c0 129ac70b 1a88df85 650dbb81
```

show chunkstat

To display the chunk statistics, use the **show chunkstat** command in privileged EXEC mode.

show chunkstat

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples This example shows how to display the chunk statistics:

```
hostname# show chunkstat
Global chunk statistics: created 181, destroyed 34, siblings created 94, siblings
destroyed 34

Per-chunk statistics: siblings created 0, siblings trimmed 0
Dump of chunk at 01edb4cc, name "Managed Chunk Queue Elements", data start @ 01edbd24, end
@ 01eddc54
next: 01eddc8c, next_sibling: 00000000, prev_sibling: 00000000
flags 00000001
maximum chunk elt's: 499, elt size: 16, index first free 498
# chunks in use: 1, HWM of total used: 1, alignment: 0
Per-chunk statistics: siblings created 0, siblings trimmed 0
Dump of chunk at 01eddc8c, name "Registry Function List", data start @ 01eddea4, end @
01ede348
next: 01ede37c, next_sibling: 00000000, prev_sibling: 00000000
flags 00000001
maximum chunk elt's: 99, elt size: 12, index first free 42
# chunks in use: 57, HWM of total used: 57, alignment: 0
```

Related Commands

Command	Description
show counters	Displays the protocol stack counters.
show cpu	Displays the CPU utilization information.

show clock

To view the time on the security appliance, use the **show clock** command in user EXEC mode.

show clock [detail]

Syntax Description	detail	(Optional) Indicates the clock source (NTP or user configuration) and the current summer-time setting (if any).

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Examples	The following is sample output from the show clock command:

```
hostname> show clock
12:35:45.205 EDT Tue Jul 27 2004
```

The following is sample output from the **show clock detail** command:

```
hostname> show clock detail
12:35:45.205 EDT Tue Jul 27 2004
Time source is user configuration
Summer time starts 02:00:00 EST Sun Apr 4 2004
Summer time ends 02:00:00 EDT Sun Oct 31 2004
```

Related Commands	Command	Description
	clock set	Manually sets the clock on the security appliance.
	clock summer-time	Sets the date range to show daylight saving time.
	clock timezone	Sets the time zone.
	ntp server	Identifies an NTP server.
	show ntp status	Shows the status of the NTP association.

show conn

To display the connection state for the designated connection type, use the **show conn** command in privileged EXEC mode. This command supports IPv4 and IPv6 addresses.

```
show conn [count | [all] [detail] [long] [state state_type] [protocol {tcp | udp}]
          [address src_ip[-src_ip] [netmask mask]] [port src_port[-src_port]]
          [address dest_ip[-dest_ip] [netmask mask]] [port dest_port[-dest_port]]]
```

Syntax Description

address	(Optional) Displays connections with the specified source or destination IP address.
all	(Optional) Displays connections that are to the device or from the device, in addition to through-traffic connections.
count	(Optional) Displays the number of active connections.
<i>dest_ip</i>	(Optional) Specifies the destination IP address (IPv4 or IPv6). To specify a range, separate the IP addresses with a dash (-), For example: 10.1.1.1-10.1.1.5
<i>dest_port</i>	(Optional) Specifies the destination port number. To specify a range, separate the port numbers with a dash (-), For example: 1000-2000
detail	(Optional) Displays connections in detail, including translation type and interface information.
long	(Optional) Displays connections in long format.
netmask mask	(Optional) Specifies a subnet mask for use with the given IP address.
port	(Optional) Displays connections with the specified source or destination port.
protocol {tcp udp}	(Optional) Specifies the connection protocol, tcp or udp .
<i>src_ip</i>	(Optional) Specifies the source IP address (IPv4 or IPv6). To specify a range, separate the IP addresses with a dash (-), For example: 10.1.1.1-10.1.1.5
<i>src_port</i>	(Optional) Specifies the source port number. To specify a range, separate the port numbers with a dash (-), For example: 1000-2000
state state_type	(Optional) Specifies the connection state type. See Table 7-9 for a list of the keywords available for connection state types.

Defaults

All through connections are shown by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0(8)	The syntax was simplified to use source and destination concepts instead of “local” and “foreign.” In the new syntax, the source address is the first address entered and the destination is the second address. The old syntax used keywords like foreign and fport to determine the destination address and port.

Usage Guidelines

The **show conn** command displays the number of active TCP and UDP connections, and provides information about connections of various types. Use the **show conn all** command to see the entire table of connections.



Note

When the security appliance creates a pinhole to allow secondary connections, this is shown as an incomplete conn by the **show conn** command. To clear this incomplete conn use the **clear conn** command.

The connection types that you can specify using the **show conn state** command are defined in [Table 7-9](#). When specifying multiple connection types, use commas without spaces to separate the keywords.

Table 7-9 Connection State Types

Keyword	Connection Type Displayed
up	Connections in the up state.
conn_inbound	Inbound connections.
ctiqbe	CTIQBE connections
data_in	Inbound data connections.
data_out	Outbound data connections.
finin	FIN inbound connections.
finout	FIN outbound connections.
h225	H.225 connections
h323	H.323 connections
http_get	HTTP get connections.
mgcp	MGCP connections.
nojava	Connections that deny access to Java applets.
rpc	RPC connections.
sip	SIP connections.
skinny	SCCP connections.

Table 7-9 Connection State Types (continued)

Keyword	Connection Type Displayed
smtp_data	SMTP mail data connections.
sqlnet_fixup_data	SQL*Net data inspection engine connections.

When you use the **detail** option, the system displays information about the translation type and interface information using the connection flags defined in [Table 7-10](#).

Table 7-10 Connection Flags

Flag	Description
a	awaiting outside ACK to SYN
A	awaiting inside ACK to SYN
B	initial SYN from outside
C	Computer Telephony Interface Quick Buffer Encoding (CTIQBE) media connection
d	dump
D	DNS
E	outside back connection
f	inside FIN
F	outside FIN
g	Media Gateway Control Protocol (MGCP) connection
G	connection is part of a group ¹
h	H.225
H	H.323
i	incomplete TCP or UDP connection
I	inbound data
k	Skinny Client Control Protocol (SCCP) media connection
m	SIP media connection
M	SMTP data
O	outbound data
p	replicated (unused)
P	inside back connection
q	SQL*Net data
r	inside acknowledged FIN
R	outside acknowledged FIN for TCP connection
R	UDP RPC ²
s	awaiting outside SYN
S	awaiting inside SYN
t	SIP transient connection ³

Table 7-10 Connection Flags (continued)

Flag	Description
T	SIP connection ⁴
U	up

1. The G flag indicates the connection is part of a group. It is set by the GRE and FTP Strict fixups to designate the control connection and all its associated secondary connections. If the control connection terminates, then all associated secondary connections are also terminated.
2. Because each row of **show conn** command output represents one connection (TCP or UDP), there will be only one R flag per row.
3. For UDP connections, the value t indicates that it will timeout after one minute.
4. For UDP connections, the value T indicates that the connection will timeout according to the value specified using the **timeout sip** command.

**Note**

For connections using a DNS server, the source port of the connection may be replaced by the *IP address of DNS server* in the **show conn** command output.

A single connection is created for multiple DNS sessions, as long as they are between the same two hosts, and the sessions have the same 5-tuple (source/destination IP address, source/destination port, and protocol). DNS identification is tracked by *app_id*, and the idle timer for each *app_id* runs independently.

Because the *app_id* expires independently, a legitimate DNS response can only pass through the security appliance within a limited period of time and there is no resource build-up. However, when you enter the **show conn** command, you will see the idle timer of a DNS connection being reset by a new DNS session. This is due to the nature of the shared DNS connection and is by design.

**Note**

When there is no TCP traffic for the period of inactivity defined by the **timeout conn** command (by default, 1:00:00), the connection is closed and the corresponding conn flag entries are no longer displayed.

Examples

When specifying multiple connection types, use commas without spaces to separate the keywords. The following example displays information about RPC, H.323, and SIP connections in the Up state:

```
hostname# show conn state up,rpc,h323,sip
```

The following is sample output from the **show conn count** command:

```
ciscoasa(config)# show conn count
22 in use, 27775 most used
```

The following is sample output from the **show conn** command. This example shows a TCP session connection from inside host 10.1.1.15 to the outside Telnet server at 10.2.49.10. Because there is no B flag, the connection is initiated from the inside. The “U”, “I”, and “O” flags denote that the connection is active and has received inbound and outbound data.

```
hostname# show conn
22 in use, 27775 most used
TCP out 10.2.49.10:23 in 10.1.1.15:1026 idle 0:00:22 bytes 1774 flags UIO
UDP out 10.2.49.10:31649 in 10.1.1.15:1028 idle 0:00:14 bytes 0 flags D-
```

```
TCP out 10.30.2.2:1500 in 10.1.1.7:1000 idle 0:00:00 bytes 0 flags saA
TCP out 10.30.2.2:1500 in 10.1.1.14:1000 idle 0:00:00 bytes 0 flags saA
TCP out 10.30.2.2:1500 in 10.1.1.1:1000 idle 0:00:00 bytes 0 flags saA
TCP out 10.30.2.2:1500 in 10.1.1.3:1000 idle 0:00:00 bytes 0 flags saA
TCP out 10.30.2.2:80 in 10.30.1.1:45804 idle 0:01:26 bytes 7918 flags UFRIO
TCP out 10.30.2.2:80 in 10.30.1.1:45003 idle 0:02:17 bytes 7918 flags UFRIO
```

The following is sample output from the **show conn detail** command. This example shows many connections, including a UDP connection from outside host 192.168.49.10 to inside host 10.1.1.15. The D flag denotes that this is a DNS connection. The number 1028 is the DNS ID over the connection.

```
hostname# show conn detail
22 in use, 27775 most used
Flags: A - awaiting inside ACK to SYN, a - awaiting outside ACK to SYN,
      B - initial SYN from outside, C - CTIQBE media, D - DNS, d - dump,
      E - outside back connection, F - outside FIN, f - inside FIN,
      G - group, g - MGCP, H - H.323, h - H.225.0, I - inbound data,
      i - incomplete, J - GTP, j - GTP data, K - GTP t3-response
      k - Skinny media, M - SMTP data, m - SIP media, O - outbound data,
      P - inside back connection, q - SQL*Net data, R - outside acknowledged FI
N,
      R - UDP SUNRPC, r - inside acknowledged FIN, S - awaiting inside SYN,
      s - awaiting outside SYN, T - SIP, t - SIP transient, U - up
TCP outside:10.30.2.2/1500 inside:10.1.1.7/1000 flags saA
TCP outside:10.30.2.2/1500 inside:10.1.1.14/1000 flags saA
TCP outside:10.30.2.2/1500 inside:10.1.1.1/1000 flags saA
TCP outside:10.30.2.2/1500 inside:10.1.1.3/1000 flags saA
TCP outside:10.30.2.2/80 inside:10.30.1.1/45804 flags UFRIO
TCP outside:10.30.2.2/80 inside:10.30.1.1/45003 flags UFRIO
TCP outside:192.168.49.10/23 inside:10.1.1.15/1026 flags UIO
UDP outside:192.168.49.10/31649 inside:10.1.1.15/1028 flags dD
```

Related Commands

Commands	Description
clear conn	Clears connections.
inspect ctiqbe	Enables CTIQBE application inspection.
inspect h323	Enables H.323 application inspection.
inspect mgcp	Enables MGCP application inspection.
inspect sip	Removes java applets from HTTP traffic.
inspect skinny	Enables SCCP application inspection.

show console-output

To display the currently captured console output, use the **show console-output** command in privileged EXEC mode.

show console-output

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Examples The following example shows the message that displays when there is no console output:

```
hostname# show console-output
Sorry, there are no messages to display
```

Related Commands	Command	Description
	show console-output	Displays the captured console output.

show context

To show context information including allocated interfaces and the configuration file URL, the number of contexts configured, or from the system execution space, a list of all contexts, use the **show context** command in privileged EXEC mode.

show context [*name* | **detail** | **count**]

Syntax Description

count	(Optional) Shows the number of contexts configured.
detail	(Optional) Shows additional detail about the context(s) including the running state and information for internal use.
<i>name</i>	(Optional) Sets the context name. If you do not specify a name, the security appliance displays all contexts. Within a context, you can only enter the current context name.

Defaults

In the system execution space, the security appliance displays all contexts if you do not specify a name.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

See the “[Examples](#)” section for a description of the display output.

Examples

The following is sample output from the **show context** command. The following sample display shows three contexts:

```
hostname# show context
```

```
Context Name      Interfaces                                URL
*admin            GigabitEthernet0/1.100                  flash:/admin.cfg
                  GigabitEthernet0/1.101
contexta          GigabitEthernet0/1.200                  flash:/contexta.cfg
                  GigabitEthernet0/1.201
contextb          GigabitEthernet0/1.300                  flash:/contextb.cfg
                  GigabitEthernet0/1.301
Total active Security Contexts: 3
```

Table 7-11 shows each field description.

Table 7-11 *show context Fields*

Field	Description
Context Name	Lists all context names. The context name with the asterisk (*) is the admin context.
Interfaces	The interfaces assigned to the context.
URL	The URL from which the security appliance loads the context configuration.

The following is sample output from the **show context detail** command:

```
hostname# show context detail
```

```
Context "admin", has been created, but initial ACL rules not complete
  Config URL: flash:/admin.cfg
  Real Interfaces: Management0/0
  Mapped Interfaces: Management0/0
  Flags: 0x00000013, ID: 1
```

```
Context "ctx", has been created, but initial ACL rules not complete
  Config URL: ctx.cfg
  Real Interfaces: GigabitEthernet0/0.10, GigabitEthernet0/1.20,
                  GigabitEthernet0/2.30
  Mapped Interfaces: int1, int2, int3
  Flags: 0x00000011, ID: 2
```

```
Context "system", is a system resource
  Config URL: startup-config
  Real Interfaces:
  Mapped Interfaces: Control0/0, GigabitEthernet0/0,
                  GigabitEthernet0/0.10, GigabitEthernet0/1, GigabitEthernet0/1.10,
                  GigabitEthernet0/1.20, GigabitEthernet0/2, GigabitEthernet0/2.30,
                  GigabitEthernet0/3, Management0/0, Management0/0.1
  Flags: 0x00000019, ID: 257
```

```
Context "null", is a system resource
  Config URL: ... null ...
  Real Interfaces:
  Mapped Interfaces:
  Flags: 0x00000009, ID: 258
```

Table 7-12 shows each field description.

Table 7-12 *Context States*

Field	Description
Context	The context name. The null context information is for internal use only. The system context represents the system execution space.
State Message:	The context state. See the possible messages below.

Table 7-12 Context States

Field	Description
Has been created, but initial ACL rules not complete	The security appliance parsed the configuration but has not yet downloaded the default ACLs to establish the default security policy. The default security policy applies to all contexts initially, and includes disallowing traffic from lower security levels to higher security levels, enabling application inspection, and other parameters. This security policy ensures that no traffic can pass through the security appliance after the configuration is parsed but before the configuration ACLs are compiled. You are unlikely to see this state because the configuration ACLs are compiled very quickly.
Has been created, but not initialized	You entered the context name command, but have not yet entered the config-url command.
Has been created, but the config hasn't been parsed	The default ACLs were downloaded, but the security appliance has not parsed the configuration. This state might exist because the configuration download might have failed because of network connectivity issues, or you have not yet entered the config-url command. To reload the configuration, from within the context, enter copy startup-config running-config . From the system, reenter the config-url command. Alternatively, you can start configuring the blank running configuration.
Is a system resource	This state applies only to the system execution space and to the null context. The null context is used by the system, and the information is for internal use only.
Is a zombie	You deleted the context using the no context or clear context command, but the context information persists in memory until the security appliance reuses the context ID for a new context, or you restart.
Is active	This context is currently running and can pass traffic according to the context configuration security policy.
Is ADMIN and active	This context is the admin context and is currently running.
Was a former ADMIN, but is now a zombie	You deleted the admin context using the clear configure context command, but the context information persists in memory until the security appliance reuses the context ID for a new context, or you restart.
Real Interfaces	The interfaces assigned to the context. If you mapped the interface IDs in the allocate-interface command, this display shows the real name of the interface. The system execution space includes all interfaces.
Mapped Interfaces	If you mapped the interface IDs in the allocate-interface command, this display shows the mapped names. If you did not map the interfaces, the display lists the real names again.
Flag	For internal use only.
ID	An internal ID for this context.

The following is sample output from the **show context count** command:

```
hostname# show context count
Total active contexts: 2
```

Related Commands	Command	Description
	admin-context	Sets the admin context.
	allocate-interface	Assigns interfaces to a context.
	changeto	Changes between contexts or the system execution space.
	config-url	Specifies the location of the context configuration.
	context	Creates a security context in the system configuration and enters context configuration mode.

show counters

To display the protocol stack counters, use the **show counters** command in privileged EXEC mode.

show counters [**all** | **context** *context-name* | **summary** | **top** *N*] [**detail**] [**protocol** *protocol_name* [:*counter_name*]] [**threshold** *N*]

Syntax Description

all	Displays the filter details.
context <i>context-name</i>	Specifies the context name.
<i>:counter_name</i>	Specifies a counter by name.
detail	Displays additional counters information.
protocol <i>protocol_name</i>	Displays the counters for the specified protocol.
summary	Displays a counter summary.
threshold <i>N</i>	Displays only those counters at or above the specified threshold. The range is 1 through 4294967295.
top <i>N</i>	Displays the counters at or above the specified threshold. The range is 1 through 4294967295.

Defaults

show counters summary detail threshold 1

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to display all counters:

```
hostname# show counters all
Protocol    Counter      Value  Context
IOS_IPC    IN_PKTS       2      single_vf
IOS_IPC    OUT_PKTS      2      single_vf

hostname# show counters
Protocol    Counter      Value  Context
NPCP       IN_PKTS      7195   Summary
NPCP       OUT_PKTS     7603   Summary
IOS_IPC    IN_PKTS      869    Summary
IOS_IPC    OUT_PKTS     865    Summary
IP         IN_PKTS      380    Summary
```

IP	OUT_PKTS	411	Summary
IP	TO_ARP	105	Summary
IP	TO_UDP	9	Summary
UDP	IN_PKTS	9	Summary
UDP	DROP_NO_APP	9	Summary
FIXUP	IN_PKTS	202	Summary

The following example shows how to display a summary of counters:

```
hostname# show counters summary
```

Protocol	Counter	Value	Context
IOS_IPC	IN_PKTS	2	Summary
IOS_IPC	OUT_PKTS	2	Summary

The following example shows how to display counters for a context:

```
hostname# show counters context single_vf
```

Protocol	Counter	Value	Context
IOS_IPC	IN_PKTS	4	single_vf
IOS_IPC	OUT_PKTS	4	single_vf

Related Commands

Command	Description
clear counters	Clears the protocol stack counters.

show cpu

To display the CPU utilization information, use the **show cpu usage** command in privileged EXEC mode.

show cpu [usage]

From the system configuration in multiple context mode:

show cpu [usage] [context {all | context_name}]

Syntax Description	all	Specifies that the display show all contexts.
	context	Specifies that the display show a context.
	context_name	Specifies the name of the context to display.
	usage	(Optional) Displays the CPU usage.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines

The cpu usage is computed using an approximation of the load every five seconds, and by further feeding this approximation into two, following moving averages.

You can use the **show cpu** command to find process related loads (that is, activity on behalf of items listed by the output of the **show process** command in both single mode and from the system configuration in multiple context mode).

Further, you can request, when in multiple context mode, a breakdown of the process related load to CPU consumed by any configured contexts by changing to each context and entering the **show cpu** command or by entering the **show cpu context** variant of this command.

While process related load is rounded to the nearest whole number, context related loads include one additional decimal digit of precision. For example, entering **show cpu** from the system context produces a different number than from entering the **show cpu context system** command. The former is an approximate summary of everything in **show cpu context all**, and the latter is only a portion of that summary.

Examples

The following example shows how to display the CPU utilization:

```
hostname# show cpu usage
CPU utilization for 5 seconds = 18%; 1 minute: 18%; 5 minutes: 18%
```

This example shows how to display the CPU utilization for the system context in multiple mode:

```
hostname# show cpu context system
CPU utilization for 5 seconds = 9.1%; 1 minute: 9.2%; 5 minutes: 9.1%
```

The following shows how to display the CPU utilization for all contexts:

```
hostname# show cpu usage context all
5 sec  1 min  5 min  Context Name
9.1%   9.2%   9.1%   system
0.0%   0.0%   0.0%   admin
5.0%   5.0%   5.0%   one
4.2%   4.3%   4.2%   two
```

This example shows how to display the CPU utilization for a context named “one”:

```
hostname/one# show cpu usage
CPU utilization for 5 seconds = 5.0%; 1 minute: 5.0%; 5 minutes: 5.0%
```

Related Commands

Command	Description
show counters	Displays the protocol stack counters.

show crashinfo

To display the contents of the crash file stored in Flash memory, enter the **show crashinfo** command in privileged EXEC mode.

show crashinfo [save]

Syntax Description

save	(Optional) Displays if the security appliance is configured to save crash information to Flash memory or not.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If the crash file is from a test crash (generated from the **crashinfo test** command), the first string of the crash file is “: Saved_Test_Crash” and the last string is “: End_Test_Crash”. If the crash file is from a real crash, the first string of the crash file is “: Saved_Crash” and the last string is “: End_Crash”. (This includes crashes from use of the **crashinfo force page-fault** or **crashinfo force watchdog** commands).

If there is no crash data saved in flash, or if the crash data has been cleared by entering the **clear crashinfo** command, the **show crashinfo** command displays an error message.

Examples

The following example shows how to display the current crash information configuration:

```
hostname# show crashinfo save
crashinfo save enable
```

The following example shows the output for a crash file test. (However, this test does not actually crash the security appliance. It provides a simulated example file.)

```
hostname(config)# crashinfo test
hostname(config)# exit
hostname# show crashinfo
: Saved_Test_Crash
```

```
Thread Name: ci/console (Old pc 0x001a6ff5 ebp 0x00e88920)
```

```

Traceback:
0: 00323143
1: 0032321b
2: 0010885c
3: 0010763c
4: 001078db
5: 00103585
6: 00000000
   vector 0x000000ff (user defined)
       edi 0x004f20c4
       esi 0x00000000
       ebp 0x00e88c20
       esp 0x00e88bd8
       ebx 0x00000001
       edx 0x00000074
       ecx 0x00322f8b
       eax 0x00322f8b
error code n/a
       eip 0x0010318c
       cs 0x00000008
       eflags 0x00000000
       CR2 0x00000000
Stack dump: base:0x00e8511c size:16384, active:1476
0x00e89118: 0x004f1bb4
0x00e89114: 0x001078b4
0x00e89110-0x00e8910c: 0x00000000
0x00e89108-0x00e890ec: 0x12345678
0x00e890e8: 0x004f1bb4
0x00e890e4: 0x00103585
0x00e890e0: 0x00e8910c
0x00e890dc-0x00e890cc: 0x12345678
0x00e890c8: 0x00000000
0x00e890c4-0x00e890bc: 0x12345678
0x00e890b8: 0x004f1bb4
0x00e890b4: 0x001078db
0x00e890b0: 0x00e890e0
0x00e890ac-0x00e890a8: 0x12345678
0x00e890a4: 0x001179b3
0x00e890a0: 0x00e890b0
0x00e8909c-0x00e89064: 0x12345678
0x00e89060: 0x12345600
0x00e8905c: 0x20232970
0x00e89058: 0x616d2d65
0x00e89054: 0x74002023
0x00e89050: 0x29676966
0x00e8904c: 0x6e6f6328
0x00e89048: 0x31636573
0x00e89044: 0x7069636f
0x00e89040: 0x64786970
0x00e8903c-0x00e88e50: 0x00000000
0x00e88e4c: 0x000a7473
0x00e88e48: 0x6574206f
0x00e88e44: 0x666e6968
0x00e88e40: 0x73617263
0x00e88e3c-0x00e88e38: 0x00000000
0x00e88e34: 0x12345600
0x00e88e30-0x00e88dfc: 0x00000000
0x00e88df8: 0x00316761
0x00e88df4: 0x74706100
0x00e88df0: 0x12345600
0x00e88dec-0x00e88ddc: 0x00000000
0x00e88dd8: 0x00000070
0x00e88dd4: 0x616d2d65

```

```

0x00e88dd0: 0x74756f00
0x00e88dcc: 0x00000000
0x00e88dc8: 0x00e88e40
0x00e88dc4: 0x004f20c4
0x00e88dc0: 0x12345600
0x00e88dbc: 0x00000000
0x00e88db8: 0x00000035
0x00e88db4: 0x315f656c
0x00e88db0: 0x62616e65
0x00e88dac: 0x0030fcf0
0x00e88da8: 0x3011111f
0x00e88da4: 0x004df43c
0x00e88da0: 0x0053fef0
0x00e88d9c: 0x004f1bb4
0x00e88d98: 0x12345600
0x00e88d94: 0x00000000
0x00e88d90: 0x00000035
0x00e88d8c: 0x315f656c
0x00e88d88: 0x62616e65
0x00e88d84: 0x00000000
0x00e88d80: 0x004f20c4
0x00e88d7c: 0x00000001
0x00e88d78: 0x01345678
0x00e88d74: 0x00f53854
0x00e88d70: 0x00f7f754
0x00e88d6c: 0x00e88db0
0x00e88d68: 0x00e88d7b
0x00e88d64: 0x00f53874
0x00e88d60: 0x00e89040
0x00e88d5c-0x00e88d54: 0x12345678
0x00e88d50-0x00e88d4c: 0x00000000
0x00e88d48: 0x004f1bb4
0x00e88d44: 0x00e88d7c
0x00e88d40: 0x00e88e40
0x00e88d3c: 0x00f53874
0x00e88d38: 0x004f1bb4
0x00e88d34: 0x0010763c
0x00e88d30: 0x00e890b0
0x00e88d2c: 0x00e88db0
0x00e88d28: 0x00e88d88
0x00e88d24: 0x0010761a
0x00e88d20: 0x00e890b0
0x00e88d1c: 0x00e88e40
0x00e88d18: 0x00f53874
0x00e88d14: 0x0010166d
0x00e88d10: 0x0000000e
0x00e88d0c: 0x00f53874
0x00e88d08: 0x00f53854
0x00e88d04: 0x0048b301
0x00e88d00: 0x00e88d30
0x00e88cfc: 0x0000000e
0x00e88cf8: 0x00f53854
0x00e88cf4: 0x0048a401
0x00e88cf0: 0x00f53854
0x00e88cec: 0x00f53874
0x00e88ce8: 0x0000000e
0x00e88ce4: 0x0048a64b
0x00e88ce0: 0x0000000e
0x00e88cdc: 0x00f53874
0x00e88cd8: 0x00f7f96c
0x00e88cd4: 0x0048b4f8
0x00e88cd0: 0x00e88d00
0x00e88ccc: 0x0000000f
0x00e88cc8: 0x00f7f96c

```

```

0x00e88cc4-0x00e88cc0: 0x0000000e
0x00e88cbc: 0x00e89040
0x00e88cb8: 0x00000000
0x00e88cb4: 0x00f5387e
0x00e88cb0: 0x00f53874
0x00e88cac: 0x00000002
0x00e88ca8: 0x00000001
0x00e88ca4: 0x00000009
0x00e88ca0-0x00e88c9c: 0x00000001
0x00e88c98: 0x00e88cb0
0x00e88c94: 0x004f20c4
0x00e88c90: 0x0000003a
0x00e88c8c: 0x00000000
0x00e88c88: 0x0000000a
0x00e88c84: 0x00489f3a
0x00e88c80: 0x00e88d88
0x00e88c7c: 0x00e88e40
0x00e88c78: 0x00e88d7c
0x00e88c74: 0x001087ed
0x00e88c70: 0x00000001
0x00e88c6c: 0x00e88cb0
0x00e88c68: 0x00000002
0x00e88c64: 0x0010885c
0x00e88c60: 0x00e88d30
0x00e88c5c: 0x00727334
0x00e88c58: 0xa0ffffff
0x00e88c54: 0x00e88cb0
0x00e88c50: 0x00000001
0x00e88c4c: 0x00e88cb0
0x00e88c48: 0x00000002
0x00e88c44: 0x0032321b
0x00e88c40: 0x00e88c60
0x00e88c3c: 0x00e88c7f
0x00e88c38: 0x00e88c5c
0x00e88c34: 0x004b1ad5
0x00e88c30: 0x00e88c60
0x00e88c2c: 0x00e88e40
0x00e88c28: 0xa0ffffff
0x00e88c24: 0x00323143
0x00e88c20: 0x00e88c40
0x00e88c1c: 0x00000000
0x00e88c18: 0x00000008
0x00e88c14: 0x0010318c
0x00e88c10-0x00e88c0c: 0x00322f8b
0x00e88c08: 0x00000074
0x00e88c04: 0x00000001
0x00e88c00: 0x00e88bd8
0x00e88bfc: 0x00e88c20
0x00e88bf8: 0x00000000
0x00e88bf4: 0x004f20c4
0x00e88bf0: 0x000000ff
0x00e88bec: 0x00322f87
0x00e88be8: 0x00f5387e
0x00e88be4: 0x00323021
0x00e88be0: 0x00e88c10
0x00e88bdc: 0x004f20c4
0x00e88bd8: 0x00000000 *
0x00e88bd4: 0x004eabb0
0x00e88bd0: 0x00000001
0x00e88bcc: 0x00f5387e
0x00e88bc8-0x00e88bc4: 0x00000000
0x00e88bc0: 0x00000008
0x00e88bbc: 0x0010318c
0x00e88bb8-0x00e88bb4: 0x00322f8b

```

```

0x00e88bb0: 0x00000074
0x00e88bac: 0x00000001
0x00e88ba8: 0x00e88bd8
0x00e88ba4: 0x00e88c20
0x00e88ba0: 0x00000000
0x00e88b9c: 0x004f20c4
0x00e88b98: 0x000000ff
0x00e88b94: 0x001031f2
0x00e88b90: 0x00e88c20
0x00e88b8c: 0xffffffff
0x00e88b88: 0x00e88cb0
0x00e88b84: 0x00320032
0x00e88b80: 0x37303133
0x00e88b7c: 0x312f6574
0x00e88b78: 0x6972772f
0x00e88b74: 0x342f7665
0x00e88b70: 0x64736666
0x00e88b6c: 0x00020000
0x00e88b68: 0x00000010
0x00e88b64: 0x00000001
0x00e88b60: 0x123456cd
0x00e88b5c: 0x00000000
0x00e88b58: 0x00000008

```

```

Cisco XXX Firewall Version X.X
Cisco XXX Device Manager Version X.X

```

```

Compiled on Fri 15-Nov-04 14:35 by root

```

```

hostname up 10 days 0 hours

```

```

Hardware:   XXX-XXX, 64 MB RAM, CPU Pentium 200 MHz
Flash i28F640J5 @ 0x300, 16MB
BIOS Flash AT29C257 @ 0xffffd8000, 32KB

```

```

0: ethernet0: address is 0003.e300.73fd, irq 10
1: ethernet1: address is 0003.e300.73fe, irq 7
2: ethernet2: address is 00d0.b7c8.139e, irq 9

```

```

Licensed Features:

```

```

Failover:           Disabled
VPN-DES:            Enabled
VPN-3DES-AES:       Disabled
Maximum Interfaces: 3
Cut-through Proxy:  Enabled
Guards:             Enabled
URL-filtering:      Enabled
Inside Hosts:       Unlimited
Throughput:         Unlimited
IKE peers:          Unlimited

```

```

This XXX has a Restricted (R) license.

```

```

Serial Number: 480430455 (0x1ca2c977)
Running Activation Key: 0xc2e94182 0xc21d8206 0x15353200 0x633f6734
Configuration last modified by enable_15 at 13:49:42.148 UTC Wed Nov 20 2004

```

```

----- show clock -----

```

```

15:34:28.129 UTC Sun Nov 24 2004

```

```

----- show memory -----

```

```

Free memory:        50444824 bytes
Used memory:        16664040 bytes

```

```

-----
Total memory:          67108864 bytes

----- show conn count -----

0 in use, 0 most used

----- show xlate count -----

0 in use, 0 most used

----- show blocks -----

  SIZE      MAX      LOW      CNT
    4      1600     1600     1600
   80       400      400      400
  256       500      499      500
 1550     1188      795      927

----- show interface -----

interface ethernet0 "outside" is up, line protocol is up
  Hardware is i82559 ethernet, address is 0003.e300.73fd
  IP address 172.23.59.232, subnet mask 255.255.0.0
  MTU 1500 bytes, BW 10000 Kbit half duplex
    6139 packets input, 830375 bytes, 0 no buffer
    Received 5990 broadcasts, 0 runts, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    90 packets output, 6160 bytes, 0 underruns
    0 output errors, 13 collisions, 0 interface resets
    0 babbles, 0 late collisions, 47 deferred
    0 lost carrier, 0 no carrier
    input queue (curr/max blocks): hardware (5/128) software (0/2)
    output queue (curr/max blocks): hardware (0/1) software (0/1)
interface ethernet1 "inside" is up, line protocol is down
  Hardware is i82559 ethernet, address is 0003.e300.73fe
  IP address 10.1.1.1, subnet mask 255.255.255.0
  MTU 1500 bytes, BW 10000 Kbit half duplex
    0 packets input, 0 bytes, 0 no buffer
    Received 0 broadcasts, 0 runts, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    1 packets output, 60 bytes, 0 underruns
    0 output errors, 0 collisions, 0 interface resets
    0 babbles, 0 late collisions, 0 deferred
    1 lost carrier, 0 no carrier
    input queue (curr/max blocks): hardware (128/128) software (0/0)
    output queue (curr/max blocks): hardware (0/1) software (0/1)
interface ethernet2 "intf2" is administratively down, line protocol is down
  Hardware is i82559 ethernet, address is 00d0.b7c8.139e
  IP address 127.0.0.1, subnet mask 255.255.255.255
  MTU 1500 bytes, BW 10000 Kbit half duplex
    0 packets input, 0 bytes, 0 no buffer
    Received 0 broadcasts, 0 runts, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    0 packets output, 0 bytes, 0 underruns
    0 output errors, 0 collisions, 0 interface resets
    0 babbles, 0 late collisions, 0 deferred
    0 lost carrier, 0 no carrier
    input queue (curr/max blocks): hardware (128/128) software (0/0)
    output queue (curr/max blocks): hardware (0/0) software (0/0)

----- show cpu usage -----

CPU utilization for 5 seconds = 0%; 1 minute: 0%; 5 minutes: 0%

```

show crashinfo

```
----- show process -----
```

	PC	SP	STATE	Runtime	SBASE	Stack	Process
Hsi	001e3329	00763e7c	0053e5c8	0	00762ef4	3784/4096	arp_timer
Lsi	001e80e9	00807074	0053e5c8	0	008060fc	3792/4096	FragDBG
Lwe	00117e3a	009dc2e4	00541d18	0	009db46c	3704/4096	dbgtrace
Lwe	003cee95	009de464	00537718	0	009dc51c	8008/8192	Logger
Hwe	003d2d18	009e155c	005379c8	0	009df5e4	8008/8192	tcp_fast
Hwe	003d2c91	009e360c	005379c8	0	009e1694	8008/8192	tcp_slow
Lsi	002ec97d	00b1a464	0053e5c8	0	00b194dc	3928/4096	xlate_clean
Lsi	002ec88b	00b1b504	0053e5c8	0	00b1a58c	3888/4096	uxlate_clean
Mrd	002e3a17	00c8f8d4	0053e600	0	00c8d93c	7908/8192	tcp_intercept_times
Lsi	00423dd5	00d3a22c	0053e5c8	0	00d392a4	3900/4096	route_process
Hsi	002d59fc	00d3b2bc	0053e5c8	0	00d3a354	3780/4096	PIX Garbage Collec
Hwe	0020e301	00d5957c	0053e5c8	0	00d55614	16048/16384	isakmp_time_keepr
Lsi	002d377c	00d7292c	0053e5c8	0	00d719a4	3928/4096	perfmon
Hwe	0020bd07	00d9c12c	0050bb90	0	00d9b1c4	3944/4096	IPSec
Mwe	00205e25	00d9e1ec	0053e5c8	0	00d9c274	7860/8192	IPsec timer handler
Hwe	003864e3	00db26bc	00557920	0	00db0764	6904/8192	qos_metric_daemon
Mwe	00255a65	00dc9244	0053e5c8	0	00dc8adc	1436/2048	IP Background
Lwe	002e450e	00e7bb94	00552c30	0	00e7ad1c	3704/4096	pix/trace
Lwe	002e471e	00e7cc44	00553368	0	00e7bdcc	3704/4096	pix/tconsole
Hwe	001e5368	00e7ed44	00730674	0	00e7ce9c	7228/8192	pix/intf0
Hwe	001e5368	00e80e14	007305d4	0	00e7ef6c	7228/8192	pix/intf1
Hwe	001e5368	00e82ee4	00730534	2470	00e8103c	4892/8192	pix/intf2
H*	001a6ff5	0009ff2c	0053e5b0	4820	00e8511c	12860/16384	ci/console
Csi	002dd8ab	00e8a124	0053e5c8	0	00e891cc	3396/4096	update_cpu_usage
Hwe	002cb4d1	00f2bfb3	0051e360	0	00f2a134	7692/8192	uauth_in
Hwe	003d17d1	00f2e0bc	00828cf0	0	00f2c1e4	7896/8192	uauth_thread
Hwe	003e71d4	00f2f20c	00537d20	0	00f2e294	3960/4096	udp_timer
Hsi	001db3ca	00f30fc4	0053e5c8	0	00f3004c	3784/4096	557mcfix
Crđ	001db37f	00f32084	0053ea40	508286220	00f310fc	3688/4096	557poll
Lsi	001db435	00f33124	0053e5c8	0	00f321ac	3700/4096	557timer
Hwe	001e5398	00f441dc	008121e0	0	00f43294	3912/4096	fover_ip0
Cwe	001dcdad	00f4523c	00872b48	120	00f44344	3528/4096	ip/0:0
Hwe	001e5398	00f4633c	008121bc	10	00f453f4	3532/4096	icmp0
Hwe	001e5398	00f47404	00812198	0	00f464cc	3896/4096	udp_thread/0
Hwe	001e5398	00f4849c	00812174	0	00f475a4	3456/4096	tcp_thread/0
Hwe	001e5398	00f495bc	00812150	0	00f48674	3912/4096	fover_ip1
Cwe	001dcdad	00f4a61c	008ea850	0	00f49724	3832/4096	ip/1:1
Hwe	001e5398	00f4b71c	0081212c	0	00f4a7d4	3912/4096	icmpl
Hwe	001e5398	00f4c7e4	00812108	0	00f4b8ac	3896/4096	udp_thread/1
Hwe	001e5398	00f4d87c	008120e4	0	00f4c984	3832/4096	tcp_thread/1
Hwe	001e5398	00f4e99c	008120c0	0	00f4da54	3912/4096	fover_ip2
Cwe	001e542d	00f4fa6c	00730534	0	00f4eb04	3944/4096	ip/2:2
Hwe	001e5398	00f50afc	0081209c	0	00f4fbb4	3912/4096	icmp2
Hwe	001e5398	00f51bc4	00812078	0	00f50c8c	3896/4096	udp_thread/2
Hwe	001e5398	00f52c5c	00812054	0	00f51d64	3832/4096	tcp_thread/2
Hwe	003d1a65	00f78284	008140f8	0	00f77fdc	300/1024	listen/http1
Mwe	0035cafa	00f7a63c	0053e5c8	0	00f786c4	7640/8192	Crypto CA

```
----- show failover -----
```

```
No license for Failover
```

```
----- show traffic -----
```

```
outside:
  received (in 865565.090 secs):
    6139 packets      830375 bytes
    0 pkts/sec        0 bytes/sec
  transmitted (in 865565.090 secs):
```



```

          90 packets      6160 bytes
          0 pkts/sec      0 bytes/sec
inside:
  received (in 865565.090 secs):
    0 packets      0 bytes
    0 pkts/sec     0 bytes/sec
  transmitted (in 865565.090 secs):
    1 packets      60 bytes
    0 pkts/sec     0 bytes/sec
intf2:
  received (in 865565.090 secs):
    0 packets      0 bytes
    0 pkts/sec     0 bytes/sec
  transmitted (in 865565.090 secs):
    0 packets      0 bytes
    0 pkts/sec     0 bytes/sec

----- show perfmon -----

PERFMON STATS:      Current      Average
Xlates              0/s          0/s
Connections         0/s          0/s
TCP Conns           0/s          0/s
UDP Conns           0/s          0/s
URL Access          0/s          0/s
URL Server Req      0/s          0/s
TCP Fixup           0/s          0/s
TCPIntercept        0/s          0/s
HTTP Fixup          0/s          0/s
FTP Fixup           0/s          0/s
AAA Authen          0/s          0/s
AAA Author          0/s          0/s
AAA Account         0/s          0/s
: End_Test_Crash

```

Related Commands

Command	Description
clear crashinfo	Deletes the contents of the crash file.
crashinfo force	Forces a crash of the security appliance.
crashinfo save disable	Disables crash information from writing to Flash memory.
crashinfo test	Tests the ability of the security appliance to save crash information to a file in Flash memory.

show crashinfo console

To display the configuration setting of the **crashinfo console** command, enter the **show crashinfo console** command in privileged EXEC mode.

show crashinfo console

Syntax Description This command has no arguments or keywords.

Defaults This command has no default settings.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Release	Modification
7.0(4)	This command was introduced.

Usage Guidelines Compliance with FIPS 140-2 prohibits the distribution of Critical Security Parameters (keys, passwords, etc.) outside of the crypto boundary (chassis). When the device crashes, due to an assert or checkheaps failure, it is possible that the stack or memory regions dumped to the console contain sensitive data. This output must be suppressed in FIPS-mode.

Examples

```
sw8-5520(config)# show crashinfo console
crashinfo console enable
```

Command	Description
clear configure fips	Clears the system or module FIPS configuration information stored in NVRAM.
crashinfo console disable	Disables the reading, writing and configuration of crash write info to flash.
fips enable	Enables or disables policy-checking to enforce FIPS compliance on the system or module.

Command	Description
fips self-test poweron	Executes power-on self-tests.
show running-config fips	Displays the FIPS configuration that is running on the security appliance.

show crypto accelerator statistics

To display the global and accelerator-specific statistics from the hardware crypto accelerator MIB, use the **show crypto accelerator statistics** command in global configuration or privileged EXEC mode.

show crypto accelerator statistics

Syntax Description This command has no keywords or variables.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples The following example entered in global configuration mode, displays global crypto accelerator statistics:

```
hostname # show crypto accelerator statistics
```

```
Crypto Accelerator Status
-----
[Capacity]
  Supports hardware crypto: True
  Supports modular hardware crypto: False
  Max accelerators: 1
  Max crypto throughput: 100 Mbps
  Max crypto connections: 750
[Global Statistics]
  Number of active accelerators: 1
  Number of non-operational accelerators: 0
  Input packets: 700
  Input bytes: 753488
  Output packets: 700
  Output error packets: 0
  Output bytes: 767496
[Accelerator 0]
  Status: Active
  Software crypto engine
  Slot: 0
  Active time: 167 seconds
  Total crypto transforms: 7
```

```

Total dropped packets: 0
[Input statistics]
  Input packets: 0
  Input bytes: 0
  Input hashed packets: 0
  Input hashed bytes: 0
  Decrypted packets: 0
  Decrypted bytes: 0
[Output statistics]
  Output packets: 0
  Output bad packets: 0
  Output bytes: 0
  Output hashed packets: 0
  Output hashed bytes: 0
  Encrypted packets: 0
  Encrypted bytes: 0
[Diffie-Hellman statistics]
  Keys generated: 0
  Secret keys derived: 0
[RSA statistics]
  Keys generated: 0
  Signatures: 0
  Verifications: 0
  Encrypted packets: 0
  Encrypted bytes: 0
  Decrypted packets: 0
  Decrypted bytes: 0
[DSA statistics]
  Keys generated: 0
  Signatures: 0
  Verifications: 0
[SSL statistics]
  Outbound records: 0
  Inbound records: 0
[RNG statistics]
  Random number requests: 98
  Random number request failures: 0
[Accelerator 1]
  Status: Active
  Encryption hardware device : Cisco ASA-55x0 on-board accelerator
(revision 0x0)

                                Boot microcode   : CNlite-MC-Boot-Cisco-1.2
                                SSL/IKE microcode: CNlite-MC-IPSEC-Admin-3.03
                                IPSec microcode  : CNlite-MC-IPSECM-MAIN-2.03

Slot: 1
Active time: 170 seconds
Total crypto transforms: 1534
Total dropped packets: 0
[Input statistics]
  Input packets: 700
  Input bytes: 753544
  Input hashed packets: 700
  Input hashed bytes: 736400
  Decrypted packets: 700
  Decrypted bytes: 719944
[Output statistics]
  Output packets: 700
  Output bad packets: 0
  Output bytes: 767552
  Output hashed packets: 700
  Output hashed bytes: 744800
  Encrypted packets: 700
  Encrypted bytes: 728352
[Diffie-Hellman statistics]

```

■ show crypto accelerator statistics

```

Keys generated: 97
Secret keys derived: 1
[RSA statistics]
Keys generated: 0
Signatures: 0
Verifications: 0
Encrypted packets: 0
Encrypted bytes: 0
Decrypted packets: 0
Decrypted bytes: 0
[DSA statistics]
Keys generated: 0
Signatures: 0
Verifications: 0
[SSL statistics]
Outbound records: 0
Inbound records: 0
[RNG statistics]
Random number requests: 1
Random number request failures: 0
hostname #

```

Related Commands

Command	Description
clear crypto accelerator statistics	Clears the global and accelerator-specific statistics in the crypto accelerator MIB.
clear crypto protocol statistics	Clears the protocol-specific statistics in the crypto accelerator MIB.
show crypto protocol statistics	Displays the protocol-specific statistics from the crypto accelerator MIB.

show crypto ca certificates

To display the certificates associated with a specific trustpoint or to display all the certificates installed on the system, use the **show crypto ca certificates** command in global configuration or privileged EXEC mode.

show crypto ca certificates [*trustpointname*]

Syntax Description

trustpointname (Optional) The name of a trustpoint. If you do not specify a name, this command displays all certificates installed on the system.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example entered in global configuration mode, displays a CA certificate for a trustpoint named tp1:

```
hostname(config)# show crypto ca certificates tp1
CA Certificate
  Status: Available
  Certificate Serial Number 2957A3FF296EF854FD0D6732FE25B45
  Certificate Usage: Signature
  Issuer:
    CN = ms-root-sha-06-2004
    OU = rootou
    O = cisco
    L = franklin
    ST = massachusetts
    C = US
    EA = a@b.con
  Subject:
    CN = ms-root-sha-06-2004
    OU = rootou
    O = cisco
    L = franklin
    ST = massachusetts
    C = US
    EA = a@b.com
```

show crypto ca certificates

```

CRL Distribution Point
  ldap://w2kadvancedsrv/CertEnroll/ms-root-sha-06-2004.crl
Validity Date:
  start date: 14:11:40 UTC Jun 26 2004
  end date: 14:01:30 UTC Jun 4 2022
Associated Trustpoints: tp2 tp1
hostname(config)#

```

Related Commands

Command	Description
crypto ca authenticate	Obtains a CA certificate for a specified trustpoint.
crypto ca crl request	Requests a CRL based on the configuration parameters of a specified trustpoint.
crypto ca enroll	Initiates the enrollment process with a CA.
crypto ca import	Imports a certificate to a specified trustpoint.
crypto ca trustpoint	Enters trustpoint mode for a specified trustpoint.

show crypto ca crls

To display all cached CRLs or to display all CRLs cached for a specified trustpoint, use the **show crypto ca crls** command in global configuration or privileged EXEC mode.

show crypto ca crls [*trustpointname*]

Syntax Description

trustpointname (Optional) The name of a trustpoint. If you do not specify a name, this command displays all CRLs cached on the system.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	
Privileged EXEC	•	•	•	•	

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example entered in global configuration mode, displays a CRL for a trustpoint named tp1:

```
hostname(config)# show crypto ca crls tp1
CRL Issuer Name:
  cn=ms-sub1-ca-5-2004,ou=Franklin DevTest,o=Cisco
Systems,l=Franklin,st=MA,c=US,ea=user@cisco.com
LastUpdate: 19:45:53 UTC Dec 24 2004
NextUpdate: 08:05:53 UTC Jan 1 2005
Retrieved from CRL Distribution Point:
  http://win2k-ad2.frk-ms-pki.cisco.com/CertEnroll/ms-sub1-ca-5-2004.crl
Associated Trustpoints: tp1
hostname(config)#
```

Related Commands

Command	Description
crypto ca authenticate	Obtains a CA certificate for a specified trustpoint.
crypto ca crl request	Requests a CRL based on the configuration parameters of a specified trustpoint.
crypto ca enroll	Initiates the enrollment process with a CA.
crypto ca import	Imports a certificate to a specified trustpoint.
crypto ca trustpoint	Enters trustpoint mode for a specified trustpoint.

show crypto ipsec df-bit

To display the IPsec DF-bit policy for IPsec packets for a specified interface, use the **show crypto ipsec df-bit** command in global configuration mode and privileged EXEC mode.

show crypto ipsec df-bit *interface*

Syntax Description

interface Specifies an interface name.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example displays the IPsec DF-bit policy for interface named inside:

```
hostname(config)# show crypto ipsec df-bit inside
df-bit inside copy
hostname(config)#
```

Related Commands

Command	Description
crypto ipsec df-bit	Configures the IPsec DF-bit policy for IPsec packets.
crypto ipsec fragmentation	Configures the fragmentation policy for IPsec packets.
show crypto ipsec fragmentation	Displays the fragmentation policy for IPsec packets.

show crypto ipsec fragmentation

To display the fragmentation policy for IPSec packets, use the **show crypto ipsec fragmentation** command in global configuration or privileged EXEC modes.

show crypto ipsec fragmentation *interface*

Syntax Description

interface Specifies an interface name.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example, entered in global configuration mode, displays the IPSec fragmentation policy for an interface named inside:

```
hostname(config)# show crypto ipsec fragmentation inside
fragmentation inside before-encryption
hostname(config)#
```

Related Commands

Command	Description
crypto ipsec fragmentation	Configures the fragmentation policy for IPSec packets.
crypto ipsec df-bit	Configures the DF-bit policy for IPSec packets.
show crypto ipsec df-bit	Displays the DF-bit policy for a specified interface.

show crypto key mypubkey

To display key pairs of the indicated type, use the **show crypto key mypubkey** command in global configuration or privileged EXEC mode.

show crypto key mypubkey {rsa | dsa}

Syntax Description

dsa	Displays DSA key pairs.
rsa	Displays RSA key pairs.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example entered in global configuration mode, displays RSA key pairs:

```
hostname(config)# show crypto key mypubkey rsa
[Display]
hostname(config)#
```

Related Commands

Command	Description
crypto key generate dsa	Generates DSA key pairs.
crypto key generate rsa	Generates RSA key pairs.
crypto key zeroize	Removes all key pairs of the indicated type.

show crypto protocol statistics

To display the protocol-specific statistics in the crypto accelerator MIB, use the **show crypto protocol statistics** command in global configuration or privileged EXEC mode.

show crypto protocol statistics *protocol*

Syntax Description

<i>protocol</i>	Specifies the name of the protocol for which to display statistics. Protocol choices are as follows: ikev1 —Internet Key Exchange version 1. ipsec —IP Security Phase-2 protocols. ssl —Secure Socket Layer. other —Reserved for new protocols. all —All protocols currently supported.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following examples entered in global configuration mode, display crypto accelerator statistics for specified protocols:

```
hostname # show crypto protocol statistics ikev1
[IKEv1 statistics]
  Encrypt packet requests: 39
  Encapsulate packet requests: 39
  Decrypt packet requests: 35
  Decapsulate packet requests: 35
  HMAC calculation requests: 84
  SA creation requests: 1
  SA rekey requests: 3
  SA deletion requests: 2
  Next phase key allocation requests: 2
  Random number generation requests: 0
  Failed requests: 0
```

show crypto protocol statistics

```
hostname # show crypto protocol statistics ipsec
[IPsec statistics]
```

```
  Encrypt packet requests: 700
  Encapsulate packet requests: 700
  Decrypt packet requests: 700
  Decapsulate packet requests: 700
  HMAC calculation requests: 1400
  SA creation requests: 2
  SA rekey requests: 0
  SA deletion requests: 0
  Next phase key allocation requests: 0
  Random number generation requests: 0
  Failed requests: 0
```

```
hostname # show crypto protocol statistics ssl
[SSL statistics]
```

```
  Encrypt packet requests: 0
  Encapsulate packet requests: 0
  Decrypt packet requests: 0
  Decapsulate packet requests: 0
  HMAC calculation requests: 0
  SA creation requests: 0
  SA rekey requests: 0
  SA deletion requests: 0
  Next phase key allocation requests: 0
  Random number generation requests: 0
  Failed requests: 0
```

```
hostname # show crypto protocol statistics other
[Other statistics]
```

```
  Encrypt packet requests: 0
  Encapsulate packet requests: 0
  Decrypt packet requests: 0
  Decapsulate packet requests: 0
  HMAC calculation requests: 0
  SA creation requests: 0
  SA rekey requests: 0
  SA deletion requests: 0
  Next phase key allocation requests: 0
  Random number generation requests: 99
  Failed requests: 0
```

```
hostname # show crypto protocol statistics all
[IKEv1 statistics]
```

```
  Encrypt packet requests: 46
  Encapsulate packet requests: 46
  Decrypt packet requests: 40
  Decapsulate packet requests: 40
  HMAC calculation requests: 91
  SA creation requests: 1
  SA rekey requests: 3
  SA deletion requests: 3
  Next phase key allocation requests: 2
  Random number generation requests: 0
  Failed requests: 0
```

```
[IKEv2 statistics]
```

```
  Encrypt packet requests: 0
  Encapsulate packet requests: 0
  Decrypt packet requests: 0
  Decapsulate packet requests: 0
  HMAC calculation requests: 0
  SA creation requests: 0
  SA rekey requests: 0
  SA deletion requests: 0
```

```

Next phase key allocation requests: 0
Random number generation requests: 0
Failed requests: 0
[IPsec statistics]
  Encrypt packet requests: 700
  Encapsulate packet requests: 700
  Decrypt packet requests: 700
  Decapsulate packet requests: 700
  HMAC calculation requests: 1400
  SA creation requests: 2
  SA rekey requests: 0
  SA deletion requests: 0
  Next phase key allocation requests: 0
  Random number generation requests: 0
  Failed requests: 0
[SSL statistics]
  Encrypt packet requests: 0
  Encapsulate packet requests: 0
  Decrypt packet requests: 0
  Decapsulate packet requests: 0
  HMAC calculation requests: 0
  SA creation requests: 0
  SA rekey requests: 0
  SA deletion requests: 0
  Next phase key allocation requests: 0
  Random number generation requests: 0
  Failed requests: 0
[SSH statistics are not supported]
[SRTP statistics are not supported]
[Other statistics]
  Encrypt packet requests: 0
  Encapsulate packet requests: 0
  Decrypt packet requests: 0
  Decapsulate packet requests: 0
  HMAC calculation requests: 0
  SA creation requests: 0
  SA rekey requests: 0
  SA deletion requests: 0
  Next phase key allocation requests: 0
  Random number generation requests: 99
  Failed requests: 0
hostname #

```

Related Commands

Command	Description
clear crypto accelerator statistics	Clears the global and accelerator-specific statistics in the crypto accelerator MIB.
clear crypto protocol statistics	Clears the protocol-specific statistics in the crypto accelerator MIB.
show crypto accelerator statistics	Displays the global and accelerator-specific statistics from the crypto accelerator MIB.

show ctiqbe

To display information about CTIQBE sessions established across the security appliance, use the **show ctiqbe** command in privileged EXEC mode.

show ctiqbe

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **show ctiqbe** command displays information of CTIQBE sessions established across the security appliance. Along with **debug ctiqbe** and **show local-host**, this command is used for troubleshooting CTIQBE inspection engine issues.



Note

We recommend that you have the **pager** command configured before using the **show ctiqbe** command. If there are a lot of CTIQBE sessions and the **pager** command is not configured, it can take a while for the **show ctiqbe** command output to reach the end.

Examples

The following is sample output from the **show ctiqbe** command under the following conditions. There is only one active CTIQBE session setup across the security appliance. It is established between an internal CTI device (for example, a Cisco IP SoftPhone) at local address 10.0.0.99 and an external Cisco Call Manager at 172.29.1.77, where TCP port 2748 is the Cisco CallManager. The heartbeat interval for the session is 120 seconds.

```
hostname# | show ctiqbe
```

```
Total: 1
| LOCAL | FOREIGN | STATE | HEARTBEAT
-----
1 | 10.0.0.99/1117 | 172.29.1.77/2748 | 1 | 120
| RTP/RTCP: PAT xlates: mapped to 172.29.1.99(1028 | 1029)
```



```

| MEDIA: Device ID 27 | Call ID 0
| Foreign 172.29.1.99 | (1028 | 1029)
| Local | 172.29.1.88 | (26822 | 26823)
| -----

```

The CTI device has already registered with the CallManager. The device internal address and RTP listening port is PATed to 172.29.1.99 UDP port 1028. Its RTCP listening port is PATed to UDP 1029.

The line beginning with `RTP/RTCP: PAT xlates:` appears only if an internal CTI device has registered with an external CallManager and the CTI device address and ports are PATed to that external interface. This line does not appear if the CallManager is located on an internal interface, or if the internal CTI device address and ports are NATed to the same external interface that is used by the CallManager.

The output indicates a call has been established between this CTI device and another phone at 172.29.1.88. The RTP and RTCP listening ports of the other phone are UDP 26822 and 26823. The other phone locates on the same interface as the CallManager because the security appliance does not maintain a CTIQBE session record associated with the second phone and CallManager. The active call leg on the CTI device side can be identified with Device ID 27 and Call ID 0.

The following is the xlate information for these CTIBQE connections:

```

hostname# show xlate debug
3 in use, 3 most used
Flags: D|DNS, d|dump, I|identity, i|inside, n|no random,
       |o|outside, r|portmap, s|static
TCP PAT from inside:10.0.0.99/1117 to outside:172.29.1.99/1025 flags ri idle 0:00:22
timeout 0:00:30
UDP PAT from inside:10.0.0.99/16908 to outside:172.29.1.99/1028 flags ri idle 0:00:00
timeout 0:04:10
UDP PAT from inside:10.0.0.99/16909 to outside:172.29.1.99/1029 flags ri idle 0:00:23
timeout 0:04:10

```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
inspect ctiqbe	Enables CTIQBE application inspection.
service-policy	Applies a policy map to one or more interfaces.
show conn	Displays the connection state for different connection types.
timeout	Sets the maximum idle time duration for different protocols and session types.

show curpriv

To display the current user privileges, use the **show curpriv** command:

```
show curpriv
```

Syntax Description This command has no arguments or keywords.

Defaults No default behaviors or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	—	—	•
Privileged EXEC	•	•	—	—	•
Unprivileged	•	•	—	—	•

Release	Modification
7.0	Modified to conform to CLI guidelines.

Usage Guidelines The **show curpriv** command displays the current privilege level. Lower privilege level numbers indicate lower privilege levels.

Examples

These examples show output from the **show curpriv** command when a user named enable_15 is at different privilege levels. The username indicates the name that the user entered when the user logged in, P_PRIV indicates that the user has entered the **enable** command, and P_CONF indicates that the user has entered the **config terminal** command.

```
hostname(config)# show curpriv
Username : enable_15
Current privilege level : 15
Current Mode/s : P_PRIV P_CONF
hostname(config)# exit
```

```
hostname(config)# show curpriv
Username : enable_15
Current privilege level : 15
Current Mode/s : P_PRIV
hostname(config)# exit
```

```
hostname(config)# show curpriv
Username : enable_1
```

```
Current privilege level : 1
Current Mode/s : P_UNPR
hostname(config)#
```

Related Commands

Command	Description
clear configure privilege	Remove privilege command statements from the configuration.
show running-config privilege	Display privilege levels for commands.

show debug

To show the current debugging configuration, use the **show debug** command.

show debug [*command* [*keywords*]]

Syntax Description

command (Optional) Specifies the debug command whose current configuration you want to view. For each *command*, the syntax following *command* is identical to the syntax supported by the associated **debug** command. For example, valid *keywords* following **show debug aaa** are the same as the valid keywords for the **debug aaa** command. Thus, **show debug aaa** supports an **accounting** keyword, which allows you to specify that you want to see the debugging configuration for that portion of AAA debugging.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The valid *command* values follow. For information about valid syntax after *command*, see the entry for **debug command**, as applicable.



Note

The availability of each *command* value depends upon the command modes that support the applicable **debug** command.

- **aaa**
- **appfw**
- **arp**
- **asdm**
- **context**
- **crypto**
- **ctiqbe**

- ctm
- dhcpc
- dhcpd
- dhcprelay
- disk
- dns
- email
- entity
- fixup
- fover
- fsm
- ftp
- generic
- gtp
- h323
- http
- http-map
- icmp
- igmp
- ils
- imagemgr
- ipsec-over-tcp
- ipv6
- iua-proxy
- kerberos
- ldap
- mfib
- mgcp
- mrib
- ntdomain
- ntp
- ospf
- parser
- pim
- pix
- pptp
- radius
- rip

- **rtsp**
- **sdi**
- **sequence**
- **sip**
- **skinny**
- **smtp**
- **sqlnet**
- **ssh**
- **ssl**
- **sunrpc**
- **tacacs**
- **timestamps**
- **vpn-sessiondb**
- **webvpn**
- **xdmcp**

Examples

The following commands enable debugging for authentication, accounting, and Flash memory. The **show debug** command is used in three ways to demonstrate how you can use it to view all debugging configuration, debugging configuration for a specific feature, and even debugging configuration for a subset of a feature.

```
hostname# debug aaa authentication
debug aaa authentication enabled at level 1
hostname# debug aaa accounting
debug aaa accounting enabled at level 1
hostname# debug disk filesystem
debug disk filesystem enabled at level 1
hostname# show debug
debug aaa authentication enabled at level 1
debug aaa accounting enabled at level 1
debug disk filesystem enabled at level 1
hostname# show debug aaa
debug aaa authentication enabled at level 1
debug aaa authorization is disabled.
debug aaa accounting enabled at level 1
debug aaa internal is disabled.
debug aaa vpn is disabled.
hostname# show debug aaa accounting
debug aaa accounting enabled at level 1
hostname#
```

Related Commands

Command	Description
debug	See all debug commands.

show dhcpd

To view DHCP binding, state, and statistical information, use the **show dhcpd** command in privileged EXEC or global configuration mode.

show dhcpd {binding [*IP_address*] | state | statistics}

Syntax Description

binding	Displays binding information for a given server IP address and its associated client hardware address and lease length.
<i>IP_address</i>	Shows the binding information for the specified IP address.
state	Displays the state of the DHCP server, such as whether it is enabled in the current context and whether it is enabled on each of the interfaces.
statistics	Displays statistical information, such as the number of address pools, bindings, expired bindings, malformed messages, sent messages, and received messages.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If you include the optional IP address in the **show dhcpd binding** command, only the binding for that IP address is shown.

The **show dhcpd binding | state | statistics** commands are also available in global configuration mode.

Examples

The following is sample output from the **show dhcpd binding** command:

```
hostname# show dhcpd binding
IP Address Hardware Address Lease Expiration Type
10.0.1.100 0100.a0c9.868e.43 84985 seconds automatic
```

The following is sample output from the **show dhcpd state** command:

```
hostname# show dhcpd state
Context Not Configured for DHCP
Interface outside, Not Configured for DHCP
```

Interface inside, Not Configured for DHCP

The following is sample output from the **show dhcpd statistics** command:

```
hostname# show dhcpd statistics
```

```
DHCP UDP Unreachable Errors: 0
```

```
DHCP Other UDP Errors: 0
```

```
Address pools          1
```

```
Automatic bindings    1
```

```
Expired bindings      1
```

```
Malformed messages    0
```

```
Message                Received
```

```
BOOTREQUEST           0
```

```
DHCPDISCOVER          1
```

```
DHCPREQUEST           2
```

```
DHCPDECLINE           0
```

```
DHCPRELEASE           0
```

```
DHCPINFORM            0
```

```
Message                Sent
```

```
BOOTREPLY             0
```

```
DHCPOFFER             1
```

```
DHCPACK               1
```

```
DHCPNAK               1
```

Related Commands

Command	Description
clear configure dhcpd	Removes all DHCP server settings.
clear dhcpd	Clears the DHCP server bindings and statistic counters.
dhcpd lease	Defines the lease length for DHCP information granted to clients.
show running-config dhcpd	Displays the current DHCP server configuration.

show dhcprelay state

To view the state of the DHCP relay agent, use the **show dhcprelay state** command in privileged EXEC or global configuration mode.

show dhcprelay state

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines This command displays the DHCP relay agent state information for the current context and each interface.

Examples The following is sample output from the **show dhcprelay state** command:

```
hostname# show dhcprelay state
```

```
Context Configured as DHCP Relay
Interface outside, Not Configured for DHCP
Interface infrastructure, Configured for DHCP RELAY SERVER
Interface inside, Configured for DHCP RELAY
```

Related Commands	Command	Description
	show dhcpd	Displays DHCP server statistics and state information.
	show dhcprelay statistics	Displays the DHCP relay statistics.
	show running-config dhcprelay	Displays the current DHCP relay agent configuration.

show dhcprelay statistics

To display the DHCP relay statistics, use the **show dhcprelay statistics** command in privileged EXEC mode.

show dhcprelay statistics

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines The output of the **show dhcprelay statistics** command increments until you enter the **clear dhcprelay statistics** command.

Examples The following shows sample output for the **show dhcprelay statistics** command:

```
hostname# show dhcprelay statistics
```

```
DHCP UDP Unreachable Errors: 0
```

```
DHCP Other UDP Errors: 0
```

```
Packets Relayed
```

```
BOOTREQUEST          0
```

```
DHCPDISCOVER         7
```

```
DHCPREQUEST          3
```

```
DHCPDECLINE          0
```

```
DHCPRELEASE          0
```

```
DHCPINFORM           0
```

```
BOOTREPLY            0
```

```
DHCPOFFER            7
```

```
DHCPACK              3
```

```
DHCPNAK              0
```

```
FeralPix(config)#
```

Related Commands	Command	Description
	clear configure dhcprelay	Removes all DHCP relay agent settings.
	clear dhcprelay statistics	Clears the DHCP relay agent statistic counters.
	debug dhcprelay	Displays debug information for the DHCP relay agent.
	show dhcprelay state	Displays the state of the DHCP relay agent.
	show running-config dhcprelay	Displays the current DHCP relay agent configuration.

show disk

To display the contents of the Flash memory, use the **show disk** command in privileged EXEC mode. To view the Flash memory for a PIX security appliance, see the **show flash** command.

show disk[0 | 1] [filesys | all]

Syntax Description	0 1	Specifies the internal Flash memory (0, the default) or the external Flash memory (1).
	filesys	Shows information about the compact Flash card.
	all	Shows the contents of Flash memory plus the file system information,

Defaults Shows the internal Flash memory by default.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following is sample output from the **show disk** command:

```
hostname# show disk
-#- --length-- -----date/time----- path
11 1301      Feb 21 2005 18:01:34 test.cfg
12 1949      Feb 21 2005 20:13:36 test1.cfg
13 2551      Jan 06 2005 10:07:36 test2.cfg
14 609223    Jan 21 2005 07:14:18 test3.cfg
15 1619      Jul 16 2004 16:06:48 test4.cfg
16 3184      Aug 03 2004 07:07:00 old_running.cfg
17 4787      Mar 04 2005 12:32:18 test5.cfg
20 1792      Jan 21 2005 07:29:24 test6.cfg
21 7765184   Mar 07 2005 19:38:30 test7.cfg
22 1674      Nov 11 2004 02:47:52 test8.cfg
23 1863      Jan 21 2005 07:29:18 test9.cfg
24 1197      Jan 19 2005 08:17:48 test10.cfg
25 608554    Jan 13 2005 06:20:54 backupconfig.cfg
26 5124096   Feb 20 2005 08:49:28 cdisk1
27 5124096   Mar 01 2005 17:59:56 cdisk2
28 2074      Jan 13 2005 08:13:26 test11.cfg
29 5124096   Mar 07 2005 19:56:58 cdisk3
30 1276      Jan 28 2005 08:31:58 lead
31 7756788   Feb 24 2005 12:59:46 asdmfile.dbg
```

```

32 7579792    Mar 08 2005 11:06:56 asdmfile1.dbg
33 7764344    Mar 04 2005 12:17:46 asdmfile2.dbg
34 5124096    Feb 24 2005 11:50:50 cdisk4
35 15322      Mar 04 2005 12:30:24 hs_err.log

```

10170368 bytes available (52711424 bytes used)

The following is sample output from the **show disk filesystems** command:

```

hostname# show disk filesystems
***** Flash Card Geometry/Format Info *****

COMPACT FLASH CARD GEOMETRY
  Number of Heads:           4
  Number of Cylinders        978
  Sectors per Cylinder       32
  Sector Size                 512
  Total Sectors               125184

COMPACT FLASH CARD FORMAT
  Number of FAT Sectors       61
  Sectors Per Cluster         8
  Number of Clusters          15352
  Number of Data Sectors      122976
  Base Root Sector            123
  Base FAT Sector              1
  Base Data Sector             155

```

Related Commands

Command	Description
dir	Displays the directory contents.
show flash	Displays the contents of the internal Flash memory.

show dns-hosts

To show the DNS cache, use the **show dns-hosts** command in privileged EXEC mode. The DNS cache includes dynamically learned entries from a DNS server as well as manually entered name and IP addresses using the **name** command.

show dns-hosts

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	This command was introduced.

Usage Guidelines See the “[Examples](#)” section for a description of the display output.

Examples The following is sample output from the **show dns-hosts** command:

```
hostname# show dns-hosts
Host                Flags      Age  Type  Address(es)
ns2.example.com     (temp, OK) 0    IP    10.102.255.44
ns1.example.com     (temp, OK) 0    IP    192.168.241.185
snowmass.example.com (temp, OK) 0    IP    10.94.146.101
server.example.com  (temp, OK) 0    IP    10.94.146.80
```

Table 7-11 shows each field description.

Table 7-13 *show dns-hosts Fields*

Field	Description
Host	Shows the hostname.
Flags	Shows the entry status, as a combination of the following: - temp—This entry is temporary because it comes from a DNS server. The security appliance removes this entry after 72 hours of inactivity. - perm—This entry is permanent because it was added with the name command. - OK—This entry is valid. ??—This entry is suspect and needs to be revalidated. - EX—This entry is expired.
Age	Shows the number of hours since this entry was last referenced.
Type	Shows the type of DNS record; this value is always IP.
Address(es)	The IP addresses.

Related Commands

Command	Description
clear dns-hosts cache	Clears the DNS cache.
dns domain-lookup	Enables the security appliance to perform a name lookup.
dns name-server	Configures a DNS server address.
dns retries	Specifies the number of times to retry the list of DNS servers when the security appliance does not receive a response.
dns timeout	Specifies the amount of time to wait before trying the next DNS server.

show failover

To display information about the failover status of the unit, use the **show failover** command in privileged EXEC mode.

show failover [**group** *num* | **history** | **interface** | **state** | **statistics**]

Syntax Description

group	Displays the running state of the specified failover group.
history	Displays failover history. The failover history displays past failover state changes and the reason for the state change.
interface	Displays failover command and stateful link information.
<i>num</i>	Failover group number.
state	Displays the failover state of both failover units. The information displayed includes the primary or secondary status of the unit, the Active/Standby status of the unit, and, if a unit is in the failed state, the reason for the failure.
statistics	Displays transmit and receive packet count of failover command interface.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was modified. The output includes additional information.

Usage Guidelines

The **show failover** command displays the dynamic failover information, interface status, and Stateful Failover statistics. The Stateful Failover Logical Update Statistics output appears only when Stateful Failover is enabled. The “xerr” and “rerr” values do not indicate errors in failover, but rather the number of packet transmit or receive errors.

In the **show failover** command output, the fields have the following values:

- Stateful Obj has these values:
 - xmit—Indicates the number of packets transmitted.
 - xerr—Indicates the number of transmit errors.
 - rcv—Indicates the number of packets received.
 - rerr—Indicates the number of receive errors.

- Each row is for a particular object static count as follows:
 - General—Indicates the sum of all stateful objects.
 - sys cmd—Refers to the logical update system commands, such as **login** or **stay alive**.
 - up time—Indicates the value for the security appliance up time, which the active security appliance passes on to the standby security appliance.
 - RPC services—Remote Procedure Call connection information.
 - TCP conn—Dynamic TCP connection information.
 - UDP conn—Dynamic UDP connection information.
 - ARP tbl—Dynamic ARP table information.
 - Xlate_Timeout—Indicates connection translation timeout information.
 - VPN IKE upd—IKE connection information.
 - VPN IPSEC upd—IPSec connection information.
 - VPN CTCP upd—cTCP tunnel connection information.
 - VPN SDI upd—SDI AAA connection information.
 - VPN DHCP upd—Tunneled DHCP connection information.

If you do not enter a failover IP address, the **show failover** command displays 0.0.0.0 for the IP address, and monitoring of the interfaces remain in a “waiting” state. You must set a failover IP address for failover to work.

Table 7-14 describes the interface states for failover.

Table 7-14 *Failover Interface States*

State	Description
Normal	The interface is up and receiving hello packets from the corresponding interface on the peer unit.
Normal (Waiting)	The interface is up but has not yet received a hello packet from the corresponding interface on the peer unit. Verify that a standby IP address has been configured for the interface and that there is connectivity between the two interfaces.
Normal (Not-Monitored)	The interface is up but is not monitored by the failover process. The failure of an interface that is not monitored does not trigger failover.
No Link	The physical link is down.
No Link (Waiting)	The physical link is down and the interface has not yet received a hello packet from the corresponding interface on the peer unit. After restoring the link, verify that a standby IP address has been configured for the interface and that there is connectivity between the two interfaces.
No Link (Not-Monitored)	The physical link is down but is not monitored by the failover process. The failure of an interface that is not monitored does not trigger failover.
Link Down	The physical link is up, but the interface is administratively down.

Table 7-14 Failover Interface States (continued)

State	Description
Link Down (Waiting)	The physical link is up, but the interface is administratively down and the interface has not yet received a hello packet from the corresponding interface on the peer unit. After bringing the interface up (using the no shutdown command in interface configuration mode), verify that a standby IP address has been configured for the interface and that there is connectivity between the two interfaces.
Link Down (Not-Monitored)	The physical link is up, but the interface is administratively down but is not monitored by the failover process. The failure of an interface that is not monitored does not trigger failover.
Testing	The interface is in testing mode due to missed hello packets from the corresponding interface on the peer unit.
Failed	Interface testing has failed and the interface is marked as failed. If the interface failure causes the failover criteria to be met, then the interface failure causes a failover to the secondary unit or failover group.

In multiple configuration mode, only the **show failover** command is available in a security context; you cannot enter the optional keywords.

Examples

The following is sample output from the **show failover** command for Active/Standby Failover.

```
hostname# show failover

Failover On
Cable status: N/A - LAN-based failover enabled
Failover unit Primary
Failover LAN Interface: fover Ethernet2 (up)
Unit Poll frequency 1 seconds, holdtime 3 seconds
Interface Poll frequency 15 seconds
Interface Policy 1
Monitored Interfaces 2 of 250 maximum
failover replication http
Last Failover at: 22:44:03 UTC Dec 8 2004
    This host: Primary - Active
        Active time: 13434 (sec)
        Interface inside (10.130.9.3): Normal
        Interface outside (10.132.9.3): Normal
    Other host: Secondary - Standby Ready
        Active time: 0 (sec)
        Interface inside (10.130.9.4): Normal
        Interface outside (10.132.9.4): Normal

Stateful Failover Logical Update Statistics
Link : fover Ethernet2 (up)
Stateful Obj  xmit      xerr      rcv      rerr
General       0          0          0          0
sys cmd      1733        0       1733          0
up time       0          0          0          0
RPC services  0          0          0          0
TCP conn      6          0          0          0
UDP conn      0          0          0          0
ARP tbl      106         0          0          0
Xlate_Timeout 0          0          0          0
VPN IKE upd   15          0          0          0
```

```

VPN IPSEC upd   90          0          0          0
VPN CTCP upd    0          0          0          0
VPN SDI upd     0          0          0          0
VPN DHCP upd    0          0          0          0

```

```

Logical Update Queue Information
          Cur      Max      Total
Recv Q:   0        2      1733
Xmit Q:   0        2     15225

```

The following is sample output from the **show failover** command for Active/Active Failover.

```
hostname# show failover
```

```

Failover On
Failover unit Primary
Failover LAN Interface: third GigabitEthernet0/2 (up)
Unit Poll frequency 1 seconds, holdtime 15 seconds
Interface Poll frequency 4 seconds
Interface Policy 1
Monitored Interfaces 8 of 250 maximum
failover replication http
Group 1 last failover at: 13:40:18 UTC Dec 9 2004
Group 2 last failover at: 13:40:06 UTC Dec 9 2004

This host:      Primary
Group 1         State:          Active
                Active time:    2896 (sec)
Group 2         State:          Standby Ready
                Active time:    0 (sec)

slot 0: ASA-5530 hw/sw rev (1.0/7.0(0)79) status (Up Sys)
slot 1: SSM-IDS-20 hw/sw rev (1.0/5.0(0.1)S91(0.1)) status (Up)
admin Interface outside (10.132.8.5): Normal
admin Interface third (10.132.9.5): Normal
admin Interface inside (10.130.8.5): Normal
admin Interface fourth (10.130.9.5): Normal
ctx1 Interface outside (10.1.1.1): Normal
ctx1 Interface inside (10.2.2.1): Normal
ctx2 Interface outside (10.3.3.2): Normal
ctx2 Interface inside (10.4.4.2): Normal

Other host:     Secondary
Group 1         State:          Standby Ready
                Active time:    190 (sec)
Group 2         State:          Active
                Active time:    3322 (sec)

slot 0: ASA-5530 hw/sw rev (1.0/7.0(0)79) status (Up Sys)
slot 1: SSM-IDS-20 hw/sw rev (1.0/5.0(0.1)S91(0.1)) status (Up)
admin Interface outside (10.132.8.6): Normal
admin Interface third (10.132.9.6): Normal
admin Interface inside (10.130.8.6): Normal
admin Interface fourth (10.130.9.6): Normal
ctx1 Interface outside (10.1.1.2): Normal
ctx1 Interface inside (10.2.2.2): Normal
ctx2 Interface outside (10.3.3.1): Normal
ctx2 Interface inside (10.4.4.1): Normal

Stateful Failover Logical Update Statistics
Link : third GigabitEthernet0/2 (up)
Stateful Obj   xmit      xerr      rcv       rerr
General        0         0         0         0
sys cmd       380         0       380         0

```

show failover

```
up time          0          0          0          0
RPC services     0          0          0          0
TCP conn         1435         0          1450         0
UDP conn         0          0          0          0
ARP tbl          124         0          65          0
Xlate_Timeout    0          0          0          0
VPN IKE upd      15          0          0          0
VPN IPSEC upd    90          0          0          0
VPN CTCP upd     0          0          0          0
VPN SDI upd      0          0          0          0
VPN DHCP upd     0          0          0          0
```

```
Logical Update Queue Information
Cur      Max      Total
Recv Q:   0        1      1895
Xmit Q:   0        0      1940
```

Related Commands

Command	Description
show running-config failover	Displays the failover commands in the current configuration.

show file

To display information about the file system, use the **show file** command in privileged EXEC mode.

show file descriptors | system | information *filename*

Syntax Description

descriptors	Displays all open file descriptors.
information	Displays information about a specific file.
<i>filename</i>	Specifies the filename.
system	Displays the size, bytes available, type of media, flags, and prefix information about the disk file system.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to display the file system information:

```
hostname# show file descriptors
No open file descriptors
hostname# show file system
File Systems:
  Size(b)    Free(b)    Type  Flags  Prefixes
* 60985344   60973056   disk   rw     disk:
```

Related Commands

Command	Description
dir	Displays the directory contents.
pwd	Displays the current working directory.

show firewall

To show the current firewall mode (routed or transparent), use the **show firewall** command in privileged EXEC mode.

show firewall

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
7.0	This command was introduced.

Examples The following is sample output from the **show firewall** command:

```
hostname# show firewall
Firewall mode: Router
```

Command	Description
firewall transparent	Sets the firewall mode.
show mode	Shows the current context mode, either single or multiple.

show flash

To display the contents of the internal Flash memory, use the **show flash:** command in privileged EXEC mode.

show flash:



Note

In the ASA 5500 series, the **flash** keyword is aliased to **disk0**.

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example shows how to display the contents of the internal Flash memory:

```
hostname# show flash:
-#- --length-- -----date/time----- path
11 1301      Feb 21 2005 18:01:34 test.cfg
12 1949      Feb 21 2005 20:13:36 pepsi.cfg
13 2551      Jan 06 2005 10:07:36 Leo.cfg
14 609223    Jan 21 2005 07:14:18 rr.cfg
15 1619      Jul 16 2004 16:06:48 hackers.cfg
16 3184      Aug 03 2004 07:07:00 old_running.cfg
17 4787      Mar 04 2005 12:32:18 admin.cfg
20 1792      Jan 21 2005 07:29:24 Marketing.cfg
21 7765184   Mar 07 2005 19:38:30 asdmfile-RLK
22 1674      Nov 11 2004 02:47:52 potts.cfg
23 1863      Jan 21 2005 07:29:18 r.cfg
24 1197      Jan 19 2005 08:17:48 tst.cfg
25 608554    Jan 13 2005 06:20:54 500kconfig
26 5124096   Feb 20 2005 08:49:28 cdisk70102
27 5124096   Mar 01 2005 17:59:56 cdisk70104
28 2074      Jan 13 2005 08:13:26 negateACL
29 5124096   Mar 07 2005 19:56:58 cdisk70105
30 1276      Jan 28 2005 08:31:58 steel
31 7756788   Feb 24 2005 12:59:46 asdmfile.50074.dbg
```

show flash

```

32 7579792    Mar 08 2005 11:06:56 asdmfile.gusingh
33 7764344    Mar 04 2005 12:17:46 asdmfile.50075.dbg
34 5124096    Feb 24 2005 11:50:50 cdisk70103
35 15322      Mar 04 2005 12:30:24 hs_err_pid2240.log

```

10170368 bytes available (52711424 bytes used)

Related Commands

Command	Description
dir	Displays the directory contents.
show disk0	Displays the contents of the internal Flash memory.
show disk1	Displays the contents of the external Flash memory card.

show fragment

To display the operational data of the IP fragment reassembly module, enter the **show fragment** command in privileged EXEC mode.

show fragment [*interface*]

Syntax Description

interface (Optional) Specifies the security appliance interface.

Defaults

If an *interface* is not specified, the command applies to all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC mode	•	•	•	•	

Command History

Release	Modification
7.0	The command was separated into two commands, show fragment and show running-config fragment , to separate the configuration data from the operational data.

Examples

This example shows how to display the operational data of the IP fragment reassembly module:

```
hostname# show fragment
Interface: inside
  Size: 200, Chain: 24, Timeout: 5, Reassembly: virtual
  Queue: 0, Assembled: 0, Fail: 0, Overflow: 0
Interface: outside1
  Size: 200, Chain: 24, Timeout: 5, Reassembly: virtual
  Queue: 0, Assembled: 0, Fail: 0, Overflow: 0
Interface: test1
  Size: 200, Chain: 24, Timeout: 5, Reassembly: virtual
  Queue: 0, Assembled: 0, Fail: 0, Overflow: 0
Interface: test2
  Size: 200, Chain: 24, Timeout: 5, Reassembly: virtual
  Queue: 0, Assembled: 0, Fail: 0, Overflow: 0
```

Related Commands

Command	Description
clear configure fragment	Clears the IP fragment reassembly configuration and resets the defaults.
clear fragment	Clears the operational data of the IP fragment reassembly module.

Command	Description
fragment	Provides additional management of packet fragmentation and improves compatibility with NFS.
show running-config fragment	Displays the IP fragment reassembly configuration.

show gc

To display the garbage collection process statistics, use the **show gc** command in privileged EXEC mode.

show gc

Syntax Description This command has no arguments or keywords.

Defaults No default behaviors or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples The following is sample output from the **show gc** command:

```
hostname# show gc
```

```
Garbage collection process stats:
Total tcp conn delete response      :          0
Total udp conn delete response      :          0
Total number of zombie cleaned      :          0
Total number of embryonic conn cleaned :          0
Total error response                 :          0
Total queries generated              :          0
Total queries with conn present response :          0
Total number of sweeps               :         946
Total number of invalid vcid         :          0
Total number of zombie vcid          :          0
```

Related Commands

Command	Description
clear gc	Removes the garbage collection process statistics.

show h225

To display information for H.225 sessions established across the security appliance, use the **show h225** command in privileged EXEC mode.

show h225

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines The **show h225** command displays information for H.225 sessions established across the security appliance. Along with the **debug h323 h225 event**, **debug h323 h245 event**, and **show local-host** commands, this command is used for troubleshooting H.323 inspection engine issues.

Before using the **show h225**, **show h245**, or **show h323-ras** commands, we recommend that you configure the **pager** command. If there are a lot of session records and the **pager** command is not configured, it may take a while for the **show** output to reach its end. If there is an abnormally large number of connections, check that the sessions are timing out based on the default timeout values or the values set by you. If they are not, then there is a problem that needs to be investigated.

Examples The following is sample output from the **show h225** command:

```
hostname# show h225
Total H.323 Calls: 1
1 Concurrent Call(s) for
| Local: | 10.130.56.3/1040 | Foreign: 172.30.254.203/1720
| 1. CRV 9861
| Local: | 10.130.56.3/1040 | Foreign: 172.30.254.203/1720
0 Concurrent Call(s) for
| Local: | 10.130.56.4/1050 | Foreign: 172.30.254.205/1720
```

This output indicates that there is currently 1 active H.323 call going through the security appliance between the local endpoint 10.130.56.3 and foreign host 172.30.254.203, and for these particular endpoints, there is 1 concurrent call between them, with a CRV (Call Reference Value) for that call of 9861.

For the local endpoint 10.130.56.4 and foreign host 172.30.254.205, there are 0 concurrent Calls. This means that there is no active call between the endpoints even though the H.225 session still exists. This could happen if, at the time of the **show h225** command, the call has already ended but the H.225 session has not yet been deleted. Alternately, it could mean that the two endpoints still have a TCP connection opened between them because they set “maintainConnection” to TRUE, so the session is kept open until they set it to FALSE again, or until the session times out based on the H.225 timeout value in your configuration.

Related Commands

Commands	Description
debug h323	Enables the display of debug information for H.323.
inspect h323	Enables H.323 application inspection.
show h245	Displays information for H.245 sessions established across the security appliance by endpoints using slow start.
show h323-ras	Displays information for H.323 RAS sessions established across the security appliance.
timeout h225 h323	Configures idle time after which an H.225 signalling connection or an H.323 control connection will be closed.

show h245

To display information for H.245 sessions established across the security appliance by endpoints using slow start, use the **show h245** command in privileged EXEC mode.

show h245

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
Preexisting	This command was preexisting.

Command History

Usage Guidelines The **show h245** command displays information for H.245 sessions established across the security appliance by endpoints using slow start. (Slow start is when the two endpoints of a call open another TCP control channel for H.245. Fast start is where the H.245 messages are exchanged as part of the H.225 messages on the H.225 control channel.) Along with the **debug h323 h245 event**, **debug h323 h225 event**, and **show local-host** commands, this command is used for troubleshooting H.323 inspection engine issues.

Examples The following is sample output from the **show h245** command:

```
hostname# show h245
Total: 1
| LOCAL | TPKT | FOREIGN | TPKT
1 | 10.130.56.3/1041 | 0 | 172.30.254.203/1245 | 0
| MEDIA: LCN 258 Foreign 172.30.254.203 RTP 49608 RTCP 49609
| Local | 10.130.56.3 RTP 49608 RTCP 49609
| MEDIA: LCN 259 Foreign 172.30.254.203 RTP 49606 RTCP 49607
| Local | 10.130.56.3 RTP 49606 RTCP 49607
```

There is currently one H.245 control session active across the security appliance. The local endpoint is 10.130.56.3, and we are expecting the next packet from this endpoint to have a TPKT header because the TPKT value is 0. (The TKTP header is a 4-byte header preceding each H.225/H.245 message. It gives

the length of the message, including the 4-byte header.) The foreign host endpoint is 172.30.254.203, and we are expecting the next packet from this endpoint to have a TPKT header because the TPKT value is 0.

The media negotiated between these endpoints have a LCN (logical channel number) of 258 with the foreign RTP IP address/port pair of 172.30.254.203/49608 and a RTCP IP address/port of 172.30.254.203/49609 with a local RTP IP address/port pair of 10.130.56.3/49608 and a RTCP port of 49609.

The second LCN of 259 has a foreign RTP IP address/port pair of 172.30.254.203/49606 and a RTCP IP address/port pair of 172.30.254.203/49607 with a local RTP IP address/port pair of 10.130.56.3/49606 and RTCP port of 49607.

Related Commands

Commands	Description
debug h323	Enables the display of debug information for H.323.
inspect h323	Enables H.323 application inspection.
show h245	Displays information for H.245 sessions established across the security appliance by endpoints using slow start.
show h323-ras	Displays information for H.323 RAS sessions established across the security appliance.
timeout h225 h323	Configures idle time after which an H.225 signalling connection or an H.323 control connection will be closed.

show h323-ras

To display information for H.323 RAS sessions established across the security appliance between a gatekeeper and its H.323 endpoint, use the **show h323-ras** command in privileged EXEC mode.

show h323-ras

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines The **show h323-ras** command displays information for H.323 RAS sessions established across the security appliance between a gatekeeper and its H.323 endpoint. Along with the **debug h323 ras event** and **show local-host** commands, this command is used for troubleshooting H.323 RAS inspection engine issues.

The **show h323-ras** command displays connection information for troubleshooting H.323 inspection engine issues, and is described in the **inspect protocol h323 {h225 | ras}** command page.

Examples The following is sample output from the **show h323-ras** command:

```
hostname# show h323-ras
Total: 1
| GK | Caller
| 172.30.254.214 10.130.56.14
```

This output shows that there is one active registration between the gatekeeper 172.30.254.214 and its client 10.130.56.14.

Related Commands

Commands	Description
debug h323	Enables the display of debug information for H.323.
inspect h323	Enables H.323 application inspection.
show h245	Displays information for H.245 sessions established across the security appliance by endpoints using slow start.
show h323-ras	Displays information for H.323 RAS sessions established across the security appliance.
timeout h225 h323	Configures idle time after which an H.225 signalling connection or an H.323 control connection will be closed.

show history

To display the previously entered commands, use the **show history** command in user EXEC mode.

show history

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **show history** command lets you display previously entered commands. You can examine commands individually with the up and down arrows, enter **^p** to display previously entered lines, or enter **^n** to display the next line.

Examples

The following example shows how to display previously entered commands when you are in user EXEC mode:

```
hostname> show history
show history
help
show history
```

The following example shows how to display previously entered commands in privileged EXEC mode:

```
hostname# show history
show history
help
show history
enable
show history
```

This example shows how to display previously entered commands in global configuration mode:

```
hostname(config)# show history
show history
help
```

```
show history
enable
show history
config t
show history
```

Related Commands

Command	Description
help	Displays help information for the command specified.

show icmp

To display the ICMP configuration, use the **show icmp** command in privileged EXEC mode.

show icmp

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
Preexisting	This command was previously existing.

Usage Guidelines The **show icmp** command displays the ICMP configuration.

Examples The following example shows the ICMP configuration:

```
hostname# show icmp
```

clear configure icmp	Clears the ICMP configuration.
debug icmp	Enables the display of debug information for ICMP.
icmp	Configures access rules for ICMP traffic that terminates at a security appliance interface.
inspect icmp	Enables or disables the ICMP inspection engine.
timeout icmp	Configures the idle timeout for ICMP.

show idb

To display information about the status of interface descriptor blocks, use the **show idb** command in privileged EXEC mode.

show idb

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC	•	•	•	—	•

Release	Modification
7.0	This command was introduced.

Command History

Usage Guidelines IDBs are the internal data structure representing interface resources. See the “[Examples](#)” section for a description of the display output.

Examples The following is sample output from the **show idb** command:

```
hostname# show idb
Maximum number of Software IDBs 280. In use 23.

              HWIDBs    SWIDBs
              Active 6    21
              Inactive 1    2
              Total IDBs 7    23
Size each (bytes) 116    212
              Total bytes 812    4876

HWIDB# 1 0xbb68ebc Control0/0
HWIDB# 2 0xcd47d84 GigabitEthernet0/0
HWIDB# 3 0xcd4c1dc GigabitEthernet0/1
HWIDB# 4 0xcd5063c GigabitEthernet0/2
HWIDB# 5 0xcd54a9c GigabitEthernet0/3
HWIDB# 6 0xcd58f04 Management0/0

SWIDB# 1 0xbb68f54 0x01010001 Control0/0
SWIDB# 2 0xcd47e1c 0xffffffff GigabitEthernet0/0
SWIDB# 3 0xcd772b4 0xffffffff GigabitEthernet0/0.1
```

```

PEER IDB#  1 0x0d44109c 0xffffffff      3 GigabitEthernet0/0.1
PEER IDB#  2 0x0d2c0674 0x00020002     2 GigabitEthernet0/0.1
PEER IDB#  3 0x0d05a084 0x00010001     1 GigabitEthernet0/0.1
SWIDB#   4 0x0bb7501c 0xffffffff GigabitEthernet0/0.2
SWIDB#   5 0x0cd4c274 0xffffffff GigabitEthernet0/1
SWIDB#   6 0x0bb75704 0xffffffff GigabitEthernet0/1.1
PEER IDB#  1 0x0cf8686c 0x00020003     2 GigabitEthernet0/1.1
SWIDB#   7 0x0bb75dec 0xffffffff GigabitEthernet0/1.2
PEER IDB#  1 0x0d2c08ac 0xffffffff      2 GigabitEthernet0/1.2
SWIDB#   8 0x0bb764d4 0xffffffff GigabitEthernet0/1.3
PEER IDB#  1 0x0d441294 0x00030001     3 GigabitEthernet0/1.3
SWIDB#   9 0x0cd506d4 0x01010002 GigabitEthernet0/2
SWIDB#  10 0x0cd54b34 0xffffffff GigabitEthernet0/3
PEER IDB#  1 0x0d3291ec 0x00030002     3 GigabitEthernet0/3
PEER IDB#  2 0x0d2c0aa4 0x00020001     2 GigabitEthernet0/3
PEER IDB#  3 0x0d05a474 0x00010002     1 GigabitEthernet0/3
SWIDB#  11 0x0cd58f9c 0xffffffff Management0/0
PEER IDB#  1 0x0d05a65c 0x00010003     1 Management0/0

```

Table 7-11 shows each field description.

Table 7-15 *show idb stats Fields*

Field	Description
HWIDBs	Shows the statistics for all HWIDBs. HWIDBs are created for each hardware port in the system.
SWIDBs	Shows the statistics for all SWIDBs. SWIDBs are created for each main and subinterface in the system, and for each interface that is allocated to a context. Some other internal software modules also create IDBs.
HWIDB#	Specifies a hardware interface entry. The IDB sequence number, address, and interface name is displayed in each line.
SWIDB#	Specifies a software interface entry. The IDB sequence number, address, corresponding vPif id, and interface name are displayed in each line.
PEER IDB#	Specifies an interface allocated to a context. The IDB sequence number, address, corresponding vPif id, context id and interface name are displayed in each line.

Related Commands

Command	Description
interface	Configures an interface and enters interface configuration mode.
show interface	Displays the runtime status and statistics of interfaces.

show igmp groups

To display the multicast groups with receivers that are directly connected to the security appliance and that were learned through IGMP, use the **show igmp groups** command in privileged EXEC mode.

show igmp groups *[[reserved | group] [if_name] [detail]] | summary*

Syntax Description

detail	(Optional) Provides a detailed description of the sources.
<i>group</i>	(Optional) The address of an IGMP group. Including this optional argument limits the display to the specified group.
<i>if_name</i>	(Optional) Displays group information for the specified interface.
reserved	(Optional) Displays information about reserved groups.
summary	(Optional) Displays group joins summary information.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If you omit all optional arguments and keywords, the **show igmp groups** command displays all directly connected multicast groups by group address, interface type, and interface number.

Examples

The following is sample output from the **show igmp groups** command:

```
hostname#show igmp groups
```

```
IGMP Connected Group Membership
Group Address    Interface    Uptime    Expires    Last Reporter
224.1.1.1        inside      00:00:53  00:03:26  192.168.1.6
```

Related Commands

Command	Description
show igmp interface	Displays multicast information for an interface.

show igmp interface

To display multicast information for an interface, use the **show igmp interface** command in privileged EXEC mode.

show igmp interface [*if_name*]

Syntax Description	<i>if_name</i> (Optional) Displays IGMP group information for the selected interface.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was modified. The detail keyword was removed.

Usage Guidelines	If you omit the optional <i>if_name</i> argument, the show igmp interface command displays information about all interfaces.

Examples	The following is sample output from the show igmp interface command:

```
hostname# show igmp interface inside

inside is up, line protocol is up
Internet address is 192.168.37.6, subnet mask is 255.255.255.0
IGMP is enabled on interface
IGMP query interval is 60 seconds
Inbound IGMP access group is not set
Multicast routing is enabled on interface
Multicast TTL threshold is 0
Multicast designated router (DR) is 192.168.37.33
No multicast groups joined
```

Related Commands	Command	Description
	show igmp groups	Displays the multicast groups with receivers that are directly connected to the security appliance and that were learned through IGMP.

show igmp traffic

To display IGMP traffic statistics, use the **show igmp traffic** command in privileged EXEC mode.

show igmp traffic

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples The following is sample output from the **show igmp traffic** command:

```
hostname# show igmp traffic

IGMP Traffic Counters
Elapsed time since counters cleared: 00:02:30
Received      Sent
Valid IGMP Packets      3      6
Queries                  2      6
Reports                  1      0
Leaves                   0      0
Mtrace packets          0      0
DVMRP packets           0      0
PIM packets             0      0

Errors:
Malformed Packets       0
Martian source          0
Bad Checksums           0
```

Related Commands

Command	Description
clear igmp counters	Clears all IGMP statistic counters.
clear igmp traffic	Clear the IGMP traffic counters.

show interface

To view interface statistics, use the **show interface** command in user EXEC mode.

show interface [*physical_interface*[.*subinterface*]] | *mapped_name* | *interface_name*] [**stats** | **detail**]

Syntax Description

detail	(Optional) Shows detailed interface information, including the order in which the interface was added, the configured state, the actual state, and asymmetrical routing statistics, if enabled by the asr-group command. If you show all interfaces, then information about the internal interfaces for SSMs displays, if installed on the ASA 5500 series adaptive security appliance. The internal interface is not user-configurable, and the information is for debugging purposes only.
<i>interface_name</i>	(Optional) Identifies the interface name set with the nameif command.
<i>mapped_name</i>	(Optional) In multiple context mode, identifies the mapped name if it was assigned using the allocate-interface command.
<i>physical_interface</i>	(Optional) Identifies the interface ID, such as gigabitethernet0/1 . See the interface command for accepted values.
stats	(Default) Shows interface information and statistics. This keyword is the default, so this keyword is optional.
subinterface	(Optional) Identifies an integer between 1 and 4294967293 designating a logical subinterface.

Defaults

If you do not identify any options, this command shows basic statistics for all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC	•	•	•	•	•

Command History

Release	Modification
7.0(1)	This command was modified to include the new interface numbering scheme, and to add the stats keyword for clarity, and the detail keyword.
7.0(4)	This command added support for the 4GE SSM interfaces.

Usage Guidelines

If an interface is shared among contexts, and you enter this command within a context, the security appliance shows only statistics for the current context. When you enter this command in the system execution space for a physical interface, the security appliance shows the combined statistics for all contexts.

The number of statistics shown for subinterfaces is a subset of the number of statistics shown for a physical interface.

You cannot use the interface name in the system execution space, because the **nameif** command is only available within a context. Similarly, if you mapped the interface ID to a mapped name using the **allocate-interface** command, you can only use the mapped name in a context. If you set the **visible** keyword in the **allocate-interface** command, the security appliance shows the interface ID in the output of the **show interface** command.

See the “[Examples](#)” section for a description of the display output.

Examples

The following is sample output from the **show interface** command:

```
hostname> show interface
Interface GigabitEthernet0/0 "", is up, line protocol is up
  Hardware is i82546GB rev03, BW 1000 Mbps
    Auto-Duplex(Half-duplex), Auto-Speed(100 Mbps)
    Available but not configured via nameif
    MAC address 000f.f775.540e, MTU not set
    IP address unassigned
    752 packets input, 173435 bytes, 0 no buffer
    Received 752 broadcasts, 0 runts, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    752 L2 decode drops
    0 packets output, 0 bytes, 0 underruns
    0 output errors, 0 collisions
    0 late collisions, 0 deferred
    input queue (curr/max blocks): hardware (0/6) software (0/0)
    output queue (curr/max blocks): hardware (0/0) software (0/0)
Interface Management0/0 "intm00", is up, line protocol is up
  Hardware is i82557, BW 100 Mbps
    Auto-Duplex(Half-duplex), Auto-Speed(100 Mbps)
    MAC address 000f.f775.5412, MTU 1500
    IP address unassigned
    751 packets input, 170487 bytes, 0 no buffer
    Received 753 broadcasts, 0 runts, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    0 L2 decode drops
    0 packets output, 0 bytes, 0 underruns
    0 output errors, 0 collisions, 0 interface resets
    0 babbles, 0 late collisions, 0 deferred
    0 lost carrier, 0 no carrier
    input queue (curr/max blocks): hardware (128/128) software (0/1)
    output queue (curr/max blocks): hardware (0/0) software (0/0)
    Received 738 VLAN untagged packets, 156831 bytes
    Transmitted 0 VLAN untagged packets, 0 bytes
    Dropped 413 VLAN untagged packets
    Management-only interface. Blocked 0 through-the-device packets
      0 IPv4 packets originated from management network
      0 IPv4 packets destined to management network
      0 IPv6 packets originated from management network
      0 IPv6 packets destined to management network
Interface GigabitEthernet1/0 "intg10", is down, line protocol is down
  Hardware is VCS7380 rev01, BW 1000 Mbps
    Auto-Duplex, Auto-Speed
    Media-type configured as RJ45 connector
    MAC address 000b.fcff.b548, MTU 1500
    IP address 17.1.9.115, subnet mask 255.0.0.0
    0 packets input, 0 bytes, 0 no buffer
    Received 0 broadcasts, 0 runts, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
```

```

0 L2 decode drops
0 packets output, 0 bytes, 0 underruns
0 output errors, 0 collisions
0 late collisions, 0 deferred
0 rate limit drops
input queue (curr/max blocks): hardware (0/0) software (0/0)
output queue (curr/max blocks): hardware (0/0) software (0/0)
Received 0 VLAN untagged packets, 0 bytes
Transmitted 0 VLAN untagged packets, 0 bytes
Dropped 0 VLAN untagged packets
...

```

Table 7-11 shows each field description.

Table 7-16 *show interface Fields*

Field	Description
Interface <i>ID</i>	The interface ID. Within a context, the security appliance shows the mapped name (if configured), unless you set the allocate-interface command visible keyword.
<i>“interface_name”</i>	The interface name set with the nameif command. In the system execution space, this field is blank because you cannot set the name in the system. If you do not configure a name, the following message appears after the Hardware line: Available but not configured via nameif
<i>is state</i>	The administrative state, as follows: - up—The interface is not shut down. - administratively down—The interface is shut down with the shutdown command.
Line protocol <i>is state</i>	The line status, as follows: - up—A working cable is plugged into the network interface. - down—Either the cable is incorrect or not plugged into the interface connector.
VLAN identifier	For subinterfaces, the VLAN ID.
Hardware	The interface type, maximum bandwidth, duplex, and speed. When the link is down, the duplex and speed show the configured values. When the link is up, these fields show the configured values with the actual settings in parentheses. The following list describes the common hardware types: - i82542 - Intel PCI Fiber Gigabit card used on PIX platforms - i82543 - Intel PCI-X Fiber Gigabit card used on PIX platforms - i82546GB - Intel PCI-X Copper Gigabit used on ASA platforms - i82547GI - Intel CSA Copper Gigabit used as backplane on ASA platforms - i82557 - Intel PCI Copper Fast Ethernet used on ASA platforms - i82559 - Intel PCI Copper Fast Ethernet used on PIX platforms - VCS7380 - Vitesse Four Port Gigabit Switch used in SSM-4GE
Media-type	(For 4GE SSM interfaces only) Shows if the interface is set as RJ-45 or SFP.

Table 7-16 *show interface Fields (continued)*

Field	Description
<i>message area</i>	A message might be displayed in some circumstances. See the following examples: - In the system execution space, you might see the following message: Available for allocation to a context - If you do not configure a name, you see the following message: Available but not configured via nameif
MAC address	The interface MAC address.
MTU	The maximum size, in bytes, of packets allowed on this interface. If you do not set the interface name, this field shows “MTU not set.”
IP address	The interface IP address set using the ip address command or received from a DHCP server. In the system execution space, this field shows “IP address unassigned” because you cannot set the IP address in the system.
Subnet mask	The subnet mask for the IP address.
Packets input	The number of packets received on this interface.
Bytes	The number of bytes received on this interface.
No buffer	The number of received packets discarded because there was no buffer space in the main system. Compare this with the ignored count. Broadcast storms on Ethernet networks are often responsible for no input buffer events.
Received:	
Broadcasts	The number of broadcasts received.
Input errors	The number of total input errors, including the types listed below. Other input-related errors can also cause the input error count to increase, and some datagrams might have more than one error; therefore, this sum might exceed the number of errors listed for the types below.
Runts	The number of packets that are discarded because they are smaller than the minimum packet size, which is 64 bytes. Runts are usually caused by collisions. They might also be caused by poor wiring and electrical interference.
Giants	The number of packets that are discarded because they exceed the maximum packet size. For example, any Ethernet packet that is greater than 1518 bytes is considered a giant.
CRC	The number of Cyclical Redundancy Check errors. When a station sends a frame, it appends a CRC to the end of the frame. This CRC is generated from an algorithm based on the data in the frame. If the frame is altered between the source and destination, the security appliance notes that the CRC does not match. A high number of CRCs is usually the result of collisions or a station transmitting bad data.
Frame	The number of frame errors. Bad frames include packets with an incorrect length or bad frame checksums. This error is usually the result of collisions or a malfunctioning Ethernet device.
Overrun	The number of times that the security appliance was incapable of handing received data to a hardware buffer because the input rate exceeded the security appliance capability to handle the data.

Table 7-16 *show interface Fields (continued)*

Field	Description
Ignored	This field is not used. The value is always 0.
Abort	This field is not used. The value is always 0.
L2 decode drops	The number of packets dropped because the name is not configured (nameif command) or a frame with an invalid VLAN id is received.
Packets output	The number of packets sent on this interface.
Bytes	The number of bytes sent on this interface.
Underruns	The number of times that the transmitter ran faster than the security appliance could handle.
Output Errors	The number of frames not transmitted because the configured maximum number of collisions was exceeded. This counter should only increment during heavy network traffic.
Collisions	The number of messages retransmitted due to an Ethernet collision (single and multiple collisions). This usually occurs on an overextended LAN (Ethernet or transceiver cable too long, more than two repeaters between stations, or too many cascaded multiport transceivers). A packet that collides is counted only once by the output packets.
Interface resets	The number of times an interface has been reset. If an interface is unable to transmit for three seconds, the security appliance resets the interface to restart transmission. During this interval, connection state is maintained. An interface reset can also happen when an interface is looped back or shut down.
Babbles	Unused. ("babble" means that the transmitter has been on the interface longer than the time taken to transmit the largest frame.)
Late collisions	The number of frames that were not transmitted because a collision occurred outside the normal collision window. A late collision is a collision that is detected late in the transmission of the packet. Normally, these should never happen. When two Ethernet hosts try to talk at once, they should collide early in the packet and both back off, or the second host should see that the first one is talking and wait. If you get a late collision, a device is jumping in and trying to send the packet on the Ethernet while the security appliance is partly finished sending the packet. The security appliance does not resend the packet, because it may have freed the buffers that held the first part of the packet. This is not a real problem because networking protocols are designed to cope with collisions by resending packets. However, late collisions indicate a problem exists in your network. Common problems are large repeated networks and Ethernet networks running beyond the specification.
Deferred	The number of frames that were deferred before transmission due to activity on the link.
Rate limit drops	(For 4GE SSM interfaces only) The number of packets dropped if you configured the interface at non-Gigabit speeds and attempted to transmit more than 10 Mbps or 100 Mbps, depending on configuration..
Lost carrier	The number of times the carrier signal was lost during transmission.
No carrier	Unused.

Table 7-16 *show interface Fields (continued)*

Field	Description
Input queue (curr/max blocks):	The number of packets in the input queue, the current and the maximum.
Hardware	The number of packets in the hardware queue.
Software	The number of packets in the software queue.
Output queue (curr/max blocks):	The number of packets in the output queue, the current and the maximum.
Hardware	The number of packets in the hardware queue.
Software	The number of packets in the software queue.
Received [VLAN untagged] packets	For a physical interface, the number of untagged VLAN packets received, and the number of bytes. For a subinterface, the number of packets received that are tagged with the correct VLAN.
Transmitted [VLAN untagged] packets	For a physical interface, the number of untagged VLAN packets transmitted, and the number of bytes. For a subinterface, the number of packets transmitted that are tagged with the correct VLAN.
Dropped [VLAN untagged] packets	For a physical interface, the number of untagged VLAN packets dropped. For a subinterface, the number of packets dropped that are tagged with the correct VLAN.

The following is sample output from the **show interface detail** command. The following example shows detailed interface statistics for all interfaces, including the internal interfaces (if present for your platform) and asymmetrical routing statistics, if enabled by the **asr-group** command:

```

hostname> show interface detail
Interface GigabitEthernet0/0 "", is up, line protocol is up
  Hardware is i82546GB rev03, BW 1000 Mbps
    Auto-Duplex(Half-duplex), Auto-Speed(100 Mbps)
    Available but not configured via nameif
    MAC address 000f.f775.540e, MTU not set
    IP address unassigned
    752 packets input, 173435 bytes, 0 no buffer
    Received 752 broadcasts, 0 runts, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    752 L2 decode drops
    0 packets output, 0 bytes, 0 underruns
    0 output errors, 0 collisions
    0 late collisions, 0 deferred
    input queue (curr/max blocks): hardware (0/6) software (0/0)
    output queue (curr/max blocks): hardware (0/0) software (0/0)
    Control Point Interface States:
      Interface number is unassigned
Interface Internal-Data0/0 "", is up, line protocol is up
  Hardware is i82547GI rev00, BW 1000 Mbps
    (Full-duplex), (1000 Mbps)
    MAC address 0000.0001.0002, MTU not set
    IP address unassigned
    6 packets input, 1094 bytes, 0 no buffer
    Received 6 broadcasts, 0 runts, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort

```

```

0 L2 decode drops, 0 demux drops
0 packets output, 0 bytes, 0 underruns
0 output errors, 0 collisions
0 late collisions, 0 deferred
input queue (curr/max blocks): hardware (0/2) software (0/0)
output queue (curr/max blocks): hardware (0/0) software (0/0)
Control Point Interface States:
    Interface number is unassigned
Interface Management0/0 "intm00", is up, line protocol is up
Hardware is i82557, BW 100 Mbps
    Auto-Duplex(Half-duplex), Auto-Speed(100 Mbps)
    MAC address 000f.f775.5412, MTU 1500
    IP address unassigned
    751 packets input, 170487 bytes, 0 no buffer
    Received 753 broadcasts, 0 runts, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    0 L2 decode drops
    0 packets output, 0 bytes, 0 underruns
    0 output errors, 0 collisions, 0 interface resets
    0 babbles, 0 late collisions, 0 deferred
    0 lost carrier, 0 no carrier
    input queue (curr/max blocks): hardware (128/128) software (0/1)
    output queue (curr/max blocks): hardware (0/0) software (0/0)
    Received 738 VLAN untagged packets, 156831 bytes
    Transmitted 0 VLAN untagged packets, 0 bytes
    Dropped 413 VLAN untagged packets
    Management-only interface. Blocked 0 through-the-device packets
        0 IPv4 packets originated from management network
        0 IPv4 packets destined to management network
        0 IPv6 packets originated from management network
        0 IPv6 packets destined to management network
    Control Point Interface States:
        Interface number is 1
        Interface config status is active
        Interface state is active
Interface GigabitEthernet1/0 "intg10", is down, line protocol is down
Hardware is VCS7380 rev01, BW 1000 Mbps
    Auto-Duplex, Auto-Speed
    Media-type configured as RJ45 connector
    MAC address 000b.fcff.b548, MTU 1500
    IP address 17.1.9.115, subnet mask 255.0.0.0
    0 packets input, 0 bytes, 0 no buffer
    Received 0 broadcasts, 0 runts, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    0 L2 decode drops
    0 packets output, 0 bytes, 0 underruns
    0 output errors, 0 collisions
    0 late collisions, 0 deferred
    0 rate limit drops
    input queue (curr/max blocks): hardware (0/0) software (0/0)
    output queue (curr/max blocks): hardware (0/0) software (0/0)
    Received 0 VLAN untagged packets, 0 bytes
    Transmitted 0 VLAN untagged packets, 0 bytes
    Dropped 0 VLAN untagged packets
    Control Point Interface States:
        Interface number is 2
        Interface config status is active
        Interface state is not active
...

```


Table 7-16 shows each field description for the **show interface detail** command. See Table 7-11 for fields that are also shown for the **show interface** command.

Table 7-17 *show interface detail Fields*

Field	Description
Demux drops	(On Internal-Data interface only) The number of packets dropped because the security appliance was unable to demultiplex packets from SSM interfaces. SSM interfaces communicate with the native interfaces across the backplane, and packets from all SSM interfaces are multiplexed on the backplane.
Control Point Interface States:	
Interface number	A number used for debugging that indicates in what order this interface was created, starting with 0.
Interface config status	The administrative state, as follows: - active—The interface is not shut down. - not active—The interface is shut down with the shutdown command.
Interface state	The actual state of the interface. In most cases, this state matches the config status above. If you configure high availability, it is possible there can be a mismatch because the security appliance brings the interfaces up or down as needed.
Asymmetrical Routing Statistics:	
Received X1 packets	Number of ASR packets received on this interface.
Transmitted X2 packets	Number of ASR packets sent on this interfaces.
Dropped X3 packets	Number of ASR packets dropped on this interface. The packets might be dropped if the interface is down when trying to forward the packet.

Related Commands

Command	Description
allocate-interface	Assigns interfaces and subinterfaces to a security context.
clear interface	Clears counters for the show interface command.
interface	Configures an interface and enters interface configuration mode.
nameif	Sets the interface name.
show interface ip brief	Shows the interface IP address and status.

show interface ip brief

To view interface IP addresses and status, use the **show interface ip brief** command in privileged EXEC mode.

show interface [*physical_interface*[.*subinterface*] | *mapped_name* | *interface_name*] **ip brief**

Syntax Description

<i>interface_name</i>	(Optional) Identifies the interface name set with the nameif command.
<i>mapped_name</i>	(Optional) In multiple context mode, identifies the mapped name if it was assigned using the allocate-interface command.
<i>physical_interface</i>	(Optional) Identifies the interface ID, such as gigabitethernet0/1 . See the interface command for accepted values.
<i>subinterface</i>	(Optional) Identifies an integer between 1 and 4294967293 designating a logical subinterface.

Defaults

If you do not specify an interface, the security appliance shows all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

In multiple context mode, if you mapped the interface ID in the **allocate-interface** command, you can only specify the mapped name or the interface name in a context.

See the “[Examples](#)” section for a description of the display output.

Examples

The following is sample output from the **show ip brief** command:

```
hostname# show interface ip brief
Interface      IP-Address      OK? Method  Status        Protocol
Control0/0     127.0.1.1       YES CONFIG  up            up
GigabitEthernet0/0  209.165.200.226 YES CONFIG  up            up
GigabitEthernet0/1  unassigned      YES unset   administratively down down
GigabitEthernet0/2  10.1.1.50       YES manual  administratively down down
GigabitEthernet0/3  192.168.2.6     YES DHCP    administratively down down
Management0/0     209.165.201.3   YES CONFIG  up
```

Table 7-16 shows each field description.

Table 7-18 *show interface ip brief Fields*

Field	Description
Interface	The interface ID or, in multiple context mode, the mapped name if you configured it using the allocate-interface command. If you show all interfaces, then information about the internal interface for the AIP SSM displays, if installed on the ASA adaptive security appliance. The internal interface is not user-configurable, and the information is for debugging purposes only.
IP-Address	The interface IP address.
OK?	This column is not currently used, and always shows “Yes.”
Method	The method by which the interface received the IP address. Values include the following: - unset—No IP address configured. - manual—Configured the running configuration. - CONFIG—Loaded from the startup configuration. - DHCP—Received from a DHCP server.
Status	The administrative state, as follows: - up—The interface is not shut down. - administratively down—The interface is shut down with the shutdown command.
Protocol	The line status, as follows: - up—A working cable is plugged into the network interface. - down—Either the cable is incorrect or not plugged into the interface connector.

Related Commands

Command	Description
allocate-interface	Assigns interfaces and subinterfaces to a security context.
interface	Configures an interface and enters interface configuration mode.
ip address	Sets the IP address for the interface or sets the management IP address for a transparent firewall.
nameif	Sets the interface name.
show interface	Displays the runtime status and statistics of interfaces.

show inventory

To display information about all of the Cisco products installed in the networking device that are assigned a product identifier (PID), version identifier (VID), and serial number (SN), use the **show inventory** command in user EXEC or privileged EXEC mode. If a Cisco entity is not assigned a PID, that entity is not retrieved or displayed.

show inventory [**slot**]

Syntax Description	slot (Optional) Specifies the SSM slot number (the system is slot 0)

- Defaults**
- If you do not specify a slot to show inventory for:
- Show inventory information of all SSMs (including for power supply)

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History	Release	Modification
	7.0	Minor semantic changes.

Usage Guidelines

The **show inventory** command retrieves and displays inventory information about each Cisco product in the form of a UDI. The UDI is a combination of three separate data elements: a product identifier (PID), a version identifier (VID), and the serial number (SN).

The PID is the name by which the product can be ordered; it has been historically called the “Product Name” or “Part Number.” This is the identifier that one would use to order an exact replacement part.

The VID is the version of the product. Whenever a product has been revised, the VID will be incremented. The VID is incremented according to a rigorous process derived from Telcordia GR-209-CORE, an industry guideline that governs product change notices.

The SN is the vendor-unique serialization of the product. Each manufactured product will carry a unique serial number assigned at the factory, which cannot be changed in the field. This is the means by which to identify an individual, specific instance of a product.

The UDI refers to each product as an entity. Some entities, such as a chassis, will have subentities like slots. Each entity will display on a separate line in a logically ordered presentation that is arranged hierarchically by Cisco entities.

Use the **show inventory** command without options to display a list of Cisco entities installed in the networking device that are assigned a PID.

Examples

The following is sample output from the **show inventory** command without any keywords or arguments. This sample output displays a list of Cisco entities installed in a router that are assigned a PID.

```
ciscoasa# show inventory
Name:"Chassis", DESCR:"ASA 5540 Adaptive Security Appliance"
PID:ASA5540          , VID:V01 , SN:P3000000998

Name:"slot 1", DESCR:"ASA 5500 Series Security Services Module-20"
PID:ASA-SSM-20      , VID:V01 , SN:P0000000999

Name:"power supply", DESCR:"ASA 5500 Series 180W AC Power Supply"
PID:ASA-180W-PWR-AC , VID:V01 , SN:123456789AB

ciscoasa# show inventory 0
Name:"Chassis", DESCR:"ASA 5540 Adaptive Security Appliance"
PID:ASA5540          , VID:V01 , SN:P3000000998

ciscoasa# show inventory 1
Name:"slot 1", DESCR:"ASA 5500 Series Security Services Module-20"
PID:ASA-SSM-20      , VID:V01 , SN:P0000000999
```

[Table 7-18](#) describes the fields shown in the display.

Table 7-19 *show inventory Field Descriptions*

Field	Description
Name	Physical name (text string) assigned to the Cisco entity. For example, console or a simple component number (port or module number), such as “1,” depending on the physical component naming syntax of the device. Equivalent to the entPhysicalName MIB variable in RFC 2737.
DESCR	Physical description of the Cisco entity that characterizes the object. Equivalent to the entPhysicalDesc MIB variable in RFC 2737.
PID	Entity product identifier. Equivalent to the entPhysicalModelName MIB variable in RFC 2737.
VID	Entity version identifier. Equivalent to the entPhysicalHardwareRev MIB variable in RFC 2737.
SN	Entity serial number. Equivalent to the entPhysicalSerialNum MIB variable in RFC 2737.

Related Commands

Command	Description
show diag	Displays diagnostic information about the controller, interface processor, and port adapters for a networking device.
show tech-support	Displays general information about the router when it reports a problem.

show ip address

To view interface IP addresses or, for transparent mode, the management IP address, use the **show ip address** command in privileged EXEC mode.

show ip address [*physical_interface* [.*subinterface*] | *mapped_name* | *interface_name*]

Syntax Description

<i>interface_name</i>	(Optional) Identifies the interface name set with the nameif command.
<i>mapped_name</i>	(Optional) In multiple context mode, identifies the mapped name if it was assigned using the allocate-interface command.
<i>physical_interface</i>	(Optional) Identifies the interface ID, such as gigabitethernet0/1 . See the interface command for accepted values.
<i>subinterface</i>	(Optional) Identifies an integer between 1 and 4294967293 designating a logical subinterface.

Defaults

If you do not specify an interface, the security appliance shows all interface IP addresses.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

This command shows the primary IP addresses (called “System” in the display) for when you configure high availability as well as the current IP addresses. If the unit is active, then the system and current IP addresses match. If the unit is standby, then the current IP addresses show the standby addresses.

Examples

The following is sample output from the **show ip address** command:

```
hostname# show ip address
System IP Addresses:
Interface      Name      IP address      Subnet mask      Method
GigabitEthernet0/0  mgmt      10.7.12.100     255.255.255.0    CONFIG
GigabitEthernet0/1  inside    10.1.1.100       255.255.255.0    CONFIG
GigabitEthernet0/2.40  outside  209.165.201.2    255.255.255.224  DHCP
GigabitEthernet0/3    dmz       209.165.200.225  255.255.255.224  manual
Current IP Addresses:
Interface      Name      IP address      Subnet mask      Method
GigabitEthernet0/0  mgmt      10.7.12.100     255.255.255.0    CONFIG
```

```

GigabitEthernet0/1      inside      10.1.1.100      255.255.255.0      CONFIG
GigabitEthernet0/2.40   outside    209.165.201.2   255.255.255.224    DHCP
GigabitEthernet0/3      dmz        209.165.200.225 255.255.255.224    manual

```

Table 7-16 shows each field description.

Table 7-20 *show ip address Fields*

Field	Description
Interface	The interface ID or, in multiple context mode, the mapped name if you configured it using the allocate-interface command.
Name	The interface name set with the nameif command.
IP address	The interface IP address.
Subnet mask	The IP address subnet mask.
Method	The method by which the interface received the IP address. Values include the following: - unset—No IP address configured. - manual—Configured the running configuration. - CONFIG—Loaded from the startup configuration. - DHCP—Received from a DHCP server.

Related Commands

Command	Description
allocate-interface	Assigns interfaces and subinterfaces to a security context.
interface	Configures an interface and enters interface configuration mode.
nameif	Sets the interface name.
show interface	Displays the runtime status and statistics of interfaces.
show interface ip brief	Shows the interface IP address and status.

show ip address dhcp

To view detailed information about the DHCP lease or server for an interface, use the **show ip address dhcp** command in privileged EXEC mode.

```
show ip address {physical_interface[.subinterface] | mapped_name | interface_name} dhcp
                {lease | server}
```

Syntax Description

<i>interface_name</i>	Identifies the interface name set with the nameif command.
lease	Shows information about the DHCP lease.
<i>mapped_name</i>	In multiple context mode, identifies the mapped name if it was assigned using the allocate-interface command.
<i>physical_interface</i>	Identifies the interface ID, such as gigabitethernet0/1 . See the interface command for accepted values.
server	Shows information about the DHCP server.
<i>subinterface</i>	Identifies an integer between 1 and 4294967293 designating a logical subinterface.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
7.0	This command was changed to include the lease and server keywords to accommodate the new server functionality.

Usage Guidelines

See the “[Examples](#)” section for a description of the display output.

Examples

The following is sample output from the **show ip address dhcp lease** command:

```
hostname# show ip address outside dhcp lease
Temp IP Addr:209.165.201.57 for peer on interface:outside
Temp sub net mask:255.255.255.224
  DHCP Lease server:209.165.200.225, state:3 Bound
  DHCP Transaction id:0x4123
  Lease:259200 secs, Renewal:129600 secs, Rebind:226800 secs
  Temp default-gateway addr:209.165.201.1
```



```

Temp ip static route0: dest 10.9.0.0 router 10.7.12.255
Next timer fires after:111797 secs
Retry count:0, Client-ID:cisco-0000.0000.0000-outside
Proxy: TRUE Proxy Network: 10.1.1.1
Hostname: device1

```

Table 7-16 shows each field description.

Table 7-21 *show ip address dhcp lease Fields*

Field	Description
Temp IP Addr	The IP address assigned to the interface.
Temp sub net mask	The subnet mask assigned to the interface.
DHCP Lease server	The DHCP server address.
state	The state of the DHCP lease, as follows: • Initial—The initialization state, where the security appliance begins the process of acquiring a lease. This state is also shown when a lease ends or when a lease negotiation fails. • Selecting—The security appliance is waiting to receive DHCPOFFER messages from one or more DHCP servers, so it can choose one. • Requesting—The security appliance is waiting to hear back from the server to which it sent its request. • Purging—The security appliance is removing the lease because of the client has released the IP address or there was some other error. • Bound—The security appliance has a valid lease and is operating normally. • Renewing—The security appliance is trying to renew the lease. It regularly sends DHCPREQUEST messages to the current DHCP server, and waits for a reply. • Rebinding—The security appliance failed to renew the lease with the original server, and now sends DHCPREQUEST messages until it gets a reply from any server or the lease ends. • Holddown—The security appliance started the process to remove the lease. • Releasing—The security appliance sends release messages to the server indicating that the IP address is no longer needed.
DHCP transaction id	A random number chosen by the client, used by the client and server to associate the request messages.
Lease	The length of time, specified by the DHCP server, that the interface can use this IP address.
Renewal	The length of time until the interface automatically attempts to renew this lease.

Table 7-21 *show ip address dhcp lease Fields (continued)*

Field	Description
Rebind	The length of time until the security appliance attempts to rebind to a DHCP server. Rebinding occurs if the security appliance cannot communicate with the original DHCP server, and 87.5 percent of the lease time has expired. The security appliance then attempts to contact any available DHCP server by broadcasting DHCP requests.
Temp default-gateway addr	The default gateway address supplied by the DHCP server.
Temp ip static route0	The default static route.
Next timer fires after	The number of seconds until the internal timer triggers.
Retry count	If the security appliance is attempting to establish a lease, this field shows the number of times the security appliance tried sending a DHCP message. For example, if the security appliance is in the Selecting state, this value shows the number of times the security appliance sent discover messages. If the security appliance is in the Requesting state, this value shows the number of times the security appliance sent request messages.
Client-ID	The client ID used in all communication with the server.
Proxy	Specifies if this interface is a proxy DHCP client for VPN clients, True or False.
Proxy Network	The requested network.
Hostname	The client hostname.

The following is sample output from the **show ip address dhcp server** command:

```
hostname# show ip address outside dhcp server

DHCP server: ANY (255.255.255.255)
Leases:      0
Offers:      0      Requests: 0      Acks: 0      Naks: 0
Declines:    0      Releases: 0      Bad: 0

DHCP server: 40.7.12.6
Leases:      1
Offers:      1      Requests: 17     Acks: 17     Naks: 0
Declines:    0      Releases: 0      Bad: 0
DNS0: 171.69.161.23,  DNS1: 171.69.161.24
WINS0: 172.69.161.23,  WINS1: 172.69.161.23
Subnet: 255.255.0.0   DNS Domain: cisco.com
```

Table 7-21 shows each field description.

Table 7-22 *show ip address dhcp server Fields*

Field	Description
DHCP server	The DHCP server address from which this interface obtained a lease. The top entry ("ANY") is the default server and is always present.
Leases	The number of leases obtained from the server. For an interface, the number of leases is typically 1. If the server is providing address for an interface that is running proxy for VPN, there will be several leases.

Table 7-22 *show ip address dhcp server Fields (continued)*

Field	Description
Offers	The number of offers from the server.
Requests	The number of requests sent to the server.
Acks	The number of acknowledgements received from the server.
Naks	The number of negative acknowledgements received from the server.
Declines	The number of declines received from the server.
Releases	The number of releases sent to the server.
Bad	The number of bad packets received from the server.
DNS0	The primary DNS server address obtained from the DHCP server.
DNS1	The secondary DNS server address obtained from the DHCP server.
WINS0	The primary WINS server address obtained from the DHCP server.
WINS1	The secondary WINS server address obtained from the DHCP server.
Subnet	The subnet address obtained from the DHCP server.
DNS Domain	The domain obtained from the DHCP server.

Related Commands

Command	Description
interface	Configures an interface and enters interface configuration mode.
ip address dhcp	Sets the interface to obtain an IP address from a DHCP server.
nameif	Sets the interface name.
show interface ip brief	Shows the interface IP address and status.
show ip address	Displays the IP addresses of interfaces.

show ip audit count

To show the number of signature matches when you apply an audit policy to an interface, use the **show ip audit count** command in privileged EXEC mode.

show ip audit count [**global** | **interface** *interface_name*]

Syntax Description

global	(Default) Shows the number of matches for all interfaces.
interface <i>interface_name</i>	(Optional) Shows the number of matches for the specified interface.

Defaults

If you do not specify a keyword, this command shows the matches for all interfaces (**global**).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To create an audit policy, use the **ip audit name** command, and to apply the policy, use the **ip audit interface** command.

Examples

The following is sample output from the **show ip audit count** command:

```
hostname# show ip audit count
IP AUDIT GLOBAL COUNTERS

1000 I Bad IP Options List          0
1001 I Record Packet Route         0
1002 I Timestamp                   0
1003 I Provide s,c,h,tcc           0
1004 I Loose Source Route           0
1005 I SATNET ID                   0
1006 I Strict Source Route          0
1100 A IP Fragment Attack           0
1102 A Impossible IP Packet        0
1103 A IP Teardrop                 0
2000 I ICMP Echo Reply              0
2001 I ICMP Unreachable             0
2002 I ICMP Source Quench          0
2003 I ICMP Redirect                0
```

```

2004 I ICMP Echo Request          10
2005 I ICMP Time Exceed           0
2006 I ICMP Parameter Problem     0
2007 I ICMP Time Request          0
2008 I ICMP Time Reply            0
2009 I ICMP Info Request          0
2010 I ICMP Info Reply            0
2011 I ICMP Address Mask Request  0
2012 I ICMP Address Mask Reply    0
2150 A Fragmented ICMP           0
2151 A Large ICMP                 0
2154 A Ping of Death              0
3040 A TCP No Flags               0
3041 A TCP SYN & FIN Flags Only   0
3042 A TCP FIN Flag Only          0
3153 A FTP Improper Address        0
3154 A FTP Improper Port          0
4050 A Bomb                       0
4051 A Snork                      0
4052 A Chargen                    0
6050 A DNS Host Info              0
6051 A DNS Zone Xfer              0
6052 A DNS Zone Xfer High Port    0
6053 A DNS All Records            0
6100 I RPC Port Registration      0
6101 I RPC Port Unregistration    0
6102 I RPC Dump                   0
6103 A Proxied RPC                0
6150 I ypserv Portmap Request     0
6151 I ypbind Portmap Request     0
6152 I yppasswdd Portmap Request  0
6153 I ypuddated Portmap Request  0
6154 I ypxfrd Portmap Request     0
6155 I mountd Portmap Request     0
6175 I rexd Portmap Request       0
6180 I rexd Attempt               0
6190 A statd Buffer Overflow      0

```

```

IP AUDIT INTERFACE COUNTERS: inside
...

```

Related Commands

Command	Description
clear ip audit count	Clears the count of signature matches for an audit policy.
ip audit interface	Assigns an audit policy to an interface.
ip audit name	Creates a named audit policy that identifies the actions to take when a packet matches an attack signature or an informational signature.
show running-config ip audit attack	Shows the configuration for the ip audit attack command.

show ip verify statistics

To show the number of packets dropped because of the Unicast RPF feature, use the **show ip verify statistics** command in privileged EXEC mode. Use the **ip verify reverse-path** command to enable Unicast RPF.

show ip verify statistics [**interface** *interface_name*]

Syntax Description

interface (Optional) Shows statistics for the specified interface.
interface_name

Defaults

This command shows statistics for all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following is sample output from the **show ip verify statistics** command:

```
hostname# show ip verify statistics
interface outside: 2 unicast rpf drops
interface inside: 1 unicast rpf drops
interface intf2: 3 unicast rpf drops
```

Related Commands

Command	Description
clear configure ip verify reverse-path	Clears the ip verify reverse-path configuration.
clear ip verify statistics	Clears the Unicast RPF statistics.
ip verify reverse-path	Enables the Unicast Reverse Path Forwarding feature to prevent IP spoofing.
show running-config ip verify reverse-path	Shows the ip verify reverse-path configuration.

show ipsec sa

To display a list of IPsec SAs, use the **show ipsec sa** command in global configuration mode or privileged EXEC mode. You can also use the alternate form of this command: **show crypto ipsec sa**.

show ipsec sa [**entry** | **identity** | **map** *map-name* | **peer** *peer-addr*] [**detail**]

Syntax Description

detail	(Optional) Displays detailed error information on what is displayed.
entry	(Optional) Displays IPsec SAs sorted by peer address
identity	(Optional) Displays IPsec SAs for sorted by identity, not including ESPs. This is a condensed form.
map <i>map-name</i>	(Optional) Displays IPsec SAs for the specified crypto map.
peer <i>peer-addr</i>	(Optional) Displays IPsec SAs for specified peer IP addresses.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following example, entered in global configuration mode, displays IPsec SAs.

```
hostname(config)# show ipsec sa
interface: outside2
  Crypto map tag: def, local addr: 10.132.0.17

  local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
  remote ident (addr/mask/prot/port): (172.20.0.21/255.255.255.255/0/0)
  current_peer: 172.20.0.21
  dynamic allocated peer ip: 10.135.1.5

  #pkts encaps: 0, #pkts encrypt: 0, #pkts digest: 0
  #pkts decaps: 1145, #pkts decrypt: 1145, #pkts verify: 1145
  #pkts compressed: 0, #pkts decompressed: 0
  #pkts not compressed: 0, #pkts comp failed: 0, #pkts decomp failed: 0
  #send errors: 0, #recv errors: 0

  local crypto endpt.: 10.132.0.17, remote crypto endpt.: 172.20.0.21
```

```

path mtu 1500, ipsec overhead 60, media mtu 1500
current outbound spi: DC15BF68

inbound esp sas:
  spi: 0x1E8246FC (511854332)
    transform: esp-3des esp-md5-hmac
    in use settings ={RA, Tunnel, }
    slot: 0, conn_id: 3, crypto-map: def
    sa timing: remaining key lifetime (sec): 548
    IV size: 8 bytes
    replay detection support: Y
outbound esp sas:
  spi: 0xDC15BF68 (3692412776)
    transform: esp-3des esp-md5-hmac
    in use settings ={RA, Tunnel, }
    slot: 0, conn_id: 3, crypto-map: def
    sa timing: remaining key lifetime (sec): 548
    IV size: 8 bytes
    replay detection support: Y

Crypto map tag: def, local addr: 10.132.0.17

  local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
hostname(config)#

```

The following example, entered in global configuration mode, displays IPSec SAs for a crypto map named def.

```

hostname(config)# show ipsec sa map def
cryptomap: def
  Crypto map tag: def, local addr: 172.20.0.17

    local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
    remote ident (addr/mask/prot/port): (10.132.0.21/255.255.255.255/0/0)
    current_peer: 10.132.0.21
    dynamic allocated peer ip: 90.135.1.5

    #pkts encaps: 0, #pkts encrypt: 0, #pkts digest: 0
    #pkts decaps: 1146, #pkts decrypt: 1146, #pkts verify: 1146
    #pkts compressed: 0, #pkts decompressed: 0
    #pkts not compressed: 0, #pkts comp failed: 0, #pkts decomp failed: 0
    #send errors: 0, #recv errors: 0

    local crypto endpt.: 172.20.0.17, remote crypto endpt.: 10.132.0.21

    path mtu 1500, ipsec overhead 60, media mtu 1500
    current outbound spi: DC15BF68

inbound esp sas:
  spi: 0x1E8246FC (511854332)
    transform: esp-3des esp-md5-hmac
    in use settings ={RA, Tunnel, }
    slot: 0, conn_id: 3, crypto-map: def
    sa timing: remaining key lifetime (sec): 480
    IV size: 8 bytes
    replay detection support: Y
outbound esp sas:
  spi: 0xDC15BF68 (3692412776)
    transform: esp-3des esp-md5-hmac
    in use settings ={RA, Tunnel, }
    slot: 0, conn_id: 3, crypto-map: def
    sa timing: remaining key lifetime (sec): 480
    IV size: 8 bytes
    replay detection support: Y

```



```

Crypto map tag: def, local addr: 172.20.0.17

local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
remote ident (addr/mask/prot/port): (192.168.132.0/255.255.255.0/0/0)
current_peer: 10.135.1.8
dynamic allocated peer ip: 0.0.0.0

#pkts encaps: 73672, #pkts encrypt: 73672, #pkts digest: 73672
#pkts decaps: 78824, #pkts decrypt: 78824, #pkts verify: 78824
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 73672, #pkts comp failed: 0, #pkts decomp failed: 0
#send errors: 0, #recv errors: 0

local crypto endpt.: 172.20.0.17, remote crypto endpt.: 10.135.1.8

path mtu 1500, ipsec overhead 60, media mtu 1500
current outbound spi: 3B6F6A35

inbound esp sas:
  spi: 0xB32CF0BD (3006066877)
    transform: esp-3des esp-md5-hmac
    in use settings = {RA, Tunnel, }
    slot: 0, conn_id: 4, crypto-map: def
    sa timing: remaining key lifetime (sec): 263
    IV size: 8 bytes
    replay detection support: Y
outbound esp sas:
  spi: 0x3B6F6A35 (997157429)
    transform: esp-3des esp-md5-hmac
    in use settings = {RA, Tunnel, }
    slot: 0, conn_id: 4, crypto-map: def
    sa timing: remaining key lifetime (sec): 263
    IV size: 8 bytes
    replay detection support: Y
hostname(config)#

```

The following example, entered in global configuration mode, shows IPSec SAs for the keyword **entry**.

```

hostname(config)# show ipsec sa entry
peer address: 10.132.0.21
Crypto map tag: def, local addr: 172.20.0.17

local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
remote ident (addr/mask/prot/port): (10.132.0.21/255.255.255.0/0/0)
current_peer: 10.132.0.21
dynamic allocated peer ip: 90.135.1.5

#pkts encaps: 0, #pkts encrypt: 0, #pkts digest: 0
#pkts decaps: 1147, #pkts decrypt: 1147, #pkts verify: 1147
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts comp failed: 0, #pkts decomp failed: 0
#send errors: 0, #recv errors: 0

local crypto endpt.: 172.20.0.17, remote crypto endpt.: 10.132.0.21

path mtu 1500, ipsec overhead 60, media mtu 1500
current outbound spi: DC15BF68

inbound esp sas:
  spi: 0x1E8246FC (511854332)
    transform: esp-3des esp-md5-hmac
    in use settings = {RA, Tunnel, }
    slot: 0, conn_id: 3, crypto-map: def

```

```

sa timing: remaining key lifetime (sec): 429
IV size: 8 bytes
replay detection support: Y
outbound esp sas:
  spi: 0xDC15BF68 (3692412776)
    transform: esp-3des esp-md5-hmac
    in use settings = {RA, Tunnel, }
    slot: 0, conn_id: 3, crypto-map: def
    sa timing: remaining key lifetime (sec): 429
    IV size: 8 bytes
    replay detection support: Y

peer address: 10.135.1.8
Crypto map tag: def, local addr: 172.20.0.17

local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
remote ident (addr/mask/prot/port): (192.168.132.0/255.255.255.0/0/0)
current_peer: 10.135.1.8
dynamic allocated peer ip: 0.0.0.0

#pkts encaps: 73723, #pkts encrypt: 73723, #pkts digest: 73723
#pkts decaps: 78878, #pkts decrypt: 78878, #pkts verify: 78878
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 73723, #pkts comp failed: 0, #pkts decomp failed: 0
#send errors: 0, #recv errors: 0

local crypto endpt.: 172.20.0.17, remote crypto endpt.: 10.135.1.8

path mtu 1500, ipsec overhead 60, media mtu 1500
current outbound spi: 3B6F6A35

inbound esp sas:
  spi: 0xB32CF0BD (3006066877)
    transform: esp-3des esp-md5-hmac
    in use settings = {RA, Tunnel, }
    slot: 0, conn_id: 4, crypto-map: def
    sa timing: remaining key lifetime (sec): 212
    IV size: 8 bytes
    replay detection support: Y
outbound esp sas:
  spi: 0x3B6F6A35 (997157429)
    transform: esp-3des esp-md5-hmac
    in use settings = {RA, Tunnel, }
    slot: 0, conn_id: 4, crypto-map: def
    sa timing: remaining key lifetime (sec): 212
    IV size: 8 bytes
    replay detection support: Y
hostname(config)#

```

The following example, entered in global configuration mode, shows IPSec SAs with the keywords **entry detail**.

```

hostname(config)# show ipsec sa entry detail
peer address: 10.132.0.21
Crypto map tag: def, local addr: 172.20.0.17

local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
remote ident (addr/mask/prot/port): (10.132.0.21/255.255.255.255/0/0)
current_peer: 10.132.0.21
dynamic allocated peer ip: 90.135.1.5

#pkts encaps: 0, #pkts encrypt: 0, #pkts digest: 0
#pkts decaps: 1148, #pkts decrypt: 1148, #pkts verify: 1148
#pkts compressed: 0, #pkts decompressed: 0

```

```

#pkts not compressed: 0, #pkts comp failed: 0, #pkts decomp failed: 0
#pkts no sa (send): 0, #pkts invalid sa (rcv): 0
#pkts encaps failed (send): 0, #pkts decaps failed (rcv): 0
#pkts invalid prot (rcv): 0, #pkts verify failed: 0
#pkts invalid identity (rcv): 0, #pkts invalid len (rcv): 0
#pkts replay rollover (send): 0, #pkts replay rollover (rcv): 0
#pkts replay failed (rcv): 0
#pkts internal err (send): 0, #pkts internal err (rcv): 0

local crypto endpt.: 172.20.0.17, remote crypto endpt.: 10.132.0.21

path mtu 1500, ipsec overhead 60, media mtu 1500
current outbound spi: DC15BF68

inbound esp sas:
  spi: 0x1E8246FC (511854332)
    transform: esp-3des esp-md5-hmac
    in use settings = {RA, Tunnel, }
    slot: 0, conn_id: 3, crypto-map: def
    sa timing: remaining key lifetime (sec): 322
    IV size: 8 bytes
    replay detection support: Y
outbound esp sas:
  spi: 0xDC15BF68 (3692412776)
    transform: esp-3des esp-md5-hmac
    in use settings = {RA, Tunnel, }
    slot: 0, conn_id: 3, crypto-map: def
    sa timing: remaining key lifetime (sec): 322
    IV size: 8 bytes
    replay detection support: Y

peer address: 10.135.1.8
Crypto map tag: def, local addr: 172.20.0.17

local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
remote ident (addr/mask/prot/port): (192.168.132.0/255.255.255.0/0/0)
current_peer: 10.135.1.8
dynamic allocated peer ip: 0.0.0.0

#pkts encaps: 73831, #pkts encrypt: 73831, #pkts digest: 73831
#pkts decaps: 78989, #pkts decrypt: 78989, #pkts verify: 78989
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 73831, #pkts comp failed: 0, #pkts decomp failed: 0
#pkts no sa (send): 0, #pkts invalid sa (rcv): 0
#pkts encaps failed (send): 0, #pkts decaps failed (rcv): 0
#pkts invalid prot (rcv): 0, #pkts verify failed: 0
#pkts invalid identity (rcv): 0, #pkts invalid len (rcv): 0
#pkts replay rollover (send): 0, #pkts replay rollover (rcv): 0
#pkts replay failed (rcv): 0
#pkts internal err (send): 0, #pkts internal err (rcv): 0

local crypto endpt.: 172.20.0.17, remote crypto endpt.: 10.135.1.8

path mtu 1500, ipsec overhead 60, media mtu 1500
current outbound spi: 3B6F6A35

inbound esp sas:
  spi: 0xB32CF0BD (3006066877)
    transform: esp-3des esp-md5-hmac
    in use settings = {RA, Tunnel, }
    slot: 0, conn_id: 4, crypto-map: def
    sa timing: remaining key lifetime (sec): 104
    IV size: 8 bytes
    replay detection support: Y

```

```

outbound esp sas:
  spi: 0x3B6F6A35 (997157429)
    transform: esp-3des esp-md5-hmac
    in use settings = {RA, Tunnel, }
    slot: 0, conn_id: 4, crypto-map: def
    sa timing: remaining key lifetime (sec): 104
    IV size: 8 bytes
    replay detection support: Y
hostname(config)#

```

The following example shows IPSec SAs with the keyword **identity**.

```

hostname(config)# show ipsec sa identity
interface: outside2
  Crypto map tag: def, local addr: 172.20.0.17

    local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
    remote ident (addr/mask/prot/port): (10.132.0.21/255.255.255.255/0/0)
    current_peer: 10.132.0.21
    dynamic allocated peer ip: 90.135.1.5

    #pkts encaps: 0, #pkts encrypt: 0, #pkts digest: 0
    #pkts decaps: 1147, #pkts decrypt: 1147, #pkts verify: 1147
    #pkts compressed: 0, #pkts decompressed: 0
    #pkts not compressed: 0, #pkts comp failed: 0, #pkts decomp failed: 0
    #send errors: 0, #recv errors: 0

    local crypto endpt.: 172.20.0.17, remote crypto endpt.: 10.132.0.21

    path mtu 1500, ipsec overhead 60, media mtu 1500
    current outbound spi: DC15BF68

  Crypto map tag: def, local addr: 172.20.0.17

    local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
    remote ident (addr/mask/prot/port): (192.168.132.0/255.255.255.0/0/0)
    current_peer: 10.135.1.8
    dynamic allocated peer ip: 0.0.0.0

    #pkts encaps: 73756, #pkts encrypt: 73756, #pkts digest: 73756
    #pkts decaps: 78911, #pkts decrypt: 78911, #pkts verify: 78911
    #pkts compressed: 0, #pkts decompressed: 0
    #pkts not compressed: 73756, #pkts comp failed: 0, #pkts decomp failed: 0
    #send errors: 0, #recv errors: 0

    local crypto endpt.: 172.20.0.17, remote crypto endpt.: 10.135.1.8

    path mtu 1500, ipsec overhead 60, media mtu 1500
    current outbound spi: 3B6F6A35

```

The following example shows IPSec SAs with the keywords **identity** and **detail**.

```

hostname(config)# show ipsec sa identity detail
interface: outside2
  Crypto map tag: def, local addr: 172.20.0.17

    local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
    remote ident (addr/mask/prot/port): (10.132.0.21/255.255.255.255/0/0)
    current_peer: 10.132.0.21
    dynamic allocated peer ip: 90.135.1.5

    #pkts encaps: 0, #pkts encrypt: 0, #pkts digest: 0
    #pkts decaps: 1147, #pkts decrypt: 1147, #pkts verify: 1147
    #pkts compressed: 0, #pkts decompressed: 0

```

```

#pkts not compressed: 0, #pkts comp failed: 0, #pkts decomp failed: 0
#pkts no sa (send): 0, #pkts invalid sa (rcv): 0
#pkts encaps failed (send): 0, #pkts decaps failed (rcv): 0
#pkts invalid prot (rcv): 0, #pkts verify failed: 0
#pkts invalid identity (rcv): 0, #pkts invalid len (rcv): 0
#pkts replay rollover (send): 0, #pkts replay rollover (rcv): 0
#pkts replay failed (rcv): 0
#pkts internal err (send): 0, #pkts internal err (rcv): 0

local crypto endpt.: 172.20.0.17, remote crypto endpt.: 10.132.0.21

path mtu 1500, ipsec overhead 60, media mtu 1500
current outbound spi: DC15BF68

Crypto map tag: def, local addr: 172.20.0.17

local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
remote ident (addr/mask/prot/port): (192.168.132.0/255.255.255.0/0/0)
current_peer: 10.135.1.8
dynamic allocated peer ip: 0.0.0.0

#pkts encaps: 73771, #pkts encrypt: 73771, #pkts digest: 73771
#pkts decaps: 78926, #pkts decrypt: 78926, #pkts verify: 78926
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 73771, #pkts comp failed: 0, #pkts decomp failed: 0
#pkts no sa (send): 0, #pkts invalid sa (rcv): 0
#pkts encaps failed (send): 0, #pkts decaps failed (rcv): 0
#pkts invalid prot (rcv): 0, #pkts verify failed: 0
#pkts invalid identity (rcv): 0, #pkts invalid len (rcv): 0
#pkts replay rollover (send): 0, #pkts replay rollover (rcv): 0
#pkts replay failed (rcv): 0
#pkts internal err (send): 0, #pkts internal err (rcv): 0

local crypto endpt.: 172.20.0.17, remote crypto endpt.: 10.135.1.8

path mtu 1500, ipsec overhead 60, media mtu 1500
current outbound spi: 3B6F6A35

```

Related Commands

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.
isakmp enable	Enables ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance.
show running-config isakmp	Displays all the active ISAKMP configuration.

show ipsec sa summary

To display a summary of IPSec SAs, use the **show ipsec sa summary** command in global configuration mode or privileged EXEC mode.

show ipsec sa summary

Syntax Description This command has no arguments or variables.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Release	Modification
7.0	This command was introduced.

Command History

Examples The following example, entered in global configuration mode, displays a summary of IPSec SAs by the following connection types:

- IPSec
- IPSec over UDP
- IPSec over NAT-T
- IPSec over TCP
- IPSec VPN load balancing

```
hostname(config)# show ipsec sa summary
```

```
Current IPSec SA's:      Peak IPSec SA's:
IPSec                   :    2      Peak Concurrent SA   :   14
IPSec over UDP          :    2      Peak Concurrent L2L  :    0
IPSec over NAT-T        :    4      Peak Concurrent RA   :   14
IPSec over TCP           :    6
IPSec VPN LB            :    0
Total                   :   14
hostname(config)#
```

Related Commands

Command	Description
clear ipsec sa	Removes IPSec SAs entirely or based on specific parameters.
show ipsec sa	Displays a list of IPSec SAs.
show ipsec stats	Displays a list of IPSec statistics.

show ipsec stats

To display a list of IPSec statistics, use the **show ipsec stats** command in global configuration mode or privileged EXEC mode.

show ipsec stats

Syntax Description This command has no keywords or variables.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples The following example, entered in global configuration mode, displays IPSec statistics:

```
hostname(config)# show ipsec stats
```

```
IPsec Global Statistics
-----
Active tunnels: 2
Previous tunnels: 9
Inbound
  Bytes: 4933013
  Decompressed bytes: 4933013
  Packets: 80348
  Dropped packets: 0
  Replay failures: 0
  Authentications: 80348
  Authentication failures: 0
  Decryptions: 80348
  Decryption failures: 0
Outbound
  Bytes: 4441740
  Uncompressed bytes: 4441740
  Packets: 74029
  Dropped packets: 0
  Authentications: 74029
  Authentication failures: 0
  Encryptions: 74029
  Encryption failures: 0
```



```
Protocol failures: 0
Missing SA failures: 0
System capacity failures: 0
hostname(config)#
```

Related Commands

Command	Description
clear ipsec sa	Clears IPSec SAs or counters based on specified parameters.
crypto ipsec transform-set	Defines a transform set.
show ipsec sa	Displays IPSec SAs based on specified parameters.
show ipsec sa summary	Displays a summary of IPSec SAs.

show ipv6 access-list

To display the IPv6 access list, use the **show ipv6 access-list** command in privileged EXEC mode. The IPv6 access list determines what IPv6 traffic can pass through the security appliance.

show ipv6 access-list [*id* [*source-ipv6-prefix/prefix-length* | **any** | **host** *source-ipv6-address*]]

Syntax Description

any	(Optional) An abbreviation for the IPv6 prefix ::/0.
host <i>source-ipv6-address</i>	(Optional) IPv6 address of a specific host. When provided, only the access rules for the specified host are displayed.
<i>id</i>	(Optional) The access list name. When provided, only the specified access list is displayed.
<i>source-ipv6-prefix</i> <i>/prefix-length</i>	(Optional) IPv6 network address and prefix. When provided, only the access rules for the specified IPv6 network are displayed.

Defaults

Displays all IPv6 access lists.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **show ipv6 access-list** command provides output similar to the **show ip access-list** command, except that it is IPv6-specific.

Examples

The following is sample output from the **show ipv6 access-list** command. It shows IPv6 access lists named inbound, tcptraffic, and outbound.

```
hostname# show ipv6 access-list
IPv6 access list inbound
  permit tcp any any eq bgp reflect tcptraffic (8 matches) sequence 10
  permit tcp any any eq telnet reflect tcptraffic (15 matches) sequence 20
  permit udp any any reflect udptraffic sequence 30
IPv6 access list tcptraffic (reflexive) (per-user)
  permit tcp host 2001:0DB8:1::1 eq bgp host 2001:0DB8:1::2 eq 11000 timeout 300 (time
    left 243) sequence 1
  permit tcp host 2001:0DB8:1::1 eq telnet host 2001:0DB8:1::2 eq 11001 timeout 300
    (time left 296) sequence 2
```

```
IPv6 access list outbound
  evaluate udptraffic
  evaluate tcptraffic
```

Related Commands

Command	Description
ipv6 access-list	Creates an IPv6 access list.

show ipv6 interface

To display the status of interfaces configured for IPv6, use the **show ipv6 interface** command in privileged EXEC mode.

show ipv6 interface [**brief**] [*if_name*] [**prefix**]

Syntax Description

brief	Displays a brief summary of IPv6 status and configuration for each interface.
<i>if_name</i>	(Optional) The internal or external interface name, as designated by the nameif command. The status and configuration for only the designated interface is shown.
prefix	(Optional) Prefix generated from a local IPv6 prefix pool.

Defaults

Displays all IPv6 interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **show ipv6 interface** command provides output similar to the **show interface** command, except that it is IPv6-specific. If the interface hardware is usable, the interface is marked *up*. If the interface can provide two-way communication, the line protocol is marked *up*.

When an interface name is not specified, information on all IPv6 interfaces is displayed. Specifying an interface name displays information about the specified interface.

Examples

The following is sample output from the **show ipv6 interface** command:

```
hostname# show ipv6 interface outside
interface ethernet0 "outside" is up, line protocol is up
  IPv6 is enabled, link-local address is 2001:0DB8::/29 [TENTATIVE]
  Global unicast address(es):
    2000::2, subnet is 2000::/64
  Joined group address(es):
    FE02::1
    FE02::1:FE11:6770
  MTU is 1500 bytes
```

```
ND DAD is enabled, number of DAD attempts: 1
ND reachable time is 30000 milliseconds
ND advertised reachable time is 0 milliseconds
ND advertised retransmit interval is 0 milliseconds
ND router advertisements are sent every 200 seconds
ND router advertisements live for 1800 seconds
```

The following is sample output from the **show ipv6 interface** command when entered with the **brief** keyword:

```
hostname# show ipv6 interface brief
outside [up/up]
    unassigned
inside [up/up]
    fe80::20d:29ff:fe1d:69f0
    fec0::a:0:0:a0a:a70
vlan101 [up/up]
    fe80::20d:29ff:fe1d:69f0
    fec0::65:0:0:a0a:6570
dmz-ca [up/up]
    unassigned
```

The following is sample output from the **show ipv6 interface** command. It shows the characteristics of an interface which has generated a prefix from an address.

```
hostname# show ipv6 interface inside prefix
IPv6 Prefix Advertisements inside
Codes: A - Address, P - Prefix-Advertisement, O - Pool
        U - Per-user prefix, D - Default          N - Not advertised, C - Calendar

AD      fec0:0:0:a::/64 [LA] Valid lifetime 2592000, preferred lifetime 604800
```

show ipv6 neighbor

To display the IPv6 neighbor discovery cache information, use the **show ipv6 neighbor** command in privileged EXEC mode.

show ipv6 neighbor [*if_name* | *address*]

Syntax Description

<i>address</i>	(Optional) Displays neighbor discovery cache information for the supplied IPv6 address only.
<i>if_name</i>	(Optional) Displays cache information for the supplied interface name, as configure by the nameif command, only.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The following information is provided by the **show ipv6 neighbor** command:

- **IPv6 Address**—the IPv6 address of the neighbor or interface.
- **Age**—the time (in minutes) since the address was confirmed to be reachable. A hyphen (-) indicates a static entry.
- **Link-layer Addr**—MAC address. If the address is unknown, a hyphen (-) is displayed.
- **State**—The state of the neighbor cache entry.



Note

Reachability detection is not applied to static entries in the IPv6 neighbor discovery cache; therefore, the descriptions for the **INCMP** (Incomplete) and **REACH** (Reachable) states are different for dynamic and static cache entries.

The following are possible states for dynamic entries in the IPv6 neighbor discovery cache:

- **INCMP**—(Incomplete) Address resolution is being performed on the entry. A neighbor solicitation message has been sent to the solicited-node multicast address of the target, but the corresponding neighbor advertisement message has not yet been received.

- **REACH**—(Reachable) Positive confirmation was received within the last ReachableTime milliseconds that the forward path to the neighbor was functioning properly. While in **REACH** state, the device takes no special action as packets are sent.
- **STALE**—More than ReachableTime milliseconds have elapsed since the last positive confirmation was received that the forward path was functioning properly. While in **STALE** state, the device takes no action until a packet is sent.
- **DELAY**—More than ReachableTime milliseconds have elapsed since the last positive confirmation was received that the forward path was functioning properly. A packet was sent within the last DELAY_FIRST_PROBE_TIME seconds. If no reachability confirmation is received within DELAY_FIRST_PROBE_TIME seconds of entering the **DELAY** state, send a neighbor solicitation message and change the state to **PROBE**.
- **PROBE**—A reachability confirmation is actively sought by resending neighbor solicitation messages every RetransTimer milliseconds until a reachability confirmation is received.
- **????**—Unknown state.

The following are possible states for static entries in the IPv6 neighbor discovery cache:

- **INCOMP**—(Incomplete) The interface for this entry is down.
- **REACH**—(Reachable) The interface for this entry is up.

- **Interface**

Interface from which the address was reachable.

Examples

The following is sample output from the **show ipv6 neighbor** command when entered with an interface:

```
hostname# show ipv6 neighbor inside
IPv6 Address                               Age Link-layer Addr State Interface
2000:0:0:4::2                             0 0003.a0d6.141e REACH inside
FE80::203:A0FF:FED6:141E                   0 0003.a0d6.141e REACH inside
3001:1::45a                               - 0002.7d1a.9472 REACH inside
```

The following is sample output from the **show ipv6 neighbor** command when entered with an IPv6 address:

```
hostname# show ipv6 neighbor 2000:0:0:4::2
IPv6 Address                               Age Link-layer Addr State Interface
2000:0:0:4::2                             0 0003.a0d6.141e REACH inside
```

Related Commands

Command	Description
clear ipv6 neighbors	Deletes all entries in the IPv6 neighbor discovery cache, except static entries.
ipv6 neighbor	Configures a static entry in the IPv6 neighbor discovery cache.

show ipv6 route

To display the contents of the IPv6 routing table, use the **show ipv6 route** command in privileged EXEC mode.

show ipv6 route

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Release	Modification
7.0	This command was introduced.

Usage Guidelines The **show ipv6 route** command provides output similar to the **show route** command, except that the information is IPv6-specific.

The following information appears in the IPv6 routing table:

- **Codes**—Indicates the protocol that derived the route. Values are as follows:
 - **C**—Connected
 - **L**—Local
 - **S**—Static
 - **R**—RIP derived
 - **B**—BGP derived
 - **I1**—ISIS L1—Integrated IS-IS Level 1 derived
 - **I2**—ISIS L2—Integrated IS-IS Level 2 derived
 - **IA**—ISIS interarea—Integrated IS-IS interarea derived
- **fe80::/10**—Indicates the IPv6 prefix of the remote network.
- **[0/0]**—The first number in the brackets is the administrative distance of the information source; the second number is the metric for the route.
- **via ::**—Specifies the address of the next router to the remote network.

- **inside**—Specifies the interface through which the next router to the specified network can be reached.

Examples

The following is sample output from the **show ipv6 route** command:

```
hostname# show ipv6 route

IPv6 Routing Table - 7 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
       U - Per-user Static route
       I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea
       O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2

L   fe80::/10 [0/0]
    via ::, inside
    via ::, vlan101
L   fec0::a:0:0:a0a:a70/128 [0/0]
    via ::, inside
C   fec0:0:0:a::/64 [0/0]
    via ::, inside
L   fec0::65:0:0:a0a:6570/128 [0/0]
    via ::, vlan101
C   fec0:0:0:65::/64 [0/0]
    via ::, vlan101
L   ff00::/8 [0/0]
    via ::, inside
    via ::, vlan101
S   ::/0 [0/0]
    via fec0::65:0:0:a0a:6575, vlan101
```

Related Commands

Command	Description
debug ipv6 route	Displays debug messages for IPv6 routing table updates and route cache updates.
ipv6 route	Adds a static entry to the IPv6 routing table.

show ipv6 routers

To display IPv6 router advertisement information received from on-link routers, use the **show ipv6 routers** command in privileged EXEC mode.

show ipv6 routers [*if_name*]

Syntax Description	<i>if_name</i>	(Optional) The internal or external interface name, as designated by the nameif command, that you want to display information about.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	When an interface name is not specified, information on all IPv6 interfaces is displayed. Specifying an interface name displays information about the specified interface.

Examples	The following is sample output from the show ipv6 routers command when entered without an interface name:

```
hostname# show ipv6 routers
Router FE80::83B3:60A4 on outside, last update 3 min
  Hops 0, Lifetime 6000 sec, AddrFlag=0, OtherFlag=0
  Reachable time 0 msec, Retransmit time 0 msec
  Prefix 3FFE:C00:8007::800:207C:4E37/96 autoconfig
  Valid lifetime -1, preferred lifetime -1
Router FE80::290:27FF:FE8C:B709 on inside, last update 0 min
  Hops 64, Lifetime 1800 sec, AddrFlag=0, OtherFlag=0
  Reachable time 0 msec, Retransmit time 0 msec
```

Related Commands	Command	Description
	ipv6 route	Adds a static entry to the IPv6 routing table.

show ipv6 traffic

To display statistics about IPv6 traffic, use the **show ipv6 traffic** command in privileged EXEC mode.

show ipv6 traffic

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines Use the **clear ipv6 traffic** command to clear the traffic counters.

Examples The following is sample output from the **show ipv6 traffic** command:

```
hostname# show ipv6 traffic
IPv6 statistics:
  Rcvd:  545 total, 545 local destination
         0 source-routed, 0 truncated
         0 format errors, 0 hop count exceeded
         0 bad header, 0 unknown option, 0 bad source
         0 unknown protocol, 0 not a router
         218 fragments, 109 total reassembled
         0 reassembly timeouts, 0 reassembly failures
  Sent:  228 generated, 0 forwarded
         1 fragmented into 2 fragments, 0 failed
         0 encapsulation failed, 0 no route, 0 too big
  Mcast: 168 received, 70 sent

ICMP statistics:
  Rcvd: 116 input, 0 checksum errors, 0 too short
         0 unknown info type, 0 unknown error type
  unreachable: 0 routing, 0 admin, 0 neighbor, 0 address, 0 port
  parameter: 0 error, 0 header, 0 option
         0 hopcount expired, 0 reassembly timeout, 0 too big
         0 echo request, 0 echo reply
         0 group query, 0 group report, 0 group reduce
```

show ipv6 traffic

```

0 router solicit, 60 router advert, 0 redirects
31 neighbor solicit, 25 neighbor advert
Sent: 85 output, 0 rate-limited
unreach: 0 routing, 0 admin, 0 neighbor, 0 address, 0 port
parameter: 0 error, 0 header, 0 option
0 hopcount expired, 0 reassembly timeout, 0 too big
0 echo request, 0 echo reply
0 group query, 0 group report, 0 group reduce
0 router solicit, 18 router advert, 0 redirects
33 neighbor solicit, 34 neighbor advert

UDP statistics:
Rcvd: 109 input, 0 checksum errors, 0 length errors
      0 no port, 0 dropped
Sent: 37 output

TCP statistics:
Rcvd: 85 input, 0 checksum errors
Sent: 103 output, 0 retransmitted

```

Related Commands

Command	Description
clear ipv6 traffic	Clears ipv6 traffic counters.

show isakmp sa

To display the IKE runtime SA database, use the **show isakmp sa** command in global configuration mode or privileged EXEC mode.

show isakmp sa [detail]

Syntax Description

detail Displays detailed output about the SA database.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The output from this command includes the following fields:

Detail not specified.

Table 7-23

IKE Peer	Type	Dir	Rky	State
209.165.200.225	L2L	Init	No	MM_Active

Detail specified.

Table 7-24

IKE Peer	Type	Dir	Rky	State	Encrypt	Hash	Auth	Lifetime
209.165.200.225	L2L	Init	No	MM_Active	3des	md5	preshrd	86400

Examples

The following example, entered in global configuration mode, displays detailed information about the SA database:

```
hostname(config)# show isakmp sa detail
hostname(config)# sho isakmp sa detail
```

show isakmp sa

```

IKE Peer  Type  Dir   Rky  State      Encrypt Hash  Auth  Lifetime
1 209.165.200.225 User  Resp No    AM_Active 3des   SHA   preshrd 86400

IKE Peer  Type  Dir   Rky  State      Encrypt Hash  Auth  Lifetime
2 209.165.200.226 User  Resp No    AM_ACTIVE 3des   SHA   preshrd 86400

IKE Peer  Type  Dir   Rky  State      Encrypt Hash  Auth  Lifetime
3 209.165.200.227 User  Resp No    AM_ACTIVE 3des   SHA   preshrd 86400

IKE Peer  Type  Dir   Rky  State      Encrypt Hash  Auth  Lifetime
4 209.165.200.228 User  Resp No    AM_ACTIVE 3des   SHA   preshrd 86400

hostname(config)#

```

Related Commands

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.
isakmp enable	Enables ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance.
show running-config isakmp	Displays all the active ISAKMP configuration.

show isakmp stats

To display runtime statistics, use the **show isakmp stats** command in global configuration mode or privileged EXEC mode.

show isakmp stats

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines The output from this command includes the following fields:

- Global IKE Statistics
- Active Tunnels
- In Octets
- In Packets
- In Drop Packets
- In Notifys
- In P2 Exchanges
- In P2 Exchange Invalids
- In P2 Exchange Rejects
- In P2 Sa Delete Requests
- Out Octets
- Out Packets
- Out Drop Packets
- Out Notifys
- Out P2 Exchanges

- Out P2 Exchange Invalids
- Out P2 Exchange Rejects
- Out P2 Sa Delete Requests
- Initiator Tunnels
- Initiator Fails
- Responder Fails
- System Capacity Fails
- Auth Fails
- Decrypt Fails
- Hash Valid Fails
- No Sa Fails

Examples

The following example, issued in global configuration mode, displays ISAKMP statistics:

```
hostname(config)# show isakmp stats
Global IKE Statistics
Active Tunnels: 132
Previous Tunnels: 132
In Octets: 195471
In Packets: 1854
In Drop Packets: 925
In Notifys: 0
In P2 Exchanges: 132
In P2 Exchange Invalids: 0
In P2 Exchange Rejects: 0
In P2 Sa Delete Requests: 0
Out Octets: 119029
Out Packets: 796
Out Drop Packets: 0
Out Notifys: 264
Out P2 Exchanges: 0
Out P2 Exchange Invalids: 0
Out P2 Exchange Rejects: 0
Out P2 Sa Delete Requests: 0
Initiator Tunnels: 0
Initiator Fails: 0
Responder Fails: 0
System Capacity Fails: 0
Auth Fails: 0
Decrypt Fails: 0
Hash Valid Fails: 0
No Sa Fails: 0
hostname(config)#
```

Related Commands

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.

Command	Description
isakmp enable	Enables ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance.
show running-config isakmp	Displays all the active ISAKMP configuration.

show local-host

To display the network states of local hosts, use the **show local-host** command in privileged EXEC mode.

```
show local-host [ip_address] [detail] [all][brief] [connection {tcp <start>[-<end>] | udp
<start>[-<end>] | embryonic <start>[-<end>]]]
```

Syntax Description

all	(Optional) Specifies to include the list of local hosts state-made connections, including to the security appliance and from the security appliance.
brief	(Optional) Displays brief information on local hosts.
connection	(Optional) Displays three types of filters based on the number and type of connections: tcp, udp and embryonic. These filters can be used individually or jointly.
detail	(Optional) Displays the detailed network states of local host information.
<i>ip_address</i>	(Optional) Specifies the local host IP address.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.
7.0(8)	Added the connection and brief options.

Usage Guidelines

The **show local-host** command lets you display the network states of local hosts. A local-host is created for any host that forwards traffic to, or through, the security appliance.

This command lets you show the translation and connection slots for the local hosts or stop all traffic on these hosts. This command provides information for hosts that are configured with the **nat 0 access-list** command when normal translation and connection states may not apply.

The **show local-host detail** command displays more information about active xlates and network connections.

Use the *ip_address* argument to limit the display to a single host.

Use the **all** keyword to list local hosts-made connections, including to the security appliance and from the security appliance. If you do not use the **all** keyword, local hosts connections to the security appliance and from the appliance do not display.

This command displays the connection limit values. If a connection limit is not set, the value displays as 0 and the limit is not applied.

In the event of a syn attack (with TCP intercept configured), the **show local-host** command output includes the number of intercepted connections in the usage count. This field typically displays only full open connections.

In the **show local-host** command output, the `TCP embryonic count to host counter` is used when a maximum embryonic limit (TCP intercept watermark) is configured for a host using a static connection. This counter shows the total embryonic connections to the host from other hosts. If this total exceeds the maximum configured limit, TCP intercept is applied to new connections to the host.

Examples

The following examples show how to display the network states of local hosts:

```
hostname# show local-host all
Interface outside: 1 active, 2 maximum active, 0 denied
local host: <11.0.0.4>,
TCP flow count/limit = 0/unlimited
TCP embryonic count to host = 0
TCP intercept watermark = unlimited
UDP flow count/limit = 0/unlimited
Conn:
105 out 11.0.0.4 in 11.0.0.3 idle 0:01:42 bytes 4464
105 out 11.0.0.4 in 11.0.0.3 idle 0:01:44 bytes 4464
Interface inside: 1 active, 2 maximum active, 0 denied
local host: <17.3.8.2>,
TCP flow count/limit = 0/unlimited
TCP embryonic count to host = 0
TCP intercept watermark = unlimited
UDP flow count/limit = 0/unlimited
Conn:
105 out 17.3.8.2 in 17.3.8.1 idle 0:01:42 bytes 4464
105 out 17.3.8.2 in 17.3.8.1 idle 0:01:44 bytes 4464
Interface NP Identity Ifc: 2 active, 4 maximum active, 0 denied
local host: <11.0.0.3>,
TCP flow count/limit = 0/unlimited
TCP embryonic count to host = 0
TCP intercept watermark = unlimited
UDP flow count/limit = 0/unlimited
Conn:
105 out 11.0.0.4 in 11.0.0.3 idle 0:01:44 bytes 4464
105 out 11.0.0.4 in 11.0.0.3 idle 0:01:42 bytes 4464
local host: <17.3.8.1>,
TCP flow count/limit = 0/unlimited
TCP embryonic count to host = 0
TCP intercept watermark = unlimited
UDP flow count/limit = 0/unlimited
Conn:
105 out 17.3.8.2 in 17.3.8.1 idle 0:01:44 bytes 4464
105 out 17.3.8.2 in 17.3.8.1 idle 0:01:42 bytes 4464

hostname# show local-host 10.1.1.91
Interface third: 0 active, 0 maximum active, 0 denied
Interface inside: 1 active, 1 maximum active, 0 denied
local host: <10.1.1.91>,
TCP flow count/limit = 1/unlimited
TCP embryonic count to (from) host = 0 (0)
TCP intercept watermark = unlimited
UDP flow count/limit = 0/unlimited

Xlate:
```

```
PAT Global 192.150.49.1(1024) Local 10.1.1.91(4984)
```

```
Conn:
```

```
TCP out 192.150.49.10:21 in 10.1.1.91:4984 idle 0:00:07 bytes 75 flags UI Interface
outside: 1 active, 1 maximum active, 0 denied
```

```
hostname# show local-host 10.1.1.91 detail
```

```
Interface third: 0 active, 0 maximum active, 0 denied
Interface inside: 1 active, 1 maximum active, 0 denied
local host: <10.1.1.91>,
TCP flow count/limit = 1/unlimited
TCP embryonic count to (from) host = 0 (0)
TCP intercept watermark = unlimited
UDP flow count/limit = 0/unlimited
```

```
Xlate:
```

```
TCP PAT from inside:10.1.1.91/4984 to outside:192.150.49.1/1024 flags ri
```

```
Conn:
```

```
TCP outside:192.150.49.10/21 inside:10.1.1.91/4984 flags UI Interface outside: 1 active, 1
maximum active, 0 denied
```

The following example shows all hosts who have at least four udp connections and have between one to 10 tcp connections at the same time:

```
hostname# show local-host connection udp 4 tcp 1-10
```

```
Interface mng: 0 active, 3 maximum active, 0 denied
Interface INSIDE: 4 active, 5 maximum active, 0 denied
local host: <10.1.1.11>,
TCP flow count/limit = 1/unlimited TCP embryonic count to host = 0 TCP intercept
watermark = unlimited UDP flow count/limit = 4/unlimited
```

```
Xlate:
```

```
Global 192.168.1.24 Local 10.1.1.11 Conn: UDP out 192.168.1.10:80 in
10.1.1.11:1730 idle 0:00:21 bytes 0 flags - UDP out 192.168.1.10:80 in
10.1.1.11:1729 idle 0:00:22 bytes 0 flags - UDP out 192.168.1.10:80 in
10.1.1.11:1728 idle 0:00:23 bytes 0 flags - UDP out 192.168.1.10:80 in
10.1.1.11:1727 idle 0:00:24 bytes 0 flags - TCP out 192.168.1.10:22 in
10.1.1.11:27337 idle 0:01:55 bytes 2641 flags UIO Interface OUTSIDE: 3 active, 5
maximum active, 0 denied
```

The following example shows local-host addresses and connection counters using the **brief** option:

```
hostname# show local-host connection udp 2
```

```
Interface mng: 0 active, 3 maximum active, 0 denied
Interface INSIDE: 4 active, 5 maximum active, 0 denied
local host: <10.1.1.11>,
TCP flow count/limit = 1/unlimited
TCP embryonic count to host = 0
TCP intercept watermark = unlimited UDP flow count/limit = 4/unlimited
Interface OUTSIDE: 3 active, 5 maximum active, 0 denied
```

The following examples shows the output when using the *brief* and *connection* syntax:

```
hostname# show local-host brief
```

```
Interface inside: 1 active, 1 maximum active, 0 denied
Interface outside: 1 active, 1 maximum active, 0 denied
Interface mgmt: 5 active, 6 maximum active, 0 denied
```

```
hostname# show local-host connection
```

```
Interface inside: 1 active, 1 maximum active, 0 denied
Interface outside: 1 active, 1 maximum active, 0 denied
Interface mgmt: 5 active, 6 maximum active, 0 denied
```

Related Commands

Command	Description
clear local-host	Releases network connections from local hosts displayed by the show local-host command.
nat	Associates a network with a pool of global IP addresses.

show logging

To show the logs in the buffer or to show other logging settings, use the **show logging** command.

show logging [**message** [*syslog_id* | **all**] | **asdm** | **queue** | **setting**]

Syntax Description		
message	(Optional)	Displays messages that are at a non-default level. See the logging message command to set the message level.
<i>syslog_id</i>	(Optional)	Specifies a message number to display.
all	(Optional)	Displays all syslog message IDs, along with whether they are enabled or disabled.
setting	(Optional)	Displays the logging setting, without displaying the logging buffer.
asdm	(Optional)	Displays ASDM logging buffer content.
queue	(Optional)	Displays the syslog message queue.

Defaults This command has no default settings.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines If the **logging buffered** command is in use, the **show logging** command without any keywords shows the current message buffer and the current settings.

The **show logging queue** command allows you to display the following:

- Number of messages that are in the queue
- Highest number of messages recorded that are in the queue
- Number of messages that are discarded because block memory was not available to process them

Examples The following is sample output from the **show logging** command:

```
hostname(config)# show logging
Syslog logging: enabled
Timestamp logging: disabled
Console logging: disabled
```

```
Monitor logging: disabled
Buffer logging: level debugging, 37 messages logged
Trap logging: disabled
305001: Portmapped translation built for gaddr 209.165.201.5/0 laddr 192.168.1.2/256
...
```

The following is sample output from the **show logging message all** command:

```
hostname(config)# show logging message all

syslog 111111: default-level alerts (enabled)
syslog 101001: default-level alerts (enabled)
syslog 101002: default-level alerts (enabled)
syslog 101003: default-level alerts (enabled)
syslog 101004: default-level alerts (enabled)
syslog 101005: default-level alerts (enabled)
syslog 102001: default-level alerts (enabled)
syslog 103001: default-level alerts (enabled)
syslog 103002: default-level alerts (enabled)
syslog 103003: default-level alerts (enabled)
syslog 103004: default-level alerts (enabled)
syslog 103005: default-level alerts (enabled)
syslog 103011: default-level alerts (enabled)
syslog 103012: default-level informational (enabled)
```

Related Commands

Command	Description
logging asdm	Enables logging to ASDM
logging buffered	Enables logging to the buffer.
logging message	Sets the message level, or disables messages.
logging queue	Configures the logging queue.

show logging rate-limit

To display the disallowed messages to the original set, use the **show logging rate-limit** command.

show logging rate-limit

Syntax Description This command has no arguments or keywords.

Defaults This command has no default settings.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
7.0	Support for this command was introduced on the security appliance.

Usage Guidelines After the information is cleared, nothing more displays until the hosts reestablish their connections.

Examples This example shows how to display the disallowed messages:

```
hostname(config)# show logging rate-limit
```

Command	Description
show logging	Displays the enabled logging options.

show mac-address-table

To show the MAC address table, use the **show mac-address-table** command in privileged EXEC mode.

show mac-address-table [*interface_name* | **count** | **static**]

Syntax Description	count	(Optional) Lists the total number of dynamic and static entries.
	<i>interface_name</i>	(Optional) Identifies the interface name for which you want to view MAC address table entries.
	static	(Optional) Lists only static entries.

Defaults If you do not specify an interface, all interface MAC address entries are shown.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	—	•	•	•	—

Release	Modification
7.0	This command was introduced.

Examples The following is sample output from the **show mac-address-table** command:

```
hostname# show mac-address-table
interface      mac address      type      Time Left
-----
outside        0009.7cbe.2100    static     -
inside         0010.7cbe.6101    static     -
inside         0009.7cbe.5101    dynamic    10
```

The following is sample output from the **show mac-address-table** command for the inside interface:

```
hostname# show mac-address-table inside
interface      mac address      type      Time Left
-----
inside        0010.7cbe.6101    static     -
inside        0009.7cbe.5101    dynamic    10
```

The following is sample output from the **show mac-address-table count** command:

```
hostname# show mac-address-table count
Static      mac-address bridges (curr/max): 0/65535
Dynamic     mac-address bridges (curr/max): 103/65535
```

Related Commands

Command	Description
firewall transparent	Sets the firewall mode to transparent.
mac-address-table aging-time	Sets the timeout for dynamic MAC address entries.
mac-address-table static	Adds a static MAC address entry to the MAC address table.
mac-learn	Disables MAC address learning.

show management-access

To display the name of the internal interface configured for management access, use the `show management-access` command in privileged EXEC mode.

show management-access

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines The **management-access** command lets you define an internal management interface using the IP address of the firewall interface specified in *mgmt_if*. (The interface names are defined by the **nameif** command and displayed in quotes, “”, in the output of the **show interface** command.)

Examples The following example shows how to configure a firewall interface named “inside” as the management access interface and display the result:

```
hostname(config)# management-access inside
hostname(config)# show management-access
management-access inside
```

Command	Description
clear configure management-access	Removes the configuration of an internal interface for management access of the security appliance.
management-access	Configures an internal interface for management access.

show memory

To display a summary of the maximum physical memory and current free memory available to the operating system, use the **show memory** command in privileged EXEC mode.

show memory [detail]

Syntax Description

detail (Optional) Displays a detailed view of free and allocated system memory.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **show memory** command lets you display a summary of the maximum physical memory and current free memory available to the operating system. Memory is allocated as needed.

You can use the **show memory detail** output with **show memory binsize** command to debug memory leaks.

You can also display the information from the **show memory** command using SNMP.

Examples

This example shows how to display a summary of the maximum physical memory and current free memory available:

```
hostname# show memory
Free memory:      845044716 bytes (79%)
Used memory:      228697108 bytes (21%)
-----
Total memory:     1073741824 bytes (100%)
```

This example shows detailed memory output:

```
hostname# show memory detail
Free memory: 15958088 bytes (24%)
Used memory:
Allocated memory in use: 29680332 bytes (44%)
Reserved memory: 21470444 bytes (32%)
-----
```

```
Total memory: 67108864 bytes (100%)

Least free memory: 4551716 bytes ( 7%)
Most used memory: 62557148 bytes (93%)

----- fragmented memory statistics -----

fragment size count total
(bytes) (bytes)
-----
16 8 128
24 4 96
32 2 64
40 5 200
64 3 192
88 1 88
168 1 168
224 1 224
256 1 256
296 2 592
392 1 392
400 1 400
1816 1 1816*
4435968 1 4435968**
11517504 1 11517504

* - top most releasable chunk.
** - contiguous memory on top of heap.

----- allocated memory statistics -----

fragment size count total
(bytes) (bytes)
-----
40 50 2000
48 144 6912
56 24957 1397592
64 101 6464
72 99 7128
80 1032 82560
88 18 1584
96 64 6144
104 57 5928
112 6 672
120 112 13440
128 15 1920
136 87 11832
144 22 3168
152 31 4712
160 90 14400
168 65 10920
176 74 13024
184 11 2024
192 8 1536
200 1 200
<output omitted>
```

Related Commands	Command	Description
	show memory profile	Displays information about the memory usage (profiling) of the security appliance.
	show memory binsize	Displays summary information about the chunks allocated for a specific bin size.

show memory binsize

To display summary information about the chunks allocated for a specific bin size, use the **show memory binsize** command in privileged EXEC mode.

show memory binsize *size*

Syntax Description

size Displays chunks (memory blocks) of a specific bin size. The bin size is from the "fragment size" column of the **show memory detail** command output.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command has no usage guidelines.

Examples

The following example displays summary information about a chunk allocated to a bin size of 500:

```
hostname# show memory binsize 500
pc = 0x00b33657, size = 460      , count = 1
```

Related Commands

Command	Description
show memory-caller address	Displays the address ranges configured on the security appliance.
show memory profile	Displays information about the memory usage (profiling) of the security appliance.
show memory	Displays a summary of the maximum physical memory and current free memory available to the operating system.

show memory delayed-free-poisoner

To display a summary of the **memory delayed-free-poisoner** queue usage, use the **show memory delayed-free-poisoner** command in privileged EXEC mode.

show memory delayed-free-poisoner

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines Use the **clear memory delayed-free-poisoner** command to clear the queue and statistics.

Examples This following is sample output from the **show memory delayed-free-poisoner** command:

```
hostname# show memory delayed-free-poisoner
delayed-free-poisoner statistics:
  3335600: memory held in queue
    6095: current queue count
      0: elements dequeued
      3: frees ignored by size
    1530: frees ignored by locking
      27: successful validate runs
      0: aborted validate runs
01:09:36: local time of last validate
```

[Table 7-25](#) describes the significant fields in the **show memory delayed-free-poisoner** command output.

Table 7-25 show memory delayed-free-poisoner Command Output Descriptions

Field	Description
memory held in queue	The memory that is held in the delayed free-memory poisoner tool queue. Such memory is normally in the “Free” quantity in the show memory output if the delayed free-memory poisoner tool is not enabled.
current queue count	The number of elements in the queue.
elements dequeued	The number of elements that have been removed from the queue. This number begins to increase when most or all of the otherwise free memory in the system ends up in being held in the queue.
frees ignored by size	The number of free requests not placed into the queue because the request was too small to hold required tracking information.
frees ignored by locking	The number of free requests intercepted by the tool not placed into the queue because the memory is in use by more than one application. The last application to free the memory back to the system ends up placing such memory regions into the queue.
successful validate runs	The number of times since monitoring was enabled or cleared using the clear memory delayed-free-poisoner command that the queue contents were validated (either automatically or by the memory delayed-free-poisoner validate command).
aborted validate runs	The number of times since monitoring was enabled or cleared using the clear memory delayed-free-poisoner command that requests to check the queue contents have been aborted because more than one task (either the periodic run or a validate request from the CLI) attempted to use the queue at a time.
local time of last validate	The local system time when the last validate run completed.

Related Commands

Command	Description
clear memory delayed-free-poisoner	Clears the delayed free-memory poisoner tool queue and statistics.
memory delayed-free-poisoner enable	Enables the delayed free-memory poisoner tool.
memory delayed-free-poisoner validate	Forces validation of the elements in the delayed free-memory poisoner tool queue.

show memory profile

To display information about the memory usage (profiling) of the security appliance, use the **show memory profile** command in privileged EXEC mode.

show memory profile [**peak**] [**detail** | **collated** | **status**]

Syntax Description

collated	(Optional) Collates the memory information displayed.
detail	(Optional) Displays detailed memory information.
peak	(Optional) Displays the peak capture buffer rather than the “in use” buffer.
status	(Optional) Displays the current state of memory profiling and the peak capture buffer.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	—	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **show memory profile** command to troubleshoot memory usage level and memory leaks. You can still see the profile buffer contents even if profiling has been stopped. Starting profiling clears the buffer automatically.



Note

The security appliance might experience a temporary reduction in performance when memory profiling is enabled.

Examples

The following example shows...

```
hostname# show memory profile
Range: start = 0x004018b4, end = 0x004169d0, increment = 00000004
Total = 0
```

The output of the **show memory profile detail** command (below) is divided into six data columns and one header column, at the far left. The address of the memory bucket corresponding to the first data column is given at the header column (the hexadecimal number). The data itself is the number of bytes

that is held by the text/code that falls in the bucket address. A period (.) in the data column means no memory is held by the text at this bucket. Other columns in the row correspond to the bucket address that is greater than the increment amount from the previous column. For example, the address bucket of the first data column in the first row is 0x001069e0. The address bucket of the second data column in the first row is 0x001069e4 and so on. Normally the header column address is the next bucket address; that is, the address of the last data column of the previous row plus the increment. All rows without any usage are suppressed. More than one such contiguous row can be suppressed, indicated with three periods at the header column (...).

```
hostname# show memory profile detail
Range: start = 0x00100020, end = 0x00e006e0, increment = 00000004
Total = 48941152
...
0x001069e0 . 24462 . . . .
...
0x00106d88 . 1865870 . . . .
...
0x0010adf0 . 7788 . . . .
...
0x00113640 . . . . 433152 .
...
0x00116790 2480 . . . .
<snip>
```

The following example shows collated output:

```
hostname# show memory profile collated
Range: start = 0x00100020, end = 0x00e006e0, increment = 00000004
Total = 48941152
24462 0x001069e4
1865870 0x00106d8c
7788 0x0010adf4
433152 0x00113650
2480 0x00116790
<snip>
```

The following example shows the peak capture buffer:

```
hostname# show memory profile peak
Range: start = 0x004018b4, end = 0x004169d0, increment = 00000004
Total = 102400
```

The following example shows the peak capture buffer and the number of bytes that is held by the text/code that falls in the corresponding bucket address:

```
hostname# show memory profile peak detail
Range: start = 0x004018b4, end = 0x004169d0, increment = 00000004
Total = 102400
...
0x00404c8c . . 102400 . . .
```

The following example shows the current state of memory profiling and the peak capture buffer:

```
hostname# show memory profile status
InUse profiling: ON
Peak profiling: OFF
Memory used by profile buffers: 11518860 bytes
Profile:
0x00100020-0x00bfc3a8(00000004)
```

Related Commands

Command	Description
memory profile enable	Enables the monitoring of memory usage (memory profiling).
memory profile text	Configures a program text range of memory to profile.
clear memory profile	Clears the memory buffers held by the memory profiling function.

show memory tracking

To display currently allocated memory tracked by the tool, use the **show memory tracking** command in privileged EXEC mode.

show memory tracking [address | dump | detail]

Syntax Description

address	(Optional) Shows memory tracking by address.
detail	(Optional) Shows internal memory tracking state.
dump	(Optional) Dumps memory tracking address.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	—	•	•

Command History

Release	Modification
7.0(8)	This command was introduced.

Usage Guidelines

Use the **show memory tracking** command to show currently allocated memory tracked by the tool.

Examples

The following example shows the **show memory tracking** command out-put:

```
hostname# show memory tracking
memory tracking by caller:
17 bytes from 1 allocates by 0x080c50c2
37 bytes from 1 allocates by 0x080c50f6
57 bytes from 1 allocates by 0x080c5125
20481 bytes from 1 allocates by 0x080c5154
```

The following examples show the **show memory tracking address**, and **show memory tracking dump** outputs:

```
hostname# show memory tracking address
memory tracking by caller:
17 bytes from 1 allocates by 0x080c50c2
37 bytes from 1 allocates by 0x080c50f6
57 bytes from 1 allocates by 0x080c5125
20481 bytes from 1 allocates by 0x080c5154
```

show memory tracking

```

memory tracking by address:
37 byte region @ 0xa893ae80 allocated by 0x080c50f6
57 byte region @ 0xa893aed0 allocated by 0x080c5125
20481 byte region @ 0xa8d7cc50 allocated by 0x080c5154
17 byte region @ 0xa8a6f370 allocated by 0x080c50c2

hostname# memory tracking dump 0xa893aed0
Tracking data for the 57 byte region at 0xa893aed0:
Timestamp: 05:59:36.309 UTC Sun Jul 29 2007
Traceback:
0x080c5125
0x080b3695
0x0873f606
0x08740573
0x080ab530
0x080ac788
0x080ad141
0x0805df8f
Dumping 57 bytes of the 57 byte region:
a893aed0: 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c | .....
a893aee0: 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c | .....
a893aef0: 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c | .....
a893af00: 0c 0c 0c 0c 0c 0c 0c 0c 0c 0c | .....

```

Related Commands

Command	Description
clear memory tracking	Clears all currently gathered information.
show memory tracking	Shows currently allocated memory.

show memory-caller address

To display the address ranges configured on the security appliance, use the **show memory-caller address** command in privileged EXEC mode.

show memory-caller address

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	—	•	•

Release	Modification
7.0	This command was introduced.

Usage Guidelines You must first configure an address ranges with the **memory caller-address** command before you can display them with the **show memory-caller address** command.

Examples The following examples show the address ranges configured with the **memory caller-address** commands, and the resulting display of the **show memory-caller address** command:

```
hostname# memory caller-address 0x00109d5c 0x00109e08
hostname# memory caller-address 0x009b0ef0 0x009b0f14
hostname# memory caller-address 0x00cf211c 0x00cf4464
```

```
hostname# show memory-caller address
Move down stack frame for the addresses:
pc = 0x00109d5c-0x00109e08
pc = 0x009b0ef0-0x009b0f14
pc = 0x00cf211c-0x00cf4464
```

If address ranges are not configured before entering the **show memory-caller address** command, no addresses display:

```
hostname# show memory-caller address
Move down stack frame for the addresses:
```

 show memory-caller address**Related Commands**

Command	Description
memory caller-address	Configures block of memory for the caller PC.

show mfib

To display MFIB in terms of forwarding entries and interfaces, use the **show mfib** command in user EXEC or privileged EXEC mode.

show mfib [*group* [*source*]] [**verbose**]

Syntax Description

<i>group</i>	(Optional) IP address of the multicast group.
<i>source</i>	(Optional) IP address of the multicast route source. This is a unicast IP address in four-part dotted-decimal notation.
verbose	(Optional) Displays additional information about the entries.

Defaults

Without the optional arguments, information for all groups is shown.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC or Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following is sample output from the **show mfib** command:

```
hostname# show mfib 224.0.2.39
Entry Flags: C - Directly Connected, S - Signal, IA - Inherit A flag,
             AR - Activity Required, D - Drop
Forwarding counts: Pkt Count/Pkts per second/Avg Pkt Size/Kbits per second
Other counts: Total/RPF failed/Other drops
Interface flags: A - Accept, F - Forward, NS - Negate Signalling
                IC - Internal Copy, NP - Not platform switched
                SP - Signal Present
Interface Counts: FS Pkt Count/PS Pkt Count
(*,224.0.1.39) Flags: S K
Forwarding: 0/0/0/0, Other: 0/0/0
```

Related Commands

Command	Description
show mfib verbose	Displays detail information about the forwarding entries and interfaces.

show mfib active

To display active multicast sources, use the **show mfib active** command in user EXEC or privileged EXEC mode.

show mfib [*group*] **active** [*kbps*]

Syntax Description

<i>group</i>	(Optional) IP address of the multicast group.
<i>kbps</i>	(Optional) Limits the display to multicast streams that are greater-than or equal to this value.

This command has no arguments or keywords.

Defaults

The default value for *kbps* is 4. If a *group* is not specified, all groups are shown.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC or Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The output for the show mfib active command displays either positive or negative numbers for the rate PPS. The security appliance displays negative numbers when RPF packets fail or when the router observes RPF packets with an interfaces out (OIF) list. This type of activity may indicate a multicast routing problem.

Examples

The following is sample output from the **show mfib active** command:

```
hostname# show mfib active
Active IP Multicast Sources - sending >= 4 kbps

Group: 224.2.127.254, (sdr.cisco.com)
  Source: 192.168.28.69 (mbone.ipd.anl.gov)
    Rate: 1 pps/4 kbps(1sec), 4 kbps(last 1 secs), 4 kbps(life avg)

Group: 224.2.201.241, ACM 97
  Source: 192.168.52.160 (webcast3-e1.acm97.interop.net)
    Rate: 9 pps/93 kbps(1sec), 145 kbps(last 20 secs), 85 kbps(life avg)
```

```
Group: 224.2.207.215, ACM 97
Source: 192.168.52.160 (webcast3-e1.acm97.interop.net)
Rate: 3 pps/31 kbps(1sec), 63 kbps(last 19 secs), 65 kbps(life avg)
```

Related Commands

Command	Description
show mroute active	Displays active multicast streams.

show mfib count

To display MFIB route and packet count data, use the **show mfib count** command in user EXEC or privileged EXEC mode.

show mfib [*group* [*source*]] **count**

Syntax Description

<i>group</i>	(Optional) IP address of the multicast group.
<i>source</i>	(Optional) IP address of the multicast route source. This is a unicast IP address in four-part dotted-decimal notation.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC or Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command displays packet drop statistics.

Examples

The following sample output from the **show mfib count** command:

```
hostname# show mfib count
MFIB global counters are :
* Packets [no input idb] : 0
* Packets [failed route lookup] : 0
* Packets [Failed idb lookup] : 0
* Packets [Mcast disabled on input I/F] : 0
```

Related Commands

Command	Description
clear mfib counters	Clears MFIB router packet counters.
show mroute count	Displays multicast route counters.

show mfib interface

To display packet statistics for interfaces that are related to the MFIB process, use the **show mfib interface** command in user EXEC or privileged EXEC mode.

show mfib interface [*interface*]

Syntax Description	<i>interface</i> (Optional) Interface name. Limits the display to the specified interface.

Defaults	Information for all MFIB interfaces is shown.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC or Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples	The following example is sample output from the show mfib interface command:

```
hostname# show mfib interface
IP Multicast Forwarding (MFIB) status:
  Configuration Status: enabled
  Operational Status: running
MFIB interface      status    CEF-based output
                  [configured, available]
      Ethernet0    up      [      no,      no]
      Ethernet1    up      [      no,      no]
      Ethernet2    up      [      no,      no]
```

Related Commands	Command	Description
	show mfib	Displays MFIB information in terms of forwarding entries and interfaces.

show mfib reserved

To display reserved groups, use the **show mfib reserved** command in user EXEC or privileged EXEC mode.

show mfib reserved [**count** | **verbose** | **active** [*kpbs*]]

Syntax Description

count	(Optional) Displays packet and route count data.
verbose	(Optional) Displays additional information.
active	(Optional) Displays active multicast sources.
<i>kpbs</i>	(Optional) Limits the display to active multicast sources greater-than or equal to this value.

Defaults

The default value for *kpbs* is 4.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC or Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command displays MFIB entries in the range 224.0.0.0 through 224.0.0.225.

Examples

The following is sample output from the **show mfib reserved** command:

```
hostname# command example
Entry Flags: C - Directly Connected, S - Signal, IA - Inherit A flag,
             AR - Activity Required, D - Drop Forwarding Counts: Pkt Count/Pkts per
             second/Avg Pkt Size/Kbits per second Other counts: Total/RPF failed/Other drops Interface
Flags: A - Accept, F - Forward, NS - Negate Signalling
             IC - Internal Copy, NP - Not platform switched
             SP - Signal Present
Interface Counts: FS Pkt Count/PS Pkt Count
(*,224.0.0.0/4) Flags: C K
    Forwarding: 0/0/0/0, Other: 0/0/0
(*,224.0.0.0/24) Flags: K
    Forwarding: 0/0/0/0, Other: 0/0/0
(*,224.0.0.1) Flags:
    Forwarding: 0/0/0/0, Other: 0/0/0
outside Flags: IC
```

```
dmz Flags: IC
inside Flags: IC
```

Related Commands

Command	Description
show mfib active	Displays active multicast streams.

show mfib status

To display the general MFIB configuration and operational status, use the **show mfib status** command in user EXEC or privileged EXEC mode.

show mfib status

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC or Privileged EXEC	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Examples The following is sample output from the **show mfib status** command:

```
hostname# show mfib status
IP Multicast Forwarding (MFIB) status:
  Configuration Status: enabled
  Operational Status: running
```

Command	Description
show mfib	Displays MFIB information in terms of forwarding entries and interfaces.

show mfib summary

To display summary information about the number of MFIB entries and interfaces, use the **show mfib summary** command in user EXEC or privileged EXEC mode.

show mfib summary

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC or Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following is sample output from the **show mfib summary** command:

```
hostname# show mfib summary
IPv6 MFIB summary:

 54      total entries [1 (S,G), 7 (*,G), 46 (*,G/m)]

 17      total MFIB interfaces
```

Related Commands	Command	Description
	show mroute summary	Displays multicast routing table summary information.

show mfib verbose

To display detail information about the forwarding entries and interfaces, use the **show mfib verbose** command in user EXEC or privileged EXEC mode.

show mfib verbose

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC or Privileged EXEC	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Examples The following is sample output from the **show mfib verbose** command:

```

hostname# show mfib verbose
Entry Flags: C - Directly Connected, S - Signal, IA - Inherit A flag,
              AR - Activity Required, D - Drop
Forwarding counts: Pkt Count/Pkts per second/Avg Pkt Size/Kbits per second
Other counts: Total/RPF failed/Other drops
Interface flags: A - Accept, F - Forward, NS - Negate Signalling
                  IC - Internal Copy, NP - Not platform switched
                  SP - Signal Present
Interface Counts: FS Pkt Count/PS Pkt Count
(*,224.0.1.39) Flags: S K
  Forwarding: 0/0/0/0, Other: 0/0/0
(*,224.0.1.40) Flags: S K
  Forwarding: 0/0/0/0, Other: 0/0/0
(*,224.0.0.0/8) Flags: K
  Forwarding: 0/0/0/0, Other: 0/0/0

```

Related Commands	Command	Description
	show mfib	Displays MFIB information in terms of forwarding entries and interfaces.
	show mfib summary	Displays summary information about the number of MFIB entries and interfaces.

show mgcp

To display MGCP configuration and session information, use the **show mgcp** command in privileged EXEC mode.

show mgcp {commands | sessions} [detail]

Syntax Description

commands	Lists the number of MGCP commands in the command queue.
sessions	Lists the number of existing MGCP sessions.
detail	(Optional) Lists additional information about each command (or session) in the output.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **show mgcp commands** command lists the number of MGCP commands in the command queue. The **show mgcp sessions** command lists the number of existing MGCP sessions. The **detail** option includes additional information about each command (or session) in the output.

Examples

The following are examples of the **show mgcp** command options:

```
hostname# show mgcp commands
1 in use, 1 most used, 200 maximum allowed
CRCX, gateway IP: host-pc-2, transaction ID: 2052, idle: 0:00:07

hostname# show mgcp commands detail
1 in use, 1 most used, 200 maximum allowed
CRCX, idle: 0:00:10
  Gateway IP | host-pc-2
  Transaction ID | 2052
  Endpoint name | aaln/1
  Call ID | 9876543210abcdef
  Connection ID |
  Media IP | 192.168.5.7
  Media port | 6058
```

■ show mgcp

```

hostname# show mgcp sessions
1 in use, 1 most used
Gateway IP host-pc-2, connection ID 6789af54c9, active 0:00:11

hostname# show mgcp sessions detail
1 in use, 1 most used
Session active 0:00:14
    Gateway IP | host-pc-2
    Call ID | 9876543210abcdef
    Connection ID | 6789af54c9
    Endpoint name | aaln/1
    Media lcl port 6166
    Media rmt IP | 192.168.5.7
    Media rmt port 6058

```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug mgcp	Enables MGCP debug information.
inspect mgcp	Enables MGCP application inspection.
mgcp-map	Defines an MGCP map and enables MGCP map configuration mode.
show conn	Displays the connection state for different connection types.

show mode

To show the security context mode for the running software image and for any image in Flash memory, use the **show mode** command in privileged EXEC mode.

show mode

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following is sample output from the **show mode** command. The following example shows the current mode and the mode for the non-running image “image.bin”:

```
hostname# show mode flash:/image.bin
Firewall mode: multiple
```

The mode can be multiple or single.

Related Commands	Command	Description
	context	Creates a security context in the system configuration and enters context configuration mode.
	mode	Sets the context mode to single or multiple.

show module

To show information about the SSM on the ASA 5500 series adaptive security appliance as well as system information, use the **show module** command in user EXEC mode.

show module [*slot* [**details**] | **all** | **1 recover**]

Syntax Description

all	(Default) Shows information for the SSM in slot 1 and the system in slot 0.
details	(Optional) Shows additional information, including remote management configuration for intelligent SSMs (for example the AIP SSM).
1 recover	(Optional) For intelligent SSMs, shows the settings for the hw-module module recover command.
<i>slot</i>	(Optional) Specifies the slot number, 0 or 1.

Defaults

Shows information for both slots.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context ¹	System
User EXEC	•	•	•	•	•

1. The **show module recover** command is only available in the system execution space.

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command shows information about the SSM as well as the system and built-in interfaces. See the “[Examples](#)” section for a description of the display output.

Examples

The following is sample output from the **show module** command. Slot 0 is the system, while slot 1 is an SSM.

```

hostname> show module
Mod Card Type                               Model          Serial No.
-----
 0 ASA 5520 Adaptive Security Appliance     ASA5520        XXXXXXXXXXXX
 1 ASA 5500 Series Security Services Module-20 ASA-SSM-20      XXXXXXXXXXXX

Mod MAC Address Range                       Hw Version     Fw Version     Sw Version
-----
 0 000b.fcfc8.c619 to 000b.fcfc8.c61d      1.0             1.0(6)5        7.0(0)77

```

```

1 000b.fcf8.019f to 000b.fcf8.019f 1.0 1.0(6)5 5.0(0.15)S91(0.15)

Mod Status
---
0 Up Sys
1 Up

```

Table 22 shows each field description.

Table 7-26 *show module Fields*

Field	Description
Mod	The slot number, 0 or 1.
Card Type	For the system shown in slot 0, the type is the platform model. For the SSM in slot 1, the SSM type.
Model	The model for this slot.
Serial No.	The serial number.
MAC Address Range	The MAC address range for interfaces on this SSM or, for the system, the built-in interfaces.
Hw Version	The hardware version.
Fw Version	The firmware version.
Sw Version	The software version.
Status	For the system in slot 0, the status is Up Sys. The status of the SSM in slot 1 is as follows: • Initializing—The SSM is being detected and the control communication is being initialized by the system. • Up—The SSM has completed initialization by the system. • Unresponsive—The system encountered an error communicating with this SSM. • Reloading—For intelligent SSMs, the SSM is reloading. • Shutting Down—The SSM is shutting down. • Down—The SSM is shut down. • Recover—For intelligent SSMs, the SSM is attempting to download a recovery image.

The following is sample output from the **show module details** command:

```

hostname> show module 1 details
Getting details from the Service Module, please wait...
ASA 5500 Series Security Services Module-20
Model: ASA-SSM-20
Hardware version: V1.0
Serial Number: 12345678
Firmware version: 1.0(7)2
Software version: 4.1(1.1)S47(0.1)
MAC Address Range: 000b.fcf8.0156 to 000b.fcf8.0156
Status: Up
Mgmt IP addr: 10.89.147.13
Mgmt web ports: 443

```

Mgmt TLS enabled: true

Table 23 shows each field description. See Table 22 for fields that are also shown for the **show module** command.

Table 7-27 *show module details Fields*

Field	Description
Mgmt IP addr	For intelligent SSMs, shows the IP address for the SSM management interface.
Mgmt web ports	For intelligent SSMs, shows the ports configured for the management interface.
Mgmt TLS enabled	For intelligent SSMs, shows whether transport layer security is enabled for connections to the management interface of the SSM (true or false).

The following is sample output from the **show module recover** command:

```
hostname> show module 1 recover
Module 1 recover parameters...
Boot Recovery Image: Yes
Image URL:          tftp://10.21.18.1/ids-oldimg
Port IP Address:    10.1.2.10
Port Mask :        255.255.255.0
Gateway IP Address: 10.1.2.254
```

Related Commands

Command	Description
debug module-boot	Shows debug messages about the SSM booting process.
hw-module module recover	Recovers an intelligent SSM by loading a recovery image from a TFTP server.
hw-module module reset	Shuts down an SSM and performs a hardware reset.
hw-module module reload	Reloads the intelligent SSM software.
hw-module module shutdown	Shuts down the SSM software in preparation for being powered off without losing configuration data.

show mrib client

To display information about the MRIB client connections, use the **show mrib client** command in user EXEC or privileged EXEC mode.

show mrib client [**filter**] [**name** *client_name*]

Syntax Description

filter	(Optional) Displays client filter. Used to view information about the MRIB flags that each client owns and the flags in which each clients is interested.
name <i>client_name</i>	(Optional) Name of a multicast routing protocol that acts as a client of MRIB, such as PIM or IGMP.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC or Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **filter** option is used to display the route and interface level flag changes that various MRIB clients have registered. This command option also shows what flags are owned by the MRIB clients.

Examples

The following sample output from the **show mrib client** command using the **filter** keyword:

```
hostname# show mrib client filter
MFWD:0 (connection id 0)
interest filter:
entry attributes: S C IA D
interface attributes: F A IC NS DP SP
groups:
include 0.0.0.0/0
interfaces:
include All
ownership filter:
groups:
include 0.0.0.0/0
interfaces:
include All
igmp:77964 (connection id 1)
```

show mrib client

```

ownership filter:
interface attributes: II ID LI LD
groups:
include 0.0.0.0/0
interfaces:
include All
pim:49287 (connection id 5)
interest filter:
entry attributes: E
interface attributes: SP II ID LI LD
groups:
include 0.0.0.0/0
interfaces:
include All
ownership filter:
entry attributes: L S C IA D
interface attributes: F A IC NS DP
groups:
include 0.0.0.0/0
interfaces:
include All

```

Related Commands

Command	Description
show mrib route	Displays MRIB table entries.

show mrib route

To display entries in the MRIB table, use the **show mrib route** command in user EXEC or privileged EXEC mode.

show mrib route *[[source | *] [group[/prefix-length]]]*

Syntax Description

<i>*</i>	(Optional) Display shared tree entries.
<i>/prefix-length</i>	(Optional) Prefix length of the MRIB route. A decimal value that indicates how many of the high-order contiguous bits of the address comprise the prefix (the network portion of the address). A slash mark must precede the decimal value.
<i>group</i>	(Optional) IP address or name of the group.
<i>source</i>	(Optional) IP address or name of the route source.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC or Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The MFIB table maintains a subset of entries and flags updated from MRIB. The flags determine the forwarding and signaling behavior according to a set of forwarding rules for multicast packets.

In addition to the list of interfaces and flags, each route entry shows various counters. Byte count is the number of total bytes forwarded. Packet count is the number of packets received for this entry. The **show mrib count** command displays global counters independent of the routes.

Examples

The following is sample output from the **show mrib route** command:

```
hostname# show mrib route
IP Multicast Routing Information Base
Entry flags: L - Domain-Local Source, E - External Source to the Domain,
             C - Directly-Connected Check, S - Signal, IA - Inherit Accept, D - Drop
Interface flags: F - Forward, A - Accept, IC - Internal Copy,
                NS - Negate Signal, DP - Don't Preserve, SP - Signal Present,
                II - Internal Interest, ID - Internal Disinterest, LI - Local Interest,
```

show mrib route

```
LD - Local Disinterest
(*,224.0.0.0/4) RPF nbr: 10.11.1.20 Flags: L C
    Decapstunnel0 Flags: NS

(*,224.0.0.0/24) Flags: D

(*,224.0.1.39) Flags: S

(*,224.0.1.40) Flags: S
    POS0/3/0/0 Flags: II LI

(*,238.1.1.1) RPF nbr: 10.11.1.20 Flags: C
    POS0/3/0/0 Flags: F NS LI
    Decapstunnel0 Flags: A

(*,239.1.1.1) RPF nbr: 10.11.1.20 Flags: C
    POS0/3/0/0 Flags: F NS
    Decapstunnel0 Flags: A
```

Related Commands

Command	Description
show mfib count	Displays route and packet count data for the MFIB table.
show mrib route summary	Displays a summary of the MRIB table entries.

show mroute

To display the IPv4 multicast routing table, use the **show mroute** command in privileged EXEC mode.

show mroute [*group* [*source*] | **reserved**] [**active** [*rate*] | **count** | **pruned** | **summary**]

Syntax Description

active <i>rate</i>	(Optional) Displays only active multicast sources. Active sources are those sending at the specified <i>rate</i> or higher. If the <i>rate</i> is not specified, active sources are those sending at a rate of 4 kbps or higher.
count	(Optional) Displays statistics about the group and source, including number of packets, packets per second, average packet size, and bits per second.
group	(Optional) IP address or name of the multicast group as defined in the DNS hosts table.
pruned	(Optional) Displays pruned routes.
reserved	(Optional) Displays reserved groups.
<i>source</i>	(Optional) Source hostname or IP address.
summary	(Optional) Displays a one-line, abbreviated summary of each entry in the multicast routing table.

Defaults

If not specified, the *rate* argument defaults to 4 kbps.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **show mroute** command displays the contents of the multicast routing table. The security appliance populates the multicast routing table by creating (S,G) and (*,G) entries based on PIM protocol messages, IGMP reports, and traffic. The asterisk (*) refers to all source addresses, the “S” refers to a single source address, and the “G” is the destination multicast group address. In creating (S, G) entries, the software uses the best path to that destination group found in the unicast routing table (through RPF).

To view the **mroute** commands in the running configuration, use the **show running-config mroute** command.

Examples

The following is sample output from the **show mroute** command:

```
hostname(config)# show mroute

Multicast Routing Table
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group,
       C - Connected, L - Local, I - Received Source Specific Host Report,
       P - Pruned, R - RP-bit set, F - Register flag, T - SPT-bit set,
       J - Join SPT
Timers: Uptime/Expires
Interface state: Interface, State

(*, 239.1.1.40), 08:07:24/never, RP 0.0.0.0, flags: DPC
  Incoming interface: Null
  RPF nbr: 0.0.0.0
  Outgoing interface list:
    inside, Null, 08:05:45/never
    tftp, Null, 08:07:24/never

(*, 239.2.2.1), 08:07:44/never, RP 140.0.0.70, flags: SCJ
  Incoming interface: outside
  RPF nbr: 140.0.0.70
  Outgoing interface list:
    inside, Forward, 08:07:44/never
```

The following fields are shown in the **show mroute** output:

- **Flags**—Provides information about the entry.
 - **D—Dense**. Entry is operating in dense mode.
 - **S—Sparse**. Entry is operating in sparse mode.
 - **B—Bidir Group**. Indicates that a multicast group is operating in bidirectional mode.
 - **s—SSM Group**. Indicates that a multicast group is within the SSM range of IP addresses. This flag is reset if the SSM range changes.
 - **C—Connected**. A member of the multicast group is present on the directly connected interface.
 - **L—Local**. The security appliance itself is a member of the multicast group. Groups are joined locally by the **igmp join-group** command (for the configured group).
 - **I—Received Source Specific Host Report**. Indicates that an (S, G) entry was created by an (S, G) report. This (S, G) report could have been created by IGMP. This flag is set only on the DR.
 - **P—Pruned**. Route has been pruned. The software keeps this information so that a downstream member can join the source.
 - **R—RP-bit set**. Indicates that the (S, G) entry is pointing toward the RP.
 - **F—Register flag**. Indicates that the software is registering for a multicast source.
 - **T—SPT-bit set**. Indicates that packets have been received on the shortest path source tree.
 - **J—Join SPT**. For (*, G) entries, indicates that the rate of traffic flowing down the shared tree is exceeding the SPT-Threshold set for the group. (The default SPT-Threshold setting is 0 kbps.) When the J - Join shortest path tree (SPT) flag is set, the next (S, G) packet received down the shared tree triggers an (S, G) join in the direction of the source, thereby causing the security appliance to join the source tree.

For (S, G) entries, indicates that the entry was created because the SPT-Threshold for the group was exceeded. When the J - Join SPT flag is set for (S, G) entries, the security appliance monitors the traffic rate on the source tree and attempts to switch back to the shared tree for this source if the traffic rate on the source tree falls below the SPT-Threshold of the group for more than 1 minute.



Note The security appliance measures the traffic rate on the shared tree and compares the measured rate to the SPT-Threshold of the group once every second. If the traffic rate exceeds the SPT-Threshold, the J - Join SPT flag is set on the (*, G) entry until the next measurement of the traffic rate. The flag is cleared when the next packet arrives on the shared tree and a new measurement interval is started.

If the default SPT-Threshold value of 0 kbps is used for the group, the J - Join SPT flag is always set on (*, G) entries and is never cleared. When the default SPT-Threshold value is used, the security appliance immediately switches to the shortest path source tree when traffic from a new source is received.

- **Timers:Uptime/Expires**—Uptime indicates per interface how long (in hours, minutes, and seconds) the entry has been in the IP multicast routing table. Expires indicates per interface how long (in hours, minutes, and seconds) until the entry will be removed from the IP multicast routing table.
- **Interface state**—Indicates the state of the incoming or outgoing interface.
 - **Interface**—The interface name listed in the incoming or outgoing interface list.
 - **State**—Indicates that packets will either be forwarded, pruned, or null on the interface depending on whether there are restrictions due to access lists or a time-to-live (TTL) threshold.
- **(*, 239.1.1.40) and (*, 239.2.2.1)**—Entries in the IP multicast routing table. The entry consists of the IP address of the source followed by the IP address of the multicast group. An asterisk (*) in place of the source indicates all sources.
- **RP**—Address of the RP. For routers and access servers operating in sparse mode, this address is always 224.0.0.0.
- **Incoming interface**—Expected interface for a multicast packet from the source. If the packet is not received on this interface, it is discarded.
- **RPF nbr**—IP address of the upstream router to the source.
- **Outgoing interface list**—Interfaces through which packets will be forwarded.

Related Commands

Command	Description
clear configure mroute	Removes the mroute commands from the running configuration.
mroute	Configures a static multicast route.
show mroute	Displays IPv4 multicast routing table.
show running-config mroute	Displays configured multicast routes.

show nameif

To view the interface name set using the **nameif** command, use the show nameif command in privileged EXEC mode.

show nameif [*physical_interface* [.*subinterface*] | *mapped_name*]

Syntax Description

mapped_name	(Optional) In multiple context mode, identifies the mapped name if it was assigned using the allocate-interface command.
<i>physical_interface</i>	(Optional) Identifies the interface ID, such as gigabitethernet0/1 . See the interface command for accepted values.
subinterface	(Optional) Identifies an integer between 1 and 4294967293 designating a logical subinterface.

Defaults

If you do not specify an interface, the security appliance shows all interface names.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

In multiple context mode, if you mapped the interface ID in the **allocate-interface** command, you can only specify the mapped name in a context. The output for this command shows only the mapped name in the Interface column.

Examples

The following is sample output from the **show nameif** command:

```
hostname# show nameif
Interface      Name      Security
GigabitEthernet0/0  outside  0
GigabitEthernet0/1  inside   100
GigabitEthernet0/2  test2    50
```


Related Commands

Command	Description
allocate-interface	Assigns interfaces and subinterfaces to a security context.
interface	Configures an interface and enters interface configuration mode.
nameif	Sets the interface name.
show interface ip brief	Shows the interface IP address and status.

show ntp associations

To view NTP association information, use the **show ntp associations** command in user EXEC mode.

show ntp associations [detail]

Syntax Description

detail (Optional) Shows additional details about each association.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC	•	•	•	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

See the “[Examples](#)” section for a description of the display output.

Examples

The following is sample output from the **show ntp associations** command:

```
hostname> show ntp associations
  address      ref clock    st  when  poll  reach  delay  offset  disp
~172.31.32.2   172.31.32.1    5   29  1024  377    4.2   -8.59   1.6
+~192.168.13.33 192.168.1.111    3   69   128  377    4.1    3.48   2.3
*~192.168.13.57 192.168.1.111    3   32   128  377    7.9   11.18   3.6
* master (syncd), # master (unsyncd), + selected, - candidate, ~ configured
```

[Table 7-26](#) shows each field description.

Table 7-28 *show ntp associations Fields*

Field	Description
(leading characters in display lines)	The first characters in a display line can be one or more of the following characters: • * —Synchronized to this peer. • # —Almost synchronized to this peer. • + —Peer selected for possible synchronization. • - —Peer is a candidate for selection. • ~ —Peer is statically configured, but not synchronized.
address	The address of the NTP peer.
ref clock	The address of the reference clock of the peer.
st	The stratum of the peer.
when	The time since the last NTP packet was received from the peer.
poll	The polling interval (in seconds).
reach	The peer reachability (as a bit string, in octal).
delay	The round-trip delay to the peer (in milliseconds).
offset	The relative time of the peer clock to the local clock (in milliseconds).
disp	The dispersion value.

The following is sample output from the **show ntp associations detail** command:

```
hostname> show ntp associations detail
172.23.56.249 configured, our_master, sane, valid, stratum 4
ref ID 172.23.56.225, time c0212639.2ecfc9e0 (20:19:05.182 UTC Fri Feb 22 2002)
our mode client, peer mode server, our poll intvl 128, peer poll intvl 128
root delay 38.04 msec, root disp 9.55, reach 177, sync dist 156.021
delay 4.47 msec, offset -0.2403 msec, dispersion 125.21
precision 2**19, version 3
org time c02128a9.731f127b (20:29:29.449 UTC Fri Feb 22 2002)
rcv time c02128a9.73c1954b (20:29:29.452 UTC Fri Feb 22 2002)
xmt time c02128a9.6b3f729e (20:29:29.418 UTC Fri Feb 22 2002)
filtdelay =      4.47      4.58      4.97      5.63      4.79      5.52      5.87      0.00
filtoffset =    -0.24    -0.36    -0.37      0.30    -0.17      0.57    -0.74      0.00
filtererror =      0.02      0.99      1.71      2.69      3.66      4.64      5.62    16000.0
```

Table 7-27 shows each field description.

Table 7-29 *show ntp associations detail Fields*

Field	Description
IP-address configured	The server (peer) IP address.
(status)	• our_master—The security appliance is synchronized to this peer. • selected—Peer is selected for possible synchronization. • candidate—Peer is a candidate for selection.

Table 7-29 *show ntp associations detail Fields (continued)*

Field	Description
(sanity)	- sane—The peer passes basic sanity checks. - insane—The peer fails basic sanity checks.
(validity)	- valid—The peer time is believed to be valid. - invalid—The peer time is believed to be invalid. - leap_add—The peer is signalling that a leap second will be added. - leap-sub—The peer is signalling that a leap second will be subtracted.
stratum	The stratum of the peer.
(reference peer)	unsynced—The peer is not synchronized to any other machine. ref ID—The address of the machine that the peer is synchronized to.
time	The last time stamp the peer received from its master.
our mode client	Our mode relative to the peer, which is always client.
peer mode server	The peer's mode relative to us, which is always server.
our poll intvl	Our poll interval to the peer.
peer poll intvl	The peer poll interval to us.
root delay	The delay along the path to the root (ultimate stratum 1 time source).
root disp	The dispersion of the path to the root.
reach	The peer reachability (as a bit string in octal).
sync dist	The peer synchronization distance.
delay	The round-trip delay to the peer.
offset	The offset of the peer clock relative to our clock.
dispersion	The dispersion of the peer clock.
precision	The precision of the peer clock (in hertz).
version	The NTP version number that the peer is using.
org time	The originate time stamp.
rcv time	The receive time stamp.
xmt time	The transmit time stamp.
filtdelay	The round-trip delay (in milliseconds) of each sample.
filtoffset	The clock offset (in milliseconds) of each sample.
filtererror	The approximate error of each sample.

Related Commands

Command	Description
ntp authenticate	Enables NTP authentication.
ntp authentication-key	Sets an encrypted authentication key to synchronize with an NTP server.
ntp server	Identifies an NTP server.

Command	Description
ntp trusted-key	Provides a key ID for the security appliance to use in packets for authentication with an NTP server.
show ntp status	Shows the status of the NTP association.

show ntp status

To show the status of each NTP association, use the **show ntp status** command in user EXEC mode.

show ntp status

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC	•	•	•	—	•

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines See the “[Examples](#)” section for a description of the display output.

Examples The following is sample output from the **show ntp status** command:

```
hostname> show ntp status
Clock is synchronized, stratum 5, reference is 172.23.56.249
nominal freq is 99.9984 Hz, actual freq is 100.0266 Hz, precision is 2**6
reference time is c02128a9.73c1954b (20:29:29.452 UTC Fri Feb 22 2002)
clock offset is -0.2403 msec, root delay is 42.51 msec
root dispersion is 135.01 msec, peer dispersion is 125.21 msec
```

[Table 7-28](#) shows each field description.

Table 7-30 *show ntp status Fields*

Field	Description
Clock	- synchronized—The security appliance is synchronized to an NTP server. - unsynchronized—The security appliance is not synchronized to an NTP server.
stratum	NTP stratum of this system.

Table 7-30 *show ntp status Fields*

Field	Description
reference	The address of the NTP server to which the security appliance is synchronized.
nominal freq	The nominal frequency of the system hardware clock.
actual freq	The measured frequency of the system hardware clock.
precision	The precision of the clock of this system (in hertz).
reference time	The reference time stamp.
clock offset	The offset of the system clock to the synchronized peer.
root delay	The total delay along the path to the root clock.
root dispersion	The dispersion of the root path.
peer dispersion	The dispersion of the synchronized peer.

Related Commands

Command	Description
ntp authenticate	Enables NTP authentication.
ntp authentication-key	Sets an encrypted authentication key to synchronize with an NTP server.
ntp server	Identifies an NTP server.
ntp trusted-key	Provides a key ID for the security appliance to use in packets for authentication with an NTP server.
show ntp associations	Shows the NTP servers with which the security appliance is associated.

show ospf

To display the general information about the OSPF routing processes, use the **show ospf** command in privileged EXEC mode.

show ospf [*pid* [*area_id*]]

Syntax Description	<i>area_id</i>	(Optional) ID of the area that is associated with the OSPF address range.
	<i>pid</i>	(Optional) The ID of the OSPF process.

Defaults Lists all OSPF processes if no *pid* is specified.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines If the *pid* is included, only information for the specified routing process is included.

Examples The following is sample output from the **show ospf** command, showing how to display general information about a specific OSPF routing process:

```
hostname# show ospf 5
Routing Process "ospf 5" with ID 127.0.0.1 and Domain ID 0.0.0.5
Supports only single TOS(TOS0) routes
Supports opaque LSA
SPF schedule delay 5 secs, Hold time between two SPFs 10 secs
Minimum LSA interval 5 secs. Minimum LSA arrival 1 secs
Number of external LSA 0. Checksum Sum 0x      0
Number of opaque AS LSA 0. Checksum Sum 0x      0
Number of DCbitless external and opaque AS LSA 0
Number of DoNotAge external and opaque AS LSA 0
Number of areas in this router is 0. 0 normal 0 stub 0 nssa
External flood list length 0
```

The following is sample output from the **show ospf** command, showing how to display general information about all OSPF routing processes:

```
hostname# show ospf
Routing Process "ospf 5" with ID 127.0.0.1 and Domain ID 0.0.0.5
```



```

Supports only single TOS(TOS0) routes
Supports opaque LSA
SPF schedule delay 5 secs, Hold time between two SPFs 10 secs
Minimum LSA interval 5 secs. Minimum LSA arrival 1 secs
Number of external LSA 0. Checksum Sum 0x      0
Number of opaque AS LSA 0. Checksum Sum 0x      0
Number of DCbitless external and opaque AS LSA 0
Number of DoNotAge external and opaque AS LSA 0
Number of areas in this router is 0. 0 normal 0 stub 0 nssa
External flood list length 0

Routing Process "ospf 12" with ID 172.23.59.232 and Domain ID 0.0.0.12
Supports only single TOS(TOS0) routes
Supports opaque LSA
SPF schedule delay 5 secs, Hold time between two SPFs 10 secs
Minimum LSA interval 5 secs. Minimum LSA arrival 1 secs
Number of external LSA 0. Checksum Sum 0x      0
Number of opaque AS LSA 0. Checksum Sum 0x      0
Number of DCbitless external and opaque AS LSA 0
Number of DoNotAge external and opaque AS LSA 0
Number of areas in this router is 0. 0 normal 0 stub 0 nssa
External flood list length 0

```

Related Commands

Command	Description
router ospf	Enables OSPF routing and configures global OSPF routing parameters.

show ospf border-routers

To display the internal OSPF routing table entries to ABRs and ASBRs, use the **show ospf border-routers** command in privileged EXEC mode.

show ospf border-routers

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Release	Modification
Preexisting	This command was preexisting.

Examples The following is sample output from the **show ospf border-routers** command:

```
hostname# show ospf border-routers
```

```
OSPF Process 109 internal Routing Table
```

```
Codes: i - Intra-area route, I - Inter-area route
```

```
i 192.168.97.53 [10] via 192.168.1.53, fifth, ABR, Area 0, SPF 20
```

```
i 192.168.103.51 [10] via 192.168.96.51, outside, ASBR, Area 192.168.12.0, SPF 14
```

```
i 192.168.103.52 [10] via 192.168.96.51, outside, ABR/ASBR, Area 192.168.12.0, SPF 14
```

Command	Description
router ospf	Enables OSPF routing and configures global OSPF routing parameters.

show ospf database

To display the information contained in the OSPF topological database on the security appliance, use the **show ospf database** command in privileged EXEC mode.

```
show ospf [pid [area_id]] database [router | network | summary | asbr-summary | external | nssa-external] [lsid] [internal] [self-originate | adv-router addr]
```

```
show ospf [pid [area_id]] database database-summary
```

Syntax Description

<i>addr</i>	(Optional) Router address.
adv-router	(Optional) Advertised router.
<i>area_id</i>	(Optional) ID of the area that is associated with the OSPF address range.
asbr-summary	(Optional) Displays an ASBR list summary.
database	Displays the database information.
database-summary	(Optional) Displays the complete database summary list.
external	(Optional) Displays routes external to a specified autonomous system.
internal	(Optional) Routes that are internal to a specified autonomous system.
<i>lsid</i>	(Optional) LSA ID.
network	(Optional) Displays the OSPF database information about the network.
nssa-external	(Optional) Displays the external not-so-stubby-area list.
<i>pid</i>	(Optional) ID of the OSPF process.
router	(Optional) Displays the router.
self-originate	(Optional) Displays the information for the specified autonomous system.
summary	(Optional) Displays a summary of the list.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The OSPF routing-related **show** commands are available in privileged mode on the security appliance. You do not need to be in an OSPF configuration mode to use the OSPF-related **show** commands.

Examples

The following is sample output from the **show ospf database** command:

```
hostname# show ospf database
OSPF Router with ID(192.168.1.11) (Process ID 1)

          Router Link States(Area 0)
Link ID  ADV Router   Age   Seq# Checksum Link count
192.168.1.8 192.168.1.8 1381 0x8000010D 0xEF60 2
192.168.1.11 192.168.1.11 1460 0x800002FE 0xEB3D 4
192.168.1.12 192.168.1.12 2027 0x80000090 0x875D 3
192.168.1.27 192.168.1.27 1323 0x800001D6 0x12CC 3

          Net Link States(Area 0)
Link ID ADV Router   Age   Seq# Checksum
172.16.1.27 192.168.1.27 1323 0x8000005B 0xA8EE
172.17.1.11 192.168.1.11 1461 0x8000005B 0x7AC

          Type-10 Opaque Link Area Link States (Area 0)
Link ID ADV Router   Age Seq# Checksum Opaque ID
10.0.0.0 192.168.1.11 1461 0x800002C8 0x8483 0
10.0.0.0 192.168.1.12 2027 0x80000080 0xF858 0
10.0.0.0 192.168.1.27 1323 0x800001BC 0x919B 0
10.0.0.1 192.168.1.11 1461 0x8000005E 0x5B43 1
```

The following is sample output from the **show ospf database asbr-summary** command:

```
hostname# show ospf database asbr-summary
OSPF Router with ID(192.168.239.66) (Process ID 300)
Summary ASB Link States(Area 0.0.0.0)
Routing Bit Set on this LSA
LS age: 1463
Options: (No TOS-capability)
LS Type: Summary Links(AS Boundary Router)
Link State ID: 172.16.245.1 (AS Boundary Router address)
Advertising Router: 172.16.241.5
LS Seq Number: 80000072
Checksum: 0x3548
Length: 28
Network Mask: 0.0.0.0
TOS: 0 Metric: 1
```

The following is sample output from the **show ospf database router** command:

```
hostname# show ospf database router
OSPF Router with id(192.168.239.66) (Process ID 300)
Router Link States(Area 0.0.0.0)
Routing Bit Set on this LSA
LS age: 1176
Options: (No TOS-capability)
LS Type: Router Links
Link State ID: 10.187.21.6
Advertising Router: 10.187.21.6
LS Seq Number: 80002CF6
Checksum: 0x73B7
Length: 120
AS Boundary Router
Number of Links: 8
Link connected to: another Router (point-to-point)
(link ID) Neighboring Router ID: 10.187.21.5
```

```
(Link Data) Router Interface address: 10.187.21.6
Number of TOS metrics: 0
TOS 0 Metrics: 2
```

The following is sample output from the **show ospf database network** command:

```
hostname# show ospf database network
OSPF Router with id(192.168.239.66) (Process ID 300)
Displaying Net Link States(Area 0.0.0.0)
LS age: 1367
Options: (No TOS-capability)
LS Type: Network Links
Link State ID: 10.187.1.3 (address of Designated Router)
Advertising Router: 192.168.239.66
LS Seq Number: 800000E7
Checksum: 0x1229
Length: 52
Network Mask: 255.255.255.0
Attached Router: 192.168.239.66
Attached Router: 10.187.241.5
Attached Router: 10.187.1.1
Attached Router: 10.187.54.5
Attached Router: 10.187.1.5
```

The following is sample output from the **show ospf database summary** command:

```
hostname# show ospf database summary
OSPF Router with id(192.168.239.66) (Process ID 300)
Displaying Summary Net Link States(Area 0.0.0.0)
LS age: 1401
Options: (No TOS-capability)
LS Type: Summary Links(Network)
Link State ID: 10.187.240.0 (summary Network Number)
Advertising Router: 10.187.241.5
LS Seq Number: 80000072
Checksum: 0x84FF
Length: 28
Network Mask: 255.255.255.0 TOS: 0 Metric: 1
```

The following is sample output from the **show ospf database external** command:

```
hostname# show ospf database external
OSPF Router with id(192.168.239.66) (Autonomous system 300)

Displaying AS External Link States
LS age: 280
Options: (No TOS-capability)
LS Type: AS External Link
Link State ID: 172.16.0.0 (External Network Number)
Advertising Router: 10.187.70.6
LS Seq Number: 80000AFD
Checksum: 0xC3A
Length: 36
Network Mask: 255.255.0.0

Metric Type: 2 (Larger than any link state path)
TOS: 0
Metric: 1
Forward Address: 0.0.0.0
External Route Tag: 0
```

 `show ospf database`**Related Commands**

Command	Description
<code>router ospf</code>	Enables OSPF routing and configures global OSPF routing parameters.

show ospf flood-list

To display a list of OSPF LSAs waiting to be flooded over an interface, use the **show ospf flood-list** command in privileged EXEC mode.

show ospf flood-list *interface_name*

Syntax Description	<i>interface_name</i>	The name of the interface for which to display neighbor information.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines	The OSPF routing-related show commands are available in privileged mode on the security appliance. You do not need to be in an OSPF configuration mode to use the OSPF-related show commands.

Examples	The following is sample output from the show ospf flood-list command:

```
hostname# show ospf flood-list outside
```

```
Interface outside, Queue length 20
Link state flooding due in 12 msec
```

Type	LS ID	ADV RTR	Seq NO	Age	Checksum
5	10.2.195.0	192.168.0.163	0x80000009	0	0xFB61
5	10.1.192.0	192.168.0.163	0x80000009	0	0x2938
5	10.2.194.0	192.168.0.163	0x80000009	0	0x757
5	10.1.193.0	192.168.0.163	0x80000009	0	0x1E42
5	10.2.193.0	192.168.0.163	0x80000009	0	0x124D
5	10.1.194.0	192.168.0.163	0x80000009	0	0x134C

Related Commands	Command	Description
	router ospf	Enables OSPF routing and configures global OSPF routing parameters.

show ospf interface

To display the OSPF-related interface information, use the **show ospf interface** command in privileged EXEC mode.

show ospf interface [*interface_name*]

Syntax Description

<i>interface_name</i>	(Optional) Name of the interface for which to display the OSPF-related information.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

When used without the *interface_name* argument, the OSPF information for all interfaces is shown.

Examples

The following is sample output from the **show ospf interface** command:

```
hostname# show ospf interface inside
inside is up, line protocol is up
Internet Address 192.168.254.202, Mask 255.255.255.0, Area 0.0.0.0
AS 201, Router ID 192.77.99.1, Network Type BROADCAST, Cost: 10
Transmit Delay is 1 sec, State OTHER, Priority 1
Designated Router id 192.168.254.10, Interface address 192.168.254.10
Backup Designated router id 192.168.254.28, Interface addr 192.168.254.28
Timer intervals configured, Hello 10, Dead 60, Wait 40, Retransmit 5
Hello due in 0:00:05
Neighbor Count is 8, Adjacent neighbor count is 2
  Adjacent with neighbor 192.168.254.28 (Backup Designated Router)
  Adjacent with neighbor 192.168.254.10 (Designated Router)
```

Related Commands

Command	Description
interface	Opens interface configuration mode.

show ospf neighbor

To display the OSPF-neighbor information on a per-interface basis, use the **show ospf neighbor** command in privileged EXEC mode.

show ospf neighbor [**detail** | *interface_name* [*nbr_router_id*]]

Syntax Description	detail	(Optional) Lists detail information for the specified router.
	<i>interface_name</i>	(Optional) Name of the interface for which to display neighbor information.
	<i>nbr_router_id</i>	(Optional) Router ID of the neighbor router.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Examples The following is sample output from the **show ospf neighbor** command. It shows how to display the OSPF-neighbor information on a per-interface basis.

```
hostname# show ospf neighbor outside

Neighbor 192.168.5.2, interface address 10.225.200.28
  In the area 0 via interface outside
  Neighbor priority is 1, State is FULL, 6 state changes
  DR is 10.225.200.28 BDR is 10.225.200.30
  Options is 0x42
  Dead timer due in 00:00:36
  Neighbor is up for 00:09:46
Index 1/1, retransmission queue length 0, number of retransmission 1
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 1, maximum is 1
Last retransmission scan time is 0 msec, maximum is 0 msec
```

 `show ospf neighbor`**Related Commands**

Command	Description
<code>neighbor</code>	Configures OSPF routers interconnecting to non-broadcast networks.
<code>router ospf</code>	Enables OSPF routing and configures global OSPF routing parameters.

show ospf request-list

To display a list of all LSAs that are requested by a router, use the **show ospf request-list** command in privileged EXEC mode.

show ospf request-list *nbr_router_id interface_name*

Syntax Description

<i>interface_name</i>	Name of the interface for which to display neighbor information. Displays the list of all LSAs that are requested by the router from this interface.
<i>nbr_router_id</i>	Router ID of the neighbor router. Displays the list of all LSAs that are requested by the router from this neighbor.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following is sample output from the **show ospf request-list** command:

```
hostname# show ospf request-list 192.168.1.12 inside

      OSPF Router with ID (192.168.1.11) (Process ID 1)

Neighbor 192.168.1.12, interface inside address 172.16.1.12

Type   LS ID      ADV RTR      Seq NO      Age    Checksum
  1    192.168.1.12  192.168.1.12  0x8000020D   8      0x6572
```

Related Commands

Command	Description
show ospf retransmission-list	Displays a list of all LSAs waiting to be resent.

show ospf retransmission-list

To display a list of all LSAs waiting to be resent, use the **show ospf retransmission-list** command in privileged EXEC mode.

show ospf retransmission-list *nbr_router_id* *interface_name*

Syntax Description

<i>interface_name</i>	Name of the interface for which to display neighbor information.
<i>nbr_router_id</i>	Router ID of the neighbor router.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The OSPF routing-related **show** commands are available in privileged mode on the security appliance. You do not need to be in an OSPF configuration mode to use the OSPF-related **show** commands.

The *nbr_router_id* argument displays the list of all LSAs that are waiting to be resent for this neighbor.

The *interface_name* argument displays the list of all LSAs that are waiting to be resent for this interface.

Examples

The following is sample output from the **show ospf retransmission-list** command, where the *nbr_router_id* argument is 192.168.1.11 and the *if_name* argument is outside:

```
hostname# show ospf retransmission-list 192.168.1.11 outside
```

```
OSPF Router with ID (192.168.1.12) (Process ID 1)
```

```
Neighbor 192.168.1.11, interface outside address 172.16.1.11
Link state retransmission due in 3764 msec, Queue length 2
```

Type	LS ID	ADV RTR	Seq NO	Age	Checksum
1	192.168.1.12	192.168.1.12	0x80000210	0	0xB196

Related Commands

Command	Description
show ospf request-list	Displays a list of all LSAs that are requested by a router.

show ospf summary-address

To display a list of all summary address redistribution information that is configured under an OSPF process, use the **show ospf summary-address** command in privileged EXEC mode.

show ospf summary-address

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Release	Modification
Preexisting	This command was preexisting.

Examples The following shows sample output from the **show ospf summary-address** command. It shows how to display a list of all summary address redistribution information before a summary address has been configured for an OSPF process with the ID of 5.

```
hostname# show ospf 5 summary-address
```

```
OSPF Process 2, Summary-address
```

```
10.2.0.0/255.255.0.0 Metric -1, Type 0, Tag 0
10.2.0.0/255.255.0.0 Metric -1, Type 0, Tag 10
```

Command	Description
summary-address	Creates aggregate addresses for OSPF.

show ospf virtual-links

To display the parameters and the current state of OSPF virtual links, use the **show ospf virtual-links** command in privileged EXEC mode.

show ospf virtual-links

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Examples The following is sample output from the **show ospf virtual-links** command:

```
hostname# show ospf virtual-links

Virtual Link to router 192.168.101.2 is up
Transit area 0.0.0.1, via interface Ethernet0, Cost of using 10
Transmit Delay is 1 sec, State POINT_TO_POINT
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 0:00:08
Adjacency State FULL
```

Related Commands	Command	Description
	area virtual-link	Defines an OSPF virtual link.

show perfmon

To display information about the performance of the security appliance, use the **show perfmon** command.

show perfmon

Syntax Description

This command has no arguments or keywords.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	

Command History

Release	Modification
7.0	Support for this command was introduced on the security appliance.
7.0(8)	The following rate outputs were added: TCP Intercept Established Conns, TCP Intercept Attempts, TCP Embryonic Conns Timeout, and Valid Conns Rate in Tcp Intercept.

Usage Guidelines

This command output does not display in a Telnet console session.

The **perfmon** command allows you to monitor the security appliance's performance. The **show perfmon** command allows you to display the information immediately.

Examples

This example shows how to display information about the security appliance performance:

```
hostname(config)# show perfmon
Context: my_context
```

PERFMON STATS:	Current	Average
Xlates	0/s	0/s
Connections	0/s	0/s
TCP Conns	0/s	0/s
UDP Conns	0/s	0/s
URL Access	0/s	0/s
URL Server Req	0/s	0/s
TCP Fixup	0/s	0/s
TCP Intercept Established Conns	0/s	0/s
TCP Intercept Attempts	0/s	0/s
TCP Embryonic Conns Timeout	0/s	0/s

HTTP Fixup	0/s	0/s
FTP Fixup	0/s	0/s
AAA Authen	0/s	0/s
AAA Author	0/s	0/s
AAA Account	0/s	0/s
VALID CONNS RATE in TCP INTERCEPT:		
	Current	Average
	100.00%	100.00%

Related Commands

Command	Description
perfmon	Displays detailed performance monitoring information.

show pim df

To display the bidirectional DF “winner” for a rendezvous point (RP) or interface, use the **show pim df** command in user EXEC or privileged EXEC mode.

show pim df [**winner**] [*rp_address* | *if_name*]

Syntax Description

<i>rp_address</i>	Can be either one of the following: - Name of the RP, as defined in the Domain Name System (DNS) hosts table or with the domain ipv4 host command. - IP address of the RP. This is a multicast IP address in four-part dotted-decimal notation.
<i>if_name</i>	The physical or logical interface name.
winner	(Optional) Displays the DF election winner per interface per RP.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC or privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command also displays the winner metric towards the RP.

Examples

The following is sample output from the **show pim df** command:

```
hostname# show df winner inside
RP          Interface  DF Winner  Metrics
172.16.1.3  Loopback3  172.17.3.2  [110/2]
172.16.1.3  Loopback2  172.17.2.2  [110/2]
172.16.1.3  Loopback1  172.17.1.2  [110/2]
172.16.1.3  inside     10.10.2.3   [0/0]
172.16.1.3  inside     10.10.1.2   [110/2]
```

show pim group-map

To display group-to-protocol mapping table, use the **show pim group-map** command in user EXEC or privileged EXEC mode.

show pim group-map [**info-source**] [*group*]

Syntax Description

<i>group</i>	(Optional) Can be either one of the following: - Name of the multicast group, as defined in the DNS hosts table or with the domain ipv4 host command. - IP address of the multicast group. This is a multicast IP address in four-part dotted-decimal notation.
info-source	(Optional) Displays the group range information source.

Defaults

Displays group-to-protocol mappings for all groups.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC or privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command displays all group protocol address mappings for the RP. Mappings are learned on the security appliance from different clients.

The PIM implementation on the security appliance has various special entries in the mapping table. Auto-rp group ranges are specifically denied from sparse-mode group range. SSM group range also does not fall under sparse-mode. Link Local multicast groups (224.0.0.0–224.0.0.225, as defined by 224.0.0.0/24) are also denied from the sparse-mode group range. The last entry shows all remaining groups in Sparse-Mode with a given RP.

If multiple RPs are configured with the **pim rp-address** command, then the appropriate group range is displayed with their corresponding RPs.

Examples

The following is sample output form the **show pim group-map** command:

```
hostname# show pim group-map
Group Range      Proto  Client Groups  RP address  Info
```

show pim group-map

```

224.0.1.39/32*   DM      static 1      0.0.0.0
224.0.1.40/32*   DM      static 1      0.0.0.0
224.0.0.0/24*    NO      static 0      0.0.0.0
232.0.0.0/8*     SSM     config 0      0.0.0.0
224.0.0.0/4*     SM      autorp 1      10.10.2.2      RPF: POS01/0/3,10.10.3.2

```

In lines 1 and 2, Auto-RP group ranges are specifically denied from the sparse mode group range.

In line 3, link-local multicast groups (224.0.0.0 to 224.0.0.255 as defined by 224.0.0.0/24) are also denied from the sparse mode group range.

In line 4, the PIM Source Specific Multicast (PIM-SSM) group range is mapped to 232.0.0.0/8.

The last entry shows that all the remaining groups are in sparse mode mapped to RP 10.10.3.2.

Related Commands

Command	Description
multicast-routing	Enables multicast routing on the security appliance.
pim rp-address	Configures the address of a PIM rendezvous point (RP).

show pim interface

To display interface-specific information for PIM, use the **show pim interface** command in user EXEC or privileged EXEC mode.

show pim interface [*if_name* | **state-off** | **state-on**]

Syntax Description

<i>if_name</i>	(Optional) The name of an interface. Including this argument limits the displayed information to the specified interface.
state-off	(Optional) Displays interfaces with PIM disabled.
state-on	(Optional) Displays interfaces with PIM enabled.

Defaults

If you do not specify an interface, PIM information for all interfaces is shown.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC or privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The PIM implementation on the security appliance considers the security appliance itself a PIM neighbor. Therefore, the neighbor count column in the output of this command shows one more than the actual number of neighbors.

Examples

The following example displays PIM information for the inside interface:

```
hostname# show pim interface inside
Address      Interface    Ver/   Nbr    Query   DR      DR
              Mode      Count  Intvl  Prior
172.16.1.4   inside      v2/S   2      100 ms  1       172.16.1.4
```

Related Commands

Command	Description
multicast-routing	Enables multicast routing on the security appliance.

show pim join-prune statistic

To display PIM join/prune aggregation statistics, use the **show pim join-prune statistics** command in user EXEC or privileged EXEC mode.

show pim join-prune statistics [*if_name*]

Syntax Description

if_name (Optional) The name of an interface. Including this argument limits the displayed information to the specified interface.

Defaults

If an interface is not specified, this command shows the join/prune statistics for all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC or privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Clear the PIM join/prune statistics with the **clear pim counters** command.

Examples

The following is sample output from the **show pim join-prune statistic** command:

```
hostname# show pim join-prune statistic
```

PIM Average Join/Prune Aggregation for last (1K/10K/50K) packets

Interface	Transmitted			Received		
inside	0 /	0 /	0	0 /	0 /	0
GigabitEthernet1	0 /	0 /	0	0 /	0 /	0
Ethernet0	0 /	0 /	0	0 /	0 /	0
Ethernet3	0 /	0 /	0	0 /	0 /	0
GigabitEthernet0	0 /	0 /	0	0 /	0 /	0
Ethernet2	0 /	0 /	0	0 /	0 /	0

Related Commands

Command	Description
clear pim counters	Clears the PIM traffic counters.

show pim neighbor

To display entries in the PIM neighbor table, use the **show pim neighbor** command in user EXEC or privileged EXEC mode.

show pim neighbor [**count** | **detail**] [*interface*]

Syntax Description

<i>interface</i>	(Optional) The name of an interface. Including this argument limits the displayed information to the specified interface.
count	(Optional) Displays the total number of PIM neighbors and the number of PIM neighbors on each interface.
detail	(Optional) Displays additional address of the neighbor learned through the upstream-detection hello option.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC or privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is used to determine the PIM neighbors known to this router through PIM hello messages. Also, this command indicates that an interface is a designated router (DR) and when the neighbor is capable of bidirectional operation.

The PIM implementation on the security appliance considers the security appliance itself to be a PIM neighbor. Therefore, the security appliance interface is shown in the output of this command. The IP address of the security appliance is indicated by an asterisk next to the address.

Examples

The following is sample output from the **show pim neighbor** command:

```
hostname# show pim neighbor inside
Neighbor Address    Interface    Uptime      Expires     DR   pri   Bidir
10.10.1.1           inside       03:40:36    00:01:41   1    B
10.10.1.2*          inside       03:41:28    00:01:32   1    (DR) B
```

 show pim neighbor**Related Commands**

Command	Description
multicast-routing	Enables multicast routing on the security appliance.

show pim range-list

To display range-list information for PIM, use the **show pim range-list** command in user EXEC or privileged EXEC mode.

show pim range-list [*rp_address*]

Syntax Description

rp_address

Can be either one of the following:

- Name of the RP, as defined in the Domain Name System (DNS) hosts table or with the domain **ipv4 host** command.
- IP address of the RP. This is a multicast IP address in four-part dotted-decimal notation.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC or privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is used to determine the multicast forwarding mode to group mapping. The output also indicates the rendezvous point (RP) address for the range, if applicable.

Examples

The following is sample output from the **show pim range-list** command:

```
hostname# show pim range-list
config SSM Exp: never Src: 0.0.0.0
  230.0.0.0/8 Up: 03:47:09
config BD RP: 172.16.1.3 Exp: never Src: 0.0.0.0
  239.0.0.0/8 Up: 03:47:16
config BD RP: 172.18.1.6 Exp: never Src: 0.0.0.0
  239.100.0.0/16 Up: 03:47:10
config SM RP: 172.18.2.6 Exp: never Src: 0.0.0.0
  235.0.0.0/8 Up: 03:47:09
```

 show pim range-list**Related Commands**

Command	Description
show pim group-map	Displays group-to-PIM mode mapping and active RP information.

show pim topology

To display PIM topology table information, use the **show pim topology** command in user EXEC or privileged EXEC mode.

show pim topology [*group*] [*source*]

Syntax Description

<i>group</i>	(Optional) Can be one of the following: - Name of the multicast group, as defined in the DNS hosts table or with the domain ipv4 host command. - IP address of the multicast group. This is a multicast IP address in four-part dotted-decimal notation.
<i>source</i>	(Optional) Can be one of the following: - Name of the multicast source, as defined in the DNS hosts table or with the domain ipv4 host command. - IP address of the multicast source. This is a multicast IP address in four-part dotted-decimal notation.

Defaults

Topology information for all groups and sources is shown.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC or privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the PIM topology table to display various entries for a given group, (*, G), (S, G), and (S, G)RPT, each with its own interface list.

PIM communicates the contents of these entries through the MRIB, which is an intermediary for communication between multicast routing protocols, such as PIM, local membership protocols, such as Internet Group Management Protocol (IGMP), and the multicast forwarding engine of the system.

The MRIB shows on which interface the data packet should be accepted and on which interfaces the data packet should be forwarded, for a given (S, G) entry. Additionally, the Multicast Forwarding Information Base (MFIB) table is used during forwarding to decide on per-packet forwarding actions.



Note

For forwarding information, use the **show mfib route** command.

Examples

The following is sample output from the **show pim topology** command:

```
hostname# show pim topology

IP PIM Multicast Topology Table
Entry state: (*S,G)[RPT/SPT] Protocol Uptime Info
Entry flags: KAT - Keep Alive Timer, AA - Assume Alive, PA - Probe Alive,
             RA - Really Alive, LH - Last Hop, DSS - Don't Signal Sources,
             RR - Register Received, SR
(*,224.0.1.40) DM Up: 15:57:24 RP: 0.0.0.0
JP: Null(never) RPF: ,0.0.0.0 Flags: LH DSS
  outside          15:57:24  off LI LH

(*,224.0.1.24) SM Up: 15:57:20 RP: 0.0.0.0
JP: Join(00:00:32) RPF: ,0.0.0.0 Flags: LH
  outside          15:57:20  fwd LI LH

(*,224.0.1.60) SM Up: 15:57:16 RP: 0.0.0.0
JP: Join(00:00:32) RPF: ,0.0.0.0 Flags: LH
  outside          15:57:16  fwd LI LH
```

Related Commands

Command	Description
show mrib route	Displays the MRIB table.

show pim topology reserved

To display PIM topology table information for reserved groups, use the **show pim topology reserved** command in user EXEC or privileged EXEC mode.

show pim topology reserved

Syntax Description This command has no arguments or keywords.

Defaults No default behaviors or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC or privileged EXEC	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Examples None.

Command	Description
show pim topology	Displays the PIM topology table.

show pim topology route-count

To display PIM topology table entry counts, use the **show pim topology route-count** command in user EXEC or privileged EXEC mode.

show pim topology route-count [detail]

Syntax Description	detail (Optional) Displays more detailed count information on a per-group basis.

Defaults	No default behaviors or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC or privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	This command displays the count of entries in the PIM topology table. To display more information about the entries, use the show pim topology command.

Examples	The following is sample output from the show pim topology route-count command:

```
hostname# show pim topology route-count
```

```
PIM Topology Table Summary
  No. of group ranges = 5
  No. of (*,G) routes = 0
  No. of (S,G) routes = 0
  No. of (S,G)RPT routes = 0
```

Related Commands	Command	Description
	show pim topology	Displays the PIM topology table.

show pim traffic

To display PIM traffic counters, use the **show pim traffic** command in user EXEC or privileged EXEC mode.

show pim traffic

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC or privileged EXEC	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Usage Guidelines Clear the PIM traffic counters with the **clear pim counters** command.

Examples The following is sample output from the **show pim traffic** command:

```
hostname# show pim traffic

PIM Traffic Counters
Elapsed time since counters cleared: 3d06h

Valid PIM Packets      Received      Sent
Hello                  0             9485
Join-Prune              0             0
Register               0             0
Register Stop          0             0
Assert                 0             0
Bidir DF Election      0             0

Errors:
Malformed Packets      0
Bad Checksums          0
Send Errors            0
Packet Sent on Loopback Errors 0
Packets Received on PIM-disabled Interface 0
Packets Received with Unknown PIM Version 0
```

 show pim traffic

Related Commands	Command	Description
	clear pim counters	Clears the PIM traffic counters.

show pim tunnel

To display information about the PIM tunnel interfaces, use the **show pim tunnels** command in user EXEC or privileged EXEC mode.

show pim tunnels [*if_name*]

Syntax Description

if_name (Optional) The name of an interface. Including this argument limits the displayed information to the specified interface.

Defaults

If an interface is not specified, this command shows the PIM tunnel information for all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
User EXEC or privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

PIM register packets are sent through the virtual encapsulation tunnel interface from the source first hop DR router to the RP. On the RP, a virtual decapsulation tunnel is used to represent the receiving interface of the PIM register packets. This command displays tunnel information for both types of interfaces.

Register tunnels are the encapsulated (in PIM register messages) multicast packets from a source that is sent to the RP for distribution through the shared tree. Registering applies only to SM, not SSM and bidirectional PIM.

Examples

The following is sample output from the **show pim tunnel** command:

```
hostname# show pim tunnel
```

```
Interface      RP Address Source Address
```

```
Encapstunnel0 10.1.1.1   10.1.1.1
```

```
Decapstunnel0 10.1.1.1   -
```

show priority-queue statistics

To display the priority-queue statistics for an interface, use the **show priority-queue statistics** command in privileged EXEC mode.

show priority-queue statistics [*interface-name*]

Syntax Description	<i>interface-name</i>	(Optional) Specifies the name of the interface for which you want to show the best-effort and low-latency queue details.

Defaults	If you omit the interface name, this command shows priority-queue statistics for all configured interfaces.	

Command Modes	The following table shows the modes in which you can enter the command:	

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples This example shows the use of the **show priority-queue statistics** command for the interface named test, and the command output. In this output, BE indicates the best-effort queue, and LLQ represents the low-latency queue:

```
hostname# show priority-queue statistics test

Priority-Queue Statistics interface test

Queue Type      = BE
Packets Dropped = 0
Packets Transmit = 0
Packets Enqueued = 0
Current Q Length = 0
Max Q Length    = 0

Queue Type      = LLQ
Packets Dropped = 0
Packets Transmit = 0
Packets Enqueued = 0
Current Q Length = 0
Max Q Length    = 0
hostname#
```

Related Commands

Command	Description
clear configure priority-queue	Removes the priority-queue configuration from the named interface.
clear priority-queue statistics	Clears the priority-queue statistics counters for an interface or for all configured interfaces
priority-queue	Configures priority queueing on an interface.
show running-config priority-queue	Shows the current priority-queue configuration on the named interface.

show processes

To display a list of the processes that are running on the security appliance, use the **show processes** command in privileged EXEC mode.

show processes [cpu-hog | memory | internals]

Defaults

By default this command displays the processes running on the security appliance.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	Support for this command was introduced on the security appliance.

Usage Guidelines

The **show processes** command allows you to display a list of the processes that are running on the security appliance.

The command can also help determine what process is using the CPU, with the optional **cpu-hog** argument. A process is flagged if it is hogging the CPU for more than 100 milliseconds. The **show process cpu-hog** command displays the following columns when invoked:

- MAXHOG - Maximum CPU hog runtime in milliseconds.
- NUMHOG - Number of CPU hog runs.
- LASTHOG - Last CPU hog runtime in milliseconds.

Processes are lightweight threads requiring only a few instructions. In the listing, PC is the program counter, SP is the stack pointer, STATE is the address of a thread queue, Runtime is the number of milliseconds that the thread has been running based on CPU clock cycles, SBASE is the stack base address, Stack is the current number of bytes that are used and the total size of the stack, and Process lists the thread's function.

The optional **memory** argument displays the memory allocated by each process, to help track memory usage by process.

The optional **internals** argument displays the number of invoked calls and giveups. Invoked is the number of times the scheduler has invoked, or ran, the process. Giveups is the number of times the process yielded the CPU back to the scheduler.

Examples

This example shows how to display a list of processes that are running on the security appliance:

```
hostname(config)# show processes
```

```

      PC      SP      STATE      Runtime      SBASE      Stack Process
Hsi 00102aa0 0a63f288 0089b068      117460 0a63e2d4 3600/4096 arp_timer
Lsi 00102aa0 0a6423b4 0089b068          10 0a64140c 3824/4096 FragDBGc
Hwe 004257c8 0a7cacd4 0082dfd8          0 0a7c9d1c 3972/4096 udp_timer
Lwe 0011751a 0a7cc438 008ea5d0          20 0a7cb474 3560/4096 dbgtrace
<--- More --->

```

hostname(config)# show processes cpu

MAXHOG	NUMHOG	LASTHOG	Process
7720	4	110	Dispatch Unit
7870	331	1010	Checkheaps
(other lines deleted for brevity)			
6170	1	6170	CTM message handle

hostname(config)# show processes memory

Allocs	Allocated (bytes)	Frees	Freed (bytes)	Process
23512	13471545	6	180	*System Main*
0	0	0	0	lu_rx
2	8324	16	19488	vpnlb_thread
(other lines deleted for brevity)				

hostname# sho proc internals

Invoked	Giveups	Process
1	0	block_diag
19108445	19108445	Dispatch Unit
1	0	CF OIR
1	0	Reload Control Thread
1	0	aaa
2	0	CMGR Server Process
1	0	CMGR Timer Process
2	0	dbgtrace
69	0	557mcfix
19108019	19108018	557poll
2	0	557statspoll
1	0	Chunk Manager
135	0	PIX Garbage Collector
6	0	route_process
1	0	IP Address Assign
1	0	QoS Support Module
1	0	Client Update Task
8973	8968	Checkheaps
6	0	Session Manager

 show processes

```
237          235  uauth
(other lines deleted for brevity)
```

show reload

To display the reload status on the security appliance, use the **show reload** command in privileged EXEC mode.

show reload

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines This command has no usage guidelines.

Examples The following example shows that a reload is scheduled for 12:00 a.m. (midnight) on Saturday, April 20:

```
hostname# show reload
Reload scheduled for 00:00:00 PDT Sat April 20 (in 12 hours and 12 minutes)
```

Related Commands	Command	Description
	reload	Reboots and reloads the configuration.

show resource types

To view the resource types for which the security appliance tracks usage, use the **show resource types** command in privileged EXEC mode.

show resource types

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Release	Modification
7.0	This command was introduced.

Examples The following sample display shows the resource types:

```
hostname# show resource types

Absolute limit types:
  Conns           Connections
  Hosts           Hosts
  IPSec           IPSec Mgmt Tunnels
  SSH             SSH Sessions
  Telnet          Telnet Sessions
  Xlates          XLATE Objects
  All             All Resources
```

Related Commands	Command	Description
	clear resource usage	Clears the resource usage statistics
	context	Adds a security context.
	show resource usage	Shows the resource usage of the security appliance.

show resource usage

To view the resource usage of the security appliance or for each context in multiple mode, use the **show resource usage** command in privileged EXEC mode.

```
show resource usage [context context_name | top n | all | summary | system]
[resource {resource_name | all}] [counter counter_name [count_threshold]]
```

Syntax	Description
context <i>context_name</i>	(Multiple mode only) Specifies the context name for which you want to view statistics. Specify all for all contexts; the security appliance lists the context usage for each context.
<i>count_threshold</i>	Sets the number above which resources are shown. The default is 1. If the usage of the resource is below the number you set, then the resource is not shown. If you specify all for the counter name, then the <i>count_threshold</i> applies to the current usage. Note To show all resources, set the <i>count_threshold</i> to 0.
counter <i>counter_name</i>	Shows counts for the following counter types: • current—Shows the active concurrent instances or the current rate of the resource. • peak—Shows the peak concurrent instances, or the peak rate of the resource since the statistics were last cleared, either using the clear resource usage command or because the device rebooted. • all—(Default) Shows all statistics.
resource <i>resource_name</i>	Shows the usage of a specific resource. Specify all (the default) for all resources. Resources include the following types: • conns—TCP or UDP connections between any two hosts, including connections between one host and multiple other hosts. • hosts—Hosts that can connect through the security appliance. • ipsec—(Single mode only) IPSec sessions. • ssh—SSH sessions. • telnet—Telnet sessions. • xlates—NAT translations.
summary	(Multiple mode only) Shows all context usage combined.
system	(Multiple mode only) Shows all context usage combined, but shows the system limits for resources instead of the combined context limits.
top <i>n</i>	(Multiple mode only) Shows the contexts that are the top <i>n</i> users of the specified resource. You must specify a single resource type, and not resource all , with this option.

Defaults

For multiple context mode, the default context is **all**, which shows resource usage for every context. For single mode, the context name is ignored and the output shows the “context” as “System.”

The default resource name is **all**, which shows all resource types.

The default counter name is **all**, which shows all statistics.

The default count threshold is **1**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following is sample output from the **show resource usage context** command, which shows the resource usage for the admin context:

```
hostname# show resource usage context admin
```

Resource	Current	Peak	Limit	Context
Telnet	1	1	5	admin
Conns	44	55	N/A	admin
Hosts	45	56	N/A	admin

The following is sample output from the **show resource usage summary** command, which shows the resource usage for all contexts and all resources. This sample shows the limits for 6 contexts.

```
hostname# show resource usage summary
```

Resource	Current	Peak	Limit	Context
Telnet	3	5	30	Summary
SSH	5	7	30	Summary
Conns	40	55	N/A	Summary
Hosts	44	56	N/A	Summary

The following is sample output from the **show resource usage summary** command, which shows the limits for 25 contexts. Because the context limit for Telnet and SSH connections is 5 per context, then the combined limit is 125. The system limit is only 100, so the system limit is shown.

```
hostname# show resource usage summary
```

Resource	Current	Peak	Limit	Context
Telnet	1	1	100[S]	Summary
SSH	2	2	100[S]	Summary
Conns	56	90	N/A	Summary
Hosts	89	102	N/A	Summary

S = System limit: Combined context limits exceed the system limit; the system limit is shown.

The following is sample output from the **show resource usage system** command, which shows the resource usage for all contexts, but it shows the system limit instead of the combined context limits:

```
hostname# show resource usage system
```

Resource	Current	Peak	Limit	Context
Telnet	3	5	100	System
SSH	5	7	100	System
Conns	40	55	N/A	System
Hosts	44	56	N/A	System

Related Commands

Command	Description
clear resource usage	Clears the resource usage statistics
context	Adds a security context.
show resource types	Shows a list of resource types.

show route

To display a default or static route for an interface, use the **show route** command in privileged EXEC mode.

show route [*interface_name ip_address netmask gateway_ip*]

Syntax Description

<i>gateway_ip</i>	(Optional) IP address of the gateway router (the next-hop address for this route).
<i>interface_name</i>	(Optional) Internal or external network interface name.
<i>ip_address</i>	(Optional) Internal or external network IP address.
<i>netmask</i>	(Optional) Network mask to apply to <i>ip_address</i> .

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following is sample output from the **show route** command:

```
hostname(config)# show route
C    10.30.10.0 255.255.255.0 is directly connected, outside
C    10.40.10.0 255.255.255.0 is directly connected, inside
C    192.168.2.0 255.255.255.0 is directly connected, faillink
C    192.168.3.0 255.255.255.0 is directly connected, statelink
```

Related Commands

Command	Description
clear configure route	Removes the route commands from the configuration that do not contain the connect keyword.
route	Specifies a static or default route for the an interface.
show running-config route	Displays configured routes.

show run fips

To verify the FIPS system location, system contact, and so forth, use the **show run fips** command.

show run fips

Syntax Description	fips	FIPS 140-2 compliance information

Defaults	This command has no default settings.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	—	•	•

Command History	Release	Modification
	7.0(4)	This command was introduced.

Usage Guidelines	The show run fips command displays information about the system configuration.

Examples	<code>sw8-ASA(config)# show run fips</code>

Related Commands	Command	Description
	clear configure fips	Clears the system or module FIPS configuration information stored in NVRAM.
	crashinfo console disable	Disables the reading, writing and configuration of crash write info to flash.
	fips enable	Enables or disablea policy-checking to enforce FIPS compliance on the system or module.
	fips self-test poweron	Executes power-on self-tests.
	service internal	Allows conditional commands that would otherwise be hidden to be shown.
	show crashinfo console	Reads, writes, and configures crash write to flash.
	show running-config fips	Displays the FIPS configuration that is running on the security appliance.

show running-config

To display the configuration that is running on the security appliance, use the **show running-config** command in privileged EXEC mode.

```
show running-config [all] [command]
```

Syntax Description

all	Displays the entire operating configuration, including defaults.
command	Displays the configuration associated with a specific command.

Defaults

If no arguments or keywords are specified, the entire non-default security appliance configuration displays.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was modified.

Usage Guidelines

The **show running-config** command displays the current running configuration on the security appliance.

You can use the **running-config** keyword only in the **show running-config** command. You cannot use this keyword with **no** or **clear**, or as a standalone command, because the CLI treats it as a nonsupported command. When you enter the **?**, **no ?**, or **clear ?** keywords, a **running-config** keyword is not listed in the command list.



Note

The device manager commands appear in the configuration after you use it to connect to or configure the security appliance.

Examples

This example show how to display the configuration that is running on the security appliance:

```
hostname# show running-config
: Saved
:
XXX Version X.X(X)
names
!
```

```
interface Ethernet0
  nameif test
  security-level 10
  ip address 10.10.88.50 255.255.255.254
!
interface Ethernet1
  nameif inside
  security-level 100
  ip address 10.86.194.176 255.255.254.0
!
interface Ethernet2
  shutdown
  no nameif
  security-level 0
  no ip address
!
interface Ethernet3
  shutdown
  no nameif
  security-level 0
  no ip address
!
interface Ethernet4
  shutdown
  no nameif
  security-level 0
  no ip address
!
interface Ethernet5
  shutdown
  no nameif
  security-level 0
  no ip address
!
enable password 8Ry2YjIyt7RRXU24 encrypted
passwd 2KFQnbNIdI.2KYOU encrypted
hostname XXX
domain-name XXX.com
boot system flash:/cdisk.bin
ftp mode passive
pager lines 24
mtu test 1500
mtu inside 1500
monitor-interface test
monitor-interface inside
ASDM image flash:ASDM
no ASDM history enable
arp timeout 14400
route inside 0.0.0.0 0.0.0.0 10.86.194.1 1
timeout xlate 3:00:00
timeout conn 2:00:00 half-closed 1:00:00 udp 0:02:00 icmp 1:00:00 rpc 1:00:00 h3
23 0:05:00 h225 1:00:00 mgcp 0:05:00 mgcp-pat 0:05:00 sip 0:30:00 sip_media 0:02
:00
timeout uauth 0:00:00 absolute
http server enable
http 0.0.0.0 0.0.0.0 inside
no snmp-server location
no snmp-server contact
snmp-server enable traps snmp
fragment size 200 test
fragment chain 24 test
fragment timeout 5 test
fragment size 200 inside
fragment chain 24 inside
```

```

fragment timeout 5 inside
telnet 0.0.0.0 0.0.0.0 inside
telnet timeout 1440
ssh timeout 5
console timeout 0
group-policy todd internal
!
class-map inspection_default
  match default-inspection-traffic
!
!
policy-map xxx_global_fw_policy
class inspection_default
  inspect dns
  inspect ftp
  inspect h323 h225
  inspect h323 ras
  inspect http
  inspect ils
  inspect mgcp
  inspect netbios
  inspect rpc
  inspect rsh
  inspect rtsp
  inspect sip
  inspect skinny
  inspect sqlnet
  inspect tftp
  inspect xdmcp
  inspect ctigbe
  inspect cuseeme
  inspect icmp
!
terminal width 80
service-policy xxx_global_fw_policy global
Cryptochecksum:bfecf4b9d1b98b7e8d97434851f57e14
: end

```

Related Commands

Command	Description
configure	Configures the security appliance from the terminal.

show running-config aaa

To show the AAA configuration in the running configuration, use the **show running-config aaa** command in privileged EXEC mode.

show running-config aaa [**accounting** | **authentication** | **authorization** | **mac-exempt** | **proxy-limit**]

Syntax Description

accounting	(Optional) Show accounting-related AAA configuration.
authentication	(Optional) Show authentication-related AAA configuration.
authorization	(Optional) Show authorization-related AAA configuration.
mac-exempt	(Optional) Show MAC address exemption AAA configuration.
proxy-limit	(Optional) Show the number of concurrent proxy connections allowed per user.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following is sample output from the **show running-config aaa** command:

```
hostname# show running-config aaa
aaa authentication match infrastructure_authentication_radiusvrs infrastructure radiusvrs
aaa accounting match infrastructure_authentication_radiusvrs infrastructure radiusvrs
aaa authentication secure-http-client
aaa local authentication attempts max-fail 16
```

Related Commands

Command	Description
aaa authentication match	Enables authentication for traffic that is identified by an access list.
aaa authorization match	Enables authorization for traffic that is identified by an access list.

Command	Description
aaa accounting match	Enables accounting for traffic that is identified by an access list.
aaa max-exempt	Specifies the use of a predefined list of MAC addresses to exempt from authentication and authorization.
aaa proxy-limit	Configure the uauth session limit by setting the maximum number of concurrent proxy connections allowed per user.

show running-config aaa-server

To display AAA server configuration, use the **show running-config aaa-server** command in privileged EXEC mode.

show running-config [**all**] **aaa-server** [*server-tag*] [(*interface-name*)] [**host** *hostname*]

Syntax Description

all	(Optional) Shows the running configuration, including default configuration values.
host <i>hostname</i>	(Optional) The symbolic name or IP address of the particular host for which you want to display AAA server statistics.
(interface-name)	(Optional) The network interface where the AAA server resides.
<i>server-tag</i>	(Optional) The symbolic name of the server group.

Defaults

Omitting the *server-tag* value displays the configurations for all AAA servers.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	•	—	—	•

Command History

Release	Modification
7.0	This command was modified to adhere to CLI guidelines

Usage Guidelines

Use this command to display the settings for a particular server group. Use the **all** parameter to display the default as well as the explicitly configured values.

Examples

To display the running configuration for the default AAA server group, use the following command:

```
hostname(config)# show running-config default aaa-server

aaa-server group1 protocol tacacs+ accounting-mode simultaneous
reactivation-mode depletion deadtime 10
max-failed-attempts 4
```

 show running-config aaa-server**Related Commands**

Command	Description
show aaa-server	Displays AAA server statistics.
clear configure aaa-server	Clears the AAA server configuration.

show running-config aaa-server host

To display AAA server statistics for a particular server, use the **show running-config aaa-server** command in global configuration or privileged EXEC mode.

show/clear aaa-server

show running-config [**all**] **aaa-server** *server-tag* [(*interface-name*)] **host** *hostname*

Syntax Description	all	(Optional) Shows the running configuration, including default configuration values.
	<i>server-tag</i>	The symbolic name of the server group.

Defaults	Omitting the default keyword displays only the explicitly configured configuration values, not the default values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	—	•
Global configuration	•	•	—	—	•

Command History	Release	Modification
	7.0	This command was modified to adhere to CLI guidelines.

Usage Guidelines	Use this command to display the statistics for a particular server group. Use the default parameter to display the default as well as the explicitly configured values.

Examples	To display the running configuration for the server group svrgrp1, use the following command: hostname(config)# show running-config default aaa-server svrgrp1

Related Commands	Command	Description
	show running-config aaa-server	Displays AAA server settings for the indicated server, group, or protocol.
	clear configure aaa	Removes the settings for all AAA servers across all groups.

show running-config access-group

To display the access group information, use the **show running-config access-group** command in privileged EXEC mode.

show running-config access-group

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
Preexisting	This command was preexisting.

Command History

Examples The following is sample output from the **show running-config access-group** command:

```
hostname# show running-config access-group
access-group 100 in interface outside
```

Command	Description
access-group	Binds an access list to an interface.
clear configure access-group	Removes access groups from all the interfaces.

Related Commands

show running-config access-list

To display the access-list configuration that is running on the security appliance, use the **show running-config access-list** command in privileged EXEC mode.

show running-config [**default**] **access-list** [**alert-interval** | **deny-flow-max**]

show running-config [**default**] **access-list** *id* [*saddr_ip*]

Syntax Description

alert-interval	Shows the alert interval for generating syslog message 106001, which alerts that the system has reached a deny flow maximum.
deny-flow-max	Shows the maximum number of concurrent deny flows that can be created.
<i>id</i>	Identifies the access list that is displayed.
<i>saddr_ip</i>	Shows the access list elements that contain the specified source IP address.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	Added keyword running-config .

Usage Guidelines

The **show running-config access-list** command allows you to display the current running access list configuration on the security appliance.

Examples

The following is sample output from the **show running-config access-list** command:

```
hostname# show running-config access-list
access-list allow-all extended permit ip any any
```

Related Commands

Command	Description
access-list ethertype	Configures an access list that controls traffic based on its EtherType.
access-list extended	Adds an access list to the configuration and configures policy for IP traffic through the firewall.

Command	Description
access-list ethertype	Configures an access list that controls traffic based on its EtherType.
clear access-list	Clears an access list counter.
clear configure access-list	Clears an access list from the running configuration.

show running-config alias

To display the overlapping addresses with dual NAT commands in the configuration, use the **show running-config alias** command in privileged EXEC mode.

show running-config alias {*interface_name*}

Syntax Description

interface_name Internal network interface name that the destination_ip overwrites.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

This example shows how to display alias information:

```
hostname# show running-config alias
```

Related Commands

Command	Description
alias	Creates an alias.
clear configure alias	Deletes an alias.

show running-config arp

To show static ARP entries created by the **arp** command in the running configuration, use the **show running-config arp** command in privileged EXEC mode.

show running-config arp

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	This command was introduced.

Examples The following is sample output from the **show running-config arp** command:

```
hostname# show running-config arp
arp inside 10.86.195.11 0008.023b.9893
```

Command	Description
arp	Adds a static ARP entry.
arp-inspection	For transparent firewall mode, inspects ARP packets to prevent ARP spoofing.
show arp	Shows the ARP table.
show arp statistics	Shows ARP statistics.

show running-config arp timeout

To view the ARP timeout configuration in the running configuration, use the **show running-config arp timeout** command in privileged EXEC mode.

show running-config arp timeout

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	This command was changed from show arp timeout .

Command History

Examples The following is sample output from the **show running-config arp timeout** command:

```
hostname# show running-config arp timeout
arp timeout 20000 seconds
```

Related Commands	Command	Description
	arp	Adds a static ARP entry.
	arp timeout	Sets the time before the security appliance rebuilds the ARP table.
	arp-inspection	For transparent firewall mode, inspects ARP packets to prevent ARP spoofing.
	show arp statistics	Shows ARP statistics.

show running-config arp-inspection

To view the ARP inspection configuration in the running configuration, use the **show running-config arp-inspection** command in privileged EXEC mode.

show running-config arp-inspection

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	—	•	•	•	—

Release	Modification
7.0	This command was changed from show arp timeout .

Examples The following is sample output from the **show running-config arp-inspection** command:

```
hostname# show running-config arp-inspection
```

```
arp-inspection inside1 enable no-flood
```

Related Commands	Command	Description
	arp	Adds a static ARP entry.
	arp-inspection	For transparent firewall mode, inspects ARP packets to prevent ARP spoofing.
	clear configure arp-inspection	Clears the ARP inspection configuration.
	firewall transparent	Sets the firewall mode to transparent.
	show arp statistics	Shows ARP statistics.

show running-config asdm

To display the **asdm** commands in the running configuration, use the **show running-config asdm** command in privileged EXEC mode.

show running-config asdm [**group** | **location**]

Syntax Description

group	(Optional) Limits the display to the asdm group commands in the running configuration.
location	(Optional) Limits the display to the asdm location commands in the running configuration.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was changed from the show running-config pdm command to the show running-config asdm command.

Usage Guidelines

To remove the **asdm** commands from the configuration, use the **clear configure asdm** command.



Note

On security appliances running in multiple context mode, the **show running-config asdm group** and **show running-config asdm location** commands are only available in the system execution space.

Examples

The following is sample output from the **show running-configuration asdm** command:

```
hostname# show running-config asdm
asdm image flash:/ASDM
asdm history enable
hostname#
```

 show running-config asdm**Related Commands**

Command	Description
show asdm image	Displays the current ASDM image file.

show running-config auth-prompt

To displays the current authentication prompt challenge text, use the `show running-config auth-prompt` command in global configuration mode.

show running-config [default] auth-prompt

Syntax Description	default (Optional) Display the default authentication prompt challenge text.

Defaults	Display the configured authentication prompt challenge text.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History	Release	Modification
	7.0	This command was modified for this release to conform to CLI guidelines.

Usage Guidelines	After you configure the authentication prompt with the auth-prompt command, use the show running-config auth-prompt command to view the current prompt text.

Examples	The following example shows the output of the show running-config auth-prompt command:

```
hostname(config)# show running-config auth-prompt
auth-prompt prompt Please login:
auth-prompt accept You're in!
auth-prompt reject Try again.
```

Related Commands	auth-prompt	Set the user authorization prompts.
	clear configure auth-prompt	Reset the user authorization prompts to the default value.

show running-config banner

To display the specified banner and all the lines that are configured for it, use the **show running-config banner** command in privileged EXEC mode.

show running-config banner [exec | login | motd]

Syntax Description

exec	(Optional) Displays the banner before the enable prompt.
login	(Optional) Displays the banner before the password login prompt when accessing the security appliance using Telnet.
motd	(Optional) Displays the message-of-the-day banner.

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	The running-config keyword was added.

Usage Guidelines

The **show running-config banner** command displays the specified banner keyword and all the lines configured for it. If a keyword is not specified, then all banners display.

Examples

This example shows how to display the message-of-the-day (motd) banner:

```
hostname# show running-config banner motd
```

Related Commands

Command	Description
banner	Creates a banner.
clear configure banner	Deletes a banner.

show running-config class-map

To display the information about the class map configuration, use the **show running-config class-map** command in privileged EXEC mode.

show running-config [**all**] **class-map** [*class_map_name*]

Syntax Description

all	(Optional) Show all running class map configuration, including default.
<i>class_map_name</i>	(Optional) Text for the class map name; the text can be up to 40 characters in length.

Defaults

The **class-map class-default** command, which contains a single **match any** command is the default class map.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	Added keyword running-config .

Examples

The following is sample output from the **show running-config class-map** command:

```
hostname# show running-config class-map
class-map tcp-port
  match port tcp eq ftp
```

Related Commands

Command	Description
class-map	Applies a traffic class to an interface.
clear configure class-map	Removes all of the traffic map definitions.

show running-config clock

To show the clock configuration in the running configuration, use the **show running-config clock** command in privileged EXEC mode.

show running-config [all] clock

Syntax Description	all	(Optional) Shows all clock commands, including the commands you have not changed from the default.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	The all keyword also displays the exact day and time for the clock summer-time command, as well as the default setting for the offset, if you did not originally set it.

Examples	The following is sample output from the show running-config clock command. Only the clock summer-time command was set.

```
hostname# show running-config clock
clock summer-time EDT recurring
```

The following is sample output from the **show running-config all clock** command. The default setting for the unconfigured **clock timezone** command displays, and the detailed information for the **clock summer-time** command displays.

```
hostname# show running-config all clock
clock timezone UTC 0
clock summer-time EDT recurring 1 Sun Apr 2:00 last Sun Oct 2:00 60
```

Related Commands

Command	Description
clock set	Manually sets the clock on the security appliance.
clock summer-time	Sets the date range to show daylight saving time.
clock timezone	Sets the time zone.

show running-config command-alias

To display the command aliases that are configured, use the **show running-config command-alias** command in privileged EXEC mode.

show running-config [all] command-alias

Syntax Description	all (Optional) Displays all command aliases configured, including defaults.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	If you do not enter the all keyword, only non-default command aliases display.

Examples	The following example displays all command aliases that are configured on the security appliance, <i>including</i> defaults:

```
hostname# show running-config all command-alias
command-alias exec h help
command-alias exec lo logout
command-alias exec p ping
command-alias exec s show
command-alias exec save copy running-config startup-config
```

The following example displays all command aliases that are configured on the security appliance, *excluding* defaults:

```
hostname# show running-config command-alias
command-alias exec save copy running-config startup-config
hostname#
```

Related Commands

Command	Description
command-alias	Creates a command alias.
clear configure command-alias	Deletes all non-default command aliases.

show running-config console timeout

To display the console connection timeout value, use the **show running-config console timeout** command in privileged EXEC mode.

show running-config console timeout

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
7.0	The running-config keyword was added.

Examples The following example shows how to display the console connection timeout setting:

```
hostname# show running-config console timeout
console timeout 0
```

Command	Description
console timeout	Sets the idle timeout for a console connection to the security appliance.
clear configure console	Resets the console connection settings to defaults.

show running-config context

To show the context configuration in the system execution space, use the **show running-config context** command in privileged EXEC mode.

show running-config context

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	—	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following is sample output from the **show running-config context** command:

```
hostname# show running-config context

admin-context admin
context admin
  allocate-interface GigabitEthernet0/0
  config-url flash:/admin.cfg
!

context A
  allocate-interface GigabitEthernet0/1
  config-url flash:/A.cfg
!
```

Related Commands	Command	Description
	admin-context	Sets the admin context.
	allocate-interface	Assigns interfaces to a context.
	changeto	Changes between contexts or the system execution space.
	config-url	Specifies the location of the context configuration.
	context	Creates a security context in the system configuration and enters context configuration mode.

show running-config crypto

To display the entire crypto configuration including IPSec, crypto maps, dynamic crypto maps, and ISAKMP, use the **show running-config crypto** command in global configuration or privileged EXEC mode.

show running-config crypto

Syntax Description This command has no keywords or arguments.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples The following example entered in privileged EXEC mode, displays all crypto configuration information:

```
hostname# show running-config crypto map
crypto map abc 1 match address xyz
crypto map abc 1 set peer 209.165.200.225
crypto map abc 1 set transform-set ttt
crypto map abc interface test
isakmp enable inside
isakmp policy 1 authentication pre-share
isakmp policy 1 encryption 3des
isakmp policy 1 hash md5
isakmp policy 1 group 2
isakmp policy 1 lifetime 86400
hostname#
```

Related Commands

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.

Command	Description
isakmp enable	Enables ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance.
show isakmp sa	Displays IKE runtime SA database with additional information.

show running-config crypto dynamic-map

To view a dynamic crypto map, use the **show running-config crypto dynamic-map** command in global configuration or privileged EXEC mode.

show running-config crypto dynamic-map

Syntax Description This command has no keywords or arguments.

Defaults No default behaviors or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples The following example entered in global configuration mode, displays all configuration information about crypto dynamic maps:

```
hostname(config)# show running-config crypto dynamic-map
```

```
Crypto Map Template "dyn1" 10
```

```
access-list 152 permit ip host 172.21.114.67 any
Current peer: 0.0.0.0
Security association lifetime: 4608000 kilobytes/120 seconds
PFS (Y/N): N
Transform sets={ tauth, t1, }
```

```
hostname(config)#
```

Related Commands	Command	Description
	clear configure isakmp	Clears all the ISAKMP configuration.
	clear configure isakmp policy	Clears all ISAKMP policy configuration.
	clear isakmp sa	Clears the IKE runtime SA database.
	isakmp enable	Enables ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance.
	show isakmp sa	Displays IKE runtime SA database with additional information.

show running-config crypto ipsec

To display the complete IPSec configuration, use the **show running-config crypto ipsec** command in global configuration or privileged EXEC mode.

show running-config crypto ipsec

Syntax Description This command has no default behavior or values.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples The following example issued in global configuration mode, displays information about the IPSec configuration:

```
hostname(config)# show running-config crypto ipsec
crypto ipsec transform-set ttt esp-3des esp-md5-hmac
hostname(config)#
```

Related Commands	Command	Description
	clear configure isakmp	Clears all the ISAKMP configuration.
	clear configure isakmp policy	Clears all ISAKMP policy configuration.
	clear isakmp sa	Clears the IKE runtime SA database.
	isakmp enable	Enables ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance.
	show isakmp sa	Displays IKE runtime SA database with additional information.

show running-config crypto isakmp

To display the complete ISAKMP configuration, use the **show running-config crypto isakmp** command in global configuration or privileged EXEC mode.

show running-config crypto isakmp

Syntax Description This command has no default behavior or values.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—
Privileged EXEC	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples The following example issued in global configuration mode, displays information about the ISKAKMP configuration:

```
hostname<config># show running-config crypto isakmp
isakmp enable inside
isakmp policy 1 authentication pre-share
isakmp policy 1 encryption 3des
isakmp policy 1 hash md5
isakmp policy 1 group 2
isakmp policy 1 lifetime 86400
hostname<config>#
```

Related Commands

Command	Description
clear configure isakmp	Clears all the ISAKMP configuration.
clear configure isakmp policy	Clears all ISAKMP policy configuration.
clear isakmp sa	Clears the IKE runtime SA database.
isakmp enable	Enables ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance.
show isakmp sa	Displays IKE runtime SA database with additional information.

show running-config crypto map

To display all configuration for all crypto maps, use the **show running-config crypto map** command in global configuration or privileged EXEC mode.

show running-config crypto map

Syntax Description This command has no keywords or arguments.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—
Privileged EXEC	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples The following example entered in privileged EXEC mode, displays all configuration information for all crypto maps:

```
hostname# show running-config crypto map
crypto map abc 1 match address xyz
crypto map abc 1 set peer 209.165.200.225
crypto map abc 1 set transform-set ttt
crypto map abc interface test
hostname#
```

Related Commands	Command	Description
	clear configure isakmp	Clears all the ISAKMP configuration.
	clear configure isakmp policy	Clears all ISAKMP policy configuration.
	clear isakmp sa	Clears the IKE runtime SA database.
	isakmp enable	Enables ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance.
	show isakmp sa	Displays IKE runtime SA database with additional information.

show running-config dhcpd

To show the DHCP configuration, use the **show running-config dhcpd** command in privileged EXEC or global configuration mode.

show running-config dhcpd

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was changed from the show dhcpd command to the show running-config dhcpd command.

Usage Guidelines The **show running-config dhcpd** command displays the DHCP commands entered in the running configuration. To see DHCP binding, state, and statistical information, use the **show dhcpd** command.

Examples The following is sample output from the **show running-config dhcpd** command:

```
hostname# show running-config dhcpd

dhcpd address 10.0.1.100-10.0.1.108 inside
dhcpd lease 3600
dhcpd ping_timeout 750
dhcpd dns 209.165.201.2 209.165.202.129
dhcpd enable inside
```

Related Commands	Command	Description
	clear configure dhcpd	Removes all DHCP server settings.
	debug dhcpd	Displays debug information for the DHCP server.
	show dhcpd	Displays DHCP binding, statistic, or state information.

show running-config dhcprelay

To view the current DHCP relay agent configuration, use the **show running-config dhcprelay** command in privileged EXEC mode.

show running-config dhcprelay

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines The **show running-config dhcprelay** command displays the current DHCP relay agent configuration. To show DHCP relay agent packet statistics, use the **show dhcprelay statistics** command.

Examples The following example shows output from the **show running-config dhcprelay** command:

```
hostname(config)# show running-config dhcprelay

dhcprelay server 10.1.1.1
dhcprelay enable inside
dhcprelay timeout 90
```

Related Commands	Command	Description
	clear configure dhcprelay	Removes all DHCP relay agent settings.
	clear dhcprelay statistics	Clears the DHCP relay agent statistic counters.
	debug dhcprelay	Displays debug information for the DHCP relay agent.
	show dhcprelay statistics	Displays DHCP relay agent statistic information.

show running-config dns

To show the DNS configuration in the running configuration, use the **show running-config dns** command in privileged EXEC mode.

show running-config dns

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	This command was introduced.

Examples The following is sample output from the **show running-config dns** command:

```
hostname# show running-config dns
dns domain-lookup inside
dns name-server
dns retries 2
dns timeout 15
dns name-server 10.1.1.1
```

Command	Description
dns domain-lookup	Enables the security appliance to perform a name lookup.
dns name-server	Configures a DNS server address.
dns retries	Specifies the number of times to retry the list of DNS servers when the security appliance does not receive a response.
dns timeout	Specifies the amount of time to wait before trying the next DNS server.
show dns-hosts	Shows the DNS cache.

show running-config domain-name

To show the domain name configuration in the running configuration, use the **show running-config domain-name** command in privileged EXEC mode.

show running-config domain-name

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	7.0	This command was changed from show domain-name .

Examples The following is sample output from the **show running-config domain-name** command:

```
hostname# show running-config domain-name
example.com
```

Related Commands	Command	Description
	domain-name	Sets the default domain name.
	hostname	Sets the security appliance hostname.

show running-config enable

To show the encrypted enable passwords, use the **show running-config enable** command in privileged EXEC mode.

show running-config enable

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
7.0	This command was changed from the show enable command.

Usage Guidelines The password is saved to the configuration in encrypted form, so you cannot view the original password after you enter it. The password displays with the **encrypted** keyword to indicate that the password is encrypted.

Examples The following is sample output from the **show running-config enable** command:

```
hostname# show running-config enable
enable password 2AfK9Kjr3BE2/J2r level 10 encrypted
enable password 8Ry2YjIyt7RRXU24 encrypted
```

Command	Description
disable	Exits privileged EXEC mode.
enable	Enters privileged EXEC mode.
enable password	Sets the enable password.

show running-config established

To display the allowed inbound connections that are based on established connections, use the **show running-config established** command in privileged EXEC mode.

show running-config established

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	The keyword running-config was added.

Usage Guidelines This command has no usage guidelines.

Examples This example shows how to display inbound connections that are based on established connections:

```
hostname# show running-config established
```

Command	Description
established	Permits return connections on ports that are based on an established connection.
clear configure established	Removes all established commands.

show running-config failover

To display the **failover** commands in the configuration, use the **show running-config failover** command in privileged EXEC mode.

show running-config [all] failover

Syntax Description	all	(Optional) Shows all failover commands, including the commands you have not changed from the default.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	The show running-config failover command displays the failover commands in the running configuration. It does not display the monitor-interface or join-failover-group commands.

Examples	The following example shows the default failover configuration before failover has been configured:

```
hostname# show running-config all failover
no failover
failover lan unit secondary
failover polltime unit 15 holdtime 45
failover polltime interface 15
failover interface policy 1
hostname#
```

Related Commands	Command	Description
	show failover	Displays failover state and statistics.

show running-config filter

To show the filtering configuration, use the **show running-config filter** command in privileged EXEC mode.

show running-config filter

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **show running-config filter** command displays the filtering configuration for the security appliance.

Examples

The following is sample output from the **show running-config filter** command, and shows the filtering configuration for the security appliance:

```
hostname# show running-config filter
!
filter activex 80 10.86.194.170 255.255.255.255 10.1.1.0 255.255.255.224
!
```

This example shows ActiveX filtering is enabled on port80 for the address 10.86.194.170.

Related Commands

Commands	Description
filter activex	Removes ActiveX objects from HTTP traffic passing through the security appliance.
filter ftp	Identifies the FTP traffic to be filtered by a URL filtering server.
filter https	Identifies the HTTPS traffic to be filtered by a Websense server.
filter java	Removes Java applets from HTTP traffic passing through the security appliance.
filter url	Directs traffic to a URL filtering server.

show running-config fips

To display the FIPS configuration that is running on the security appliance, use the **show running-config fips** command.

show running-config fips

Syntax Description

fips	FIPS-2 compliance information

Defaults

This command has no default settings.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0(4)	This command was introduced.

Usage Guidelines

The **show running-config fips** command allows you to display the current running fips configuration. You use the **running-config** keyword only in the **show running-config fips** command. You cannot use this keyword with no or clear, or as a standalone command as it is not supported. When you enter the **?**, **no ?**, or **clear ?** keywords, a **running-config** keyword is not listed in the command list.

Examples

```
sw8-ASA(config)# show running-config fips
```

Related Commands

Command	Description
clear configure fips	Clears the system or module FIPS configuration information stored in NVRAM.
crashinfo console disable	Disables the reading, writing and configuration of crash write info to flash.
fips enable	Enables or disablea policy-checking to enforce FIPS compliance on the system or module.
fips self-test poweron	Executes power-on self-tests.
show crashinfo console	Displays crashinfo console settings.

show running-config fragment

To display the current configuration of the fragment databases, use the **show running-config fragment** command in privileged EXEC mode.

show running-config fragment [*interface*]

Syntax Description

interface (Optional) Specifies the security appliance interface.

Defaults

If an interface is not specified, the command applies to all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	The keyword running-config was added.

Usage Guidelines

The **show running-config fragment** command displays the current configuration of the fragment databases. If you specify an interface name, only information for the database residing at the specified interface displays. If you do not specify an interface name, the command applies to all interfaces.

Use the **show running-config fragment** command to display this information:

- **Size**—Maximum number of packets set by the **size** keyword. This value is the maximum number of fragments that are allowed on the interface.
- **Chain**—Maximum number of fragments for a single packet set by the **chain** keyword.
- **Timeout**—Maximum number of seconds set by the **timeout** keyword. This is the maximum number of seconds to wait for an entire fragmented packet to arrive. The timer starts after the first fragment of a packet arrives. If all fragments of the packet do not arrive by the number of seconds specified, all fragments of the packet that were already received will be discarded.

Examples

The following example shows how to display the states of the fragment databases on all interfaces:

```
hostname# show running-config fragment
fragment size 200 inside
fragment chain 24 inside
fragment timeout 5 inside
fragment size 200 outside1
fragment chain 24 outside1
fragment timeout 5 outside1
```

```

fragment size 200 outside2
fragment chain 24 outside2
fragment timeout 5 outside2
fragment size 200 outside3
fragment chain 24 outside3
fragment timeout 5 outside3

```

The following example shows how to display the states of the fragment databases on interfaces that start with the name “outside”:

**Note**

In this example, the interfaces named “outside1”, “outside2”, and “outside3” display.

```

hostname# show running-config fragment outside
fragment size 200 outside1
fragment chain 24 outside1
fragment timeout 5 outside1
fragment size 200 outside2
fragment chain 24 outside2
fragment timeout 5 outside2
fragment size 200 outside3
fragment chain 24 outside3
fragment timeout 5 outside3

```

The following example shows how to display the states of the fragment databases on the interfaces named “outside1” only:

```

hostname# show running-config fragment outside1
fragment size 200 outside1
fragment chain 24 outside1
fragment timeout 5 outside1

```

Related Commands

Command	Description
clear configure fragment	Resets all the IP fragment reassembly configurations to defaults.
clear fragment	Clears the operational data of the IP fragment reassembly module.
fragment	Provides additional management of packet fragmentation and improves compatibility with NFS.
show fragment	Displays the operational data of the IP fragment reassembly module.

show running-config ftp-map

To show the FTP maps that have been configured, use the **show running-config ftp-map** command in privileged EXEC mode.

show running-config ftp-map *map_name*

Syntax Description

map_name Displays configuration for the specified FTP map.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **show running-config ftp-map** command displays the FTP maps that have been configured.

Examples

The following is sample output from the **show running-config ftp-map** command:

```
hostname# show running-config ftp-map ftp-policy
!
ftp-map ftp-policy
request-command deny put stou appe
!
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
ftp-map	Defines an FTP map and enables FTP map configuration mode.
inspect ftp	Applies a specific FTP map to use for application inspection.
mask-syst-reply	Hides the FTP server response from clients.
request-command deny	Specifies FTP commands to disallow.

show running-config ftp mode

To show the client mode configured for FTP, use the **show running-config ftp mode** command in privileged EXEC mode.

show running-config ftp mode

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **show running-config ftp mode** command displays the client mode that is used by the security appliance when accessing an FTP server.

Examples

The following is sample output from the **show running-config ftp-mode** command:

```
hostname# show running-config ftp-mode
!
ftp-mode passive
!
```

Related Commands

Commands	Description
copy	Uploads or downloads image files or configuration files to or from an FTP server.
debug ftp client	Displays detailed information about FTP client activity.
ftp mode passive	Sets the FTP client mode used by the security appliance when accessing an FTP server.

show running-config global

To display the **global** commands in the configuration, use the **show running-config global** command in privileged EXEC mode.

show running-config global

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Release	Modification
7.0	Added keyword running-config .

Examples The following is sample output from the **show running-config global** command:

```
hostname# show running-config global
global (outside1) 10 interface
```

Related Commands	Command	Description
	clear configure global	Removes global commands from the configuration.
	global	Creates entries from a pool of global addresses.

show running-config group-delimiter

To display the current delimiter to be used when parsing group names from the user names that are received when tunnels are being negotiated, use the **show running-config group-delimiter** command in global configuration mode.

show running-config group-delimiter

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	—	—	•

Release	Modification
7.0	This command was introduced.

Usage Guidelines Use this command to display the currently configured group-delimiter.

Examples This example shows a **show running-config group-delimiter** command and its output:

```
hostname(config)# show running-config group-delimiter
group-delimiter @
```

Command	Description
group-delimiter	Enables group-name parsing and specifies the delimiter to be used when parsing group names from the user names that are received when tunnels are being negotiated.

show running-config group-policy

To display the running configuration for a particular group policy, use the **show running-config group-policy** command in privileged EXEC mode and append the name of the group policy. To display the running configuration for all group policies, use this command without naming a specific group policy. To have either display include the default configuration, use the **default** keyword.

show running-config [default] group-policy [name]

Syntax Description

default	Displays the running configuration including default values.
name	Specifies the name of the group policy.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to display the running configuration, including default values, for the group policy named FirstGroup:

```
hostname# show running-config default group-policy FirstGroup
```

Related Commands

Command	Description
group-policy	Creates, edits, or removes a group policy.
group-policy attributes	Enters group-policy attributes mode, which lets you configure AVPs for a specified group policy.
clear config group-policy	Removes the configuration for a particular group policy or for all group policies.

show running-config gtp-map

To show the GTP maps that have been configured, use the **show running-config gtp-map** command in privileged EXEC mode.

show running-config gtp-map *map_name*

Syntax Description.	<i>map_name</i>	Displays configuration for the specified GTP map.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	The show running-config gtp-map command displays the GTP maps that have been configured.

Examples	The following is sample output from the show running-config gtp-map command:

```
hostname# show running-config gtp-map gtp-policy
!
gtp-map gtp-policy
 request-queue 300
 message-length min 20 max 300
 drop message 20
 tunnel-limit 10000
!
```

Related Commands	Commands	Description
	clear service-policy inspect gtp	Clears global GTP statistics.
	debug gtp	Displays detailed information about GTP inspection.
	gtp-map	Defines a GTP map and enables GTP map configuration mode.

Commands	Description
inspect gtp	Applies a specific GTP map to use for application inspection.
show service-policy inspect gtp	Displays the GTP configuration.

show running-config http

To display the current set of configured http commands, use the **show running-config http** command in privileged EXEC mode.

show running-config http

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Examples

The following sample output shows how to use the **show running-config http** command:

```
hostname# show running-config http
http server enabled
0.0.0.0 0.0.0.0 inside
```

Related Commands

Command	Description
clear http	Remove the HTTP configuration: disable the HTTP server and remove hosts that can access the HTTP server.
http	Specifies hosts that can access the HTTP server by IP address and subnet mask. Specifies the security appliance interface through which the host accesses the HTTP server.
http authentication-certificate	Requires authentication via certificate from users who are establishing HTTPS connections to the security appliance.
http redirect	Specifies that the security appliance redirect HTTP connections to HTTPS.
http server enable	Enables the HTTP server.

show running-config http-map

To show the HTTP maps that have been configured, use the **show running-config http-map** command in privileged EXEC mode.

show running-config http-map *map_name*

Syntax Description

map_name Displays configuration for the specified HTTP map.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **show running-config http-map** command displays the HTTP maps that have been configured.

Examples

The following is sample output from the **show running-config http-map** command:

```
hostname# show running-config http-map http-policy
!
http-map http-policy
content-length min 100 max 2000 action reset log
content-type-verification match-req-rsp reset log
max-header-length request bytes 100 action log reset
max-uri-length 100 action reset log
!
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug http-map	Displays detailed information about traffic associated with an HTTP map.
http-map	Defines an HTTP map for configuring enhanced HTTP inspection.

Commands	Description
inspect http	Applies a specific HTTP map to use for application inspection.
policy-map	Associates a class map with specific security actions.

show running-config icmp

To show the access rules configured for ICMP traffic, use the **show running-config icmp** command in privileged EXEC mode.

show running-config icmp *map_name*

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **show running-config icmp** command displays the access rules configured for ICMP traffic.

Examples

The following is sample output from the **show running-config icmp** command:

```
hostname# show running-config icmp
!
icmp permit host 172.16.2.15 echo-reply outside
icmp permit 172.22.1.0 255.255.0.0 echo-reply outside
icmp permit any unreachable outside
!
```

Related Commands

Commands	Description
clear configure icmp	Clears the ICMP configuration.
debug icmp	Enables the display of debug information for ICMP.
show icmp	Displays ICMP configuration.
timeout icmp	Configures the idle timeout for ICMP.

show running-config imap4s

To display the running configuration for IMAP4S, use the **show running-config imap4s** command in privileged EXEC mode.

show running-config [all] imap4s

Syntax Description	all (Optional) Displays the running configuration including default values.

Defaults	No default behavior or values.

Command History	Release	Modification
	7.0	This command was introduced.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Examples	The following is sample output from the show running-config imap4s command:

```
hostname# show running-config imap4s
```

```
imap4s
server 10.160.105.2
authentication-server-group KerbSvr
authentication aaa
```

```
hostname# show running-config all imap4s
```

```
imap4s
port 993
server 10.160.105.2
outstanding 20
name-separator :
server-separator @
authentication-server-group KerbSvr
no authorization-server-group
no accounting-server-group
no default-group-policy
authentication aaa
```

Related Commands

Command	Description
clear configure imap4s	Removes the IMAP4S configuration.
imap4s	Creates or edits an IMAP4S e-mail proxy configuration.

show running-config interface

To show the interface configuration in the running configuration, use the **show running-config interface** command in privileged EXEC mode.

```
show running-config [all] interface [physical_interface[.subinterface] | mapped_name |
interface_name]
```

Syntax Description

all	(Optional) Shows all interface commands, including the commands you have not changed from the default.
<i>interface_name</i>	(Optional) Identifies the interface name set with the nameif command.
<i>mapped_name</i>	(Optional) In multiple context mode, identifies the mapped name if it was assigned using the allocate-interface command.
<i>physical_interface</i>	(Optional) Identifies the interface ID, such as gigabitethernet0/1 . See the interface command for accepted values.
<i>subinterface</i>	(Optional) Identifies an integer between 1 and 4294967293 designating a logical subinterface.

Defaults

If you do not specify an interface, this command shows the configuration for all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You cannot use the interface name in the system execution space, because the **nameif** command is only available within a context. Similarly, if you mapped the interface ID to a mapped name using the **allocate-interface** command, you can only use the mapped name in a context.

Examples

The following is sample output from the **show running-config interface** command. The following example shows the running configuration for all interfaces. The GigabitEthernet0/2 and 0/3 interfaces have not been configured yet, and show the default configuration. The Management0/0 interface also shows the default settings.

```
formula_1# show running-config interface
!
interface GigabitEthernet0/0
```

```

nameif inside
security-level 100
ip address 10.86.194.60 255.255.254.0
webvpn enable
!
interface GigabitEthernet0/1
shutdown
nameif test
security-level 0
ip address 10.10.4.200 255.255.0.0
!
interface GigabitEthernet0/2
shutdown
no nameif
security-level 0
no ip address
!
interface GigabitEthernet0/3
shutdown
no nameif
security-level 0
no ip address
!
interface Management0/0
shutdown
no nameif
security-level 0
no ip address

```

Related Commands

Command	Description
allocate-interface	Assigns interfaces and subinterfaces to a security context.
clear configure interface	Clears the interface configuration.
interface	Configures an interface and enters interface configuration mode.
nameif	Sets the interface name.
show interface	Displays the runtime status and statistics of interfaces.

show running-config ip address

To show the IP address configuration in the running configuration, use the **show running-config ip address** command in privileged EXEC mode.

show running-config ip address [*physical_interface* [.*subinterface*] | *mapped_name* | *interface_name*]

Syntax Description

<i>interface_name</i>	(Optional) Identifies the interface name set with the nameif command.
<i>mapped_name</i>	(Optional) In multiple context mode, identifies the mapped name if it was assigned using the allocate-interface command.
<i>physical_interface</i>	(Optional) Identifies the interface ID, such as gigabitethernet0/1 . See the interface command for accepted values.
<i>subinterface</i>	(Optional) Identifies an integer between 1 and 4294967293 designating a logical subinterface.

Defaults

If you do not specify an interface, this command shows the IP address configuration for all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

In multiple context mode, if you mapped the interface ID in the **allocate-interface** command, you can only specify the mapped name or the interface name in a context.

In transparent firewall mode, do not specify an interface because this command shows only the management IP address; the transparent firewall does not have IP addresses associated with interfaces.

This display also shows the **nameif** command and **security-level** command configuration.

Examples

The following is sample output from the **show running-config ip address** command:

```
hostname# show running-config ip address
!
interface GigabitEthernet0/0
 nameif inside
 security-level 100
```



```
ip address 10.86.194.60 255.255.254.0
!
interface GigabitEthernet0/1
 nameif test
 security-level 0
 ip address 10.10.4.200 255.255.0.0
!
```

Related Commands

Command	Description
clear configure interface	Clears the interface configuration.
interface	Configures an interface and enters interface configuration mode.
ip address	Sets the IP address for the interface or sets the management IP address for a transparent firewall.
nameif	Sets the interface name.
security-level	Sets the security level for the interface.

show running-config ip audit attack

To show the **ip audit attack** configuration in the running configuration, use the **show running-config ip audit attack** command in privileged EXEC mode.

show running-config ip audit attack

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	This command was changed from show ip audit attack .

Examples The following is sample output from the **show running-config ip audit attack** command:

```
hostname# show running-config ip audit attack
ip audit attack action drop
```

Related Commands	Command	Description
	ip audit attack	Sets the default actions for packets that match an attack signature.
	ip audit info	Sets the default actions for packets that match an informational signature.
	ip audit interface	Assigns an audit policy to an interface.
	ip audit name	Creates a named audit policy that identifies the actions to take when a packet matches an attack signature or an informational signature.
	ip audit signature	Disables a signature.

show running-config ip audit info

To show the **ip audit info** configuration in the running configuration, use the **show running-config ip audit info** command in privileged EXEC mode.

show running-config ip audit info

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was changed from show ip audit info .

Examples The following is sample output from the **show running-config ip audit info** command:

```
hostname# show running-config ip audit info
ip audit info action drop
```

Related Commands	Command	Description
	ip audit attack	Sets the default actions for packets that match an attack signature.
	ip audit info	Sets the default actions for packets that match an informational signature.
	ip audit interface	Assigns an audit policy to an interface.
	ip audit name	Creates a named audit policy that identifies the actions to take when a packet matches an attack signature or an informational signature.
	ip audit signature	Disables a signature.

show running-config ip audit interface

To show the **ip audit interface** configuration in the running configuration, use the **show running-config ip audit interface** command in privileged EXEC mode.

show running-config ip audit interface [*interface_name*]

Syntax Description

interface_name (Optional) Specifies the interface name.

Defaults

If you do not specify an interface name, this command shows the configuration for all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was changed from show ip audit interface .

Examples

The following is sample output from the **show running-config ip audit interface** command:

```
hostname# show running-config ip audit interface
ip audit interface inside insidepolicy
ip audit interface outside outsidepolicy
```

Related Commands

Command	Description
ip audit attack	Sets the default actions for packets that match an attack signature.
ip audit info	Sets the default actions for packets that match an informational signature.
ip audit interface	Assigns an audit policy to an interface.
ip audit name	Creates a named audit policy that identifies the actions to take when a packet matches an attack signature or an informational signature.
ip audit signature	Disables a signature.

show running-config ip audit name

To show the **ip audit name** configuration in the running configuration, use the **show running-config ip audit name** command in privileged EXEC mode.

show running-config ip audit name [*name* [**info** | **attack**]]

Syntax Description	attack	(Optional) Shows the named audit policy configuration for attack signatures.
	info	(Optional) Shows the named audit policy configuration for informational signatures.
	<i>name</i>	(Optional) Shows the configuration for the audit policy name created using the ip audit name command.

Defaults If you do not specify a name, this command shows the configuration for all audit policies.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was changed from show ip audit name .

Examples The following is sample output from the **show running-config ip audit name** command:

```
hostname# show running-config ip audit name
ip audit name insidepolicy1 attack action alarm
ip audit name insidepolicy2 info action alarm
ip audit name outsidepolicy1 attack action reset
ip audit name outsidepolicy2 info action alarm
```

Related Commands	Command	Description
	ip audit attack	Sets the default actions for packets that match an attack signature.
	ip audit info	Sets the default actions for packets that match an informational signature.
	ip audit interface	Assigns an audit policy to an interface.
	ip audit name	Creates a named audit policy that identifies the actions to take when a packet matches an attack signature or an informational signature.
	ip audit signature	Disables a signature.

show running-config ip audit signature

To show the **ip audit signature** configuration in the running configuration, use the **show running-config ip audit signature** command in privileged EXEC mode.

show running-config ip audit signature [*signature_number*]

Syntax Description

signature_number (Optional) Shows the configuration for the signature number, if present. See the **ip audit signature** command for a list of supported signatures.

Defaults

If you do not specify a number, this command shows the configuration for all signatures.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was changed from show ip audit signature .

Examples

The following is sample output from the **show running-config ip audit signature** command:

```
hostname# show running-config ip audit signature
ip audit signature 1000 disable
```

Related Commands

Command	Description
ip audit attack	Sets the default actions for packets that match an attack signature.
ip audit info	Sets the default actions for packets that match an informational signature.
ip audit interface	Assigns an audit policy to an interface.
ip audit name	Creates a named audit policy that identifies the actions to take when a packet matches an attack signature or an informational signature.
ip audit signature	Disables a signature.

show running-config ip local pool

To display IP address pools, use the **show running-config ip local pool** command in privileged EXEC mode.

show running-config ip local pool [*poolname*]

Syntax Description

poolname (Optional) Specifies the name of the IP address pool.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
EXEC	•	—	•	—	—
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following is sample output from the **show running-config ip local pool** command:

```
hostname(config)# show running-config ip local pool firstpool
```

```
Pool          Begin          End          Mask          Free          In use
firstpool          10.20.30.40    10.20.30.50    255.255.255.0    11
0
```

Available Addresses:

```
10.20.30.40
10.20.30.41
10.20.30.42
10.20.30.43
10.20.30.44
10.20.30.45
10.20.30.46
10.20.30.47
10.20.30.48
10.20.30.49
10.20.30.50
```

```
hostname(config)#
```

 `show running-config ip local pool`**Related Commands**

Command	Description
<code>clear configure ip local pool</code>	Removes all ip local pools
<code>ip local pool</code>	Configures an IP address pool.

show running-config ip verify reverse-path

To show the **ip verify reverse-path** configuration in the running configuration, use the **show running-config ip verify reverse-path** command in privileged EXEC mode.

show running-config ip verify reverse-path [**interface** *interface_name*]

Syntax Description

interface (Optional) Shows the configuration for the specified interface.
interface_name

Defaults

This command shows the configuration for all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
7.0	This command was changed from show ip verify reverse-path .

Examples

The following is sample output from the **show ip verify statistics** command:

```
hostname# show running-config ip verify reverse-path
ip verify reverse-path interface inside
ip verify reverse-path interface outside
ip verify reverse-path interface dmz
```

Related Commands

Command	Description
clear configure ip verify reverse-path	Clears the ip verify reverse-path configuration.
clear ip verify statistics	Clears the Unicast RPF statistics.
ip verify reverse-path	Enables the Unicast Reverse Path Forwarding feature to prevent IP spoofing.
show ip verify statistics	Shows the Unicast RPF statistics.

show running-config ipv6

To display the IPv6 commands in the running configuration, use the **show running-config ipv6** command in privileged EXEC mode.

show running-config [all] ipv6

Syntax Description

all (Optional) Shows all **ipv6** commands, including the commands you have not changed from the default, in the running configuration.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following is sample output from the **show running-config ipv6** command:

```
hostname# show running-config ipv6
ipv6 unicast-routing
ipv6 route vlan101 ::/0 fec0::65:0:0:a0a:6575
ipv6 access-list outside_inbound_ipv6 permit ip any any
ipv6 access-list vlan101_inbound_ipv6 permit ip any any
hostname#
```

Related Commands

Command	Description
debug ipv6	Displays IPv6 debug messages.
show ipv6 access-list	Displays the IPv6 access list.
show ipv6 interface	Displays the status of the IPv6 interfaces.
show ipv6 route	Displays the contents of the IPv6 routing table.
show ipv6 traffic	Displays IPv6 traffic statistics.

show running-config isakmp

To display the complete ISAKMP configuration, use the **show running-config isakmp** command in global configuration or privileged EXEC mode.

show running-config isakmp

Syntax Description This command has no default behavior or values.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—
Privileged EXEC	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Examples The following example issued in global configuration mode, displays information about the ISAKMP configuration:

```
hostname(config)# show running-config isakmp
isakmp enable inside
isakmp policy 1 authentication pre-share
isakmp policy 1 encryption 3des
isakmp policy 1 hash md5
isakmp policy 1 group 2
isakmp policy 1 lifetime 86400
hostname(config)#
```

Related Commands	Command	Description
	clear configure isakmp	Clears all the ISAKMP configuration.
	clear configure isakmp policy	Clears all ISAKMP policy configuration.
	clear isakmp sa	Clears the IKE runtime SA database.
	isakmp enable	Enables ISAKMP negotiation on the interface on which the IPSec peer communicates with the security appliance.
	show isakmp sa	Displays IKE runtime SA database with additional information.

show running-config logging

To display all currently running logging configuration, use the **show running-config logging** command in privileged EXEC mode.

show running-config [all] logging [level | disabled]

Syntax Description

all	(Optional) Displays the logging configuration, including commands that you have not changed from the default.
disabled	(Optional) Displays only the disabled system log message configuration.
level	(Optional) Displays only the configuration for system log messages with a non-default severity level.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was changed from the show logging command.

Examples

The following is an example of the **show running-config logging disabled** command:

```
hostname# show running-config logging disabled
no logging message 720067
```

Related Commands

Command	Description
logging message	Configures logging.
show logging	Shows the log buffer and other logging settings.

show logging rate-limit

To display the disallowed messages to the original set, use the **show logging rate-limit** command.

show logging rate-limit

Syntax Description This command has no arguments or keywords.

Defaults This command has no default settings.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	7.0	Support for this command was introduced on the security appliance.

Usage Guidelines After the information is cleared, nothing more displays until the hosts reestablish their connections.

Examples This example shows how to display the disallowed messages:

```
hostname(config)# show logging rate-limit
```

Related Commands	Command	Description
	show logging	Displays the enabled logging options.

show running-config mac-address-table

To view the **mac-address-table static** and **mac-address-table aging-time** configuration in the running configuration, use the **show running-config mac-address-table** command in privileged EXEC mode.

show running-config mac-address-table

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	—	•	•	•	—

Release	Modification
7.0	This command was introduced.

Examples The following is sample output from the **show running-config mac-learn** command:

```
hostname# show running-config mac-address-table
mac-address-table aging-time 50
mac-address-table static inside1 0010.7cbe.6101
```

Related Commands	Command	Description
	firewall transparent	Sets the firewall mode to transparent.
	mac-address-table aging-time	Sets the timeout for dynamic MAC address entries.
	mac-address-table static	Adds static MAC address entries to the MAC address table.
	mac-learn	Disables MAC address learning.
	show mac-address-table	Shows the MAC address table, including dynamic and static entries.

show running-config mac-learn

To view the **mac-learn** configuration in the running configuration, use the **show running-config mac-learn** command in privileged EXEC mode.

show running-config mac-learn

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	—	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following is sample output from the **show running-config mac-learn** command:

```
hostname# show running-config mac-learn
mac-learn disable
```

Related Commands	Command	Description
	firewall transparent	Sets the firewall mode to transparent.
	mac-address-table static	Adds static MAC address entries to the MAC address table.
	mac-learn	Disables MAC address learning.
	show mac-address-table	Shows the MAC address table, including dynamic and static entries.

show running-config mac-list

To display a list of MAC addresses previously specified in a **mac-list** command with the indicated MAC list number, use the **show running-config mac-list** command in privileged EXEC mode.

show running-config mac-list *id*

Syntax Description

id A hexadecimal MAC address list number.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	—	•

Command History

Release	Modification
7.0	This command was modified to conform to CLI guidelines.

Usage Guidelines

The **show running-config aaa** command displays the **mac-list** command statements as part of the AAA configuration.

Examples

The following example shows how to display a MAC address list with the *id* equal to adc:

```
hostname(config)# show running-config mac-list adc
mac-list adc permit 00a0.cp5d.0282 ffff.ffff.ffff
mac-list adc deny 00a1.cp5d.0282 ffff.ffff.ffff
mac-list ac permit 0050.54ff.0000 ffff.ffff.0000
mac-list ac deny 0061.54ff.b440 ffff.ffff.ffff
mac-list ac deny 0072.54ff.b440 ffff.ffff.ffff
```

Related Commands

Command	Description
mac-list	Add a list of MAC addresses using a first-match search.
clear configure mac-list	Remove the indicated mac-list command statements.
show running-config aaa	Display the running AAA configuration values.

show running-config management-access

To display the name of the internal interface configured for management access, use the **show running-config management-access** command in privileged EXEC mode.

show running-config management-access

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines The **management-access** command lets you define an internal management interface using the IP address of the firewall interface specified in *mgmt_if*. (The interface names are defined by the **nameif** command and displayed in quotes, “”, in the output of the **show interface** command.)

Examples The following example shows how to configure a firewall interface named “inside” as the management access interface and display the result:

```
hostname# management-access inside
hostname# show running-config management-access
management-access inside
```

Related Commands	Command	Description
	clear configure management-access	Removes the configuration of an internal interface for management access of the security appliance.
	management-access	Configures an internal interface for management access.

show running-config mgcp-map

To show the MGCP maps that have been configured, use the **show running-config mgcp-map** command in privileged EXEC mode.

show running-config mgcp-map *map_name*

Syntax Description.	<i>map_name</i>	Displays configuration for the specified MGCP map.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	The show running-config mgcp-map command displays the MGCP maps that have been configured.

Examples	The following is sample output from the show running-config mgcp-map command:

```
hostname# show running-config mgcp-map mgcp-policy
!
mgcp-map mgcp-policy
call-agent 10.10.11.5 101
call-agent 10.10.11.6 101
call-agent 10.10.11.7 102
call-agent 10.10.11.8 102
gateway 10.10.10.115 101
gateway 10.10.10.116 102
gateway 10.10.10.117 102
command-queue 150
```

Related Commands	Commands	Description
	debug mgcp	Enables MGCP debug information.
	mgcp-map	Defines an MGCP map and enables MGCP map configuration mode.

Commands	Description
show conn	Displays the connection state for different connection types.
show mgcp	Displays information about MGCP sessions established through the security appliance.
timeout	Sets the maximum idle time duration for different protocols and session types.

show running-config mroute

To display the static multicast route table in the configuration use the **show running-config mroute** command in privileged EXEC mode.

show running-config mroute [*dst* [*src*]]

Syntax Description

<i>dst</i>	The Class D address of the multicast group.
<i>src</i>	The IP address of the multicast source.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	Added keyword running-config .

Examples

The following is sample output from the **show running-config mroute** command:

```
hostname# show running-config mroute
```

Related Commands

Command	Description
mroute	Configures a static multicast route.

show running-config mtu

To display the current maximum transmission unit block size, use the **show running-config mtu** command in privileged EXEC mode.

show running-config mtu [*interface_name*]

Syntax Description

interface_name (Optional) Internal or external network interface name.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	—	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following is sample output from the **show running-config mtu** command:

```
hostname# show running-config mtu
mtu outside 1500
mtu inside 1500
mtu dmz 1500
hostname# show running-config mtu outside
mtu outside 1500
```

Related Commands

Command	Description
clear configure mtu	Clears the configured maximum transmission unit values on all interfaces.
mtu	Specifies the maximum transmission unit for an interface.

show running-config multicast-routing

To display the **multicast-routing** command, if present, in the running configuration, use the **show running-config multicast-routing** command in privileged EXEC mode.

show running-config multicast-routing

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Usage Guidelines The **show running-config multicast-routing** command displays the **multicast-routing** command in the running configuration. Enter the **clear configure multicast-routing** command to remove the **multicast-routing** command from the running configuration.

Examples The following is sample output from the **show running-config multicast-routing** command:

```
hostname# show running-config multicast-routing

multicast-routing
```

Command	Description
clear configure multicast-routing	Removes the multicast-routing command from the running configuration.
multicast-routing	Enables multicast routing on the security appliance.

show running-config name

To display a list of names associated with IP addresses (configured with the **name** command), use the **show running-config name** command in privileged EXEC mode.

show running-config name

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	The running-config keyword was added.

Examples This example shows how to display a list of names associated with IP addresses:

```
hostname# show running-config name
name 192.168.42.3 sa_inside
name 209.165.201.3 sa_outside
```

Related Commands	Command	Description
	clear configure name	Clears the list of names from the configuration.
	name	Associates a name with an IP address.

show running-config nameif

To show the interface name configuration in the running configuration, use the **show running-config nameif** command in privileged EXEC mode.

show running-config nameif [*physical_interface* [, *subinterface*] | *mapped_name*]

Syntax Description

<i>mapped_name</i>	(Optional) In multiple context mode, identifies the mapped name if it was assigned using the allocate-interface command.
<i>physical_interface</i>	(Optional) Identifies the interface ID, such as gigabitethernet0/1 . See the interface command for accepted values.
<i>subinterface</i>	(Optional) Identifies an integer between 1 and 4294967293 designating a logical subinterface.

Defaults

If you do not specify an interface, this command shows the interface name configuration for all interfaces.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was changed from show nameif .

Usage Guidelines

In multiple context mode, if you mapped the interface ID in the **allocate-interface** command, you can only specify the mapped name in a context.

This display also shows the **security-level** command configuration.

Examples

The following is sample output from the **show running-config nameif** command:

```
hostname# show running-config nameif
!
interface GigabitEthernet0/0
  nameif inside
  security-level 100
!
interface GigabitEthernet0/1
  nameif test
  security-level 0
!
```


Related Commands

Command	Description
allocate-interface	Assigns interfaces and subinterfaces to a security context.
clear configure interface	Clears the interface configuration.
interface	Configures an interface and enters interface configuration mode.
nameif	Sets the interface name.
security-level	Sets the security level for the interface.

show running-config names

To display the IP address-to-name conversions, use the **show running-config names** command in privileged EXEC mode.

show running-config names

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	The keyword running-config was added.

Usage Guidelines Use with the **names** command.

Examples The following example shows how to display the IP address-to-name conversion:

```
hostname# show running-config names
name 192.168.42.3 sa_inside
name 209.165.201.3 sa_outside
```

Command	Description
clear configure name	Clears the list of names from the configuration.
name	Associates a name with an IP address.
names	Enables IP address-to-name conversions that you can configured with the name command.
show running-config name	Displays a list of names associated with IP addresses.

show running-config nat

To display a pool of global IP addresses that are associated with a network, use the **show running-config nat** command in privileged EXEC mode.

show running-config nat [*interface_name*] [*nat_id*]

Syntax Description

<i>interface_name</i>	(Optional) Name of the network interface.
<i>nat_id</i>	(Optional) ID of the group of host or networks.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	Added keyword running-config .

Usage Guidelines

This command displays the maximum connection value for the UDP protocol. Every time the UPD maximum connection value is not set, the value will be displayed as 0 by default and will not be applied.



Note

In transparent mode, only NAT ID 0 is valid.

Examples

This example shows how to display a pool of global IP addresses that are associated with a network:

```
hostname# show running-config nat
nat (inside) 1001 10.7.2.0 255.255.255.224 0 0
nat (inside) 1001 10.7.2.32 255.255.255.224 0 0
nat (inside) 1001 10.7.2.64 255.255.255.224 0 0
nat (inside) 1002 10.7.2.96 255.255.255.224 0 0
nat (inside) 1002 10.7.2.128 255.255.255.224 0 0
nat (inside) 1002 10.7.2.160 255.255.255.224 0 0
nat (inside) 1003 10.7.2.192 255.255.255.224 0 0
nat (inside) 1003 10.7.2.224 255.255.255.224 0 0
```

 show running-config nat

Related Commands	Command	Description
	clear configure nat	Removes the NAT configuration.
	nat	Associates a network with a pool of global IP addresses.

show running-config nat-control

To show the NAT configuration requirement, use the **show running-config nat-control** command in privileged EXEC mode.

show running-config nat-control

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	•	—

Release	Modification
7.0	This command was introduced.

Command History

Examples The following is sample output from the **show running-config nat-control** command:

```
hostname# show running-config nat-control
no nat-control
```

Command	Description
nat	Defines an address on one interface that is translated to a global address on another interface.
nat-control	Allows inside hosts to communicate with outside networks without configuring a NAT rule.

Related Commands

show running-config ntp

To show the NTP configuration in the running configuration, use the **show running-config ntp** command in privileged EXEC mode.

show running-config ntp

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples The following is sample output from the **show running-config ntp** command:

```
hostname# show running-config ntp
ntp authentication-key 1 md5 test2
ntp authentication-key 2 md5 test
ntp trusted-key 1
ntp trusted-key 2
ntp server 10.1.1.1 key 1
ntp server 10.2.1.1 key 2 prefer
```

Related Commands

Command	Description
ntp authenticate	Enables NTP authentication.
ntp authentication-key	Sets an encrypted authentication key to synchronize with an NTP server.
ntp server	Identifies an NTP server.
ntp trusted-key	Provides a key ID for the security appliance to use in packets for authentication with an NTP server.
show ntp status	Shows the status of the NTP association.

show running-config object-group

To display the current object groups, use the **show running-config object-group** command in privileged EXEC mode.

show running-config [**all**] **object-group** [**protocol** | **service** | **network** | **icmp-type** | **id** *obj_grp_id*]

Syntax Description

icmp-type	(Optional) Displays ICMP type object groups.
id <i>obj_grp_id</i>	(Optional) Displays the specified object group.
network	(Optional) Displays network object groups.
protocol	(Optional) Displays protocol object groups.
service	(Optional) Displays service object groups.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following is sample output from the **show running-config object-group** command:

```
hostname# show running-config object-group
object-group protocol proto_grp_1
  protocol-object udp
  protocol-object tcp
object-group service eng_service tcp
  port-object eq smtp
  port-object eq telnet
object-group icmp-type icmp-allowed
  icmp-object echo
  icmp-object time-exceeded
```

Related Commands

Command	Description
clear configure object-group	Removes all the object group commands from the configuration.
group-object	Adds network object groups.
network-object	Adds a network object to a network object group.
object-group	Defines object groups to optimize your configuration.
port-object	Adds a port object to a service object group.

show running-config passwd

To show the encrypted login passwords, use the **show running-config passwd** command in privileged EXEC mode.

show running-config {passwd | password}

Syntax Description

passwd | password You can enter either command; they are aliased to each other.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	This command was changed from the show passwd command.

Usage Guidelines

The password is saved to the configuration in encrypted form, so you cannot view the original password after you enter it. The password displays with the **encrypted** keyword to indicate that the password is encrypted.

Examples

The following is sample output from the **show running-config passwd** command:

```
hostname# show running-config passwd
passwd 2AfK9Kjr3BE2/J2r encrypted
```

Related Commands

Command	Description
clear configure passwd	Clears the login password.
enable	Enters privileged EXEC mode.
enable password	Sets the enable password.
passwd	Sets the login password.
show curpriv	Shows the currently logged in username and the user privilege level.

show running-config pim

To display the PIM commands in the running configuration, use the **show running-config pim** command in privileged EXEC mode.

show running-config pim

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Usage Guidelines The **show running-config pim** command displays the **pim** commands entered in global configuration mode. It does not show the **pim** commands entered in interface configuration mode. To see the **pim** commands entered in interface configuration mode, enter the **show running-config interface** command.

Examples The following is sample output from the **show running-config pim** command:

```
hostname# show running-config pim
```

```
pim old-register-checksum
pim spt-threshold infinity
```

Related Commands	Command	Description
	clear configure pim	Removes the pim commands from the running configuration.
	show running-config interface	Displays interface configuration commands entered in interface configuration mode.

show running-config policy-map

To display all the policy-map configurations or the default policy-map configuration, use the **show running-config policy-map** command in privileged EXEC mode.

show running-config [all] policy-map

Syntax Description	all (Optional) Display the default policy-map configuration.

Defaults	Omitting the all keyword displays only the explicitly configured policy-map configuration.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	Specifying the all keyword displays the default policy-map configuration as well as the explicitly configured policy-map configuration.

Examples	This example shows the use of the show running-config policy-map command for the policy map named localmap1, and the command output:

```
hostname# show running-config policy-map
!
policy-map localmap1
  description this is a test.
  class firstclass
  priority
  ids promiscuous fail0close
  set connection random-seq# enable
  class class-default
!
```

Related Commands	Command	Description

policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
clear configure policy-map	Removes the entire policy configuration.

show running-config pop3s

To display the running configuration for POP3S, use the **show running-config pop3s** command in privileged EXEC mode. To have the display include the default configuration, use the **all** keyword.

show running-config [all] pop3s

Syntax Description	all	Displays the running configuration including default values.

Defaults	No default behavior or values.

Command History	Release	Modification
	7.0	This command was introduced.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—
Global configuration	•	—	•	—	—

Examples	The following is sample output from the show running-config pop3s command:

```
hostname# show running-config pop3s
```

```
pop3s
server 10.160.102.188
authentication-server-group KerbSvr
authentication aaa
```

```
hostname# show running-config all pop3s
```

```
pop3s
port 995
server 10.160.102.188
outstanding 20
name-separator :
server-separator @
authentication-server-group KerbSvr
no authorization-server-group
no accounting-server-group
no default-group-policy
authentication aaa
```

 show running-config pop3s**Related Commands**

Command	Description
clear configure pop3s	Removes the POP3S configuration.
pop3s	Creates or edits a POP3S e-mail proxy configuration.

show running-config port-forward

To display the set(s) of applications that WebVPN users can access over forwarded TCP ports, use the **show running-config port-forward** command in privileged EXEC mode.

show running-config [all] port-forward

Syntax Description	all (Optional) Displays the running configuration including default values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following is sample output from the **show running-config port-forward** command:

```
hostname# show running-config port-forward

port-forward Telnet 3500 10.148.1.5 23
port-forward Telnet 3501 10.148.1.81 23
port-forward Telnet 3502 10.148.1.82 23
port-forward SSH2 4976 10.148.1.81 22
port-forward SSH2 4977 10.148.1.85 22
port-forward Apps1 10143 flask.CompanyA.com 143
port-forward Apps1 10110 flask.CompanyA.com 110
port-forward Apps1 10025 flask.CompanyA.com 25
port-forward Apps1 11533 sametime-im.CompanyA.com 1533
port-forward Apps1 10022 ddts.CompanyA.com 22
port-forward Apps1 54000 10.148.1.5 23
port-forward Apps1 58000 vpn3060-1 23
port-forward Apps1 58001 vpn3005-1 23
hostname#
```

Related Commands	Command	Description
	clear configure port-forward	Removes all port forwarding commands from the configuration. If you include the listname, the security appliance removes only the commands for that list.
	port-forward	Configures the set of applications that WebVPN users can access.
	port-forward (webvpn)	Enables WebVPN application access for a user or group policy.

show running-config prefix-list

To display the **prefix-list** command in the running configuration, use the **show running-config prefix-list** command in privileged EXEC mode.

show running-config prefix-list

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was changed from the show prefix-list command to the show running-config prefix-list command.

Usage Guidelines The **prefix-list description** commands always appear before their associated **prefix-list** commands in the running configuration. It does not matter what order you entered them.

Examples The following is sample output from the **show running-config prefix-list** command:

```
hostname# show running-config prefix-list

!
prefix-list abc description A sample prefix list
prefix-list abc seq 5 permit 192.168.0.0/8 le 24
prefix-list abc seq 10 deny 10.0.0.0/8 le 32
!
```

Related Commands	Command	Description
	clear configure prefix-list	Clears the prefix-list commands from the running configuration.

show running-config priority-queue

To display the priority queue configuration details for an interface, use the **show running-config priority-queue** command in privileged EXEC mode.

show running-config priority-queue *interface-name*

Syntax Description

<i>interface-name</i>	Specifies the name of the interface for which you want to show the priority queue details

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

This example shows the use of the show running-config priority-queue command for the interface named test, and the command output:

```
hostname# show running-config priority-queue test
priority-queue test
  queue-limit 50
  tx-ring-limit 10
hostname#
```

Related Commands

Command	Description
clear configure priority-queue	Removes the priority-queue configuration from the named interface.
priority-queue	Configures priority queueing on an interface.
show priority-queue statistics	Shows the statistics for the priority queue configured on the named interface.

show running-config privilege

To display the privileges for a command or a set of commands, use the **show running-config privilege** command in privileged EXEC mode.

show running-config [**all**] **privilege** [**all** | **command** *command* | **level** *level*]

Syntax Description

all	(Optional) First occurrence -- Displays the default privilege level.
all	(Optional) Second occurrence -- Displays the privilege level for all commands.
command <i>command</i>	(Optional) Displays the privilege level for a specific command.
level <i>level</i>	(Optional) Displays the commands that are configured with the specified level; valid values are from 0 to 15.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	—	—	•

Command History

Release	Modification
7.0	This command was modified for this release to conform to CLI guidelines.

Usage Guidelines

Use the **show running-config privilege** command to view the current privilege level.

Examples

```
hostname(config)# show running-config privilege level 0
privilege show level 0 command checksum
privilege show level 0 command curpriv
privilege configure level 0 mode enable command enable
privilege show level 0 command history
privilege configure level 0 command login
privilege configure level 0 command logout
privilege show level 0 command pager
privilege clear level 0 command pager
privilege configure level 0 command pager
privilege configure level 0 command quit
privilege show level 0 command version
```

Related Commands

Command	Description
clear configure privilege	Remove privilege command statements from the configuration.
privilege	Configure the command privilege levels.
show curpriv	Display current privilege level.
show running-config privilege	Display privilege levels for commands.

show running-config rip

To display the information about the RIP configuration, use the **show running-config rip** command in privileged EXEC mode.

show running-config [**all**] **rip** [*interface_name*]

Syntax Description	all	(Optional) Shows all RIP commands, including the commands you have not changed from the default.
	<i>interface_name</i>	(Optional) Displays only the RIP commands for the specified interface.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was changed from show rip to show running-config rip .

Examples	This example shows how to display RIP information:

```
hostname# show running-config rip
rip outside passive version 2 authentication md5 thisisakey 2
rip outside default version 2 authentication md5 thisisakey 2
rip inside passive version 1
rip dmz passive version 2
```

Related Commands	Command	Description
	clear configure rip	Clears all RIP commands from the running configuration.
	debug rip	Displays debug information for RIP.
	rip	Configures RIP on the specified interface.

show running-config route

To display the route configuration that is running on the security appliance, use the **show running-config route** command in privileged EXEC mode.

show running-config [all] route

Syntax Description No default behavior or values.

Defaults This command has no arguments or keywords.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	Added keyword running-config .

Examples The following is sample output from the **show running-config route** command:

```
hostname# show running-config route
route outside 10.30.10.0 255.255.255.0 1
```

Related Commands	Command	Description
	clear configure route	Removes the route commands from the configuration that do not contain the connect keyword.
	route	Specifies a static or default route for the an interface.
	show route	Displays route information.

show running-config route-map

To display the information about the route map configuration, use the **show running-config route-map** command in privileged EXEC mode.

show running-config route-map [*map_tag*]

Syntax Description

map_tag (Optional) Text for the route-map tag.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	•	—

Command History

Release	Modification
7.0	Added keyword running-config .

Usage Guidelines

To show all route-maps defined in the configuration, use the **show running-config route-map** command. To show individual route-maps by name, use the **show running-config route-map** *map_tag* command, where *map_tag* is the name of the route-map. Multiple route maps may share the same map tag name.

Examples

The following is sample output from the **show running-config route-map** command:

```
hostname# show running-config route-map
route-map maptag1 permit sequence 10
    set metric 5
    match metric 3
route-map maptag1 permit sequence 12
    set metric 5
    match interface backup
    match metric 3
route-map maptag2 deny sequence 10
    match interface dmz
```

Related Commands

Command	Description
clear configure route-map	Removes the conditions for redistributing the routes from one routing protocol into another routing protocol.
route-map	Defines the conditions for redistributing routes from one routing protocol into another.

show running-config router

To display the global commands in the router configuration, use the **show running-config router** command in privileged EXEC mode.

show running-config [*all*] **router** [*ospf* [*process_id*]]

Syntax Description	<i>all</i>	Shows all router commands, including the commands you have not changed from the default.
	ospf	(Optional) Displays only the OSPF commands in the configuration.
	<i>process_id</i>	(Optional) Displays the commands for the selected OSPF process.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was changed from the show router command to the show running-config router command.

Examples The following is sample output from the **show running-config router** command:

```
hostname# show running-config router ospf 1
router ospf 1
  log-adj-changes detail
  ignore lsa mospf
  no compatible rfc1583
  distance ospf external 200
  timers spf 10 20
  timers lsa-group-pacing 60
```

Related Commands	Command	Description
	clear configure router	Clears all router commands from the running configuration.

show running-config same-security-traffic

To display the same-security interface communication, use the **show running-config same-security-traffic** command in privileged EXEC mode.

show running-config same-security-traffic

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following is sample output from the **show running-config same-security-traffic** command:

```
hostname# show running-config same-security-traffic
```

Related Commands	Command	Description
	same-security-traffic	Permits communication between interfaces with equal security levels.

show running-config service

To display the system services, use the **show running-config service** command in privileged EXEC mode.

show running-config service

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	The keyword running-config was added.

Examples This command shows how to display the system services:

```
hostname# show running-config service
service resetoutside
```

Command	Description
service	Enables system services.

show running-config service-policy

To display all currently running service policy configurations, use the **show running-config service-policy** command in global configuration mode.

show running-config service-policy

Syntax Description	default	Displays the default service policy.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	7.0	This command was introduced.

Examples	The following is an example of the show running-config service-policy command:

```
hostname# show running-config service-policy
```

Related Commands	Command	Description
	show service-policy	Displays the service policy.
	service-policy	Configures service policies.
	clear service-policy	Clears service policy configurations.
	clear configure service-policy	Clears service policy configurations.

show running-configuration smtps

To display the running configuration for smtps, use the **show running-configuration smtps** command in privileged EXEC mode. To have the display include the default configuration, use the **all** keyword.

show running-configuration [all] smtps

Syntax Description	all	Displays the running configuration including default values.

Defaults	No default behavior or values.

Command History	Release	Modification
	7.0	This command was introduced.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—
Global configuration	•	—	•	—	—

Examples	The following is sample output from the show running-config smtps command:

```
hostname# show running-configuration smtps
```

```
smtps
server 10.1.1.21
authentication-server-group KerbSvr
authentication aaa
```

```
hostname# show running-config all smtps
```

```
smtps
port 995
server 10.1.1.21
outstanding 20
name-separator :
server-separator @
authentication-server-group KerbSvr
no authorization-server-group
no accounting-server-group
no default-group-policy
authentication aaa
hostname#
```

Related Commands	Command	Description
	clear configure smtps	Removes the SMTPS configuration.
	smtps	Creates or edits an SMTPS e-mail proxy configuration

show running-config snmp-map

To show the SNMP maps that have been configured, use the **show running-config snmp-map** command in privileged EXEC mode.

show running-config snmp-map *map_name*

Syntax Description.	<i>map_name</i>	Displays configuration for the specified SNMP map.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	The show running-config snmp-map command displays the SNMP maps that have been configured.

Examples	The following is sample output from the show running-config snmp-map command:

```
hostname# show running-config snmp-map snmp-policy
!
snmp-map snmp-policy
deny version 1
!
```

Related Commands	Commands	Description
	class-map	Defines the traffic class to which to apply security actions.
	deny version	Disallows traffic using a specific version of SNMP.
	inspect snmp	Enable SNMP application inspection.
	snmp-map	Defines an SNMP map and enables SNMP map configuration mode.

show running-config snmp-server

To display all currently running SNMP server configurations, use the **show running-config snmp-server** command in global configuration mode.

show running-config [default] snmp-server

Syntax Description	default	Displays the default snmp server configuration.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	

Command History	Release	Modification
	PIX Version 7.0	This command was introduced.

Examples	The following is an example of the show running-config snmp-server command:

```
hostname# show running-config snmp-server
```

Related Commands	Command	Description
	snmp-server	Configures the SNMP server.
	clear snmp-server	Clears the SNMP server configuration.
	show snmp-server statistics	Displays SNMP server configuration.

show running-config ssh

To show the SSH commands in the current configuration, use the **show running-config ssh** command in privileged EXEC mode.

show running-config [**default**] **ssh** [**timeout** | **version**]

show run [**default**] **ssh** [**timeout**]

Syntax Description

default	(Optional) Displays the default SSH configuration values along with the configured values.
timeout	(Optional) Displays the current SSH session timeout value.
version	(Optional) Displays the version of SSH currently being supported.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	The command was changed from the show ssh command to the show running-config ssh command.

Usage Guidelines

This command shows the current ssh configuration. To display only the SSH session timeout value, use the **timeout** option. To see a list of active SSH sessions, use the **show ssh sessions** command.

Examples

The following example displays the SSH session timeout:

```
hostname# show running-config timeout
ssh timeout 5 minutes
hostname#
```

Related Commands

Command	Description
clear configure ssh	Clears all SSH commands from the running configuration.
ssh	Allows SSH connectivity to the security appliance from the specified client or network.
ssh scopy enable	Enables a secure copy server on the security appliance.
ssh timeout	Sets the timeout value for idle SSH sessions.
ssh version	Restricts the security appliance to using either SSH Version 1 or SSH Version 2.

show running-config ssl

To display the current set of configured ssl commands, use the **show running-config ssl** command in privileged EXEC mode.

show running-config ssl

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following is sample output from the **show running-config ssl** command:

```
hostname# show running-config ssl
ssl server-version tlsv1
ssl client-version tlsv1-only
ssl encryption 3des-sha1
ssl trust-point Firstcert
```

Related Commands

Command	Description
clear config ssl	Removes all ssl commands from the configuration, reverting to the default values.
ssl client-version	Specifies the SSL/TLS protocol version the security appliance uses when acting as a client.
ssl server-version	Specifies the SSL/TLS protocol version the security appliance uses when acting as a server
ssl trust-point	Specifies the certificate trust point that represents the SSL certificate for an interface.

show running-config static

To display all **static** commands in the configuration, use the **show running-config static** command in privileged EXEC mode.

show running-config static

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	The keyword running-config was added.

Usage Guidelines This command displays the maximum connections value for the UDP protocol. If the UDP maximum connections value is “0” or not set, the limit enforcement is disabled.

Examples This example shows how to display all static commands in the configuration:

```
hostname# show running-config static
static (inside,outside) 192.150.49.91 10.1.1.91 netmask 255.255.255.255
static (inside,outside) 192.150.49.200 10.1.1.200 netmask 255.255.255.255 tcp 255 0
```



Note

No UDP value connection limit is shown.

Command	Description
clear configure static	Removes all the static commands from the configuration.
static	Configures a persistent one-to-one address translation rule by mapping a local IP address to a global IP address.

show running-config sunrpc-server

To display the information about the SunRPC configuration, use the **show running-config sunrpc-server** command in privileged EXEC mode.

show running-config sunrpc-server *interface_name* *ip_addr* *mask* **service** *service_type* **protocol** [TCP | UDP] **port** *port* [- *port*] **timeout** *hh:mm:ss*

Syntax Description

<i>interface_name</i>	Server interface.
<i>ip_addr</i>	Server IP address.
<i>mask</i>	Network mask.
port <i>port</i> - <i>port</i>	SunRPC protocol port range and optionally, a second port.
protocol	SunRPC transport protocol.
service	Specifies a service.
<i>service_type</i>	Sets the SunRPC service program type.
timeout <i>hh:mm:ss</i>	Specifies the timeout idle time after which the access for the SunRPC service traffic is closed.
TCP	(Optional) Specifies TCP.
UDP	(Optional) Specifies UDP.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The *service_type* is specified in the **sunrpcinfo** command.

Examples

The following is sample output from the **show running-config sunrpc-server** command:

```
hostname# show running-config sunrpc-server
inside 30.26.0.23 255.255.0.0 service 2147483647 protocol TCP port 2222 timeout 0:03:00
```

Related Commands

Command	Description
clear configure sunrpc-server	Clears the SunRPC services from the security appliance.
debug sunrpc	Enables debug information for SunRPC.
show conn	Displays the connection state for different connection types, including SunRPC.
sunrpc-server	Creates the SunRPC services table.
timeout	Sets the maximum idle time duration for different protocols and session types, including SunRPC.

show running-config sysopt

To show the **sysopt** command configuration in the running configuration, use the **show running-config sysopt** command in privileged EXEC mode.

show running-config sysopt

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
7.0	This command was changed from the show sysopt command.

Examples The following is sample output from the **show running-config sysopt** command:

```
hostname# show running-config sysopt
no sysopt connection timewait
sysopt connection tcpmss 1200
sysopt connection tcpmss minimum 400
no sysopt nodnsalias inbound
no sysopt nodnsalias outbound
no sysopt radius ignore-secret
sysopt connection permit-ipsec
```

Related Commands	Command	Description
	clear configure sysopt	Clears the sysopt command configuration.
	sysopt connection permit-ipsec	Permits any packets that come from an IPSec tunnel without checking any ACLs for interfaces.
	sysopt connection tcpmss	Overrides the maximum TCP segment size or ensures that the maximum is not less than a specified size.
	sysopt connection timewait	Forces each TCP connection to linger in a shortened TIME_WAIT state after the final normal TCP close-down sequence.
	sysopt nodnsalias	Disables alteration of the DNS A record address when you use the alias command.

show running-config tcp-map

To display the information about the TCP map configuration, use the **show running-config tcp-map** command in privileged EXEC mode.

show running-config tcp-map [*tcp_map_name*]

Syntax Description	<i>tcp_map_name</i> (Optional) Text for the TCP map name; the text can be up to 58 characters in length.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples	The following is sample output from the show running-config tcp-map command:

```
hostname# show running-config tcp-map
tcp-map localmap
```

Related Commands	Command	Description
	tcp-map	Creates a TCP map and allows access to tcp-map configuration mode.
	clear configure tcp-map	Clears the TCP map configuration.

show running-config telnet

To display the current list of IP addresses that are authorized to use Telnet connections to the security appliance, use the **show running-config telnet** command in privileged EXEC mode. You can also use this command to display the number of minutes that a Telnet session can remain idle before being closed by the security appliance.

show running-config telnet [timeout]

Syntax Description	timeout	(Optional) Displays the number of minutes that a Telnet session can be idle before being closed by the security appliance.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	The keyword running-config was added.

Examples	This example shows how to display the current list of IP addresses that are authorized for use by Telnet connections to the security appliance:

```
hostname# show running-config telnet
2003 Jul 15 14:49:36 %MGMT-5-LOGIN_FAIL:User failed to
log in from 128.107.183.22 through Telnet
2003 Jul 15 14:50:27 %MGMT-5-LOGIN_FAIL:User failed to log in from 128.107.183.
22 through Telnet
```

Related Commands	Command	Description
	clear configure telnet	Removes the Telnet connection from the configuration.
	telnet	Adds Telnet access to the console and sets the idle timeout.

show running-config terminal

To display the current terminal settings, use the **show running-config terminal** command in privileged EXEC mode.

show running-config terminal

Syntax Description This command has no keywords or arguments.

Defaults The default display width is 80 columns.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
7.0	The running-config keyword was added.

Examples The following example clears the page length setting:

```
hostname# show running-config terminal
```

```
Width = 80, no monitor
```

Command	Description
clear configure terminal	Clears the terminal display width setting.
terminal	Sets the terminal line parameters.
terminal width	Sets the terminal display width.

show running-config tftp-server

To display the default TFTP server address and directory, use the **show running-config tftp-server** command in global configuration mode.

show running-config tftp-server

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Release	Modification
7.0	The running-config keyword was added.

Command History

Examples This example shows how to display the IP/IPv6 address of the default TFTP server and the directory of the configuration file:

```
hostname(config)# show running-config tftp-server
tftp-server inside 10.1.1.42 /temp/config/test_config
```

Command	Description
configure net	Loads the configuration from the TFTP server and path you specify.
tftp-server	Configures the default TFTP server address and the directory of the configuration file.

Related Commands

show running-config timeout

To display the timeout value of all protocols, or just a specific one, use the **show running-config timeout** command in privileged EXEC mode.

show running-config timeout *protocol*

Syntax Description	<i>protocol</i> (Optional) Displays the timeout value of the specified protocol. Supported protocols are: xlate , conn , udp , icmp , rpc , h323 , h225 , mgcp , mgcp-pat , sip , sip_media , and uauth .

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	7.0	The running-config and mgcp-pat keywords were added.

Examples	This example shows how to display the timeout values for the system:

```
hostname(config)# show timeout
timeout xlate 3:00:00
timeout conn 1:00:00 half-closed 0:10:00 udp 0:02:00 icmp 0:00:02 rpc 0:10:00 h3
23 0:05:00 h225 1:00:00 mgcp 0:05:00 mgcp-pat 0:05:00 sip 0:30:00 sip_media 0:02
:00
timeout uauth 0:00:00 absolute
```

Related Commands	Command	Description
	clear configure timeout	Restores the default idle time durations.
	timeout	Sets the maximum idle time duration.

show running-config tunnel-group

To display tunnel group information about all or a specified tunnel group and tunnel-group attributes, use the **show running-config tunnel-group** command in global configuration or privileged EXEC mode.

show running-config [**all**] **tunnel-group** [*name* [**general-attributes** | **ipsec-attributes** | **ppp-attributes**]]

Syntax Description

all	[Optional] Displays all tunnel-group commands, including the commands you have not changed from the default.
general-attributes	Displays configuration information for general attributes.
ipsec-attributes	Displays configuration information for IPsec attributes.
<i>name</i>	Specifies the name of the tunnel group.
ppp-attributes	Displays configuration information for PPP attributes.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•		•		
Privileged EXEC	•		•		

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example entered in global configuration mode, displays the current configuration for all tunnel groups:

```
hostname<config># show running-config tunnel-group
tunnel-group 209.165.200.225 type IPSec_L2L
tunnel-group 209.165.200.225 ipsec-attributes
    pre-shared-key xyzx
hostname<config>#
```

Related Commands	Command	Description
	clear configure tunnel-group	Removes tunnel-group configuration
	tunnel-group general-attributes	Enters subconfiguration mode for specifying general attributes for specified tunnel group.
	tunnel-group ipsec-attributes	Enters subconfiguration mode for specifying IPSec attributes for specified tunnel group.
	tunnel-group	Enters tunnel-group subconfiguration mode for the specified type.

show running-config url-block

To show the configuration for buffers and memory allocation used by URL filtering, use the **show running-config url-block** command in privileged EXEC mode.

show running-config url-block [block | url-mempool | url-size]

Syntax Description

block	Displays the configuration for the maximum number of blocks that will be buffered.
url-mempool	Displays the configuration for the maximum allow URL size (in KB).
url-size	Displays the configuration for the memory resource (in KB) allocated for the long URL buffer.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was previously existing.

Usage Guidelines

The **show running-config url-block** command displays the configuration for buffers and memory allocation used by URL filtering.

Examples

The following is sample output from the **show running-config url-block** command:

```
hostname# show running-config url-block
!
url-block block 56
!
```

Related Commands

Commands	Description
clear url-block block statistics	Clears the block buffer usage counters.
show url-block	Displays information about the URL cache, which is used for buffering URLs while waiting for responses from an N2H2 or Websense filtering server.
url-block	Manage the URL buffers used for web server responses.
url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

show running-config url-cache

To show the cache configuration used by URL filtering, use the **show running-config url-cache** command in privileged EXEC mode.

show running-config url-cache

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was previously existing.

Usage Guidelines

The **show running-config url-cache** command displays the cache configuration used by URL filtering.

Examples

The following is sample output from the **show running-config url-cache** command:

```
hostname# show running-config url-cache
!
url-cache src_dst 128
!
```

Related Commands

Commands	Description
clear url-cache statistics	Removes url-cache command statements from the configuration.
filter url	Directs traffic to a URL filtering server.
show url-cache statistics	Displays information about the URL cache, which is used for buffering URLs while waiting for responses from an N2H2 or Websense filtering server.
url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

show running-configuration url-list

To display the set(s) of URLs that WebVPN users can access, use the **show running-configuration url-list** command in privileged EXEC mode.

show running-configuration url-list

Syntax Description This command has no arguments or keywords.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—
Global configuration	•	—	•	—	—
Webvpn	•	—	•	—	—

Command History	Release	Modification
	7.0	This command was introduced.

Examples The following is sample output from the **show running-configuration url-list** command:

```
hostname# show running-configuration url-list
url-list userURL "SW Engineering" http://10.1.1.2
url-list userURL "My Company" http://www.mycompany.com
url-list userURL "401K Program" https://401k.com
url-list userURL "Exchange5.5 Mail" http://10.1.1.11/exchange
url-list URLlist2 "OWA-2000" http://10.1.1.7/exchange
```

Related Commands	Command	Description
	clear configuration url-list	Removes all url-list commands from the configuration. If you include the listname, the security appliance removes only the commands for that list.
	url-list	Configures the set of URLs that WebVPN users can access.
	url-list	Enables WebVPN URL access for a specific group policy or user.

show running-config url-server

To show the URL filtering server configuration, use the **show running-config url-server** command in privileged EXEC mode.

show running-config url-server

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was previously existing.

Usage Guidelines

The **show running-config url-server** command displays the URL filtering server configuration.

Examples

The following is sample output from the **show running-config url-server** command:

```
hostname# show running-config url-server
!
url-server (perimeter) vendor websense host 10.0.1.1
!
```

Related Commands

Commands	Description
clear url-server	Clears the URL filtering server statistics.
show url-server	Displays information about the URL cache, which is used for buffering URLs while waiting for responses from an N2H2 or Websense filtering server.
url-block	Manages the URL buffers used for web server responses while waiting for a filtering decision from the filtering server.
url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

show running-config username

To display the running configuration for a particular user, use the **show running-config username** command in privileged EXEC mode with the username appended. To display the running configuration for all users, use this command without a username.

show running-config [**all**] **username** [*name*] [**attributes**]

Syntax Description

attributes	Displays the specific AVPs for the user(s)
all	(Optional) Displays all username commands, including the commands you have not changed from the default.
<i>name</i>	Provides the name of the user.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	—	•	—	—
Global configuration	•	—	•	—	—
Username	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following is sample output from the show the running-config username for a user named anyuser:

```
hostname# show running-config username anyuser
username anyuser password .8T1d6ik58/lzXS5 encrypted privilege 3
username anyuser attributes
vpn-group-policy DefaultGroupPolicy
vpn-idle-timeout 10
vpn-session-timeout 120
vpn-tunnel-protocol IPSec
```

Related Commands

Command	Description
clear config username	Clears the username database.
username	Adds a user to the security appliance database.
username attributes	Lets you configure attributes for specific users.

show running-config virtual

To display the IP address of the security appliance virtual server, use the **show running-config virtual** command in privileged EXEC mode.

show running-config [all] virtual

Syntax Description	all	Display the virtual server IP address of all virtual servers.

Defaults	Omitting the all keyword displays the explicitly configured IP address of the current virtual server or servers.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	—	•

Command History	Release	Modification
	7.0	This command was modified to conform to CLI guidelines.

Usage Guidelines	You must be in privileged EXEC mode to use this command.

Examples	This example displays the show running-config virtual command output for a situation in which there is a previously configured HTTP virtual server:

```
hostname(config)# show running-config virtual
virtual http 192.168.201.1
```

Related Commands	Command	Description
	clear configure virtual	Removes virtual command statements from the configuration.
	virtual	Displays the address for authentication virtual servers.

show running-config vpn load-balancing

To display the current VPN load-balancing virtual cluster configuration, use the **show running-config vpn load-balancing** command in global configuration, privileged EXEC, or VPN load-balancing mode.

show running-config [all] vpn load-balancing

Syntax Description

all Display both the default and the explicitly configured VPN load-balancing configuration.

Defaults

Omitting the **all** keyword displays the explicitly configured VPN load-balancing configuration.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—
Privileged EXEC	•	—	•	—	—
vpn load-balancing	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **show running-config vpn load-balancing** command also displays configuration information for the following related commands: **cluster encryption**, **cluster ip address**, **cluster key**, **cluster port**, **nat**, **participate**, and **priority**.

Examples

This example displays **show running-config vpn load-balancing** command and its output, with the **all** option enabled:

```
hostname(config)# show running-config all vpn load-balancing
vpn load-balancing
  no nat
  priority 9
  interface lbpublic test
  interface lbprivate inside
  no cluster ip address
  no cluster encryption
  cluster port 9023
  no participate
```

 show running-config vpn load-balancing**Related Commands**

Command	Description
clear configure vpn load-balancing	Removes vpn load-balancing command statements from the configuration.
show vpn load-balancing	Displays the VPN load-balancing runtime statistics.
vpn load-balancing	Enters vpn load-balancing mode.

show running-configuration vpn-sessiondb

To display the current set of configured vpn-sessiondb commands, use the **show running-configuration vpn-sessiondb** command in privileged EXEC mode.

show running-configuration [all] vpn-sessiondb

Syntax Description	all	(Optional) Displays all vpn-sessiondb commands, including the commands you have not changed from the default

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines	As of Release 7.0, this command displays only the VPN maximum sessions limit, if configured.

Examples	The following is sample output for the show running-configuration vpn-sessiondb command: hostname# show running-configuration vpn-sessiondb

Related Commands	Command	Description
	show vpn-sessiondb	Displays sessions with or without extended details, optionally filtered and sorted by criteria you specify.
	show vpn-sessiondb summary	Displays a session summary, including total current session, current sessions of each type, peak and total cumulative, maximum concurrent sessions

show running-configuration webvpn

To display the running configuration for webvpn, use the **show running-configuration webvpn** command in privileged EXEC mode. To have the display include the default configuration, use the **all** keyword.

show running-configuration [all] webvpn

Syntax Description	all	Displays the running configuration including default values.

Defaults	No default behavior or values.

Command History	Release	Modification
	7.0	This command was introduced.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	—	•	—	—
Global configuration	•	—	•	—	—

Examples	The following is sample output from the show running-config webvpn command:

```
hostname# show running-configuration webvpn
webvpn
  title WebVPN Services for ASA-4
  title-color green
  default-idle-timeout 0
  nbns-server 10.148.1.28 master timeout 2 retry 2
  accounting-server-group RadiusACS1
  authentication-server-group RadiusACS2
  authorization-dn-attributes CN

hostname# (config-webvpn) # show running-config all webvpn

webvpn
  title WebVPN Services for ASA-4
  username-prompt Username
  password-prompt Password
  login-message Please enter your username and password
  logout-message Goodbye
  no logo
  title-color green
  secondary-color #CCCCFF
```



```
text-color white
secondary-text-color black
default-idle-timeout 0
no http-proxy
no https-proxy
nbns-server 10.148.1.28 master timeout 2 retry 2
accounting-server-group RadiusACS1
authentication-server-group RadiusACS2
no authorization-server-group
default-group-policy DfltGrpPolicy
authentication aaa
no authorization-required
authorization-dn-attributes CN
hostname#
```

Related Commands

Command	Description
clear configure smtps	Removes the smtps configuration.
smtps	Creates or edits an SMTPS e-mail proxy configuration

show service-policy

To display the configured service policies, use the **service-policy** command in global configuration mode.

```
show service-policy [global | interface intf] [inspect | ips | police | priority | set connection]
```

```
show service-policy [global | interface intf] [flow protocol {host src_host | src_ip src_mask}  
[eq src_port] {host dest_host | dest_ip dest_mask} [eq dest_port] [icmp_number |  
icmp_control_message]]
```

Syntax Description

<i>dest_ip</i>	The destination IP address of the traffic flow.
<i>dest_mask</i>	The subnet mask of the traffic flow destination IP address.
<i>dest_port</i>	(Optional) The destination port used in the traffic flow.
eq	(Optional) The equals operator, requiring the source or destination port, as applicable, to match the port number that follows.
flow	(Optional) Specifies a traffic flow for which you want to see the policies that the security appliance would apply to the flow. The arguments and keywords following the flow keyword specify the flow in ip-5-tuple format.
global	(Optional) Limits output to the global policy, which applies to all interfaces.
host <i>dest_host</i>	The host destination IP address of the traffic flow.
host <i>src_host</i>	The host source IP address of the traffic flow.
<i>icmp_control_message</i>	(Optional) Specifies an ICMP control message of the traffic flow. Valid values for the <i>icmp_control_message</i> argument are listed in the “Usage Guidelines” section, below.
<i>icmp_number</i>	(Optional) Specifies the ICMP protocol number of the traffic flow.
inspect	(Optional) Limits the output to policies that include an inspect command.
interface <i>intf</i>	(Optional) Displays policies applied to the interface specified by the <i>intf</i> argument, where <i>intf</i> is the interface name given by the nameif command.
ips	Limits output to policies that include the ips command.
police	Limits output to policies that include the police command.
priority	Limits output to policies that include the priority command.
set connection	Limits output to policies that include the set connection command.
<i>protocol</i>	The protocol used in the traffic flow. Valid values for the <i>protocol</i> argument are listed in the “Usage Guidelines” section, below.
<i>src_ip</i>	The source IP address used in the traffic flow.
<i>src_mask</i>	The source IP netmask used in the traffic flow.
<i>src_port</i>	The source port used in the traffic flow.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **flow** keyword lets you determine, for any flow that you can describe, the policies that the security appliance would apply to that flow. You can use this to check that your service policy configuration will provide the services you want for specific connections. The arguments and keywords following the **flow** keyword specifies the flow in ip-5-tuple format with no object grouping.

Because the flow is described in ip-5-tuple format, not all match criteria are supported. Following are the list of match criteria that are supported for flow match:

- **match access-list**
- **match port**
- **match rtp**
- **match default-inspection-traffic**

The **priority** keyword is used to display the aggregate counter values of packets transmitted through an interface.

The number of embryonic connections displayed in the **show service-policy** command output indicates the current number of embryonic connections to an interface for traffic matching that defined by the **class-map** command. The `embryonic-conn-max` field shows the maximum embryonic limit configured for the traffic class using the Modular Policy Framework. If the current embryonic connections displayed equals or exceeds the maximum, TCP intercept is applied to new TCP connections that match the traffic type defined by the **class-map** command.

protocol Argument Values

The following are valid values for the *protocol* argument:

- *number*—The protocol number (0 - 255).
- **ah**
- **eigrp**
- **esp**
- **gre**
- **icmp**
- **icmp6**
- **igmp**
- **igrp**
- **ip**
- **ipinip**

- ipsec
- nos
- ospf
- pcp
- pim
- pptp
- snp
- tcp
- udp

icmp_control_message Argument Values

The following are valid values for the *icmp_control_message* argument:

- alternate-address
- conversion-error
- echo
- echo-reply
- information-reply
- information-request
- mask-reply
- mask-request
- mobile-redirect
- parameter-problem
- redirect
- router-advertisement
- router-solicitation
- source-quench
- time-exceeded
- timestamp-reply
- timestamp-request
- traceroute
- unreachable

Examples

The following example shows the syntax of the **show service-policy** command:

```
hostname# show service-policy global
```

```
Global policy:
```

```
Service-policy: inbound_policy
```

```
Class-map: ftp-port
```

```
Inspect: ftp strict inbound_ftp, packet 0, drop 0, reset-drop 0
```

```
hostname# show service-policy priority
```

```

Interface outside:

Global policy:
  Service-policy: sa_global_fw_policy

Interface outside:
  Service-policy: ramap
  Class-map: clientmap
    Priority:
      Interface outside: aggregate drop 0, aggregate transmit 5207048
  Class-map: udpmap
    Priority:
      Interface outside: aggregate drop 0, aggregate transmit 5207048
  Class-map: cmap

hostname# show service-policy flow udp host 209.165.200.229 host 209.165.202.158 eq 5060

Global policy:
  Service-policy: f1_global_fw_policy
  Class-map: inspection_default
    Match: default-inspection-traffic
  Action:
    Input flow: inspect sip

Interface outside:
  Service-policy: test
  Class-map: test
    Match: access-list test
    Access rule: permit ip 209.165.200.229 255.255.255.224 209.165.202.158
255.255.255.224
  Action:
    Input flow: ids inline
    Input flow: set connection conn-max 10 embryonic-conn-max 20

```

Related Commands

Command	Description
clear configure service-policy	Clears service policy configurations.
clear service-policy	Clears all service policy configurations.
service-policy	Configures the service policy.
show running-config service-policy	Displays the service policies configured in the running configuration.

show service-policy inspect gtp

To display the GTP configuration, use the **show service-policy inspect gtp** command in privileged EXEC mode.

```
show service-policy [interface int] inspect gtp {pdp-context [apn ap_name | detail | imsi
IMSI_value | ms-addr IP_address | tid tunnel_ID | version version_num ] | pdpmb | requests
| statistics [gsn IP_address] }
```

Syntax Description.

apn	(Optional) Displays the detailed output of the PDP contexts based on the APN specified.
<i>ap_name</i>	Identifies the specific access point name for which statistics are displayed.
detail	(Optional) Displays the detailed output of the PDP contexts.
imsi	Displays the detailed output of the PDP contexts based on the IMSI specified.
<i>IMSI_value</i>	Hexadecimal value that identifies the specific IMSI for which statistics are displayed.
interface	(Optional) Identifies a specific interface.
<i>int</i>	Identifies the interface for which information will be displayed.
gsn	(Optional) Identifies the GPRS support node, which is interface between the GPRS wireless data network and other networks.
gtp	(Optional) Displays the service policy for GTP.
<i>IP_address</i>	IP address for which statistics are displayed.
ms-addr	(Optional) Displays the detailed output of the PDP contexts based on the MS Address specified.
pdp-context	(Optional) Identifies the Packet Data Protocol context
pdpmb	(Optional) Displays the status of the PDP master control block.
requests	(Optional) Displays status of GTP requests.
statistics	(Optional) Displays GTP statistics.
tid	(Optional) Displays the detailed output of the PDP contexts based on the TID specified.
<i>tunnel_ID</i>	Hexadecimal value that identifies the specific tunnel for which statistics are displayed.
version	(Optional) Displays the detailed output of the PDP contexts based on the GTP version.
<i>version_num</i>	Specifies the version of the PDP context for which statistics are displayed. The valid range is 0 to 255.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can use the vertical bar `|` to filter the display. Type `|` for more display filtering options.

The **show pdp-context** command displays PDP context-related information.

The Packet Data Protocol context is identified by the tunnel ID, which is a combination of IMSI and NSAPI. A GTP tunnel is defined by two associated PDP Contexts in different GSN nodes and is identified with a Tunnel ID. A GTP tunnel is necessary to forward packets between an external packet data network and a mobile station user.

The **show gtp requests** command displays current requests in the request queue.

Examples

The following is sample output from the **show gtp requests** command:

```
hostname# show gtp requests
0 in use, 0 most used, 200 maximum allowed
```

You can use the vertical bar `|` to filter the display, as in the following example:

```
hostname# show service-policy gtp statistics | grep gsn
```

This example shows the GTP statistics with the word `gsn` in the output.

The following command shows the statistics for GTP inspection:

```
hostname# show service-policy inspect gtp statistics
GPRS GTP Statistics:
  version_not_support | 0 | msg_too_short | 0
  unknown_msg | 0 | unexpected_sig_msg | 0
  unexpected_data_msg | 0 | ie_duplicated | 0
  mandatory_ie_missing | 0 | mandatory_ie_incorrect | 0
  optional_ie_incorrect | 0 | ie_unknown | 0
  ie_out_of_order | 0 | ie_unexpected | 0
  total_forwarded | 0 | total_dropped | 0
  signalling_msg_dropped | 0 | data_msg_dropped | 0
  signalling_msg_forwarded | 0 | data_msg_forwarded | 0
  total_created_pdp | 0 | total_deleted_pdp | 0
  total_created_pdpmb | 0 | total_deleted_pdpmb | 0
  pdp_non_existent | 0
```

The following command displays information about the PDP contexts:

```
hostname# show service-policy inspect gtp pdp-context
1 in use, 1 most used, timeout 0:00:00

Version TID | MS Addr | SGSN Addr | Idle | APN
```

show service-policy inspect gtp

```
v1 | 1234567890123425 | 1.1.1.1 | 11.0.0.2 0:00:13 gprs.cisco.com

| user_name (IMSI): 214365870921435 | MS address: | 1.1.1.1
| primary pdp: Y | nsapi: 2
| sgsn_addr_signal: | 11.0.0.2 | sgsn_addr_data: | 11.0.0.2
| ggsn_addr_signal: | 9.9.9.9 | ggsn_addr_data: | 9.9.9.9
| sgsn control teid: | 0x000001d1 | sgsn data teid: | 0x000001d3
| ggsn control teid: | 0x6306ffa0 | ggsn data teid: | 0x6305f9fc
| seq_tpdu_up: | 0 | seq_tpdu_down: | 0
| signal_sequence: | 0
| upstream_signal_flow: | 0 | upstream_data_flow: | 0
| downstream_signal_flow: | 0 | downstream_data_flow: | 0
| RAupdate_flow: | 0
```

Table 7-29 describes each column the output from the **show service-policy inspect gtp pdp-context** command.

Table 7-31 PDP Contexts

Column Heading	Description
Version	Displays the version of GTP.
TID	Displays the tunnel identifier.
MS Addr	Displays the mobile station address.
SGSN Addr	Displays the serving gateway service node.
Idle	Displays the time for which the PDP context has not been in use.
APN	Displays the access point name.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
clear service-policy inspect gtp	Clears global GTP statistics.
debug gtp	Displays detailed information about GTP inspection.
gtp-map	Defines a GTP map and enables GTP map configuration mode.
inspect gtp	Applies a specific GTP map to use for application inspection.

show shun

To display shun information, use the **show shun** command in privileged EXEC mode.

show shun [*src_ip* | *statistics*]

Syntax Description

<i>src_ip</i>	(Optional) Displays the information for that address.
<i>statistics</i>	(Optional) Displays the interface counters only.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

The following is sample output from the **show shun** command:

```
hostname# show shun
shun (outside) 10.1.1.27 10.2.2.89 555 666 6
shun (inside1) 10.1.1.27 10.2.2.89 555 666 6
```

Related Commands

Command	Description
clear shun	Disables all the shuns that are currently enabled and clears the shun statistics.
shun	Enables a dynamic response to an attacking host by preventing new connections and disallowing packets from any existing connection.

show sip

To display SIP sessions, use the **show sip** command in privileged EXEC mode.

show sip

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **show sip** command assists in troubleshooting SIP inspection engine issues and is described with the **inspect protocol sip udp 5060** command. The **show timeout sip** command displays the timeout value of the designated protocol.

The **show sip** command displays information for SIP sessions established across the security appliance. Along with the **debug sip** and **show local-host** commands, this command is used for troubleshooting SIP inspection engine issues.



Note

We recommend that you configure the **pager** command before using the **show sip** command. If there are a lot of SIP session records and the **pager** command is not configured, it will take a while for the **show sip** command output to reach its end.

Examples

The following is sample output from the **show sip** command:

```
hostname# show sip
Total: 2
call-id c3943000-960ca-2e43-228f@10.130.56.44
| state Call init, idle 0:00:01
call-id c3943000-860ca-7e1f-11f7@10.130.56.45
| state Active, idle 0:00:06
```

This sample shows two active SIP sessions on the security appliance (as shown in the `Total` field). Each `call-id` represents a call.

The first session, with the `call-id c3943000-960ca-2e43-228f@10.130.56.44`, is in the state `Call Init`, which means the session is still in call setup. Call setup is complete only when the ACK is seen. This session has been idle for 1 second.

The second session is in the state `Active`, in which call setup is complete and the endpoints are exchanging media. This session has been idle for 6 seconds.

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug sip	Enables debug information for SIP.
inspect sip	Enables SIP application inspection.
show conn	Displays the connection state for different connection types.
timeout	Sets the maximum idle time duration for different protocols and session types.

show skinny

To troubleshoot SCCP (Skinny) inspection engine issues, use the **show skinny** command in privileged EXEC mode.

show skinny

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines The **show skinny** command assists in troubleshooting SCCP (Skinny) inspection engine issues.

Examples The following is sample output from the **show skinny** command under the following conditions. There are two active Skinny sessions set up across the security appliance. The first one is established between an internal Cisco IP Phone at local address 10.0.0.11 and an external Cisco CallManager at 172.18.1.33. TCP port 2000 is the CallManager. The second one is established between another internal Cisco IP Phone at local address 10.0.0.22 and the same Cisco CallManager.

hostname# **show skinny**

	LOCAL	FOREIGN	STATE
1	10.0.0.11/52238	172.18.1.33/2000	1
	MEDIA 10.0.0.11/22948	172.18.1.22/20798	
2	10.0.0.22/52232	172.18.1.33/2000	1
	MEDIA 10.0.0.22/20798	172.18.1.11/22948	

The output indicates a call has been established between both internal Cisco IP Phones. The RTP listening ports of the first and second phones are UDP 22948 and 20798 respectively.

The following is the xlate information for these Skinny connections:

```
hostname# show xlate debug
2 in use, 2 most used
Flags: D|DNS, d|dump, I|identity, i|inside, n|no random,
       |o|outside, r|portmap, s|static
NAT from inside:10.0.0.11 to outside:172.18.1.11 flags si idle 0:00:16 timeout 0:05:00
NAT from inside:10.0.0.22 to outside:172.18.1.22 flags si idle 0:00:14 timeout 0:05:00
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug skinny	Enables SCCP debug information.
inspect skinny	Enables SCCP application inspection.
show conn	Displays the connection state for different connection types.
timeout	Sets the maximum idle time duration for different protocols and session types.

show snmp-server statistics

To display information about the SNMP server statistics, use the **show snmp-server statistics** command in privileged EXEC mode.

show snmp-server statistics

Syntax Description This command has no arguments or keywords.

Defaults This command has no default settings.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	

Release	Modification
7.0	This command was introduced.

Examples This example shows how to display the SNMP server statistics:

```
hostname# show snmp-server statistics
0 SNMP packets input
  0 Bad SNMP version errors
  0 Unknown community name
  0 Illegal operation for community name supplied
  0 Encoding errors
  0 Number of requested variables
  0 Number of altered variables
  0 Get-request PDUs
  0 Get-next PDUs
  0 Get-bulk PDUs
  0 Set-request PDUs (Not supported)
0 SNMP packets output
  0 Too big errors (Maximum packet size 512)
  0 No such name errors
  0 Bad values errors
  0 General errors
  0 Response PDUs
  0 Trap PDUs
```

Related Commands

Command	Description
snmp-server	Provides the security appliance event information through SNMP.
clear configure snmp-server	Disables the Simple Network Management Protocol (SNMP) server.
show running-config snmp-server	Displays the SNMP server configuration.

show ssh sessions

To display information about the active SSH session on the security appliance, use the **show ssh sessions** command in privileged EXEC mode.

show ssh sessions [*ip_address*]

Syntax Description	<i>ip_address</i> (Optional) Displays session information for only the specified IP address.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines	The SID is a unique number that identifies the SSH session. The Client IP is the IP address of the system running an SSH client. The Version is the protocol version number that the SSH client supports. If the SSH only supports SSH version 1, then the Version column displays 1.5. If the SSH client supports both SSH version 1 and SSH version 2, then the Version column displays 1.99. If the SSH client only supports SSH version 2, then the Version column displays 2.0. The Encryption column shows the type of encryption that the SSH client is using. The State column shows the progress that the client is making as it interacts with the security appliance. The Username column lists the login username that has been authenticated for the session.

Examples	The following example demonstrates the output of the show ssh sessions command:

```
hostname# show ssh sessions
SID Client IP      Version Mode Encryption Hmac      State      Username
0   172.69.39.39    1.99  IN   aes128-cbc md5      SessionStarted pat
                                OUT   aes128-cbc md5      SessionStarted pat
1   172.23.56.236   1.5   -    3DES     -        SessionStarted pat
2   172.69.39.29    1.99  IN   3des-cbc sha1     SessionStarted pat
                                OUT   3des-cbc sha1     SessionStarted pat
```


Related Commands

Command	Description
ssh disconnect	Disconnects an active SSH session.
ssh timeout	Sets the timeout value for idle SSH sessions.

show startup-config

To show the startup configuration, use the show startup-config command in privileged EXEC mode.

show startup-config

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines In multiple context mode, this command shows the startup configuration for your current execution space: the system configuration or the security context.

Examples The following is sample output from the **show startup-config** command:

```
hostname# show startup-config
: Saved
: Written by enable_15 at 01:44:55.598 UTC Thu Apr 17 2003

Version 7.0(0)28
!
interface GigabitEthernet0/0
 nameif inside
 security-level 100
 ip address 10.86.194.60 255.255.254.0
 webvpn enable
!
interface GigabitEthernet0/1
 shutdown
 nameif test
 security-level 0
 ip address 10.10.4.200 255.255.0.0
!
...
!
```

```
enable password 8Ry2YjIyt7RRXU24 encrypted
passwd 2KFQnbNIdI.2KYOU encrypted
hostname firewall1
domain-name example.com
boot system disk0:/cdisk.bin
ftp mode passive
names
name 10.10.4.200 outside
access-list xyz extended permit ip host 192.168.0.4 host 150.150.0.3
!
ftp-map ftp_map
!
ftp-map inbound_ftp
deny-request-cmd appe stor stou
!

...

Cryptochecksum:4edf97923899e712ed0da8c338e07e63
```

Related Commands

Command	Description
show running-config	Shows the running configuration.

show sunrpc-server active

To display the pinholes open for Sun RPC services, use the **show sunrpc-server active** command in privileged EXEC mode.

show sunrpc-server active

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Use the **show sunrpc-server active** command to display the pinholes open for Sun RPC services, such as NFS and NIS.

Examples

To display the pinholes open for Sun RPC services, enter the **show sunrpc-server active** command. The following is sample output from the **show sunrpc-server active** command:

```
hostname# show sunrpc-server active
      LOCAL          FOREIGN          SERVICE TIMEOUT
-----
192.168.100.2/0 209.165.200.5/32780 100005 00:10:00
```

Related Commands

Command	Description
clear configure sunrpc-server	Clears the Sun remote processor call services from the security appliance.
clear sunrpc-server active	Clears the pinholes opened for Sun RPC services, such as NFS or NIS.
inspect sunrpc	Enables or disables Sun RPC application inspection and configures the port used.
show running-config sunrpc-server	Displays information about the SunRPC services configuration.

show tcpstat

To display the status of the security appliance TCP stack and the TCP connections that are terminated on the security appliance (for debugging), use the **show tcpstat** command in privileged EXEC mode. This command supports IPv4 and IPv6 addresses.

show tcpstat

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines The **show tcpstat** command allows you to display the status of the TCP stack and TCP connections that are terminated on the security appliance. The TCP statistics displayed are described in [Table 7-30](#).

Table 7-32 TCP Statistics in the show tcpstat Command

Statistic	Description
tcb_cnt	Number of TCP users.
proxy_cnt	Number of TCP proxies. TCP proxies are used by user authorization.
tcp_xmt pkts	Number of packets that were transmitted by the TCP stack.
tcp_rcv good pkts	Number of good packets that were received by the TCP stack.
tcp_rcv drop pkts	Number of received packets that the TCP stack dropped.
tcp bad chksum	Number of received packets that had a bad checksum.
tcp user hash add	Number of TCP users that were added to the hash table.
tcp user hash add dup	Number of times a TCP user was already in the hash table when trying to add a new user.
tcp user srch hash hit	Number of times a TCP user was found in the hash table when searching.

Table 7-32 TCP Statistics in the show tcpstat Command (continued)

Statistic	Description
tcp user srch hash miss	Number of times a TCP user was not found in the hash table when searching.
tcp user hash delete	Number of times that a TCP user was deleted from the hash table.
tcp user hash delete miss	Number of times that a TCP user was not found in the hash table when trying to delete the user.
lip	Local IP address of the TCP user.
fip	Foreign IP address of the TCP user.
lp	Local port of the TCP user.
fp	Foreign port of the TCP user.
st	State (see RFC 793) of the TCP user. The possible values are as follows: 1 CLOSED 2 LISTEN 3 SYN_SENT 4 SYN_RCVD 5 ESTABLISHED 6 FIN_WAIT_1 7 FIN_WAIT_2 8 CLOSE_WAIT 9 CLOSING 10 LAST_ACK 11 TIME_WAIT
rexqlen	Length of the retransmit queue of the TCP user.
inqlen	Length of the input queue of the TCP user.
tw_timer	Value of the time_wait timer (in milliseconds) of the TCP user.
to_timer	Value of the inactivity timeout timer (in milliseconds) of the TCP user.
cl_timer	Value of the close request timer (in milliseconds) of the TCP user.
per_timer	Value of the persist timer (in milliseconds) of the TCP user.
rt_timer	Value of the retransmit timer (in milliseconds) of the TCP user.
tries	Retransmit count of the TCP user.

Examples

This example shows how to display the status of the TCP stack on the security appliance:

```
hostname# show tcpstat
          CURRENT MAX      TOTAL
tcb_cnt    2      12      320
proxy_cnt  0       0      160

tcp_xmt pkts = 540591
tcp_rcv good pkts = 6583
tcp_rcv drop pkts = 2
```

```
tcp bad chksum = 0
tcp user hash add = 2028
tcp user hash add dup = 0
tcp user srch hash hit = 316753
tcp user srch hash miss = 6663
tcp user hash delete = 2027
tcp user hash delete miss = 0

lip = 172.23.59.230 fip = 10.21.96.254 lp = 443 fp = 2567 st = 4 rexqlen = 0
in0
  tw_timer = 0 to_timer = 179000 cl_timer = 0 per_timer = 0
rt_timer = 0
tries 0
```

Related Commands

Command	Description
show conn	Displays the connections used and those that are available.

show tech-support

To display the information that is used for diagnosis by technical support analysts, use the **show tech-support** command in privileged EXEC mode.

show tech-support [**detail** | **file** | **no-config**]

Syntax Description

detail	(Optional) Lists detailed information.
file	(Optional) Writes the output of the command to a file.
no-config	(Optional) Excludes the output of the running configuration.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	—	•

Command History

Release	Modification
7.0	The detail and file keywords were added.

Usage Guidelines

The **show tech-support** command lets you list information that technical support analysts need to help you diagnose problems. This command combines the output from the **show** commands that provide the most information to a technical support analyst.

Examples

The following example shows how to display information that is used for technical support analysis, excluding the output of the running configuration:

```
hostname# show tech-support no-config

Cisco XXX Firewall Version X.X(X)
Cisco Device Manager Version X.X(X)

Compiled on Fri 15-Apr-05 14:35 by root

XXX up 2 days 8 hours

Hardware:   XXX, 64 MB RAM, CPU Pentium 200 MHz
Flash i28F640J5 @ 0x300, 16MB
BIOS Flash AT29C257 @ 0xffffd8000, 32KB

0: ethernet0: address is 0003.e300.73fd, irq 10
```



```

1: ethernet1: address is 0003.e300.73fe, irq 7
2: ethernet2: address is 00d0.b7c8.139e, irq 9
Licensed Features:
Failover:           Disabled
VPN-DES:            Enabled
VPN-3DES-AES:       Disabled
Maximum Interfaces: 3
Cut-through Proxy:  Enabled
Guards:             Enabled
URL-filtering:       Enabled
Inside Hosts:        Unlimited
Throughput:          Unlimited
IKE peers:           Unlimited

This XXX has a Restricted (R) license.

Serial Number: 480430455 (0x1ca2c977)
Running Activation Key: 0xc2e94182 0xc21d8206 0x15353200 0x633f6734
Configuration last modified by enable_15 at 23:05:24.264 UTC Sat Nov 16 2002

----- show clock -----

00:08:14.911 UTC Sun Apr 17 2005

----- show memory -----

Free memory:        50708168 bytes
Used memory:         16400696 bytes
-----
Total memory:        67108864 bytes

----- show conn count -----

0 in use, 0 most used

----- show xlate count -----

0 in use, 0 most used

----- show blocks -----

  SIZE    MAX    LOW    CNT
    4    1600   1600   1600
   80     400    400    400
  256     500    499    500
 1550   1188    795    919

----- show interface -----

interface ethernet0 "outside" is up, line protocol is up
  Hardware is i82559 ethernet, address is 0003.e300.73fd
  IP address 172.23.59.232, subnet mask 255.255.0.0
  MTU 1500 bytes, BW 10000 Kbit half duplex
    1267 packets input, 185042 bytes, 0 no buffer
    Received 1248 broadcasts, 0 runts, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    20 packets output, 1352 bytes, 0 underruns
    0 output errors, 0 collisions, 0 interface resets
    0 babbles, 0 late collisions, 9 deferred
    0 lost carrier, 0 no carrier
    input queue (curr/max blocks): hardware (13/128) software (0/2)
    output queue (curr/max blocks): hardware (0/1) software (0/1)
interface ethernet1 "inside" is up, line protocol is down
  Hardware is i82559 ethernet, address is 0003.e300.73fe

```

```

IP address 10.1.1.1, subnet mask 255.255.255.0
MTU 1500 bytes, BW 10000 Kbit half duplex
    0 packets input, 0 bytes, 0 no buffer
    Received 0 broadcasts, 0 runs, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    1 packets output, 60 bytes, 0 underruns
    0 output errors, 0 collisions, 0 interface resets
    0 babbles, 0 late collisions, 0 deferred
    1 lost carrier, 0 no carrier
    input queue (curr/max blocks): hardware (128/128) software (0/0)
    output queue (curr/max blocks): hardware (0/1) software (0/1)
interface ethernet2 "intf2" is administratively down, line protocol is down
Hardware is i82559 ethernet, address is 00d0.b7c8.139e
IP address 127.0.0.1, subnet mask 255.255.255.255
MTU 1500 bytes, BW 10000 Kbit half duplex
    0 packets input, 0 bytes, 0 no buffer
    Received 0 broadcasts, 0 runs, 0 giants
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    0 packets output, 0 bytes, 0 underruns
    0 output errors, 0 collisions, 0 interface resets
    0 babbles, 0 late collisions, 0 deferred
    0 lost carrier, 0 no carrier
    input queue (curr/max blocks): hardware (128/128) software (0/0)
    output queue (curr/max blocks): hardware (0/0) software (0/0)

```

```
----- show cpu usage -----
```

```
CPU utilization for 5 seconds = 0%; 1 minute: 0%; 5 minutes: 0%
```

```
----- show process -----
```

	PC	SP	STATE	Runtime	SBASE	Stack	Process
Hsi	001e3329	00763e7c	0053e5c8	0	00762ef4	3784/4096	arp_timer
Lsi	001e80e9	00807074	0053e5c8	0	008060fc	3832/4096	FragDBGc
Lwe	00117e3a	009dc2e4	00541d18	0	009db46c	3704/4096	dbgtrace
Lwe	003cee95	009de464	00537718	0	009dc51c	8008/8192	Logger
Hwe	003d2d18	009e155c	005379c8	0	009df5e4	8008/8192	tcp_fast
Hwe	003d2c91	009e360c	005379c8	0	009e1694	8008/8192	tcp_slow
Lsi	002ec97d	00b1a464	0053e5c8	0	00b194dc	3928/4096	xlate clean
Lsi	002ec88b	00b1b504	0053e5c8	0	00b1a58c	3888/4096	uxlate clean
Mwe	002e3a17	00c8f8d4	0053e5c8	0	00c8d93c	7908/8192	tcp_intercept_times
Lsi	00423dd5	00d3a22c	0053e5c8	0	00d392a4	3900/4096	route_process
Hsi	002d59fc	00d3b2bc	0053e5c8	0	00d3a354	3780/4096	XXX Garbage Collec
Hwe	0020e301	00d5957c	0053e5c8	0	00d55614	16048/16384	isakmp_time_keep
Lsi	002d377c	00d7292c	0053e5c8	0	00d719a4	3928/4096	perfmon
Hwe	0020bd07	00d9c12c	0050bb90	0	00d9b1c4	3944/4096	IPSec
Mwe	00205e25	00d9e1ec	0053e5c8	0	00d9c274	7860/8192	IPsec timer handler
Hwe	003864e3	00db26bc	00557920	0	00db0764	6952/8192	qos_metric_daemon
Mwe	00255a65	00dc9244	0053e5c8	0	00dc8adc	1436/2048	IP Background
Lwe	002e450e	00e7bb94	00552c30	0	00e7ad1c	3704/4096	XXX/trace
Lwe	002e471e	00e7cc44	00553368	0	00e7bdcc	3704/4096	XXX/tconsole
Hwe	001e5368	00e7ed44	00730674	0	00e7ce9c	7228/8192	XXX/intf0
Hwe	001e5368	00e80e14	007305d4	0	00e7ef6c	7228/8192	XXX/intf1
Hwe	001e5368	00e82ee4	00730534	2470	00e8103c	4892/8192	XXX/intf2
H*	0011d7f7	0009ff2c	0053e5b0	780	00e8511c	13004/16384	ci/console
Csi	002dd8ab	00e8a124	0053e5c8	0	00e891cc	3396/4096	update_cpu_usage
Hwe	002cb4d1	00f2bfbc	0051e360	0	00f2a134	7692/8192	uauth_in
Hwe	003d17d1	00f2e0bc	00828cf0	0	00f2c1e4	7896/8192	uauth_thread
Hwe	003e71d4	00f2f20c	00537d20	0	00f2e294	3960/4096	udp_timer
Hsi	001db3ca	00f30fc4	0053e5c8	0	00f3004c	3784/4096	557mcfix
Crd	001db37f	00f32084	0053ea40	121094970	00f310fc	3744/4096	557poll
Lsi	001db435	00f33124	0053e5c8	0	00f321ac	3700/4096	557timer
Hwe	001e5398	00f441dc	008121e0	0	00f43294	3912/4096	fover_ip0

```

Cwe 001dcdad 00f4523c 00872b48      20 00f44344 3528/4096 ip/0:0
Hwe 001e5398 00f4633c 008121bc      0 00f453f4 3532/4096 icmp0
Hwe 001e5398 00f47404 00812198      0 00f464cc 3896/4096 udp_thread/0
Hwe 001e5398 00f4849c 00812174      0 00f475a4 3832/4096 tcp_thread/0
Hwe 001e5398 00f495bc 00812150      0 00f48674 3912/4096 fover_ip1
Cwe 001dcdad 00f4a61c 008ea850      0 00f49724 3832/4096 ip/1:1
Hwe 001e5398 00f4b71c 0081212c      0 00f4a7d4 3912/4096 icmp1
Hwe 001e5398 00f4c7e4 00812108      0 00f4b8ac 3896/4096 udp_thread/1
Hwe 001e5398 00f4d87c 008120e4      0 00f4c984 3832/4096 tcp_thread/1
Hwe 001e5398 00f4e99c 008120c0      0 00f4da54 3912/4096 fover_ip2
Cwe 001e542d 00f4fa6c 00730534      0 00f4eb04 3944/4096 ip/2:2
Hwe 001e5398 00f50afc 0081209c      0 00f4fbb4 3912/4096 icmp2
Hwe 001e5398 00f51bc4 00812078      0 00f50c8c 3896/4096 udp_thread/2
Hwe 001e5398 00f52c5c 00812054      0 00f51d64 3832/4096 tcp_thread/2
Hwe 003d1a65 00f78284 008140f8      0 00f77fdc 300/1024 listen/http1
Mwe 0035cafa 00f7a63c 0053e5c8      0 00f786c4 7640/8192 Crypto CA

```

----- show failover -----

No license for Failover

----- show traffic -----

```

outside:
  received (in 205213.390 secs):
    1267 packets    185042 bytes
    0 pkts/sec      0 bytes/sec
  transmitted (in 205213.390 secs):
    20 packets      1352 bytes
    0 pkts/sec      0 bytes/sec
inside:
  received (in 205215.800 secs):
    0 packets       0 bytes
    0 pkts/sec      0 bytes/sec
  transmitted (in 205215.800 secs):
    1 packets       60 bytes
    0 pkts/sec      0 bytes/sec
intf2:
  received (in 205215.810 secs):
    0 packets       0 bytes
    0 pkts/sec      0 bytes/sec
  transmitted (in 205215.810 secs):
    0 packets       0 bytes
    0 pkts/sec      0 bytes/sec

```

----- show perfmon -----

PERFMON STATS:	Current	Average
Xlates	0/s	0/s
Connections	0/s	0/s
TCP Conns	0/s	0/s
UDP Conns	0/s	0/s
URL Access	0/s	0/s
URL Server Req	0/s	0/s
TCP Fixup	0/s	0/s
TCPIntercept	0/s	0/s
HTTP Fixup	0/s	0/s
FTP Fixup	0/s	0/s
AAA Authen	0/s	0/s
AAA Author	0/s	0/s
AAA Account	0/s	0/s

Related Commands

Command	Description
show clock	Displays the clock for use with the Syslog Server (PFSS) and the Public Key Infrastructure (PKI) protocol.
show conn count	Displays the connections used and available.
show cpu	Display the CPU utilization information.
show failover	Displays the status of a connection and which security appliance is active
show memory	Displays a summary of the maximum physical memory and current free memory that is available to the operating system.
show perfmon	Displays information about the performance of the security appliance
show processes	Displays a list of the processes that are running.
show running-config	Displays the configuration that is currently running on the security appliance.
show xlate	Displays information about the translation slot.

show traffic

To display interface transmit and receive activity, use the **show traffic** command in privileged EXEC mode.

show traffic

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines The **show traffic** command lists the number of packets and bytes moving through each interface since the last show traffic command was entered or since the security appliance came online. The number of seconds is the duration the security appliance has been online since the last reboot, unless the **clear traffic** command was entered since the last reboot. If this is the case, then the number of seconds is the duration since that command was entered.

Examples The following example shows output from the **show traffic** command:

```
hostname# show traffic
outside:
  received (in 102.080 secs):
    2048 packets 204295 bytes
    20 pkts/sec 2001 bytes/sec
  transmitted (in 102.080 secs):
    2048 packets 204056 bytes
    20 pkts/sec 1998 bytes/sec

Ethernet0:
  received (in 102.080 secs):
    2049 packets 233027 bytes
    20 pkts/sec 2282 bytes/sec
  transmitted (in 102.080 secs):
    2048 packets 232750 bytes
    20 pkts/sec 2280 bytes/sec
```

 show traffic**Related Commands**

Command	Description
clear traffic	Resets the counters for transmit and receive activity.

show uauth

To display one or all currently authenticated users, the host IP to which they are bound, and any cached IP and port authorization information, use the **show uauth** command in privileged EXEC mode.

show uauth [*username*]

Syntax Description

username (Optional) Specifies, by username, the user authentication and authorization information to display.

Defaults

Omitting username displays the authorization information for all users.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	—	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **show uauth** command displays the AAA authorization and authentication caches for one user or for all users.

This command is used with the **timeout** command.

Each user host IP address has an authorization cache attached to it. The cache allows up to 16 address and service pairs for each user host. If the user attempts to access a service that has been cached from the correct host, the security appliance considers it preauthorized and immediately proxies the connection. Once you are authorized to access a website, for example, the authorization server is not contacted for each image as it is loaded (assuming the images come from the same IP address). This process significantly increases performance and reduces the load on the authorization server.

The output from the **show uauth** command displays the username that is provided to the authorization server for authentication and authorization purposes, the IP address to which the username is bound, and whether the user is authenticated only or has cached services.



Note

When you enable Xauth, an entry is added to the uauth table (as shown by the **show uauth** command) for the IP address that is assigned to the client. However, when using Xauth with the Easy VPN Remote feature in Network Extension Mode, the IPSec tunnel is created from network to network, so that the users behind the firewall cannot be associated with a single IP address. For this reason, a uauth entry

cannot be created upon completion of Xauth. If AAA authorization or accounting services are required, you can enable the AAA authentication proxy to authenticate users behind the firewall. For more information on AAA authentication proxies, see to the **aaa** commands.

Use the **timeout uauth** command to specify how long the cache should be kept after the user connections become idle. Use the **clear uauth** command to delete all the authorization caches for all the users, which will cause them to have to reauthenticate the next time that they create a connection.

Examples

This example shows sample output from the **show uauth** command when no users are authenticated and one user authentication is in progress:

```
hostname(config)# show uauth
Current      Most Seen
Authenticated Users      0          0
Authen In Progress      0          1
```

This example shows sample output from the **show uauth** command when three users are authenticated and authorized to use services through the security appliance:

```
hostname(config)# show uauth
user 'pat' from 209.165.201.2 authenticated
user 'robin' from 209.165.201.4 authorized to:
    port 192.168.67.34/telnet      192.168.67.11/http      192.168.67.33/tcp/8001
    192.168.67.56/tcp/25      192.168.67.42/ftp
user 'terry' from 209.165.201.7 authorized to:
    port 192.168.1.50/http      209.165.201.8/http
```

Related Commands

Command	Description
clear uauth	Remove current user authentication and authorization information.
timeout	Set the maximum idle time duration.

show url-block

To display the number of packets held in the url-block buffer and the number (if any) dropped due to exceeding the buffer limit or retransmission, use the **show url-block** command in privileged EXEC mode.

show url-block [block statistics]

Syntax Description	block statistics (Optional) Displays block buffer usage statistics.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines	The show url-block block statistics command displays the number of packets held in the url block buffer and the number (if any) dropped due to exceeding the buffer limit or retransmission.

Examples	The following is sample output from the show url-block command:

```
hostname# show url-block
| url-block url-mempool 128 | url-block url-size 4 | url-block block 128
```

This shows the configuration of the URL block buffer.

The following is sample output from the **show url-block block statistics** command:

```
hostname# show url-block block statistics

URL Pending Packet Buffer Stats with max block 128 |
Cumulative number of packets held: | 896
Maximum number of packets held (per URL): | 3
Current number of packets held (global): | 38
Packets dropped due to
| exceeding url-block buffer limit: | 7546
| HTTP server retransmission: | 10
Number of packets released back to client: | 0
```

Related Commands	Commands	Description
	clear url-block block statistics	Clears the block buffer usage counters.
	filter url	Directs traffic to a URL filtering server.
	url-block	Manage the URL buffers used for web server responses.
	url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
	url-server	Identifies an N2H2 or Websense server for use with the filter command.

show url-cache statistics

To display information about the url-cache, which is used for URL responses received from an N2H2 or Websense filtering server, use the **show url-cache statistics** command in privileged EXEC mode.

show url-cache statistics

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines The **show url-cache statistics** command displays the following entries:

- Size—The size of the cache in kilobytes, set with the **url-cache size** option.
- Entries—The maximum number of cache entries based on the cache size.
- In Use—The current number of entries in the cache.
- Lookups—The number of times the security appliance has looked for a cache entry.
- Hits—The number of times the security appliance has found an entry in the cache.

You can view additional information about N2H2 Sentian or Websense filtering activity with the **show perfmon** command.

Examples The following is sample output from the **show url-cache statistics** command:

```
hostname# show url-cache statistics
```

```
URL Filter Cache Stats
-----
| Size :      1KB
  Entries :      36
    In Use :      30
  Lookups :     300
| Hits :      290
```

Related Commands	Commands	Description
	clear url-cache statistics	Removes url-cache command statements from the configuration.
	filter url	Directs traffic to a URL filtering server.
	url-block	Manage the URL buffers used for web server responses.
	url-cache	Enables URL caching for responses received from an N2H2 or Websense server and sets the size of the cache.
	url-server	Identifies an N2H2 or Websense server for use with the filter command.

show url-server

To display information about the URL filtering server, use the **show url-server** command in privileged EXEC mode.

show url-server statistics

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines The **show url-server statistics** command displays the URL server vendor; number of URLs total, allowed, and denied; number of HTTPS connections total, allowed, and denied; number of TCP connections total, allowed, and denied; and the URL server status.

The **show url-server** command displays the following information:

- For N2H2, **url-server (if_name) vendor n2h2 host local_ip port number timeout seconds protocol [{TCP | UDP}] {version 1 | 4}**
- For Websense, **url-server (if_name) vendor websense host local_ip timeout seconds protocol [{TCP | UDP}]**

Examples The following is sample output from the **show url-server statistics** command:

```
hostname## show url-server statistics

URL Server Statistics: |
Vendor websense
HTTPs total/allowed/denied 0/0/0
HTTPSS total/allowed/denied 0/0/0
FTPs total/allowed/denied 0/0/0 |
URL Server Status: |
172.23.58.103 UP |
URL Packets Send and Receive Stats: |
Message Send Receive
```

show url-server

```
STATUS_REQUEST 200 200
LOOKUP_REQUEST 10 10
LOG_REQUEST 20 NA
```

Related Commands

Commands	Description
clear url-server	Clears the URL filtering server statistics.
filter url	Directs traffic to a URL filtering server.
url-block	Manage the URL buffers used for web server responses.
url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

show version

To display the software version, hardware configuration, license key, and related uptime data, use the **show version** command in user EXEC mode.

show version

Syntax Description This command has no arguments or keywords.

Defaults No default behaviors or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
User EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines The **show version** command allows you to display the software version, operating time since the last reboot, processor type, Flash partition type, interface boards, serial number (BIOS ID), activation key value, license type (R or UR), and time stamp for when the configuration was last modified.

The serial number listed with the **show version** command is for the Flash partition BIOS. This number is different from the serial number on the chassis. When you get a software upgrade, you will need the serial number that appears in the **show version** command, not the chassis number.



Note

The uptime value indicates how long a failover set has been running. If one unit stops running, the uptime value will continue to increase as long as the other unit continues to operate.

Examples The following example shows how to display the software version, hardware configuration, license key, and related uptime information:

```
hostname# show version

Cisco PIX Security Appliance Software Version 7.0(4)
Device Manager Version 5.0(4)

Compiled on Tue 27-Sep-05 10:41 by root
System image file is "flash:/cdisk.bin"
```

```

Config file at boot was "startup-config"

pix2 up 7 days 7 hours

Hardware:   PIX-515E, 128 MB RAM, CPU Pentium II 433 MHz
Flash E28F128J3 @ 0xffff00000, 16MB
BIOS Flash AM29F400B @ 0xfffd8000, 32KB

0: Ext: Ethernet0      : address is 0011.2094.1d2b, irq 10
1: Ext: Ethernet1      : address is 0011.2094.1d2c, irq 11

Licensed features for this platform:
Maximum Physical Interfaces : 6
Maximum VLANs               : 25
Inside Hosts                : Unlimited
Failover                    : Active/Active
VPN-DES                     : Enabled
VPN-3DES-AES                : Enabled
Cut-through Proxy           : Enabled
Guards                      : Enabled
URL Filtering                : Enabled
Security Contexts           : 5
GTP/GPRS                    : Enabled
VPN Peers                   : Unlimited

This platform has an Unrestricted (UR) license.

Serial Number: 808184143
Running Activation Key: 0xcfc22f25d 0xec1c3174 0x8cb138a0 0xaad8b878 0x4f32fd90
Configuration last modified by enable_15 at 14:18:26.103 UTC Thu Oct 6 2005
hostname#

```

Related Commands

Command	Description
show hardware	Displays detail hardware information.
show serial	Displays the hardware serial information.
show uptime	Displays how long the security appliance has been up.

show vpn load-balancing

To display the runtime statistics for the VPN load-balancing virtual cluster configuration, use the **show vpn-load-balancing** command in global configuration, privileged EXEC, or VPN load-balancing mode.

show vpn load-balancing

Syntax Description This command has no variables or arguments.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—
Privileged EXEC	•	—	•	—	—
vpn load-balancing	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Usage Guidelines The **show vpn load-balancing** command displays statistical information for the virtual VPN load-balancing cluster. If the local device is not participating in the VPN load-balancing cluster, this command indicates that VPN load balancing has not been configured for this device.

Examples This example displays **show vpn load-balancing** command and its output for a situation in which the local device is participating in the VPN load-balancing cluster:

```
hostname(config-load-balancing)# show vpn load-balancing
```

```
Status: enabled
Role: Master
Failover: n/a
Encryption: enabled
Cluster IP: 192.168.1.100
Peers: 1
Public IP Role Pri Model Load (%) Sessions
-----
* 192.168.1.40 Master 10 PIX-515 0 0
192.168.1.110 Backup 5 PIX-515 0 0
hostname(config-load-balancing)#
```

If the local device is not participating in the VPN load-balancing cluster, the **show vpn load-balancing** command shows a different result:

```
hostname(config)# show vpn load-balancing  
VPN Load Balancing has not been configured.
```

Related Commands

Command	Description
clear configure vpn load-balancing	Removes vpn load-balancing command statements from the configuration.
show running-config vpn load-balancing	Displays the the current VPN load-balancing virtual cluster configuration.
vpn load-balancing	Enters vpn load-balancing mode.

show vpn-sessiondb

To display information about VPN sessions, use the show **vpn-sessiondb** command in privileged EXEC mode. The command includes options for displaying information in full or in detail, lets you specify type of sessions to display, and provides options to filter and sort the information. The syntax table and usage notes organize the choices accordingly.

```
show vpn-sessiondb [detail] [full] {remote | l2l | index indexnumber | webvpn | svc | email-proxy}
[filter {name username | ipaddress IPaddr | a-ipaddress IPaddr | p-ipaddress IPaddr |
tunnel-group groupname | protocol protocol-name | encryption encryption-algo}]
[sort {name | ipaddress | a-ipaddress | p-ip address | tunnel-group | protocol | encryption}]
```

Syntax Descriptions

Granularity of Display

detail	Displays extended details about a session. For example, using the detail option for an IPSec session displays additional details such as the IKE hashing algorithm, authentication mode, and rekey interval. If you choose detail , and the full option, the security appliance displays the detailed output in a machine-readable format.
filter	Filters the output to display only the information you specify by using one or more of the filter options. For more information, see usage notes.
full	Displays streamed, untruncated output. Output is delineated by characters and a \n string between records.
sort	Sorts the output according to the sort option you specify. For more information, see usage notes.

Session Type to Display

email-proxy	Displays email-proxy sessions. You can display this information for e-mail proxy sessions, or you can filter it by using the following filter and sort options: name (connection name), ipaddress (client), encryption .
index <i>indexnumber</i>	Displays a single session by index number. Specify the index number for the session, 1 - 750. Filter and sort options do not apply.
l2l	Displays VPN LAN-to-LAN session information. You can display this information for all groups or you can filter it by using the following filter and sort options: name , ipaddress , protocol , encryption .
remote	Displays remote-access sessions. You can display this information for all groups or you can filter it by using the following filter options: name , a-ipaddress , p-ipaddress , tunnel-group , protocol , encryption .
svc	Displays SVC sessions. You can display this information for all groups or you can filter it by using the following filter options: a-ipaddress , encryption , name , p-ipaddress .
vpn-lb	Displays VPN Load Balancing Management sessions. You can display this information for all groups or you can filter it by using the following filter options: encryption , ipaddress , name , protocol .
webvpn	Displays information about WebVPN sessions. You can display this information for all groups or you can filter it by using the following filter and sort options: name , ipaddress , encryption .

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can use the following options to filter and to sort the session display:

Filter/Sort Option	Meaning						
filter a-ipaddress <i>IPaddr</i>	Filters the output to display information for the specified assigned IP address or addresses only.						
sort a-ipaddress	Sorts the display by assigned IP addresses.						
filter encryption <i>encryption-algo</i>	Filters the output to display information for sessions using the specified encryption algorithm(s) only.						
sort encryption	Sorts the display by encryption algorithm. Encryption algorithms include:						
	<table> <tr> <td>aes128</td><td>des</td></tr> <tr> <td>aes192</td><td>3des</td></tr> <tr> <td>aes256</td><td>rc4</td></tr> </table>	aes128	des	aes192	3des	aes256	rc4
aes128	des						
aes192	3des						
aes256	rc4						
filter ipaddress <i>IPaddr</i>	Filters the output to display information for the specified inside IP address or addresses only.						
sort ipaddress	Sorts the display by inside IP addresses.						
filter name <i>username</i>	Filters the output to display sessions for the specified username(s).						
sort name	Sorts the display by usernames in alphabetical order.						
filter p-address <i>IPaddr</i>	Filters the output to display information for the specified outside IP address only.						
sort p-address	Sorts the display by the specified outside IP address or addresses.						
filter protocol <i>protocol-name</i>	Filters the output to display information for sessions using the specified protocol(s) only.						
sort protocol	Sorts the display by protocol. Protocols include:						

Filter/Sort Option	Meaning	
	IKE	IPSecoverTCP
	IMAP4S	IPSecOverUDP
	IPSec	SMTPS
	IPSecLAN2LAN	userHTTPS
	IPSecLAN2LANOverNatT	vcaLAN2LAN
	IPSecOverNatT	
filter tunnel-group <i>groupname</i>	Filters the output to display information for the specified tunnel group(s) only.	
sort tunnel-group	Sorts the display by tunnel group.	
 character	Modifies the output, using the following arguments: {begin include exclude grep [-v]} {reg_exp}	
<cr>	Sends the output to the console.	

The following example, entered in privileged EXEC mode, shows detailed information about LAN-to-LAN sessions:

```

hostname# show vpn-sessiondb detail 121
Session Type: LAN-to-LAN Detailed
Connection   : 172.16.0.1
Index        : 1                      IP Addr      : 172.16.0.1
Protocol     : IPSecLAN2LAN           Encryption   : AES256
Bytes Tx     : 48484156               Bytes Rx     : 875049248
Login Time   : 09:32:03 est Mon Aug 2 2004
Duration     : 6:16:26
Filter Name   :

IKE Sessions: 1 IPSec Sessions: 2

IKE:
  Session ID   : 1
  UDP Src Port : 500                      UDP Dst Port : 500
  IKE Neg Mode : Main                     Auth Mode    : preSharedKeys
  Encryption   : AES256                   Hashing      : SHA1
  Rekey Int (T): 86400 Seconds             Rekey Left(T): 63814 Seconds
  D/H Group    : 5

IPSec:
  Session ID   : 2
  Local Addr   : 10.0.0.0/255.255.255.0
  Remote Addr  : 209.165.201.30/255.255.255.0
  Encryption   : AES256                   Hashing      : SHA1
  Encapsulation: Tunnel                   PFS Group    : 5
  Rekey Int (T): 28800 Seconds             Rekey Left(T): 10903 Seconds
  Bytes Tx     : 46865224                  Bytes Rx     : 2639672
  Pkts Tx      : 1635314                    Pkts Rx      : 37526

IPSec:
  Session ID   : 3
  Local Addr   : 10.0.0.1/255.255.255.0
  Remote Addr  : 209.165.201.30/255.255.255.0
  Encryption   : AES256                   Hashing      : SHA1
  Encapsulation: Tunnel                   PFS Group    : 5
  Rekey Int (T): 28800 Seconds             Rekey Left(T): 6282 Seconds

```

■ show vpn-sessiondb

```

Bytes Tx      : 1619268          Bytes Rx      : 872409912
Pkts Tx       : 19277           Pkts Rx       : 1596809

```

hostname#

Related Commands

Command	Description
show running-configuration vpn-sessiondb	Displays the VPN session database running configuration.
show vpn-sessiondb ratio	Displays VPN session encryption or protocol ratios.
show vpn-sessiondb summary	Displays a summary of all VPN sessions.

show vpn-sessiondb ratio

To display the ratio of current sessions as a percentage by protocol or encryption algorithm, use the **show vpn-sessiondb ratio** command in privileged EXEC mode.

show vpn-sessiondb ratio {protocol | encryption} [**filter** *groupname*]

Syntax Description

encryption	Identifies the encryption protocols you want to display. Refers to phase 2 encryption. Encryption algorithms include: aes128 des aes192 3des aes256 rc4
filter <i>groupname</i>	Filters the output to include session ratios only for the tunnel group you specify.
protocol	Identifies the protocols you want to display. Protocols include: IKE SMTPS IMAP4S userHTTPS IPSec vcaLAN2LAN IPSecLAN2LAN IPSecLAN2LANOverNatT IPSecOverNatT IPSecoverTCP IPSecOverUDP

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
				Multiple	
Command Mode	Routed	Transparent	Single	Context	System
Privileged EXEC	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following is sample output for the **show vpn-sessiondb ratio** command, with **encryption** as the argument:

show vpn-sessiondb ratio

```
hostname# show vpn-sessiondb ratio enc
Filter Group      : All
Total Active Sessions: 5
Cumulative Sessions : 9

Encryption      Sessions      Percent
none            0              0%
DES             1              20%
3DES            0              0%
AES128          4              80%
AES192          0              0%
AES256          0              0%
```

The following is sample output for the **show vpn-sessiondb ratio** command with **protocol** as the argument:

```
hostname# show vpn-sessiondb ratio protocol
Filter Group      : All
Total Active Sessions: 6
Cumulative Sessions : 10

Protocol      Sessions      Percent
IKE           0              0%
IPSec         1              20%
IPSecLAN2LAN  0              0%
IPSecLAN2LANOverNatT  0              0%
IPSecOverNatT  0              0%
IPSecOverTCP  1 20%
IPSecOverUDP  0              0%
vpnLoadBalanceMgmt  0              0%
userHTTPS     0              0%
IMAP4S        3 30%
POP3S         0              0%
SMTPS         3 30%
```

Related Commandss

Command	Description
show vpn-sessiondb	Displays sessions with or without extended details, optionally filtered and sorted by criteria you specify.
show vpn-sessiondb summary	Displays a session summary, including total current session, current sessions of each type, peak and total cumulative, maximum concurrent sessions

show vpn-sessiondb summary

To display the a summary of current VPN sessions, use the **show vpn-sessiondb summary** command in privileged EXEC mode. The session summary includes total current sessions, current sessions of each type, peak and total cumulative sessions, and maximum concurrent sessions.

show vpn-sessiondb summary

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following is sample output for the **show vpn-sessiondb summary** command:

```
hostname# show vpn-sessiondb summary
```

```
Active Sessions:          Session Information:
  LAN-to-LAN : 2           Peak Concurrent : 7
  Remote Access : 5       Concurrent Limit: 2000
  WebVPN : 0              Cumulative Sessions: 12
  Email Proxy : 0
```

Related Commands

Command	Description
show vpn-sessiondb	Displays sessions with or without extended details, optionally filtered and sorted by criteria you specify.
show vpn-sessiondb ratio	Displays VPN session encryption or protocol ratios.

show xlate

To display information about the translation slots, use the **show xlate** command in privileged EXEC mode.

```
show xlate [global ip1[-ip2] [netmask mask]] [local ip1[-ip2] [netmask mask]]
           [gport port1[-port2]] [lport port1[-port2]] [interface if_name] [state state] [debug] [detail]
```

show xlate count

Syntax Description

count	Displays the translation count.
debug	(Optional) Displays xlate debug information.
detail	(Optional) Displays detail xlate information.
global <i>ip1</i> [- <i>ip2</i>]	(Optional) Displays the active translations by global IP address or range of addresses.
gport <i>port1</i> [- <i>port2</i>]	Displays the active translations by the global port or range of ports.
interface <i>if_name</i>	(Optional) Displays the active translations by interface.
local <i>ip1</i> [- <i>ip2</i>]	(Optional) Displays the active translations by local IP address or range of addresses.
lport <i>port1</i> [- <i>port2</i>]	Displays the active translations by local port or range of ports.
netmask <i>mask</i>	(Optional) Specifies the network mask to qualify the global or local IP addresses.
state <i>state</i>	(Optional) Displays the active translations by state. You can enter one or more of the following states: • static—specifies static translations. • portmap—specifies PAT global translations. • norandomseq—specifies a nat or static translation with the norandomseq setting. • identity—specifies nat 0 identity address translations. When specifying more than one state, separate the states with a space.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **show xlate** command displays the contents of the translation slots. The **show xlate detail** command displays the following information:

- **{ ICMP|TCP|UDP } PAT from interface:real-address/real-port to interface:mapped-address/mapped-port flags translation-flags**
- **NAT from interface:real-address/real-port to interface:mapped-address/mapped-port flags translation-flags**

The translation flags are defined in [Table 7-31](#).

Table 7-33 Translation Flags

Flag	Description
s	Static translation slot
d	Dump translation slot on next cleaning cycle
r	Port map translation (Port Address Translation)
n	No randomization of TCP sequence number
i	Inside address translation
D	DNS A RR rewrite
I	Identity translation from nat 0

**Note**

When the **vpncient** configuration is enabled and the inside host is sending out DNS requests, the **show xlate** command may list multiple xlates for a static translation.

Examples

The following is sample output from the **show xlate** command. It shows how translation slot information with three active PATs.

```
hostname# show xlate
```

```
3 in use, 3 most used
PAT Global 192.150.49.1(0) Local 10.1.1.15 ICMP id 340
PAT Global 192.150.49.1(1024) Local 10.1.1.15(1028)
PAT Global 192.150.49.1(1024) Local 10.1.1.15(516)
```

The following is sample output from the **show xlate detail** command. It shows the translation type and interface information with three active PATs.

The first entry is a TCP PAT for host port (10.1.1.15, 1025) on the inside network to host-port (192.150.49.1, 1024) on the outside network. The **r** flag indicates that the translation is a PAT. The **i** flag indicates that the translation applies to the inside address port.

The second entry is a UDP PAT for host port (10.1.1.15, 1028) on the inside network to host port (192.150.49.1, 1024) on the outside network. The **r** flag indicates that the translation is a PAT. The **i** flag indicates that the translation applies to the inside address port.

The third entry is an ICMP PAT for host-ICMP-id (10.1.1.15, 21505) on the inside network to host-ICMP-id (192.150.49.1, 0) on the outside network. The r flag indicates that the translation is a PAT. The i flag indicates that the translation applies to the inside address ICMP ID.

The inside address fields appear as source addresses on packets traversing from the more secure interface to the less secure interface. They appear as destination addresses on packets traversing from the less secure interface to the more secure interface.

```
hostname# show xlate detail
```

```
3 in use, 3 most used
Flags: D - DNS, d - dump, I - identity, i - inside, n - no random,
       r - portmap, s - static
TCP PAT from inside:10.1.1.15/1026 to outside:192.150.49.1/1024 flags ri
UDP PAT from inside:10.1.1.15/1028 to outside:192.150.49.1/1024 flags ri
ICMP PAT from inside:10.1.1.15/21505 to outside:192.150.49.1/0 flags ri
```

The following is sample output from the **show xlate** command. It shows two static translations. The first translation has one associated connection (called “nconns”), and the second translation has four associated connections.

```
hostname# show xlate
```

```
Global 209.165.201.10 Local 209.165.201.10 static nconns 1 econns 0
Global 209.165.201.30 Local 209.165.201.30 static nconns 4 econns 0
```

Related Commands

Command	Description
clear xlate	Clears current translation and connection information.
show conn	Displays all active connections.
show local-host	Displays the local host network information.
show uauth	Displays the currently authenticated users.

shun

To enable a dynamic response to an attacking host by preventing new connections and disallowing packets from any existing connection, use the **shun** command in privileged EXEC mode. To disable a shun that is based on the *src_ip*, the actual address that is used by the security appliance for shun lookups, use the **no** form of this command.

```
shun src_ip [dst_ip src_port dest_port [protocol]] [vlan vlan_id]
```

```
no shun src_ip [vlan vlan_id]
```

Syntax Description

<i>dest_port</i>	(Optional) Destination port of the connection causing the shun.
<i>dst_ip</i>	(Optional) Address of the target host.
<i>protocol</i>	(Optional) IP protocol, such as UDP or TCP. Not optional if <i>dst_ip</i> is specified.
<i>src_ip</i>	Address of the attacking host.
<i>src_port</i>	(Optional) Source port of the connection causing the shun.
<i>vlan_id</i>	(Optional) Specifies the VLAN ID.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **shun** command allows you to apply a blocking function to the interface receiving the attack. Packets containing the IP source address of the attacking host are dropped and logged until the blocking function is removed manually or by the Cisco IPS master module. No traffic from the IP source address is allowed to traverse the security appliance. Any remaining connections time out as part of the normal architecture. The blocking function of the **shun** command is applied whether or not a connection with the specified host address is currently active.

The **shun** command only blocks packets inbound from that IP on the local interface. Packets destined to the IP address are still allowed.

If you use the **shun** command only with the source IP address of the host, then the default is 0. No further traffic from the offending host is allowed.

Because the **shun** command is used to block attacks dynamically, it is not displayed in the security appliance configuration.

Whenever an interface is removed, all shuns that are attached to that interface are also removed. If you add a new interface or replace the same interface (same name), then you must add that interface to the IPS Sensor if you want the IPS Sensor to monitor that interface.

Examples

The following example shows that the offending host (10.1.1.27) makes a connection with the victim (10.2.2.89) with TCP. The connection in the security appliance connection table reads as follows:

```
10.1.1.27, 555-> 10.2.2.89, 666 PROT TCP
```

If you applied the **shun** command in the following way:

```
hostname# shun 10.1.1.27 10.2.2.89 555 666 tcp
```

the preceding command deletes the connection from the security appliance connection table and also prevents packets from 10.1.1.27 from going through the security appliance. The offending host can be inside or outside of the security appliance.

Related Commands

Command	Description
clear shun	Disables all the shuns that are currently enabled and clears the shun statistics.
show shun	Displays the shun information.

shutdown

To disable an interface, use the **shutdown** command in interface configuration mode. To enable an interface, use the **no** form of this command.

shutdown

no shutdown

Syntax Description

This command has no arguments or keywords.

Defaults

All physical interfaces are shut down by default. Allocated interfaces in security contexts are not shut down in the configuration.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Interface configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was moved from a keyword of the interface command to an interface configuration mode command.

Usage Guidelines

By default, all physical interfaces are shut down. You must enable the physical interface before any traffic can pass through an enabled subinterface. For multiple context mode, if you allocate a physical interface or subinterface to a context, the interfaces are enabled by default in the context. However, before traffic can pass through the context interface, you must also enable the interface in the system configuration. If you shut down an interface in the system execution space, then that interface is down in all contexts that share it.

Examples\

The following example enables a main interface:

```
hostname(config)# interface gigabitethernet0/2
hostname(config-if)# speed 1000
hostname(config-if)# duplex full
hostname(config-if)# nameif inside
hostname(config-if)# security-level 100
hostname(config-if)# ip address 10.1.1.1 255.255.255.0
hostname(config-if)# no shutdown
```

The following example enables a subinterface:

```
hostname(config)# interface gigabitethernet0/2.1
hostname(config-subif)# vlan 101
hostname(config-subif)# nameif dmz1
hostname(config-subif)# security-level 50
hostname(config-subif)# ip address 10.1.2.1 255.255.255.0
hostname(config-subif)# no shutdown
```

The following example shuts down the subinterface:

```
hostname(config)# interface gigabitethernet0/2.1
hostname(config-subif)# vlan 101
hostname(config-subif)# nameif dmz1
hostname(config-subif)# security-level 50
hostname(config-subif)# ip address 10.1.2.1 255.255.255.0
hostname(config-subif)# shutdown
```

Related Commands

Command	Description
clear xlate	Resets all translations for existing connections, causing the connections to be reset.
interface	Configures an interface and enters interface configuration mode.

smtps

To enter SMTPS configuration mode, use the **smtps** command in global configuration mode. To remove any commands entered in SMTPS command mode, use the **no** version of this command. SMTPS is a TCP/IP protocol that lets you to send e-mail over an SSL connection.

smtps

no smtps

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to enter SMTPS configuration mode:

```
hostname(config)# smtps
hostname(config-smtps)#
```

Related Commands

Command	Description
clear configure smtps	Removes the SMTPS configuration.
show running-config smtps	Displays the running configuration for SMTPS.

smtp-server

To configure an SMTP server, use the **smtp-server** command in global configuration mode. To remove the attribute from the configuration, use the **no** version of this command.

The security appliance includes an internal SMTP client that the Events system can use to notify external entities that a certain event has occurred. You can configure SMTP servers to receive these event notices, and then forward them to specified e-mail addresses. The SMTP facility is active only when you enable E-mail events an the security appliance.

smtp-server {*primary_server*} [*backup_server*]

no smtp-server

Syntax Description

<i>primary_server</i>	Identifies the primary SMTP server. Use either an IP address or DNS name
<i>backup_server</i>	Identifies a backup SMTP server to relay event messages in the event the primary SMTP server is unavailable. Use either an IP address or DNS name.

Defaults

No SMTP server is configured by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Examples

The following example shows how to set an SMTP server with an IP address of 10.1.1.24, and a backup SMTP server with an IP address of 10.1.1.34:

```
hostname(config)# smtp-server 10.1.1.24 10.1.1.34
```

Related Commands

Command	Description

snmp-server

To provide the security appliance event information through SNMP, use the **snmp-server** command in privileged EXEC mode. To disable the SNMP commands, use the **no** form of this command.

snmp-server {**community** | **contact** | **location**} *text*}

no snmp-server {**community** | **contact** | **location**} *text*}

snmp-server host *interface_name ip_addr* [**community** *commstr*] [**trap** | **poll**] [**version** *vers*]
[**udp-port** *udp_port*]

no snmp-server host *interface_name ip_addr* [**community** *commstr*] [**trap** | **poll**] [**version** *vers*]
[**udp-port** *udp_port*]

snmp-server enable [**traps** [**all** | *feature* [*trap1* ... [*trapn*]]]

no snmp-server enable [**traps** [**all** | *feature* [*trap1* ... [*trapn*]]]

snmp-server listen-port *lport*

no snmp-server listen-port *lport*

Syntax Description

community <i>text</i>	Specifies the security appliance community string to the SNMP management station.
contact <i>text</i>	Specifies the name of the contact person or the PIX system administrator.
location <i>text</i>	Specifies the security appliance location.
host	Specifies an IP address of the SNMP management station to which traps should be sent and/or from which the SNMP requests come.
<i>interface_name</i>	Interface name where the SNMP management station resides.
<i>ip_addr</i>	IP address of a host to which SNMP traps should be sent and/or from which the SNMP requests come.
trap	(Optional) Specifies that only traps are sent and that this host is not allowed to poll.
poll	(Optional) Specifies that this host is allowed to poll.
enable	Enable specific SNMP trap notifications.
enable traps	Enables sending log messages as SNMP trap notifications.
all	Enable or disable traps for all features.
community	Specifies the community string of the security appliance.
<i>commstr</i>	The community string for a specific host.
feature	The feature for which traps are enabled.
<i>trapn</i>	A specific trap to enable.
listen-port	Override the default port (161) for incoming SNMP requests. ¹
<i>lport</i>	The port on which incoming requests will be accepted.
udp-port <i>udp_port</i>	Configure port to which notifications will be sent

1. The **listen-port** keyword is only available in admin context because the **snmp-server** command is not available in the system context.

Defaults

By default, both traps and polls are acted upon.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **snmp-server** command allows you to identify the site, management station, community string, and user information.

Enter the password key in use at the SNMP management station. The SNMP community string is a shared secret among the SNMP management station and the network nodes being managed. The security appliance uses the key to determine if the incoming SNMP request is valid. For example, you could designate a site with a community string and then configure the routers, security appliance, and the management station with this same string. The security appliance uses this string and does not respond to requests with an invalid community string.

The **contact text** is case sensitive and can be up to 127 characters. Spaces are accepted, but multiple spaces are shortened to a single space.

The **location text** is case sensitive and can be up to 127 characters. Spaces are accepted, but multiple spaces are shortened to a single space.

You can specify up to 32 SNMP management stations.

When configuring a host using the **snmp-server host** command, specifying the **trap** option will cause the device to reject incoming requests from the host.

The **clear configure snmp-server** and **no snmp-server** commands disable the SNMP commands in the configuration as follows:

```
hostname(config)# no snmp-server location
hostname(config)# no snmp-server contact
hostname(config)# snmp-server community public
hostname(config)# no snmp-server enable traps
```

Examples

This example shows the commands that you would enter to start receiving SNMP requests from a management station:

```
hostname(config)# snmp-server community wallawallabingbang
hostname(config)# snmp-server location Building 42, Sector 54
hostname(config)# snmp-server contact Sherlock Holmes
hostname(config)# snmp-server host perimeter 10.1.2.42
```

Related Commands	Command	Description
	clear configure snmp-server	Disables the Simple Network Management Protocol (SNMP) server.
	show snmp-server statistics	Displays information about the SNMP server.
	show running-config snmp-server	Displays the SNMP server configuration.

snmp-map

To identify a specific map for defining the parameters for SNMP inspection, use the **snmp-map** command in global configuration mode. To remove the map, use the **no** form of this command.

snmp-map *map_name*

no snmp-map *map_name*

Syntax Description

map_name The name of the SNMP map.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **snmp-map** command to identify a specific map to use for defining the parameters for SNMP inspection. When you enter this command, the system enters the SNMP map configuration mode, which lets you enter the different commands used for defining the specific map. After defining the SNMP map, you use the **inspect snmp** command to enable the map. Then you use the **class-map**, **policy-map**, and **service-policy** commands to define a class of traffic, to apply the **inspect** command to the class, and to apply the policy to one or more interfaces.

Examples

The following example shows how to identify SNMP traffic, define a SNMP map, define a policy, and apply the policy to the outside interface.

```
hostname(config)# access-list snmp-acl permit tcp any any eq 161
hostname(config)# access-list snmp-acl permit tcp any any eq 162
hostname(config)# class-map snmp-port
hostname(config-cmap)# match access-list snmp-acl
hostname(config-cmap)# exit
hostname(config)# snmp-map inbound_snmp
hostname(config-snmp-map)# deny version 1
hostname(config-snmp-map)# exit
hostname(config)# policy-map inbound_policy
hostname(config-pmap)# class snmp-port
hostname(config-pmap-c)# inspect snmp inbound_snmp
```

```
hostname(config-pmap-c)# exit
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
deny version	Disallows traffic using a specific version of SNMP.
inspect snmp	Enable SNMP application inspection.
policy-map	Associates a class map with specific security actions.

snmp-server enable trap remote-access

To enable threshold trapping, use the **snmp-server enable trap remote-access** command in global configuration mode. To disable threshold trapping, use the **no** version of this command. This command lets the security appliance send traps when remote access sessions reach the number set with the **remote-access threshold session-threshold-exceeded** command.

snmp-server enable trap remote-access session-threshold-exceeded

no snmp-server enable trap remote-access

Syntax Description

session-threshold-exceeded	Session threshold is exceeded.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to enable threshold trapping:

```
hostname# snmp-server enable trap remote-access session-threshold-exceeded
```

Related Commands

Command	Description
remote-access threshold session-threshold-exceeded	Specifies a number of active, concurrent, remote access sessions, at which point the security appliance sends traps.

speed

To set the speed of a copper (RJ-45) Ethernet interface, use the **speed** command in interface configuration mode. To restore the speed setting to the default, use the **no** form of this command.

speed { **auto** | **10** | **100** | **1000** | **nonegotiate** }

no speed [**auto** | **10** | **100** | **1000** | **nonegotiate**]

Syntax Description

10	Sets the speed to 10BASE-T.
100	Sets the speed to 100BASE-T.
1000	Sets the speed to 1000BASE-T. For copper Gigabit Ethernet only.
auto	Auto detects the speed.
nonegotiate	For fiber interfaces, sets the speed to 1000 Mbps and does not negotiate link parameters. This command and the no form of this command are the only settings available for fiber interfaces. When you set the value to no speed nonegotiate (the default), the interface enables link negotiation, which exchanges flow-control parameters and remote fault information.

Defaults

For copper interfaces, the default is **speed auto**.

For fiber interfaces, the default is **no speed nonegotiate**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was moved from a keyword of the interface command to an interface configuration mode command.

Usage Guidelines

Set the speed on the physical interface only.

If your network does not support auto detection, set the speed to a specific value.

For RJ-45 interfaces on the ASA 5500 series adaptive security appliance, the default auto-negotiation setting also includes the Auto-MDI/MDIX feature. Auto-MDI/MDIX eliminates the need for crossover cabling by performing an internal crossover when a straight cable is detected during the auto-negotiation phase. Either the speed or duplex must be set to auto-negotiate to enable Auto-MDI/MDIX for the interface. If you explicitly set both the speed and duplex to a fixed value, thus disabling auto-negotiation for both settings, then Auto-MDI/MDIX is also disabled.

Examples

The following example sets the speed to 1000BASE-T:

```
hostname(config)# interface gigabitethernet0/1
hostname(config-if)# speed 1000
hostname(config-if)# duplex full
hostname(config-if)# nameif inside
hostname(config-if)# security-level 100
hostname(config-if)# ip address 10.1.1.1 255.255.255.0
hostname(config-if)# no shutdown
```

Related Commands

Command	Description
clear configure interface	Clears all configuration for an interface.
duplex	Sets the duplex mode.
interface	Configures an interface and enters interface configuration mode.
show interface	Displays the runtime status and statistics of interfaces.
show running-config interface	Shows the interface configuration.

split-dns

To enter a list of domains to be resolved through the split tunnel, use the **split-dns** command in group-policy configuration mode. To delete a list, use the **no** form of this command.

To delete all split tunneling domain lists, use the **no split-dns** command without arguments. This deletes all configured split tunneling domain lists, including a null list created by issuing the **split-dns none** command.

When there are no split tunneling domain lists, users inherit any that exist in the default group policy. To prevent users from inheriting such split tunneling domain lists, use the **split-dns none** command.

split-dns { **value** *domain-name1 domain-name2 domain-nameN* | **none** }

no split-dns [*domain-name domain-name2 domain-nameN*]

Syntax Description

value <i>domain-name</i>	Provides a domain name that the security appliance resolves through the split tunnel.
none	Indicates that there is no split DNS list. Sets a split DNS list with a null value, thereby disallowing a split DNS list. Prevents inheriting a split DNS list from a default or specified group policy.

Defaults

Split DNS is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use a single space to separate each entry in the list of domains. There is no limit on the number of entries, but the entire string can be no longer than 255 characters. You can use only alphanumeric characters, hyphens (-), and periods (.).

The **no split-dns** command, when used without arguments, deletes all current values, including a null value created by issuing the **split-dns none** command.



Note

The AnyConnect VPN client and the SSL VPN Client do not support split DNS.

Examples

The following example shows how to configure the domains Domain1, Domain2, Domain3 and Domain4 to be resolved through split tunneling for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# split-dns value Domain1 Domain2 Domain3 Domain4
```

Related Commands

Command	Description
default-domain	Specifies a default domain name that the IPsec client uses for DNS queries that omit the domain field.
split-dns	Provides a list of domains to be resolved through the split tunnel.
split-tunnel-network-list	Identifies the access list the security appliance uses to distinguish networks that require tunneling and those that do not.
split-tunnel-policy	Lets an IPsec client conditionally direct packets over an IPsec tunnel in encrypted form, or to a network interface in cleartext form

split-tunnel-network-list

To create a network list for split tunneling, use the **split-tunnel-network-list** command in group-policy configuration mode. To delete a network list, use the **no** form of this command.

To delete all split tunneling network lists, use the **no split-tunnel-network-list** command without arguments. This deletes all configured network lists, including a null list created by issuing the **split-tunnel-network-list none** command.

When there are no split tunneling network lists, users inherit any network lists that exist in the default or specified group policy. To prevent users from inheriting such network lists, use the **split-tunnel-network-list none** command.

Split tunneling network lists distinguish networks that require traffic to travel across the tunnel from those that do not require tunneling.

split-tunnel-network-list {**value** *access-list name* | **none**}

no split-tunnel-network-list value [*access-list name*]

Syntax Description

value <i>access-list name</i>	Identifies an access list that enumerates the networks to tunnel or not tunnel.
none	Indicates that there is no network list for split tunneling; the security appliance tunnels all traffic. Sets a split tunneling network list with a null value, thereby disallowing split tunneling. Prevents inheriting a default split tunneling network list from a default or specified group policy.

Defaults

By default, there are no split tunneling network lists.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Group-policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The security appliance makes split tunneling decisions on the basis of a network list, which is a standard ACL that consists of a list of addresses on the private network.

The **no split-tunnel-network-list** command, when used without arguments, deletes all current network lists, including a null value created by issuing the **split-tunnel-network-list none** command.

Examples

The following example shows how to set a network list called FirstList for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# split-tunnel-network-list FirstList
```

Related Commands

Command	Description
access-list	Creates an access list, or uses a downloadable access list.
default-domain	Specifies a default domain name that the IPsec client uses for DNS queries that omit the domain field.
split-dns	Provides a list of domains to be resolved through the split tunnel.
split-tunnel-policy	Lets an IPsec client conditionally direct packets over an IPsec tunnel in encrypted form, or to a network interface in cleartext form.

split-tunnel-policy

To set a split tunneling policy, use the **split-tunnel-policy** command in group-policy configuration mode. To remove the split-tunnel-policy attribute from the running configuration, use the **no** form of this command. This enables inheritance of a value for split tunneling from another group policy.

Split tunneling lets a remote-access IPsec client conditionally direct packets over an IPsec tunnel in encrypted form, or to a network interface in cleartext form. With split-tunneling enabled, packets not bound for destinations on the other side of the IPsec tunnel do not have to be encrypted, sent across the tunnel, decrypted, and then routed to a final destination.

This command applies this split tunneling policy to a specific network.

split-tunnel-policy {tunnelall | tunnelspecified | excludespecified}

no split-tunnel-policy

Syntax Description

excludespecified	Defines a list of networks to which traffic goes in the clear. This feature is useful for remote users who want to access devices on their local network, such as printers, while they are connected to the corporate network through a tunnel. This option applies only to the Cisco VPN Client.
split-tunnel-policy	Indicates that you are setting rules for tunneling traffic.
tunnelall	Specifies that no traffic goes in the clear or to any other destination than the security appliance. Remote users reach internet networks through the corporate network and do not have access to local networks.
tunnelspecified	Tunnels all traffic from or to the specified networks. This option enables split tunneling. It lets you create a network list of addresses to tunnel. Data to all other addresses travels in the clear, and is routed by the remote user's internet service provider.

Defaults

Split tunneling is disabled by default, which is tunnelall.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Split tunneling is primarily a traffic management feature, not a security feature. In fact, for optimum security, we recommend that you not enable split tunneling.

Examples

The following example shows how to set a split tunneling policy of tunneling only specified networks for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# split-tunnel-policy tunnelspecified
```

Related Commands

Command	Description
default-domain	Specifies a default domain name that the IPSec client uses for DNS queries that omit the domain field.
split-dns	Provides a list of domains to be resolved through the split tunnel.
split-tunnel-network-list none	Indicates that no access list exists for split tunneling. All traffic travels across the tunnel.
split-tunnel-network-list value	Identifies the access list the security appliance uses to distinguish networks that require tunneling and those that do not.

ssh

To add SSH access to the security appliance, use the **ssh** command in global configuration mode. To disable SSH access to the security appliance, use the **no** form of this command. This command supports IPv4 and IPv6 addresses.

```
ssh {ip_address mask | ipv6_address/prefix} interface
```

```
no ssh {ip_address mask | ipv6_address/prefix} interface
```

Syntax Description

<i>interface</i>	The security appliance interface on which SSH is enabled. If not specified, SSH is enabled on all interfaces except the outside interface.
<i>ip_address</i>	IPv4 address of the host or network authorized to initiate an SSH connection to the security appliance. For hosts, you can also enter a host name.
<i>ipv6_address/prefix</i>	The IPv6 address and prefix of the host or network authorized to initiate an SSH connection to the security appliance.
<i>mask</i>	Network mask for <i>ip_address</i> .

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **ssh ip_address** command specifies hosts or networks that are authorized to initiate an SSH connection to the security appliance. You can have multiple **ssh** commands in the configuration. The **no** form of the command removes a specific SSH command from the configuration. Use the **clear configure ssh** command to remove all SSH commands.

Before you can begin using SSH to the security appliance, you must generate a default RSA key using the **crypto key generate rsa** command.

The following security algorithms and ciphers are supported on the security appliance:

- 3DES and AES ciphers for data encryption
- HMAC-SHA and HMAC-MD5 algorithms for packet integrity

- RSA public key algorithm for host authentication
- Diffie-Hellman Group 1 algorithm for key exchange

The following SSH Version 2 features are not supported on the security appliance:

- X11 forwarding
- Port forwarding
- SFTP support
- Kerberos and AFS ticket passing
- Data compression

Examples

The following example shows how to configure the inside interface to accept SSH version 2 connections from a management console with the IP address 10.1.1.1. The idle session timeout is set to 60 minutes and SCP is enabled.

```
hostname(config)# ssh 10.1.1.1 255.255.255.0 inside
hostname(config)# ssh version 2
hostname(config)# ssh copy enable
hostname(config)# ssh timeout 60
```

Related Commands

Command	Description
clear configure ssh	Clears all SSH commands from the running configuration.
crypto key generate rsa	Generates RSA key pairs for identity certificates.
debug ssh	Displays debug information and error messages for SSH commands.
show running-config ssh	Displays the current SSH commands in the running configuration.
ssh scopy enable	Enables a secure copy server on the security appliance.
ssh version	Restricts the security appliance to using either SSH Version 1 or SSH Version 2.

ssh disconnect

To disconnect an active SSH session, use the **ssh disconnect** command in privileged EXEC mode.

ssh disconnect *session_id*

Syntax Description

session_id Disconnects the SSH session specified by the ID number.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

You must specify a session ID. Use the **show ssh sessions** command to obtain the ID of the SSH session you want to disconnect.

Examples

The following example shows an SSH session being disconnected:

```
hostname# show ssh sessions
SID Client IP      Version Mode Encryption Hmac      State      Username
0  172.69.39.39     1.99  IN   aes128-cbc md5      SessionStarted pat
                                OUT aes128-cbc md5      SessionStarted pat
1  172.23.56.236    1.5   -    3DES      -        SessionStarted pat
2  172.69.39.29     1.99  IN   3des-cbc  sha1     SessionStarted pat
                                OUT 3des-cbc  sha1     SessionStarted pat

hostname# ssh disconnect 2
hostname# show ssh sessions
SID Client IP      Version Mode Encryption Hmac      State      Username
0  172.69.39.29     1.99  IN   aes128-cbc md5      SessionStarted pat
                                OUT aes128-cbc md5      SessionStarted pat
1  172.23.56.236    1.5   -    3DES      -        SessionStarted pat
```

Related Commands

Command	Description
show ssh sessions	Displays information about active SSH sessions to the security appliance.
ssh timeout	Sets the timeout value for idle SSH sessions.

ssh scopy enable

To enable Secure Copy (SCP) on the security appliance, use the **ssh scopy enable** command in global configuration mode. To disable SCP, use the **no** form of this command.

ssh scopy enable

no ssh scopy enable

Syntax Description This command has no keywords or arguments.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	•

Command History	Release	Modification
	7.0	This command was introduced.

Usage Guidelines SCP is a server-only implementation; it will be able to accept and terminate connections for SCP but can not initiate them. The security appliance has the following restrictions:

- There is no directory support in this implementation of SCP, limiting remote client access to the security appliance internal files.
- There is no banner support when using SCP.
- SCP does not support wildcards.
- The security appliance license must have the VPN-3DES-AES feature to support SSH version 2 connections.

Examples The following example shows how to configure the inside interface to accept SSH Version 2 connections from a management console with the IP address 10.1.1.1. The idle session timeout is set to 60 minutes and SCP is enabled.

```
hostname(config)# ssh 10.1.1.1 255.255.255.0 inside
hostname(config)# ssh version 2
hostname(config)# ssh scopy enable
hostname(config)# ssh timeout 60
```

Related Commands

Command	Description
clear configure ssh	Clears all SSH commands from the running configuration.
debug ssh	Displays debug information and error messages for SSH commands.
show running-config ssh	Displays the current SSH commands in the running configuration.
ssh	Allows SSH connectivity to the security appliance from the specified client or network.
ssh version	Restricts the security appliance to using either SSH Version 1 or SSH Version 2.

ssh timeout

To change the default SSH session idle timeout value, use the **ssh timeout** command in global configuration mode. To restore the default timeout value, use the **no** form of this command.

ssh timeout *number*

no ssh timeout

Syntax Description

number Specifies the duration in minutes that an SSH session can remain inactive before being disconnected. Valid values are from 1 to 60 minutes.

Defaults

The default session timeout value is 5 minutes.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **ssh timeout** command specifies the duration in minutes that a session can be idle before being disconnected. The default duration is 5 minutes.

Examples

The following example shows how to configure the inside interface to accept only SSH version 2 connections from a management console with the IP address 10.1.1.1. The idle session timeout is set to 60 minutes and SCP is enabled.

```
hostname(config)# ssh 10.1.1.1 255.255.255.0 inside
hostname(config)# ssh version 2
hostname(config)# ssh copy enable
hostname(config)# ssh timeout 60
```

Related Commands

Command	Description
clear configure ssh	Clears all SSH commands from the running configuration.
show running-config ssh	Displays the current SSH commands in the running configuration.

Command	Description
show ssh sessions	Displays information about active SSH sessions to the security appliance.
ssh disconnect	Disconnects an active SSH session.

ssh version

To restrict the version of SSH accepted by the security appliance, use the **ssh version** command in global configuration mode. To restore the default value, use the **no** form of this command. The default values permits SSH Version 1 and SSH Version 2 connections to the security appliance.

ssh version {1 | 2}

no ssh version [1 | 2]

Syntax Description

1	Specifies that only SSH Version 1 connections are supported.
2	Specifies that only SSH Version 2 connections are supported.

Defaults

By default, both SSH Version 1 and SSH Version 2 are supported.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

1 and 2 specify which version of SSH the security appliance is restricted to using. The **no** form of the command returns the security appliance to the default stance, which is compatible mode (both version can be used).

Examples

The following example shows how to configure the inside interface to accept SSH Version 2 connections from a management console with the IP address 10.1.1.1. The idle session timeout is set to 60 minutes and SCP is enabled.

```
hostname(config)# ssh 10.1.1.1 255.255.255.0 inside
hostname(config)# ssh version 2
hostname(config)# ssh copy enable
hostname(config)# ssh timeout 60
```

Related Commands

Command	Description
clear configure ssh	Clears all SSH commands from the running configuration.
debug ssh	Displays debug information and error messages for SSH commands.
show running-config ssh	Displays the current SSH commands in the running configuration.
ssh	Allows SSH connectivity to the security appliance from the specified client or network.

ssl client-version

To specify the SSL/TLS protocol version the security appliance uses when acting as a client, use the **ssl client-version** command in global configuration mode. To revert to the default, **any**, use the **no** version of this command. This command lets you restrict the versions of SSL/TLS that the security appliance sends.

ssl client-version [*any* | *ssl3-only* | *tlsv1-only*]

no ssl client-version

Syntax Description

any	The security appliance sends SSL version3 hellos, and negotiates either SSL version 3 or TLS version 1.
ssl3-only	The security appliance sends SSL version 3 hellos, and accepts only SSL version 3.
tlsv1-only	The security appliance sends TLSv1 client hellos, and accepts only TLS version 1.

Defaults

The default value is **any**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

TCP Port Forwarding does not work when a WebVPN user connects with some SSL versions, as follows:

Negotiate SSLv3	Java downloads
Negotiate SSLv3/TLSv1	Java downloads
Negotiate TLSv1	Java does NOT download
TLSv1Only	Java does NOT download
SSLv3Only	Java does NOT download

The issue is that JAVA only negotiates SSLv3 in the client Hello packet when you launch the Port Forwarding application.

Examples

The following example shows how to configure the security appliance to communicate using only TLSv1 when acting as an SSL client:

```
hostname(config)# ssl client-version tlsv1-only
```

Related Commands

Command	Description
clear config ssl	Removes all SSL commands from the configuration, reverting to the default values.
ssl encryption	Specifies the encryption algorithms that the SSL/TLS protocol uses.
show running-config ssl	Displays the current set of configured SSL commands.
ssl server-version	Specifies the SSL/TLS protocol version the security appliance uses when acting as a server.
ssl trust-point	Specifies the certificate trust point that represents the SSL certificate for an interface.

ssl encryption

To specify the encryption algorithms that the SSL/TLS protocol uses, use the **ssl encryption** command in global configuration mode. Issuing the command again overwrites the previous setting. The ordering of the algorithms determines preference for their use. You can add or remove algorithms to meet the needs of your environment. To restore the default, which is the complete set of encryption algorithms, use the **no** version of the command.

ssl encryption [*3des-sha1*] [*des-sha1*] [*rc4-md5*] [*possibly others*]

no ssl encryption

Syntax Description

<i>3des-sha1</i>	Specifies triple DES encryption with Secure Hash Algorithm 1.
<i>des-sha1</i>	Specifies DES encryption with Secure Hash Algorithm 1.
<i>rc4-md5</i>	Specifies RC4 encryption with an MD5 hash function.
<i>possibly others</i>	Indicates that more encryption algorithms may be added in future releases.

Defaults

The default is to have all algorithms available in the following order:

[*3des-sha1*] [*des-sha1*] [*rc4-md5*] [*possibly others*]

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to configure the security appliance to use the 3des-sha1 and des-sha1 encryption algorithms:

```
hostname(config)# ssl encryption 3des-sha1 des-sha1
```

Related Commands

Command	Description
clear config ssl	Removes all SSL commands from the configuration, reverting to the default values.
show running-config ssl	Displays the current set of configured SSL commands.

Command	Description
ssl client-version	Specifies the SSL/TLS protocol version the security appliance uses when acting as a client.
ssl server-version	Specifies the SSL/TLS protocol version the security appliance uses when acting as a server.
ssl trust-point	Specifies the certificate trust point that represents the SSL certificate for an interface.

ssl server-version

To specify the SSL/TLS protocol version the security appliance uses when acting as a server, use the **ssl server-version** command in global configuration mode. To revert to the default, any, use the **no** version of this command. This command lets you restrict the versions of SSL/TSL that the security appliance accepts.

ssl server-version [*any* | *ssl3* | *tlsv1* | *ssl3-only* | *tlsv1-only*]

no ssl server-version

Syntax Description

<i>any</i>	The security appliance accepts SSL version 2 client hellos, and negotiates either SSL version 3 or TLS version 1.
<i>ssl3</i>	The security appliance accepts SSL version 2 client hellos, and negotiates to SSL version 3.
<i>ssl3-only</i>	The security appliance accepts only SSL version 3 client hellos, and uses only SSL version 3.
<i>tlsv1</i>	The security appliance accepts SSL version 2 client hellos, and negotiates to TLS version 1.
<i>tlsv1-only</i>	The security appliance accepts only TLSv1 client hellos, and uses only TLS version 1.

Defaults

The default value is **any**.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

TCP Port Forwarding does not work when a WebVPN user connects with some SSL versions, as follows:

Negotiate SSLv3	Java downloads
Negotiate SSLv3/TLSv1	Java downloads
Negotiate TLSv1	Java does NOT download
TLSv1Only	Java does NOT download
SSLv3Only	Java does NOT download

If you configure e-mail proxy, do not set the SSL version to TLSv1 Only. Outlook and Outlook Express do not support TLS.

Examples

The following example shows how to configure the security appliance to communicate using only TLSv1 when acting as an SSL server:

```
hostname(config)# ssl server-version tlsv1-only
```

Related Commands

Command	Description
<code>clear config ssl</code>	Removes all ssl commands from the configuration, reverting to the default values.
<code>show running-config ssl</code>	Displays the current set of configured ssl commands.
<code>ssl client-version</code>	Specifies the SSL/TLS protocol version the security appliance uses when acting as a client.
<code>ssl encryption</code>	Specifies the encryption algorithms that the SSL/TLS protocol uses.
<code>ssl trust-point</code>	Specifies the certificate trust point that represents the SSL certificate for an interface.

ssl trust-point

To specify the certificate trustpoint that represents the SSL certificate for an interface, use the **ssl trust-point** command with the *interface* argument in global configuration mode. If you do not specify an interface, this command creates the fallback trustpoint for all interfaces that do not have a trustpoint configured. To remove an SSL trustpoint from the configuration that does not specify an interface, use the **no** version of this command. To remove an entry that does specify an interface, use the **no ssl trust-point {trustpoint [interface]}** version of the command.

ssl trust-point {trustpoint [interface]}

no ssl trust-point

Syntax Description

<i>interface</i>	The name for the interface to which the trustpoint applies. The nameif command specifies the name of the interface.
trustpoint	The <i>name</i> of the CA trustpoint as configured in the crypto ca trustpoint {name} command.

Defaults

The default is no trustpoint association. The security appliance uses the default self-generated RSA key-pair certificate.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Observe these guidelines when using this command:

- The value for *trustpoint* must be the name of the CA trustpoint as configured in the **crypto ca trustpoint {name}** command.
- The value for *interface* must be the *nameif* name of a previously configured interface.
- Removing a trustpoint also removes any **ssl trust-point** entries that reference that trustpoint.
- You can have one **ssl trustpoint** entry for each interface and one that specifies no interfaces.
- You can reuse the same trustpoint for multiple entries.

The following example explains how to use the **no** versions of this command:

The configuration includes these SSL trustpoints:

```
ssl trust-point tp1
ssl trust-point tp2 outside
```

Issue the command:

```
no ssl trust-point
```

Then show run ssl will have:

```
ssl trust-point tp2 outside
```

Examples

The following example shows how to configure an ssl trustpoint called FirstTrust for the inside interface, and a trustpoint called DefaultTrust with no associated interface.

```
hostname(config)# ssl trust-point FirstTrust inside
hostname(config)# ssl trust-point DefaultTrust
```

The next example shows how to use the **no** version of the command to delete a trustpoint that has no associated interface:

```
hostname(config)# show running-configuration ssl
ssl trust-point FirstTrust inside
ssl trust-point DefaultTrust
hostname(config)# no ssl trust-point
hostname(config)# show running-configuration ssl
ssl trust-point FirstTrust inside
```

The next example shows how to delete a trustpoint that does have an associated interface:

```
hostname(config)# show running-configuration ssl
ssl trust-point FirstTrust inside
ssl trust-point DefaultTrust
hostname(config)# no ssl trust-point FirstTrust inside
hostname(config)# show running-configuration ssl
ssl trust-point DefaultTrust
```

Command	Description
clear config ssl	Removes all SSL commands from the configuration, reverting to the default values.
show running-config ssl	Displays the current set of configured SSL commands.
ssl client-version	Specifies the SSL/TLS protocol version the security appliance uses when acting as a client.
ssl encryption	Specifies the encryption algorithms that the SSL/TLS protocol uses.
ssl server-version	Specifies the SSL/TLS protocol version the security appliance uses when acting as a server.

static

To configure a persistent one-to-one address translation rule by mapping a real IP address to a mapped IP address, use the **static** command in global configuration mode. To restore the default settings, use the **no** form of this command.

For static NAT:

```
static (real_ifc,mapped_ifc) {mapped_ip | interface} {real_ip [netmask mask] |  
  access-list access_list_name} [dns] [norandomseq [nailed]] [[tcp] {max_conns {emb_lim}}  
  [udp udp_max_conns]]
```

```
no static (real_ifc,mapped_ifc) {mapped_ip | interface} {real_ip [netmask mask] |  
  access-list access_list_name} [dns] [norandomseq [nailed]] [[tcp] {max_conns {emb_lim}}  
  [udp udp_max_conns]]
```

For static PAT:

```
static (real_ifc,mapped_ifc) {tcp | udp} {mapped_ip | interface} mapped_port {real_ip real_port  
  [netmask mask]} | {access-list access_list_name} [dns] [norandomseq [nailed]] [[tcp]  
  {max_conns {emb_lim}}] [udp udp_max_conns]]
```

```
no static (real_ifc,mapped_ifc) {tcp | udp} {mapped_ip | interface} mapped_port {real_ip  
  real_port [netmask mask]} | {access-list access_list_name} [dns] [norandomseq [nailed]]  
  [[tcp] {max_conns {emb_lim}}] [udp udp_max_conns]]
```

Syntax Description

access-list <i>access_list_name</i>	Lets you identify real addresses for NAT by specifying the real and destination addresses (or ports). This feature is known as policy NAT. The subnet mask used in the access list is also used for the <i>mapped_ip</i>. You can only include permit statements in the access list. You can also specify the real and destination ports in the access list using the eq operator. Policy NAT does not consider the inactive or time-range keywords; all ACEs are considered to be active for policy NAT configuration.
dns	(Optional) Rewrites the A record, or address record, in DNS replies that match this static. For DNS replies traversing from a mapped interface to a real interface, the A record is rewritten from the mapped value to the real value. Inversely, for DNS replies traversing from a real interface to a mapped interface, the A record is rewritten from the real value to the mapped value.
<i>emb_lim</i>	(Optional) Specifies the maximum number of embryonic connections per host. The default is 0, which means unlimited embryonic connections. Limiting the number of embryonic connections protects you from a DoS attack. The security appliance uses the embryonic limit to trigger TCP Intercept, which protects inside systems from a DoS attack perpetrated by flooding an interface with TCP SYN packets. An embryonic connection is a connection request that has not finished the necessary handshake between source and destination. This option does not apply to outside NAT. The TCP intercept feature applies only to hosts or servers on a higher security level. If you set the embryonic limit for outside NAT, the embryonic limit is ignored.

interface	Uses the interface IP address as the mapped address. Use this keyword if you want to use the interface address, but the address is dynamically assigned using DHCP. Note You must use the interface keyword instead of specifying the actual IP address when you want to include the IP address of an interface in a static PAT entry. Otherwise, an error message is generated.
<i>mapped_ifc</i>	Specifies the name of the interface connected to the mapped IP address network.
<i>mapped_ip</i>	Specifies the address to which the real address is translated.
<i>mapped_port</i>	Specifies the mapped TCP or UDP port. You can specify ports by either a literal name or a number in the range of 0 to 65535. You can view valid port numbers online at the following website: http://www.iana.org/assignments/port-numbers
nailed	(Optional) Allows TCP sessions for asymmetrically routed traffic. This option allows inbound traffic to traverse the security appliance without a corresponding outbound connection to establish the state. This command is used in conjunction with the failover timeout command. The failover timeout command specifies the amount of time after a system boots or becomes active that the nailed sessions are accepted. If not configured, the connections cannot be reestablished. Note Adding the nailed option to the static command causes TCP state tracking and sequence checking to be skipped for the connection. Using the asr-group command to configure asymmetric routing support is more secure than using the static command with the nailed option and is the recommended method for configuring asymmetric routing support.
netmask mask	Specifies the subnet mask for the real and mapped addresses. For single hosts, use 255.255.255.255. If you do not enter a mask, then the default mask for the IP address class is used, with one exception. If a host-bit is non-zero after masking, a host mask of 255.255.255.255 is used. If you use the access-list keyword instead of the <i>real_ip</i> , then the subnet mask used in the access list is also used for the <i>mapped_ip</i> .
norandomseq	(Optional) Disables TCP ISN randomization protection. Each TCP connection has two ISNs: one generated by the client and one generated by the server. The security appliance randomizes the ISN of the TCP SYN passing in both the inbound and outbound directions. Randomizing the ISN of the protected host prevents an attacker from predicting the next ISN for a new connection and potentially hijacking the new session. TCP initial sequence number randomization can be disabled if required. For example: • If another in-line firewall is also randomizing the initial sequence numbers, there is no need for both firewalls to be performing this action, even though this action does not affect the traffic. • If you use eBGP multi-hop through the security appliance, and the eBGP peers are using MD5. Randomization breaks the MD5 checksum. • You use a WAAS device that requires the security appliance not to randomize the sequence numbers of connections.
<i>real_ifc</i>	Specifies the name of the interface connected to the real IP address network.
<i>real_ip</i>	Specifies the real address that you want to translate.

<i>real_port</i>	Specifies the real TCP or UDP port. You can specify ports by either a literal name or a number in the range of 0 to 65535. You can view valid port numbers online at the following website: http://www.iana.org/assignments/port-numbers
tcp	For static PAT, specifies the protocol as TCP.
tcp <i>max_conns</i>	Specifies the maximum number of simultaneous TCP and UDP connections for the entire subnet. The default is 0, which means unlimited connections. (Idle connections are closed after the idle timeout specified by the timeout conn command.) This option does not apply to outside NAT. The security appliance only tracks connections from a higher security interface to a lower security interface.
udp	For static PAT, specifies the protocol as UDP.
udp <i>udp_max_conns</i>	(Optional) Used with the udp keyword to set the maximum number of simultaneous UDP connections the <i>real_ip</i> hosts are each allowed to use.

Defaults

The defaults are as follows:

- No embryonic limit.
- No connection limits.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Static NAT creates a fixed translation of real address(es) to mapped address(es). With dynamic NAT and PAT, each host uses a different address or port for each subsequent translation. Because the mapped address is the same for each consecutive connection with static NAT, and a persistent translation rule exists, static NAT allows hosts on the destination network to initiate traffic to a translated host (if there is an access list that allows it).



Note

For static policy NAT, in undoing the translation, the ACL in the **static** command is not used. If the destination address in the packet matches the mapped address in the static rule, the static rule is used to untranslate the address.

The main difference between dynamic NAT and a range of addresses for static NAT is that static NAT allows a remote host to initiate a connection to a translated host (if there is an access list that allows it), while dynamic NAT does not. You also need an equal number of mapped addresses as real addresses with static NAT.

Static PAT is the same as static NAT, except it lets you specify the protocol (TCP or UDP) and port for the real and mapped addresses.

This feature lets you identify the same mapped address across many different static statements, so long as the port is different for each statement (you cannot use the same mapped address for multiple static NAT statements).

You cannot use the same real or mapped address in multiple **static** commands between the same two interfaces. Do not use a mapped address in the **static** command that is also defined in a **global** command for the same mapped interface.

When you specify the ports in policy NAT for applications that require application inspection for secondary channels (FTP, VoIP, etc.), the security appliance automatically translates the secondary ports.

NAT, in the conventional sense, is not available in transparent firewall mode. In transparent firewall mode, you can use the **static** command to configure maximum connections, maximum embryonic connections, and TCP sequence randomization. In this case, both the real and mapped IP addresses are the same.

You can alternatively configure maximum connections, maximum embryonic connections, and TCP sequence randomization using the **set connection** commands. If you configure these settings for the same traffic using both methods, then the security appliance uses the lower limit. For TCP sequence randomization, if it is disabled using either method, then the security appliance disables TCP sequence randomization.

If you specify a network for translation (for example, 10.1.1.0 255.255.255.0), then the security appliance translates the .0 and .255 addresses. If you want to prevent access to these addresses, be sure to configure an access list to deny access.

After changing or removing a static command statement, use the **clear xlate** command to clear the translations.

Examples

Static NAT Examples

For example, the following policy static NAT example shows a single real address that is translated to two mapped addresses depending on the destination address:

```
hostname(config)# access-list NET1 permit ip host 10.1.2.27 209.165.201.0 255.255.255.224
hostname(config)# access-list NET2 permit ip host 10.1.2.27 209.165.200.224
255.255.255.224
hostname(config)# static (inside,outside) 209.165.202.129 access-list NET1
hostname(config)# static (inside,outside) 209.165.202.130 access-list NET2
```

The following command maps an inside IP address (10.1.1.3) to an outside IP address (209.165.201.12):

```
hostname(config)# static (inside,outside) 209.165.201.12 10.1.1.3 netmask 255.255.255.255
```

The following command maps the outside address (209.165.201.15) to an inside address (10.1.1.6):

```
hostname(config)# static (outside,inside) 10.1.1.6 209.165.201.15 netmask 255.255.255.255
```

The following command statically maps an entire subnet:

```
hostname(config)# static (inside,dmz) 10.1.1.0 10.1.2.0 netmask 255.255.255.0
```

This example shows how to permit a finite number of users to call in through H.323 using Intel Internet Phone, CU-SeeMe, CU-SeeMe Pro, MeetingPoint, or Microsoft NetMeeting. The **static** command maps addresses 209.165.201.0 through 209.165.201.30 to local addresses 10.1.1.0 through 10.1.1.30 (209.165.201.1 maps to 10.1.1.1, 209.165.201.10 maps to 10.1.1.10, and so on).

```
hostname(config)# static (inside, outside) 209.165.201.0 10.1.1.0 netmask 255.255.255.224
hostname(config)# access-list acl_out permit tcp any 209.165.201.0 255.255.255.224 eq h323
hostname(config)# access-group acl_out in interface outside
```

This example shows the commands that are used to disable Mail Guard:

```
hostname(config)# static (dmz1,outside) 209.165.201.1 10.1.1.1 netmask 255.255.255.255
hostname(config)# access-list acl_out permit tcp any host 209.165.201.1 eq smtp
hostname(config)# access-group acl_out in interface outside
hostname(config)# no fixup protocol smtp 25
```

In the example, the **static** command allows you to set up a global address to permit outside hosts access to the 10.1.1.1 mail server host on the dmz1 interface. You should set the MX record for DNS to point to the 209.165.201.1 address so that mail is sent to this address. The **access-list** command allows the outside users to access the global address through the SMTP port (25). The **no fixup protocol** command disables Mail Guard.

Static PAT Examples

For example, for Telnet traffic initiated from hosts on the 10.1.3.0 network to the security appliance outside interface (10.1.2.14), you can redirect the traffic to the inside host at 10.1.1.15 by entering the following commands:

```
hostname(config)# access-list TELNET permit tcp host 10.1.1.15 eq telnet 10.1.3.0
255.255.255.0 eq telnet
hostname(config)# static (inside,outside) tcp 10.1.2.14 telnet access-list TELNET
```

For HTTP traffic initiated from hosts on the 10.1.3.0 network to the security appliance outside interface (10.1.2.14), you can redirect the traffic to the inside host at 10.1.1.15 by entering:

```
hostname(config)# access-list HTTP permit tcp host 10.1.1.15 eq http 10.1.3.0
255.255.255.0 eq http
hostname(config)# static (inside,outside) tcp 10.1.2.14 http access-list HTTP
```

To redirect Telnet traffic from the security appliance outside interface (10.1.2.14) to the inside host at 10.1.1.15, enter the following command:

```
hostname(config)# static (inside,outside) tcp 10.1.2.14 telnet 10.1.1.15 telnet netmask
255.255.255.255
```

If you want to allow the preceding real Telnet server to initiate connections, though, then you need to provide additional translation. For example, to translate all other types of traffic, enter the following commands. The original **static** command provides translation for Telnet to the server, while the **nat** and **global** commands provide PAT for outbound connections from the server.

```
hostname(config)# static (inside,outside) tcp 10.1.2.14 telnet 10.1.1.15 telnet netmask
255.255.255.255
hostname(config)# nat (inside) 1 10.1.1.15 255.255.255.255
hostname(config)# global (outside) 1 10.1.2.14
```

If you also have a separate translation for all inside traffic, and the inside hosts use a different mapped address from the Telnet server, you can still configure traffic initiated from the Telnet server to use the same mapped address as the **static** statement that allows Telnet traffic to the server. You need to create a more exclusive **nat** statement just for the Telnet server. Because **nat** statements are read for the best

match, more exclusive **nat** statements are matched before general statements. The following example shows the Telnet **static** statement, the more exclusive **nat** statement for initiated traffic from the Telnet server, and the statement for other inside hosts, which uses a different mapped address.

```
hostname(config)# static (inside,outside) tcp 10.1.2.14 telnet 10.1.1.15 telnet netmask
255.255.255.255
hostname(config)# nat (inside) 1 10.1.1.15 255.255.255.255
hostname(config)# global (outside) 1 10.1.2.14
hostname(config)# nat (inside) 2 10.1.1.0 255.255.255.0
hostname(config)# global (outside) 2 10.1.2.78
```

To translate a well-known port (80) to another port (8080), enter the following command:

```
hostname(config)# static (inside,outside) tcp 10.1.2.45 80 10.1.1.16 8080 netmask
255.255.255.255
```

Related Commands

Command	Description
clear configure static	Removes static commands from the configuration.
clear xlate	Clears all translations.
nat	Configures dynamic NAT.
show running-config static	Displays all static commands in the configuration.
timeout conn	Sets the timeout for connections.

strict-http

To allow forwarding of non-compliant HTTP traffic, use the **strict-http** command in HTTP map configuration mode, which is accessible using the **http-map** command. To reset this feature to its default behavior, use the **no** form of the command.

strict-http action {allow | reset | drop} [log]

no strict-http action {allow | reset | drop} [log]

Syntax Description

action	The action taken when a message fails this command inspection.
allow	Allows the message.
drop	Closes the connection.
log	(Optional) Generate a syslog.
reset	Closes the connection with a TCP reset message to client and server.

Defaults

This command is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
HTTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Although strict HTTP inspection cannot be disabled, the **strict-http action allow** command causes the security appliance to allow forwarding of non-compliant HTTP traffic. This command overrides the default behavior, which is to deny forwarding of non-compliant HTTP traffic.

Examples

The following example allows forwarding of non-compliant HTTP traffic:

```
hostname(config)# http-map inbound_http
hostname(config-http-map)# strict-http allow
hostname(config-http-map)# exit
```

Related Commands

Commands	Description
class-map	Defines the traffic class to which to apply security actions.
debug appfw	Displays detailed information about traffic associated with enhanced HTTP inspection.
http-map	Defines an HTTP map for configuring enhanced HTTP inspection.
inspect http	Applies a specific HTTP map to use for application inspection.
policy-map	Associates a class map with specific security actions.

strip-group

This command applies only to usernames received in the form user@realm. A realm is an administrative domain appended to a username with the @ delimiter (juser@abc).

To enable or disable strip-group processing, use the **strip-group** command in tunnel-group general-attributes mode. The security appliance selects the tunnel group for PPP connections by obtaining the group name from the username presented by the VPN client. When strip-group processing is enabled, the security appliance sends only the user part of the username for authorization/authentication. Otherwise (if disabled), the security appliance sends the entire username including the realm.

To disable strip-group processing, use the **no** form of this command.

strip-group

no strip-group

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting for this command is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group general attributes configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute only to the IPSec remote access tunnel-type.

Examples

The following example configures a remote access tunnel group named “remotegrp” for type IPSec remote access, then enters general configuration mode, sets the tunnel group named “remotegrp” as the default group policy, and then enables strip group for that tunnel group:

```
hostname(config)# tunnel-group remotegrp type IPSec_ra
hostname(config)# tunnel-group remotegrp general
hostname(config-general)# default-group-policy remotegrp
hostname(config-general)# strip-group
hostname(config-general)
```

Related Commands	Command	Description
	clear-configure tunnel-group	Clears all configured tunnel groups.
	group-delimiter	Enables group-name parsing and specifies the delimiter to be used when parsing group names from the user names that are received when tunnels are being negotiated.
	show running-config tunnel group	Shows the tunnel group configuration for all tunnel groups or for a particular tunnel group.
	tunnel-group-map default group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

strip-realm

To enable or disable strip-realm processing, use the **strip-realm** command in tunnel-group general-attributes configuration mode. Strip-realm processing removes the realm from the username when sending the username to the authentication or authorization server. A realm is an administrative domain appended to a username with the @ delimiter (username@realm). If the command is enabled, the security appliance sends only the user part of the username authorization/authentication. Otherwise, the security appliance sends the entire username.

To disable strip-realm processing, use the **no** form of this command.

strip-realm

no strip-realm

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting for this command is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group general attributes configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute only to the IPSec remote access tunnel-type.

Examples

The following example configures a remote access tunnel group named “remotegrp” for type IPSec remote access, then enters general configuration mode, sets the tunnel group named “remotegrp” as the default group policy, and then enables strip realm for that tunnel group:

```
hostname(config)# tunnel-group remotegrp type IPSec_ra
hostname(config)# tunnel-group remotegrp general
hostname(config-general)# default-group-policy remotegrp
hostname(config-general)# strip-realm
```

neral)

ostname(config-ge

Related Commands

Command	Description
clear configure tunnel-group	Clears all configured tunnel groups.
show running-config tunnel-group	Shows the indicated certificate map entry.
tunnel-limit	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

subject-name (crypto ca certificate map)

To indicate that rule entry is applied to the subject DN of the IPSec peer certificate, use the **subject-name** command in CA certificate map configuration mode. To remove an subject-name, use the **no** form of the command.

subject-name [*attr tag*] *eq* | *ne* | *co* | *nc* *string*

no subject-name [*attr tag*] *eq* | *ne* | *co* | *nc* *string*

Syntax Description

attr tag	Indicates that only the specified attribute value from the certificate DN will be compared to the rule entry string. The tag values are as follows: DNQ = DN qualifier GENQ = Generational qualifier I = Initials GN = Given name N = Name SN = Surname IP = IP address SER = Serial number UNAME = Unstructured name EA = Email address T = Title O = Organization Name L = Locality SP = State/Province C = Country OU = Organizational unit CN = Common name
co	Specifies that the rule entry string must be a substring in the DN string or indicated attribute.
eq	Specifies that the DN string or indicated attribute must match the entire rule string.
nc	Specifies that the rule entry string must not be a substring in the DN string or indicated attribute.
ne	Specifies that the DN string or indicated attribute must not match the entire rule string.
string	Specifies the value to be matched.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca certificate map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters the CA certificate map mode for certificate map 1 and creates a rule entry indicating that the Organization attribute of the certificate subject name must be equal to Central.

```
hostname(config)# crypto ca certificate map 1
hostname(ca-certificate-map)# subject-name attr o eq central
hostname(ca-certificate-map)# exit
```

Related Commands

Command	Description
crypto ca certificate map	Enters CA certificate map mode.
issuer-name	Identifies the DN from the CA certificate that is to be compared to the rule entry string.
tunnel-group-map	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

subject-name (crypto ca trustpoint)

To include the indicated subject DN in the certificate during enrollment, use the **subject-name** command in crypto ca trustpoint configuration mode. This is the person or system that uses the certificate. To restore the default setting, use the **no** form of the command.

subject-name *X.500_name*

no subject-name

Syntax Description

<i>X.500_name</i>	Defines the X.500 distinguished name, for example: cn=crl,ou=certs,o=CAName,c=US. The maximum length is 1K characters (effectively unbounded).

Defaults

The default setting is not to include the subject name.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and sets up automatic enrollment at the URL https://frog.phoobin.com and includes the subject DN OU tiedye.com in the the enrollment request for trustpoint central:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# enrollment url http://frog.phoobin.com/
hostname(ca-trustpoint)# subject-name ou=tiedye.com
hostname(ca-trustpoint)#
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint configuration mode.
default enrollment	Returns enrollment parameters to their defaults.
enrollment url	Specifies the URL for enrolling with a CA.

summary-address

To create aggregate addresses for OSPF, use the **summary-address** command in router configuration mode. To remove the summary address or specific summary address options, use the **no** form of this command.

summary-address *addr mask* [**not-advertise**] [**tag** *tag_value*]

no summary-address *addr mask* [**not-advertise**] [**tag** *tag_value*]

Syntax Description

<i>addr</i>	Value of the summary address that is designated for a range of addresses.
<i>mask</i>	IP subnet mask that is used for the summary route.
not-advertise	(Optional) Suppresses routes that match the specified prefix/mask pair.
tag <i>tag_value</i>	(Optional) A 32-bit decimal value attached to each external route. This value is not used by OSPF itself. It may be used to communicate information between ASBRs. If none is specified, then the remote autonomous system number is used for routes from BGP and EGP; for other protocols, zero (0) is used. Valid values range from 0 to 4294967295.

Defaults

The defaults are as follows:

- *tag_value* is 0.
- Routes that match the specified prefix/mask pair are not suppressed.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Routes learned from other routing protocols can be summarized. Using this command for OSPF causes an OSPF Autonomous System Boundary Router (ASBR) to advertise one external route as an aggregate for all redistributed routes that are covered by the address. This command summarizes only routes from other routing protocols that are being redistributed into OSPF. Use the **area range** command for route summarization between OSPF areas.

To remove a **summary-address** command from the configuration, use the **no** form of the command without specifying any of the optional keywords or arguments. To remove an option from a summary command in the configuration, use the **no** form of the command with the options that you want removed. See the “Examples” section for more information.

Examples

The following example configures route summarization with a **tag** set to 3:

```
hostname(config-router)# summary-address 1.1.0.0 255.255.0.0 tag 3  
hostname(config-router)#
```

The following example shows how to use the **no** form of the **summary-address** command with an option to set that option back to the default value. In this example, the **tag** value, set to 3 in the previous example, is removed from the **summary-address** command.

```
hostname(config-router)# no summary-address 1.1.0.0 255.255.0.0 tag 3  
hostname(config-router)#
```

The following example removes the **summary-address** command from the configuration:

```
hostname(config-router)# no summary-address 1.1.0.0 255.255.0.0  
hostname(config-router)#
```

Related Commands

Command	Description
area range	Consolidates and summarizes routes at an area boundary.
router ospf	Enters router configuration mode.
show ospf	Displays the summary address settings for each OSPF routing process.
summary-address	

sunrpc-server

To create entries in the SunRPC services table, use the **sunrpc-server** command in global configuration mode. To remove SunRPC services table entries from the configuration, use the **no** form of this command.

sunrpc-server *ifc_name ip_addr mask service service_type protocol [tcp | udp] port port [- port] timeout hh:mm:ss*

no sunrpc-server *ifc_name ip_addr mask service service_type protocol [tcp | udp] port port [- port] timeout hh:mm:ss*

no sunrpc-server active service service_type server ip_addr

Syntax Description

<i>ifc_name</i>	Server interface name.
<i>ip_addr</i>	SunRPC server IP address.
<i>mask</i>	Network mask.
port port [- port]	Specifies the SunRPC protocol port range.
port- port	(Optional) Specifies the SunRPC protocol port range.
protocol tcp	Specifies the SunRPC transport protocol.
protocol udp	Specifies the SunRPC transport protocol.
<i>service</i>	Specifies a service.
<i>service_type</i>	Sets the SunRPC service program number as specified in the sunrpcinfo command.
timeout hh:mm:ss	Specifies the timeout idle time after which the access for the SunRPC service traffic is closed.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The SunRPC services table is used to allow SunRPC traffic through the security appliance based on an established SunRPC session for the duration specified by the timeout.

Examples

The following example shows how to create an SunRPC services table:

```
hostname(config)# sunrpc-server outside 10.0.0.1 255.0.0.0 service 100003 protocol TCP  
port 111 timeout 0:11:00  
hostname(config)# sunrpc-server outside 10.0.0.1 255.0.0.0 service 100005 protocol TCP  
port 111 timeout 0:11:00
```

Related Commands

Command	Description
clear configure sunrpc-server	Clears the Sun remote processor call services from the security appliance.
show running-config sunrpc-server	Displays the information about the SunRPC configuration.

support-user-cert-validation

To validate a remote user certificate based on the current trustpoint, provided that this trustpoint is authenticated to the CA that issued the remote certificate, use the **support-user-cert-validation** command in crypto ca trustpoint configuration mode. To restore the default setting, use the **no** form of the command.

support-user-cert-validation

no support-user-cert-validation

Syntax Description

This command has no arguments or keywords.

Defaults

The default setting is to support user certificate validation.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Crypto ca trustpoint configuration	•	•	•	•	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The security appliance can have two trustpoints with the same CA resulting in two different identity certificates from the same CA. This option is automatically disabled if the trustpoint is authenticated to a CA that is already associated with another trustpoint that has enabled this feature. This prevents ambiguity in the choice of path-validation parameters. If the user attempts to activate this feature on a trustpoint that has been authenticated to a CA already associated with another trustpoint that has enabled this feature, the action is not permitted. No two trustpoints can have this setting enabled and be authenticated to the same CA.

Examples

The following example enters crypto ca trustpoint configuration mode for trustpoint central, and enables the trustpoint central to accept user validation:

```
hostname(config)# crypto ca trustpoint central
hostname(ca-trustpoint)# support-user-cert-validation
hostname(ca-trustpoint)#
```

Related Commands

Command	Description
crypto ca trustpoint	Enters trustpoint configuration mode.
default enrollment	Returns enrollment parameters to their defaults.

syn-data

To allow or drop SYN packets with data, use the **syn-data** command in tcp-map configuration mode. To remove this specification, use the **no** form of this command.

syn-data { **allow** | **drop** }

no syn-data { **allow** | **drop** }

Syntax Description

allow	Allows SYN packets that contain data.
drop	Drops SYN packets that contain data.

Defaults

Packets with SYN data are allowed by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tcp-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **tcp-map** command is used along with the Modular Policy Framework infrastructure. Define the class of traffic using the **class-map** command and customize the TCP inspection with **tcp-map** commands. Apply the new TCP map using the **policy-map** command. Activate TCP inspection with **service-policy** commands.

Use the **tcp-map** command to enter tcp-map configuration mode. Use the **syn-data** command in tcp-map configuration mode to drop packets with data in SYN packets.

According to the TCP specification, TCP implementations are required to accept data contained in a SYN packet. Because this is a subtle and obscure point, some implementations may not handle this correctly. To avoid any vulnerabilities to insertion attacks involving incorrect end-system implementations, you may choose to drop packets with data in SYN packets.

Examples

The following example shows how to drop SYN packets with data on all TCP flows:

```
hostname(config)# access-list TCP extended permit tcp any any
hostname(config)# tcp-map tmap
hostname(config-tcp-map)# syn-data drop
hostname(config)# class-map cmap
hostname(config-cmap)# match access-list TCP
```



```
hostname(config)# policy-map pmap
hostname(config-pmap)# class cmap
hostname(config-pmap)# set connection advanced-options tmap
hostname(config)# service-policy pmap global
```

Related Commands

Command	Description
class (policy-map)	Specifies a class map to use for traffic classification.
help	Shows syntax help for the policy-map , class (policy-map) , and description commands.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
set connection	Configures connection values.
tcp-map	Creates a TCP map and allows access to tcp-map configuration mode.

sysopt connection permit-ipsec

For traffic that enters the security appliance through an IPSec tunnel and is then decrypted, use the **sysopt connection permit-ipsec** command in global configuration mode to allow the traffic to bypass interface access lists. Group policy and per-user authorization access lists still apply to the traffic. To disable this feature, use the **no** form of this command.

sysopt connection permit-ipsec

no sysopt connection permit-ipsec

Syntax Description

This command has no arguments or keywords.

Defaults

This feature is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0(1)	This command is now enabled by default. Also, only interface access lists are bypassed; group policy or per-user access lists remain in force.

Usage Guidelines

You might want to bypass interface access lists for decrypted traffic to simplify configuration and to maximize the security appliance performance. If you disable this feature, you must apply an access list to the ingress interface that permits decrypted IPSec packets from all IPSec peers (see the **access-list** and **access-group** commands).

Examples

The following example lets IPSec traffic bypass interface access lists:

```
hostname(config)# sysopt connection permit-ipsec
```

Related Commands

Command	Description
clear configure sysopt	Clears the sysopt command configuration.
show running-config sysopt	Shows the sysopt command configuration.

Command	Description
sysopt connection tpmss	Overrides the maximum TCP segment size or ensures that the maximum is not less than a specified size.
sysopt connection timewait	Forces each TCP connection to linger in a shortened TIME_WAIT state after the final normal TCP close-down sequence.

sysopt connection tcpmss

To ensure that the maximum TCP segment size does not exceed the value you set and that the maximum is not less than a specified size, use the **sysopt connection tcpmss** command in global configuration mode. To restore the default setting, use the **no** form of this command.

sysopt connection tcpmss [**minimum**] *bytes*

no sysopt connection tcpmss [**minimum**] [*bytes*]

Syntax Description

<i>bytes</i>	Sets the maximum TCP segment size in bytes, between 48 and any maximum number. The default value is 1380 bytes. You can disable this feature by setting <i>bytes</i> to 0. For the minimum keyword, the <i>bytes</i> represent the smallest maximum value allowed.
minimum	Overrides the maximum segment size to be no less than <i>bytes</i> , between 48 and 65535 bytes. This feature is disabled by default (set to 0).

Defaults

The default maximum value is 1380 bytes. The minimum feature is disabled by default (set to 0).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Both the host and the server can set the maximum segment size when they first establish a connection. If either maximum exceeds the value you set with the **sysopt connection tcpmss** command, then the security appliance overrides the maximum and inserts the value you set. If either maximum is less than the value you set with the **sysopt connection tcpmss minimum** command, then the security appliance overrides the maximum and inserts the “minimum” value you set (the minimum value is actually the smallest maximum allowed). For example, if you set a maximum size of 1200 bytes and a minimum size of 400 bytes, when a host requests a maximum size of 1300 bytes, then the security appliance alters the packet to request 1200 bytes (the maximum). If another host requests a maximum value of 300 bytes, then the security appliance alters the packet to request 400 bytes (the minimum).

The default of 1380 bytes allows room for header information so that the total packet size does not exceed 1500 bytes, which is the default MTU for Ethernet. See the following calculation:

1380 data + 20 TCP + 20 IP + 24 AH + 24 ESP_CIPHER + 12 ESP_AUTH + 20 IP = 1500 bytes

If the host or server does not request a maximum segment size, the security appliance assumes that the RFC 793 default value of 536 bytes is in effect.

If you set the maximum size to be greater than 1380, packets might become fragmented, depending on the MTU size (which is 1500 by default). Large numbers of fragments can impact the performance of the security appliance when it uses the Frag Guard feature. Setting the minimum size prevents the TCP server from sending many small TCP data packets to the client and impacting the performance of the server and the network.

**Note**

Although not advised for normal use of this feature, if you encounter the syslog IPFRAG messages 209001 and 209002, you can raise the *bytes* value.

Examples

The following example sets the maximum size to 1200 and the minimum to 400:

```
hostname(config)# sysopt connection tcpmss 1200
hostname(config)# sysopt connection tcpmss minimum 400
```

Related Commands

Command	Description
clear configure sysopt	Clears the sysopt command configuration.
show running-config sysopt	Shows the sysopt command configuration.
sysopt connection permit-ipsec	Permits any packets that come from an IPSec tunnel without checking any ACLs for interfaces.
sysopt connection timewait	Forces each TCP connection to linger in a shortened TIME_WAIT state after the final normal TCP close-down sequence.

sysopt connection timewait

To force each TCP connection to linger in a shortened TIME_WAIT state of at least 15 seconds after the final normal TCP close-down sequence, use the **sysopt connection timewait** command in global configuration mode. To disable this feature, use the **no** form of this command. You might want to use this feature if an end host application default TCP terminating sequence is a simultaneous close.

sysopt connection timewait

Syntax Description This command has no arguments or keywords.

Defaults This feature is disabled by default.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines The default behavior of the security appliance is to track the shutdown sequence and release the connection after two FINs and the ACK of the last FIN segment. This quick release heuristic enables the security appliance to sustain a high connection rate, based on the most common closing sequence, known as the normal close sequence. However, in a simultaneous close, both ends of the transaction initiate the closing sequence, as opposed to the normal close sequence where one end closes and the other end acknowledges prior to initiating its own closing sequence (see RFC 793). Thus, in a simultaneous close, the quick release forces one side of the connection to linger in the CLOSING state. Having many sockets in the CLOSING state can degrade the performance of an end host. For example, some WinSock mainframe clients are known to exhibit this behavior and degrade the performance of the mainframe server. Using the **sysopt connection timewait** command creates a window for the simultaneous close down sequence to complete.

Examples The following example enables the timewait feature:

```
hostname(config)# sysopt connection timewait
```

Related Commands

Command	Description
clear configure sysopt	Clears the sysopt command configuration.
show running-config sysopt	Shows the sysopt command configuration.
sysopt connection permit-ipsec	Permits any packets that come from an IPSec tunnel without checking any ACLs for interfaces.
sysopt connection tcpmss	Overrides the maximum TCP segment size or ensures that the maximum is not less than a specified size.

sysopt nodnsalias

To disable DNS inspection that alters the DNS A record address when you use the **alias** command, use the **sysopt nodnsalias** command in global configuration mode. To disable this feature, use the **no** form of this command. You might want to disable DNS application inspection if you want the **alias** command to perform only NAT, and DNS packet alteration is undesirable.

sysopt nodnsalias {inbound | outbound}

no sysopt nodnsalias {inbound | outbound}

Syntax Description

inbound	Disables DNS record alteration for packets from lower security interfaces to higher security interfaces specified by an alias command.
outbound	Disables DNS record alteration for packets from higher security interfaces specified by an alias command to lower security interfaces.

Defaults

This feature is disabled by default (DNS record address alteration is enabled).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **alias** command performs NAT and DNS A record address alteration. In some cases, you might want to disable the DNS record alteration.

Examples

The following example disables the DNS address alteration for inbound packets:

```
hostname(config)# sysopt nodnsalias inbound
```

Related Commands

Command	Description
alias	Translates an outside address and alters the DNS records to accommodate the translation.
clear configure sysopt	Clears the sysopt command configuration.

Command	Description
show running-config sysopt	Shows the sysopt command configuration.
sysopt noproxyarp	Disables proxy ARP on an interface.

sysopt noproxyarp

To disable proxy ARP for NAT global addresses on an interface, use the **sysopt noproxyarp** command in global configuration mode. To reenable proxy ARP for global addresses, use the **no** form of this command.

```
sysopt noproxyarp interface_name

no sysopt noproxyarp interface_name
```

Syntax Description	interface_name	The interface name for which you want to disable proxy ARP.

Defaults	Proxy ARP for global addresses is enabled by default.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

In rare circumstances, you might want to disable proxy ARP for global addresses.

When a host sends IP traffic to another device on the same Ethernet network, the host needs to know the MAC address of the device. ARP is a Layer 2 protocol that resolves an IP address to a MAC address. A host sends an ARP request asking “Who is this IP address?” The device owning the IP address replies, “I own that IP address; here is my MAC address.”

Proxy ARP is when a device responds to an ARP request with its own MAC address, even though the device does not own the IP address. The security appliance uses proxy ARP when you configure NAT and specify a global address that is on the same network as the security appliance interface. The only way traffic can reach the hosts is if the security appliance uses proxy ARP to claim that the security appliance MAC address is assigned to destination global addresses.

Examples

The following example disables proxy ARP on the inside interface:

```
hostname(config)# sysopt noproxyarp inside
```

Related Commands

Command	Description
alias	Translates an outside address and alters the DNS records to accommodate the translation.
clear configure sysopt	Clears the sysopt command configuration.
show running-config sysopt	Shows the sysopt command configuration.
sysopt nodnsalias	Disables alteration of the DNS A record address when you use the alias command.

sysopt radius ignore-secret

To ignore the authentication key in RADIUS accounting responses, use the **sysopt radius ignore-secret** command in global configuration mode. To disable this feature, use the **no** form of this command. You might need to ignore the key for compatibility with some RADIUS servers.

sysopt radius ignore-secret

no sysopt radius ignore-secret

Syntax Description

This command has no arguments or keywords.

Defaults

This feature is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Some RADIUS servers fail to include the key in the authenticator hash within the accounting acknowledgment response. This usage caveat can cause the security appliance to continually retransmit the accounting request. Use the **sysopt radius ignore-secret** command to ignore the key in these acknowledgments, thus avoiding the retransmit problem. (The key identified here is the same one you set with the **aaa-server host** command.)

Examples

The following example ignores the authentication key in accounting responses:

```
hostname(config)# sysopt radius ignore-secret
```

Related Commands

Command	Description
aaa-server host	Identifies a AAA server.
clear configure sysopt	Clears the sysopt command configuration.
show running-config sysopt	Shows the sysopt command configuration.

sysopt uauth allow-http-cache

To let the web browser supply a username and password from its cache when it reauthenticates with the virtual HTTP server on the security appliance (see the **virtual http** command), use the **sysopt uauth allow-http-cache** command in global configuration mode. If you do not allow the HTTP cache, then after your authentication session times out, the next time you connect to the virtual HTTP server, you are prompted again for your username and password. To disable this feature, use the **no** form of this command.

sysopt uauth allow-http-cache

no sysopt uauth allow-http-cache

Syntax Description This command has no arguments or keywords.

Defaults This feature is disabled by default.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples The following example allows the HTTP cache to be used:

```
hostname(config)# sysopt uauth allow-http-cache
```

Related Commands	Command	Description
	virtual http	When you use HTTP authentication on the security appliance, and the HTTP server also requires authentication, this command allows you to authenticate separately with the security appliance and with the HTTP server. Without virtual HTTP, the same username and password you used to authenticate with the security appliance is sent to the HTTP server; you are not prompted separately for the HTTP server username and password.
	clear configure sysopt	Clears the sysopt command configuration.
	show running-config sysopt	Shows the sysopt command configuration.

■ `sysopt uauth allow-http-cache`



T through Z Commands

tcp-map

To define a set of TCP normalization actions, use the **tcp-map** command in global configuration mode. The TCP normalization feature lets you specify criteria that identify abnormal packets, which the security appliance drops when they are detected. To remove the TCP map, use the **no** form of this command.

tcp-map *map_name*

no tcp-map *map_name*

Syntax Description

map_name Specifies the TCP map name.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0(1)	This command was introduced.

Usage Guidelines

This feature uses Modular Policy Framework. First define the TCP normalization actions you want to take using the **tcp-map** command. The **tcp-map** command enters tcp-map configuration mode, where you can enter one or more commands to define the TCP normalization actions. Then define the traffic to which you want to apply the TCP map using the **class-map** command. Enter the **policy-map** command to define the policy, and enter the **class** command to reference the class map. In class configuration mode, enter the **set connection advanced-options** command to reference the TCP map. Finally, apply the policy map to an interface using the **service-policy** command. For more information about how Modular Policy Framework works, see the *Cisco Security Appliance Command Line Configuration Guide*.

The following commands are available in tcp-map configuration mode:

check-retransmission	Enables and disables the retransmit data checks.
checksum-verification	Enables and disable checksum verification.
exceed-mss	Allows or drops packets that exceed MSS set by peer.

queue-limit	Configures the maximum number of out-of-order packets that can be queued for a TCP connection. This command is only available on the ASA 5500 series adaptive security appliance. On the PIX 500 series security appliance, the queue limit is 3 and cannot be changed.
reserved-bits	Sets the reserved flags policy in the security appliance.
syn-data	Allows or drops SYN packets with data.
tcp-options	Allows or clears the selective-ack, timestamps, or window-scale TCP options.
ttl-evasion-protection	Enables or disables the TTL evasion protection offered by the security appliance.
urgent-flag	Allows or clears the URG pointer through the security appliance.
window-variation	Drops a connection that has changed its window size unexpectedly.

Examples

For example, to allow urgent flag and urgent offset packets for all traffic sent to the range of TCP ports between the well known FTP data port and the Telnet port, enter the following commands:

```
hostname(config)# tcp-map tmap
hostname(config-tcp-map)# urgent-flag allow

hostname(config-tcp-map)# class-map urg-class
hostname(config-cmap)# match port tcp range ftp-data telnet

hostname(config-cmap)# policy-map pmap
hostname(config-pmap)# class urg-class
hostname(config-pmap-c)# set connection advanced-options tmap

hostname(config-pmap-c)# service-policy pmap global
```

Related Commands

Command	Description
class (policy-map)	Specifies a class map to use for traffic classification.
clear configure tcp-map	Clears the TCP map configuration.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
show running-config tcp-map	Displays the information about the TCP map configuration.
tcp-options	Allows or clears the selective-ack, timestamps, or window-scale TCP options.

tcp-options

To allow or clear the TCP options through the security appliance, use the **tcp-options** command in tcp-map configuration mode. To remove this specification, use the **no** form of this command.

tcp-options {selective-ack | timestamp | window-scale} {allow | clear}

no tcp-options {selective-ack | timestamp | window-scale} {allow | clear}

tcp-options range *lower upper* {allow | clear | drop}

no tcp-options range *lower upper* {allow | clear | drop}

Syntax Description

allow	Allows the TCP options through the TCP normalizer.
clear	Clears the TCP options through the TCP normalizer and allows the packet.
drop	Drops the packet.
<i>lower</i>	Lower bound ranges (6-7) and (9-255).
selective-ack	Sets the selective acknowledgement mechanism (SACK) option. The default is to allow the SACK option.
timestamp	Sets the timestamp option. Clearing the timestamp option will disable PAWS and RTT. The default is to allow the timestamp option.
<i>upper</i>	Upper bound range (6-7) and (9-255).
window-scale	Sets the window scale mechanism option. The default is to allow the window scale mechanism option.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tcp-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **tcp-map** command is used along with the Modular Policy Framework infrastructure. Define the class of traffic using the **class-map** command and customize the TCP inspection with **tcp-map** commands. Apply the new TCP map using the **policy-map** command. Activate TCP inspection with **service-policy** commands.

Use the **tcp-map** command to enter tcp-map configuration mode. Use the **tcp-options** command in tcp-map configuration mode to clear selective-acknowledgement, window-scale, and timestamp TCP options. You can also clear or drop packets with options that are not very well defined.

Examples

The following example shows how to drop all packets with TCP options in the ranges of 6-7 and 9-255:

```
hostname(config)# access-list TCP extended permit tcp any any
hostname(config)# tcp-map tmap
hostname(config-tcp-map)# tcp-options range 6 7 drop
hostname(config-tcp-map)# tcp-options range 9 255 drop
hostname(config)# class-map cmap
hostname(config-cmap)# match access-list TCP
hostname(config)# policy-map pmap
hostname(config-pmap)# class cmap
hostname(config-pmap)# set connection advanced-options tmap
hostname(config)# service-policy pmap global
```

Related Commands

Command	Description
class	Specifies a class map to use for traffic classification.
help	Shows syntax help for the policy-map , class , and description commands.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
set connection	Configures connection values.
tcp-map	Creates a TCP map and allows access to tcp-map configuration mode.

telnet

To add Telnet access to the console and set the idle timeout, use the **telnet** command in global configuration mode. To remove Telnet access from a previously set IP address, use the **no** form of this command.

```
telnet {{hostname | IP_address mask interface_name} | {IPv6_address interface_name} |
{timeout number}}
```

```
no telnet {{hostname | IP_address mask interface_name} | {IPv6_address interface_name} |
{timeout number}}
```

Syntax Description

<i>hostname</i>	Specifies the name of a host that can access the Telnet console of the security appliance.
<i>interface_name</i>	Specifies the name of the network interface to Telnet to.
<i>IP_address</i>	Specifies the IP address of a host or network authorized to log in to the security appliance.
<i>IPv6_address</i>	Specifies the IPv6 address/prefix authorized to log in to the security appliance.
<i>mask</i>	Specifies the netmask associated with the IP address.
timeout number	Number of minutes that a Telnet session can be idle before being closed by the security appliance; valid values are from 1 to 1440 minutes.

Defaults

By default, Telnet sessions left idle for five minutes are closed by the security appliance.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	The variable <i>IPv6_address</i> was added. The no telnet timeout command was added too.

Usage Guidelines

The **telnet** command lets you specify which hosts can access the security appliance console with Telnet. You can enable Telnet to the security appliance on all interfaces. However, the security appliance enforces that all Telnet traffic to the outside interface be protected by IPSec. To enable a Telnet session to the outside interface, configure IPSec on the outside interface to include IP traffic that is generated by the security appliance and enable Telnet on the outside interface.

Use the **no telnet** command to remove Telnet access from a previously set IP address. Use the **telnet timeout** command to set the maximum time that a console Telnet session can be idle before being logged off by the security appliance. You cannot use the **no telnet** command with the **telnet timeout** command.

If you enter an IP address, you must also enter a netmask. There is no default netmask. Do not use the subnetwork mask of the internal network. The *netmask* is only a bit mask for the IP address. To limit access to a single IP address, use 255 in each octet; for example, 255.255.255.255.

If IPSec is operating, you can specify an unsecure interface name, which is typically, the outside interface. At a minimum, you might configure the **crypto map** command to specify an interface name with the **telnet** command.

Use the **passwd** command to set a password for Telnet access to the console. The default is **cisco**. Use the **who** command to view which IP addresses are currently accessing the security appliance console. Use the **kill** command to terminate an active Telnet console session.

If you use the **aaa** command with the **console** keyword, Telnet console access must be authenticated with an authentication server.



Note

If you have configured the **aaa** command to require authentication for security appliance Telnet console access and the console login request times out, you can gain access to the security appliance from the serial console by entering the security appliance username and the password that was set with the **enable password** command.

Examples

This example shows how to permit hosts 192.168.1.3 and 192.168.1.4 to access the security appliance console through Telnet. In addition, all the hosts on the 192.168.2.0 network are given access.

```
hostname(config)# telnet 192.168.1.3 255.255.255.255 inside
hostname(config)# telnet 192.168.1.4 255.255.255.255 inside
hostname(config)# telnet 192.168.2.0 255.255.255.0 inside
hostname(config)# show running-config telnet
192.168.1.3 255.255.255.255 inside
192.168.1.4 255.255.255.255 inside
192.168.2.0 255.255.255.0 inside
```

This example shows how to change the maximum session idle duration:

```
hostname(config)# telnet timeout 10
hostname(config)# show running-config telnet timeout
telnet timeout 10 minutes
```

This example shows a Telnet console login session (the password does not display when entered):

```
hostname# passwd: cisco

Welcome to the XXX
...
Type help or '?' for a list of available commands.
hostname>
```

You can remove individual entries with the **no telnet** command or all telnet command statements with the **clear configure telnet** command:

```
hostname(config)# no telnet 192.168.1.3 255.255.255.255 inside
hostname(config)# show running-config telnet
192.168.1.4 255.255.255.255 inside
192.168.2.0 255.255.255.0 inside
```

```
hostname(config)# clear configure telnet
```

Related Commands

Command	Description
clear configure telnet	Removes a Telnet connection from the configuration.
kill	Terminates a Telnet session.
show running-config telnet	Displays the current list of IP addresses that are authorized to use Telnet connections to the security appliance.
who	Displays active Telnet administration sessions on the security appliance.

terminal

To set the terminal line parameters, use the **terminal** command in privileged EXEC mode.

terminal {**monitor** | **no monitor** | **pager lines** [*lines*]}

Syntax Description

monitor	Enables the display of syslog messages on this terminal.
no monitor	Disables the display of syslog messages on this terminal.
pager lines <i>lines</i>	Sets the number of lines on a page before the “---more---” prompt appears. The default is 24 lines; 0 means no page limit. The range is 0 through 2147483647 lines.

Defaults

The default for **terminal monitor pager** is 24 lines, if the *lines* argument is unspecified.

Command Modes

The following table shows the modes in which you can enter the command:

	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
7.0	The pager lines commands were added.

Examples

This example shows how to enable logging and then disable logging only in the current session:

```
hostname# terminal monitor
hostname# terminal no monitor
```

Related Commands

Command	Description
clear configure terminal	Clears the terminal display width setting.
show running-config terminal	Displays the current terminal settings.
terminal width	Sets the terminal display width in global configuration mode.

terminal width

To set the width for displaying information during console sessions, use the **terminal width** command in global configuration mode. To disable, use the **no** form of this command.

terminal width *columns*

no terminal width *columns*

Syntax Description

columns Specifies the terminal width in columns. The default is 80. The range is 40 to 511.

Defaults

The default display width is 80 columns.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Examples

This example shows how to terminal display width to 100 columns:

```
hostname# terminal width 100
```

Related Commands

Command	Description
clear configure terminal	Clears the terminal display width setting.
show running-config terminal	Displays the current terminal settings.
terminal	Sets the terminal line parameters in privileged EXEC mode.

test aaa-server

Use the **test aaa-server** command to check whether the security appliance can authenticate or authorize users with a particular AAA server. Failure to reach the AAA server may be due to incorrect configuration on the security appliance, or the AAA server may be unreachable for other reasons, such as restrictive network configurations or server downtime.

```
test aaa-server {authentication | authorization} server-tag [host server-ip] [username username]
[password password]
```

Syntax Description

authentication	Specifies that the security appliance should send a test authentication request.
authorization	Specifies that the security appliance should send a test authorization request.
host <i>server-ip</i>	Specifies The IP address of the AAA server.
password <i>password</i>	Specifies the password for the username given. The password argument is available only for authentication tests. Make sure the password is correct for the username entered; otherwise, the authentication test will fail.
<i>server-tag</i>	Specifies the symbolic name of the server group, as defined by the aaa-server protocol command.
username <i>username</i>	Specifies the username of the account used to test the AAA server settings. Make sure the username exists on the AAA server; otherwise, the test will fail.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0(4)	This command was introduced.

Usage Guidelines

The **test aaa-server** command enables you to verify that the security appliance can authenticate and authorize users with a particular AAA server. Using this command simplifies verification of the configuration on the security appliance by removing the necessity of testing with a real supplicant. It also helps you isolate whether authentication and authorization failures are due to misconfiguration of AAA server parameters, a connection problem to the AAA server, or other configuration errors on the security appliance.

When you enter the command, you can omit the **host** and **password** keyword and argument pairs. The security appliance will prompt you for their values. If you are performing an authentication test, you can also omit the **password** keyword and argument pair and provide the password when the security appliance prompts you.

Examples

The following example configures a RADIUS AAA server named “svrgrp1” on host “192.168.3.4”, sets a timeout of 9 seconds, sets a retry-interval of 7 seconds, and configures authentication port 1650. The **test aaa-server** command following the setup of the AAA server parameters indicates that the authentication test failed to reach the server.

```
hostname(config)# aaa-server svrgrp1 protocol radius
hostname(config-aaa-server-group)# aaa-server svrgrp1 host 192.168.3.4
hostname(config-aaa-server-host)# timeout 9
hostname(config-aaa-server-host)# retry-interval 7
hostname(config-aaa-server-host)# authentication-port 1650
hostname(config-aaa-server-host)# exit
hostname(config)# test aaa-server authentication svrgrp1
Server IP Address or name: 192.168.3.4
Username: bogus
Password: *****
INFO: Attempting Authentication test to IP address <192.168.3.4> (timeout: 10 seconds)
ERROR: Authentication Server not responding: No error
```

Related Commands

Command	Description
aaa-server host	Specifies parameters for a specific AAA server.
show running-config aaa-server	Displays AAA server statistics for all AAA servers, for a particular server group, for a particular server within a particular group, or for a particular protocol.

text-color

To set a color for text in the WebVPN title bar on the login, home page, and file access page, use the **text-color** command in webvpn mode. To remove a text color from the configuration and reset the default, use the no form of this command.

text-color [*black | white | auto*]

no text-color

Syntax Description

auto	Chooses black or white based on the settings for the secondary-color command. That is, if the secondary color is black, this value is white.
black	The default text color for title bars is white.
white	You can change the color to black.

Defaults

The default text color for the title bars is white.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to set the text color for title bars to black:

```
hostname(config)# webvpn
hostname(config-webvpn)# text-color black
```

Related Commands

Command	Description
secondary-text-color	Sets the secondary text color for the WebVPN login, home page, and file access page.

tftp-server

To specify the default TFTP server and path and filename for use with **configure net** or **write net** commands, use the **tftp-server** command in global configuration mode. To remove the server configuration, use the **no** form of this command. This command supports IPv4 and IPv6 addresses.

tftp-server *interface_name* *server* *filename*

no tftp-server [*interface_name* *server* *filename*]

Syntax Description

<i>interface_name</i>	Specifies the gateway interface name. If you specify an interface other than the highest security interface, a warning message informs you that the interface is unsecure.
<i>server</i>	Sets the TFTP server IP address or name. You can enter an IPv4 or IPv6 address.
<i>filename</i>	Specifies the path and filename.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
7.0	The gateway interface is now required.

Usage Guidelines

The **tftp-server** command simplifies entering the **configure net** and **write net** commands. When you enter the **configure net** or **write net** commands, you can either inherit the TFTP server specified by the **tftp-server** command, or provide your own value. You can also inherit the path in the **tftp-server** command as is, add a path and filename to the end of the **tftp-server** command value, or override the **tftp-server** command value.

The security appliance supports only one **tftp-server** command.

Examples

This example shows how to specify a TFTP server and then read the configuration from the /temp/config/test_config directory:

```
hostname(config)# tftp-server inside 10.1.1.42 /temp/config/test_config
hostname(config)# configure net
```

Related Commands	Command	Description
	configure net	Loads the configuration from the TFTP server and path you specify.
	show running-config	Displays the default TFTP server address and the directory of the configuration file.
	tftp-server	

timeout

To set the maximum idle time duration, use the **timeout** command in global configuration mode.

timeout [**xlate** | **conn** | **udp** | **icmp** | **rpc** | **h225** | **h323** | **mgcp** | **mgcp-pat** | **sip** | **sip_media** | **uauth** *hh:mm:ss*]

Syntax Description

conn	(Optional) Specifies the idle time after which a connection closes; the minimum duration is five minutes.
<i>hh:mm:ss</i>	Specifies the timeout.
h225 <i>hh:mm:ss</i>	(Optional) Specifies the idle time after which an H.225 signaling connection closes.
h323	(Optional) Specifies the idle time after which H.245 (TCP) and H.323 (UDP) media connections close. The default is five minutes.
 Note Because the same connection flag is set on both H.245 and H.323 media connections, the H.245 (TCP) connection shares the idle timeout with the H.323 (RTP and RTCP) media connection.	
half-closed	(Optional) Specifies the idle time after which a TCP half-closed connection will be freed.
icmp	(Optional) Specifies the idle time for ICMP.
mgcp <i>hh:mm:ss</i>	(Optional) Sets the idle time after which an MGCP media connection is removed.
mgcp-pat <i>hh:mm:ss</i>	(Optional) Sets the absolute interval after which an MGCP PAT translation is removed.
rpc	(Optional) Specifies the idle time until an RPC slot is freed; the minimum duration is one minute.
sip	(Optional) Modifies the SIP timer.
sip_media	(Optional) Modifies the SIP media timer, which is used for SIP RTP/RTCP with SIP UDP media packets, instead of the UDP inactivity timeout.
sunrpc	(Optional) Specifies the idle time after which a SUNRPC slot will be closed.
uauth	(Optional) Sets the duration before the authentication and authorization cache times out and the user has to reauthenticate the next connection.
udp	(Optional) Specifies the idle time until a UDP slot is freed; the minimum duration is one minute.
xlate	(Optional) Specifies the idle time until a translation slot is freed; the minimum value is one minute.

Defaults

The defaults are as follows:

- **conn** *hh:mm:ss* is 1 hour (**01:00:00**).
- **h225** *hh:mm:ss* is 1 hour (**01:00:00**).
- **h323** *hh:mm:ss* is 5 minutes (**00:05:00**).
- **half-closed** *hh:mm:ss* is 10 minutes (**00:10:00**).

- **icmp** *hh:mm:ss* is 2 minutes (**00:00:02**).
- **mgcp** *hh:mm:ss* is 5 minutes (**00:05:00**).
- **mgcp-pat** *hh:mm:ss* is 5 minutes (**00:05:00**).
- **rpc** *hh:mm:ss* is 10 minutes (**00:10:00**).
- **sip** *hh:mm:* is 30 minutes (**00:30:00**).
- **sip_media** *hh:mm:ss* is 2 minutes (**00:02:00**).
- **sunrpc** *hh:mm:ss* is 10 minutes (**00:10:00**).
- **uauth** timer is **absolute**.
- **udp** *hh:mm:ss* is 2 minutes (**00:02:00**).
- **xlate** *hh:mm:ss* is 3 hours (**03:00:00**).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration mode	•	•	•	•	—

Command History

Release	Modification
7.0	They keyword mgcp-pat was added.

Usage Guidelines

The **timeout** command lets you set the idle time for connection, translation UDP, and RPC slots. If the slot has not been used for the idle time specified, the resource is returned to the free pool. TCP connection slots are freed approximately 60 seconds after a normal connection close sequence.



Note

Do not use the **timeout uauth 0:0:0** command if passive FTP is used for the connection or if the **virtual** command is used for web authentication.

The connection timer takes precedence over the translation timer; the translation timer works only after all connections have timed out.

When setting the **conn** *hh:mm:ss*, use **0:0:0** to never time out a connection.

When setting the **half-closed** *hh:mm:ss*, use **0:0:0** to never time out a half-closed connection.

When setting the **h255** *hh:mm:ss*, **h225 00:00:00** means to never tear down an H.225 signaling connection. A timeout value of **h225 00:00:01** disables the timer and closes the TCP connection immediately after all calls are cleared.

The **uauth** *hh:mm:ss* duration must be shorter than the **xlate** keyword. Set to **0** to disable caching. Do not set to zero if passive FTP is used on the connections.

To disable the **absolute** keyword, set the uauth timer to 0 (zero).

Examples

The following example shows how to configure the maximum idle time durations:

```
hostname(config)# timeout uauth 0:5:00 absolute uauth 0:4:00 inactivity
hostname(config)# show running-config timeout
timeout xlate 3:00:00
timeout conn 1:00:00 half-closed 0:10:00 udp 0:02:00 rpc 0:10:00 h323 0:05:00
sip 0:30:00 sip_media 0:02:00
timeout uauth 0:05:00 absolute uauth 0:04:00 inactivity
```

Related Commands

Command	Description
show running-config timeout	Displays the timeout value of the designated protocol.

timeout (aaa-server host)

To configure the host-specific maximum response time, in seconds, allowed before giving up on establishing a connection with the AAA server, use the **timeout** command in aaa-server host mode. To remove the timeout value and reset the timeout to the default value of 10 seconds, use the **no** form of this command.

timeout *seconds*

no timeout

Syntax Description

<i>seconds</i>	Specifies the timeout interval (1-60 seconds) for the request. This is the time after which the security appliance gives up on the request to the primary AAA server. If there is a standby AAA server, the security appliance sends the request to the backup server.

Defaults

The default timeout value is 10 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
aaa-server host configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command is valid for all AAA server protocol types.

Use the **timeout** command to specify the length of time during which the security appliance attempts to make a connection to a AAA server. Use the **retry-interval** command to specify the amount of time the security appliance waits between connection attempts.

The timeout is the total amount of time that the security appliance spends trying to complete a transaction with a server. The retry interval determines how often the communication is retried during the timeout period. Thus, if the retry interval is greater than or equal to the timeout value, you will see no retries. If you want to see retries, the retry interval must be less than the timeout value.

Examples

The following example configures a RADIUS AAA server named “svrgrp1” on host 1.2.3.4 to use a timeout value of 30 seconds, with a retry interval of 10 seconds. Thus, the security appliance tries the communication attempt three times before giving up after 30 seconds.

```
hostname(config)# aaa-server svrgrp1 protocol radius
```

```
hostname(config-aaa-server-group)# aaa-server svrgrp1 host 1.2.3.4
hostname(config-aaa-server-host)# timeout 30
hostname(config-aaa-server-host)# retry-interval 10
hostname(config-aaa-server-host)# exit
hostname(config)#
```

Related Commands

Command	Description
aaa-server host	Enters aaa server host configuration mode so you can configure AAA server parameters that are host specific.
clear configure aaa-server	Removes all AAA command statements from the configuration.
show running-config aaa	Displays the current AAA configuration values.

timeout (gtp-map)

To change the inactivity timers for a GTP session, use the **timeout** command in GTP map configuration mode, which is accessed by using the **gtp-map** command. Use the **no** form of this command to set these intervals to their default values.

timeout { **gsn** | **pdp-context** | **request** | **signaling** | **tunnel** } *hh:mm:ss*

no timeout { **gsn** | **pdp-context** | **request** | **signaling** | **tunnel** } *hh:mm:ss*

Syntax Description

<i>hh:mm:ss</i>	This is the timeout where <i>hh</i> specifies the hour, <i>mm</i> specifies the minutes, and <i>ss</i> specifies the seconds. The value 0 means never tear down immediately.
gsn	Specifies the period of inactivity after which a GSN will be removed.
pdp-context	Specifies the maximum period of time allowed before beginning to receive the PDP context.
request	Specifies the the maximum period of time allowed before beginning to receive the GTP message.
signaling	Specifies the period of inactivity after which the GTP signaling will be removed.
tunnel	Specifies the the period of inactivity after which the GTP tunnel will be torn down.

Defaults

The default is 30 minutes for **gsn**, **pdp-context**, and **signaling**.

The default for **request** is 1 minute.

The default for **tunnel** is 1 minute (in the case where a Delete PDP Context Request is not received).

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
GTP map configuration	•	•	•	•	No

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The Packet Data Protocol (PDP) context is identified by the Tunnel Identifier (TID), which is a combination of IMSI and NSAPI. Each MS can have up to 15 NSAPIs, allowing it to create multiple PDP contexts each with a different NSAPI, based on application requirements for varied QoS levels.

A GTP tunnel is defined by two associated PDP Contexts in different GSN nodes and is identified with a Tunnel ID. A GTP tunnel is necessary to forward packets between an external packet data network and a mobile station user.

Examples

The following example sets a timeout value for the request queue of 2 minutes:

```
hostname(config)# gtp-map gtp-policy  
hostname(config-gtpmap)# timeout request 00:02:00
```

Related Commands

Commands	Description
clear service-policy inspect gtp	Clears global GTP statistics.
debug gtp	Displays detailed information about GTP inspection.
gtp-map	Defines a GTP map and enables GTP map configuration mode.
inspect gtp	Applies a specific GTP map to use for application inspection.
show service-policy inspect gtp	Displays the GTP configuration.

time-range

To enter time-range configuration mode and define a time range that you can attach to traffic rules, or an action, use the **time-range** command in global configuration mode. To disable, use the **no** form of this command.

time-range *name*

no time-range *name*

Syntax Description

name Name of the time range. The name must be 64 characters or less.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Creating a time range does not restrict access to the device. The **time-range** command defines the time range only. After a time range is defined, you can attach it to traffic rules or an action.

To implement a time-based ACL, use the **time-range** command to define specific times of the day and week. Then use the with the **access-list extended time-range** command to bind the time range to an ACL.

The time range relies on the system clock of the security appliance; however, the feature works best with NTP synchronization.

Examples

The following example creates a time range named “New_York_Minute” and enters time range configuration mode:

```
hostname(config)# time-range New_York_Minute
hostname(config-time-range)#
```

After you have created a time range and entered time-range configuration mode, you can define time range parameters with the **absolute** and **periodic** commands. To restore default settings for the **time-range** command **absolute** and **periodic** keywords, use the **default** command in time-range configuration mode.

To implement a time-based ACL, use the **time-range** command to define specific times of the day and week. Then use the with the **access-list extended** command to bind the time range to an ACL. The following example binds an ACL named “Sales” to a time range named “New_York_Minute”:

```
hostname(config)# access-list Sales line 1 extended deny tcp host 209.165.200.225 host 209.165.201.1 time-range New_York_Minute
hostname(config)#
```

See the **access-list extended** command for more information about ACLs.

Related Commands

Command	Description
absolute	Defines an absolute time when a time range is in effect.
access-list extended	Configures a policy for permitting or denying IP traffic through the security appliance.
default	Restores default settings for the time-range command absolute and periodic keywords.
periodic	Specifies a recurring (weekly) time range for functions that support the time-range feature.

timers lsa-group-pacing

To specify the interval at which OSPF link-state advertisements (LSAs) are collected into a group and refreshed, checksummed, or aged, use the **timers lsa-group-pacing** command in router configuration mode. To restore the default value, use the **no** form of this command.

timers lsa-group-pacing *seconds*

no timers lsa-group-pacing [*seconds*]

Syntax Description

<i>seconds</i>	The interval at which OSPF link-state advertisements (LSAs) are collected into a group and refreshed, checksummed, or aged. Valid values are from 10 to 1800 seconds.

Defaults

The default interval is 240 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To change the interval at which the OSPF link-state advertisements (LSAs) are collected into a group and refreshed, checksummed, or aged, use the **timers lsa-group-pacing** *seconds* command. To return to the default timer values, use the **no timers lsa-group-pacing** command.

Examples

The following example sets the group processing interval of LSAs to 500 seconds:

```
hostname(config-router)# timers lsa-group-pacing 500
hostname(config-router)#
```

Related Commands

Command	Description
router ospf	Enters router configuration mode.
show ospf	Displays general information about the OSPF routing processes.
timers spf	Specifies the shortest path first (SPF) calculation delay and hold time

timers spf

To specify the shortest path first (SPF) calculation delay and hold time, use the **timers spf** command in router configuration mode. To restore the default values, use the **no** form of this command.

timers spf *delay holdtime*

no timers spf [*delay holdtime*]

Syntax Description

<i>delay</i>	Specifies the delay time between when OSPF receives a topology change and when it starts a shortest path first (SPF) calculation in seconds, from 1 to 65535.
<i>holdtime</i>	The hold time between two consecutive SPF calculations in seconds; valid values are from 1 to 65535.

Defaults

The defaults are as follows:

- *delay* is 5 seconds.
- *holdtime* is 10 seconds.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Router configuration	•	—	•	—	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

To configure the delay time between when the OSPF protocol receives a topology change and when it starts a calculation, and the hold time between two consecutive SPF calculations, use the **timers spf** command. To return to the default timer values, use the **no timers spf** command.

Examples

The following example sets the SPF calculation delay to 10 seconds and the SPF calculation hold time to 20 seconds:

```
hostname(config-router)# timers spf 10 20
hostname(config-router)#
```

Related Commands	Command	Description
	router ospf	Enters router configuration mode.
	show ospf	Displays general information about the OSPF routing processes.
	timers	Specifies the interval at which OSPF link-state advertisements (LSAs) are collected and refreshed, checksummed, or aged.
	lsa-group-pacing	

title

To set a title for WebVPN users to see on the browser and on the WebVPN title bar, use the **title** command in webvpn mode. To remove a title from the configuration and reset the default, use the **no** form of this command.

title [*string*]

no title

Syntax Description

string (Optional) Specifies the HTML string in the browser title and on the WebVPN title bar. Maximum 255 characters.

Defaults

The default title is “WebVPN Service”.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

To have no title, use the **title** command without a string.

Examples

The following example shows how to create the WebVPN title, “Our Company WebVPN Services”:

```
hostname(config)# webvpn
```

```
hostname(config-webvpn)# title Our Company WebVPN Services
```

title-color

To set a color for the WebVPN title bar on the login, home page and file access page, use the **title-color** command in webvpn mode. To remove a title color from the configuration and reset the default, use the **no** form of this command.

title-color {color}

no title-color

Syntax Description

color	(Optional) Specifies the color. You can use a comma separated RGB value, an HTML color value, or the name of the color if recognized in HTML. • RGB format is 0,0,0, a range of decimal numbers from 0 to 255 for each color (red, green, blue); the comma separated entry indicates the level of intensity of each color to combine with the others. • HTML format is #000000, six digits in hexadecimal format; the first and second represent red, the third and fourth green, and the fifth and sixth represent blue. • Name length maximum is 32 characters.

Defaults

The default title is HTML #999CC, a lavender shade.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The number of HTML and RGB values recommended for use is 216, many fewer than the mathematical possibilities. Many displays can handle only 256 colors, and 40 of those look differently on MACs and PCs. For best results, check published HTML and RGB tables. To find tables online, enter RGB in a search engine.

Examples

The following example shows how to set an RGB color value of 153, 204, 255, which is sky blue:

```
hostname(config)# webvpn
```

```
hostname(config-webvpn)# title-color 153,204,255
```

Related Commands

Command	Description
secondary-color	Sets a secondary color for the WebVPN title bar on the login, home page and file access page.

transfer-encoding

To restrict HTTP traffic by specifying a transfer encoding type, use the **transfer-encoding** command in HTTP map configuration mode, which is accessible using the **http-map** command. To disable this feature, use the **no** form of this command.

transfer-encoding type {**chunked** | **compress** | **deflate** | **gzip** | **identity** | **default**} **action** {**allow** | **reset** | **drop**} [**log**]

no transfer-encoding type {**chunked** | **compress** | **deflate** | **gzip** | **identity** | **default**} **action** {**allow** | **reset** | **drop**} [**log**]

Syntax Description

action	Specifies the action taken when a connection using the specified transfer encoding type is detected.
allow	Allows the message.
chunked	Identifies the transfer encoding type in which the message body is transferred as a series of chunks.
compress	Identifies the transfer encoding type in which the message body is transferred using UNIX file compression.
default	Specifies the default action taken by the security appliance when the traffic contains a supported request method that is not on a configured list.
deflate	Identifies the transfer encoding type in which the message body is transferred using zlib format (RFC 1950) and deflate compression (RFC 1951).
drop	Closes the connection.
gzip	Identifies the transfer encoding type in which the message body is transferred using GNU zip (RFC 1952).
identity	Identifies connections in which the message body is no transfer encoding is performed.
log	(Optional) Generates a syslog.
reset	Sends a TCP reset message to client and server.
type	Specifies the type of transfer encoding to be controlled through HTTP application inspection.

Defaults

This command is disabled by default. When the command is enabled and a supported transfer encoding type is not specified, the default action is to allow the connection without logging. To change the default action, use the **default** keyword and specify a different default action.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
HTTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

When you enable the **transfer-encoding** command, the security appliance applies the specified action to HTTP connections for each supported and configured transfer encoding type.

The security appliance applies the **default** action to all traffic that does *not* match the transfer encoding types on the configured list. The preconfigured **default** action is to **allow** connections without logging.

For example, given the preconfigured default action, if you specify one or more encoding types with the action of **drop** and **log**, the security appliance drops connections containing the configured encoding types, logs each connection, and allows all connections for the other supported encoding types.

If you want to configure a more restrictive policy, change the default action to **drop** (or **reset**) and **log** (if you want to log the event). Then configure each permitted encoding type with the **allow** action.

Enter the **transfer-encoding** command once for each setting you wish to apply. You use one instance of the **transfer-encoding** command to change the default action and one instance to add each encoding type to the list of configured transfer encoding types.

When you use the **no** form of this command to remove an application category from the list of configured application types, any characters in the command line after the application category keyword are ignored.

Examples

The following example provides a permissive policy, using the preconfigured default, which allows all supported application types that are not specifically prohibited.

```
hostname(config)# http-map inbound_http
hostname(config-http-map)# transfer-encoding gzip drop log
hostname(config-http-map)# exit
```

In this case, only connections using GNU zip are dropped and the event is logged.

The following example provides a restrictive policy, with the default action changed to reset the connection and to log the event for any encoding type that is not specifically allowed.

```
hostname(config)# http-map inbound_http
hostname(config-http-map)# port-misuse default action reset log
hostname(config-http-map)# port-misuse identity allow
hostname(config-http-map)# exit
```

In this case, only connections using no transfer encoding are allowed. When HTTP traffic for the other supported encoding types is received, the security appliance resets the connection and creates a syslog entry.

Related Commands	Commands	Description
	class-map	Defines the traffic class to which to apply security actions.
	debug appfw	Displays detailed information about traffic associated with enhanced HTTP inspection.
	http-map	Defines an HTTP map for configuring enhanced HTTP inspection.
	inspect http	Applies a specific HTTP map to use for application inspection.
	policy-map	Associates a class map with specific security actions.

trust-point

To specify the name of a trustpoint that identifies the certificate to be sent to the IKE peer, use the **trust-point** command in tunnel-group ipsec-attributes mode. To eliminate a trustpoint specification, use the **no** form of this command.

trust-point *trust-point-name*

no trust-point *trust-point-name*

Syntax Description

<i>trust-point-name</i>	Specifies the name of the trustpoint to use.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tunnel-group ipsec attributes	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can apply this attribute to all tunnel-group types.

Examples

The following example entered in config-ipsec configuration mode, configures a trustpoint for identifying the certificate to be sent to the IKE peer for the IPSec LAN-to-LAN tunnel group named 209.165.200.225:

```
hostname(config)# tunnel-group 209.165.200.225 type IPSec_L2L
hostname(config)# tunnel-group 209.165.200.225 ipsec-attributes
hostname(config-ipsec)# trust-point mytrustpoint
hostname(config-ipsec)#
```

Related Commands

Command	Description
clear configure tunnel-group	Clears all configured tunnel groups.
crypto ca trustpoint	Enters the trustpoint mode for the specified trustpoint.

Command	Description
show running-config tunnel-group	Shows the configuration for the indicated tunnel group or for all tunnel groups.
tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

ttl-evasion-protection

To disable the Time-To-Live evasion protection, use the **ttl-evasion-protection** command in tcp-map configuration mode. To remove this specification, use the **no** form of this command.

ttl-evasion-protection

no ttl-evasion-protection

Syntax Description

This command has no arguments or keywords.

Defaults

TTL evasion protection offered by the security appliance is enabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tcp-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **tcp-map** command is used along with the Modular Policy Framework infrastructure. Define the class of traffic using the **class-map** command and customize the TCP inspection with **tcp-map** commands. Apply the new TCP map using the **policy-map** command. Activate TCP inspection with **service-policy** commands.

Use the **tcp-map** command to enter tcp-map configuration mode. Use the **ttl-evasion-protection** command in tcp-map configuration mode to prevent attacks that attempt to evade security policy.

For instance, an attacker can send a packet that passes policy with a very short TTL. When the TTL goes to zero, a router between the security appliance and the endpoint drops the packet. It is at this point that the attacker can send a malicious packet with a long TTL that appears to the security appliance to be a retransmission and is passed. To the endpoint host, however, it is the first packet that has been received by the attacker. In this case, an attacker is able to succeed without security preventing the attack. Enabling this feature prevents such attacks.

Examples

The following example shows how to disable TTL evasion protection on flows from network 10.0.0.0 to 20.0.0.0:

```
hostname(config)# access-list TCP1 extended permit tcp 10.0.0.0 255.0.0.0 20.0.0.0
255.0.0.0
hostname(config)# tcp-map tmap
```

```

hostname(config-tcp-map)# ttl-evasion-protection disable
hostname(config)# class-map cmap
hostname(config-cmap)# match access-list TCP1
hostname(config)# policy-map pmap
hostname(config-pmap)# class cmap
hostname(config-pmap)# set connection advanced-options tmap
hostname(config)# service-policy pmap global

```

Related Commands

Command	Description
class (policy-map)	Specifies a class map to use for traffic classification.
help	Shows syntax help for the policy-map , class , and description commands.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
set connection	Configures connection values.
tcp-map	Creates a TCP map and allows access to tcp-map configuration mode.

tunnel-group

To create and manage the database of connection-specific records for IPSec, use the **tunnel-group** command in global configuration mode. To remove a tunnel group, use the **no** form of this command.

tunnel-group *name type type*

no tunnel-group *name*

Syntax Description

<i>name</i>	Specifies the name of the tunnel group. This can be any string you choose. If the name is an IP address, it is usually the IP address of the peer.
<i>type</i>	Specifies the type of tunnel group: ipsec-ra—IPSec remote access ipsec-l2l—IPsec LAN-to-LAN

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—



Note

The tunnel-group command is available in transparent firewall mode to allow configuration of a LAN-to-LAN tunnel group, but not a remote-access group. All the tunnel-group commands that are available for LAN-to-LAN are also available in transparent firewall mode.

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The security appliance has two default tunnel groups: DefaultRAGroup, which is the default IPSec remote-access tunnel group, and DefaultL2Lgroup, which is the default IPSec LAN-to-LAN tunnel group. You can change them but not delete them. The security appliance uses these groups to configure default tunnel parameters for remote access and LAN-to-LAN tunnel groups when there is no specific tunnel group identified during tunnel negotiation.

The **tunnel-group** command has the following commands. Each of these commands puts you in a configuration mode for configuring the attributes at the level of the configuration mode.

- **tunnel-group general-attributes**
- **tunnel-group ipsec-attributes**

Examples

The following example entered in global configuration mode, configures an IPsec LAN-to-LAN tunnel group. The name is the IP address of the LAN-to-LAN peer:

```
hostname(config)# tunnel-group 209.165.200.225 type ipsec-l2l
hostname(config)#
```

Related Commands

Command	Description
clear configure tunnel-group	Clears all configured tunnel groups.
show running-config tunnel-group	Shows the tunnel group configuration for all tunnel groups or for a particular tunnel group.
tunnel-group map	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

tunnel-group general-attributes

To enter the general-attribute configuration mode, use the **tunnel-group general-attributes** command in global configuration mode. This mode is used to configure settings that are common to all supported tunneling protocols.

To remove all general attributes, use the **no** form of this command.

tunnel-group *name* **general-attributes**

no tunnel-group *name* **general-attributes**

Syntax Description

general-attributes	Specifies attributes for this tunnel-group.
<i>name</i>	Specifies the name of the tunnel-group.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The following table lists the commands belonging in this group and the tunnel-group type where you can configure them:

General Attribute	Availability by Tunnel-Group Type
accounting-server-group	IPSec RA, IPSec L2L
address-pool	IPSec RA
authentication-server-group	IPSec RA
authorization-server-group	IPSec RA
default-group-policy	IPSec RA, IPSec L2L
dhcp-server	IPSec RA
strip-group	IPSec RA
strip-realm	IPSec RA

Examples

The following example entered in global configuration mode, creates a tunnel group for an IPSec LAN-to-LAN connection using the IP address of the LAN-to-LAN peer, then enters general configuration mode for configuring general attributes. The name of the tunnel group is 209.165.200.225.

```
hostname(config)# tunnel-group 209.165.200.225 type IPSec_L2L
hostname(config)# tunnel-group 209.165.200.225 general
hostname(config-general)#
```

The following example entered in global configuration mode, creates a tunnel group named "remotegrp" for an IPSec remote access connection, and then enters general configuration mode for configuring general attributes for the tunnel group named "remotegrp":

```
hostname(config)# tunnel-group remotegrp type ipsec_ra
hostname(config)# tunnel-group remotegrp general
hostname(config-general)#
```

Related Commands

Command	Description
crypto ca certificate map	Enters CA certificate map mode.
subject-name (crypto ca certificate map)	Identifies the DN from the CA certificate that is to be compared to the rule entry string.
tunnel-group-map default-group	Designates an existing tunnel-group name as the default tunnel group.

tunnel-group ipsec-attributes

To enter the ipsec-attribute configuration mode, use the **tunnel-group ipsec-attributes** command in global configuration mode. This mode is used to configure settings that are specific to the IPSec tunneling protocol.

To remove all IPSec attributes, use the **no** form of this command.

tunnel-group *name* **ipsec-attributes**

no tunnel-group *name* **ipsec-attributes**

Syntax Description

ipsec-attributes	Specifies attributes for this tunnel-group.
<i>name</i>	Specifies the name of the tunnel-group.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The following commands belong in this group:

IPSec Attribute	Availability by Tunnel-Group Type
authorization-dn-attributes	IPSec RA
authorization-required	IPSec RA
chain	IPSec RA, IPSec L2L
client-update	IPSec RA
isakmp keepalive	IPSec RA
peer-id-validate	IPSec RA, IPSec L2L
pre-shared-key	IPSec RA, IPSec L2L
radius-with-expiry	IPSec RA
trust-point	IPSec RA, IPSec L2L

Examples

The following example entered in global configuration, creates a tunnel group for the IPSec remote-access tunnel group named remotegrp, and then specifies IPSec group attributes:

```
hostname(config)# tunnel-group remotegrp type ipsec_ra
hostname(config)# tunnel-group remotegrp ipsec-attributes
hostname(config-ipsec)
```

Related Commands

Command	Description
clear configure tunnel-group	Clears all configured tunnel groups.
show running-config tunnel-group	Shows the tunnel group configuration for all tunnel groups or for a particular tunnel group.
tunnel-group-map default-group	Associates the certificate map entries created using the crypto ca certificate map command with tunnel groups.

tunnel-group-map default-group

The **tunnel-group-map** commands configure the policy and rules by which certificate-based IKE sessions are mapped to tunnel groups. To associate the certificate map entries, created using the **crypto ca certificate map** command, with tunnel groups, use the **tunnel-group-map** command in global configuration mode. You can invoke this command multiple times as long as each invocation is unique and you do not reference a map index more than once.

Use the **no** form of this command to eliminate a tunnel-group-map.

tunnel-group-map [*rule-index*] **default-group** *tunnel-group-name*

no tunnel-group-map

Syntax Description

default-group <i>tunnel-group-name</i>	Specifies a default tunnel group to use when the name cannot be derived by other configured methods. The <i>tunnel-group name</i> must already exist.
<i>rule index</i>	Optional. Refers to parameters specified by the crypto ca certificate map command. The values are 1 to 65535.

Defaults

The default value for the **tunnel-group-map default-group** is DefaultRAGroup.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **crypto ca certificate map** command maintains a prioritized list of certificate mapping rules. There can be only one map. But this map can have up to 65535 rules. Refer to the documentation on the **crypto ca certificate map** command for more information.

The processing that derives the tunnel-group name from the certificate ignores entries in the certificate map that are not associated with a tunnel group (any map rule not identified by this command).

Examples

The following example entered in global configuration mode, specifies a default tunnel group to use when the name cannot be derived by other configured methods. The name of the tunnel group to use is group1:

```
hostname(config)# tunnel-group-map default-group group1
hostname(config)#
```

Related Commands

Command	Description
crypto ca certificate map	Enters crypto ca certificate map mode.
subject-name (crypto ca certificate map)	Identifies the DN from the CA certificate that is to be compared to the rule entry string.
tunnel-group-map enable	Configures the policy and rules by which certificate-based IKE sessions are mapped to tunnel groups

tunnel-group-map enable

The **tunnel-group-map enable** command configures the policy and rules by which certificate-based IKE sessions are mapped to tunnel groups. Use the **no** form of this command to restore the default values.

tunnel-group-map [*rule-index*] **enable** *policy*

no tunnel-group-map enable [*rule-index*]

Syntax Description

<i>policy</i>	Specifies the policy for deriving the tunnel group name from the certificate. <i>Policy</i> can be one of the following: ike-id—Indicates that if a tunnel-group is not determined based on a rule lookup or taken from the ou, then the certificate-based IKE sessions are mapped to a tunnel group based on the content of the phase1 IKE ID. ou—Indicates that if a tunnel-group is not determined based on a rule lookup, then use the value of the organizational unit (OU) in the subject distinguished name (DN). peer-ip—Indicates that if a tunnel-group is not determined based on a rule lookup or taken from the ou or ike-id methods, then use the established peer IP address. rules—Indicates that the certificate-based IKE sessions are mapped to a tunnel group based on the certificate map associations configured by this command.
<i>rule index</i>	Optional. Refers to parameters specified by the crypto ca certificate map command. The values are 1 to 65535.

Defaults

The default values for the **tunnel-group-map** command are **enable ou** and **default-group** set to DefaultRAGroup.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **crypto ca certificate map** command maintains a prioritized list of certificate mapping rules. There can be only one map. But this map can have up to 65535 rules. Refer to the documentation on the **crypto ca certificate map** command for more information.

Examples

The following example enables mapping of certificate-based IKE sessions to a tunnel group based on the content of the phase1 IKE ID:

```
hostname(config)# tunnel-group-map enable ike-id
hostname(config)#
```

The following example enables mapping of certificate-based IKE sessions to a tunnel group based on the established IP address of the peer:

```
hostname(config)# tunnel-group-map enable peer-ip
hostname(config)#
```

The following example enables mapping of certificate-based IKE sessions based on the organizational unit (OU) in the subject distinguished name (DN):

```
hostname(config)# tunnel-group-map enable ou
hostname(config)#
```

The following example enables mapping of certificate-based IKE sessions based on established rules:

```
hostname(config)# tunnel-group-map enable rules
hostname(config)#
```

Related Commands

Command	Description
crypto ca certificate map	Enters CA certificate map mode.
subject-name (crypto ca certificate map)	Identifies the DN from the CA certificate that is to be compared to the rule entry string.
tunnel-group-map default-group	Designates an existing tunnel-group name as the default tunnel group.

tunnel-limit

To specify the maximum number of GTP tunnels allowed to be active on the security appliance, use the **tunnel limit** command in GTP map configuration mode, which is accessed by using the **gtp-map** command. Use the **no** to set the tunnel limit back to its default.

tunnel-limit *max_tunnels*

no tunnel-limit *max_tunnels*

Syntax Description

max_tunnels This is the maximum number of tunnels allowed. The ranges is from 1 to 4294967295 for the global overall tunnel limit.

Defaults

The default for the tunnel limit is 500.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
GTP map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

New requests will be dropped once the number of tunnels specified by this command is reached.

Examples

The following example specifies a maximum of 10,000 tunnels for GTP traffic:

```
hostname(config)# gtp-map gtp-policy
hostname(config-gtpmap)# tunnel-limit 10000
```

Related Commands

Commands	Description
clear service-policy inspect gtp	Clears global GTP statistics.
debug gtp	Displays detailed information about GTP inspection.
gtp-map	Defines a GTP map and enables GTP map configuration mode.

Commands	Description
inspect gtp	Applies a specific GTP map to use for application inspection.
show service-policy inspect gtp	Displays the GTP configuration.

tx-ring-limit

To specify the depth of the priority queues, use the **tx-ring-limit** command in priority-queue mode. To remove this specification, use the **no** form of this command.

tx-ring-limit *number-of-packets*

no tx-ring-limit *number-of-packets*

Syntax Description

<i>number-of-packets</i>	Specifies the maximum number of low-latency or normal priority packets allowed into the Ethernet transmit driver before the driver pushes back to the queues on the interface to let them buffer packets until the congestion clears. The range of tx-ring-limit values is 3 through 128 packets on the PIX platform and 3 through 256 packets on the ASA platform.

Defaults

The default **tx-ring-limit** is 128 packets.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Priority-queue	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The security appliance allows two classes of traffic: low-latency queuing (LLQ) for higher priority, latency sensitive traffic (such as voice and video) and best-effort, the default, for all other traffic. The security appliance recognizes priority traffic and enforces appropriate Quality of Service (QoS) policies. You can configure the size and depth of the priority queue to fine-tune the traffic flow.

You must use the **priority-queue** command to create the priority queue for an interface before priority queuing takes effect. You can apply one **priority-queue** command to any interface that can be defined by the **nameif** command.

The **priority-queue** command enters priority-queue mode, as shown by the prompt. In priority-queue mode, you can configure the maximum number of packets allowed in the transmit queue at any given time (**tx-ring-limit** command) and the number of packets of either type (priority or best-effort) allowed to be buffered before dropping packets (**queue-limit** command).



Note

You *must* configure the **priority-queue** command in order to enable priority queueing for the interface.

The tx-ring-limit and the queue-limit that you specify affect both the higher priority low-latency queue and the best-effort queue. The tx-ring-limit is the number of either type of packets allowed into the driver before the driver pushes back to the queues sitting in front of the interface to let them buffer packets until the congestion clears. In general, you can adjust these two parameters to optimize the flow of low-latency traffic.

Because queues are not of infinite size, they can fill and overflow. When a queue is full, any additional packets cannot get into the queue and are dropped. This is *tail drop*. To avoid having the queue fill up, you can use the **queue-limit** command to increase the queue buffer size.

**Note**

The upper limit of the range of values for the **queue-limit** and **tx-ring-limit** commands is determined dynamically at run time. To view this limit, enter **help** or **?** on the command line. The key determinant is the memory needed to support the queues and the memory available on the device. The range of **queue-limit** values is 0 through 2048 packets. The range of **tx-ring-limit** values is 3 through 128 packets on the PIX platform and 3 through 256 packets on the ASA platform.

Examples

The following example configures a priority queue for the interface named test, specifying a queue limit of 2048 packets and a transmit queue limit of 256 packets.

```
hostname(config)# priority-queue test
hostname(priority-queue)# queue-limit 2048
hostname(priority-queue)# tx-ring-limit 256
```

Related Commands

Command	Description
clear configure priority-queue	Removes the current priority queue configuration on the named interface.
priority-queue	Configures priority queuing on an interface.
queue-limit	Specifies the maximum number of packets that can be enqueued to a priority queue before it drops data.
show priority-queue statistics	Shows the priority-queue statistics for the named interface.
show running-config priority-queue	Shows the current priority queue configuration. If you specify the all keyword, this command displays all the current priority-queue , queue-limit , and tx-ring-limit command configuration values.

urgent-flag

To allow or clear the URG pointer through the TCP normalizer, use the **urgent-flag** command in tcp-map configuration mode. To remove this specification, use the **no** form of this command.

urgent-flag {allow | clear}

no urgent-flag {allow | clear}

Syntax Description

allow	Allows the URG pointer through the TCP normalizer.
clear	Clears the URG pointer through the TCP normalizer.

Defaults

The urgent flag and urgent offset are clear by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tcp-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **tcp-map** command is used along with the Modular Policy Framework infrastructure. Define the class of traffic using the **class-map** command and customize the TCP inspection with **tcp-map** commands. Apply the new TCP map using the **policy-map** command. Activate TCP inspection with **service-policy** commands.

Use the **tcp-map** command to enter tcp-map configuration mode. Use the **urgent-flag** command in tcp-map configuration mode to allow the urgent flag.

The URG flag is used to indicate that the packet contains information that is of higher priority than other data within the stream. The TCP RFC is vague about the exact interpretation of the URG flag, therefore, end systems handle urgent offsets in different ways, which may make the end system vulnerable to attacks. The default behavior is to clear the URG flag and offset.

Examples

The following example shows how to allow the urgent flag:

```
hostname(config)# tcp-map tmap
hostname(config-tcp-map)# urgent-flag allow
hostname(config)# class-map cmap
hostname(config-cmap)# match port tcp eq 513
hostname(config)# policy-map pmap
```

```
hostname(config-pmap)# class cmap
hostname(config-pmap)# set connection advanced-options tmap
hostname(config)# service-policy pmap global
```

Related Commands

Command	Description
class	Specifies a class map to use for traffic classification.
help	Shows syntax help for the policy-map , class , and description commands.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
set connection	Configures connection values.
tcp-map	Creates a TCP map and allows access to tcp-map configuration mode.

url

To maintain the list of static URLs for retrieving CRLs, use the **url** command in **crl configure** configuration mode. The **crl configure** configuration mode is accessible from the **crypto ca trustpoint** configuration mode. To delete an existing URL, use the **no** form of this command.

url *index url*

no url *index url*

Syntax Description

<i>index</i>	Specifies a value from 1 to 5 that determines the rank of each URL in the list. The security appliance tries the URL at index 1 first.
<i>url</i>	Specifies the URL from which to retrieve the CRL.

Defaults

No default behaviors or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
CRL configure configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You cannot overwrite existing URLs. To replace an existing URL, first delete it using the **no** form of this command.

Examples

The following example enters **ca-crl** configuration mode, and sets up an index 3 for creating and maintaining a list of URLs for CRL retrieval and configures the URL **https://foobin.com** from which to retrieve CRLs:

```
hostname(configure)# crypto ca trustpoint central
hostname(ca-trustpoint)# crl configure
hostname(ca-crl)# url 3 https://foobin.com
hostname(ca-crl)#
```

Related Commands

Command	Description
crl configure	Enters ca-crl configuration mode.
crypto ca trustpoint	Enters trustpoint configuration mode.
policy	Specifies the source for retrieving CRLs.

url-block

The **url-block** commands can be used to manage the URL buffers used for web server responses while waiting for a filtering decision from the filtering server. The **url-block** commands are also used to manage filtering of long URLs. To remove the configuration, use the **no** form of this command.

url-block block *block_buffer_limit*

no url-block block *block_buffer_limit*

Websense only:

url-block url-mempool *memory_pool_size*

no url-block url-mempool *memory_pool_size*

The numeric parameters for the **url-block** command are lower in multi-context mode than in single-context mode. For example:

Single-context:

url-block block *block_buffer_limit*—max is 128

url-block url-mempool *memory_pool_size*—max is 10240

Multi-context:

url-block block *block_buffer_limit*—max is 16

url-block url-mempool *memory_pool_size*—max is 512

Syntax Description

block <i>block_buffer_limit</i>	Creates an HTTP response buffer to store web server responses while waiting for a filtering decision from the filtering server. The permitted values are from 0 to 128, which specifies the number of 1550-byte blocks.
url-mempool <i>memory_pool_size</i>	For Websense URL filtering only. The size of the URL buffer memory pool in Kilobytes (KB). The permitted values are from 2 to 10240, which specifies a URL buffer memory pool from 2 KB to 10240 KB.
 Note This is not supported on the UDP transport servers.	
url-size <i>long_url_size</i>	For Websense URL filtering only. The maximum allowed URL size in KB. The permitted values are 2, 3, or 4, which specifies a maximum URL size of 2 KB, 3 KB, or 4KB.
 Note This is not supported on the UDP transport servers.	

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

For Websense filtering servers, the **url-block url-size** command allows filtering of long URLs, up to 4 KB. For both Websense and N2H2 filtering servers, the **url-block block** command causes the security appliance to buffer packets received from a web server in response to a web client request while waiting for a response from the URL filtering server. This improves performance for the web client compared to the default security appliance behavior, which is to drop the packets and to require the web server to retransmit the packets if the connection is permitted.

If you use the **url-block block** command and the filtering server permits the connection, the security appliance sends the blocks to the web client from the HTTP response buffer and removes the blocks from the buffer. If the filtering server denies the connection, the security appliance sends a deny message to the web client and removes the blocks from the HTTP response buffer.

Use the **url-block block command** to specify the number of blocks to use for buffering web server responses while waiting for a filtering decision from the filtering server.

Use the **url-block url-size** command with the **url-block url-mempool** command to specify the maximum length of a URL to be filtered by a Websense filtering server and the maximum memory to assign to the URL buffer. Use these commands to pass URLs longer than 1159 bytes, up to a maximum of 4096 bytes, to the Websense server. The **url-block url-size** command stores URLs longer than 1159 bytes in a buffer and then passes the URL to the Websense server (through a TCP packet stream) so that the Websense server can grant or deny access to that URL.

Examples

The following example assigns 56 1550-byte blocks for buffering responses from the URL filtering server:

```
hostname#(config)# url-block block 56
```

Related Commands

Commands	Description
clear url-block block statistics	Clears the block buffer usage counters.
filter url	Directs traffic to a URL filtering server.
show url-block	Displays information about the URL cache, which is used for buffering URLs while waiting for responses from an N2H2 or Websense filtering server.

url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

url-cache

To enable URL caching for URL responses received from an N2H2 or Websense server and to set the size of the cache, use the **url-cache** command in global configuration mode. To remove the configuration, use the **no** form of this command.

url-cache {**dst** | **src_dst**} *kbytes* [**kb**]

no url-cache {**dst** | **src_dst**} *kbytes* [**kb**]

Syntax Description

dst	Cache entries based on the URL destination address. Select this mode if all users share the same URL filtering policy on the N2H2 or Websense server.
size <i>kbytes</i>	Specifies a value for the cache size within the range 1 to 128 KB.
src_dst	Cache entries based on the both the source address initiating the URL request as well as the URL destination address. Select this mode if users do not share the same URL filtering policy on the N2H2 or Websense server.
statistics	Use the statistics option to display additional URL cache statistics, including the number of cache lookups and hit rate.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **url-cache** command provides a configuration option to buffer the response from a web server if its response is faster than that from the N2H2 or Websense filtering service server. This prevents the web server response from being loaded twice.

Use the **url-cache** command to enable URL caching, set the size of the cache, and display cache statistics.

Caching stores URL access privileges in memory on the security appliance. When a host requests a connection, the security appliance first looks in the URL cache for matching access privileges instead of forwarding the request to the N2H2 or Websense server. Disable caching with the **no url-cache** command.

**Note**

If you change settings on the N2H2 or Websense server, disable the cache with the **no url-cache** command and then re-enable the cache with the **url-cache** command.

Using the URL cache does not update the Websense accounting logs for Websense protocol Version 1. If you are using Websense protocol Version 1, let Websense run to accumulate logs so you can view the Websense accounting information. After you get a usage profile that meets your security needs, enable **url-cache** to increase throughput. Accounting logs are updated for Websense protocol Version 4 and for N2H2 URL filtering while using the **url-cache** command.

Examples

The following example caches all outbound HTTP connections based on the source and destination addresses:

```
hostname(config)# url-cache src_dst 128
```

Related Commands

Commands	Description
clear url-cache statistics	Removes url-cache command statements from the configuration.
filter url	Directs traffic to a URL filtering server.
show url-cache statistics	Displays information about the URL cache, which is used for URL responses received from an N2H2 or Websense filtering server.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

url-list

To configure a set of URLs for WebVPN users to access, use the **url-list** command in global configuration mode. To configure a list with multiple URLs, use this command with the same listname multiple times, once for each URL. To remove an entire configured list, use the **no url-list listname** command. To remove a configured URL, use the **no url-list listname url** command.

To configure multiple lists, use this command multiple times, assigning a unique *listname* to each list.

url-list {*listname displayname url*}

no url-list *listname*

no url-list *listname url*

Syntax Description

<i>displayname</i>	Provides the text that displays on the WebVPN end user interface to identify the URL. Maximum 64 characters. The <i>displayname</i> must be unique for a given list. Spaces are allowed.
<i>listname</i>	Groups the set of URLs that WebVPN users can access. Maximum 64 characters. Maximum 64 characters. Semi-colons (;) ampersands (&), and less-than (<) characters are not allowed.
<i>url</i>	Specifies the link. Supported URL types are http, https and cifs.

Defaults

There is no default URL list.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration mode	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You use the url-list command in global configuration mode to create one or more lists of URLs. To allow access to the URLs in a list for a specific group policy or user, use the *listname* you create here with the **url-list** command in webvpn mode.

Examples

The following example shows how to create a URL list called *Marketing URLs* that provides access to www.cisco.com, www.example.com, and www.example.org. The following table provides values that the example uses for each application.

listname	displayname	url
Marketing URLs	Cisco Systems	http://www.cisco.com
Marketing URLs	Example Company, Inc.	http://www.example.com
Marketing URLs	Example Organization	http://www.example.org

```
hostname(config)# url-list Marketing URLs Cisco Systems http://www.cisco.com
hostname(config)# url-list Marketing URLs Example Company, Inc. http://www.example.com
hostname(config)# url-list Marketing URLs Example Organization http://www.example.org
```

Related Commands

Command	Description
clear configuration url-list	Removes all url-list commands from the configuration. If you include the listname, the security appliance removes only the commands for that list.
url-list	Use this command in webvpn mode to permit a group policy or user to access a previously configured list of urls.
show running-configuration url-list	Displays the current set of configured urls.
webvpn	Use in group-policy configuration mode or in username configuration mode. Lets you enter webvpn mode to configure parameters that apply to group policies or usernames.
webvpn	Use in global configuration mode. Lets you configure global settings for WebVPN.

url-list (webvpn)

To apply a list of WebVPN servers and URLs to a particular user or group policy, use the **url-list** command in webvpn mode, which you enter from group-policy or username mode. To remove a list, including a null value created by using the **url-list none command**, use the **no** form of this command. The **no** option allows inheritance of a value from another group policy. To prevent inheriting a url list, use the **url-list none** command. Using the command a second time overrides the previous setting.

url-list { value *name* | **none** }

no url-list

Syntax Description

value <i>name</i>	Specifies the name of a previously configured list of urls. To configure such a list, use the url-list command in global configuration mode.
none	Sets a null value for url lists. Prevents inheriting a list from a default or specified group policy.

Defaults

There is no default URL list.

Command Modes

The following table shows the modes in which you enter the commands:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn mode	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Using the command a second time overrides the previous setting.

Before you can use the **url-list** command in webvpn mode to identify a URL list that you want to display on the WebVPN home page for a user or group policy, you must create the list. Use the **url-list** command in global configuration mode to create one or more lists.

Examples

The following example shows how to set a URL list called FirstGroupURLs for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# webvpn
hostname(config-group-webvpn)# url-list value FirstGroupURLs
```

Related Commands

Command	Description
clear configure url-list <i>[listname]</i>	Removes all url-list commands from the configuration. If you include the listname, the security appliance removes only the commands for that list.
show running-configuration url-list	Displays the current set of configured url-list commands.
url-list	Use this command in webvpn mode, which you access in global configuration mode, to configure the set of URLs that WebVPN users can access.
webvpn	Lets you enter webvpn mode, which you access in group-policy configuration mode or in username configuration mode, to configure webvpn setting for a specific group policy or user.

url-server

To identify an N2H2 or Websense server for use with the **filter** command, use the **url-server** command. To remove the configuration, use the **no** form of this command.

N2H2

```
url-server (if_name) vendor n2h2 host local_ip [port number] [timeout seconds] [protocol { TCP | UDP [connections num_conns]}]
```

```
no url-server (if_name) vendor n2h2 host local_ip [port number] [timeout seconds] [protocol { TCP | UDP [connections num_conns]}]
```

Websense

```
url-server (if_name) vendor websense host local_ip [timeout seconds] [protocol { TCP | UDP | connections num_conns } | version]
```

```
no url-server (if_name) vendor websense host local_ip [timeout seconds] [protocol { TCP | UDP | connections num_conns } | version]
```

Syntax Description

N2H2

connections	Limits the maximum number of connections permitted.
<i>num_conns</i>	Specifies the maximum number of connections permitted.
host <i>local_ip</i>	The server that runs the URL filtering application.
<i>if_name</i>	(Optional) The network interface where the authentication server resides. If not specified, the default is inside.
port <i>number</i>	The N2H2 server port. The security appliance also listens for UDP replies on this port. The default port number is 4005.
protocol	The protocol can be configured using TCP or UDP keywords. The default is TCP.
timeout <i>seconds</i>	The maximum idle time permitted before the security appliance switches to the next server you specified. The default is 30 seconds.
vendor n2h2	Indicates URL filtering service vendor is N2H2.

Websense

connections	Limits the maximum number of connections permitted.
<i>if_name</i>	The network interface where the authentication server resides. If not specified, the default is inside.
host <i>local_ip</i>	The server that runs the URL filtering application.
timeout <i>seconds</i>	The maximum idle time permitted before the security appliance switches to the next server you specified. The default is 30 seconds.
protocol	The protocol can be configured using TCP or UDP keywords. The default is TCP protocol, Version 1.

vendor websense	Indicates URL filtering service vendor is Websense.
version	Specifies protocol Version 1 or 4 . The default is TCP protocol Version 1. TCP can be configured using Version 1 or Version 4. UDP can be configured using Version 4 only.

Defaults

This command is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **url-server** command designates the server running the N2H2 or Websense URL filtering application. The limit is 16 URL servers; however, and you can use only one application at a time, either N2H2 or Websense. Additionally, changing your configuration on the security appliance does not update the configuration on the application server; this must be done separately, according to the vendor instructions.

The **url-server** command must be configured before issuing the **filter** command for HTTPS and FTP. If all URL servers are removed from the server list, then all **filter** commands related to URL filtering are also removed.

Once you designate the server, enable the URL filtering service with the **filter url** command.

Follow these steps to filter URLs:

- Step 1** Designate the URL filtering application server with the appropriate form of the vendor-specific **url-server** command.
- Step 2** Enable URL filtering with the **filter** command.
- Step 3** (Optional) Use the **url-cache** command to enable URL caching to improve perceived response time.
- Step 4** (Optional) Enable long URL and HTTP buffering support using the **url-block** command.
- Step 5** Use the **show url-block block statistics**, **show url-cache statistics**, or the **show url-server statistics** commands to view run information.

For more information about Filtering by N2H2, visit N2H2's website at:

<http://www.n2h2.com>

For more information on Websense filtering services, visit the following website:

<http://www.websense.com/>

Examples

Using N2H2, the following example filters all outbound HTTP connections except those from the 10.0.2.54 host:

```
hostname(config)# url-server (perimeter) vendor n2h2 host 10.0.1.1
hostname(config)# filter url http 0 0 0 0
hostname(config)# filter url except 10.0.2.54 255.255.255.255 0 0
```

Using Websense, the following example filters all outbound HTTP connections except those from the 10.0.2.54 host:

```
hostname(config)# url-server (perimeter) vendor websense host 10.0.1.1 protocol TCP
version 4
hostname(config)# filter url http 0 0 0 0
hostname(config)# filter url except 10.0.2.54 255.255.255.255 0 0
```

Related Commands

Commands	Description
clear url-server	Clears the URL filtering server statistics.
filter url	Directs traffic to a URL filtering server.
show url-block	Displays information about the URL cache, which is used for buffering URLs while waiting for responses from an N2H2 or Websense filtering server.
url-cache	Enables URL caching while pending responses from an N2H2 or Websense server and sets the size of the cache.
url-server	Identifies an N2H2 or Websense server for use with the filter command.

user-authentication

To enable user authentication, use the **user-authentication enable** command in group-policy configuration mode. To disable user authentication, use the **user-authentication disable** command. To remove the user authentication attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a value for user authentication from another group policy.

When enabled, user authentication requires that individual users behind a hardware client authenticate to gain access to the network across the tunnel.

user-authentication {enable | disable}

no user-authentication

Syntax Description

disable	Disables user authentication.
enable	Enables user authentication.

Defaults

User authentication is disabled.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Individual users authenticate according to the order of authentication servers that you configure. If you require user authentication on the primary security appliance, be sure to configure it on any backup servers as well.

Examples

The following example shows how to enable user authentication for the group policy named “FirstGroup”:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# user-authentication enable
```

Related Commands	Command	Description
	ip-phone-bypass	Lets IP phones connect without undergoing user authentication. Secure unit authentication remains in effect.
	leap-bypass	Lets LEAP packets from wireless devices behind a VPN client travel across a VPN tunnel prior to user authentication, when enabled. This lets workstations using Cisco wireless access point devices establish LEAP authentication. Then they authenticate again per user authentication.
	secure-unit-authentication	Provides additional security by requiring the VPN client to authenticate with a username and password each time the client initiates a tunnel.
	user-authentication-idle-timeout	Sets an idle timeout for individual users. If there is no communication activity on a user connection in the idle timeout period, the security appliance terminates the connection.

user-authentication-idle-timeout

To set an idle timeout for individual users behind hardware clients, use the **user-authentication-idle-timeout** command in group-policy configuration mode. To delete the idle timeout value, use the **no** form of this command. This option allows inheritance of an idle timeout value from another group policy. To prevent inheriting an idle timeout value, use the **user-authentication-idle-timeout none** command.

If there is no communication activity by a user behind a hardware client in the idle timeout period, the security appliance terminates the connection.

user-authentication-idle-timeout {*minutes* | **none**}

no user-authentication-idle-timeout

Syntax Description

minutes	Specifies the number of minutes in the idle timeout period. The range is from 1 through 35791394 minutes
none	Permits an unlimited idle timeout period. Sets idle timeout with a null value, thereby disallowing an idle timeout. Prevents inheriting an user authentication idle timeout value from a default or specified group policy.

Defaults

30 minutes.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The minimum is 1 minute, the default is 30 minutes, and the maximum is 10,080 minutes.

Examples

The following example shows how to set an idle timeout value of 45 minutes for the group policy named “FirstGroup”:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# user-authentication-idle-timeout 45
```

Related Commands	Command	Description
	user-authentication	Requires users behind hardware clients to identify themselves to the security appliance before connecting.

username

To add a user to the security appliance database, enter the **username** command in global configuration mode. To remove a user, use the **no** version of this command with the username you want to remove. To remove all usernames, use the **no** version of this command without appending a username.

username {*name*} {**nopassword** | **password** *password* [**encrypted**]} [**privilege** *priv_level*]

no username [*name*]

Syntax Description

encrypted	Indicates that the password is encrypted.
<i>name</i>	Provides the name of the user.
nopassword	Indicates that this user needs no password.
password <i>password</i>	Indicates that this user has a password, and provides the password.
privilege <i>priv_level</i>	Sets a privilege level for this user. The range is from 0 to 15, with lower numbers having less ability to use commands and administer the security appliance. The default privilege level is 2. The typical privilege level for a system administrator is 15.

Defaults

By default, VPN users that you add with this command have no attributes or group policy association. You must configure all values explicitly.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The internal user authentication database consists of the users entered with the username command. The login command uses this database for authentication.

Examples

The following example shows how to configure a user named anyuser with a n encrypted password of 12345678 and a privilege level of 12:

```
hostname(config)# username anyuser password 12345678 encrypted privilege 12
```

Related Commands	Command	Description
	clear config username	Clears the configuration for a particular user or for all users.
	show running-config username	Displays the running configuration for a particular user or for all users.
	username attributes	Enters username attributes mode, which lets you configure AVPs for specific users.

username attributes

To enter the username attributes mode, use the **username attributes** command in username configuration mode. To remove all attributes for a particular user, use the **no** form of this command and append the username. To remove all attributes for all users, use the **no** form of this command without appending a username. The attributes mode lets you configure AVPs for a specified user.

username {*name*} **attributes**

no username [*name*] **attributes**

Syntax Description

name Provides the name of the user.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Username	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The internal user authentication database consists of the users entered with the username command. The login command uses this database for authentication.

The syntax of the commands in attributes mode have the following characteristics in common:

- The **no** form removes the attribute from the running configuration.
- The **none** keyword also removes the attribute from the running configuration. But it does so by setting the attribute to a null value, thereby preventing inheritance.
- Boolean attributes have explicit syntax for enabled and disabled settings.

Examples

The following example shows how to enter username attributes configuration mode for a user named anyuser:

```
hostname(config)# username anyuser attributes
```

Related Commands	Command	Description
	clear config username	Clears the username database.
	show running-config username	Displays the running configuration for a particular user or for all users.
	username	Adds a user to the security appliance database.

username-prompt

To configure the prompt for the username for initial login to WebVPN, use the **username-prompt** command in webvpn mode. To revert to the default, “Login:,” use the **no** form of this command.

username-prompt [*prompt*]

no username-prompt

Syntax Description

prompt ((Optional) Specifies the string that prompts users to enter a username. Maximum 16 characters.

Defaults

The default prompt is “Login:”

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Webvpn	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to configure the password prompt, “Enter Username:”:

```
hostname(config)# webvpn
hostname(config-webvpn)# password-prompt Enter Username:
```

virtual http

To configure a virtual HTTP server, use the **virtual http** command in global configuration mode. To disable the virtual server, use the **no** form of this command. When you use HTTP authentication on the security appliance, and the HTTP server also requires authentication, this command allows you to authenticate separately with the security appliance and with the HTTP server. Without virtual HTTP, the same username and password you used to authenticate with the security appliance is sent to the HTTP server; you are not prompted separately for the HTTP server username and password.

virtual http *ip_address* [**warning**]

no virtual http *ip_address* [**warning**]

Syntax Description

<i>ip_address</i>	Sets the IP address for the virtual HTTP server on the security appliance. Make sure this address is an unused address that is routed to the security appliance.
warning	(Optional) Notifies users that the HTTP connection needs to be redirected to the security appliance. This keyword applies only for text-based browsers, where the redirect cannot happen automatically.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

If you enable HTTP authentication (see the **aaa authentication match** command or the **aaa authentication include** command), then the security appliance prompts each user for a username and password so it can authenticate them with a AAA server. After the AAA server authenticates the user, the connection is allowed to continue to the HTTP server. However, the AAA server username and password is still included in the HTTP packet. If the HTTP server also has its own authentication mechanism, then the user is not prompted again for a username and password because there is already a username and password included in the packet. Assuming the username and password is not the same for the AAA and HTTP servers, then the HTTP authentication fails.

To allow a user to be prompted separately by the HTTP server, enable the virtual HTTP server on the security appliance using the **virtual http** command. This command redirects all HTTP connections that require AAA authentication to the virtual HTTP server on the security appliance. The security appliance

prompts for the AAA server username and password. After the AAA server authenticates the user, the security appliance redirects the HTTP connection back to the original server, but it does not include the AAA server username and password. Because the username and password are not included in the HTTP packet, the HTTP server prompts the user separately for the HTTP server username and password.

For inbound users (from lower security to higher security), you must also include the virtual HTTP address as a destination interface in the access list applied to the source interface. Moreover, you must add a **static** command for the virtual HTTP IP address, even if NAT is not required (using the **no nat-control** command). An identity NAT command is typically used (where you translate the address to itself).

For outbound users, there is an explicit permit for traffic, but if you apply an access list to an inside interface, be sure to allow access to the virtual HTTP address. A **static** statement is not required.



Caution

Do not set the **timeout uauth** command duration to 0 seconds when using the **virtual http** command, because this setting prevents HTTP connections to the real web server.

Examples

The following example shows how to enable virtual HTTP along with AAA authentication:

```
hostname(config)# virtual http 209.165.202.129
hostname(config)# access-list ACL-IN extended permit tcp any host 209.165.200.225 eq http
hostname(config)# access-list ACL-IN remark This is the HTTP server on the inside
hostname(config)# access-list ACL-IN extended permit tcp any host 209.165.202.129 eq http
hostname(config)# access-list ACL-IN remark This is the virtual HTTP address
hostname(config)# access-group ACL-IN in interface outside
hostname(config)# static (inside, outside) 209.165.202.129 209.165.202.129 netmask
255.255.255.255
hostname(config)# access-list AUTH extended permit tcp any host 209.165.200.225 eq http
hostname(config)# access-list AUTH remark This is the HTTP server on the inside
hostname(config)# access-list AUTH extended permit tcp any host 209.165.202.129 eq http
hostname(config)# access-list AUTH remark This is the virtual HTTP address
hostname(config)# aaa authentication match AUTH outside tacacs+
```

Related Commands

Command	Description
clear configure virtual	Removes virtual command statements from the configuration.
show running-config virtual	Displays the IP address of the security appliance virtual server.
sysopt uauth allow-http-cache	When you enable the virtual http command, this command lets you use the username and password in the browser cache to reconnect to the virtual server.
virtual telnet	Provides a virtual Telnet server on the security appliance to let users authenticate with the security appliance before initiating other types of connections that require authentication.

virtual telnet

To configure a virtual Telnet server on the security appliance, use the **virtual telnet** command in global configuration mode. You might need to authenticate users with the virtual Telnet server if you require authentication for other types of traffic for which the security appliance does not supply an authentication prompt. To disable the server, use the **no** form of this command.

virtual telnet *ip_address*

no virtual telnet *ip_address*

Syntax Description

ip_address Sets the IP address for the virtual Telnet server on the security appliance. Make sure this address is an unused address that is routed to the security appliance.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	•	•	•	—

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

Although you can configure network access authentication for any protocol or service (see the **aaa authentication match** or **aaa authentication include** command), you can authenticate directly with HTTP, Telnet, or FTP only. A user must first authenticate with one of these services before other traffic that requires authentication is allowed through. If you do not want to allow HTTP, Telnet, or FTP through the security appliance, but want to authenticate other types of traffic, you can configure virtual Telnet; the user Telnets to a given IP address configured on the security appliance, and the security appliance provides a Telnet prompt.

You must configure authentication for Telnet access to the virtual Telnet address as well as the other services you want to authenticate using the **authentication match** or **aaa authentication include** command.

When an unauthenticated user connects to the virtual Telnet IP address, the user is challenged for a username and password, and then authenticated by the AAA server. Once authenticated, the user sees the message “Authentication Successful.” Then, the user can successfully access other services that require authentication.

For inbound users (from lower security to higher security), you must also include the virtual Telnet address as a destination interface in the access list applied to the source interface. Moreover, you must add a **static** command for the virtual Telnet IP address, even if NAT is not required (using the **no nat-control** command). An identity NAT command is typically used (where you translate the address to itself).

For outbound users, there is an explicit permit for traffic, but if you apply an access list to an inside interface, be sure to allow access to the virtual Telnet address. A **static** statement is not required.

To logout from the security appliance, reconnect to the virtual Telnet IP address; you are prompted to log out.

Examples

This example shows how to enable virtual Telnet along with AAA authentication for other services:

```
hostname(config)# virtual telnet 209.165.202.129
hostname(config)# access-list ACL-IN extended permit tcp any host 209.165.200.225 eq smtp
hostname(config)# access-list ACL-IN remark This is the SMTP server on the inside
hostname(config)# access-list ACL-IN extended permit tcp any host 209.165.202.129 eq
telnet
hostname(config)# access-list ACL-IN remark This is the virtual Telnet address
hostname(config)# access-group ACL-IN in interface outside
hostname(config)# static (inside, outside) 209.165.202.129 209.165.202.129 netmask
255.255.255.255
hostname(config)# access-list AUTH extended permit tcp any host 209.165.200.225 eq smtp
hostname(config)# access-list AUTH remark This is the SMTP server on the inside
hostname(config)# access-list AUTH extended permit tcp any host 209.165.202.129 eq telnet
hostname(config)# access-list AUTH remark This is the virtual Telnet address
hostname(config)# aaa authentication match AUTH outside tacacs+
```

Related Commands

Command	Description
clear configure virtual	Removes virtual command statements from the configuration.
show running-config virtual	Displays the IP address of the security appliance virtual server.
virtual http	When you use HTTP authentication on the security appliance, and the HTTP server also requires authentication, this command allows you to authenticate separately with the security appliance and with the HTTP server. Without virtual HTTP, the same username and password you used to authenticate with the security appliance is sent to the HTTP server; you are not prompted separately for the HTTP server username and password.

vlan

To assign a VLAN ID to a subinterface, use the **vlan** command in interface configuration mode. To remove a VLAN ID, use the **no** form of this command. Subinterfaces require a VLAN ID to pass traffic. VLAN subinterfaces let you configure multiple logical interfaces on a single physical interface. VLANs let you keep traffic separate on a given physical interface, for example, for multiple security contexts.

vlan *id*

no vlan

Syntax Description

<i>id</i>	Specifies an integer between 1 and 4094. Some VLAN IDs might be reserved on connected switches, so check the switch documentation for more information.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Interface configuration	•	•	•	—	•

Command History

Release	Modification
7.0	This command was moved from a keyword of the interface command to an interface configuration mode command.

Usage Guidelines

You can only assign a single VLAN to a subinterface, and not to the physical interface. Each subinterface must have a VLAN ID before it can pass traffic. To change a VLAN ID, you do not need to remove the old VLAN ID with the **no** option; you can enter the **vlan** command with a different VLAN ID, and the security appliance changes the old ID.

You need to enable the physical interface with the **no shutdown** command to let subinterfaces be enabled. If you enable subinterfaces, you typically do not also want the physical interface to pass traffic, because the physical interface passes untagged packets. Therefore, you cannot prevent traffic from passing through the physical interface by bringing down the interface. Instead, ensure that the physical interface does not pass traffic by leaving out the **nameif** command. If you want to let the physical interface pass untagged packets, you can configure the **nameif** command as usual.

The maximum number of subinterfaces varies depending on your platform. See the *Cisco Security Appliance Command Line Configuration Guide* for the maximum subinterfaces per platform.

Examples

The following example assigns VLAN 101 to a subinterface:

```
hostname(config)# interface gigabitethernet0/0.1
hostname(config-subif)# vlan 101
hostname(config-subif)# nameif dmz1
hostname(config-subif)# security-level 50
hostname(config-subif)# ip address 10.1.2.1 255.255.255.0
hostname(config-subif)# no shutdown
```

The following example changes the VLAN to 102:

```
hostname(config)# show running-config interface gigabitethernet0/0.1
interface GigabitEthernet0/0.1
    vlan 101
    nameif dmz1
    security-level 50
    ip address 10.1.2.1 255.255.255.0

hostname(config)# interface gigabitethernet0/0.1
hostname(config-interface)# vlan 102

hostname(config)# show running-config interface gigabitethernet0/0.1
interface GigabitEthernet0/0.1
    vlan 102
    nameif dmz1
    security-level 50
    ip address 10.1.2.1 255.255.255.0
```

Related Commands

Command	Description
allocate-interface	Assigns interfaces and subinterfaces to a security context.
interface	Configures an interface and enters interface configuration mode.
show running-config interface	Shows the current configuration of the interface.

vpn-access-hours

To associate a group policy with a configured time-range policy, use the **vpn-access-hours** command in group-policy configuration mode or username configuration mode. To remove the attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a time-range value from another group policy. To prevent inheriting a value, use the **vpn-access-hours none** command.

vpn-access hours value {*time-range*} | **none**

no vpn-access hours

Syntax Description

none	Sets VPN access hours to a null value, thereby allowing no time-range policy. Prevents inheriting a value from a default or specified group policy.
<i>time-range</i>	Specifies the name of a configured time-range policy.

Defaults

Unrestricted.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—
Username	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Examples

The following example shows how to associate the group policy named FirstGroup with a time-range policy called 824:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# vpn-access-hours 824
```

Related Commands

Command	Description
time-range	Sets days of the week and hours of the day for access to the network, including start and end dates.

vpn-addr-assign

To specify a method for assigning IP addresses to remote access clients, use the **vpn-addr-assign** command in global configuration mode. To remove the attribute from the configuration, use the **no** version of this command. To remove all configured Vpn address assignment methods from the security appliance, use the **no** version of this command. without arguments.

vpn-addr-assign {aaa | dhcp | local}

no vpn-addr-assign [aaa | dhcp | local]

Syntax Description

aaa	Obtains IP addresses from an external AAA authentication server.
dhcp	Obtains IP addresses via DHCP.
local	Assigns IP addresses from internal authentication server, and associates them with a tunnel group.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

If you choose DHCP, you must also use the **dhcp-network-scope** command to define the range of IP addresses that the DHCP server can use.

If you choose local, you must also use the **ip-local-pool** command to define the range of IP addresses to use. You then use the **vpn-framed-ip-address** and **vpn-framed-netmask** commands to assign IP addresses and netmasks to individual users.

If you choose AAA, you obtain IP addresses from either a previously configured RADIUS server.

Examples

The following example shows how to configure DHCP as the address assignment method:

```
hostname(config)# vpn-addr-assign dhcp
```

Related Commands	Command	Description
	dhcp-network-scope	Specifies the range of IP addresses the security appliance DHCP server should use to assign addresses to users of a group policy.
	ip-local-pool	Creates a local IP address pool.
	vpn-framed-ip-address	Specifies the IP address to assign to a particular user.
	vpn-framed-ip-netmask	Specifies the netmask to assign to a particular user.

vpn-filter

To specify the name of the ACL to use for VPN connections, use the **vpn-filter** command in group policy or username mode. To remove the ACL, including a null value created by issuing the **vpn-filter none** command, use the **no** form of this command. The **no** option allows inheritance of a value from another group policy. To prevent inheriting values, use the **vpn-filter none** command.

You configure ACLs to permit or deny various types of traffic for this user or group policy. You then use the **vpn-filter** command to apply those ACLs.

vpn-filter { *value* *ACL name* | **none** }

no vpn-filter

Syntax Description

none	Indicates that there is no access list. Sets a null value, thereby disallowing an access list. Prevents inheriting an access list from another group policy.
value <i>ACL name</i>	Provides the name of the previously configured access list.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—
Username	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

WebVPN does not use the ACL defined in the **vpn-filter** command.

Examples

The following example shows how to set a filter that invokes an access list named `acl_vpn` for the group policy named `FirstGroup`:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# vpn-filter value acl_vpn
```

Related Commands

Command	Description
access-list	Creates an access list, or uses a downloadable access list.

vpn-framed-ip-address

To specify the IP address to assign to a particular user, use the **vpn-framed-ip-address** command in username mode. To remove the IP address, use the **no** form of this command.

vpn-framed-ip-address {*ip_address*}

no vpn-framed-ip-address

Syntax Description	<i>ip_address</i>	Provides the IP address for this user.

Defaults	No default behavior or values.

Command Modes	The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Username	•	—	•	—	—

Release	Modification
7.0	This command was introduced.

Examples	The following example shows how to set an IP address of 10.92.166.7 for a user named anyuser:

```
hostname(config)# username anyuser attributes
hostname(config-username)# vpn-framed-ip-address 10.92.166.7
```

Related Commands	Command	Description
	vpn-framed-ip-netmask	Provides the subnet mask for this user.

vpn-framed-ip-netmask

To specify the subnet mask to assign to a particular user, use the **vpn-framed-ip-netmask** command in username mode. To remove the subnet mask, use the **no** form of this command.

vpn-framed-ip-netmask {*netmask*}

no vpn-framed-ip-netmask

Syntax Description

netmask Provides the subnet mask for this user.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Username	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to set a subnet mask of 255.255.255. 254 for a user named anyuser:

```
hostname(config)# username anyuser attributes
hostname(config-username)# vpn-framed-ip-netmask 255.255.255.254
```



Note

If RADIUS only returns the subnet mask, the authentication uses the IP address from the local pool which has its own subnet netmask. It does not use the mask from RADIUS. To prevent this, return both the netmask and IP address from RADIUS.

Related Commands

Command	Description
vpn-framed-ip-address	Provides the IP address for this user.

vpn-group-policy

To have a user inherit attributes from a configured group policy, use the **vpn-group-policy** command in username configuration mode. To remove a group policy from a user configuration, use the **no** version of this command. Using this command lets users inherit attributes that you have not configured at the username level.

vpn-group-policy {group-policy name}

no vpn-group-policy {group-policy name}

Syntax Description

group-policy name	Provides the name of the group policy.

Defaults

By default, VPN users have no group policy association.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Username	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

You can override the value of an attribute in a group policy for a particular user by configuring it in username mode, if that attribute is available in username mode.

Examples

The following example shows how to configure a user named anyuser to use attributes from the group policy named FirstGroup:

```
hostname(config)# username anyuser attributes
hostname(config-username)# vpn-group-policy FirstGroup
```

Related Commands

Command	Description
group-policy	Adds a group policy to the security appliance database.
group-policy attributes	Enters group-policy attributes mode, which lets you configure AVPs for a group policy.

Command	Description
username	Adds a user to the security appliance database.
username attributes	Enters username attributes mode, which lets you configure AVPs for specific users.

vpn-idle-timeout

To configure a user timeout period use the **vpn-idle-timeout** command in group-policy configuration mode or in username configuration mode. If there is no communication activity on the connection in this period, the security appliance terminates the connection.

To remove the attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a time-out value from another group policy. To prevent inheriting a value, use the **vpn-idle-timeout none** command.

vpn-idle-timeout {*minutes* | **none**}

no vpn-idle-timeout

Syntax Description

<i>minutes</i>	Specifies the number of minutes in the timeout period. Use an integer between 1 and 35791394.
none	Permits an unlimited idle timeout period. Sets idle timeout with a null value, thereby disallowing an idle timeout. Prevents inheriting a value from a default or specified group policy.

Defaults

30 minutes.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—
Username	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to set a VPN idle timeout of 15 minutes for the group policy named “FirstGroup”:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# vpn-idle-timeout 30
```

Related Commands

group-policy	Creates or edits a group policy.
vpn-session-timeout	Configures the maximum amount of time allowed for VPN connections. At the end of this period of time, the security appliance terminates the connection.

vpn load-balancing

To enter vpn load-balancing mode, in which you can configure VPN load balancing and related functions, use the **vpn load-balancing** command in global configuration mode.

vpn load-balancing



Note

Only ASA Models 5540 and 5520 support VPN load balancing. VPN load balancing also requires an active 3DES/AES license. The security appliance checks for the existence of this crypto license before enabling load balancing. If it does not detect an active 3DES or AES license, the security appliance prevents the enabling of load balancing and also prevents internal configuration of 3DES by the load balancing system unless the license permits this usage.

Syntax Description

This command has no arguments or keywords.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration mode	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use the **vpn load-balancing** command to enter vpn load-balancing mode. The following commands are available in vpn load-balancing mode:

cluster encryption

cluster ip address

cluster key

cluster port

interface

nat

participate

priority

See the individual command descriptions for detailed information.

Examples

The following is an example of the **vpn load-balancing** command; note the change in the prompt:

```
hostname(config)# vpn load-balancing
hostname(config-load-balancing)#
```

The following is an example of a VPN load-balancing command sequence that includes an interface command that specifies the public interface of the cluster as “test” and the private interface of the cluster as “foo”:

```
hostname(config)# interface GigabitEthernet 0/1
hostname(config-if)# ip address 209.165.202.159 255.255.255.0
hostname(config)# nameif test
hostname(config)# interface GigabitEthernet 0/2
hostname(config-if)# ip address 209.165.201.30 255.255.255.0
hostname(config)# nameif foo
hostname(config)# vpn load-balancing
hostname(config-load-balancing)# nat 192.168.10.10
hostname(config-load-balancing)# priority 9
hostname(config-load-balancing)# interface lbpublic test
hostname(config-load-balancing)# interface lbprivate foo
hostname(config-load-balancing)# cluster ip address 209.165.202.224
hostname(config-load-balancing)# cluster key 123456789
hostname(config-load-balancing)# cluster encryption
hostname(config-load-balancing)# cluster port 9023
hostname(config-load-balancing)# participate
```

Command	Description
clear configure vpn load-balancing	Removes the load-balancing runtime configuration and disables load balancing.
show running-config vpn load-balancing	Displays the the current VPN load-balancing virtual cluster configuration.
show vpn load-balancing	Displays VPN load-balancing runtime statistics.

vpn-sessiondb logoff

To log off all or selected VPN sessions, use the **vpn-sessiondb logoff** command in global configuration mode.

vpn-sessiondb logoff { **remote** | **l2l** | **webvpn** | **email-proxy** | **protocol** *protocol-name* | **name** *username* | **ipaddress** *IPaddr* | **tunnel-group** *groupname* | **index** *indexnumber* | **all** }

Syntax Description

all	Logs off all VPN sessions.																
email-proxy	Logs off all e-mail proxy sessions.																
index <i>indexnumber</i>	Logs off a single session by index number. Specify the index number for the session.																
ipaddress <i>IPaddr</i>	Logs off sessions for the IP address hat you specify.																
l2l	Logs off all LAN-to-LAN sessions.																
name <i>username</i>	Logs off sessions for the username that you specify.																
protocol <i>protocol-name</i>	Logs off sessions for protocols that you specify. The protocols include: <table> <tr> <td>IKE</td><td>POP3S</td></tr> <tr> <td>IMAP4S</td><td>SMTPTS</td></tr> <tr> <td>IPSec</td><td>userHTTPS</td></tr> <tr> <td>IPSecLAN2LAN</td><td>vcaLAN2LAN</td></tr> <tr> <td>IPSecLAN2LANOverNatT</td><td></td></tr> <tr> <td>IPSecOverNatT</td><td></td></tr> <tr> <td>IPSecoverTCP</td><td></td></tr> <tr> <td>IPSecOverUDP</td><td></td></tr> </table>	IKE	POP3S	IMAP4S	SMTPTS	IPSec	userHTTPS	IPSecLAN2LAN	vcaLAN2LAN	IPSecLAN2LANOverNatT		IPSecOverNatT		IPSecoverTCP		IPSecOverUDP	
IKE	POP3S																
IMAP4S	SMTPTS																
IPSec	userHTTPS																
IPSecLAN2LAN	vcaLAN2LAN																
IPSecLAN2LANOverNatT																	
IPSecOverNatT																	
IPSecoverTCP																	
IPSecOverUDP																	
remote	Logs off all remote-access sessions.																
tunnel-group <i>groupname</i>	Logs off sessions for the tunnel group that you specify.																
webvpn	Logs off all WebVPN sessions.																

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to log off all remote-access sessions:

```
hostname# vpn-sessiondb logoff remote
```

The next example shows how to log off all IPSec sessions:

```
hostname# vpn-sessiondb logoff protocol IPSec
```

vpn-sessiondb max-session-limit

To limit VPN sessions to a lower value than the security appliance allows, use the **vpn-sessiondb max-session-limit** command in global configuration mode. To remove the session limit, use the **no** version of this command. To overwrite the current setting, use the command again.

vpn-sessiondb max-session-limit *{session-limit}*

no vpn-sessiondb max-session-limit

Syntax Description

session-limit Specifies the maximum number of VPN sessions permitted.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This command applies to all types of VPN sessions, including WebVPN.

Examples

The following example shows how to set a maximum VPN session limit of 450:

```
hostname# vpn-sessiondb max-session-limit 450
```


vpn-session-timeout

To configure a maximum amount of time allowed for VPN connections, use the **vpn-session-timeout** command in group-policy configuration mode or in username configuration mode. At the end of this period of time, the security appliance terminates the connection.

To remove the attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a time-out value from another group policy. To prevent inheriting a value, use the **vpn-session-timeout none** command.

vpn-session-timeout {*minutes* | **none**}

no vpn-session-timeout

Syntax Description

<i>minutes</i>	Specifies the number of minutes in the timeout period. Use an integer between 1 and 35791394.
none	Permits an unlimited session timeout period. Sets session timeout with a null value, thereby disallowing a session timeout. Prevents inheriting a value from a default or specified group policy.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Group-policy	•	—	•	—	—
Username	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Examples

The following example shows how to set a VPN session timeout of 180 minutes for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# vpn-session-timeout 180
```

Related Commands

group-policy	Creates or edits a group policy.
vpn-idle-timeout	Configures the user timeout period. If there is no communication activity on the connection in this period, the security appliance terminates the connection.

vpn-simultaneous-logins

To configure the number of simultaneous logins permitted for a user, use the **vpn-simultaneous-logins** command in group-policy configuration mode or username configuration mode. To remove the attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a value from another group policy. Enter 0 to disable login and prevent user access.

vpn-simultaneous-logins {*integer*}

no vpn-simultaneous-logins

Syntax Description

integer A number between 0 and 2147483647.

Defaults

The default is 3 simultaneous logins.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—
Username	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Enter 0 to disable login and prevent user access.

Examples

The following example shows how to allow a maximum of 4 simultaneous logins for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# vpn-simultaneous-logins 4
```

vpn-tunnel-protocol

To configure a VPN tunnel type (IPSec or WebVPN), use the **vpn-tunnel-protocol** command in group-policy configuration mode or username configuration mode. To remove the attribute from the running configuration, use the **no** form of this command.

vpn-tunnel-protocol {webvpn | IPSec}

no vpn-tunnel-protocol [webvpn | IPSec]

Syntax Description

IPSec	Negotiates an IPSec tunnel between two peers (a remote access client or another secure gateway). Creates security associations that govern authentication, encryption, encapsulation, and key management.
webvpn	Provides VPN services to remote users via an HTTPS-enabled web browser, and does not require a client

Defaults

IPSec.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—
Username	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Use this command to configure one or more tunneling modes. You must configure at least one tunneling mode for users to connect over a VPN tunnel.

Examples

The following example shows how to configure WebVPN and IPSec tunneling modes for the group policy named “FirstGroup”:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# vpn-tunnel-protocol webvpn
hostname(config-group-policy)# vpn-tunnel-protocol IPSec
```

webvpn

To enter webvpn mode, in global configuration mode, enter the **webvpn** command. To remove any commands entered with this command, use the **no webvpn** command. These webvpn commands apply to all WebVPN users.

These webvpn commands let you configure AAA servers, default group policies, default idle timeout, http and https proxies, and NBNS servers for WebVPN, as well as the appearance of WebVPN screens that end users see.

webvpn

no webvpn

Syntax Description

This command has no arguments or keywords.

Defaults

WebVPN is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Global configuration	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

This WebVPN mode lets you configure global settings for WebVPN. WebVPN mode, which you enter from either group-policy mode or username mode, lets you customize a WebVPN configuration for specific users or group policies.

Examples

The following example shows how to enter WebVPN command mode:

```
hostname(config)# webvpn
hostname(config-webvpn)#
```

webvpn (group-policy, username)

To enter this webvpn mode, use the **webvpn** command in group-policy configuration mode or in username configuration mode. To remove all commands entered in webvpn mode, use the **no** form of this command. These webvpn commands apply to the username or group policy from which you configure them.

Webvpn commands for group policies and usernames define access to files, MAPI proxy, URLs and TCP applications over WebVPN. They also identify ACLs and types of traffic to filter.

webvpn

no webvpn

Syntax Description

This command has no arguments or keywords.

Defaults

WebVPN is disabled by default.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	•	—	—	•
Username	•	•	—	—	•

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Webvpn mode, which you enter from global configuration mode, lets you configure global settings for WebVPN.

Webvpn mode, described in this section, and which you enter from group-policy or username mode, lets you customize a WebVPN configuration for specific users or group policies.

You do not need to configure WebVPN to use e-mail proxies.

WebVPN lets users establish a secure, remote-access VPN tunnel to the security appliance using a web browser. There is no need for either a software or hardware client. WebVPN provides easy access to a broad range of web resources and web-enabled applications from almost any computer on the Internet. WebVPN uses SSL and its successor, TLS1 to provide a secure connection between remote users and specific, supported internal resources that you configure at a central site. The security appliance recognizes connections that need to be proxied, and the HTTP server interacts with the authentication subsystem to authenticate users.

Examples

The following example shows how to enter webvpn mode for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes  
hostname(config-group-policy)# webvpn  
hostname(config-webvpn)#
```

Related Commands

Command	Description
filter	Identifies the access list to be used for WebVPN connections.
functions	Configures file access and file browsing, MAPI Proxy, and URL entry over WebVPN.
homepage	Sets the URL of the webpage that displays when WebVPN users log in.
html-content-filter	Identifies Java, ActiveX, images, scripts, and cookies to filter for WebVPN sessions.
port-forward	Enables WebVPN application access.
port-forward-name	Configures the display name that identifies TCP port forwarding to end users.
url-list	Identifies a list of servers and URLs that users can access via WebVPN.

who

To display active Telnet administration sessions on the security appliance, use the **who** command in privileged EXEC mode.

who [*local_ip*]

Syntax Description

local_ip (Optional) Specifies to limit the listing to one internal IP address or network address, either IPv4 or IPv6.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The **who** command allows you to display the TTY_ID and IP address of each Telnet client that is currently logged into the security appliance.

Examples

This example shows the output of the **who** command when a client is logged into the security appliance through a Telnet session:

```
hostname# who
0: 100.0.0.2
hostname# who 100.0.0.2
0: 100.0.0.2
hostname#
```

Related Commands

Command	Description
kill	Terminate a Telnet session.
telnet	Adds Telnet access to the security appliance console and sets the idle timeout.

window-variation

To drop a connection with a window size variation, use the **window-variation** command in tcp-map configuration mode. To remove this specification, use the **no** form of this command.

window variation { **allow-connection** | **drop-connection** }

no window variation { **allow-connection** | **drop-connection** }

Syntax Description

allow-connection	Allows the connection.
drop-connection	Drops the connection.

Defaults

The default action is to allow the connection.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Tcp-map configuration	•	•	•	•	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

The **tcp-map** command is used along with the Modular Policy Framework infrastructure. Define the class of traffic using the **class-map** command and customize the TCP inspection with **tcp-map** commands. Apply the new TCP map using the **policy-map** command. Activate TCP inspection with **service-policy** commands.

Use the **tcp-map** command to enter tcp-map configuration mode. Use the **window-variation** command in tcp-map configuration mode to drop all connections with a window size that has been shrunk.

The window size mechanism allows TCP to advertise a large window and to subsequently advertise a much smaller window without having accepted too much data. From the TCP specification, “shrinking the window” is strongly discouraged. When this condition is detected, the connection can be dropped.

Examples

The following example shows how to drop all connections with a varied window size:

```
hostname(config)# access-list TCP extended permit tcp any any
hostname(config)# tcp-map tmap
hostname(config-tcp-map)# window-variation drop-connection
hostname(config)# class-map cmap
hostname(config-cmap)# match access-list TCP
hostname(config)# policy-map pmap
```

```
hostname(config-pmap)# class cmap
hostname(config-pmap)# set connection advanced-options tmap
hostname(config)# service-policy pmap global
```

Related Commands

Command	Description
class	Specifies a class map to use for traffic classification.
help	Shows syntax help for the policy-map , class , and description commands.
policy-map	Configures a policy; that is, an association of a traffic class and one or more actions.
set connection	Configures connection values.
tcp-map	Creates a TCP map and allows access to tcp-map configuration mode.

wins-server

To set the IP address of the primary and secondary WINS servers, use the **wins-server** command in group-policy configuration mode. To remove the attribute from the running configuration, use the **no** form of this command. This option allows inheritance of a WINS server from another group policy. To prevent inheriting a server, use the **wins-server none** command.

wins-server value {*ip_address*} [*ip_address*] | none

no wins-server

Syntax Description

none	Sets wins-servers to a null value, thereby allowing no WINS servers. Prevents inheriting a value from a default or specified group policy.
value <i>ip_address</i>	Specifies the IP address of the primary and secondary WINS servers.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Group-policy	•	—	•	—	—

Command History

Release	Modification
7.0	This command was introduced.

Usage Guidelines

Every time you issue the **wins-server** command you overwrite the existing setting. For example, if you configure WINS server x.x.x.x and then configure WINS server y.y.y.y, the second command overwrites the first, and y.y.y.y becomes the sole WINS server. The same holds true for multiple servers. To add a WINS server rather than overwrite previously configured servers, include the IP addresses of all WINS servers when you enter this command.

Examples

The following example shows how to configure WINS servers with the IP addresses 10.10.10.15, 10.10.10.30, and 10.10.10.45 for the group policy named FirstGroup:

```
hostname(config)# group-policy FirstGroup attributes
hostname(config-group-policy)# wins-server value 10.10.10.15 10.10.10.30 10.10.10.45
```

write erase

To erase the startup configuration, use the **write erase** command in privileged EXEC mode. The running configuration remains intact.

write erase

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	—	•

Release	Modification
Preexisting	This command was preexisting.

Command History

Usage Guidelines This command is not supported within a security context. Context startup configurations are identified by the [config-url](#) command in the system configuration. If you want to delete a context configuration, you can remove the file manually from the remote server (if specified) or clear the file from Flash memory using the **delete** command in the system execution space.

Examples The following example erases the startup configuration:

```
hostname# write erase
Erase configuration in flash memory? [confirm] y
```

Command	Description
configure net	Merges a configuration file from the specified TFTP URL with the running configuration.
delete	Removes a file from Flash memory.
show running-config	Shows the running configuration.
write memory	Saves the running configuration to the startup configuration.

Related Commands

write memory

To save the running configuration to the startup configuration, use the **write memory** command in privileged EXEC mode.

write memory

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines The running configuration is the configuration currently running in memory, including any changes you made at the command line. Changes are only preserved between reboots if you save them to the startup configuration, which is the configuration loaded into running memory at startup. The location of the startup configuration for single context mode and for the system in multiple context mode can be changed from the default location (a hidden file) to a location of your choosing using the **boot config** command. For multiple context mode, a context startup configuration is at the location specified by the **config-url** command in the system configuration.

In multiple context mode, this command saves only the current configuration; you cannot save all contexts with a single command. You must enter this command separately for the system and for each context. Context startup configurations can reside on external servers. In this case, the security appliance saves the configuration back to the server specified by the **config-url** command, except for HTTP and HTTPS URLs, which do not allow you to save the configuration back to the server. Because the system uses the admin context interfaces to access context startup configurations, the **write memory** command also uses the admin context interfaces. The **write net** command, however, uses the context interfaces to write a configuration to a TFTP server.

The **write memory** command is equivalent to the **copy running-config startup-config** command.

Examples The following example saves the running configuration to the startup configuration:

```
hostname# write memory
Building configuration...
```

```
Cryptochecksum: e43e0621 9772bebe b685e74f 748e4454
```

```
19319 bytes copied in 3.570 secs (6439 bytes/sec)
[OK]
```

```
hostname#
```

Related Commands

Command	Description
admin-context	Sets the admin context.
boot	Sets the boot image and startup configuration.
configure memory	Merges the startup configuration with the running configuration.
config-url	Specifies the location of the context configuration.
copy running-config startup-config	Copies the running configuration to the startup configuration.
write net	Copies the running configuration to a TFTP server.

write net

To save the running configuration to a TFTP server, use the **write net** command in privileged EXEC mode.

write net [*server*:*filename*] | *:filename*

Syntax Description

<i>:filename</i>	Specifies the path and filename. If you already set the filename using the tftp-server command, then this argument is optional. If you specify the filename in this command as well as a name in the tftp-server command, the security appliance treats the tftp-server command filename as a directory, and adds the write net command filename as a file under the directory. To override the tftp-server command value, enter a slash in front of the path and filename. The slash indicates that the path is not relative to the tftpboot directory, but is an absolute path. The URL generated for this file includes a double slash (//) in front of the filename path. If the file you want is in the tftpboot directory, you can include the path for the tftpboot directory in the filename path. If your TFTP server does not support this type of URL, use the copy running-config tftp command instead. If you specified the TFTP server address using the tftp-server command, you can enter the filename alone preceded by a colon (:).
<i>server</i> :	Sets the TFTP server IP address or name. This address overrides the address you set in the tftp-server command, if present. The default gateway interface is the highest security interface; however, you can set a different interface name using the tftp-server command.

Defaults

No default behavior or values.

Command Modes

The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple	
				Context	System
Privileged EXEC	•	•	•	•	•

Command History

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines

The running configuration is the configuration currently running in memory, including any changes you made at the command line.

In multiple context mode, this command saves only the current configuration; you cannot save all contexts with a single command. You must enter this command separately for the system and for each context. The **write net** command uses the context interfaces to write a configuration to a TFTP server. The **write memory** command, however, uses the admin context interfaces to save to the startup configuration because the system uses the admin context interfaces to access context startup configurations.

The **write net** command is equivalent to the **copy running-config tftp** command.

Examples

The following example sets the TFTP server and filename in the **tftp-server** command:

```
hostname# tftp-server inside 10.1.1.1 /configs/contextbackup.cfg
hostname# write net
```

The following example sets the server and filename in the **write net** command. The **tftp-server** command is not populated.

```
hostname# write net 10.1.1.1:/configs/contextbackup.cfg
```

The following example sets the server and filename in the **write net** command. The **tftp-server** command supplies the directory name, and the server address is overridden.

```
hostname# tftp-server 10.1.1.1 configs
hostname# write net 10.1.2.1:context.cfg
```

Related Commands

Command	Description
configure net	Merges a configuration file from the specified TFTP URL with the running configuration.
copy running-config tftp	Copies the running configuration to a TFTP server.
show running-config	Shows the running configuration.
tftp-server	Sets a default TFTP server and path for use in other commands.
write memory	Saves the running configuration to the startup configuration.

write standby

To copy the security appliance or context running configuration to the failover standby unit, use the **write standby** command in privileged EXEC mode.

write standby

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Release	Modification
Preexisting	This command was preexisting.

Usage Guidelines For Active/Standby failover, the **write standby** command writes the configuration stored in the RAM of the active failover unit to the RAM on the standby unit. Use the **write standby** command if the primary and secondary unit configurations have different information. Enter this command on the active unit.

For Active/Active failover, the **write standby** command behaves as follows:

- If you enter the **write standby** command in the system execution space, the system configuration and the configurations for all of the security contexts on the security appliance is written to the peer unit. This includes configuration information for security contexts that are in the standby state. You must enter the command in the system execution space on the unit that has failover group 1 in the active state.
- If you enter the **write standby** command in a security context, only the configuration for the security context is written to the peer unit. You must enter the command in the security context on the unit where the security context appears in the active state.



Note

The **write standby** command replicates the configuration to the running configuration of the peer unit; it does not save the configuration to the startup configuration. To save the configuration changes to the startup configuration, use the **copy running-config startup-config** command on the same unit that you entered the **write standby** command. The command will be replicated to the peer unit and the configuration saved to the startup configuration.

When Stateful Failover is enabled, the **write standby** command also replicates state information to the standby unit after the configuration replication is complete.

Examples

The following example writes the current running configuration to the standby unit:

```
hostname# write standby
Building configuration...
[OK]
hostname#
```

Related Commands

Command	Description
failover	Forces the standby unit to reboot.
reload-standby	

write terminal

To show the running configuration on the terminal, use the **write terminal** command in privileged EXEC mode.

write terminal

Syntax Description This command has no arguments or keywords.

Defaults No default behavior or values.

Command Modes The following table shows the modes in which you can enter the command:

Command Mode	Firewall Mode		Security Context		
	Routed	Transparent	Single	Multiple Context	System
Privileged EXEC	•	•	•	•	•

Command History	Release	Modification
	Preexisting	This command was preexisting.

Usage Guidelines This command is equivalent to the [show running-config](#) command.

Examples The following example writes the running configuration to the terminal:

```
hostname# write terminal
: Saved
:
ASA Version 7.0(0)61
multicast-routing
names
name 10.10.4.200 outside
!
interface GigabitEthernet0/0
 nameif inside
 security-level 100
 ip address 10.86.194.60 255.255.254.0
 webvpn enable
...
```

Related Commands	Command	Description
	configure net	Merges a configuration file from the specified TFTP URL with the running configuration.
	show running-config	Shows the running configuration.
	write memory	Saves the running configuration to the startup configuration.