

Send documentation comments to mdsfeedback-doc@cisco.com.



Cisco MDS 9000 Family Release Notes for Cisco MDS 9000 EPLD Images, Release 5.x

Part Number: OL-17601-08

Release Date: July 17, 2011



Note

Release notes are sometimes updated with new information. Refer to the following website for the most recent version of the *Cisco MDS 9000 Family Release Notes*:
http://www.cisco.com/en/US/products/ps5989/prod_release_notes_list.html

Contents

This document contains the following sections:

- [Introduction, page 2](#)
- [Changes Since the Last Release, page 2](#)
- [Determining the EPLD Versions on Your Modules, page 2](#)
- [Installing and Upgrading the EPLD Version, page 6](#)
- [Upgrading the Power Management EPLD Nondisruptively, page 8](#)
- [Guidelines and Limitations, page 9](#)
- [EPLD Support Matrix, page 9](#)
- [Related Documentation, page 15](#)
- [Obtaining Documentation, Obtaining Support, and Security Guidelines, page 18](#)



Americas Headquarters:

Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

Send documentation comments to mdsfeedback-doc@cisco.com.

Introduction

Switches and directors in the Cisco MDS 9000 Family contain several electrical programmable logical devices (EPLDs) that provide hardware functionalities in all of the modules. As of Cisco MDS SAN-OS Release 1.2, EPLD image upgrades are periodically provided to include enhanced hardware functionality or to resolve known issues.

You do not need to update your EPLD image unless otherwise advised by TAC. For detailed functional image upgrade instructions, refer to the *Cisco MDS 9000 NX-OS Fundamentals Configuration Guide*. To download the EPLD image, go to the following URL:

<http://www.cisco.com/kobayashi/sw-center/index.shtml>



Note

As of NX-OS Release 4.1(1b), SAN-OS has been changed to NX-OS. References to SAN-OS releases before 4.1(1b) still apply.



Note

For information on configuring, upgrading, and displaying EPLD images, refer to the *Cisco MDS 9000 NX-OS Fundamentals Configuration Guide* and the *Cisco MDS 9000 Family Command Reference*.



Note

Except for the Cisco MDS 9222i switch, the Cisco MDS 9200 Series switches do not support EPLD upgrades.

Changes Since the Last Release

There is a new EPLD image for Cisco MDS NX-OS Release 5.2(1). The image name is EPLD m9000-epld-5.2.1.img file.

There are no caveats associated with the EPLD m9000-epld-5.2.1.img file.

Determining the EPLD Versions on Your Modules

You can determine the EPLD versions by using CLI commands. This section includes the following topics:

- [Module EPLD Versions, page 2](#)
- [Clock Module EPLD Versions, page 6](#)

Module EPLD Versions

Use the **show version module slot epld** command to view all current EPLD versions on a specified module.

Example 1 Displaying Current EPLD Versions for a Specified Module

```
switch# show version module 2 epld
EPLD Device Version
```

Send documentation comments to mdsfeedback-doc@cisco.com.

```
-----
Power Manager      0x07
XBUS IO            0x07
UD Flow Control    0x05
PCI ASIC I/F       0x05
PCI Bridge         0x07
```

Use the **show version epld url** command to view available EPLD versions. The following command output example shows available EPLD versions.



Note

If you are not using a module that requires the latest EPLD image, then you do not need to upgrade the EPLD image on your switch. See the EPLD Support Matrix in [Table 1](#) for additional information about the modules supported by different EPLD versions.

Example 2 Displaying Module EPLD Versions

```
switch# show version epld bootflash:m9000-epld-5.2.1.gimg
```

```
Copy complete, now saving to disk (please wait)...
```

```
Len 5591285, CS 0xa9, string MDS series EPLD image, built on Mon Jul 18 04:44:24
2011
```

```
MDS series EPLD image, built on Mon Jul 18 04:44:24 2011
```

Module Type	EPLD Device	Version
MDS 9500 Supervisor 2 (Part No: 73-9621-XX)	Power Manager	0x0e
	XBUS IO	0x0b
	Fabric Controller 1	0x0b
	Fabric Controller 2	0x46
	Fabric Controller 3	0x51
MDS 9500 Supervisor 2 (Part No: 73-12342-XX)	Power Manager	0x0e
	XBUS IO	0x2f
	Fabric Controller 1	0x0b
	Fabric Controller 2	0x46
	Fabric Controller 3	0x51
MDS 9500 Supervisor 2 (Part No: 73-13231-XX)	Power Manager	0x0e
	XBUS IO	0x2f
	Fabric Controller 1	0x0b
	Fabric Controller 2	0x46
	Fabric Controller 3	0x51
10 Gbps FC Module	Power Manager	0x0b
	XBUS IO	0x0b
1/2/4 Gbps FC Module (12 Port)	Power Manager	0x0b

Send documentation comments to mdsfeedback-doc@cisco.com.

	XBUS IO	0x0b
1/2/4 Gbps FC Module (24 Port)	Power Manager	0x0b
	XBUS IO	0x0b
1/2/4 Gbps FC Module (48 Port)	Power Manager	0x0b
	XBUS IO	0x0b
MDS 9124 Fabric Switch	Power Manager	0x0b
MDS FC Blade Switch (IBM BladeCntr)	Power Manager	0x08
Multiservice Module (18/4 Port)	Power Manager	0x08
	XBUS IO	0x08
MDS 9222i Multiservice Switch	Power Manager	0x08
	XBUS IO	0x03
Multiservice FIPS Module (18/4 Port)	Power Manager	0x08
	XBUS IO	0x08
MDS 9124e Blade Switch (HP C-Class)	Power Manager	0x04
MDS 9134 Fabric Switch	Power Manager	0x11
Clock card	Clock Controller	0x05
1/2/4/8 Gbps FC Module (48 Port)	Power Manager	0x02
	XBUS IO	0x06
1/2/4/8 Gbps FC Module (48 Port)	Power Manager	0x05
	XBUS IO	0x15

Send documentation comments to mdsfeedback-doc@cisco.com.

1/2/4/8 Gbps FC Module (24 Port)	Power Manager	0x05
	XBUS IO	0x15
16x1GE Port	Power Manager	0x09
	XBUS IO	0x23
NEC 24-port 1/2/4G SUP/LC	Power Manager	0x01
48-port 1/2/4/8G Fabric Switch	Power Manager	0x0a
10-Gbps 16-Port FCoE Module	Power Manager	0x06
	XBUS IO	0x20
1/2/4/8/10 Gbps Advanced FC Module	Power Manager	0x09
	XBUS IO	0x26
24-port 1/2/4/8G Blade (HP) Switch	Power Manager	0x05
10-Gbps 8-Port FCoE Module	Power Manager	0x02
	XBUS IO	0x04
1/2/4/8/10 Gbps Advanced FC Module	Power Manager	0x09
	XBUS IO	0x26

switch#



Note

Do not upgrade the EPLD on the MDS FC Blade Switch (IBM BladeCntr) module if the version contained in the EPLD image file for the MDS FC Blade Switch (IBM BladeCntr) module is 0x7.

[Send documentation comments to mdsfeedback-doc@cisco.com.](mailto:mdsfeedback-doc@cisco.com)

Clock Module EPLD Versions

Use the **show version clock-module epld** command to view current EPLD versions on the Cisco MDS 9513 clock modules. The following command output example shows available clock module EPLD versions.

Example 3 Displaying Clock Module EPLD Versions

```
switch# show version clock-module epld
```

EPLD Device	Version
-----	-----
Clock Controller (Clock A)	0x05
Clock Controller (Clock B)	0x05

Installing and Upgrading the EPLD Version

EPLDs can be installed, upgraded, or downgraded using CLI commands. This section includes the following topics:

- [Installing and Upgrading Module EPLDs, page 6](#)
- [Installing or Upgrading Clock Module EPLDs, page 8](#)



Note

When attempting to use USB ports, the following message may be displayed:

Please upgrade Power Management EPLD to version 0xD or higher.

You may need to upgrade the Power Management EPLD for the supervisor modules to version 0xD or higher to use the USB ports. After upgrading the Power Management EPLD, you must power cycle the supervisor modules by power cycling the chassis. This is a disruptive upgrade. To perform a nondisruptive upgrade, see “[Upgrading the Power Management EPLD Nondisruptively](#)”.

Installing and Upgrading Module EPLDs

Use the **install module module-number epld** command to upgrade EPLD images for a module. The modules that can be upgraded with this command are the standby supervisor and the switching modules. To upgrade the modules, you must enter the **install module module-number epld** command from the active supervisor. The active supervisor cannot be upgraded, only the standby supervisor can be upgraded.

Example 4 Upgrading Module EPLDs

```
switch# install module 9 epld bootflash:m9000-epld.3.2.1.img
```

EPLD	Curr Ver	New Ver
-----	-----	-----
XBUS IO	0x07	0x07
UD Flow Control	0x05	0x05
PCI ASIC I/F	0x05	0x05
PCI Bridge	0x05	0x07
WARNING: Upgrade process could take upto 15 minutes.		

Send documentation comments to mdsfeedback-doc@cisco.com.

```
Module 9 will be powered down now!!
```

```
Do you want to continue (y/n) ? y
```

```
\ <-----progress twirl
```

```
Module 9 EPLD upgrade is successful
```

If you forcefully upgrade a module that is not online, all EPLDs are forcefully upgraded. If the module is not present in the switch, an error is returned. If the module is present, the upgrade process continues.

To upgrade a module that is not online but is present in the chassis, use the **install module module-number epld** command. The switch software prompts you to continue after reporting the module state. When you confirm your intention to continue, the upgrade continues.

```
switch# install module 2 epld bootflash:m9000-epld-2.01b.img
```

```
\ <-----progress twirl
```

```
Module 2 EPLD upgrade is successful
```



Note

When you upgrade the EPLDs on the Cisco MDS 9100 Family switches or when you upgrade EPLDs for a module in slot 1 of a Cisco MDS 9222i switch, the following message is displayed:

```
Data traffic on the switch will stop now!!
```

```
Do you want to continue (y/n) ?
```

When you install a Supervisor-2 module on a Cisco MDS 9513 Director, the external crossbar module will be upgraded with the standby Supervisor-2 module if a new EPLD version for the external crossbar module is available. To upgrade the external crossbar module, you need to have the standby Supervisor-2 module present and run the **install module module-number epld** command from the active supervisor module.

Example 5 Upgrading External Crossbar Modules

```
switch# install module 8 epld bootflash:m9000-epld-4.1.3.img
```

```
EPLD                               Curr Ver    New Ver
```

```
-----
```

```
Power Manager
```

```
0x0c
```

```
0x0e
```

```
XBUS IO
```

```
0x0a
```

```
0x0b
```

```
Fabric Controller 1
```

```
0x09
```

```
0x0b
```

```
WARNING: Upgrade process could take up to 15 minutes.
```

```
Module 8 will be powered down now!!
```

```
Do you want to continue (y/n) ?y
```

```
-
```

```
Module 8 EPLD upgrade is successful
```



Note

When a Fabric 2 Module is present on the switch, the Fabric Controller 2 epld will be upgraded and the output will display Fabric Controller 2 and its current and new versions.

Send documentation comments to mdsfeedback-doc@cisco.com.

Upgrading the Power Management EPLD Nondisruptively

To upgrade the Power Management EPLD on supervisor modules in a nondisruptive manner, follow these steps:

-
- Step 1** Upgrade the Power Management EPLD on the standby supervisor module. From the active supervisor module, enter the **install module x epld bootflash: epld_image_file_x_x_x** CLI command.
- After the EPLD upgrade is complete, the standby supervisor module will reboot.
- Step 2** When the standby Supervisor module is online, physically remove the standby supervisor module and reinstall it.
- The standby supervisor module will come up with the new Power Management EPLD version.
- Step 3** After the standby supervisor module comes online, perform a switchover and wait till the new standby supervisor module comes online.
- Step 4** From the active supervisor module, repeat steps 1 through 3.
-

Installing or Upgrading Clock Module EPLDs

Use the **install clock-module epld url** command on the active supervisor module to upgrade EPLD images for the clock modules. After upgrading the clock modules, power cycle the entire chassis for the change to take effect. Rebooting the chassis is not enough for the changes to take effect; you must turn off and turn on the chassis.

Example 6 Upgrading Clock Module EPLDs

```
switch# install clock-module epld bootflash:m9000-epld-3.2.1.img
```

```
Len 3184500, CS 0x04, string MDS series EPLD image, built on Thu Jul 19 16:50:07 2007
```

```
EPLD                               Curr Ver    New Ver
-----
Clock Controller                   0x03       0x05
There are some newer versions of EPLDs in the image!
Do you want to continue (y/n) ? y
```

```
Proceeding to program Clock Module B.
```

```
Do you want to switchover Clock Modules after programming Clock Module B.
System Will Reset! y/n) ?n
|
Clock Module B EPLD upgrade is successful.
```

A Cisco MDS 9513 Director switch has two clock modules that can be upgraded. The EPLD upgrade utility only upgrades the standby clock module. You can check to see which clock module is in standby mode by entering the **show environment** command.

Example 7 Upgrading standby clock module

```
switch# show environment
Clock:
```

```
-----
Clock          Model          Hw          Status
```

Send documentation comments to mdsfeedback-doc@cisco.com.

```
-----
A          DS-C9513-CL          0.101      Ok/Standby
B          DS-C9513-CL          0.101      Ok/Active
```

During the upgrade of the standby clock module the EPLD upgrade prompts you for the switchover of the clock modules. If you choose to allow the clock module switchover, the switch will reboot. After the switch reboots, enter the **show environment** command to verify that the previous active clock module is now the standby clock module. You can continue to upgrade the new standby clock module and allow a clock switchover to return the clock modules to their previous active and standby states.

Guidelines and Limitations

When you upgrade or downgrade the EPLDs, observe the following guidelines and limitations:

- You can upgrade each module individually that is online. The EPLD upgrade is only disruptive to the module being upgraded.
- If you interrupt an upgrade, the module must be upgraded again.
- The upgrade or downgrade can only be executed from the active supervisor module. While the active supervisor module cannot be upgraded, you can upgrade the other modules individually.
- In Cisco MDS 9100 Series fabric switches, be sure to specify one (1) as the module number.
- EPLD upgrades are not allowed for the following modules in slot 2 of the Cisco MDS 9222i Multiservice Modular Switch:
 - MDS 9000 8-port IP Storage Services Module
 - MDS 9000 32-port Fibre Channel Storage Services Module (SSM)

EPLD Support Matrix

Table 1 lists the EPLD images and the Cisco modules they support.

Table 1 *EPLD Support Matrix*

Cisco MDS 9000 EPLD Image Versions												
Cisco MDS 9000 Modules	5.2.1	5.0.4 and later versions	5.0.1a and later versions	4.2.7a	4.1.3, 4.1.1a, and later versions	3.3.5a,	3.3.2, 3.2.2c, 3.2.1	3.1.1	3.0.1	2.1.2	2.0.1b	1.2.1a
Supervisor-2A module	X	X		X		X						
Supervisor-2 module	X	X	X	X	X	X	X	X	X			
Supervisor-1 module					X ¹	X	X	X	X	X	X	X

Send documentation comments to mdsfeedback-doc@cisco.com.

Table 1 *EPLD Support Matrix (continued)*

Cisco MDS 9000 EPLD Image Versions												
Cisco MDS 9000 Modules	5.2.1	5.0.4 and later versions	5.0.1a and later versions	4.2.7a	4.1.3, 4.1.1a, and later versions	3.3.5a,	3.3.2, 3.2.2c, 3.2.1	3.1.1	3.0.1	2.1.2	2.0.1b	1.2.1a
Cisco MDS 9513 external crossbar module	X	X	X	X	X	X	X	X	X			
Cisco MDS 9513 clock module	X	X	X	X	X	X	X	X	X			
48-port 4-Gbps Fibre Channel switching module	X	X	X	X	X	X	X	X	X			
24-port 4-Gbps Fibre Channel switching module	X	X	X	X	X	X	X	X	X			
12-port 4-Gbps Fibre Channel switching module	X	X	X	X	X	X	X	X	X			
4-port 10-Gbps Fibre Channel switching module	X	X	X	X	X	X	X	X	X			
32-Port Fibre Channel Storage Services Module (SSM)				X	X	X	X	X	X	X		

Send documentation comments to mdsfeedback-doc@cisco.com.

Table 1 EPLD Support Matrix (continued)

Cisco MDS 9000 EPLD Image Versions												
Cisco MDS 9000 Modules	5.2.1	5.0.4 and later versions	5.0.1a and later versions	4.2.7a	4.1.3, 4.1.1a, and later versions	3.3.5a,	3.3.2, 3.2.2c, 3.2.1	3.1.1	3.0.1	2.1.2	2.0.1b	1.2.1a
8-port Gigabit Ethernet IP Storage Services module					X ¹	X	X	X	X	X	X	
4-port Gigabit Ethernet IP Storage Services module					X ¹	X	X	X	X	X	X	
14-port Fibre Channel/ 2-port Gigabit Ethernet Multiprotocol Services (MPS-14/2) module				X	X	X	X	X	X	X	X	
32-Port Fibre Channel Advanced Services Module (ASM)					X	X	X	X	X	X	X	
Caching Services Module (CSM)					X	X	X	X	X	X	X	

Send documentation comments to mdsfeedback-doc@cisco.com.

Table 1 *EPLD Support Matrix (continued)*

Cisco MDS 9000 EPLD Image Versions												
Cisco MDS 9000 Modules	5.2.1	5.0.4 and later versions	5.0.1a and later versions	4.2.7a	4.1.3, 4.1.1a, and later versions	3.3.5a,	3.3.2, 3.2.2c, 3.2.1	3.1.1	3.0.1	2.1.2	2.0.1b	1.2.1a
32-Port 1-Gbps/2-Gbps Fibre Channel Switching Module				X	X		X	X	X	X	X	X
16-Port 1-Gbps/2-Gbps Fibre Channel Switching Module				X	X	X	X	X	X	X	X	X
Cisco MDS 9124 Fabric Switch	X	X	X	X	X	X	X	X				
Cisco Fabric Switch for HP c-Class BladeSystem	X	X	X	X	X	X	X	X				
Cisco Fabric Switch for IBM BladeCenter	X	X	X	X	X	X	X	X				
Cisco MDS 9134 Fabric Switch	X	X	X	X	X	X	X					
Cisco MDS 9148 Fabric Switch	X	X	X									

Send documentation comments to mdsfeedback-doc@cisco.com.

Table 1 EPLD Support Matrix (continued)

Cisco MDS 9000 EPLD Image Versions												
Cisco MDS 9000 Modules	5.2.1	5.0.4 and later versions	5.0.1a and later versions	4.2.7a	4.1.3, 4.1.1a, and later versions	3.3.5a,	3.3.2, 3.2.2c, 3.2.1	3.1.1	3.0.1	2.1.2	2.0.1b	1.2.1a
18-port Fibre Channel/ 4-port Gigabit Ethernet Multiservice Module (MSM-18/4)	X	X	X	X	X		X					
MDS 9222i Multiservice Switch	X	X	X	X	X	X	X					
48-port 8-Gbps Fibre Channel module	X	X	X	X	X							
4/44-port 8-Gbps Host-Optimized Fibre Channel module	X	X	X	X	X							
24-port 8-Gbps Fibre Channel module	X	X	X		X							
16-Port Storage Services Node (SSN-16)	X	X	X	X	X							
8-port FCoE Module	X											

Send documentation comments to mdsfeedback-doc@cisco.com.

Table 1 *EPLD Support Matrix (continued)*

Cisco MDS 9000 EPLD Image Versions												
Cisco MDS 9000 Modules	5.2.1	5.0.4 and later versions	5.0.1a and later versions	4.2.7a	4.1.3, 4.1.1a, and later versions	3.3.5a,	3.3.2, 3.2.2c, 3.2.1	3.1.1	3.0.1	2.1.2	2.0.1b	1.2.1a
48-port 8-Gbps Advanced Fibre Channel module	X											
32-port 8-Gbps Advanced Fibre Channel module	X											

1. NX-OS 4.x does not support the following modules: the Supervisor-1 module, the 8-port Gigabit Ethernet IP Storage Services module, and the 4-port Gigabit Ethernet IP Storage Services module. Even so, the m9000-epld-4.1.3.img and the m9000-epld-4.1.1a.img contain an EPLD version for these modules. If you wish to use these modules with the newest EPLD version, upgrade to SAN-OS 3.3(2) or higher and its corresponding EPLD image. The EPLD image for SAN-OS 3.3(2) and higher is kept up-to-date with the newest EPLD versions available in NX-OS 4.x.

Table 2 shows the NX-OS and SAN-OS releases that are compatible with specific EPLD images.

Table 2 *Release Compatibility Matrix*

SAN-OS or NX-OS Release	EPLD Image
NX-OS 5.2(1)	m9000-epld-5.2.1.img
NX-OS 5.0(4)	m9000-epld-5.0.4.img
NX-OS 5.0(1a)	m9000-epld-5.0.1a.img
NX-OS 4.2(7a)	m9000-epld-4.2.7a.img
NX-OS 4.2(3)	m9000-epld-4.1.3.img
NX-OS 4.2(1b)	m9000-epld-4.1.3.img
NX-OS 4.2(1a)	m9000-epld-4.1.3.img
NX-OS 4.1(3a)	m9000-epld-4.1.3.img
NX-OS 4.1(3)	m9000-epld-4.1.3.img
NX-OS 4.1(1c)	m9000-epld-4.1.1a.img
NX-OS 4.1(1b)	m9000-epld-4.1.1a.img
SAN-OS 3.3(5a)	m9000-epld-3.3.5a.img
SAN-OS 3.3(3)	m9000-epld-3.3.2.img
SAN-OS 3.3(2)	m9000-epld-3.3.2.img

Send documentation comments to mdsfeedback-doc@cisco.com.

Table 2 **Release Compatibility Matrix (continued)**

SAN-OS or NX-OS Release	EPLD Image
SAN-OS 3.3(1c) SAN-OS 3.2(3a) SAN-OS 3.2(2c)	m9000-epld-3.2.2c.img
SAN-OS 3.2(1a)	m9000-epld-3.2.1.img

Related Documentation

The documentation set for the Cisco MDS 9000 Family includes the following documents. To find a document online, use the Cisco MDS NX-OS Documentation Locator at:

http://www.cisco.com/en/US/docs/storage/san_switches/mds9000/roadmaps/doclocator.htm

Related Documentation

The documentation set for the Cisco MDS 9000 Family includes the following documents. To find a document online, use the Cisco MDS NX-OS Documentation Locator at:

http://www.cisco.com/en/US/docs/storage/san_switches/mds9000/roadmaps/doclocator.htm

Release Notes

- *Cisco MDS 9000 Family Release Notes for Cisco MDS NX-OS Releases*
- *Cisco MDS 9000 Family Release Notes for MDS SAN-OS Releases*
- *Cisco MDS 9000 Family Release Notes for Cisco MDS 9000 EPLD Images*
- *Cisco DCNM Release Notes*

Regulatory Compliance and Safety Information

- *Regulatory Compliance and Safety Information for the Cisco MDS 9000 Family*

Compatibility Information

- *Cisco Data Center Interoperability Support Matrix*
- *Cisco DCNM Release Compatibility Matrix*
- *Cisco MDS 9000 NX-OS Hardware and Software Compatibility Information and Feature Lists*
- *Cisco MDS 9000 Family Switch-to-Switch Interoperability Configuration Guide*

[Send documentation comments to mdsfeedback-doc@cisco.com.](mailto:mdsfeedback-doc@cisco.com)

Hardware Installation

- *Cisco MDS 9500 Series Hardware Installation Guide*
- *Cisco MDS 9200 Series Hardware Installation Guide*
- *Cisco MDS 9100 Series Hardware Installation Guide*
- *Cisco MDS 9124 and Cisco MDS 9134 Multilayer Fabric Switch Quick Start Guide*

Software Installation and Upgrade

- *Cisco MDS 9000 NX-OS Software Upgrade and Downgrade Guide*

Cisco NX-OS

- *Cisco MDS 9000 Family NX-OS Licensing Guide*
- *Cisco MDS 9000 Family NX-OS Fundamentals Configuration Guide*
- *Cisco MDS 9000 Family NX-OS Interfaces Configuration Guide*
- *Cisco MDS 9000 Family NX-OS Fabric Configuration Guide*
- *Cisco MDS 9000 Family NX-OS Quality of Service Configuration Guide*
- *Cisco MDS 9000 Family NX-OS Security Configuration Guide*
- *Cisco MDS 9000 Family NX-OS IP Services Configuration Guide*
- *Cisco MDS 9000 Family NX-OS Intelligent Storage Services Configuration Guide*
- *Cisco MDS 9000 Family NX-OS High Availability and Redundancy Configuration Guide*
- *Cisco MDS 9000 Family NX-OS Inter-VSAN Routing Configuration Guide*
- *Cisco MDS 9000 Family Cookbook for Cisco MDS SAN-OS*

Cisco DCNM-SAN

- *Cisco DCNM Fundamentals Guide, Release 5.x*
- *System Management Configuration Guide, Cisco DCNM for SAN, Release 5.x*
- *Interfaces Configuration Guide, Cisco DCNM for SAN, Release 5.x*
- *Fabric Configuration Guide, Cisco DCNM for SAN, Release 5.x*
- *Quality of Service Configuration Guide, Cisco DCNM for SAN, Release 5.x*
- *Security Configuration Guide, Cisco DCNM for SAN, Release 5.x*
- *IP Services Configuration Guide, Cisco DCNM for SAN, Release 5.x*
- *Intelligent Storage Services Configuration Guide, Cisco DCNM for SAN, Release 5.x*
- *High Availability and Redundancy Configuration Guide, Cisco DCNM for SAN, Release 5.x*
- *Inter-VSAN Routing Configuration Guide, Cisco DCNM for SAN, Release 5.x*
- *SMI-S and Web Services Programming Guide, Cisco DCNM for SAN, Release 5.x*

Send documentation comments to mdsfeedback-doc@cisco.com.

Command-Line Interface

- *Cisco MDS 9000 Family Command Reference*

Intelligent Storage Networking Services Configuration Guides

- *Cisco MDS 9000 Family I/O Acceleration Configuration Guide*
- *Cisco MDS 9000 Family SANTap Deployment Guide*
- *Cisco MDS 9000 Family Data Mobility Manager Configuration Guide*
- *Cisco MDS 9000 Family Storage Media Encryption Configuration Guide*

Troubleshooting and Reference

- *Cisco MDS 9000 Family and Nexus 7000 Series System Messages Reference*
- *Cisco MDS 9000 Family SAN-OS Troubleshooting Guide*
- *Cisco MDS 9000 Family NX-OS MIB Quick Reference*
- *Cisco DCNM for SAN Database Schema Reference*

Send documentation comments to mdsfeedback-doc@cisco.com.

Obtaining Documentation, Obtaining Support, and Security Guidelines

For information on obtaining documentation, obtaining support, providing documentation feedback, security guidelines, and also recommended aliases and general Cisco documents, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at: <http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

This document is to be used in conjunction with the documents listed in the “[Related Documentation](#)” section.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Copyright © 2003 - 2011 Cisco Systems, Inc. All rights reserved.