

Send comments to nexus5k-docfeedback@cisco.com



D Commands

This chapter describes the Cisco NX-OS FabricPath commands that begin with D.

Send comments to nexus5k-docfeedback@cisco.com

description (FabricPath)

To configure the topology description, use the **description** command.

description *desc*

no description *desc*

Syntax Description	<i>desc</i> Line description. The maximum size is 80 bytes.	
Command Default	None	
Command Modes	Global configuration mode	
Command History	Release	Modification
	5.1(3)N1(1)	This command was introduced.
Usage Guidelines	This command requires an Enhanced Layer 2 license.	
Examples	This example shows how to configure the topology description: <pre>switch# configure terminal switch#(config)# description FabricPath Topology 50 Configuration switch#(config)#</pre>	
Related Commands	Command	Description
	fabricpath domain default	Enables FabricPath Layer 2 IS-IS.