



# V Commands

---

This chapter describes the Cisco NX-OS FabricPath commands that begin with V.

# vlan

To configure fabricpath Operation, Maintenance, Administration (OAM) VLAN, use the **vlan** command in fabricpath OAM profile configuration mode. To remove the VLAN information, use the **no** form of this command.

**vlan** *vlan-id*

**no vlan**

## Syntax Description

<i>vlan-id</i>	An integer. The range is from 1 to 3967.
----------------	--

## Command Default

The fabricpath OAM VLAN is not configured.

## Command Modes

Fabricpath oam profile (config-fb-oam-profile)

## Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

## Examples

This example shows how to configure a VLAN:

```
switch# configure terminal
Enter configuration commands, one per line. End with CNTL/Z.
switch(config)# fabricpath oam profile 100
switch(config-fp-oam-profile)# vlan 100
```

## Related Commands

Command	Description
---------	-------------