



D Commands

This chapter describes the Cisco NX-OS FabricPath commands that begin with D.

description (FabricPath)

To configure the topology description, use the **description** command.

description *desc*

no description *desc*

Syntax Description	<i>desc</i>	Line description. The maximum size is 80 bytes.
---------------------------	-------------	---

Command Default	None	
------------------------	------	--

Command Modes	Global configuration mode	
----------------------	---------------------------	--

Command History	Release	Modification
	5.2(1)N1(1)	This command was introduced.

Usage Guidelines	This command requires an Enhanced Layer 2 license.	
-------------------------	--	--

Examples	This example shows how to configure the topology description: switch# configure terminal switch#(config) fabricpath topology 50 switch#(config-fp-topology) # description FabricPath Topology 50 Configuration	
-----------------	--	--

Related Commands	Command	Description
	fabricpath domain default	Enables FabricPath Layer 2 IS-IS.