



D Commands

This chapter describes the Cisco NX-OS FabricPath commands that begin with D.

description (FabricPath)

To configure the topology description, use the **description** command.

description *desc*

no description *desc*

Syntax Description

<i>desc</i>	Line description. The maximum size is 80 bytes.
-------------	---

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

This command requires an Enhanced Layer 2 license.

Examples

This example shows how to configure the topology description:

```
switch# configure terminal
switch#(config)# fabricpath topology 50
switch#(config-fp-topology)# description FabricPath Topology 50 Configuration
```

Related Commands

Command	Description
fabricpath domain default	Enables FabricPath Layer 2 IS-IS.