

Software version TC5.0
November 2011

EX90

User guide



What's in this guide?

The top menu bar and the entries in the Table of Contents are all hyperlinks. Just click on them to go to the topic.

We recommend that you visit the Cisco web site regularly for updated versions of this guide. Go to: <http://www.cisco.com>

Introduction

Introduction	4
--------------------	---

Connecting the EX90

Rear sockets access	7
The EX90 parts	7
Connecting	7
Connecting for use as PC screen	7
Connecting a PC to the unit	8
Use as PC screen	8
Setting the screen resolution	8
Using an external monitor to show presentations ..	8

Using the EX90

Camera adjustments	10
Use as document camera	10
Touch controller—initial view	11
Initial settings—before you begin	12
Searching for an entry in any of the lists	14
Calling an entry in any of the lists	15
Two calls at the same time	16
Two calls at the same time	16
Transferring calls	17
Calling participants to set up a Multisite call	18
Adding participants to an ongoing call (Multisite) ..	19
Layout control in MultiSite	20
Adding participants to an ongoing call (Multiway) ..	21
History	22
Searching	22
Directory	22
Favorites	22
Do not disturb	23
Using Touch Tones (DTMF)	23
Far end camera control	23
Sharing contents—conducting presentations	24

Scheduled meetings

Looking into the List of Meetings	26
Joining a Meeting	27
Joining while already in a call	27
Parallel meetings	27
Extending an ongoing meeting	27

The Settings using Touch

Setting the EX90 in standby	29
Shutting down the EX90	29
Reverting to factory default settings	29
Gaining access to the Settings	30
System Information	31
Call Status	32
Language	33
Camera Control and Settings	34
Display Settings	35
Ringtone & Sound Settings	36
Background	37
Administrator Settings—Date, Time & Location	38
Administrator Settings—Call Settings	39
Administrator Settings—IP Settings	40
Administrator Settings—H.323 Settings	41
Administrator Settings—SIP Settings	42
Administrator Settings—Provisioning	43
Administrator Settings—Multiway	44
Administrator Settings—Web Snapshots	45
Administrator Settings—EMC Resilience Mode	46
Administrator Settings—Factory Reset	47
Restart System	48



Chapter 1

Introduction

Introduction

The objective of this documentation is to provide the reader with assistance in using and configuring the product. The specifications for the product and the information in this Guide are subject to change at any time, without notice, by Cisco. Every effort has been made to supply complete and accurate information in this Guide; however, Cisco assumes no responsibility or liability for any errors or inaccuracies that may appear in this document.


All trademarks used in this document are the property of their respective holders.

This Guide may be reproduced in its entirety, including all copyright and intellectual property notices, in limited quantities in connection with the use of this product. Except for the limited exception set forth in the previous sentence, no part of this Guide may be reproduced, stored in a retrieval system, or transmitted, in any form, or by any means, electronically, mechanically, by photocopying, or otherwise, without the prior written permission of Cisco.

The following photographers have contributed:

Anette Linnea Rasmussen
Alex Bramwell
Stephen Coburn
Eric Gevaert
Stephen Coburn
Stocksnapper
Yurok Aleksandrovich
ordus
Sven Taubert
Bas Meelker
Paylessimages
Vilnis

This unit makes use of photos provided by Fotolia. These photos are Copyright © Fotolia.





Chapter 2

Connecting the EX90

Connecting the EX90


Connect the cables as shown. Sockets are located behind the rear cover. If you have one LAN connection only—and need that for your PC—the EX90 has a built in Gigabit ethernet switch that enables you to connect your PC to the EX90 to access the LAN through the EX90.

Rear sockets access

Remove cover to get access to the connector sockets.

The cover is vented in the lower left corner (external view) due to the rear mounted loudspeaker.

When mounting the cover back on, make sure the vents are where the speaker is (as shown).



The EX90 parts


Camera with built-in privacy shutter.



The Cisco TelePresence touch screen controller



Connecting




- 1 Connect your PC here if you need to share a single LAN connection with the EX90.
- 2 Connect your EX90 to the LAN.
- 3 USB socket (for future use).
- 4 Connect the touch screen controller.
- 5 HDMI In (inner socket) and HDMI Out* (outer socket).
- 6 Connect power here.

* HDMI out is used when connecting an extra monitor (typically for presentations)—see the next page for more.

Connecting for use as PC screen

Your EX90 has an HD display, which also may serve as your PC screen.

Connect your PC to the sockets on the rear panel as shown below.



Connect your PC video to 1 and PC audio to 2

A resolution of 1920 × 1200 is recommended. For a list of other screen resolutions supported, see “Setting the screen resolution” on page 9.

Connecting a PC to the unit

Your EX90 has an HD display, which also may serve as your PC screen. Connect your PC to the sockets on the rear panel as shown below. For optimal PC image quality, digital output (DVI) from the PC is recommended. If both DVI and HDMI are connected, a **Source** button appears in the setup menu on the touch screen to let you select which source to use as PC screen.



Connect your PC video to ① and PC audio to ②

Use as PC screen

Your EX90 has an HD display, which also may serve as your PC screen. Connect your PC to the sockets on the rear panel as shown above.

Your EX90 will serve as your PC screen outside calls. In a call tap **Presentation** to view your desktop. Your desktop is not exposed to the other side before you press **Present**.

Setting the screen resolution

A resolution of 1920 × 1200 is recommended. However, other resolutions may also be used as shown in the below tables.

Digital input via DVI

1920 × 1200 (recommended)
1920 × 1080
1776 × 1000 (not full screen)
1680 × 1050
1600 × 1200 (not full screen)
1440 × 900
1400 × 1050 (not full screen)
1280 × 1024 (not full screen)
1280 × 960 (not full screen)
1280 × 800
1280 × 768 (not full screen)
1280 × 720 (not full screen)
1152 × 648 (not full screen)
1024 × 768 (not full screen)
960 × 600 (not full screen)
800 × 600 (not full screen)

Analog input via DVI

1920 × 1200 (recommended)

1680 × 1050
1600 × 1200 (not full screen)
1440 × 900

1280 × 1024 (not full screen)

1024 × 768 (not full screen)

800 × 600 (not full screen)

Screen resolution must be set via the web interface, using the **Video Output HDMI [1] Resolution** setting. For details on this, see the EX90 Administrator Guide, which is available separately for download.

Using an external monitor to show presentations

You may connect an external monitor to your EX90 to have it work with two monitors at the same time. The second monitor can be configured to show presentations instead of having everything on a single screen.

To enable the use of a second monitor the system must be configured for it.

This is done via the web interface using the **Video DefaultPresentationSource** setting. Doing so is described in the EX90 Administrator Guide which is available separately for download .



Chapter 3

Using the EX90

Camera adjustments

The camera can be tilted mechanically in vertical direction.



Turn the circumference to activate the privacy shutter.




Use as document camera

Tilt the camera as shown to use it as a document camera. Image is automatically turned upside down, so that both parties will see the document correctly.



Touch controller—initial view



Initial settings—before you begin

1


Tap **Selfview** to see what others will see of you.

2



Tilt the camera to obtain the best view. The best view will be the view that positions your face as high up on the screen as possible without cutting off the top of your head.

3






If you need to adjust the camera, tap **Camera Control**.

Entering **Camera Control** will also cause the EX90 to show selfview, so if you know that camera adjustments are needed, you do not have to activate selfview first.




4






Adjust zoom and focus as required. Tap **Back** to exit menu.



Searching for an entry in any of the lists




Calling an entry in any of the lists







Favorites. The list of favorites is your own shortlist of people and places you frequently call or otherwise want to have easy access to.

Directory. The directory serves as your corporate phone book. This directory cannot be edited by you. You may, however, copy entries to your list of favorites and edit them there.

History lists the received, placed and missed calls since the last time the list was cleared.

Keypad. Tap the keypad icon  to produce the keypad to enter a number or URI.

Two calls at the same time



If your EX90 is equipped with the optional MultiSite feature you may also set up a video conference with three participants and yourself. See "Calling more than one" on page 18.

Click on the person you currently talk to (here **Peer Gynt**) to terminate or transfer that call.

Transferring calls

1




In a SIP call tap the name along the bottom line of the screen.

2




... then tap **Transfer**...

3



Now, tap **Contacts** to gain access to the call lists and dial field.

4



Call the person to whom the current call shall be transferred. When you tap the green call button (not shown), the call will be transferred.

5

The call will now be transferred. This will work irrespective of who initiated the call.

Note that you may combine **Transfer** with the **Hold** and **Swap** features as much as you want.

This means, for example, that in a call you may:


- Put your current call on hold and call a second party.
- Then initiate a transfer of the one on hold to the second party.
- You may now disengage yourself by tapping **END** on your unit.

Calling participants to set up a Multisite call


Calling more than one using Multisite is an optional feature that may, or may not, be present on your system. If in doubt, ask your System Administrator.




Enter a name, number or address, or pick an entry from the **Directory**, the list of **Favorites**, or from the **History**.




Tap **Add Participant**



The entry will appear on the bottom line of the touch pad, as outlined.



Repeat the procedure to add a second participant.



When both have been added, tap **START** to call them all.




Tap **END** to terminate the entire conference. To disconnect just one of the participants, tap the participant's name along the bottom line and then tap **END**.

Adding participants to an ongoing call (Multisite)

Calling more than one using Multisite is an optional feature that may, or may not, be present on your system. If in doubt, ask your System Administrator.




While in a call you may add another participant, provided that your system permits to do so. Tap **Add** ...



... then select, in the usual way, whom to add to the ongoing call.



Once you have selected someone, the **ADD TO MEETING** dialog box will be produced ...



... now, tap **ADD TO MEETING** to include this participant in the meeting.



Tap **END** to terminate the entire conference. To disconnect just one of the participants, tap the participant's name along the bottom line and then tap **END**.

Layout control in MultiSite

1



If you are in a MultiSite call or in a Point-to-point call with a presentation, you may alter the layout on the screen. To do this start by tapping **More** ...

2



... then tap **Layout** ...

3



... and finally select your preferred layout.



Takes you one menu level back

The one who speaks get the full screen. Nothing else is shown.

The one who speaks gets the main frame. The others are shown as PiP (Picture in Picture).

The one who speaks gets the main frame. The others are shown as images below the main frame.

All participants are shown in frames of identical sizes.

When a presentation is included in a call, all participants will be shown **above** the presentation instead of below. This will provide a better feeling of eye contact. Full screen will show the presentation only.

Adding participants to an ongoing call (Multiway)

Calling more than one using Multiway is an optional feature that may, or may not, be present on your system. If in doubt, ask your System Administrator.




While in a call you may add participants provided that your system permits to do so. Tap **Hold** to put the ongoing call on hold...




... then select, in the usual way, whom to add to the ongoing call.



Once you have selected someone, tap **Start** to begin including this participant in the meeting.




The call will now be transferred to the Multiway server and handled from there. This may take a little while...



When everything is ready the **Join** button will appear. Tap this and the bottom line will change to read **Meeting**. This may take a little while.

Since the calls have been transferred to the Multiway server you are still in a point-to-point call, but now with the Multiway server as the far end. This applies to all the other participants as well.



Tap **END** to disconnect yourself. The other participants must do the same to disconnect from the Multiway server.

History

History lists the received, placed and missed calls since the last time the list was cleared.


Tap **History** to produce the list ...

... then tap an entry.



You will now be able to:

- Call the entry by tapping **Start**.
- Add the entry to an ongoing call (optional feature).
- Add the entry to **Favorites**.
- Edit the entry information and then place the call.
- Change the call rate settings.
- Remove the entry from the list.
- Clear the entire list. To do this, scroll as outlined beyond what appears to be the top of the list. A **Clear List** button will then appear.



Directory

The **Directory** serves as your corporate phone book. This directory cannot be edited by you. You may, however, copy entries to your list of favorites and edit them there.

Tap **Contacts** (if needed) and then tap **Directory**. The directory is typically organized as folders.



Tap a folder (1) to show its contents, scroll (2) if needed to locate a folder or an entry within a folder.

Once located, tap the entry to call, edit or add to your list of favorites in the same way as with the history list.

It may happen that an entry copied from the directory to the list of favorites later is updated in the directory. This update will not be reflected in your list of favorites—you must then manually update the entry in the list of favorites.

Favorites

Favorites is your own shortlist of contacts you frequently call or otherwise want to have easy access to.

Adding to Favorites. To add someone to the list of favorites, locate the entry in **Directory** or **History** (as outlined) and tap it (1). This will produce a dialog box which allows you to tap **Add to Favorites** (2).



You may now edit the entry, if needed—just tap a field and the keyboard will be produced. Tap **Save** to put changes into effect.



Favorites should be considered as an editable directory and is used in the same way as **History**.

Searching

You may search for entries (numbers or URIs). Searches will be conducted within all the folders, i.e. within the **Favorites**, the **Directory** and the **History**.

Tap in the **Search or Dial** field and key in the name, URI or number. Matches will appear as you search.

Once located, tap the entry to call, edit or add to **Favorites**.




When searching within the corporate **Directory**, the search will apply to the current directory folder and its subfolders only. To go one level up, tap **Back**. To make the search apply to the entire corporate directory, do not enter (tap) any folder before the search is commenced.

Do not disturb

When set to **Do Not Disturb** (DND), ringtones are muted and missed calls you get while having DND active, will be presented when you exit DND..

You may, however, place calls as much as you like. To activate this feature, press the icon in the upper left corner. Press again to deactivate.



You may also hide the Do Not Disturb poster by tapping **Hide**.

Using Touch Tones (DTMF)

Sometimes you may be urged to enter touch tones (DTMF) during a call, typically to reach extensions or to provide a pin code.



In a call, tap **Touch Tones**

Use the touch tone keypad. Tap anywhere outside it to exit.



Far end camera control

If the other end point permits it, you may control their camera. This is known as **Far end camera control**.

If the other camera cannot be controlled, nothing happens.

This works in Point-to-point calls as well as MultiSite calls.




Tap the name, whose camera shall be controlled, along the bottom line (1) and then tap **Camera Control** (2).



Adjust zoom and pan as required (1). Tap **Back** to exit the menu (2).

Sharing contents—conducting presentations


1



You may share contents while in a call. The EX90 accepts two sources—via DVI and via HDMI.

Note! You must be in a call to be able to share contents. Your presentation source must be powered and active as well as connected. Otherwise the **Presentation** icon (button) will fail to appear.

2



Once you are in a call—and the presentation source is connected, powered and active—the **Presentation** icon (button) will appear.

In a call tap **Presentation** ...

3



... then tap **PRESENT** to start sharing contents.

4



Tap **STOP PRESENTING** to stop sharing contents.

If you have two sources connected, you will be presented with the possibility to swap between these at any time.



Chapter 4


Scheduled meetings

Looking into the List of Meetings

The features shown on this page are all optional and may—or may not—be available for your system.



Tap **Meetings** to display the list of upcoming meetings on this endpoint...




The List of Meetings contains 14 days of scheduled meetings. The list is sorted using Grouping headers. The main grouping category is by day (eg: Today, Tomorrow, Thursday, then WEDNESDAY, October 26, 2011).



On your video system a Meeting reminder will appear at the top of the List of Meetings once it is possible to join a meeting. Exactly when that is will depend on the Start time buffer setting. Default buffer setting is 10 minutes.



If you tap an item in the list (1) then more information will become available. When the **JOIN MEETING** button is gray (as shown here) you are outside the time window permitting you to join the meeting. Tap as outlined (2) to expand the dialog box to get more information.




The dialog box will also state when it is possible to join the meeting. Tap as outlined to collapse the dialog box.

When a scheduled meeting appears as *Private meeting* it will contain information about the organizer only. There will be no title, no expandable meeting outline as well as no dial-in information.

Joining a Meeting


The features shown on this page are all optional and may—or may not—be available for your system.



When a scheduled meeting is about to start a reminder will appear. To join the meeting tap **JOIN MEETING** (1), as outlined. This connects you to the “dial-in” address.


The meeting title field is expandable—tap as shown (2).

The expanded field contains meeting details and dial-in information. Depending on the amount of information it may be scrollable.



Besides joining the meeting, you may tap **Snooze** to temporarily hide the Reminder for 5 minutes or **Dismiss** to close the Reminder.


Joining while already in a call



If you already are in a call, the **JOIN MEETING** button will change to **JOIN & END CURRENT**.


- Tap the **JOIN & END CURRENT** button to join the new meeting, ending the current.
- Tap **Join & Hold Current** to temporarily join the meeting.
- Tap **Snooze** to temporarily hide the Reminder for 5 minutes.
- Tap **Dismiss** to go on with your current meeting.

Parallel meetings



When Parallel Meetings occur (two or more meetings taking place simultaneously), the reminder will be displayed in context of the meeting list, displaying all upcoming meetings. Choose which meeting to join and then join the selected meeting.

Extending an ongoing meeting



Scheduled meetings have a fixed start and end time. You may want to extend an ongoing meeting. This will be accepted by the system provided that no other meeting is scheduled for the video system during the period of extension.

If an extension is sustainable, the **Meeting will end** notification will include an **Extend** and a **Dismiss** option.

- To extend a meeting, tap the **Extend** button.




The EX90 can be configured via the touch screen controller or via its web interface. For full access to all configurable parameters the web interface must be used—the touch screen controller provides access to a limited set of parameters only.

Chapter 4

The Settings using Touch

Setting the EX90 in standby

Outside a call, you may have the unit enter standby mode by touching the **Power** button on the main unit (the screen). The *Standby* dialog is displayed and the unit enters standby immediately. This does not work when you are in a call.



Tap as shown to wake up the system from standby.

Reverting to factory default settings


To revert to the factory default settings, do as follows:

1. Disconnect the power cord.
2. Reconnect the power cord—a green light will illuminate shortly after.
3. Press the **Power** button as soon as the green light appears. Keep it depressed for 15 seconds or so, until the green light starts flashing.
4. Release the button and press twice within 2 seconds. All settings will now revert to factory default settings.

Shutting down the EX90

Outside a call, press the **Power** button until the *Shutdown progress bar* is filled completely.

Release the button and the unit will go in shutdown in just a few seconds.




To start the system again, press the **Power** button until the LED illuminates (green light).

Gaining access to the Settings

Access the Settings as follows:



Tap **More** followed
by **Settings** ...



... and then you get access to the settings available. Observe that there are several other settings available, but these can be accessed from the web interface only. See the Administrator guide for your Cisco product. This guide is available for download separately.

System Information

The **System information** provides all the system information at a glance.

Scroll down to also see status on video inputs (DVI and HDMI).

Settings		Exit
System Information	System Name: <input type="text" value="Cisco TelePresence EX90"/>	
Call Status	Uptime: 3 hours, 8 minutes	
Language	NETWORK	
Camera Control & Settings	IPv4 Address: <input type="text" value="192.168.1.100"/>	
Display Settings	IPv6 Address: <input type="text" value=":::"/>	
Ringtone & Sound Settings	H323	
Background	Number: <input type="text" value="12345678"/>	
Administrator Settings	ID: <input type="text" value="12345678901234567890"/>	
Restart	Gatekeeper: <input type="text" value="192.168.1.100"/>	
	Status: Registered	
	SIP	
	Address: <input type="text" value="192.168.1.100"/>	
	Proxy: <input type="text" value="192.168.1.100"/>	
	Status: Registered. Secured. Not verified.	
	SOFTWARE	
	Version: TC5.0.0.0	
	Touch Screen: TT3.0.0.0	
	Options Installed: MultiSite, PremiumResolution	
	HARDWARE	

Call Status

The **Call Status** pane provides in-call information on such things as call rate and frame rate, protocols used, packet loss and jitter.

Settings

Exit

System Information

Call Status

Language

Camera Control & Settings

Display Settings

Ringtone & Sound Settings

Background

Administrator Settings

Restart

Remote URI:

Call Rate: n/aEncryption Type: n/a

Protocol: n/aEncryption Status: n/a

VIDEO

TransmitPresentationReceivePresentation

Protocol: n/a n/a n/a n/a

Resolution: n/a n/a n/a n/a

Frame Rate: n/a n/a n/a n/a

Channel Rate: n/a n/a n/a n/a

Total Packet Loss (%): n/a n/a

Current Packet Loss (%): n/a n/a

Jitter: n/a n/a

AUDIO

TransmitReceive

Protocol: n/a n/a

Channel Rate: n/a n/a


Total Packet Loss (%): n/a n/a

Current Packet Loss (%): n/a n/a

Jitter: n/a n/a

Language

The **Language** pane lets you set the on-screen language to your preferred choice.




Camera Control and Settings

The **Camera Control & Settings** pane lets you set the whitebalance and exposure of the camera. If you do not want to tweak this yourself, just leave it to the system by selecting **Auto**.

Backlight compensation comes in handy when there is much light behind you. Without compensation you will easily appear very dark to the far end.

Note how the settings chosen are indicated. In the example shown, Backlight compensation is set to Off.




Display Settings

The **Display settings** let you adjust:

Preferred brightness by moving the *Brightness* slider.

The color balance. There are four preset color settings (Cold, Neutral, Warm and your own (Custom)) available. When you select Custom, you may use the Red, Green and Blue sliders to specify your own setting.

The DVI mode can be set to automatically detect the type of video signal received, or forced to analog or digital. The DVI mode is used when the unit is connected to a PC to serve as a PC monitor.



The screenshot shows the 'Settings' application interface. On the left is a sidebar menu with the following items: System Information, Call Status, Language, Camera Control & Settings, Display Settings (highlighted in light blue), Ringtone & Sound Settings, Background, Administrator Settings (with a right arrow), and Restart. The main area on the right is titled 'Settings' and contains an 'Exit' button in the top right corner. Below the title bar, the settings are organized into sections: 'Brightness (61)' with a slider from 0 to 100; 'Colors' with four tabs: Cold, Neutral (selected), Warm, and Custom; three sliders for 'Red (50)', 'Green (50)', and 'Blue (50)', each ranging from 0 to 100; and 'DVI Mode' with three tabs: Auto, Digital, and Analog.

Ringtone & Sound Settings


The **Ringtone & Sound Settings** pane lets you specify:

Keytones on or off. When set to on you will hear a sound every time you tap a field on the Touch controller.

Ringtone volume. How loud your ringtone shall sound.

Ringtone. Select among several ringtones. You will hear a sample every time you tap a ringtone.


Note how the settings chosen are indicated. In the example shown, Keytones are set to Off.



Background

The background image on the touch screen controller can be changed.

Tap one of the small images to use it as background image.




Administrator Settings—Date, Time & Location

The **Date, Time & Location** settings let you specify:

- 24h or 12h time format.
- Your preferred date format.
- Your preferred time zone.
- Whether date and time shall be set automatically or manually.

Note how the settings chosen are indicated. In the example shown, Time format is set to 24h.



The screenshot shows the 'Administrator Settings' window with the 'Date, Time & Location' tab selected. The settings are as follows:


Setting	Value
Time Format	24h (selected), 12h
Date Format	dd.mm.yy (selected), mm.dd.yy, yy.mm.dd
Time Zone	- GMT+01:00 (Amsterdam, Berlin, E) +
Date & Time Mode	Auto (selected), Manual
NTP Mode	Auto (selected), Manual
NTP Server	ntp.tandberg.com

Administrator Settings—Call Settings

The **Call Settings** pane lets you specify:

- **Auto Answer** On or Off. If you set this to **On**, the system will respond automatically to incoming calls. Note that the microphone will NOT be muted. If risk of eavesdropping is an issue, you may want to set this setting to **Off**.
- **Auto Answer Delay**. Specify the time until your system actually responds to an incoming call.
- **Default Call Rate**. If your connection has limited capacity you may want to use this setting.
- **Max Incoming/Outgoing Bandwidth**. You may specify these separately. May come in handy if you are on an asymmetric connection.
- **Default Call Protocol**. Specify which protocol to use as default.

Note how the settings chosen are indicated. In the example shown, Auto Answer is set to Off.




Administrator Settings		Exit
Date, Time & Location	Auto Answer	OFF ON
Call Settings	Auto Answer Delay	- 0s +
Network Settings >	Call Rate	
Web Snapshots	Default Call Rate	- 1152 +
EMC Resilience Mode	Max Incoming Bandwidth	- 6000 +
Reset	Max Outgoing Bandwidth	- 6000 +
	Default Call Protocol	H323 Sip

Administrator Settings—IP Settings

The **IP settings** pane lets you specify:

- The use of **DHCP** or **Static** IP addresses. If you decide to use **Static**, make sure you tap **Save** before leaving the menu.



The screenshot shows the 'Network Settings' interface with the 'IP Settings' pane selected. The interface includes a 'Back' button and an 'Exit' button. The 'IP Settings' pane contains the following fields and options:

IP Settings	
IP Version	<input type="radio"/> IPv4 <input type="radio"/> IPv6
IP Assignment	<input type="radio"/> Auto <input type="radio"/> Manual
IP Address	<input type="text" value="192.168.1.1"/>
Subnet Mask	<input type="text" value="255.255.255.0"/>
Gateway	<input type="text" value="192.168.1.1"/>
DNS Server 1	<input type="text" value="192.168.1.1"/>
DNS Server 2	<input type="text" value="192.168.1.1"/>
DNS Server 3	<input type="text"/>
DNS Domain Name	<input type="text"/>

Administrator Settings—H.323 Settings

The **H.323 Settings** pane lets you specify:


- An **H.323 alias**.
- Your **H.323 id**.
- **Gatekeeper discovery** (**Manual** or **Automatic**).
- The **Gatekeeper address** must be specified by you if discovery has been set to manual.
- **Authentication mode** **On** or **Off**. If set to **On**, the video system will send **Login name** and Password to the Gatekeeper for authentication.

In addition there are:

- Two fields to enter **Login name** and **Password**. The alphanumeric keyboard will appear whenever needed.

Be sure to:

- Tap **Save** to put changes into effect.



The screenshot shows the 'Network Settings' screen with a sidebar on the left containing the following menu items: 'IP & VLAN', 'H323 Settings' (highlighted), 'SIP Settings', 'Provisioning', and 'Multiway'. The main area is titled 'Network Settings' and includes a 'Back' button and an 'Exit' button. The settings are organized into two columns:

Setting	Value
H323 Number	[Text Field]
H323 Id	[Text Field]
Gatekeeper Discovery	Auto Manual
Gatekeeper Address	[Text Field]
Authentication Mode	OFF ON
Login Name	[Text Field]
Password	[Text Field]


Administrator Settings—SIP Settings

The **SIP settings** pane lets you specify:

- Your **URI**.
- The **Default transport layer**, this can be set to **TCP**, **UDP**, **TLS** or **Auto**.
- The **Proxy type** can be set to **Standard**, **Alcatel**, **Avaya**, **Cisco**, **Microsoft**, **Nortel**, **Experimental**, **Siemens**.
The experimental setting is for testing purposes.
- **Outbound** is not used in this version.
- **Proxy discovery** can automatic or manual. In the case of manual the proxy address must be specified by you.
- **Login name** and **Password** is required by the VCS.

Be sure to:

- Tap **Save** to put settings into effect.




The screenshot shows the 'SIP Settings' pane within the 'Network Settings' section. The left sidebar lists 'IP & VLAN', 'H323 Settings', 'SIP Settings' (highlighted), 'Provisioning', and 'Multiway'. The main area contains the following settings:

- URI:** A text input field containing a placeholder IP address.
- Default Transport:** A set of buttons for 'TCP', 'UDP', 'TLS', and 'Auto'. 'Auto' is currently selected.
- Proxy Type:** A dropdown menu showing 'Standard' with minus and plus icons for selection.
- Proxy Discovery:** A set of buttons for 'Auto' and 'Manual'. 'Auto' is currently selected.
- Proxy Address:** A text input field containing a placeholder IP address.
- Login Name:** A text input field.
- Password:** A text input field.

Administrator Settings—Provisioning

Provisioning connects you to CUCM, Callway or VCS. When either of these were ordered and received from Cisco you should also have obtained the necessary information and codes. Just follow the wizard.



Administrator Settings—Multiway

Insert the address to the Multiway server.

Back

Network Settings

Exit

IP & VLAN

H323 Settings

SIP Settings

Provisioning


Multiway

Multiway Settings

Multiway Address

Administrator Settings—Web Snapshots


Snapshots of what the video system's camera captures can be obtained from the web interface of the system, provided that the feature has been enabled on the video system.



Administrator Settings—EMC Resilience Mode


If the Touch controller is used in environments with considerable amounts of electromagnetic noise present, you may experience an appearance of false signals—as if someone tapped the Touch controller when nobody obviously did so.

To cope with this you may set the **EMC Resilience Mode** to **On**. You must then tap and hold for a little while, rather than just tap, in order to make the system aware of your tapping. This will avoid the appearance of false signals.




Administrator Settings—Factory Reset

You may want to reset your video system. Note that you will loose all configurations, the call history and your local list of contacts. Release keys and options installed will be retained.



Restart System

You may force a system restart. This will not affect your settings.



THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.



On our web site you will find an overview of the worldwide Cisco contacts.

Go to: <http://www.cisco.com/web/siteassets/contacts/index.html>

Corporate Headquarters
Ciso Systems, Inc.
170 West Tasman Dr.
San Jose, CA 95134 USA