



Hardware and Software Interoperability Matrix

This document provides interoperability matrices for Cisco Unified Computing System components and configurations that have been tested and validated by Cisco, by Cisco partners, or both. Use this document as a reference for supported hardware and software.

This document contains the following sections:

- [Audience](#)
- [Operating System Interoperability Matrix](#)
- [Converged Network Adapter Interoperability Matrix](#)
- [Host Bus Adapter Interoperability Matrix](#)
- [LAN on Motherboard Interoperability Matrix](#)
- [Network Interface Card Interoperability Matrix](#)
- [RAID Controller on Motherboard or PCIe Adapter Interoperability Matrix](#)
- [Storage Controller Interoperability Matrix](#)
- [PCIe Flash Storage Interoperability Matrix](#)
- [Graphics Processing Unit Interoperability Matrix](#)
- [PCoIP Adapter Interoperability Matrix](#)
- [Third-Party Qualified Adapters](#)
- [Related Documentation](#)
- [Obtaining Documentation and Submitting a Service Request](#)

Audience

This document is designed for use by Cisco TAC, sales, support engineers, professional service partners, and systems administrators responsible for the design and deployment of the Unified Computing System in the data center environment.

This document applies to the following C-Series Servers in the Cisco Unified Computing System, and the corresponding software releases:

Server	Software Container	HUU
C220 (SFF/LFF) M3	1.5.1f	1.5.1f
C240 (SFF/LFF) M3	1.5.1f	1.5.1f
C22/C24 (SFF) M3	1.5.1f	1.5.1f
C420 M3	1.5.1f	1.5.1f
C460 (M1 /M2) C260 M2	1.5.1f	1.5.1f
C200 M1, C200 (SFF/LFF) M2, C210 (M1 / M2) C250 (M1/M2)	1.4.3s	1.4.3s.4

The content of this document is updated on a regular basis. The current version was created on 2013-05-14.

Operating System Interoperability Matrix

Table 1 lists the operating systems that the Unified Computing System C Series Servers support.

Table 1: Operating System

UCS Server	Vendor	Operating System Version	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24M3(SFF/LFF),C420 M3	Microsoft	Windows Server 2008 R2 SP1 x64 w/Hyper-V	12
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Microsoft	Windows Server 2008 SP2 x64 w/Hyper-V	12, 18
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Microsoft	Windows Server 2012	12
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Novell	SUSE Linux Enterprise Server 11.2 64bit	

UCS Server	Vendor	Operating System Version	Notes
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Oracle	Solaris 10 8/11 (U10)	
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Oracle	Solaris 10 9/10 (U9)	
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Oracle	Solaris 11	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Oracle	Oracle Linux 5.7 64bit (Redhat Compatible Kernel)	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Oracle	Oracle Linux 5.7 64bit (Unbreakable Enterprise Kernel R1)	6, 11
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Oracle	Oracle Linux 5.8 64bit (Redhat Compatible Kernel)	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Oracle	Oracle Linux 5.8 64bit (Unbreakable Enterprise Kernel R2)	6, 11
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Oracle	Oracle Linux 5.9 64bit (Redhat Compatible Kernel)	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Oracle	Oracle Linux 5.9 64bit (Unbreakable Enterprise Kernel R2)	6, 11

UCS Server	Vendor	Operating System Version	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Oracle	Oracle Linux 6.2 64bit (Redhat Compatible Kernel)	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Oracle	Oracle Linux 6.2 64bit (Unbreakable Enterprise Kernel R2)	6, 11
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Oracle	Oracle Linux 6.3 64bit (Redhat Compatible Kernel)	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Oracle	Oracle Linux 6.3 64bit (Unbreakable Enterprise Kernel R2)	6, 11
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Oracle	Oracle VM 3.1.1	11
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Redhat	Red Hat Enterprise Linux 5.7 64bit	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Redhat	Red Hat Enterprise Linux 5.8 64bit	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Redhat	Red Hat Enterprise Linux 5.9 64bit	

UCS Server	Vendor	Operating System Version	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Redhat	Red Hat Enterprise Linux 6.2 64bit	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Redhat	Red Hat Enterprise Linux 6.3 64bit	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Redhat	Red Hat Enterprise Linux 6.4 64bit	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	VMware	VMware vSphere ESX 4.1 U2	6, 16
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	VMware	VMware vSphere ESXi 4.1 U2	13
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	VMware	VMware vSphere ESX 4.1 U3	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	VMware	VMware vSphere ESXi 4.1 U3	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	VMware	VMware vSphere ESXi 5.0	13

UCS Server	Vendor	Operating System Version	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	VMware	VMware vSphere ESXi 5.0 U1	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	VMware	VMware vSphere ESXi 5.0 U2	
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	VMware	VMware vSphere ESXi 5.1	
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Citrix	Xen Server 6.0.2	6, 11
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Citrix	Xen Server 6.1	6, 11

Converged Network Adapter Interoperability Matrix

Table 2 lists the converged network adapters that the Unified Computing System C Series Servers support.

Table 2: Converged Network Adapters

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	SUSE Linux Enterprise Server 11.2 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	Red Hat Enterprise Linux 5.8 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	Red Hat Enterprise Linux 5.9 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFFLFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	Red Hat Enterprise Linux 6.2 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFFLFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	Red Hat Enterprise Linux 6.3 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	Oracle Linux 5.8 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	Oracle Linux 5.9 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	Oracle Linux 6.3 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	VMware vSphere ESXi 4.1 U2	1.4.0.215/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13, 16

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	VMware vSphere ESX 4.1 U3	1.4.0.215/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13, 16
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	VMware vSphere ESXi 4.1 U3	1.4.0.215/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13, 16
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	VMware vSphere ESXi 5.0	1.5.0.22/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	VMware vSphere ESXi 5.0 U1	1.5.0.22/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	VMware vSphere ESXi 5.1	1.5.0.22/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	Windows Server 2008 SP2 x64 w/ Hyper-V	2.1.0.20/2.2.0.13 (NIC)	2.1(1.c)	2.1(1.c)	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	2.1.0.20/2.2.0.13 (NIC)	2.1(1.c)	2.1(1.c)	
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF)	Cisco	P81E Dual Port 10-Gbps Ethernet to PCIe Virtual Interface Card	Windows Server 2012	2.2.0.17/2.2.0.13 (NIC)	2.1(1.c)	2.1(1.c)	
C260 M2, C460 M2, C220/C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	SUSE Linux Enterprise Server 11.2 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	Red Hat Enterprise Linux 5.8 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	Red Hat Enterprise Linux 5.9 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	Red Hat Enterprise Linux 6.2 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	Red Hat Enterprise Linux 6.3 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	VMware vSphere ESXi 4.1 U2	1.4.0.215/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	VMware vSphere ESX 4.1 U3	1.4.0.215/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	6
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	VMware vSphere ESXi 4.1 U3	1.4.0.215/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF),C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	VMware vSphere ESXi 5.0	1.5.0.22/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF), C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	VMware vSphere ESXi 5.0 U1	1.5.0.22/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF), C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	VMware vSphere ESXi 5.1	1.5.0.22/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF), C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	2.1.0.20/2.2.0.13 (NIC)	2.1(1.c)	2.1(1.c)	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C240 M3 NEBS, C22/C24 M3(SFF/LFF), C420 M3	Cisco	UCS VIC 1225 10-Gbps 2 port CNA SFP+	Windows Server 2012	2.2.0.17/2.2.0.13 (NIC)	2.1(1.c)	2.1(1.c)	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Cisco	UCS VIC 1225T 10-Gbase-T 2 port CNA	SUSE Linux Enterprise Server 11.2 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C260 M2, C460 M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Cisco	UCS VIC 1225T 10-Gbase-T 2 port CNA	Red Hat Enterprise Linux 5.8 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C260 M2, C460 M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Cisco	UCS VIC 1225T 10-Gbase-T 2 port CNA	Red Hat Enterprise Linux 5.9 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C260 M2, C460 M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Cisco	UCS VIC 1225T 10-Gbase-T 2 port CNA	Red Hat Enterprise Linux 6.2 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Cisco	UCS VIC 1225T 10-Gbase-T 2 port CNA	Red Hat Enterprise Linux 6.3 64bit	1.5.0.22/2.1.1.41 (NIC)	2.1(1.c)	2.1(1.c)	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Cisco	UCS VIC 1225T 10-Gbase-T 2 port CNA	VMware vSphere ESXi 4.1 U2	1.4.0.215/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Cisco	UCS VIC 1225T 10-Gbase-T 2 port CNA	VMware vSphere ESXi 4.1 U3	1.4.0.215/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Cisco	UCS VIC 1225T 10-Gbase-T 2 port CNA	VMware vSphere ESXi 5.0	1.5.0.22/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Cisco	UCS VIC 1225T 10-Gbase-T 2 port CNA	VMware vSphere ESXi 5.0 U1	1.5.0.22/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Cisco	UCS VIC 1225T 10-Gbase-T 2 port CNA	VMware vSphere ESXi 5.1	1.5.0.22/2.1.2.38 (NIC)	2.1(1.c)	2.1(1.c)	8, 13
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Cisco	UCS VIC 1225T 10-Gbase-T 2 port CNA	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	2.1.0.20/2.2.0.13 (NIC)	2.1(1.c)	2.1(1.c)	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Cisco	UCS VIC 1225T 10-Gbase-T 2 port CNA	Windows Server 2012	2.2.0.17/2.2.0.13 (NIC)	2.1(1.c)	2.1(1.c)	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 5.7 64bit	0:8.2.2.4/4.2.324.11 (NIC)	4.2.324.30	4.03a0	14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 5.8 64bit	0:8.2.2.4/4.2.324.11 (NIC)	4.2.324.30	4.03a0	14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 5.9 64bit	0:8.2.0.128.3p/ 4.2.116r (NIC)	4.2.324.30	4.03a0	14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 6.2 64bit	0:8.3.7.5/4.2.324.11 (NIC)	4.2.324.30	4.03a0	14

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 6.3 64bit	0:8.3.7.5/4.2.324.11 (NIC)	4.2.324.30	4.03a0	14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 6.4 64bit	0:8.3.5.86.1p/4.4.161.0r. (NIC)	4.2.324.30	4.03a0	14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 5.7 64bit	0:8.2.0.106.1p/4.0.462.0 (NIC)	4.2.324.30	4.03a0	5, 14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 5.8 64bit	0:8.3.5.45.4p/4.0.160r (NIC)	4.2.324.30	4.03a0	5, 14

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 5.9 64bit	0:8.3.5.82.2p/ 4.4.31.0o (NIC)	4.2.324.30	4.03a0	5, 14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 6.2 64bit	0:8.3.5.45.4p/ 4.0.160r (NIC)	4.2.324.30	4.03a0	5, 14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 6.3 64bit	0:8.3.5.68.6p/ 4.2.220o (NIC)	4.2.324.30	4.03a0	5, 14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	SUSE Linux Enterprise Server 11.2 64bit	0:8.3.7.5/4.2.324.11 (NIC)	4.2.324.30	4.03a0	14

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESX 4.1 U2	0:8.2.1.141.55/4.2.324.4 (NIC)	4.2.324.30	4.03a0	14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 4.1 U2	0:8.2.1.141.55/4.2.324.4 (NIC)	4.2.324.30	4.03a0	8, 14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESX 4.1 U3	0:8.2.1.141.55/4.2.324.4 (NIC)	4.2.324.30	4.03a0	14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 4.1 U3	0:8.2.1.141.55/4.2.324.4 (NIC)	4.2.324.30	4.03a0	8, 14

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.0	0:8.2.4.141.55/ 4.2.327.0 (NIC)	4.2.324.30	4.03a0	14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.0 U1	0:8.2.4.141.55/ 4.2.327.0 (NIC)	4.2.324.30	4.03a0	14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.0 U2	0:8.2.4.141.55/ 4.2.327.0 (NIC)	4.2.324.30	4.03a0	14
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCel0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.1	0:8.2.4.141.55/ 4.2.327.0 (NIC)	4.2.324.30	4.03a0	8, 14

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCEl0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	2.72.12.1/4.2.390.6 (NIC)	4.2.324.30	4.03a0	14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCEl0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	2.72.12.1/4.2.390.6 (NIC)	4.2.324.30	4.03a0	14
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCEl0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Windows Server 2012	2.72.12.1/4.2.390.6 (NIC)	4.2.324.30	4.03a0	14
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCEl0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Xen Server 6.0.2	0:8.3.5.39.1p/ 2.104.277.1(nic)	4.2.324.30	4.03a0	5, 14

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCell0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Xen Server 6.1	0:8.3.5.77.1p/ 4.1.450.7(nic)	4.2.324.30	4.03a0	5, 14
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Emulex	OneConnect OCell0102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle VM 3.1.1	0:8.3.5.58.2p/ 4.1.297o (NIC)	4.2.324.30	4.03a0	5, 14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 5.7 64bit	0:8.2.2.4/4.2.324.11 (NIC)	4.1.402.18	4.03a0	14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 5.8 64bit	0:8.2.0.2.4/ 4.2.324.11 (NIC)	4.1.402.18	4.03a0	14

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCE1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 5.9 64bit	0:8.2.0.128.3p/4.2.116r (NIC)	4.1.402.18	4.03a0	14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCE1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 6.2 64bit	0:8.3.7.5/4.2.324.11 (NIC)	4.1.402.18	4.03a0	14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCE1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 6.3 64bit	0:8.3.7.5/4.2.324.11 (NIC)	4.1.402.18	4.03a0	14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCE1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 6.4 64bit	0:8.3.5.86.1p/4.4.161.0r. (NIC)	4.1.402.18	4.03a0	14

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 5.7 64bit	0:8.3.5.44/ 2.103.298r (NIC)	4.1.402.18	4.03a0	5, 14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 5.8 64bit	0:8.3.5.45.4p/ 4.0.160r (NIC)	4.1.402.18	4.03a0	5, 14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 5.9 64bit	0:8.3.5.82.2p/ 4.4.31.0o (NIC)	4.1.402.18	4.03a0	5, 14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 6.2 64bit	0:8.3.5.45.4p/ 4.0.160r (NIC)	4.1.402.18	4.03a0	5, 14

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCEl1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 6.3 64bit	0:8.3..5.68.6p/4.2.220o (NIC)	4.1.402.18	4.03a0	5, 14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCEl1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESX 4.1 U2	0:8.2.1.141.55/4.2.324.4 (NIC)	4.1.402.18	4.03a0	29, 14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCEl1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 4.1 U2	0:8.2.1.141.55/4.2.324.4 (NIC)	4.1.402.18	4.03a0	13, 29, 14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCEl1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESX 4.1 U3	0:8.2.1.141.55/4.2.324.4 (NIC)	4.1.402.18	4.03a0	13, 14

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 4.1 U3	0:8.2.1.141.55/4.2.324.4 (NIC)	4.1.402.18	4.03a0	13, 14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.0	0:8.2.4.141.55/4.2.327.0 (NIC)	4.1.402.18	4.03a0	13, 14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.0 U1	0:8.2.4.141.55/4.2.327.0 (NIC)	4.1.402.18	4.03a0	14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.0 U2	0:8.2.4.141.55/4.2.327.0 (NIC)	4.1.402.18	4.03a0	14

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2,,C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	OneConnect OCE1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.1	0:8.2.4.141.55/ 4.2.327.0 (NIC)	4.1.402.18	4.03a0	14
C260 M2, C460 M2,,C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	OneConnect OCE1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	2.72.12.1/4.2.390.6 (NIC)	4.1.402.18	4.03a0	14
C260 M2, C460 M2,,C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	OneConnect OCE1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	2.72.12.1/4.2.390.6 (NIC)	4.1.402.18	4.03a0	14
C260 M2, C460 M2,,C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	OneConnect OCE1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Windows Server 2012	2.72.12.1/4.2.390.6 (NIC)	4.1.402.18	4.03a0	14

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Xen Server 6.0.2	0:8.3.5.39.1p/ 2.104.277.1 (NIC)	4.1.402.18	4.03a0	5, 14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Xen Server 6.1	0:8.3.5.77.1p/ 4.1.450.7 (NIC)	4.1.402.18	4.03a0	5, 14
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Emulex	OneConnect OCell1102-FX Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle VM 3.1.1	0:8.3.5.58.2p/ 4.1.297o (NIC)	4.1.402.18	4.03a0	5, 14
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 5.7 64bit	8.04.00.06.5.6-k/ v1.00.00.31 (NIC)	5.07.00	3.13	6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 5.8 64bit	8.04.00.06.5.6-k/ v1.00.00.31 (NIC)	5.07.00	3.13	6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 5.9 64bit	8.03.07.15.05.09-k/ v1.00.00.30 (NIC)	5.07.00	3.13	11, 6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 6.2 64bit	8.04.00.06.06.0-k/ v1.00.00.31 (NIC)	5.07.00	3.13	6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 6.3 64bit	8.04.00.06.06.0-k/ v1.00.00.31 (NIC)	5.07.00	3.13	6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 6.4 64bit	8.04.00.08.06.4-k/ v1.00.00.31 (NIC)	5.07.00	3.13	6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 5.7 64bit	8.03.07.04.32.1-k/ v1.00.00.27.00.00-01 (NIC)	5.07.00	3.13	5, 6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 5.8 64bit	8.03.07.08.32.1-k/ v1.00.00.29.00.00-01 (NIC)	5.07.00	3.13	5, 6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 5.9 64bit	8.04.00.08.39.0-k/ 1.00.00.30 (NIC)	5.07.00	3.13	5, 6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 6.2 64bit	8.03.07.08.32.1-k/ v1.00.00.29.00.00-01 (NIC)	5.07.00	3.13	5, 6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 6.3 64bit	8.04.00.03.39.0-k/ v1.00.00.30 (NIC)	5.07.00	3.13	5, 6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	SUSE Linux Enterprise Server 11.2 64bit	8.04.00.06.11.1-k/ 1.00.00.31 (NIC)	5.07.00	3.13	6
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Solaris 10 8/11 (U10)	3.05	5.07.00	3.13	5, 6
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Solaris 10 9/10 (U9)	3.00/1.05	5.07.00	3.13	5, 6
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Solaris 11	3.05/1.12 (NIC)	5.07.00	3.13	5, 6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESX 4.1 U2	841.k1.48.1-1vmw/ v1.00.00.47-0517c	5.07.00	3.13	6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 4.1 U2	841.k1.48.1-1vmw/v1.00.00.47-0517c	5.07.00	3.13	6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESX 4.1 U3	841.k1.48.1-1vmw/v1.00.00.47-0517c	5.07.00	3.13	6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 4.1 U3	841.k1.48.1-1vmw/v1.00.00.47-0517c	5.07.00	3.13	6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.0	934.5.4.0-1vmw/v2.00.00.54-04202012	5.07.00	3.13	6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.0 U1	934.5.4.0-1vmw/v2.00.00.54-04202012	5.07.00	3.13	6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.0 U2	934.5.4.0-1vmw/v2.00.00.54-04202012	5.07.00	3.13	6
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.1	934.5.4.0-1vmw/v2.00.00.54-04202012	5.07.00	3.13	6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	9.1.10.15/1.0.1.12	5.07.00	3.13	6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	9.1.10.15/1.0.1.7	5.07.00	3.13	6
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Windows Server 2012	9.1.10.15/1.0.1.15	5.07.00	3.13	6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Xen Server 6.0.2	8.03.07.03.55.6-k2/v1.00.00.28..00.00-01	5.07.00	3.13	5, 6
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Xen Server 6.1	8.04.00.02.55.6-k/v1.00.00.30	5.07.00	3.13	5, 6
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	QLogic	QLE8152 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle VM 3.1.1	8.03.07.12.39.0-k/v1.00.00.29.00.00-01 (NIC)	5.07.00	3.13	5, 6
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 5.7 64bit	8.04.00.06.5.6-k/5.0.29.2 (NIC)/50301.0405.0740(SCSI)	4.12.52	3.13	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 5.8 64bit	8.04.00.06.5.6-k/5.0.29.2 (NIC)/50301.0405.0740(SCSI)	4.12.52	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 5.9 64bit	8.03.07.15.05.09-k/ 5.0.29 (NIC)	4.12.52	3.13	6
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 6.2 64bit	8.04.00.06.06.0-k/ 5.0.29.2 (NIC)/ 5.03.01.04.00.00-k0	4.12.52	3.13	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 6.3 64bit	8.04.00.06.06.0-k/ 5.0.29.2 (NIC)/ 5.03.01.04.00.00-k0	4.12.52	3.13	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Red Hat Enterprise Linux 6.4 64bit	8.04.00.08.06.4-k/ 5.0.29 (NIC)/ 5.03.00.00.06.04-k2(SCSI)	4.12.52	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 5.7 64bit	8.03.07.04.32.1-k/ 5.0.15.2 (NIC)	4.12.52	3.13	5, 6
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 5.8 64bit	8.03.07.08.32.1-k/ 5.0.24 (NIC)	4.12.52	3.13	5, 6
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 5.9 64bit	8.03.07.08.32.1-k/ 5.0.24 (NIC)	4.12.52	3.13	5, 6
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 6.2 64bit	8.03.07.08.32.1-k/ 5.0.24 (NIC)	4.12.52	3.13	5, 6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle Linux 6.3 64bit	8.04.00.03.39.0-k/ 5.0.28.1 (NIC)	4.12.52	3.13	5, 6
C260 M2, C460 M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	SUSE Linux Enterprise Server 11.2 64bit	8.04.00.06.11.1-k/ 5.0.29.2 (NIC)/ 5.03.01.04.00.00-k0(SCSI)	4.12.52	3.13	
C260 M2, C460 M2,,C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Solaris 10 8/11 (U10)	3.05/v1.0.a12 (NIC)	4.12.52	3.13	5, 6
C260 M2, C460 M2	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Solaris 10 9/10 (U9)	3.00	4.12.52	3.13	5, 6
C260 M2, C460 M2	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Solaris 11	3.05/v1.0.a12 (NIC)	4.12.52	3.13	5, 6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESX 4.1 U2	841.k1.48.1-1vmw/4.0.744 (NIC)	4.12.52	3.13	6
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 4.1 U2	841.k1.48.1-1vmw/4.0.744 (NIC)	4.12.52	3.13	6, 13, 16
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESX 4.1 U3	841.k1.48.1-1vmw/4.0.744 (NIC)	4.12.52	3.13	8, 6
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 4.1 U3	841.k1.48.1-1vmw/4.0.744 (NIC)	4.12.52	3.13	8, 13, 16, 6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2,,C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.0	943.5.4.0-1vmw/ 5.0.750	4.12.52	3.13	6
C260 M2, C460 M2,,C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.0 U1	943.5.4.0-1vmw/ 5.0.750	4.12.52	3.13	
C260 M2, C460 M2,,C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.0 U2	943.5.4.0-1vmw/ 5.0.750	4.12.52	3.13	8
C260 M2, C460 M2,,C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	VMware vSphere ESXi 5.1	943.5.4.0-1vmw/ 5.0.750	4.12.52	3.13	8

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	9.1.10.15/ 4.7.16.907 (NIC)/ 2.1.5.35(iSCSI)	4.12.52	3.13	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	9.1.10.15/ 4.6.12.217 (NIC)/ 2.1.5.35(iSCSI)	4.12.52	3.13	
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Windows Server 2012	9.1.10.15/ 4.7.16.907 (NIC)/ 2.1.5.35(iSCSI)	4.12.52	3.13	
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Xen Server 6.0.2	8.03.07.03.55.6-k2 /5.0.24 (NIC)	4.12.52	3.13	5, 6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Xen Server 6.1	8.04.00.02.55.6-k/ 5.0.27 (NIC)	4.12.52	3.13	5, 6
C260 M2, C460 M2,,C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	QLogic	QLE8242 Dual Port 10-Gbps Ethernet to PCIe Converged Network Adapter	Oracle VM 3.1.1	8.03.07.12.39.0-k/ 5.0.25.1 (NIC)	4.12.52	3.13	5, 6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF),C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.7 64bit	3.11.33	0.9-3	2.2.07	33

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.8 64bit	3.11.33	0.9-3	2.2.07	33
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.9 64bit	3.11.33	0.9-3	2.2.07	33
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.2 64bit	3.11.33	0.9-3	2.2.07	32, 33

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.3 64bit	3.11.33	0.9-3	2.2.07	26, 33
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.4 64bit	3.9.15-k	0.9-3	2.2.07	33, 5
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.7 64bit	3.2.10-NAPI	0.9-3	2.2.07	5, 6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.8 64bit	3.4.24-NAPI	0.9-3	2.2.07	5, 6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.9 64bit	3.10.16	0.9-3	2.2.07	5, 6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 6.2 64bit	3.4.24-NAPI	0.9-3	2.2.07	5, 6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 6.3 64bit	3.6.7-k	0.9-3	2.2.07	5, 6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	SUSE Linux Enterprise Server 11.2 64bit	3.11.33	0.9-3	2.2.07	32, 33
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 10 8/11 (U10)	1.0.18	0.9-3	2.2.07	5, 6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 10 9/10 (U9)	1.0.12	0.9-3	2.2.07	5, 6
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U2	3.9.13-NAPI	0.9-3	2.2.07	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U2	3.9.13-NAPI	0.9-3	2.2.07	13, 16

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U3	3.9.13-NAPI	0.9-3	2.2.07	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U3	3.9.13-NAPI	0.9-3	2.2.07	13, 16
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0	3.11.32iov	0.9-3	2.2.07	13

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U1	3.11.32iov	0.9-3	2.2.07	13
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U2	3.11.32iov	0.9-3	2.2.07	13
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.1	3.11.32iov	0.9-3	2.2.07	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	3.2.61.0	0.9-3	2.2.07	5, 33
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	3.2.61.0	0.9-3	2.2.07	5, 33
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2012	3.2.61.0	0.9-3	2.2.07	5, 33

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Xen Server 6.0.2	3.6.7-NAPI	0.9-3	2.2.07	
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Xen Server 6.1	3.8.21-NAPI	0.9-3	2.2.07	
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Intel	X520 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle VM 3.1.1	3.4.8-k	0.9-3	2.2.07	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.7 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	7.4.11	7.4.10	30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.8 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	7.4.11	7.4.10	30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.9 64bit	1.72.51-0 (NIC)	7.4.11	7.4.10	5, 6, 30

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.2 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	7.4.11	7.4.10	30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.3 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	7.4.11	7.4.10	30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.4 64bit	1.72.51-0 (NIC)/ 2.7.2.2(iSCSI)	7.4.11	7.4.10	30

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	SUSE Linux Enterprise Server 11.2 64bit	1.74.17 (NIC)	7.4.11	7.4.10	30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.8 64bit	1.70.00-0	7.4.19	v7.4.12	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.9 64bit	1.72.50-0	7.4.19	v7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 6.2 64bit	1.70.00-0	7.4.19	v7.4.12	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 6.3 64bit	1.72.00-0	7.4.19	v7.4.12	
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 10 9/10 (U9)	6.4.35	7.4.11	7.4.10	5, 30

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 10 8/11 (U10)	6.4.35	7.4.11	7.4.10	5, 30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 11	vv6.4.37.1	7.4.11	7.4.10	5, 30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U2	1.74.17.v41.1 (NIC)/2.74.07.v41.1	7.4.11	7.4.10	30

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U2	1.74.17.v41.1 (NIC)/2.74.07.v41.1	7.4.11	7.4.10	, 5, 6, 30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U3	1.74.17.v41.1 (NIC)/2.74.07.v41.1	7.4.11	7.4.10	30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U3	1.74.17.v41.1 (NIC)/2.74.07.v41.1	7.4.11	7.4.10	8, 17, 30

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0	1.74.17.v50.1 (NIC)/2.74.07.v50.1	7.4.11	7.4.10	8, 17, 30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U1	1.74.17.v50.1 (NIC)/2.74.07.v50.1	7.4.11	7.4.10	8, 17, 30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U2	1.74.17.v50.1 (NIC)/2.74.07.v50.1	7.4.11	7.4.10	8, 17, 30

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.1	1.74.17.v50.1 (NIC)/2.74.07.v50.1	7.4.11	7.4.10	8, 17, 30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	7.4.6.0(FC)/7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	7.4.11	7.4.10	30
C200/C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	7.4.6.0(FC)/7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	7.4.11	7.4.10	30

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2012	7.4.6.0(FC)/7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	7.4.11	7.4.10	30
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Xen Server 6.0.2	1.70.35 (NIC)	7.4.11	7.4.10	30
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Xen Server 6.1	1.72.55 (NIC)	7.4.11	7.4.10	30

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	NetXtreme II 57712 SFP+ Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle VM 3.1.1	1.70.00-0	7.4.11	7.4.10	30
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.8 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	7.4.19	v7.4.12	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.9 64bit	1.74.17 (NIC)/ 1.72.51-0(iSCSI)	7.4.19	v7.4.12	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.2 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)/ 2.2.17(FCoE)	7.4.19	v7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.3 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)/ 2.2.17(FCoE)	7.4.19	v7.4.12	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.4 64bit	1.72.51-0 (NIC)/ 2.7.2.2(iSCSI)/ 1.0.12(FCoE)	7.4.19	v7.4.12	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U2	1.74.17.v41.1 (NIC)	7.4.19	v7.4.12	5, 6
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U3	1.74.17.v41.1 (NIC)	7.4.19	v7.4.12	5, 6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U1	1.74.17.v50.1(Nic)/ 2.74.07.v50.1(ISCsi)	7.4.19	v7.4.12	17, 33
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U2	1.72.54.v50.2 (NIC)	7.4.19	v7.4.12	5, 6
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.1	1.74.02.v50.2(FCoE)/ 2.74.07.v50.1(ISCsi)	7.4.19	v7.4.12	13, 32
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Oracle Linux 5.8 64bit	1.70.00-0	7.4.19	v7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Oracle Linux 5.9 64bit	1.72.50-0	7.4.19	v7.4.12	
C260 M2, C460 M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Oracle Linux 6.2 64bit	1.70.00-0	7.4.19	v7.4.12	
C260 M2, C460 M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Oracle Linux 6.3 64bit	1.72.00-0	7.4.19	v7.4.12	
C260 M2, C460 M2, C220/C240 M3(SFF/ LFF), C22/ C24 M3(SFF/ LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	SUSE Linux Enterprise Server 11.2 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)/ 2.2.17(FCoE)	7.4.19	v7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Xen Server 6.0.2	1.70.35	7.4.19	v7.4.12	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Xen Server 6.1	1.72.55	7.4.19	v7.4.12	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)/ 7.4.6(FCoE)	7.4.19	v7.4.12	
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)/ 7.4.6(FCoE)	7.4.19	v7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/C240 M3(SFF/LFF), C22/C24 M3(SFF/LFF), C420 M3	Broadcom	Broadcom 57810 10 GbE SFP+ CNA Gigabit Ethernet PCIe Adapter	Windows Server 2012	7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)/ 7.4.6(FCoE)	7.4.19	v7.4.12	

Host Bus Adapter Interoperability Matrix

Table 3 lists the host bus adapters that the Unified Computing System C Series Servers support.

Table 3: Host Bus Adapters

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/LFF), C22/ C24 M3(SFF/LFF), C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Red Hat Enterprise Linux 5.7 64bit	0:8.2.2.4	ZS2.82A4	ZB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Red Hat Enterprise Linux 5.8 64bit	0:8.2.2.4	ZS2.82A4	ZB2.12a9	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Red Hat Enterprise Linux 5.9 64bit	0:8.2.0.128.3p	ZS2.82A4	ZB2.12a9	11

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Red Hat Enterprise Linux 6.2 64bit	0:8.3.7.5	ZS2.82A4	ZB2.12a9	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Red Hat Enterprise Linux 6.3 64bit	0:8.3.7.5	ZS2.82A4	ZB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Red Hat Enterprise Linux 6.4 64bit	0:8.3.5.86.1p	ZS2.82A4	ZB2.12a9	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Oracle Linux 5.7 64bit	0:8.3.5.44	ZS2.82A4	ZB2.12a9	32

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Oracle Linux 5.8 64bit	0:8.3.5.45.4p	ZS2.82A4	ZB2.12a9	32
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Oracle Linux 5.9 64bit	0:8.3.5.82.2p	ZS2.82A4	ZB2.12a9	32

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Oracle Linux 6.2 64bit	0:8.3.5.45.4p	ZS2.82A4	ZB2.12a9	32
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Oracle Linux 6.3 64bit	0:8.3.5.68.6p	ZS2.82A4	ZB2.12a9	32

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	SUSE Linux Enterprise Server 11.2 64bit	0:8.3.7.5	ZS2.82A4	ZB2.12a9	32
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESX 4.1 U2	0:8.2.1.141.55	ZS2.82A4	ZB2.12a9	29

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESXi 4.1 U2	0:8.2.1.141.55	ZS2.82A4	ZB2.12a9	13, 16, 29
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESX 4.1 U3	0:8.2.1.141.55	ZS2.82A4	ZB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESXi 4.1 U3	0:8.2.1.141.55	ZS2.82A4	ZB2.12a9	8 13, 16
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESXi 5.0	0:8.2.4.141.55	ZS2.82A4	ZB2.12a9	13

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESXi 5.0 U1	0:8.2.4.141.55	ZS2.82A4	ZB2.12a9	8
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESXi 5.0 U2	0:8.2.4.141.55	ZS2.82A4	ZB2.12a9	8

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESXi 5.1	0:8.2.4.141.55	ZS2.82A4	ZB2.12a9	8 13
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	2.72.12.1	ZS2.82A4	ZB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF),C22/ C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	2.72.12.1	ZS2.82A4	ZB2.12a9	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Windows Server 2012	2.72.12.1	ZS2.82A4	ZB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Xen Server 6.0.2	0:8.3.5.39.1P	ZS2.82A4	ZB2.12a9	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Xen Server 6.1	0:8.3.5.77.1P	ZS2.82A4	ZB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe11002 4-Gbps Fibre Channel PCI Express Host Bus Adapter	Oracle VM 3.1.1	0:8.3.5.58.2p	ZS2.82A4	ZB2.12a9	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Red Hat Enterprise Linux 5.7 64bit	0:8.2.2.4	US2.01A4	UB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Red Hat Enterprise Linux 5.8 64bit	0:8.2.2.4	US2.01A4	UB2.12a9	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Red Hat Enterprise Linux 5.9 64bit	0:8.2.0.128.3p	US2.01A4	UB2.12a9	11

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Red Hat Enterprise Linux 6.2 64bit	0:8.3.7.5	US2.01A4	UB2.12a9	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Red Hat Enterprise Linux 6.3 64bit	0:8.3.7.5	US2.01A4	UB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Red Hat Enterprise Linux 6.4 64bit	0:8.3.5.86.1p	US2.01A4	UB2.12a9	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Oracle Linux 5.7 64bit	0:8.3.5.44	US2.01A4	UB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Oracle Linux 5.8 64bit	0:8.3.5.45.4p	US2.01A4	UB2.12a9	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Oracle Linux 5.9 64bit	0:8.3.5.82.2p	US2.01A4	UB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Oracle Linux 6.2 64bit	0:8.3.5.45.4p	US2.01A4	UB2.12a9	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Oracle Linux 6.3 64bit	0:8.3.5.68.6p	US2.01A4	UB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	SUSE Linux Enterprise Server 11.2 64bit	0:8.3.7.5	US2.01A4	UB2.12a9	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESX 4.1 U2	0:8.2.1.141.55	US2.01A4	UB2.12a9	29

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESXi 4.1 U2	0:8.2.1.141.55	US2.01A4	UB2.12a9	13, 16, 29
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESX 4.1 U3	0:8.2.1.141.55	US2.01A4	UB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESXi 4.1 U3	0:8.2.1.141.55	US2.01A4	UB2.12a9	8 13
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESXi 5.0	0:8.2.4.141.55	US2.01A4	UB2.12a9	13

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESXi 5.0 U1	0:8.2.4.141.55	US2.01A4	UB2.12a9	8
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESXi 5.0 U2	0:8.2.4.141.55	US2.01A4	UB2.12a9	8

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	VMware vSphere ESXi 5.1	0:8.2.4.141.55	US2.01A4	UB2.12a9	8 13
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	2.72.12.1	US2.01A4	UB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	2.72.12.1	US2.01A4	UB2.12a9	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Windows Server 2012	2.72.12.1	US2.01A4	UB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Xen Server 6.0.2	0:8.3.5.39.1P	US2.01A4	UB2.12a9	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Xen Server 6.1	0:8.3.5.77.1P	US2.01A4	UB2.12a9	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Emulex	LightPulse LPe12002 8-Gbps Fibre Channel PCI Express Host Bus Adapter	Oracle VM 3.1.1	0:8.3.5.58.2p	US2.01A4	UB2.12a9	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Red Hat Enterprise Linux 5.7 64bit	8.04.00.06.5.6-k	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Red Hat Enterprise Linux 5.8 64bit	8.04.00.06.5.6-k	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Red Hat Enterprise Linux 5.9 64bit	8.03.07.15.05.09-k	5.07.00	3.13	11

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Red Hat Enterprise Linux 6.2 64bit	8.04.00.06.06.0-k	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Red Hat Enterprise Linux 6.3 64bit	8.04.00.06.06.0-k	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Red Hat Enterprise Linux 6.4 64bit	8.04.00.08.06.4-k	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Oracle Linux 5.7 64bit	8.03.07.04.32.1-k	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Oracle Linux 5.8 64bit	8.03.07.08.32.1-k	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Oracle Linux 5.9 64bit	8.04.00.08.39.0-k	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Oracle Linux 6.2 64bit	8.03.07.08.32.1-k	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Oracle Linux 6.3 64bit	8.04.00.03.39.0-k	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	SUSE Linux Enterprise Server 11.2 64bit	8.04.00.06.11.1-k	5.07.00	3.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF), C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Solaris 10 8/11 (U10)	3.05	5.07.00	3.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Solaris 10 9/10 (U9)	3.00	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Solaris 11	3.05	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESX 4.1 U2	841.k1.48.1-1vmw	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESXi 4.1 U2	841.k1.48.1-1vmw	5.07.00	3.13	13, 16

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESX 4.1 U3	841.k1.48.1-1vmw	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESXi 4.1 U3	841.k1.48.1-1vmw	5.07.00	3.13	13, 16

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESXi 5.0	934.5.4.0-1vmw	5.07.00	3.13	13
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESXi 5.0 U1	934.5.4.0-1vmw	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESXi 5.0 U2	934.5.4.0-1vmw	5.07.00	3.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESXi 5.1	934.5.4.0-1vmw	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	9.1.10.26	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	9.1.10.26	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Windows Server 2012	9.1.10.26	5.07.00	3.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Xen Server 6.0.2	8.03.07.03.55.6-k2	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Xen Server 6.1	8.04.00.02.55.6-k	5.07.00	3.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF), C420 M3	QLogic	SANblade QLE2462 4-Gbps Fibre Channel to PCI Express Host Bus Adapter	Oracle VM 3.1.1	8.03.07.12.39.0-k	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Red Hat Enterprise Linux 5.7 64bit	8.04.00.06.5.6-k	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Red Hat Enterprise Linux 5.8 64bit	8.04.00.06.5.6-k	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Red Hat Enterprise Linux 5.9 64bit	8.03.07.15.05.09-k	5.07.00	3.13	11
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Red Hat Enterprise Linux 6.2 64bit	8.04.00.06.06.0-k	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Red Hat Enterprise Linux 6.3 64bit	8.04.00.06.06.0-k	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Red Hat Enterprise Linux 6.4 64bit	8.04.00.08.06.4-k	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Oracle Linux 5.7 64bit	8.03.07.04.32.1-k	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Oracle Linux 5.8 64bit	8.03.07.08.32.1-k	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Oracle Linux 5.9 64bit	8.04.00.08.39.0-k	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Oracle Linux 6.2 64bit	8.03.07.08.32.1-k	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Oracle Linux 6.3 64bit	8.04.00.03.39.0-k	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	SUSE Linux Enterprise Server 11.2 64bit	8.04.00.06.11.1-k	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Solaris 10 8/11 (U10)	3.05	5.07.00	3.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Solaris 10 9/10 (U9)	3.00	5.07.00	3.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Solaris 11	3.05	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESX 4.1 U2	841.k1.48.1-1vmw	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESXi 4.1 U2	841.k1.48.1-1vmw	5.07.00	3.13	13, 16

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESX 4.1 U3	841.k1.48.1-1vmw	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESXi 4.1 U3	841.k1.48.1-1vmw	5.07.00	3.13	13, 16

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESXi 5.0	934.5.4.0-1vmw	5.07.00	3.13	13
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESXi 5.0 U1	934.5.4.0-1vmw	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESXi 5.0 U2	934.5.4.0-1vmw	5.07.00	3.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	VMware vSphere ESXi 5.1	934.5.4.0-1vmw	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	9.1.10.26	5.07.00	3.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	9.1.10.26	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Windows Server 2012	9.1.10.26	5.07.00	3.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Xen Server 6.0.2	8.03.07.03.55.6-k2	5.07.00	3.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Xen Server 6.1	8.04.00.02.55.6-k	5.07.00	3.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	QLogic	SANblade QLE2562 8-Gbps Fibre Channel to PCI Express Host Bus Adapter	Oracle VM 3.1.1	8.03.07.12.39.0-k	5.07.00	3.13	

LAN on Motherboard Interoperability Matrix

Table 4 lists the LAN on motherboard adapters that the Unified Computing System C Series Servers support.

Table 4: LAN on Motherboard

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 5.7 64bit	2.2.3e/2.7.4.1f	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 5.8 64bit	2.2.3e/2.7.4.1f	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 5.9 64bit	2.2.3e/2.7.4.1f	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 6.2 64bit	2.2.3e/2.7.4.1f	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 6.3 64bit	2.2.3e/2.7.4.1f	6.0.0	v6.4.4	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 6.4 64bit	2.2.3/2.7.2.2	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Oracle Linux 5.7 64bit	2.0.21	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Oracle Linux 5.8 64bit	2.1.11/2.7.0.3	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Oracle Linux 5.9 64bit	2.1.11/2.7.0.3	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Oracle Linux 6.2 64bit	2.1.11/2.7.0.3	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Oracle Linux 6.3 64bit	2.2.1/2.7.0.3	6.0.0	v6.4.4	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	SUSE Linux Enterprise Server 11.2 64bit	2.2.3e/2.7.4.1f	6.0.0	v6.4.4	
C250 M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Solaris 10 8/11 (U10)	6.4.2	6.0.0	v6.4.4	
C250 M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Solaris 10 9/10 (U9)	6.4.2	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESX 4.1 U2	2.2.3e.v41.1	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 4.1 U2	2.2.3e.v41.1	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESX 4.1 U3	2.2.3e.v41.1	6.0.0	v6.4.4	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 4.1 U3	2.2.3e.v41.1	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.0	2.2.3e.v50.1	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.0 U1	2.2.3e.v50.1	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.0 U2	2.2.3e.v50.1	6.0.0	v6.4.4	
C250 M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.1	2.2.3e.v50.1	6.0.0	v6.4.4	
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	7.4.23.0/7.4.3.0	6.0.0	v6.4.4	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C250 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	7.4.23.0/7.4.3.0	6.0.0	v6.4.4	
C250 M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Windows Server 2012	7.4.23.0/7.4.3.0	6.0.0	v6.4.4	
C250 M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Xen Server 6.0.2	2.1.12b	6.0.0	v6.4.4	
C250 M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Xen Server 6.1	2.1.12b	6.0.0	v6.4.4	
C250 M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Oracle VM 3.1.1	2.1.11	6.0.0	v6.4.4	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 5.7 64bit	2.2.3e/2.7.4.1f	7.4.0	v7.4.1	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 5.8 64bit	2.2.3e/2.7.4.1f	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 5.9 64bit	2.1.11/2.7.2.2	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 6.2 64bit	2.2.3e/2.7.4.1f	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 6.3 64bit	2.2.3e/2.7.4.1f	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 6.4 64bit	2.2.3/2.7.2.2	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Oracle Linux 5.7 64bit	2.0.21	7.4.0	v7.4.1	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Oracle Linux 5.8 64bit	2.1.11/2.7.0.3	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Oracle Linux 5.9 64bit	2.2.3/2.7.2.2	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Oracle Linux 6.2 64bit	2.1.11/2.7.0.3	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Oracle Linux 6.3 64bit	2.2.1/2.7.0.3	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	SUSE Linux Enterprise Server 11.2 64bit	2.2.3e/2.7.4.1f	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Solaris 10 8/11 (U10)	6.4.2	7.4.0	v7.4.1	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Solaris 10 9/10 (U9)	6.4.2	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Solaris 11	6.0.3	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESX 4.1 U2	2.2.3e.v41.1/ 2.74.07.v41.1	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 4.1 U2	2.2.3e.v41.1/ 2.74.07.v41.1	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESX 4.1 U3	2.2.3e.v41.1/ 2.74.07.v41.1	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 4.1 U3	2.2.3e.v41.1/ 2.74.07.v41.1	7.4.0	v7.4.1	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.0	2.2.3e.v50.1/ 2.74.07.v50.1	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.0 U1	2.2.3e.v50.1/ 2.74.07.v50.1	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.0 U2	2.2.3e.v50.1/ 2.74.07.v50.1	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.1	2.2.3e.v50.1/ 2.74.07.v50.1	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	7.4.23.0/7.4.3.0	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	7.4.23.0/7.4.3.0	7.4.0	v7.4.1	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Windows Server 2012	7.4.23.0/7.4.3.0	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Xen Server 6.0.2	2.1.12b	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Xen Server 6.1	2.1.1j	7.4.0	v7.4.1	
C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Quad Port Gigabit Ethernet Onboard Controller	Oracle VM 3.1.1	2.1.11	7.4.0	v7.4.1	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 5.7 64bit	1.74.17 (NIC)	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 5.8 64bit	1.74.17 (NIC)	6.2.25	v7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 5.9 64bit	1.72.51-0 (NIC)	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 6.2 64bit	1.74.17 (NIC)	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 6.3 64bit	1.74.17 (NIC)	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 6.4 64bit	1.72.51-0 (NIC)	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Oracle Linux 5.7 64bit	1.62.00-6	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Oracle Linux 5.8 64bit	1.70.00-0	6.2.25	v7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Oracle Linux 5.9 64bit	1.70.00-0 (NIC)	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Oracle Linux 6.2 64bit	1.70.00-0	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Oracle Linux 6.3 64bit	1.72.00-0	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	SUSE Linux Enterprise Server 11.2 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Solaris 10 8/11 (U10)	6.4.35	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Solaris 10 9/10 (U9)	6.4.35	6.2.25	v7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Solaris 11	6.4.37.1	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	VMware vSphere ESX 4.1 U2	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 4.1 U2	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	VMware vSphere ESX 4.1 U3	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 4.1 U3	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.0	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	6.2.25	v7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.0 U1	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.0 U2	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.1	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Windows Server 2012	7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	6.2.25	v7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Xen Server 6.0.2	1.70.35	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Xen Server 6.1	1.72.55	6.2.25	v7.4.12	
C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet Onboard Controller	Oracle VM 3.1.1	1.70.00-0	6.2.25	v7.4.12	
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Red Hat Enterprise Linux 5.7 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	7.4.19	v7.4.13	
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Red Hat Enterprise Linux 5.8 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	7.4.19	v7.4.13	
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Red Hat Enterprise Linux 5.9 64bit	1.72.51-0 (NIC)	7.4.19	v7.4.13	5, 6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Red Hat Enterprise Linux 6.2 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	7.4.19	v7.4.13	
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Red Hat Enterprise Linux 6.3 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	7.4.19	v7.4.13	
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Red Hat Enterprise Linux 6.4 64bit	1.72.51-0 (NIC)/ 2.7.2.2(iSCSI)	7.4.19	v7.4.13	
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Oracle Linux 5.7 64bit	1.0.2/1.62.00-6 (NIC)	7.4.19	v7.4.13	5, 6
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Oracle Linux 5.8 64bit	1.70.00-0 (NIC)	7.4.19	v7.4.13	5, 6
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Oracle Linux 5.9 64bit	1.72.50-0 (NIC)	7.4.19	v7.4.13	5, 6
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Oracle Linux 6.2 64bit	1.70.00-0 (NIC)	7.4.19	v7.4.13	5, 6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Oracle Linux 6.3 64bit	1.72.00-0	7.4.19	v7.4.13	5, 6
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	SUSE Linux Enterprise Server 11.2 64bit	1.74.17 (NIC)	7.4.19	v7.4.13	
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Solaris 10 8/11 (U10)	6.4.35	7.4.19	v7.4.13	5, 6
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Solaris 10 9/10 (U9)	6.4.35	7.4.19	v7.4.13	5, 6
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Solaris 11	6.4.37.1	7.4.19	v7.4.13	5, 6
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	VMware vSphere ESX 4.1 U2	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	7.4.19	v7.4.13	
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	VMware vSphere ESXi 4.1 U2	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	7.4.19	v7.4.13	5

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	VMware vSphere ESX 4.1 U3	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	7.4.19	v7.4.13	
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	VMware vSphere ESXi 4.1 U3	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	7.4.19	v7.4.13	8
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	VMware vSphere ESXi 5.0	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	7.4.19	v7.4.13	5
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	VMware vSphere ESXi 5.0 U1	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	7.4.19	v7.4.13	8
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	VMware vSphere ESXi 5.0 U2	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	7.4.19	v7.4.13	8
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	VMware vSphere ESXi 5.1	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	7.4.19	v7.4.13	8
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	7.4.6.0(FC)/7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	7.4.19	v7.4.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Windows Server 2008 SP2 x64 w/ Hyper-V	7.4.6.0(FC)/7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	7.4.19	v7.4.13	
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Windows Server 2012	7.4.6.0(FC)/7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	7.4.19	v7.4.13	
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Xen Server 6.0.2	1.70.35 (NIC)	7.4.19	v7.4.13	5, 6
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Xen Server 6.1	1.72.55 (NIC)	7.4.19	v7.4.13	5, 6
C260 M2	Broadcom	CISCO LOM BCM57712 Dual Port 10GbE NIC SFP+	Oracle VM 3.1.1	1.70.00-0	7.4.19	v7.4.13	5, 6
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 5.7 64bit	4.0.17	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 5.8 64bit	4.0.17	1.4-3	1.3.35	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 5.9 64bit	4.0.17	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 6.2 64bit	4.0.17	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 6.3 64bit	4.0.17	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Red Hat Enterprise Linux 6.4 64bit	4.0.1-k	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Oracle Linux 5.7 64bit	3.0.6-k	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Oracle Linux 5.8 64bit	3.0.6-k	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Oracle Linux 5.9 64bit	3.4.8	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Oracle Linux 6.2 64bit	3.0.6-k	1.4-3	1.3.35	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Oracle Linux 6.3 64bit	3.2.10-k	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	SUSE Linux Enterprise Server 11.2 64bit	4.0.17	1.4-3	1.3.35	
C200/ C210 M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Solaris 10 8/11 (U10)	1.1.18	1.4-3	1.3.35	
C200/ C210 M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Solaris 10 9/10 (U9)	1.1.14	1.4-3	1.3.35	
C200/ C210 M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Solaris 11	2.3.5	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	VMware vSphere ESX 4.1 U2	3.2.10	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 4.1 U2	3.2.10	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	VMware vSphere ESX 4.1 U3	3.2.10	1.4-3	1.3.35	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 4.1 U3	3.2.10	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.0	4.0.17	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.0 U1	4.0.17	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.0 U2	4.0.17	1.4-3	1.3.35	
C200/ C210 M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	VMware vSphere ESXi 5.1	4.0.17	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	11.17.27.0	1.4-3	1.3.35	
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	11.17.27.0	1.4-3	1.3.35	
C200/ C210 M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Windows Server 2012	12.1.77.0	1.4-3	1.3.35	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Xen Server 6.0.2	3.2.10	1.4-3	1.3.35	
C200/ C210 M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Xen Server 6.1	3.3.6	1.4-3	1.3.35	
C200/ C210 M2, C200 M2(SFF)	Intel	82576 Gigabit Ethernet Onboard Controller	Oracle VM 3.1.1	3.0.6-k2	1.4-3	1.3.35	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Red Hat Enterprise Linux 5.7 64bit	4.0.17	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Red Hat Enterprise Linux 5.8 64bit	4.0.17	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Red Hat Enterprise Linux 5.9 64bit	4.0.17	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Red Hat Enterprise Linux 6.2 64bit	4.0.17	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Red Hat Enterprise Linux 6.3 64bit	4.0.17	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Red Hat Enterprise Linux 6.4 64bit	4.0.1-k	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Oracle Linux 5.7 64bit	3.0.6-k2	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Oracle Linux 5.8 64bit	3.0.6-k	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Oracle Linux 5.9 64bit	3.4.8	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Oracle Linux 6.2 64bit	3.0.6-k	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Oracle Linux 6.3 64bit	3.2.10-k	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	SUSE Linux Enterprise Server 11.2 64bit	4.0.17	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Solaris 10 8/11 (U10)	1.1.18	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	VMware vSphere ESX 4.1 U2	3.2.10	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	VMware vSphere ESXi 4.1 U2	3.2.10	1.6-1	v1.3.98	13, 16
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	VMware vSphere ESX 4.1 U3	3.2.10	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	VMware vSphere ESXi 4.1 U3	3.2.10	1.6-1	v1.3.98	13, 16
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	VMware vSphere ESXi 5.0	4.0.17	1.6-1	v1.3.98	13

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	VMware vSphere ESXi 5.0 U1	4.0.17	1.6-1	v1.3.98	13
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	VMware vSphere ESXi 5.0 U2	4.0.17	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	VMware vSphere ESXi 5.1	4.0.17	1.6-1	v1.3.98	13
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	12.3.35.0	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	12.3.35.0	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Windows Server 2012	12.3.35.0	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Xen Server 6.0.2	3.2.10	1.6-1	v1.3.98	
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Xen Server 6.1	3.3.6	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet I350-T4 Onboard Controller	Oracle VM 3.1.1	3.0.6-k2	1.6-1	v1.3.98	

Network Interface Card Interoperability Matrix

Table 5 lists the network interface cards that the Unified Computing System C Series Servers support.

Table 5: Network Interface Cards

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C250 M1 & M2, C460 M1 & M2	Mellanox	ConnectX-2 EN 10 Gigabit Ethernet	SUSE Linux Enterprise Server 10 SP4 64bit	1.5.9	2.7.8.100	1.5.5	
C260 M2	Mellanox	ConnectX-2 EN 10 Gigabit Ethernet	SUSE Linux Enterprise Server 11.1 64bit	1.5.6	2.7.8.100	1.5.5	
C200/ C210 M1 & M2, C200 M2(SFF), C260 M2	Mellanox	ConnectX-2 EN 10 Gigabit Ethernet	Red Hat Enterprise Linux 5.6 64bit	1.5.6	2.7.8.100	1.5.5	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Mellanox	ConnectX-2 EN MNPH29D- XTR 10 Gigabit Ethernet	Red Hat Enterprise Linux 5.6 64bit	1.5.6	2.9.1000	3.3.400	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Mellanox	ConnectX-2 EN MNPH29D- XTR 10 Gigabit Ethernet	SUSE Linux Enterprise Server 11.1 64bit	1.5.6	2.9.1000	3.3.400	
C220/ C240 M3(SFF/ LFF),C420 M3	Mellanox	ConnectX-3 EN 10 Gigabit Ethernet	Red Hat Enterprise Linux 5.7 64bit	1.5.9	2.11.500	v3.4.000	
C220/ C240 M3(SFF/ LFF),C420 M3	Mellanox	ConnectX-3 EN 10 Gigabit Ethernet	Red Hat Enterprise Linux 5.8 64bit	1.5.9	2.11.500	v3.4.000	
C220/ C240 M3(SFF/ LFF),C420 M3	Mellanox	ConnectX-3 EN 10 Gigabit Ethernet	Red Hat Enterprise Linux 6.2 64bit	1.5.9	2.11.500	v3.4.000	
C220/ C240 M3(SFF/ LFF),C420 M3	Mellanox	ConnectX-3 EN 10 Gigabit Ethernet	Red Hat Enterprise Linux 6.3 64bit	1.5.9	2.11.500	v3.4.000	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF),C420 M3	Mellanox	ConnectX-3 EN 10 Gigabit Ethernet	SUSE Linux Enterprise Server 11.2 64bit	1.5.9	2.11.500	v3.4.000	
C220/ C240 M3(SFF/ LFF),C420 M3	Mellanox	ConnectX-3 EN 10 Gigabit Ethernet	VMware vSphere ESXi 5.0 U1	1.6.1.2	2.11.500	v3.4.000	
C460 M1, C250 M1 & M2	SolarFlare	SFN5122F Dual-Port 10G SFP+	SUSE Linux Enterprise Server 10 SP3 64bit	3.3.0.6246	3.2.1.6100	v3.2.1.6087	19
C460 M1, C250 M1 & M2	SolarFlare	SFN5122F Dual-Port 10G SFP+	SUSE Linux Enterprise Server 10 SP4 64bit	3.3.0.6246	3.2.1.6100	v3.2.1.6087	19
C250 M2, C460 M2	SolarFlare	SFN5122F Dual-Port 10G SFP+	SUSE Linux Enterprise Server 11.1 64bit	3.3.0.6246	3.2.1.6100	v3.2.1.6087	19
C460 M2	SolarFlare	SFN5122F Dual-Port 10G SFP+	SUSE Linux Enterprise Server 11.2 64bit	3.3.0.6246	3.2.1.6100	v3.2.1.6087	19
C240 M3	SolarFlare	SFN5122F Dual-Port 10G SFP+	Red Hat Enterprise Linux 5.8 64bit	3.0	3.2.1.6100	v3.2.1.6087	19
C240 M3	SolarFlare	SFN5122F Dual-Port 10G SFP+	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	3.2.1.6076	3.2.1.6100	v3.2.1.6087	19

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C220/ C240 M3(SFF/ LFF),C420 M3	SolarFlare	SFN6122F Dual-Port 10G SFP+	Red Hat Enterprise Linux 6.2 64bit	3.3.0.6246	3.2.1.6100	v3.2.1.6087	
C260 M2, C220/ C240 M3(SFF/ LFF),C420 M3	SolarFlare	SFN6122F Dual-Port 10G SFP+	Red Hat Enterprise Linux 6.3 64bit	3.3.0.6246	3.2.1.6100	v3.2.1.6087	
C260 M2, C220/ C240 M3(SFF/ LFF),C420 M3	SolarFlare	SFN6122F Dual-Port 10G SFP+	SUSE Linux Enterprise Server 11.2 64bit	3.3.0.6246	3.2.1.6100	v3.2.1.6087	
C260 M2, C220/ C240 M3(SFF/ LFF),C420 M3	SolarFlare	SFN6122F Dual-Port 10G SFP+	VMware vSphere ESXi 5.0 U1	3.2.1.6082	3.2.1.6100	v3.2.1.6087	
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.7 64bit	2.2.3e/2.7.4.1f	7.4.0	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.8 64bit	2.2.3e/2.7.4.1f	7.4.0	7.4.12	
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.9 64bit	2.1.11/2.7.2.2	7.4.0	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.2 64bit	2.2.3e/2.7.4.1f	7.4.0	7.4.12	15
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.3 64bit	2.2.3e/2.7.4.1f	7.4.0	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.4 64bit	2.2.3/2.7.2.2	7.4.0	7.4.12	
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Oracle Linux 5.7 64bit	2.0.21	7.4.0	7.4.12	6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Oracle Linux 5.8 64bit	2.1.11	7.4.0	7.4.12	6
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Oracle Linux 5.9 64bit	2.2.3	7.4.0	7.4.12	6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Oracle Linux 6.2 64bit	2.1.11	7.4.0	7.4.12	6
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Oracle Linux 6.3 64bit	2.2.1	7.4.0	7.4.12	6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	SUSE Linux Enterprise Server 11.2 64bit	2.2.3e/2.7.4.1f	7.4.0	7.4.12	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Solaris 10 8/11 (U10)	6.4.2	7.4.0	7.4.12	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Solaris 10 9/10 (U9)	6.4.2	7.4.0	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Solaris 11	6.0.3	7.4.0	7.4.12	
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U2	2.2.3e.v41.1/ 2.74.07.v41.1	7.4.0	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U2	2.2.3e.v41.1/ 2.74.07.v41.1	7.4.0	7.4.12	13, 16
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U3	2.2.3e.v41.1/ 2.74.07.v41.1	7.4.0	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U3	2.2.3e.v41.1/ 2.74.07.v41.1	7.4.0	7.4.12	13, 16
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0	2.2.3e.v50.1/ 2.74.07.v50.1	7.4.0	7.4.12	23, 13

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U1	2.2.3e.v50.1/ 2.74.07.v50.1	7.4.0	7.4.12	23
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U2	2.2.3e.v50.1/ 2.74.07.v50.1	7.4.0	7.4.12	23

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2,C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.1	2.2.3e.v50.1/ 2.74.07.v50.1	7.4.0	7.4.12	23
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	7.4.23.0	7.4.0	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2,C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	7.4.23.0	7.4.0	7.4.12	
C200/ C210 M2,C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Windows Server 2012	7.4.23.0	7.4.0	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2,C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Xen Server 6.0.2	2.1.12b	7.4.0	7.4.12	6
C200/ C210 M2,C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Xen Server 6.1	2.2.1j	7.4.0	7.4.12	6

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	Broadcom	NetXtreme II 5709 Dual and Quad Port Gigabit Ethernet PCIe Adapter	Oracle VM 3.1.1	2.1.11	7.4.0	7.4.12	6
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.7 64bit	1.74.17 (NIC)	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.8 64bit	1.74.17 (NIC)	7.4.19	7.4.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.8 64bit	1.72.51-0 (NIC)	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.2 64bit	1.74.17 (NIC)	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.3 64bit	1.74.17 (NIC)	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.4 64bit	1.72.51-0 (NIC)	7.4.19	7.4.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.7 64bit	1.62.00-6	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.8 64bit	1.70.00-0	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.9 64bit	1.70.00-0 (NIC)	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 6.2 64bit	1.70.00-0	7.4.19	7.4.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 6.3 64bit	1.72.00-0	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	SUSE Linux Enterprise Server 11.2 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	7.4.19	7.4.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 10 8/11 (U10)	6.4.35	7.4.19	7.4.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 10 9/10 (U9)	6.4.35	7.4.19	7.4.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 11	6.4.37.1	7.4.19	7.4.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U2	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U2	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U3	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U3	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	7.4.19	7.4.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U1	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U2	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	7.4.19	7.4.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.1	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	7.4.19	7.4.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	7.4.19	7.4.13	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	7.4.19	7.4.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2012	7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	7.4.19	7.4.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Xen Server 6.0.2	1.70.35	7.4.19	7.4.13	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Xen Server 6.1	1.72.55	7.4.19	7.4.13	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Broadcom	NetXtreme II 57711 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle VM 3.1.1	1.70.00-0	7.4.19	7.4.13	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.7 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.8 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.9 64bit	1.72.51-0 (NIC)/ 2.7.2.2(iSCSI)	6.2.25	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.2 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.3 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.4 64bit	1.72.51-0 (NIC)/ 2.7.2.2(iSCSI)	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.7 64bit	1.62.00-6 (NIC)	6.2.25	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.8 64bit	1.70.00-0 (NIC)	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.9 64bit	1.72.50-0 (NIC)	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 6.2 64bit	1.70.00-0 (NIC)	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 6.3 64bit	1.72.00-0	6.2.25	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	SUSE Linux Enterprise Server 11.2 64bit	1.74.17 (NIC)/ 2.7.4.1f(iSCSI)	6.2.25	7.4.12	
C260 M2, C460 M2	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 10 9/10 (U9)	6.4.35	6.2.25	7.4.12	
C260 M2, C460 M2	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 10 8/11 (U10)	6.4.35	6.2.25	7.4.12	
C260 M2, C460 M2	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 11	vv6.4.37.1	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U2	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	6.2.25	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U2	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	6.2.25	7.4.12	17
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U3	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	6.2.25	7.4.12	17
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U3	1.74.17.v41.1 (NIC)/ 2.74.07.v41.1	6.2.25	7.4.12	17
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	6.2.25	7.4.12	17

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U1	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	6.2.25	7.4.12	17, 8
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U2	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	6.2.25	7.4.12	17
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.1	1.74.17.v50.1 (NIC)/ 2.74.07.v50.1	6.2.25	7.4.12	17
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	7.4.6.0(FC)/7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	6.2.25	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	7.4.6.0(FC)/7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2012	7.4.6.0(FC)/7.4.23.0 (NIC)/ 7.4.3.0(iSCSI)	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Xen Server 6.0.2	1.70.35 (NIC)	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Xen Server 6.1	1.72.55 (NIC)	6.2.25	7.4.12	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C22/C24 M3(SFF/ LFF),C420 M3	Broadcom	Broadcom 57712 10G BaseT Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle VM 3.1.1	1.70.00-0	6.2.25	7.4.12	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Red Hat Enterprise Linux 5.7 64bit	4.0.17	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Red Hat Enterprise Linux 5.8 64bit	4.0.17	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Red Hat Enterprise Linux 5.9 64bit	4.0.17	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Red Hat Enterprise Linux 6.2 64bit	4.0.17	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Red Hat Enterprise Linux 6.3 64bit	4.0.17	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Red Hat Enterprise Linux 6.4 64bit	4.0.1-k	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Oracle Linux 5.7 64bit	3.0.6-k2	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Oracle Linux 5.8 64bit	3.0.6-k	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Oracle Linux 5.9 64bit	3.4.8	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Oracle Linux 6.2 64bit	3.0.6-k	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Oracle Linux 6.3 64bit	3.2.10-k	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	SUSE Linux Enterprise Server 11.2 64bit	3.4.7	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Solaris 10 8/11 (U10)	v1.1.18	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	VMware vSphere ESX 4.1 U2	3.2.10	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	VMware vSphere ESXi 4.1 U2	3.2.10	1.6-1	v1.3.98	13, 16
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	VMware vSphere ESXi 5.0	4.0.17	1.6-1	v1.3.98	13
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	VMware vSphere ESXi 5.0 U1	4.0.17	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	VMware vSphere ESXi 5.0 U2	4.0.17	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	VMware vSphere ESXi 5.1	4.0.17	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	12.3.35.0	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Windows Server 2008 SP2 x64 w/ Hyper-V	12.3.35.0	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Windows Server 2012	12.3.35.0	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Xen Server 6.0.2	3.2.10	1.6-1	v1.3.98	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Xen Server 6.1	3.3.6	1.6-1	v1.3.98	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	Intel Ethernet Server Adapter I350-T4	Oracle VM 3.1.1	3.0.6-k2	1.6-1	v1.3.98	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.7 64bit	4.0.17	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.8 64bit	4.0.17	1.7-3	1.3.50	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.9 64bit	4.0.17	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.2 64bit	4.0.17	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.3 64bit	4.0.17	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.4 64bit	4.0.1-k	1.7-3	1.3.50	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Oracle Linux 5.7 64bit	3.0.6-k	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Oracle Linux 5.8 64bit	3.0.6-k	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Oracle Linux 5.9 64bit	3.4.8	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Oracle Linux 6.2 64bit	3.0.6-k	1.7-3	1.3.50	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Oracle Linux 6.3 64bit	3.2.10-k	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	SUSE Linux Enterprise Server 11.2 64bit	4.0.17	1.7-3	1.3.50	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Solaris 10 8/11 (U10)	1.1.18	1.7-3	1.3.50	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Solaris 10 9/10 (U9)	1.1.14	1.7-3	1.3.50	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Solaris 11	1.1.18	1.7-3	1.3.50	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U2	3.2.10	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U2	3.2.10	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U3	3.2.10	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U3	3.2.10	1.7-3	1.3.50	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0	4.0.17	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U1	4.0.17	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U2	4.0.17	1.7-3	1.3.50	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.1	4.0.17	1.7-3	1.3.50	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	11.17.27.0	1.7-3	1.3.50	
C200/ C210 M1 & M2, C200 M2(SFF), C250 M1 & M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	11.17.27.0	1.7-3	1.3.50	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Windows Server 2012	12.1.77.0	1.7-3	1.3.50	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Xen Server 6.0.2	3.2.10	1.7-3	1.3.50	
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Xen Server 6.1	3.3.6	1.7-3	1.3.50	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2, C200 M2(SFF), C250 M2, C260 M2, C460 M1 & M2	Intel	82576 based Quad Port Gigabit Ethernet PCIe Adapter	Oracle VM 3.1.1	3.0.6-k2	1.7-3	1.3.50	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.7 64bit	3.11.33	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.8 64bit	3.11.33	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 5.9 64bit	3.11.33	2.4-2	2.2.07	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.2 64bit	3.11.33	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.3 64bit	3.11.33	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Red Hat Enterprise Linux 6.4 64bit	3.9.15-k	2.4-2	2.2.07	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.7 64bit	3.2.10-NAPI	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.8 64bit	3.4.24-NAPI	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 5.9 64bit	3.10.16	2.4-2	2.2.07	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 6.2 64bit	3.4.24-NAPI	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle Linux 6.3 64bit	3.6.7-k	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	SUSE Linux Enterprise Server 11.2 64bit	3.11.33	2.4-2	2.2.07	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 10 8/11 (U10)	1.0.18	2.4-2	2.2.07	
C260 M2, C460 M2	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Solaris 10 9/10 (U9)	1.0.12	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U2	3.9.13-NAPI	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U2	3.9.13-NAPI	2.4-2	2.2.07	13, 16

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESX 4.1 U3	3.9.13-NAPI	2.4-2	2.2.07	13, 16
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 4.1 U3	3.9.13-NAPI	2.4-2	2.2.07	13, 16
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0	3.11.32iov	2.4-2	2.2.07	13

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U1	3.11.32iov	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.0 U2	3.11.32iov	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	VMware vSphere ESXi 5.1	3.11.32iov	2.4-2	2.2.07	13

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	3.2.61.0	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	3.2.61.0	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF),C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Windows Server 2012	3.2.61.0	2.4-2	2.2.07	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Xen Server 6.0.2	3.6.7-NAPI	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Xen Server 6.1	3.8.21-NAPI	2.4-2	2.2.07	
C260 M2, C460 M2, C220/ C240 M3(SFF/ LFF), C240 M3 NEBS, C22/C24 M3(SFF/ LFF), C420 M3	Intel	X540 Dual Port 10 Gigabit Ethernet PCIe Adapter	Oracle VM 3.1.1	3.4.8-k	2.4-2	2.2.07	

RAID Controller on Motherboard or PCIe Adapter Interoperability Matrix

Table 6 lists the RAID controller on motherboard or PCIe adapters that the Unified Computing System C Series Servers support.

Table 6: RAID Controller on Motherboard or PCIe Adapters

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200 M1	LSI	MegaRAID SAS 8708EM2	Red Hat Enterprise Linux 5.7 64bit	00.00.05.38-rh1	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	Red Hat Enterprise Linux 5.8 64bit	00.00.05.40-rh2	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	Red Hat Enterprise Linux 5.9 64bit	00.00.05.40-rc1	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	Red Hat Enterprise Linux 6.2 64bit	00.00.05.40-rh2	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	Red Hat Enterprise Linux 6.3 64bit	00.00.06.14-rh1	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	SUSE Linux Enterprise Server 11.2 64bit	00.00.05.38-rc1	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	Solaris 10 8/11 (U10)	2.9	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	VMware vSphere ESX 4.1 U2	00.00.05.30	1.40.272-1225	2.07.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200 M1	LSI	MegaRAID SAS 8708EM2	VMware vSphere ESXi 4.1 U2	00.00.05.30	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	VMware vSphere ESX 4.1 U3	00.00.05.30	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	VMware vSphere ESXi 4.1 U3	00.00.05.30	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	VMware vSphere ESXi 5.0	00.00.04.32.1vmw	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	VMware vSphere ESXi 5.0 U1	00.00.05.34-4vmw	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	VMware vSphere ESXi 5.0 U2	00.00.05.34-4vmw	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	4.32.0.64	1.40.272-1225	2.07.00	
C200 M1	LSI	MegaRAID SAS 8708EM2	Windows Server 2008 SP2 x64 w/ Hyper-V	4.32.0.64	1.40.272-1225	2.07.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	2.130.363-2183	3.24.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	2.130.363-2183	3.24.00	11
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Oracle Linux 5.7 64bit	00.00.05.34-rc1	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Oracle Linux 5.8 64bit	00.00.05.40-rc1	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Oracle Linux 5.9 64bit	00.00.05.40-rc1	2.130.363-2183	3.24.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Oracle Linux 6.2 64bit	00.00.05.40-rc1	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Oracle Linux 6.3 64bit	00.00.05.40-rc1	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Solaris 10 8/11 (U10)	2.9	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Solaris 10 9/10 (U9)	2.4	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	VMware vSphere ESX 4.1 U2	6.504.09.00	2.130.363-2183	3.24.00	31
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	VMware vSphere ESXi 4.1 U2	6.504.09.00	2.130.363-2183	3.24.00	31
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	VMware vSphere ESX 4.1 U3	6.504.09.00	2.130.363-2183	3.24.00	31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	VMware vSphere ESXi 4.1 U3	6.504.09.00	2.130.363-2183	3.24.00	31
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	VMware vSphere ESXi 5.0	00.00.05.34	2.130.363-2183	3.24.00	31
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	2.130.363-2183	3.24.00	31
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	2.130.363-2183	3.24.00	31
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	2.130.363-2183	3.24.00	31
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Windows Server 2012	6.504.4.0	2.130.363-2183	3.24.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Xen Server 6.0.2	00.00.05.41	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Xen Server 6.1	00.00.06.15	2.130.363-2183	3.24.00	
C200 M2	LSI	MegaRAID 9260-4i PCIe RAID Controller	Oracle VM 3.1.1	00.00.05.40-rc1	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	2.130.363-2183	3.24.00	11
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	2.130.363-2183	3.24.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Oracle Linux 5.7 64bit	00.00.05.34-rc1	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Oracle Linux 5.8 64bit	00.00.05.40-rc1	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Oracle Linux 5.9 64bit	00.00.05.40-rc1	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Oracle Linux 6.2 64bit	00.00.05.40-rc1	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Oracle Linux 6.3 64bit	00.00.05.40-rc1	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Solaris 10 8/11 (U10)	2.9	2.130.363-2183	3.24.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Solaris 10 9/10 (U9)	2.4	2.130363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Solaris 11	2.9	2.130363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESX 4.1 U2	6.504.09.00	2.130363-2183	3.24.00	31
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESXi 4.1 U2	6.504.09.00	2.130363-2183	3.24.00	31
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESX 4.1 U3	6.504.09.00	2.130363-2183	3.24.00	31
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESXi 4.1 U3	6.504.09.00	2.130363-2183	3.24.00	31
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESXi 5.0	00.00.05.34	2.130363-2183	3.24.00	31
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	2.130363-2183	3.24.00	31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	2.130.363-2183	3.24.00	31
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	2.130.363-2183	3.24.00	31
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	06.504.4.0	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	06.504.4.0	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Windows Server 2012	06.504.4.0	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Xen Server 6.0.2	00.00.05.41	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Xen Server 6.1	00.00.06.15	2.130.363-2183	3.24.00	
C200 M2(SFF)	LSI	MegaRAID 9260-8i PCIe RAID Controller	Oracle VM 3.1.1	00.00.05.40-rc1	2.130.363-2183	3.24.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	2.130.363-2183	3.25.00	11
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Oracle Linux 5.7 64bit	00.00.05.34-rc1	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Oracle Linux 5.8 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Oracle Linux 5.9 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Oracle Linux 6.2 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Oracle Linux 6.3 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Solaris 10 8/11 (U10)	2.9	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Solaris 10 9/10 (U9)	2.4	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Solaris 11	2.9	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESX 4.1 U2	6.504.09.00	2.130.363-2183	3.25.00	31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESXi 4.1 U2	6.504.09.00	2.130363-2183	3.25.00	31
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESX 4.1 U3	6.504.09.00	2.130363-2183	3.25.00	31
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESXi 4.1 U3	6.504.09.00	2.130363-2183	3.25.00	31
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESXi 5.0	00.00.05.34	2.130363-2183	3.25.00	31
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	2.130363-2183	3.25.00	31
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	2.130363-2183	3.25.00	31
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	2.130363-2183	3.25.00	31
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	06.504.4.0	2.130363-2183	3.25.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	06.504.4.0	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Windows Server 2012	06.504.4.0	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Xen Server 6.0.2	00.00.05.41	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Xen Server 6.1	00.00.06.15	2.130.363-2183	3.25.00	
C460 M1 & M2	LSI	MegaRAID 9260-8i PCIe RAID Controller	Oracle VM 3.1.1	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	2.130.363-2183	3.24.00	11

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	2.130.363-2183	3.24.00	
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Oracle Linux 5.7 64bit	00.00.05.34-rc1	2.130.363-2183	3.24.00	
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Oracle Linux 5.8 64bit	00.00.05.40-rc1	2.130.363-2183	3.24.00	
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Oracle Linux 5.9 64bit	00.00.05.40-rc1	2.130.363-2183	3.24.00	
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Oracle Linux 6.2 64bit	00.00.05.40-rc1	2.130.363-2183	3.24.00	
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Oracle Linux 6.3 64bit	00.00.05.40-rc1	2.130.363-2183	3.24.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	2.130.363-2183	3.24.00	
C210 M2, C250 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Solaris 10 8/11 (U10)	2.9	2.130.363-2183	3.24.00	
C210 M2, C250 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Solaris 10 9/10 (U9)	2.4	2.130.363-2183	3.24.00	
C210 M2, C250 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Solaris 11	2.9	2.130.363-2183	3.24.00	
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESX 4.1 U2	6.504.09.00	2.130.363-2183	3.24.00	31
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESXi 4.1 U2	6.504.09.00	2.130.363-2183	3.24.00	31
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESX 4.1 U3	6.504.09.00	2.130.363-2183	3.24.00	31
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESXi 4.1 U3	6.504.09.00	2.130.363-2183	3.24.00	31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESXi 5.0	00.00.05.34	2.130.363-2183	3.24.00	31
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	2.130.363-2183	3.24.00	31
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	2.130.363-2183	3.24.00	31
C210 M2, C250 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	2.130.363-2183	3.24.00	31
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	2.130.363-2183	3.24.00	
C210 M1 & M2, C250 M1 & M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	2.130.363-2183	3.24.00	
C210 M2, C250 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Windows Server 2012	6.504.4.0	2.130.363-2183	3.24.00	
C210 M2, C250 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Xen Server 6.0.2	00.00.05.41	2.130.363-2183	3.24.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C210 M2, C250 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Xen Server 6.1	00.00.06.15	2.130.363-2183	3.24.00	
C210 M2, C250 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Oracle VM 3.1.1	00.00.05.40-rc1	2.130.363-2183	3.24.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	2.130.363-2183	3.25.00	11
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	2.130.363-2183	3.25.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Oracle Linux 5.7 64bit	00.00.05.34-rc1	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Oracle Linux 5.8 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Oracle Linux 5.9 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Oracle Linux 6.2 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Oracle Linux 6.3 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Solaris 10 8/11 (U10)	2.9	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Solaris 10 9/10 (U9)	2.4	2.130.363-2183	3.25.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Solaris 11	2.9	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESX 4.1 U2	6.504.09.00	2.130.363-2183	3.25.00	31
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESXi 4.1 U2	6.504.09.00	2.130.363-2183	3.25.00	31
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESX 4.1 U3	6.504.09.00	2.130.363-2183	3.25.00	31
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESXi 4.1 U3	6.504.09.00	2.130.363-2183	3.25.00	31
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESXi 5.0	00.00.05.34	2.130.363-2183	3.25.00	31
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	2.130.363-2183	3.25.00	31
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	2.130.363-2183	3.25.00	31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	2.130.363-2183	3.25.00	31
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Windows Server 2012	6.504.4.0	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Xen Server 6.0.2	00.00.05.41	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Xen Server 6.1	00.00.06.15	2.130.363-2183	3.25.00	
C260 M2	LSI	MegaRAID 9261-8i PCIe RAID Controller	Oracle VM 3.1.1	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	Red Hat Enterprise Linux 5.7 64bit	3.04.20rh	1.32.09.00	6.34.00.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	Red Hat Enterprise Linux 5.8 64bit	3.04.20rh	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	Red Hat Enterprise Linux 5.9 64bit	3.04.20rh1	1.32.09.00	6.34.00.00	11
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	Red Hat Enterprise Linux 6.2 64bit	3.04.19	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	Red Hat Enterprise Linux 6.3 64bit	3.04.20	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	Red Hat Enterprise Linux 6.4 64bit	3.04.20	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	Oracle Linux 5.7 64bit	3.04.18	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	Oracle Linux 5.8 64bit	3.04.19	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	Oracle Linux 5.9 64bit	3.04.19	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	Oracle Linux 6.2 64bit	3.04.19	1.32.09.00	6.34.00.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C250 M1 & M2	LSI	SAS3081E-R PCIe RAID Controller	Oracle Linux 6.3 64bit	3.04.19	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081E-R PCIe RAID Controller	SUSE Linux Enterprise Server 11.2 64bit	4.28.00.00suse	1.32.09.00	6.34.00.00	
C250 M2	LSI	SAS3081E-R PCIe RAID Controller	Solaris 10 8/11 (U10)	1.109	1.32.09.00	6.34.00.00	
C250 M2	LSI	SAS3081E-R PCIe RAID Controller	Solaris 10 9/10 (U9)	2.4	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081E-R PCIe RAID Controller	VMware vSphere ESX 4.1 U2	4.21.00.01.1-8vmw	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081E-R PCIe RAID Controller	VMware vSphere ESXi 4.1 U2	4.21.00.01.1-8vmw	1.32.09.00	6.34.00.00	
C250 M2	LSI	SAS3081E-R PCIe RAID Controller	VMware vSphere ESX 4.1 U3	4.21.00.01.1-9vmw	1.32.09.00	6.34.00.00	
C250 M2	LSI	SAS3081E-R PCIe RAID Controller	VMware vSphere ESXi 4.1 U3	4.21.00.01.1-9vmw	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081E-R PCIe RAID Controller	VMware vSphere ESXi 5.0	4.23.01.00-5vmw	1.32.09.00	6.34.00.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	VMware vSphere ESXi 5.0 U1	4.23.01.00-5vmw	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	VMware vSphere ESXi 5.0 U2	4.23.01.00-5vmw	1.32.09.00	6.34.00.00	
C250 M2	LSI	SAS3081ER PCIe RAID Controller	VMware vSphere ESXi 5.1	4.23.01.00-6vmw	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	1.34.2.0	1.32.09.00	6.34.00.00	
C250 M1 & M2	LSI	SAS3081ER PCIe RAID Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	1.34.2.0	1.32.09.00	6.34.00.00	
C250 M2	LSI	SAS3081ER PCIe RAID Controller	Windows Server 2012	1.34.2.6	1.32.09.00	6.34.00.00	
C250 M2	LSI	SAS3081ER PCIe RAID Controller	Xen Server 6.0.2	4.22.00.00	1.32.09.00	6.34.00.00	
C250 M2	LSI	SAS3081ER PCIe RAID Controller	Xen Server 6.1	4.28.00.00	1.32.09.00	6.34.00.00	
C250 M2	LSI	SAS3081ER PCIe RAID Controller	Oracle VM 3.1.1	3.04.19	1.32.09.00	6.34.00.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Red Hat Enterprise Linux 5.7 64bit	3.04.18rh	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Red Hat Enterprise Linux 5.8 64bit	3.04.20rh	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Red Hat Enterprise Linux 5.9 64bit	3.04.20rh1	1.32.09.00	6.34.00.00	11
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Red Hat Enterprise Linux 6.2 64bit	3.04.19	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Red Hat Enterprise Linux 6.3 64bit	3.04.20	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Red Hat Enterprise Linux 6.4 64bit	3.04.20	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Oracle Linux 5.7 64bit	3.04.18	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Oracle Linux 5.8 64bit	3.04.19	1.32.09.00	6.34.00.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Oracle Linux 5.9 64bit	3.04.19	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Oracle Linux 6.2 64bit	3.04.19	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Oracle Linux 6.3 64bit	3.04.19	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	SUSE Linux Enterprise Server 11.2 64bit	4.28.00.00suse	1.32.09.00	6.34.00.00	
C200/ C210 M2	LSI	1064E Controller Based Mezzanine Adapter	Solaris 10 8/11 (U10)	1.109	1.32.09.00	6.34.00.00	
C200/ C210 M2	LSI	1064E Controller Based Mezzanine Adapter	Solaris 10 9/10 (U9)	1.100	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	VMware vSphere ESX 4.1 U2	4.21.00.01.1-8vmw	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	VMware vSphere ESXi 4.1 U2	4.21.00.01.1-8vmw	1.32.09.00	6.34.00.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	VMware vSphere ESX 4.1 U3	00.00.05.30	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	VMware vSphere ESXi 4.1 U3	00.00.05.30	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	VMware vSphere ESXi 5.0	4.23.01.00-5vmw	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	VMware vSphere ESXi 5.0 U1	4.23.01.00-5vmw	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	VMware vSphere ESXi 5.0 U2	4.23.01.00-5vmw	1.32.09.00	6.34.00.00	
C200/ C210 M2	LSI	1064E Controller Based Mezzanine Adapter	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	1.34.2.0	1.32.09.00	6.34.00.00	
C200/ C210 M1 & M2	LSI	1064E Controller Based Mezzanine Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	1.34.2.0	1.32.09.00	6.34.00.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2	LSI	1064E Controller Based Mezzanine Adapter	Windows Server 2012	1.34.2.6	1.32.09.00	6.34.00.00	
C200/ C210 M2	LSI	1064E Controller Based Mezzanine Adapter	Xen Server 6.0.2	4.22.00.00	1.32.09.00	6.34.00.00	
C200/ C210 M2	LSI	1064E Controller Based Mezzanine Adapter	Xen Server 6.1	4.28.00.00	1.32.09.00	6.34.00.00	
C200/ C210 M2	LSI	1064E Controller Based Mezzanine Adapter	Oracle VM 3.1.1	3.04.19	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Red Hat Enterprise Linux 5.7 64bit	3.04.18rh	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Red Hat Enterprise Linux 5.8 64bit	3.04.20rh	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Red Hat Enterprise Linux 5.9 64bit	3.04.20rh1	1.32.09.00	6.34.00.00	11
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Red Hat Enterprise Linux 6.2 64bit	3.04.19	1.32.09.00	6.34.00.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Red Hat Enterprise Linux 6.3 64bit	3.04.20	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Red Hat Enterprise Linux 6.4 64bit	3.04.20	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Oracle Linux 5.7 64bit	3.04.17	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Oracle Linux 5.8 64bit	3.04.18	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Oracle Linux 5.9 64bit	3.04.19	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Oracle Linux 6.2 64bit	3.04.19	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Oracle Linux 6.3 64bit	3.04.19	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	SUSE Linux Enterprise Server 11.2 64bit	4.28.00.00suse	1.32.09.00	6.34.00.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Solaris 10 8/11 (U10)	1.109	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Solaris 10 9/10 (U9)	1.100	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	VMware vSphere ESX 4.1 U2	4.21.00.01.1-8vmw	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	VMware vSphere ESXi 4.1 U2	4.21.00.01.1-8vmw	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	VMware vSphere ESX 4.1 U3	00.00.05.30	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	VMware vSphere ESXi 4.1 U3	00.00.05.30	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	VMware vSphere ESXi 5.0	4.23.01.00-5vmw	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	VMware vSphere ESXi 5.0 U1	4.23.01.00-5vmw	1.32.09.00	6.34.00.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	VMware vSphere ESXi 5.0 U2	4.23.01.00-5vmw	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	1.34.2.0	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Windows Server 2008 SP2 x64 w/ Hyper-V	1.34.2.0	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Windows Server 2012	1.34.2.6	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Xen Server 6.0.2	4.22.00.00	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Xen Server 6.1	4.28.00.00	1.32.09.00	6.34.00.00	
C200 M2(SFF)	LSI	1068E Controller Based Mezzanine Adapter	Oracle VM 3.1.1	3.04.19	1.32.09.00	6.34.00.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	2.130.363-2183	3.25.00	11
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Oracle Linux 5.7 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Oracle Linux 5.8 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Oracle Linux 5.9 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Oracle Linux 6.2 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Oracle Linux 6.3 64bit	00.00.05.40-rc1	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Solaris 10 8/11 (U10)	2.9	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Solaris 10 9/10 (U9)	2.4	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	VMware vSphere ESX 4.1 U2	06.504.09.00	2.130.363-2183	3.25.00	31
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	VMware vSphere ESXi 4.1 U2	06.504.09.00	2.130.363-2183	3.25.00	31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	VMware vSphere ESX 4.1 U3	06.504.09.00	2.130.363-2183	3.25.00	31
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	VMware vSphere ESXi 4.1 U3	06.504.09.00	2.130.363-2183	3.25.00	31
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	VMware vSphere ESXi 5.0	00.00.05.34	2.130.363-2183	3.25.00	31
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	2.130.363-2183	3.25.00	31
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	2.130.363-2183	3.25.00	31
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	2.130.363-2183	3.25.00	31
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	2.130.363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	2.130.363-2183	3.25.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Windows Server 2012	6.504.4.0	2.130363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Xen Server 6.0.2	00.00.05.41	2.130363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Xen Server 6.1	00.00.06.15	2.130363-2183	3.25.00	
C200/ C210 M2 , C200 M2(SFF)	LSI	MegaRAID 9280-4i/4e PCIe RAID Controller	Oracle VM 3.1.1	00.00.05.40-rc1	2.130363-2183	3.25.00	
C460 M1 & M2, C22/C24 M3(SFF/ LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	2.130364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/ LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	2.130364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/ LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	2.130364-2185	4.31.00	11, 25
C460 M1 & M2, C22/C24 M3(SFF/ LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	2.130364-2185	4.31.00	25

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	2.130.364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	2.130.364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Oracle Linux 5.7 64bit	00.00.05.40-rc1	2.130.364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Oracle Linux 5.8 64bit	00.00.05.40-rc1	2.130.364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Oracle Linux 5.9 64bit	00.00.05.40-rc1	2.130.364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Oracle Linux 6.2 64bit	00.00.05.40-rc1	2.130.364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Oracle Linux 6.3 64bit	00.00.05.40-rc1	2.130.364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	2.130.364-2185	4.31.00	25

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Solaris 10 8/11 (U10)	2.9	2.130.364.2185	4.31.00	25
C460 M1 & M2	LSI	MegaRAID 9240-8i PCIe RAID Controller	Solaris 10 9/10 (U9)	2.4	2.130.364.2185	4.31.00	25
C460 M1 & M2	LSI	MegaRAID 9240-8i PCIe RAID Controller	Solaris 11	2.9	2.130.364.2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	VMware vSphere ESX 4.1 U2	06.504.09.00	2.130.364.2185	4.31.00	25, 31
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	VMware vSphere ESXi 4.1 U2	06.504.09.00	2.130.364.2185	4.31.00	25, 13, 16, 31
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	VMware vSphere ESX 4.1 U3	06.504.09.00	2.130.364.2185	4.31.00	25, 13, 16, 31
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	VMware vSphere ESXi 4.1 U3	06.504.09.00	2.130.364.2185	4.31.00	25, 13, 16, 31
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	VMware vSphere ESXi 5.0	00.00.05.34	2.130.364.2185	4.31.00	25, 13, 31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2, C22/C24 M3(SFF/ LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	2.130.364-2185	4.31.00	25, 31
C460 M1 & M2, C22/C24 M3(SFF/ LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	2.130.364-2185	4.31.00	25, 31
C460 M1 & M2, C22/C24 M3(SFF/ LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	2.130.364-2185	4.31.00	25, 31
C460 M1 & M2, C22/C24 M3(SFF/ LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	2.130.364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/ LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	2.130.364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/ LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Windows Server 2012	6.504.4.0	2.130.364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/ LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Xen Server 6.0.2	00.00.05.41	2.130.364-2185	4.31.00	25
C460 M1 & M2, C22/C24 M3(SFF/ LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Xen Server 6.1	00.00.06.15	2.130.364-2185	4.31.00	25

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C460 M1 & M2, C22/C24 M3(SFF/LFF)	LSI	MegaRAID 9240-8i PCIe RAID Controller	Oracle VM 3.1.1	00.00.05.40-rc1	2.130364-2185	4.31.00	25
C220/C240 M3(SFF/LFF)	LSI	LSI 9266-8i/9266CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	3.220.75-2196	5.38.00	22
C220/C240 M3(SFF/LFF)	LSI	LSI 9266-8i/9266CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	3.220.75-2196	5.38.00	22
C220/C240 M3(SFF/LFF)	LSI	LSI 9266-8i/9266CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	3.220.75-2196	5.38.00	11, 22
C220/C240 M3(SFF/LFF)	LSI	LSI 9266-8i/9266CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	3.220.75-2196	5.38.00	22
C220/C240 M3(SFF/LFF)	LSI	LSI 9266-8i/9266CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	3.220.75-2196	5.38.00	22
C220/C240 M3(SFF/LFF)	LSI	LSI 9266-8i/9266CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	3.220.75-2196	5.38.00	22
C220/C240 M3(SFF/LFF)	LSI	LSI 9266-8i/9266CV-8i MegaRaid SAS HBA	Oracle Linux 5.7 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	22

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	Oracle Linux 5.8 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	22
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	Oracle Linux 5.9 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	22
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	Oracle Linux 6.2 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	22
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	Oracle Linux 6.3 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	22
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	3.220.75-2196	5.38.00	22
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	Solaris 10 8/11 (U10)	v2.9	3.220.75-2196	5.38.00	22
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	VMware vSphere ESX 4.1 U2	06.504.09.00	3.220.75-2196	5.38.00	22, 31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U2	06.504.09.00	3.220.75-2196	5.38.00	22, 13, 16, 31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	VMware vSphere ESX 4.1 U3	06.504.09.00	3.220.75-2196	5.38.00	22, 13, 16, 31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U3	06.504.09.00	3.220.75-2196	5.38.00	22, 13, 16, 31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.0	00.00.05.34	3.220.75-2196	5.38.00	13, 22, 31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	3.220.75-2196	5.38.00	22, 31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	3.220.75-2196	5.38.00	22, 31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	3.220.75-2196	5.38.00	13, 22, 31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	3.220.75-2196	5.38.00	22
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	3.220.75-2196	5.38.00	22

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	Windows Server 2012	6.504.4.0	3.220.75-2196	5.38.00	22
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	Xen Server 6.0.2	00.00.05.41	3.220.75-2196	5.38.00	22
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	Xen Server 6.1	00.00.06.15	3.220.75-2196	5.38.00	22
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9266-8i/ 9266CV-8i MegaRaid SAS HBA	Oracle VM 3.1.1	00.00.05.40-rc1	3.220.75-2196	5.38.00	22
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	2.130.364-2185	4.31.00	
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	2.130.364-2185	4.31.00	
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	2.130.364-2185	4.31.00	11
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	2.130.364-2185	4.31.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/C240 M3(SFF/LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	2.130.364.2185	4.31.00	
C220/C240 M3(SFF/LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	2.130.364.2185	4.31.00	
C220/C240 M3(SFF/LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Oracle Linux 5.7 64bit	00.00.05.40-rc1	2.130.364.2185	4.31.00	
C220/C240 M3(SFF/LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Oracle Linux 5.8 64bit	00.00.05.40-rc1	2.130.364.2185	4.31.00	
C220/C240 M3(SFF/LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Oracle Linux 5.9 64bit	00.00.05.40-rc1	2.130.364.2185	4.31.00	
C220/C240 M3(SFF/LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Oracle Linux 6.2 64bit	00.00.05.40-rc1	2.130.364.2185	4.31.00	
C220/C240 M3(SFF/LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Oracle Linux 6.3 64bit	00.00.05.40-rc1	2.130.364.2185	4.31.00	
C220/C240 M3(SFF/LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	2.130.364.2185	4.31.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Solaris 10 8/11 (U10)	03.03.00	2.130.364-2185	4.31.00	
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	VMware vSphere ESX 4.1 U2	06.504.09.00	2.130.364-2185	4.31.00	
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	VMware vSphere ESXi 4.1 U2	06.504.09.00	2.130.364-2185	4.31.00	13, 16
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	VMware vSphere ESX 4.1 U3	06.504.09.00	2.130.364-2185	4.31.00	13, 16
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	VMware vSphere ESXi 4.1 U3	06.504.09.00	2.130.364-2185	4.31.00	13, 16
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	VMware vSphere ESXi 5.0	00.00.05.34	2.130.364-2185	4.31.00	13
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	2.130.364-2185	4.31.00	
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	2.130.364-2185	4.31.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	2.130364-2185	4.31.00	
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	2.130364-2185	4.31.00	
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	2.130364-2185	4.31.00	
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Windows Server 2012	6.504.4.0	2.130364-2185	4.31.00	
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Xen Server 6.0.2	00.00.05.41	2.130364-2185	4.31.00	
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Xen Server 6.1	00.00.06.15	2.130364-2185	4.31.00	
C220/ C240 M3(SFF/ LFF)	LSI	Cisco UCSC RAID SAS 2008M-8i	Oracle VM 3.1.1	00.00.05.40-rc1	2.130364-2185	4.31.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	I/O Controller Hub 10 RAID (ICH10R)	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	13.21.614.2010			2
C200/ C210 M1 & M2, C200 M2(SFF)	Intel	I/O Controller Hub 10 RAID (ICH10R)	Windows Server 2008 SP2 x64 w/ Hyper-V	13.21.614.2010			2
C220 M3 SFF , C220 M3 LFF, C240 M3 SFF, C22 M3 SFF, C22 M3 LFF, C24 M3 SFF	LSI	LSI Embedded SWRAID (MegaSR)	Red Hat Enterprise Linux 5.7 64bit	15.00.0725.2012			2, 21
C220 M3 SFF , C220 M3 LFF, C240 M3 SFF, C22 M3 SFF, C22 M3 LFF, C24 M3 SFF	LSI	LSI Embedded SWRAID (MegaSR)	Red Hat Enterprise Linux 5.8 64bit	15.00.0725.2012			2, 21
C220 M3 SFF , C220 M3 LFF, C240 M3 SFF, C22 M3 SFF, C22 M3 LFF, C24 M3 SFF	LSI	LSI Embedded SWRAID (MegaSR)	Red Hat Enterprise Linux 6.2 64bit	15.00.0725.2012			2, 21

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220 M3 SFF , C220 M3 LFF, C240 M3 SFF, C22 M3 SFF, C22 M3 LFF, C24 M3 SFF	LSI	LSI Embedded SWRAID (MegaSR)	Red Hat Enterprise Linux 6.3 64bit	15.00.0725.2012			2, 21
C220 M3 SFF , C220 M3 LFF, C240 M3 SFF, C22 M3 SFF, C22 M3 LFF, C24 M3 SFF	LSI	LSI Embedded SWRAID (MegaSR)	SUSE Linux Enterprise Server 11.2 64bit	15.00.0725.2012			2, 20, 21
C220 M3 SFF , C220 M3 LFF, C240 M3 SFF, C22 M3 SFF, C22 M3 LFF, C24 M3 SFF	LSI	LSI Embedded SWRAID (MegaSR)	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	15.0.811.2012			2, 21
C220 M3 SFF , C220 M3 LFF, C240 M3 SFF, C22 M3 SFF, C22 M3 LFF, C24 M3 SFF	LSI	LSI Embedded SWRAID (MegaSR)	Windows Server 2008 SP2 x64 w/ Hyper-V	15.0.811.2012			2, 21

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220 M3 SFF , C220 M3 LFF, C240 M3 SFF, C22 M3 SFF, C22 M3 LFF, C24 M3 SFF	LSI	LSI Embedded SWRAID (MegaSR)	Windows Server 2012 x64	15.0.811.2012			2, 21
C220 M3 LFF	Intel	Intel Embedded SWRAID (RSTe)	Red Hat Enterprise Linux 6.2 64bit	1.0.0-rh			2
C220 M3 LFF	Intel	Intel Embedded SWRAID (RSTe)	Red Hat Enterprise Linux 6.3 64bit	1.1.0-rh			2
C22/C24 M3(SFF/ LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/ LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/ LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	3.220.75-2196	5.38.00	11
C22/C24 M3(SFF/ LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/ LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	3.220.75-2196	5.38.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Oracle Linux 5.7 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Oracle Linux 5.8 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Oracle Linux 5.9 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Oracle Linux 6.2 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Oracle Linux 6.3 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Solaris 10 8/11 (U10)	v2.9	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	VMware vSphere ESX 4.1 U2	06.504.09.00	3.220.75-2196	5.38.00	31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U2	06.504.09.00	3.220.75-2196	5.38.00	13, 16, 31
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	VMware vSphere ESX 4.1 U3	06.504.09.00	3.220.75-2196	5.38.00	13, 16, 31
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U3	06.504.09.00	3.220.75-2196	5.38.00	13, 16, 31
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.0	00.00.05.34	3.220.75-2196	5.38.00	13, 31
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	3.220.75-2196	5.38.00	31
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	3.220.75-2196	5.38.00	31
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	3.220.75-2196	5.38.00	31
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	3.220.75-2196	5.38.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Windows Server 2012	6.504.4.0	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Xen Server 6.0.2	00.00.05.41	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Xen Server 6.1	00.00.06.15	3.220.75-2196	5.38.00	
C22/C24 M3(SFF/LFF)	LSI	LSI 9265CV-8i MegaRaid SAS HBA	Oracle VM 3.1.1	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	2.130.364-2185	4.31.00	11
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	2.130.364-2185	4.31.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Oracle Linux 5.7 64bit	00.00.05.40-rc1	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Oracle Linux 5.8 64bit	00.00.05.40-rc1	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Oracle Linux 5.9 64bit	00.00.05.40-rc1	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Oracle Linux 6.2 64bit	00.00.05.40-rc1	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Oracle Linux 6.3 64bit	00.00.05.40-rc1	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Solaris 10 8/11 (U10)	v2.9	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	VMware vSphere ESX 4.1 U2	06.504.09.00	2.130.364-2185	4.31.00	31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U2	06.504.09.00	2.130.364.2185	4.31.00	13, 16, 31
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	VMware vSphere ESX 4.1 U3	06.504.09.00	2.130.364.2185	4.31.00	13, 16, 31
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U3	06.504.09.00	2.130.364.2185	4.31.00	13, 16, 31
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	VMware vSphere ESXi 5.0	00.00.05.34	2.130.364.2185	4.31.00	1, 31
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	2.130.364.2185	4.31.00	31
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	2.130.364.2185	4.31.00	31
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	2.130.364.2185	4.31.00	31
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	2.130.364.2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	2.130.364.2185	4.31.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Windows Server 2012	6.504.4.0	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Xen Server 6.0.2	00.00.05.41	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Xen Server 6.1	00.00.06.15	2.130.364-2185	4.31.00	
C22 M3 SFF, C22 M3 LFF	LSI	LSI 9220-4i MegaRaid SAS HBA	Oracle VM 3.1.1	00.00.05.40-rc1	2.130.364-2185	4.31.00	
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	2.130.364-2185	4.31.00	
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	2.130.364-2185	4.31.00	
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	2.130.364-2185	4.31.00	11
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	2.130.364-2185	4.31.00	
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	2.130.364-2185	4.31.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C22/C24 M3(SFF),C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	2.130.364.2185	4.31.00	
C22/C24 M3(SFF),C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Oracle Linux 5.7 64bit	00.00.05.40-rc1	2.130.364.2185	4.31.00	
C22/C24 M3(SFF),C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Oracle Linux 5.8 64bit	00.00.05.40-rc1	2.130.364.2185	4.31.00	
C22/C24 M3(SFF),C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Oracle Linux 5.9 64bit	00.00.05.40-rc1	2.130.364.2185	4.31.00	
C22/C24 M3(SFF),C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Oracle Linux 6.2 64bit	00.00.05.40-rc1	2.130.364.2185	4.31.00	
C22/C24 M3(SFF),C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Oracle Linux 6.3 64bit	00.00.05.40-rc1	2.130.364.2185	4.31.00	
C22/C24 M3(SFF),C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	2.130.364.2185	4.31.00	
C22/C24 M3(SFF),C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Solaris 10 8/11 (U10)	v2.9	2.130.364.2185	4.31.00	
C22/C24 M3(SFF),C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	VMware vSphere ESX 4.1 U2	06.504.09.00	2.130.364.2185	4.31.00	31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U2	06.504.09.00	2.130.364-2185	4.31.00	13, 16, 31
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	VMware vSphere ESX 4.1 U3	06.504.09.00	2.130.364-2185	4.31.00	13, 16, 31
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U3	06.504.09.00	2.130.364-2185	4.31.00	13, 16, 31
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.0	00.00.05.34	2.130.364-2185	4.31.00	1, 31
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	2.130.364-2185	4.31.00	31
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	2.130.364-2185	4.31.00	31
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	2.130.364-2185	4.31.00	31
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	2.130.364-2185	4.31.00	
C22/C24 M3(SFF)C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	2.130.364-2185	4.31.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C22/C24 M3(SFF), C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Windows Server 2012	6.504.4.0	2.130.364-2185	4.31.00	
C22/C24 M3(SFF), C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Xen Server 6.0.2	00.00.05.41	2.130.364-2185	4.31.00	
C22/C24 M3(SFF), C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Xen Server 6.1	00.00.06.15	2.130.364-2185	4.31.00	
C22/C24 M3(SFF), C24 M3(LFF)	LSI	LSI 9220-8i MegaRaid SAS HBA	Oracle VM 3.1.1	00.00.05.40-rc1	2.130.364-2185	4.31.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	3.220.75-2196	5.38.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Oracle Linux 5.7 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Oracle Linux 5.8 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Oracle Linux 5.9 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Oracle Linux 6.2 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Oracle Linux 6.3 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	3.220.75-2196	5.38.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Solaris 10 8/11 (U10)	v2.9	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	VMware vSphere ESX 4.1 U2	06.504.09.00	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U2	06.504.09.00	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	VMware vSphere ESX 4.1 U3	06.504.09.00	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U3	06.504.09.00	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.0	00.00.05.34	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	3.220.75-2196	5.38.00	31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Windows Server 2012	6.504.4.0	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Xen Server 6.0.2	00.00.05.41	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Xen Server 6.1	00.00.06.15	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9271CV-8i MegaRaid SAS HBA	Oracle VM 3.1.1	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	3.220.75-2196	5.38.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Oracle Linux 5.7 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Oracle Linux 5.8 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Oracle Linux 5.9 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Oracle Linux 6.2 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Oracle Linux 6.3 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Solaris 10 8/11 (U10)	v2.9	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	VMware vSphere ESX 4.1 U2	06.504.09.00	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U2	06.504.09.00	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	VMware vSphere ESX 4.1 U3	06.504.09.00	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U3	06.504.09.00	3.220.75-2196	5.38.00	31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	VMware vSphere ESXi 5.0	00.00.05.34	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	3.220.75-2196	5.38.00	31
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Windows Server 2012	6.504.4.0	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Xen Server 6.0.2	00.00.05.41	3.220.75-2196	5.38.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Xen Server 6.1	00.00.06.15	3.220.75-2196	5.38.00	
C420 M3, C220/ C240 M3(SFF/ LFF)	LSI	LSI 9286CV-8e MegaRaid SAS HBA	Oracle VM 3.1.1	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Red Hat Enterprise Linux 5.7 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Red Hat Enterprise Linux 5.8 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Red Hat Enterprise Linux 5.9 64bit	00.00.06.15-rh	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Red Hat Enterprise Linux 6.2 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Red Hat Enterprise Linux 6.3 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Red Hat Enterprise Linux 6.4 64bit	06.504.01.00-rh1	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Oracle Linux 5.7 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Oracle Linux 5.8 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Oracle Linux 5.9 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Oracle Linux 6.2 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Oracle Linux 6.3 64bit	00.00.05.40-rc1	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	SUSE Linux Enterprise Server 11.2 64bit	06.504.01.00	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Solaris 10 8/11 (U10)	v2.9	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	VMware vSphere ESX 4.1 U2	06.504.09.00	3.220.75-2196	5.38.00	31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U2	06.504.09.00	3.220.75-2196	5.38.00	31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	VMware vSphere ESX 4.1 U3	06.504.09.00	3.220.75-2196	5.38.00	31

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	VMware vSphere ESXi 4.1 U3	06.504.09.00	3.220.75-2196	5.38.00	31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	VMware vSphere ESXi 5.0	00.00.05.34	3.220.75-2196	5.38.00	31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U1	00.00.05.34-1vmw	3.220.75-2196	5.38.00	31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	VMware vSphere ESXi 5.0 U2	00.00.05.34-1vmw	3.220.75-2196	5.38.00	31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	VMware vSphere ESXi 5.1	00.00.05.34-4vmw	3.220.75-2196	5.38.00	31
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	6.504.4.0	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Windows Server 2008 SP2 x64 w/ Hyper-V	6.504.4.0	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Windows Server 2012	6.504.4.0	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Xen Server 6.0.2	00.00.05.41	3.220.75-2196	5.38.00	

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Xen Server 6.1	00.00.06.15	3.220.75-2196	5.38.00	
C220/ C240 M3(SFF/ LFF)	LSI	LSI 9285CV-8e MegaRaid SAS HBA	Oracle VM 3.1.1	00.00.05.40-rc1	3.220.75-2196	5.38.00	

Storage Controller Interoperability Matrix

Table 7 lists the storage controllers that the Unified Computing System C Series Servers support.

Table 7: Storage Controllers

UCS Server	Vendor	Storage Controller Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C210 M2	LSI	LSI 9201 Mass Storage Controller	Red Hat Enterprise Linux 5.7 64bit	3.04.18rh	11.00.00.00-IT	7.11.00.00	11
C210 M2	LSI	LSI 9201 Mass Storage Controller	Red Hat Enterprise Linux 5.8 64bit	3.04.20rh	11.00.00.00-IT	7.11.00.00	11
C210 M2	LSI	LSI 9201 Mass Storage Controller	Red Hat Enterprise Linux 5.9 64bit	3.04.20rh	11.00.00.00-IT	7.11.00.00	11
C210 M2	LSI	LSI 9201 Mass Storage Controller	Red Hat Enterprise Linux 6.2 64bit	3.04.19	11.00.00.00-IT	7.11.00.00	11
C210 M2	LSI	LSI 9201 Mass Storage Controller	Red Hat Enterprise Linux 6.3 64bit	3.04.20	11.00.00.00-IT	7.11.00.00	11

UCS Server	Vendor	Storage Controller Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C210 M2	LSI	LSI 9201 Mass Storage Controller	Red Hat Enterprise Linux 6.4 64bit	3.04.20	11.00.00.00-IT	7.11.00.00	11
C210 M2	LSI	LSI 9201 Mass Storage Controller	Oracle Linux 5.7 64bit	3.04.18	11.00.00.00-IT	7.11.00.00	
C210 M2	LSI	LSI 9201 Mass Storage Controller	Oracle Linux 5.8 64bit	3.04.19	11.00.00.00-IT	7.11.00.00	
C210 M2	LSI	LSI 9201 Mass Storage Controller	Oracle Linux 5.9 64bit	3.04.19	11.00.00.00-IT	7.11.00.00	
C210 M2	LSI	LSI 9201 Mass Storage Controller	Oracle Linux 6.2 64bit	3.04.19	11.00.00.00-IT	7.11.00.00	
C210 M2	LSI	LSI 9201 Mass Storage Controller	Oracle Linux 6.3 64bit	3.04.19	11.00.00.00-IT	7.11.00.00	
C210 M2	LSI	LSI 9201 Mass Storage Controller	SUSE Linux Enterprise Server 11.2 64bit	4.28.00.00suse	11.00.00.00-IT	7.11.00.00	
C210 M2	LSI	LSI 9201 Mass Storage Controller	Windows Server 2008 R2 SP1 x64 w/ Hyper-V	2.0.49.0	11.00.00.00-IT	7.11.00.00	

UCS Server	Vendor	Storage Controller Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS	Notes
C210 M2	LSI	LSI 9201 Mass Storage Controller	Windows Server 2008 SP2 x64 w/ Hyper-V	2.0.49.0	11.00.00.00-HT	7.11.00.00	
C210 M2	LSI	LSI 9201 Mass Storage Controller	Windows Server 2012	2.0.55.84	11.00.00.00-HT	7.11.00.00	
C210 M2	LSI	LSI 9201 Mass Storage Controller	Xen Server 6.0.2	00.00.05.41	11.00.00.00-HT	7.11.00.00	
C210 M2	LSI	LSI 9201 Mass Storage Controller	Xen Server 6.1	00.00.05.41	11.00.00.00-HT	7.11.00.00	
C210 M2	LSI	LSI 9201 Mass Storage Controller	Oracle VM 3.1.1	00.00.05.40-rc1	11.00.00.00-HT	7.11.00.00	

PCIe Flash Storage Interoperability Matrix

Table 8 lists the PCIe flash storage devices that the Unified Computing System C Series Servers support.

Table 8: PCIe Flash Storage Devices

UCS Server	Vendor	Flash Device Model	Operating System	Adapter Driver	Adapter Firmware	Notes
C460 M2	Fusion IO	Fusion-io MLC ioDrive -1.2TB	Red Hat Enterprise Linux 5.6 64bit	3.2.2	v7.1.13	
C460 M2	Fusion IO	Fusion-io MLC ioDrive -1.2TB	SUSE Linux Enterprise Server 11.1 64bit	3.1.5	v7.1.13	

UCS Server	Vendor	Flash Device Model	Operating System	Adapter Driver	Adapter Firmware	Notes
C460 M2	Fusion IO	Fusion-io MLC ioDrive -1.2TB	Windows Server 2008 R2 SP1 x64 w/Hyper-V	3.2.2	v7.1.13	
C460 M2	Fusion IO	Fusion-io MLC ioDrive -1.2TB	Windows Server 2008 SP2 x64 w/Hyper-V	3.2.2	v7.1.13	
C460 M2	Fusion IO	Fusion-io MLC ioDrive -1.2TB	VMware vSphere ESXi 4.1 U1	3.2.2	v7.1.13	
C200/C210 M2, C200 M2(SFF), C250 M2, C460 M2	Fusion IO	Fusion-io MLC ioDrive - 640GB/ 320GB	Red Hat Enterprise Linux 5.6 64bit	3.2.2	v7.1.13	
C200/C210 M2, C200 M2(SFF), C250 M2, C460 M2	Fusion IO	Fusion-io MLC ioDrive - 640GB/ 320GB	SUSE Linux Enterprise Server 11.1 64bit	3.1.5	v7.1.13	
C200/C210 M2, C200 M2(SFF), C250 M2, C460 M2	Fusion IO	Fusion-io MLC ioDrive - 640GB/ 320GB	Windows Server 2008 R2 SP1 x64 w/Hyper-V	3.2.2	v7.1.13	
C200/C210 M2, C200 M2(SFF), C250 M2, C460 M2	Fusion IO	Fusion-io MLC ioDrive - 640GB/ 320GB	Windows Server 2008 SP2 x64 w/Hyper-V	3.2.2	v7.1.13	
C200/C210 M2, C200 M2(SFF), C250 M2, C460 M2	Fusion IO	Fusion-io MLC ioDrive - 640GB/ 320GB	VMware vSphere ESXi 4.1 U1	3.2.2	v7.1.13	

UCS Server	Vendor	Flash Device Model	Operating System	Adapter Driver	Adapter Firmware	Notes
C220/C240 M3(SFF/LFF), C260 M2, C460 M2, C420M3	Fusion IO	Fusion-io MLC ioDrive2 365GB/ 785GB/ 1.2TB	Red Hat Enterprise Linux 5.7 64bit	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF), C260 M2, C460 M2, C420M3	Fusion IO	Fusion-io MLC ioDrive2 365GB/ 785GB/ 1.2TB	Red Hat Enterprise Linux 5.8 64bit	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF), C260 M2, C460 M2, C420M3	Fusion IO	Fusion-io MLC ioDrive2 365GB/ 785GB/ 1.2TB	Red Hat Enterprise Linux 6.2 64bit	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF), C260 M2, C460 M2, C420M3	Fusion IO	Fusion-io MLC ioDrive2 365GB/ 785GB/ 1.2TB	Red Hat Enterprise Linux 6.3 64bit	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF), C260 M2, C460 M2, C420M3	Fusion IO	Fusion-io MLC ioDrive2 365GB/ 785GB/ 1.2TB	SUSE Linux Enterprise Server 11.2 64bit	3.2.2	V7.1.13	
C260 M2, C460 M2	Fusion IO	Fusion-io MLC ioDrive2 365GB	SLES for SAP Applications 11	3.1.5	V7.1.13	
C260 M2, C460 M2	Fusion IO	Fusion-io MLC ioDrive2 365GB	SLES for SAP Applications 11	3.2.2	V7.1.13	

UCS Server	Vendor	Flash Device Model	Operating System	Adapter Driver	Adapter Firmware	Notes
C220/C240 M3(SFF/LFF), C260 M2, C460 M2, C420M3	Fusion IO	Fusion-io MLC ioDrive2 365GB/ 785GB/ 1.2TB	VMware vSphere ESXi 5.0	3.2.2	V7.1.13	13
C220/C240 M3(SFF/LFF), C260 M2, C460 M2, C420M3	Fusion IO	Fusion-io MLC ioDrive2 365GB/ 785GB/ 1.2TB	VMware vSphere ESXi 5.0 U1	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF), C260 M2, C460 M2, C420M3	Fusion IO	Fusion-io MLC ioDrive2 365GB/ 785GB/ 1.2TB	Windows Server 2008 R2 SP1 x64 w/Hyper-V	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF), C460 M2	Fusion IO	Fusion-io MLC ioDrive2 Duo 2.4TB	Red Hat Enterprise Linux 5.7 64bit	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF), C460 M2	Fusion IO	Fusion-io MLC ioDrive2 Duo 2.4TB	Red Hat Enterprise Linux 5.8 64bit	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF), C460 M2	Fusion IO	Fusion-io MLC ioDrive2 Duo 2.4TB	Red Hat Enterprise Linux 6.2 64bit	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF), C460 M2	Fusion IO	Fusion-io MLC ioDrive2 Duo 2.4TB	Red Hat Enterprise Linux 6.3 64bit	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF), C460 M2	Fusion IO	Fusion-io MLC ioDrive2 Duo 2.4TB	VMware vSphere ESXi 5.0	3.2.2	V7.1.13	13

UCS Server	Vendor	Flash Device Model	Operating System	Adapter Driver	Adapter Firmware	Notes
C220/C240 M3(SFF/LFF), C460 M2	Fusion IO	Fusion-io MLC ioDrive2 Duo 2.4TB	VMware vSphere ESXi 5.0 U1	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF), C460 M2	Fusion IO	Fusion-io MLC ioDrive2 Duo 2.4TB	VMware vSphere ESXi 5.0 U2	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF), C460 M2	Fusion IO	Fusion-io MLC ioDrive2 Duo 2.4TB	Windows Server 2008 R2 SP1 x64 w/Hyper-V	3.2.2	V7.1.13	
C220/C240 M3(SFF/LFF)	Virident	Virident FlashMAX II 2.2TB	Red Hat Enterprise Linux 6.2 64bit	3.2.2	3.1.1	
C220/C240 M3(SFF/LFF)	Virident	Virident FlashMAX II 2.2TB	Red Hat Enterprise Linux 6.3 64bit	3.2.2	3.1.1	

Graphics Processing Unit Interoperability Matrix

Table 9 lists the graphics processing units that the Unified Computing System C Series Servers support.

Table 9: Graphics Processing Units

UCS Server	Vendor	GPU Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS
C460 M2	NVIDIA	NVIDIA Display controller	Windows Server 2008 R2 SP1 x64 w/Hyper-V	3.1.1.172	3.20	
C460 M2	NVIDIA	NVIDIA Display controller	Red Hat Enterprise Linux 5.8 64bit	3.1.1.172	3.20	

UCS Server	Vendor	GPU Model	Operating System	Adapter Driver	Adapter Firmware	Adapter Boot Code / BIOS
C460 M2	NVIDIA	NVIDIA Display controller	Red Hat Enterprise Linux 6.2 64bit	3.1.1.172	3.20	
C460 M2	NVIDIA	NVIDIA Display controller	SUSE Linux Enterprise Server 11.2 64bit	3.1.1.172	3.20	
C240 M3	NVIDIA	NVIDIA Display controller	Windows Server 2012 w/Hyper-V	310.90	F0.47.10.00.00	80.07.6D.00.01/04
C240 M3	NVIDIA	NVIDIA Display controller	Xen Server 6.1		F0.47.10.00.00	80.07.6D.00.01/04
C240 M3	NVIDIA	NVIDIA Display controller	Windows Server 2012 w/Hyper-V	310.90	F0.47.0B.00.00	80.04.60.00.20/21
C240 M3	NVIDIA	NVIDIA Display controller	Xen Server 6.1		F0.47.0B.00.00	80.04.60.00.20/21

PCoIP Adapter Interoperability Matrix

Table 10 lists the PCoIP adapters that the Unified Computing System C Series Servers support.

Table 10: PCoIP Adapters

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware
C220/C240 M3(SFF/LFF)	Teradici	APEX2800	VMware vSphere ESXi 4.1 U2	15907	15907
C220/C240 M3(SFF/LFF)	Teradici	APEX2800	VMware vSphere ESXi 5.0	15907	15907
C220/C240 M3(SFF/LFF)	Teradici	APEX2800	VMware vSphere ESXi 5.0 U1	15907	15907

UCS Server	Vendor	Adapter Model	Operating System	Adapter Driver	Adapter Firmware
C420 M3	Teradici	APEX2800	VMware vSphere ESXi 4.1 U2	15907	15907
C420 M3	Teradici	APEX2800	VMware vSphere ESXi 5.0 U1	15907	15907

Third-Party Qualified Adapters

For adapters qualified by EMC (PCIEHHS-3XXL and PCIEHHS-3XXM), please see:

<https://elabnavigator.emc.com/>

The following adapters have been qualified by NetApp. Please contact 1-800-4NETAPP for technical support:

Server	Adapter	Storage
C220 SFF	SAS9200-8e	NetApp NOSH (E5460)
C220 SFF	SAS9200-8e	NetApp VSS (E2660)
C220 SFF	SAS9200-8e	NetApp Fast Track (E5424)

Notes

- 1 Netqueue not supported.
- 2 Driver version is for Software RAID.
- 3 55xx processor family supported, this OS version does not support the 56xx processor family.
- 4 The 2.6.18-164.9.1 errata kernel (or newer) is required to run Red Hat Enterprise Linux 5.4 on a Cisco UCS C460 M1.
- 5 Boot from SAN is not supported.
- 6 Boot from iSCSI is not supported.
- 7 FCoE is not supported.
- 8 Boot from SAN requires Cisco Customized ISO image available for download at www.vmware.com.
- 9 Inbox Driver versions may not be supported, download from device vendor site and install driver to enable device access.
- 10 C460 M1 supports only SLES10.3 errata kernel, not the GA release.
- 11 Supports inbox drivers only.
- 12 Windows Full installation option is supported. Server Core option is also supported.

- 13 Cisco Custom image is required for installing ESXi on all M3 servers. It is advisable to use it for M1/M2 servers if you want to use SAN boot
- 14 Emulex CNAs do not support CEE/CIN mode
- 15 RHEL 6.2 is not supported by Broadcom for adapters with firmware T6.4 & lower.
- 16 Requires VMware Patch on C220/C240 M3 and C22/C24 M3. Refer VMware KB article at <http://kb.vmware.com/kb/2014170>.
- 17 Boot from iSCSI requires Cisco Customized ISO image available for download at www.vmware.com.
- 18 For installing Windows Server 2008 x64 w/Hyper-V SP2 with 1TB or higher memory, install Microsoft hotfix available at <http://support.microsoft.com/kb/2430673>
- 19 Faceplate does not strictly conform to the PCI mechanical spec and could have interference when used in slots 4 & 5. Use card only in slots 1-3 in C250
- 20 ROMB Not Supported
- 21 ROMB is supported on C220 SFF, C220 LFF, C240SFF-16HDD, C22 SFF, C22 LFF, C24 SFF-16 HDD but not supported on C240/C24 SFF-24 HDDs and C240/C24 LFF.
- 22 C240 M3 SFF with no SAS Expander can support upto 2 9266cv-8i.
- 23 saying that iSCSI boot is carried out with inbox drivers and the async needs to be installed from the OS
- 24 When Software Raid is enabled the Option ROM of all other cards should be disabled, otherwise the system never boots up.
- 25 LSi 9240-8i in Alpine C460 M1 and C460 M2 does not have RAID 5 support and it will support only 8 HDD's.
- 26 SAN boot for X520 works only in legacy BIOS mode, and not in UEFI mode
- 27 Qlogic FCoE (QLE8242): Will not support SAN Boot in ESXi 5.0 U1. Recommendation: Install 5.0 to do SAN Boot from this adapter, then upgrade to 5.0 U1.
- 28 (Please do not remove this line)
- 29 In all Romley based platforms Emulex adapters are not supported in all slots of the riser that goes to second CPU in ESXi 4.1U2
- 30 Broadcom 57712 SFP+ not supported in C420 in UCSM mode
- 31 LSI RAID Controller support for VMWARE ESXi is listed per family and not per card. The Raid controllers are listed with just the Vendor Id and Device ID. Subsystem Vendor Id and Subsystem Device ID are left 0x0. What that means is all controllers with the same Vendor Id and Device Id are supported for that version of ESXi
- 32 Boot from SAN is supported.
- 33 Boot from iSCSI is supported.

Related Documentation

Links to the latest versions of related Cisco documentation are available in the *Cisco UCS Rack-Mount Servers Documentation Roadmap*, located at:

<http://www.cisco.com/go/unifiedcomputing/c-series-doc>

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as a Really Simple Syndication (RSS) feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service and Cisco currently supports RSS version 2.0.