



Commands

- [acknowledge chassis, page 12](#)
- [acknowledge fault, page 12](#)
- [acknowledge server, page 13](#)
- [acknowledge slot, page 14](#)
- [activate firmware, page 15](#)
- [add alertgroups, page 16](#)
- [add privilege, page 17](#)
- [associate server, page 19](#)
- [associate server-pool, page 20](#)
- [cd, page 20](#)
- [clear alertgroups, page 21](#)
- [clear cores, page 22](#)
- [cluster force primary, page 23](#)
- [cluster lead, page 24](#)
- [commit-buffer, page 25](#)
- [connect adapter, page 25](#)
- [connect bmc, page 26](#)
- [connect clp, page 26](#)
- [connect iom, page 27](#)
- [connect nxos, page 27](#)
- [create adapter, page 28](#)
- [create backup, page 29](#)
- [create block, page 30](#)
- [create boot-definition, page 31](#)

- [create boot-policy, page 32](#)
- [create cap-qual, page 33](#)
- [create certreq, page 34](#)
- [create chassis, page 35](#)
- [create class chassis-stats, page 36](#)
- [create class cmc-stats, page 37](#)
- [create class cpu-stats, page 38](#)
- [create class dimm-stats, page 38](#)
- [create class ether-error-stats, page 39](#)
- [create class ether-if-stats, page 40](#)
- [create class ether-loss-stats, page 41](#)
- [create class ethernet-port-err-stats, page 42](#)
- [create class ethernet-port-multicast-stats, page 43](#)
- [create class ethernet-port-over-under-sized-stats, page 43](#)
- [create class ethernet-port-stats, page 44](#)
- [create class ethernet-port-stats-by-size-large-packets, page 45](#)
- [create class ethernet-port-stats-by-size-small-packets, page 46](#)
- [create class ether-rx-stats, page 47](#)
- [create class ether-tx-stats, page 47](#)
- [create class fan-module-stats, page 48](#)
- [create class fan-stats, page 49](#)
- [create class fc-error-stats, page 50](#)
- [create class fc-if-event-stats, page 51](#)
- [create class fc-if-fc4-counters, page 51](#)
- [create class fc-if-frame-stats, page 52](#)
- [create class fc-port-stats, page 53](#)
- [create class fc-stats, page 54](#)
- [create class mb-power-stats, page 55](#)
- [create class mb-temp-stats, page 55](#)
- [create class memory-runtime, page 56](#)
- [create class menlo-dce-port-stats, page 57](#)
- [create class menlo-eth-error-stats, page 58](#)
- [create class menlo-eth-stats, page 58](#)

- [create class menlo-fc-error-stats, page 59](#)
- [create class menlo-fc-stats, page 60](#)
- [create class menlo-host-port-stats, page 61](#)
- [create class menlo-mcpu-error-stats, page 61](#)
- [create class menlo-mcpu-stats, page 62](#)
- [create class menlo-net-eg-stats, page 63](#)
- [create class menlo-net-in-stats, page 64](#)
- [create class menlo-q-error-stats, page 65](#)
- [create class menlo-q-stats, page 65](#)
- [create class processor-runtime, page 66](#)
- [create class psu-input-stats, page 67](#)
- [create class psu-stats, page 68](#)
- [create class system-stats, page 68](#)
- [create class vnic-stats, page 69](#)
- [create destination, page 70](#)
- [create dns, page 71](#)
- [create dynamic-conn-policy, page 71](#)
- [create epuser, page 72](#)
- [create eth-if, page 73](#)
- [create eth-profile, page 74](#)
- [create fcoe-if, page 75](#)
- [create fc-profile, page 75](#)
- [create fw-host-pack, page 76](#)
- [create fw-mgmt-pack, page 77](#)
- [create hv-conn, page 78](#)
- [create import-config, page 79](#)
- [create initiator, page 80](#)
- [create interface, page 80](#)
- [create ipmi-access-profile, page 81](#)
- [create keyring, page 82](#)
- [create lan, page 83](#)
- [create local, page 84](#)
- [create local-disk-config, page 84](#)

- [create local-disk-config-policy, page 85](#)
- [create locale, page 86](#)
- [create local-user, page 87](#)
- [create mac-pool, page 87](#)
- [create mac-security, page 88](#)
- [create member-port, page 89](#)
- [create memory, page 90](#)
- [create network, page 91](#)
- [create ntp-server, page 92](#)
- [create org, page 92](#)
- [create org-ref, page 93](#)
- [create pack-image, page 94](#)
- [create path, page 95](#)
- [create pin-group, page 96](#)
- [create policy, page 97](#)
- [create pooling-policy, page 98](#)
- [create port-channel, page 99](#)
- [create port-profile, page 100](#)
- [create processor, page 101](#)
- [create profile, page 101](#)
- [create property \(cpu\), page 102](#)
- [create property \(packet errors\), page 103](#)
- [create property \(packet size\), page 105](#)
- [create qos-policy, page 107](#)
- [create role, page 107](#)
- [create san-image, page 108](#)
- [create scrub-policy, page 109](#)
- [create server, page 110](#)
- [create server-autoconfig-policy, page 111](#)
- [create server-disc-policy, page 112](#)
- [create server-inherit-policy, page 112](#)
- [create server-pool, page 113](#)
- [create server-qual, page 114](#)

- [create service-profile, page 115](#)
- [create slot, page 116](#)
- [create snmp-trap, page 116](#)
- [create sol-config, page 117](#)
- [create sol-policy, page 118](#)
- [create stats-threshold-policy, page 119](#)
- [create storage, page 120](#)
- [create trustpoint, page 120](#)
- [create uuid-suffix-pool, page 121](#)
- [create vhba, page 122](#)
- [create vhba-templ, page 123](#)
- [create virtual-media, page 124](#)
- [create vlan, page 125](#)
- [create vnic, page 126](#)
- [create vnic-egress-policy, page 127](#)
- [create vnic-templ, page 128](#)
- [create vsan, page 129](#)
- [create wwn-pool, page 130](#)
- [cycle, page 131](#)
- [decommission chassis, page 131](#)
- [decommission server, page 132](#)
- [delete adapter, page 133](#)
- [delete backup, page 133](#)
- [delete block, page 134](#)
- [delete boot-definition, page 135](#)
- [delete boot-policy, page 136](#)
- [delete certreq, page 136](#)
- [delete chassis, page 137](#)
- [delete class chassis-stats, page 138](#)
- [delete class cpu-stats, page 139](#)
- [delete class dimm-stats, page 139](#)
- [delete class ether-error-stats, page 140](#)
- [delete class ether-if-stats, page 141](#)

- [delete class ether-loss-stats, page 141](#)
- [delete class ether-rx-stats, page 142](#)
- [delete class ether-tx-stats, page 143](#)
- [delete destination, page 144](#)
- [delete dns, page 144](#)
- [delete dynamic-vnic-conn-policy, page 145](#)
- [delete epuser, page 146](#)
- [delete eth-if, page 146](#)
- [delete eth-profile, page 147](#)
- [delete fc-profile, page 148](#)
- [delete image, page 149](#)
- [delete import-config, page 150](#)
- [delete initiator, page 151](#)
- [delete interface, page 152](#)
- [delete ipmi-access-profile, page 153](#)
- [delete keyring, page 153](#)
- [delete lan, page 154](#)
- [delete local, page 155](#)
- [delete locale, page 155](#)
- [delete local-disk-config, page 156](#)
- [delete local-user, page 157](#)
- [delete mac-pool, page 158](#)
- [delete mac-security, page 158](#)
- [delete member-port, page 159](#)
- [delete memory, page 160](#)
- [delete org-ref, page 161](#)
- [delete path, page 162](#)
- [delete pin-group, page 162](#)
- [delete policy, page 163](#)
- [delete pooling-policy, page 164](#)
- [delete port-channel, page 165](#)
- [delete processor, page 166](#)
- [delete qos-policy, page 166](#)

- [delete role, page 167](#)
- [delete scrub-policy, page 168](#)
- [delete server, page 169](#)
- [delete server-disc-policy, page 169](#)
- [delete server-pool, page 170](#)
- [delete server-qual, page 171](#)
- [delete storage, page 172](#)
- [delete target, page 172](#)
- [delete trustpoint, page 173](#)
- [delete uuid-suffix-pool, page 174](#)
- [delete vhba, page 174](#)
- [delete vlan, page 175](#)
- [delete vnic, page 176](#)
- [delete vnic-templ, page 177](#)
- [delete vsan, page 177](#)
- [delete wwn-pool, page 178](#)
- [disable cimxml, page 179](#)
- [disable http, page 180](#)
- [disable https, page 180](#)
- [disable snmp, page 181](#)
- [disable telnet-server, page 182](#)
- [disassociate, page 182](#)
- [download image, page 183](#)
- [enable cimxml, page 184](#)
- [enable core-export-target, page 185](#)
- [enable http, page 185](#)
- [enable https, page 186](#)
- [enable snmp, page 187](#)
- [enable telnet-server, page 188](#)
- [enter adapter, page 188](#)
- [enter chassis, page 189](#)
- [enter memory, page 190](#)
- [enter processor, page 191](#)

- [enter storage, page 192](#)
- [power, page 193](#)
- [reboot, page 193](#)
- [recommission chassis, page 194](#)
- [remove privilege, page 195](#)
- [remove server, page 197](#)
- [reset, page 197](#)
- [reset-cmos, page 198](#)
- [scope adapter, page 199](#)
- [scope backup, page 200](#)
- [scope block, page 200](#)
- [scope bmc, page 201](#)
- [scope boot-definition, page 202](#)
- [scope boot-policy, page 203](#)
- [scope capability, page 203](#)
- [scope cap-qual, page 204](#)
- [scope chassis, page 205](#)
- [scope chassis-disc-policy, page 206](#)
- [scope eth-classified, page 206](#)
- [scope eth-server, page 207](#)
- [scope eth-uplink, page 208](#)
- [scope fc-uplink, page 209](#)
- [scope firmware, page 210](#)
- [scope flow-control, page 210](#)
- [scope import-config, page 211](#)
- [scope iom, page 212](#)
- [scope ipmi-access-profile, page 213](#)
- [scope ldap, page 213](#)
- [scope locale, page 214](#)
- [scope monitoring, page 215](#)
- [scope org, page 216](#)
- [scope port-channel, page 216](#)
- [scope qos, page 217](#)

- [scope radius, page 218](#)
- [scope role, page 218](#)
- [scope security, page 219](#)
- [scope server, page 220](#)
- [scope server-qual, page 221](#)
- [scope services, page 221](#)
- [scope system, page 222](#)
- [scope tacacs, page 223](#)
- [scope vhba, page 223](#)
- [scope vhba-templ, page 224](#)
- [scope vnic, page 225](#)
- [scope vnic-templ, page 226](#)
- [scope wwn-pool, page 226](#)
- [set action, page 227](#)
- [set adaptor-profile, page 228](#)
- [set adminstate, page 229](#)
- [set agent-policy, page 230](#)
- [set arch, page 231](#)
- [set attribute, page 232](#)
- [set authentication console, page 233](#)
- [set authentication default, page 234](#)
- [set authport, page 234](#)
- [set basedn, page 235](#)
- [set blocksize, page 236](#)
- [set boot-policy, page 237](#)
- [set cimxml port, page 238](#)
- [set clock, page 238](#)
- [set cos, page 239](#)
- [set descr, page 240](#)
- [set disk-scrub, page 242](#)
- [set email, page 242](#)
- [set expiration, page 243](#)
- [set filter, page 245](#)

- [set firstname, page 245](#)
- [set flow-control-policy, page 246](#)
- [set host-fw-policy, page 247](#)
- [set http port, page 248](#)
- [set https keyring, page 249](#)
- [set https port, page 249](#)
- [set ipmi-access-profile, page 250](#)
- [set key, page 251](#)
- [set lastname, page 252](#)
- [set local-disk-policy, page 253](#)
- [set lun, page 253](#)
- [set maxcap, page 254](#)
- [set maxcores, page 255](#)
- [set maximum, page 256](#)
- [set maxprocs, page 257](#)
- [set maxthreads, page 257](#)
- [set mgmt-fw-policy, page 258](#)
- [set mincap, page 259](#)
- [set mincores, page 260](#)
- [set minprocs, page 261](#)
- [set minthreads, page 262](#)
- [set mode, page 262](#)
- [set mtu, page 264](#)
- [set name, page 264](#)
- [set numberofblocks, page 265](#)
- [set order, page 266](#)
- [set password, page 267](#)
- [set perdiskcap, page 268](#)
- [set pers-bind, page 269](#)
- [set phone, page 270](#)
- [set pin-group, page 270](#)
- [set pool, page 271](#)
- [set port, page 272](#)

- [set prio, page 273](#)
- [set qos-policy, page 274](#)
- [set qualifier, page 275](#)
- [set reboot-on-update, page 275](#)
- [set receive, page 276](#)
- [set retries, page 277](#)
- [set rootdn, page 278](#)
- [set scrub-policy, page 279](#)
- [set send, page 280](#)
- [set snmp community, page 280](#)
- [set sol-policy, page 281](#)
- [set speed, page 282](#)
- [set src-templ-name, page 283](#)
- [set sshkey, page 284](#)
- [set ssl, page 285](#)
- [set stats-policy, page 286](#)
- [set stepping, page 287](#)
- [set syslog console, page 287](#)
- [set syslog file, page 288](#)
- [set syslog min-level, page 290](#)
- [set syslog monitor, page 291](#)
- [set syslog remote-destination, page 292](#)
- [set target, page 294](#)
- [set template-name, page 295](#)
- [set timeout, page 296](#)
- [set units, page 297](#)
- [set version, page 297](#)
- [set vhba, page 298](#)
- [set virtual-ip, page 299](#)
- [set vnic, page 300](#)
- [set weight, page 301](#)
- [set width, page 301](#)
- [set wwn, page 302](#)

- [top, page 303](#)
- [up, page 304](#)
- [update firmware, page 304](#)
- [where, page 305](#)

acknowledge chassis

To acknowledge a chassis, use the **acknowledge chassis** command.

acknowledge chassis *id*

Syntax Description	<i>id</i> Chassis identification number. The range of valid values is 1 to 255.	
Command Default	None	
Command Modes	Any command mode	
Command History	Release	Modification
	1.0(1)	This command was introduced.
Usage Guidelines	Use this command to verify the existence of devices in your network. For example, you can acknowledge a chassis that was recently commissioned, to ensure that it exists.	
Examples	<p>This example shows how to acknowledge a chassis:</p> <pre>switch-A# acknowledge chassis 10 switch-A* # commit-buffer switch-A #</pre>	
Related Commands	Command	Description
	show chassis	
	show server	

acknowledge fault

To acknowledge a fault, use the **acknowledge fault** command.

acknowledge fault *id*

Syntax Description	<i>id</i> Fault identification number. The range of valid values is 0 to 9223372036854775807.	
Command Default	None	
Command Modes	Any command mode	
Command History	Release	Modification
	1.0(1)	This command was introduced.
Examples	<p>The following example shows how to acknowledge a fault:</p> <pre>switch-A# acknowledge fault 1 switch-A* # commit-buffer switch-A #</pre>	
Related Commands	Command	Description
	show cli	
	show fault	

acknowledge server

To acknowledge a server, use the **acknowledge server** command.

acknowledge server {*chassis-id / blade-id* | *slot-id*}

Syntax Description	chassis-id / blade-id	Chassis and blade identification numbers.
	slot-id	Slot identification number. The range of valid values is 1 to 8.
Command Default	None	
Command Modes	Chassis (/chassis)	
	Any command mode	

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to verify the existence of devices in your network. For example, you can acknowledge a server that was recently commissioned, to ensure that it exists. *slot -id* is used only in /chassis mode.

Examples

The following example shows how to acknowledge a server in /chassis mode:

```
switch-A# scope chassis 1
switch-A /chassis # acknowledge server 2
switch-A /chassis* # commit-buffer
switch-A /chassis #
```

Related Commands

Command	Description
show chassis	
show server	

acknowledge slot

To acknowledge a slot, use the **acknowledge slot** command.

acknowledge slot {*chassis-id* / *blade-id* | *slot-id*}

Syntax Description

<i>chassis-id</i> / <i>blade-id</i>	Sever identification number.
<i>slot-id</i>	Slot identification number. The range of valid values is 1 to 8.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to verify the existence of devices in your network. For example, you can acknowledge a chassis that was recently commissioned using *slot -id*, to ensure that it exists. *slot -id* is used only in /chassis mode.

Examples

The following example shows how to acknowledge a slot in /chassis mode:

```
switch-A# scope chassis 1
switch-A /chassis # acknowledge slot 1
switch-A /chassis* # commit-buffer
switch-A /chassis #
```

Related Commands

Command	Description
show server	
show slot	

activate firmware

To activate firmware for a device, use the **activate firmware** command.

activate firmware *version* { **kernel-version** *kernel-version* [**ignorecompcheck**] | **system-version** *system-version* [**ignorecompcheck**] } +

Syntax Description

kernel-version	Specifies switch kernel version firmware.
<i>kernel-version</i>	Kernel version.
system-version	Specifies switch system version firmware.
<i>system-version</i>	System version.
ignorecompcheck	(Optional) Specifies a compatability check.

Command Default

None

Command Modes

Input output module (/chassis/iom)
System (/system)
Fabric interconnect (/fabric)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use the **ignorecompcheck** keyword to run a compatability check when you activate the firmware.

Examples

The following example shows how to activate a specific version of software:

```
switch-A# scope fabric a
switch-A /fabric # activate firmware kernel-version 3.0 ignorecompcheck
switch-A /fabric* # commit-buffer
switch-A /fabric #
```

Related Commands

Command	Description
show firmware	
show version	

add alertgroups

To add an alert group, use the **add alertgroups** command.

```
add alertgroups { ciscotac | diagnostic | environmental | inventory | license | lifecycle | linecard | supervisor
| syslogport | system | test } +
```

Syntax Description

ciscotac	Specifies the Cisco technical support (TAC) alert group.
diagnostic	Specifies the diagnostic alert group.
environmental	Specifies the environmental alert group.
inventory	Specifies the inventory alert group.
license	Specifies the license alert group.
lifecycle	Specifies the lifecycle alert group.
linecard	Specifies the linecard alert group.
supervisor	Specicify the supervisor alert group.
syslogport	Specifies the syslogport alert group.
system	Specifies the system alert group.
test	Specifies the test alert group.

Command Default

None

Command Modes

Profile (/monitoring/callhome/profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

The following example shows how to add an alert group:

```
switch-A# scope monitoring
switch-A /monitoring # scope callhome

switch-A /monitoring/callhome # scope profile profileOne
switch-A /monitoring/callhome/profile # add alertgroups diagnostic
switch-A /monitoring/callhome/profile* # commit-buffer
switch-A /monitoring/callhome/profile #
```

add privilege

To add privileges, use the **add privilege** command.

add privilege { aaa | admin | ext-lan-config | ext-lan-policy | ext-lan-qos | ext-lan-security | ext-san-config | ext-san-policy | ext-san-qos | ext-san-security | fault | service-profile-config | service-profile-config-policy | service-profile-network | service-profile-network-policy | service-profile-qos | service-profile-qos-policy | service-profile-security | service-profile-security-policy | service-profile-server | service-profile-server-policy | service-profile-storage | service-profile-storage-policy | operations | server-equipment | server-maintenance | server-policy | server-security | pod-config | pod-policy | pod-qos | pod-security | read-only } +

Syntax Description

aaa	Specifies AAA privileges.
admin	Specifies admin privileges.
ext-lan-config	Specifies external LAN configuration privileges.
ext-lan-policy	Specifies external LAN policy privileges.
ext-lan-qos	Specifies external LAN QoS privileges.
ext-lan-security	Specifies external LAN security privileges.
ext-san-config	Specifies external SAN configuration privileges.
ext-san-policy	Specifies external SAN policy privileges.
ext-san-qos	Specifies external SAN QoS privileges.
ext-san-security	Specifies external SAN security privileges.

fault	Specifies fault privileges.
service-profile-config	Specifies service profile configuration privileges.
service-profile-config-policy	Specifies service profile configuration policy privileges.
service-profile-network	Specifies service profile network privileges.
service-profile-network-policy	Specifies service profile network policy privileges.
service-profile-qos	Specifies service profile QoS privileges.
service-profile-qos-policy	Specifies service profile QoS policy privileges.
service-profile-security	Specifies service profile security privileges.
service-profile-security-policy	Specifies service profile security policy privileges.
service-profile-server	Specifies service profile server privileges.
service-profile-server-policy	Specifies service profile server policy privileges.
service-profile-storage	Specifies service profile storage privileges.
service-profile-storage-policy	Specifies service profile storage policy privileges.
operations	Specifies operations privileges.
server-equipment	Specifies server equipment privileges.
server-maintenance	Specifies server maintenance privileges.
server-policy	Specifies server policy privileges.
server-security	Specifies server security privileges.
pod-config	Specifies pod configuration privileges.
pod-policy	Specifies pod policy privileges.
pod-qos	Specifies pod QoS privileges.
pod-security	Specifies pod security privileges.
read-only	Specifies read-only privileges.

Command Default

None

Command Modes

Role (/security/role)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to add privileges:

```
switch-A # scope security
switch-A /security # scope role role1
switch-A /security/role # add privilege ext-san-config ext-san-policy ext-san-qos
ext-san-security
switch-A /security/role* # commit-buffer
switch-A /security/role #
```

associate server

To associate a server, use the **associate server** command.

associate server *chassis-id/blade-id*

Syntax Description

<i>chassis-id/blade-id</i>	Chassis and blade identification numbers. The range of valid values is 1 to 4294967295.
----------------------------	---

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to associate a server:

```
switch-A# scope org 1
switch-A /org # scope service-profile 1
switch-A /org/service-profile # associate server 1
switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show assoc	
show server	

associate server-pool

To associate a server pool with a service profile, use the **associate server-pool** command.

associate server-pool *server-pool* [*name*]

Syntax Description

<i>server-pool</i>	Server pool name. The range of valid values is 1 to 16.
<i>name</i>	(Optional) Qualifier. The range of valid values is 1 to 16.

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to associate a server pool:

```
switch-A# scope org 1
switch-A /org # scope service-profile 1
switch-A /org/service-profile # associate server-pool 1
switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show assoc	
show server	

cd

To change directories, use the **cd** command.

cd {bootflash:| volatile:}

Syntax Description

bootflash:	Specifies the bootflash directory.
volatile:	Specifies the volatile directory.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

The **cd** command is on the local management port command line. Use the **connect local-mgmt** command to connect to that command line.

Examples

This example shows how to change directories:

```
switch-A# connect local-mgmt
Nexus 5000 Switch
Cisco UCS 6100 Series Fabric Interconnect
```

TAC support: <http://www.cisco.com/tac>

Copyright (c) 2009, Cisco Systems, Inc. All rights reserved.

The copyrights to certain works contained herein are owned by other third parties and are used and distributed under license. Some parts of this software may be covered under the GNU Public License or the GNU Lesser General Public License. A copy of each such license is available at <http://www.gnu.org/licenses/gpl.html> and <http://www.gnu.org/licenses/lgpl.html>

```
switch-A(local-mgmt)# cd volatile:
switch-A(local-mgmt)#
```

clear alertgroups

To clear alert groups, use the **clear alertgroups** command.

clear alertgroups

This command has no arguments or keywords.

Command Default

None

Command Modes

Profile (/monitoring/callhome/profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to clear alert groups:

```
switch-A# scope monitoring
switch-A /monitoring # scope callhome
switch-A /monitoring/callhome # scope profile profileOne
switch-A /monitoring/callhome/profile # clear alertgroups
switch-A /monitoring/callhome/profile* # commit-buffer
switch-A /monitoring/callhome/profile #
```

Related Commands

Command	Description
show policy	
show profile	

clear cores

To clear core files, use the **clear cores** command.

clear cores

This command has no arguments or keywords.

Command Default

None

Command Modes

Sysdebug (/monitoring/sysdebug)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Core files are records of core dumps. Use the **clear cores** command to clear information out of core dump records.

Examples

This example shows how to clear core files:

```
switch-A# scope monitoring
switch-A /monitoring # scope sysdebug
switch-A /monitoring/sysdebug # clear cores
switch-A /monitoring/sysdebug # commit-buffer
switch-A /monitoring/sysdebug #
```

Related Commands

Command	Description
show alert-groups	

Command	Description
show cores	

cluster force primary

To force a cluster to be the primary cluster, use the **cluster force primary** command.

cluster force primary

Command Default This command has no arguments or keywords.
None

Command Modes Local management (local-mgmt)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Usage Guidelines The **cluster** commands are switch-specific local management commands. You have to execute a **connect local-mgmt** command to connect to the management port.

Examples This example shows how to force a cluster to be the primary cluster:

```
switch-A# connect local-mgmt
Nexus 5000 Switch
Cisco UCS 6100 Series Fabric Interconnect

TAC support: http://www.cisco.com/tac

Copyright (c) 2009, Cisco Systems, Inc. All rights reserved.

The copyrights to certain works contained herein are owned by
other third parties and are used and distributed under license.
Some parts of this software may be covered under the GNU Public
License or the GNU Lesser General Public License. A copy of
each such license is available at
http://www.gnu.org/licenses/gpl.html and
http://www.gnu.org/licenses/lgpl.html
switch-A# cluster force primary
switch-A#
```

Related Commands	Command	Description
	show cluster	
	show file	

cluster lead

To designate a cluster leader, use the **cluster lead** command.

cluster lead [**a** | **b**]

Syntax Description

a	Specifies switch A.
b	Specifies switch B.

Command Default

None

Command Modes

Local management (local-mgmt)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

The **cluster** commands are switch-specific local management commands. You must first execute a **connect local-mgmt** command to connect to the management port.

Examples

This example shows how to designate a cluster leader:

```
switch-A# connect local-mgmt
Nexus 5000 Switch
Cisco UCS 6100 Series Fabric Interconnect

TAC support: http://www.cisco.com/tac

Copyright (c) 2009, Cisco Systems, Inc. All rights reserved.

The copyrights to certain works contained herein are owned by
other third parties and are used and distributed under license.
Some parts of this software may be covered under the GNU Public
License or the GNU Lesser General Public License. A copy of
each such license is available at
http://www.gnu.org/licenses/gpl.html and
http://www.gnu.org/licenses/lgpl.html
switch-A# cluster lead b
switch-A#
```

Related Commands

Command	Description
show cluster	
show files	

commit-buffer

To save or verify configuration changes, use the **commit-buffer** command.

commit-buffer [**verify-only**]

Syntax Description	<div><div>verify-only</div><div>(Optional) Specifies verification only.</div></div>				
Command Default	None				
Command Modes	Any command mode				
Command History	<table><tr><th>Release</th><th>Modification</th></tr><tr><td>1.0(1)</td><td>This command was introduced.</td></tr></table>	Release	Modification	1.0(1)	This command was introduced.
Release	Modification				
1.0(1)	This command was introduced.				
Usage Guidelines	The * to the right of the command mode name signifies that the configuration change has not been committed.				
Examples	<div>This example shows how to save configuration changes:</div> <div>switch-A-A# create org 3 switch-A /org* # commit-buffer switch-A /org #</div>				

connect adapter

To connect to an adapter, use the **connect adapter** command.

connect adapter *chassis-id/server-id/adapter-id*

Syntax Description	<div><i>chassis-id/server-id/adapter-id</i></div> <div>Adapter identification number.</div>	
Command Default	None	
Command Modes	Any command mode	

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to connect to an adapter:

```
switch-A# connect adapter 1/1/1
adapter 1/1 #
```

connect bmc

To connect to the BMC (Baseboard Management Controller), use the **connect bmc** command.

connect bmc *chassis-id/blade-id*

Syntax Description

<i>chassis-id/blade-id</i>	Chassis and blade identification numbers.
----------------------------	---

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

The following example shows how to connect to the Baseboard Management Controller:

```
switch-A# connect bmc 1/1
Trying 127.5.1.1...
Connected to 127.5.1.1.
Escape character is '^]'.

NUOVA-IBMC login:
```

connect clp

To connect to DMTF CLP, use the **connect clp** command.

connect clp

This command has no arguments or keywords.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to connect to DMTF CLP:

```
switch-A# connect clp
/admin1 CLP ->
```

connect iom

To connect to an IO module, use the **connect iom** command.

connect iom *id*

Syntax Description

<i>id</i>	Chassis identification number. The valid range of values is 1 to 255.
-----------	---

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to connect to a IO module:

```
switch-A# connect iom 1
Attaching to FEX 1 ...
To exit type 'exit', to abort type '$.'
fex-1#
```

connect nxos

To connect to the NX-OS, use the **connect nxos** command.

connect nxos [**a** | **b**]

Syntax Description

a (Optional) Specifies switch A.

b (Optional) Specifies switch B.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to NXOS:

```
switch-A-A# connect nxos b
Nexus 5000 Switch
Cisco UCS 6100 Series Fabric Interconnect
```

TAC support: <http://www.cisco.com/tac>

Copyright (c) 2009, Cisco Systems, Inc. All rights reserved.

The copyrights to certain works contained herein are owned by other third parties and are used and distributed under license. Some parts of this software may be covered under the GNU Public License or the GNU Lesser General Public License. A copy of each such license is available at <http://www.gnu.org/licenses/gpl.html> and <http://www.gnu.org/licenses/lgpl.html>

```
switch-B#
```

create adapter

To create an adapter, use the **create adapter** command.

create adapter

This command has no arguments or keywords.

Command Default

None

Command Modes

Server qualification (/org/server-qual)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples

This example shows how to create an adapter:

```
switch-A# scope org org3
switch-A /org # scope server-qual sq2
switch-A /org/server-qual # create adapter
switch-A /org/server-qual/adapter* # commit-buffer
switch-A /org/server-qual/adapter #
```

Related Commands

Command	Description
show adapter	
show chassis	

create backup

To create a backup, use the **create backup** command.

create backup *file* { **all-configuration** | **logical-configuration** | **system-configuration** | **full-state** } { **disabled** | **enabled** }

Syntax Description

<i>file</i>	Managment file name. Use one of the following keywords for file type: ftp , scp , sftp , or tftp .
all-configuration	Specifies a server, fabric, and system-related configuration backup.
logical-configuration	Specifies a server and fabric backup.
system-configuration	Specifies a system-related configuration backup.
full-state	Specifies a full state backup for disaster recovery.
disabled	Specifies disabled.
enabled	Specifies enabled.

Command Default

None

Command Modes

System (/system)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

No more than one backup can be created and committed.

When you specify disabled, backup functionality is disabled. When you specify enabled, backup functionality is enabled.

Examples

This example shows how to create a backup:

```
switch-A# scope system
switch-A /system # create backup ftp: full-state enabled

Password:
switch-A /system/backup* # commit-buffer
switch-A /system/backup #
```

Related Commands

Command	Description
show backup	
show image	

create block

To create a block, use the **create block** command.

IP pool configuration

create block *from to default-gw subnet-mask*

WWN pool, UUID pool, and MAC pool configuration

create block *from to*

Syntax Description

<i>from</i>	From address, identifier, or world-wide name. Specify a MAC address in the format NN:NN:NN:NN:NN:NN. Specify a UUID in the format NNNN-NNNNNNNNNNNN. Specify a WWN in the format HH:HH:HH:HH:HH:HH:HH:HH. Specify an IP address in the format A.B.C.D.
<i>to</i>	To address, identifier, or world-wide name. Specify a MAC address in the format NN:NN:NN:NN:NN:NN. Specify a UUID in the format NNNN-NNNNNNNNNNNN. Specify a WWN in the format HH:HH:HH:HH:HH:HH:HH:HH. Specify an IP address in the format A.B.C.D.
<i>default-gw</i>	Default gateway.

<i>subnet-mask</i>	Subnet mask.
--------------------	--------------

Command Default

None

Command Modes

IP pool (/org/ip-pool)
 WWN pool (/org/wwn-pool)
 UUID suffix pool (/org/uuid-suffix-pool)
 MAC pool (/org/mac-pool)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create addresses, identifiers, and world-wide names.

Use IP pool configuration mode to create IP address blocks. Use WWN pool, UUID pool, and MAC pool configuration mode to create addresses, UUIDs, and WWNs.

Examples

This example shows how to create a block:

```
switch-A# scope org org3
switch-A /org # scope mac-pool mp1
switch-A /org/mac-pool # create block 1a:2b:3c:4d:21:31 1b:2a:3c:4d:21:31
switch-A /org/mac-pool* # commit-buffer
switch-A /org/mac-pool #
```

Related Commands

Command	Description
show mac-pool	
show pooled	

create boot-definition

To create a boot definition, use the **create boot-definition** command.

create boot-definition

This command has no arguments or keywords.

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to create a boot definition:

```
switch-A# scope org org3
switch-A /org # scope service-profile spl
switch-A /org/service-profile # create boot-definition
switch-A /org/service-profile/boot-definition* # commit-buffer
switch-A /org/service-profile/boot-definition #
```

Related Commands

Command	Description
show boot-definition	
show lan	

create boot-policy

To create a boot policy, use the **create boot-policy** command.

create boot-policy *name* **purpose** { **operational** | **utility** } *

Syntax Description

<i>name</i>	Policy name. The range of valid values is 1 to 16.
purpose	Specifies the purpose of the policy.
operational	Specifies an operational policy.
utility	Specifies a utility policy.

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to create a boot policy:

```
switch-A# scope org org3
switch-A /org # create boot-policy boot1

switch-A /org/boot-policy* #commit-buffer
switch-A /org/boot-policy #
```

Related Commands

Command	Description
show lan	
show virtual-media	

create cap-qual

To create an capacity qualification, use the **create cap-qual** command.

```
create cap-qual { fcoe | non-virtualized-eth-if | non-virtualized-fc-if | path-encap-consolidated |
path-encap-virtual | protected-eth-if | protected-fc-if | protected-fcoe | virtualized-eth-if | virtualized-fc-if
| virtualized-scsi-if }
```

Syntax Description

fcoe	Specifies Fibre Channel over Ethernet.
non-virtualized-eth-if	Specifies non-virtualized Ethernet interface.
non-virtualized-fc-if	Specifies non-virtualized Fibre Channel interface.
path-encap-consolidated	Specifies path encapsulation consolidated.
path-encap-virtual	Specifies path encapsulation virtual.
protected-eth-if	Specifies protected Ethernet interface.
protected-fc-if	Specifies protected Fibre Channel interface.
protected-fcoe	Specifies protected Fibre Channel over Ethernet.
virtualized-eth-if	Specifies virtualized Ethernet interface.
virtualized-fc-if	Specifies virtualized Fibre Channel interface.
virtualized-scsi-if	Specifies virtualized SCSI interface.

Command Default

None

Command Modes

Adapter (/org/server-qual/adapter)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Creates an adapter capacity qualification for the specified adapter type and enters organization server qualification adapter mode.

Examples

This example shows how to create a capacity qualification:

```
switch-A# scope org org3
switch-A /org # scope server-qual sq2

switch-A /org/server-qual # scope adapter 1/1/1
switch-A /org/server-qual/adapter # create cap-qual cq10
switch-A /org/server-qual/adapter* # commit-buffer
switch-A /org/server-qual/adapter #
```

Related Commands

Command	Description
show adapter	
show server-qual	

create certreq

To create a keyring certificate request, use the **create certreq** command.

create certreq { **subject-name** *name* | **ip** *ip-address* } + [**password** *password*]

Syntax Description

subject-name	Specifies subject name.
<i>name</i>	Subject name. The range of valid values is 1 to 16.
ip	Specifies IP address.
<i>ip-address</i>	IP address. The format is A.B.C.D.
password	(Optional) Specifies password.
<i>password</i>	Password. The range of valid values is 1 to 16.

Command Default

None

Command Modes

Keyring (/security/keyring)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Before you create a certreq you must set modulus.

Examples

This example shows how to create a keyring certificate request:

```
switch-A# scope security
switch-A /security # scope keyring k1
switch-A /security/keyring # create certreq subject-name cr3
switch-A /security/keyring* # commit-buffer
switch-A /security/keyring #
```

Related Commands

Command	Description
show certreq	
show keyring	

create chassis

To create a chassis, use the **create chassis** command.

create chassis *min-id max-id*

Syntax Description

<i>min-id</i>	Minimum chassis identification number. The range of valid values is 1 to 255.
<i>max-id</i>	Maximum chassis identification number. The range of valid values is 1 to 255.

Command Default

None

Command Modes

Server qualification (/org/server-qual)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Creates a chassis with the specified name, and enters organization chassis mode.

Examples

This example shows how to create a chassis:

```
switch-A# scope org org3
switch-A /org # scope server-qual sq2
switch-A /org/server-qual # create chassis 2 2
switch-A /org/server-qual/chassis* # commit-buffer
switch-A /org/server-qual/chassis #
```

Related Commands

Command	Description
show chassis	
show server	

create class chassis-stats

To create a chassis statistics class, use the **create class chassis-stats** command.

create class chassis-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to place thresholds on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for chassis statistics.

Examples

This example shows how to create a chassis statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy tp10

switch-A /eth-server/stats-threshold-policy # create class chassis-stats
switch-A /eth-server/stats-threshold-policy* # commit-buffer
switch-A /eth-server/stats-threshold-policy #
```

Related Commands

Command	Description
show chassis	
show class	

create class cmc-stats

To create a CMC statistics class, use the **create class cmc-stats** command.

create class cmc-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to place thresholds on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for CMC statistics.

Examples

This example shows how to create a chassis statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy tp10

switch-A /eth-server/stats-threshold-policy # create class cmc-stats
switch-A /eth-server/stats-threshold-policy* # commit-buffer
switch-A /eth-server/stats-threshold-policy #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class cpu-stats

To create a CPU statistics class, use the **create class cpu-stats** command.

create class cpu-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for CPUs.

Examples

This example shows how to create a CPU statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p1
switch-A /org/stats-threshold-policy # create class cpu-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class dimm-stats

To create a DIMM statistics class, use the **create class dimm-stats** command.

create class dimm-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for DIMMs.

Examples

This example shows how to create a DIMM statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p1
switch-A /org/stats-threshold-policy # create class dimm-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class ether-error-stats

To create an Ethernet error statistics class, use the **create class ether-error-stats** command.

create class ether-error-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy under Ethernet uplink (/eth-uplink/stats-threshold-policy)
 Statistics threshold policy under Ethernet server (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0	This command was introduced.

Usage Guidelines

Use classes to place thresholds on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Ethernet error statistics.

Examples

This example shows how to create an Ethernet error statistics class:

```
switch-A# scope eth-uplink
switch-A /eth-uplink # scope stats-threshold-policy p10

switch-A /eth-uplink/stats-threshold-policy # create class ether-error-stats
switch-A /eth-uplink/stats-threshold-policy* # commit-buffer
switch-A /eth-uplink/stats-threshold-policy #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class ether-if-stats

To create an Ethernet interface statistics class, use the **create class ether-if-stats** command.

create class ether-if-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to place a threshold on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Ethernet interface statistics.

Examples

This example shows how to create an Ethernet interface statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p1
switch-A /org/stats-threshold-policy # create class ether-if-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class ether-loss-stats

To create an Ethernet loss statistics class, use the **create class ether-loss-stats** command.

create class ether-loss-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy under Ethernet server (/eth-server/stats-threshold-policy)
 Statistics threshold policy under Ethernet uplink (/eth-uplink/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to place a threshold on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Ethernet loss statistics.

Examples

This example shows how to create an Ethernet loss statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy p10

switch-A /eth-server/stats-threshold-policy # create class ether-loss-stats
switch-A /eth-server/stats-threshold-policy/class* # commit-buffer
switch-A /eth-server/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class ethernet-port-err-stats

To create an Ethernet port error statistics class, use the **create class ethernet-port-err-stats** command.

create class ethernet-port-err-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to place a threshold on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Ethernet port error statistics.

Examples

This example shows how to create an Ethernet port error statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class ethernet-port-err-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class ethernet-port-multicast-stats

To create an Ethernet port multicast statistics class, use the **create class ethernet-port-multicast-stats** command.

create class ethernet-port-multicast-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to place a threshold on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Ethernet port multicast statistics.

Examples

This example shows how to create an Ethernet port multicast statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class ethernet-port-multicast-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class ethernet-port-over-under-sized-stats

To create an Ethernet port over-under-sized statistics class, use the **create class ethernet-port-over-under-sized-stats** command.

create class ethernet-port-over-under-sized-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to place a threshold on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Ethernet port over-under-sized statistics.

Examples

This example shows how to create an Ethernet port statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class ethernet-port-over-under-sized-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class ethernet-port-stats

To create an Ethernet port statistics class, use the **create class ethernet-port-stats** command.

create class ethernet-port-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to place a threshold on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Ethernet port statistics.

Examples

This example shows how to create an Ethernet port statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class ethernet-port-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class ethernet-port-stats-by-size-large-packets

To create an Ethernet port large packet statistics class, use the **create class ethernet-port-stats-by-size-large-packets** command.

create class ethernet-port-stats-by-size-large-packets

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to place thresholds on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Ethernet port small packet statistics.

Examples

This example shows how to create an Ethernet port large packet statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class ethernet-port-stats-by-size-large-packets
```

```
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class ethernet-port-stats-by-size-small-packets

To create an Ethernet port small packet statistics class, use the **create class ethernet-port-stats-by-size-small-packets** command.

create class ethernet-port-stats-by-size-small-packets

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to place thresholds on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Ethernet port small packet statistics.

Examples

This example shows how to create an Ethernet port small packet statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class ethernet-port-stats-by-size-small-packets

switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class ether-rx-stats

To create an Ethernet receive statistics class, use the **create class ether-rx-stats** command.

create class ether-rx-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy under Ethernet server (/eth-server/stats-threshold-policy)

Statistics threshold policy under Ethernet uplink (/eth-uplink/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to place a threshold on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Ethernet receive statistics.

Examples

This example shows how to create an Ethernet receive statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy p10

switch-A /eth-server/stats-threshold-policy # create class ether-rx-stats
switch-A /eth-server/stats-threshold-policy/class* # commit-buffer
switch-A /eth-server/stats-threshold-policy/class #
```

Related Commands

Command	Description
show eth-uplink	
show stats-threshold-policy	

create class ether-tx-stats

To create an Ethernet transmission statistics class, use the **create class ether-tx-stats** command.

create class ether-tx-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy under Ethernet uplink (/eth-uplink/stats-threshold-policy)

Statistics threshold policy under Ethernet server (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to place a threshold on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Ethernet transmission statistics.

Examples

This example shows how to create an Ethernet transmission statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy p10

switch-A /eth-server/stats-threshold-policy # create class eth-tx-stats
switch-A /eth-server/stats-threshold-policy/class* # commit-buffer
switch-A /eth-server/stats-threshold-policy/class #
```

Related Commands

Command	Description
show eth-uplink	
show stats-threshold-policy	

create class fan-module-stats

To create a fan module statistics class, use the **create class fan-module-stats** command.

create class fan-module-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/eth-server/stats-threshold-policy)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Usage Guidelines	Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for fan module statistics.
------------------	--

Examples	<p>This example shows how to create a fan module statistics class:</p> <pre>switch-A# scope eth-server switch-A /eth-server # scope stats-threshold-policy p10 switch-A /eth-server/stats-threshold-policy # create class fan-module-stats switch-A /eth-server/stats-threshold-policy* # commit-buffer switch-A /eth-server/stats-threshold-policy #</pre>
----------	--

Related Commands	Command	Description
	show fan-module	
	show stats-threshold-policy	

create class fan-stats

To create a fan statistics class, use the **create class fan-stats** command.

create class fan-stats

This command has no arguments or keywords.

Command Default	None
-----------------	------

Command Modes	Statistics threshold policy (/eth-server/stats-threshold-policy)
---------------	--

Command History	Release	Modification
	1.0(1)	This command was introduced.

Usage Guidelines	Use classes to place thresholds on statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for fan statistics.
------------------	---

Examples

This example shows how to create a fan statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy p10

switch-A /eth-server/stats-threshold-policy # create class fan-stats
switch-A /eth-server/stats-threshold-policy* # commit-buffer
switch-A /eth-server/stats-threshold-policy #
```

Related Commands

Command	Description
show fan-module	
show stats-threshold-policy	

create class fc-error-stats

To create a Fibre Channel error statistics class, use the **create class fc-error-stats** command.

create class fc-error-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy /fc-uplink/stats-threshold-policy

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Fibre Channel error statistics.

Examples

This example shows how to create a Fibre Channel error statistics class:

```
switch-A# scope fc-uplink
switch-A /org # scope stats-threshold-policy p10
Pubs-A /org/stats-threshold-policy # create class fc-error-stats
Pubs-A /org/stats-threshold-policy/class* # commit-buffer
Pubs-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	

Command	Description
show stats-threshold-policy	

create class fc-if-event-stats

To create Fibre Channel event statistics, use the **create class fc-if-event-stats** command.

create class fc-if-event-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Fibre Channel event statistics.

Examples

The following example

```
switch-A # scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class fc-if-event-stats
switch-A /org/stats-threshold-policy* # commit-buffer
switch-A /org/stats-threshold-policy #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class fc-if-fc4-counters

To create Fibre Channel counters, use the **create class fc-if-fc4-counters** command.

create class fc-if-fc4-counters

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Fibre Channel counter statistics.

Examples

This example shows how to create Fibre Channel counters:

```
switch-A # scope org org3
switch-A /org # switch-A /org # scope stats-threshold-policy p10

switch-A /org/stats-threshold-policy # create class fc-if-fc4-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class fc-if-frame-stats

To create a Fibre Channel frame statistics class, use the **create class fc-if-frame-stats** command.

create class fc-if-frame-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Fibre Channel frame statistics.

Examples

This example shows how to create a Fibre Channel frame statistics class:

```
switch-A # scope org org3
switch-A /org # switch-A /org # scope stats-threshold-policy p10

switch-A /org/stats-threshold-policy # create class fc-if-frame-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class fc-port-stats

To create Fibre Channel port statistics class, use the **create class fc-port-stats** command.

create class fc-port-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Fibre Channel port statistics.

Examples

This example shows how to create a Fibre Channel port statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class fc-port-stats
```

```
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class fc-stats

To create a Fibre Channel statistics class, use the **create class fc-stats** command.

create class fc-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/fc-uplink/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Fibre Channel statistics.

Examples

This example shows how to create a Fibre Channel statistics class:

```
switch-A# scope fc-uplink
switch-A /fc-uplink # scope stats-threshold-policy p10

switch-A /fc-uplink/stats-threshold-policy # create class fc-stats
switch-A /fc-uplink/stats-threshold-policy/class* # commit-buffer
switch-A /fc-uplink/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class mb-power-stats

To create a mother board power statistics class, use the **create class mb-power-stats** command.

create class mb-power-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for mother board power statistics.

Examples

This example shows how to create a mother board power statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class mb-power-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class mb-temp-stats

To create a temporary mother board statistics class, use the **create class mb-temp-stats** command.

create class mb-temp-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Mb statistics.

Examples

This example shows how to create a temporary mother board statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class mb-temp-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show class mb-temp-stats	

create class memory-runtime

To create a memory runtime class, use the **create class memory-runtime** command.

create class memory-runtime

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to create a memory runtime class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class memory-runtime
switch-A /org/stats-threshold-policy* # commit-buffer
switch-A /org/stats-threshold-policy #
```

Related Commands

Command	Description
show class	
show memory	

create class menlo-dce-port-stats

To create a Menlo port statistics class, use the **create class menlo-dce-port-stats** command.

create class menlo-dce-port-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Menlo Ethernet port statistics.

Examples

This example shows how to create a Menlo port statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class menlo-dce-port-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	

Command	Description
show stats-threshold-policy	

create class menlo-eth-error-stats

To create a Menlo Ethernet error statistics class, use the **create class menlo-eth-error-stats** command.

create class menlo-eth-error-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Menlo Ethernet error statistics.

Examples

This example shows how to create a Menlo Ethernet error statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class menlo-eth-error-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class menlo-eth-stats

To create a Menlo Ethernet statistics class, use the **create class menlo-eth-stats** command.

create class menlo-eth-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Menlo Ethernet statistics.

Examples

This example shows how to create a Menlo Ethernet statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class menlo-eth-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class menlo-fc-error-stats

To create Menlo Fibre Channel error statistics, use the **create class menlo-fc-error-stats** command.

create class menlo-fc-error-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Menlo Fibre Channel error statistics.

Examples

This example shows how to create Menlo Fibre Channel error statistics:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class menlo-fc-error-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class menlo-fc-stats

To create Menlo Fibre Channel statistics, use the **create class menlo-fc-stats** command.

create class menlo-fc-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Menlo Fibre Channel statistics.

Examples

This example shows how to create Menlo Fibre Channel statistics:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class menlo-fc-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class menlo-host-port-stats

To create Menlo host port statistics, use the **create class menlo-host-port-stats** command.

create class menlo-host-port-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Menlo host port statistics.

Examples

This example shows how to create Menlo host port statistics:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class menlo-host-port-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class menlo-mcpu-error-stats

To create a Menlo CPU error statistics class, use the **create class menlo-mcpu-error-stats** command.

create class menlo-mcpu-error-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Menlo CPU error statistics.

Examples

This example shows how to create a Menlo CPU error statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class menlo-mcpu-error-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class menlo-mcpu-stats

To create a Menlo CPU statistics class, use the **create class menlo-mcpu-stats** command.

create class menlo-mcpu-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Menlo CPU statistics.

Examples

This example shows how to create a Menlo CPU statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class menlo-mcpu-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class menlo-net-eg-stats

To create a Menlo network egress statistics class, use the **create class menlo-net-eg-stats** command.

create class menlo-net-eg-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Menlo network egress traffic statistics.

Examples

This example shows how to create a Menlo network egress statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class menlo-net-eg-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class menlo-net-in-stats

To create a Menlo network ingress statistics class, use the **create class menlo-net-in-stats** command.

create class menlo-net-in-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Menlo network ingress traffic statistics.

Examples

This example shows how to create a Menlo network ingress statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class menlo-net-in-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	

Command	Description
show stats-threshold-policy	

create class menlo-q-error-stats

To create a Menlo Qlogic error statistics class, use the **create class menlo-q-error-stats** command.

create class menlo-q-error-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Menlo Qlogic error statistics.

Examples

This example shows how to create a Menlo Qlogic error statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class menlo-q-error-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class menlo-q-stats

To create a Menlo Qlogic statistics class, use the **create class menlo-q-stats** command.

create class menlo-q-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Menlo Qlogic statistics.

Examples

This example shows how to create a Menlo Qlogic statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class menlo-q-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class processor-runtime

To create a processor runtime statistics class, use the **create class processor-runtime** command.

create class processor-runtime

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to create a processor runtime statistics class:

```
switch-A# scope org org10
switch-A /org # scope stats-threshold-policy p10
switch-A /org/stats-threshold-policy # create class processor-runtime
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-statistics	

create class psu-input-stats

To create a power supply input statistics class, use the **create class psu-input-stats** command.

create class psu-input-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for power supply input statistics.

Examples

This example shows how to create a power supply input statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy p10

switch-A /eth-server/stats-threshold-policy # create class psu-input-stats
switch-A /eth-server/stats-threshold-policy/class* # commit-buffer
switch-A /eth-server/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	

Command	Description
show stats-threshold-policy	

create class psu-stats

To create a power supply statistics class, use the **create class psu-stats** command.

create class psu-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for power supply statistics.

Examples

This example shows how to create power supply statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy p10

switch-A /eth-server/stats-threshold-policy # create class psu-stats
switch-A /eth-server/stats-threshold-policy/class* # commit-buffer
switch-A /eth-server/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

create class system-stats

To create a system statistics class, use the **create class system-stats** command.

create class system-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for system statistics.

Examples

This example shows how to create a system statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy p10

switch-A /eth-server/stats-threshold-policy # create class system-stats
switch-A /eth-server/stats-threshold-policy/class* # commit-buffer
switch-A /eth-server/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show system	

create class vnic-stats

To create a Virtual NIC statistics class, use the **create class vnic-stats** command.

create class vnic-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use classes to threshold statistics. For example, you might want to define a threshold on a port that raises a fault if the average number of packets dropped exceeds a certain amount. For this class, you would create thresholds for Virtual NIC statistics.

Examples

This example shows how to create a Virtual NIC statistics class:

```
switch-A# scope org org3
switch-A /org # scope stats-threshold-policy pl
switch-A /org/stats-threshold-policy # create class vnic-stats
switch-A /org/stats-threshold-policy/class* # commit-buffer
switch-A /org/stats-threshold-policy/class #
```

Related Commands

Command	Description
show class	
show vnic-templ	

create destination

To create an email destination, use the **create destination** command.

create destination *email*

Syntax Description

<i>email</i>	Email destination.
--------------	--------------------

Command Default

None

Command Modes

Profile (/monitoring/callhome/profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to create an email destination:

```
switch-A# scope monitoring
switch-A /monitoring # scope callhome
```

```
switch-A /monitoring/callhome # scope profile p3  
switch-A /monitoring/callhome/profile # create destination home@test.com  
switch-A /monitoring/callhome/profile* # commit-buffer  
switch-A /monitoring/callhome/profile #
```

Related Commands

Command	Description
show callhome	
show destination	

create dns

To create a DNS host name , use the **create dns** command.

create dns *name*

Syntax Description

<i>name</i>	DNS host name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Services (/system/services)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to create a DNS host name:

```
switch-A# scope system  
switch-A /system # scope services  
switch-A /system/services # create dns dns10  
switch-A /system/services* # commit-buffer  
switch-A /system/services #
```

Related Commands

Command	Description
show dns	
show ntp	

create dynamic-conn-policy

To create a dynamic VNIC connection policy, use the **create dynamic-conn-policy** command.

create dynamic-conn-policy *name* **protection** { **none** | **protected** } *

Syntax Description

<i>name</i>	Connection name. The range of valid values is 1 to
protection	Specifies that the connection is protected.
none	Specifies no protection.
protected	Specifies protection.

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to create a dynamic VNIC connection policy:

```
switch-A# scope org org10
switch-A /org # create dynamic-vnic-conn-policy cp10 protection none

switch-A /org/dynamic-vnic-conn-policy* # commit-buffer
switch-A /org/dynamic-vnic-conn-policy #
```

Related Commands

Command	Description
show dynamic-vnic-connection-policy	
show vnic-templ	

create epuser

To create an end-point user, use the **create epuser** command.

create epuser *name*

Syntax Description

<i>name</i>	End-point user name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

IPMI access profile (/org/ipmi-access-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Creates the specified endpoint user and enters organization IPMI access profile endpoint user mode.

More than one endpoint user can be created within an IPMI access profile, with each endpoint user having its own password and privileges

Examples

This example shows how to create an end-point user:

```
switch-A# scope org org10
switch-A /org # scope ipmi-access-profile ap10
switch-A /org/ipmi-access-profile # create epuser user10
switch-A /org/ipmi-access-profile/epuser* # commit-buffer
switch-A /org/ipmi-access-profile/epuser #
```

Related Commands

Command	Description
show epuser	
show ipmi-access-profile	

create eth-if

To create an Ethernet interface, use the **create eth-if** command.

create eth-if *name*

Syntax Description

<i>name</i>	Interface name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Virtual NIC (/org/service-profile/vnic)

Virtual NIC template (/org/vnic-templ)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to create an Ethernet interface:

```
switch-A# scope org org10
switch-A /org # scope service-profile sp10
switch-A /org/service-profile # scope vnic vn10
switch-A /org/service-profile/vnic # create eth-if if10
switch-A /org/service-profile/vnic/eth-if* # commit-buffer
switch-A /org/service-profile/vnic/eth-if #
```

Related Commands

Command	Description
show eth-profile	
show service-profile	

create eth-profile

To create an Ethernet profile, use the **create eth-profile** command.

create eth-profile *name*

Syntax Description

<i>name</i>	Profile name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to create an Ethernet profile:

```
switch-A# scope org org10
switch-A /org # create eth-profile ep10
switch-A /org/eth-profile* # commit-buffer
switch-A /org/eth-profile #
```

Related Commands

Command	Description
show failover	
show interrupt	

create fcoe-if

To create a FCoE (Fibre Channel over Ethernet) interface, use the **create fcoe-if** command.

create fcoe-if

This command has no arguments or keywords.

Command Default

None

Command Modes

Virtual NIC (/org/service-profile/vnic)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to create an FCoE interface:

```
switch# scope org org3
switch /org # scope service-profile sp1
switch /org/service-profile # scope vnic
switch /org/service-profile/vnic # create fcoe-if
switch /org/service-profile/vnic* # commit-buffer
switch /org/service-profile/vnic #
```

Related Commands

Command	Description
show interface	
show vnic	

create fc-profile

To create a Fibre Channel profile, use the **create fc-profile** command.

create fc-profile *name*

Syntax Description

<i>name</i>	Profile name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a Fibre Channel profile, and enter organization Fibre Channel profile mode.

Examples

This example shows how to create a Fibre Channel profile:

```
switch# scope org org3
switch /org # create fc-profile fp3
switch /org/fc-profile* # commit-buffer
switch /org/fc-profile #
```

Related Commands

Command	Description
show eth-profile	
show fc-profile	

create fw-host-pack

To create a host pack, use the **create fw-host-pack** command.

create fw-host-pack *name*

Syntax Description

<i>name</i>	Pack name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

A pack is a collection of host firmware images for devices like adapters, HBAs, NICs, and raid controllers. Use this command to create a host firmware package and enter organization firmware host package mode.

Examples

This example shows how to create a host pack:

```
switch-A# scope org org3
Pubs-A /org # create fw-host-pack hp4
Pubs-A /org/fw-host-pack* # commit-buffer
Pubs-A /org/fw-host-pack #
```

Related Commands

Command	Description
show fw- host-pack	
show fw-mgmt-pack	

create fw-mgmt-pack

To create a management pack, use the **create fw-mgmt-pack** command.

create fw-mgmt-pack *name*

Syntax Description

<i>name</i>	Pack name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

A pack is a collection of host firmware images for devices like adapters, HBAs, NICs, and raid controllers. Use this command to create a management firmware package and enter organization firmware management package mode.

Examples

This example shows how to create a management pack:

```
switch# scope org org3
switch /org # create fw-mgmt-pack mp4
switch /org/fw-host-pack* # commit-buffer
switch /org/fw-host-pack #
```

Related Commands

Command	Description
show fw- host-pack	
show fw-mgmt-pack	

create hv-conn

To create an HV connection, use the **create hv-conn** command.

create hv-conn protection { none | protected } *

Syntax Description

protection	Specifies that the connection is protected.
none	Specifies no protection.
protected	Specifies protection.

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a Hypervisor connection, and enter organization HV connection mode.

Examples

This example shows how to create a HV connection:

```
switch# scope org org3
switch /org # scope service-profile sp1
switch /org/service-profile # create hv-conn
switch /org/service-profile/hv-conn* # commit-buffer
switch /org/service-profile/hv-conn #
```

Related Commands

Command	Description
show connectivity	
show hv-conn	

create import-config

To create a import configuration, use the **create import-config** command.

create import-config {ftp:| scp:| sftp:| tftp:} { disabled | enabled } { merge | replace }

Syntax Description

ftp:	Specifies File Transfer Protocol.
scp:	Specifies Secure Copy Protocol.
sftp:	Specifies Secure File Transfer Protocol.
tftp:	Specifies Trivial File Transfer Protocol.
disabled	Specifies disabled.
enabled	Specifies enabled.
merge	Specifies merge.
replace	Specifies replace.

Command Default

None

Command Modes

System (/system)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a configuration for importing files, and enter organization import configuration mode.

Examples

This example shows how to create an import configuration:

```
switch# scope system
switch /system # create import-config ftp: enabled replace

switch /service/import-config* # commit-buffer
switch /service/import-config #
```

Related Commands

Command	Description
show image	

Command	Description
show import-config	

create initiator

To create an initiator, use the **create initiator** command.

create initiator *id*

Syntax Description	
<i>id</i>	Initiator identification number. The range of valid values is 1 to 16.

Command Default	None
-----------------	------

Command Modes	WWN pool (/org/wwn-pool)
---------------	--------------------------

Command History	Release	Modification
	1.0(1)	This command was introduced.

Usage Guidelines	Use this command to create a WWN initiator, and enter organization initiator mode.
------------------	--

Examples

This example shows how to create an initiator:

```
switch-A# scope org org3
switch-A /org # scope wwn-pool wwnpool3
switch-A /org/wwn-pool # create initiator
switch-A /org/wwn-pool/initiator* # commit-buffer
switch-A /org/wwn-pool/initiator #
```

Related Commands	Command	Description
	show block	
	show initiator	

create interface

To create an interface, use the **create interface** command.

create interface *slot-id port-id*

Syntax Description	<i>slot-id</i>	Slot identification number. The range of valid values is 2 to 5.
	<i>port-id</i>	Port identification number. The range of valid values is 1 to 40.
Command Default	None	
Command Modes	Fabric interconnect under Fibre Channel uplink (/fc-uplink/fabric) Fabric interconnect under Ethernet server (/eth-server/fabric) Fabric interconnect under Ethernet uplink (/eth-uplink/fabric)	
Command History	Release	Modification
	1.0(1)	This command was introduced.
Usage Guidelines	Use this command to create an Ethernet or Fibre Channel interface, and enter organization interface mode.	
Examples	This example shows how to create an interface: <pre> switch# scope fc-uplink switch /fc-uplink # scope switch b switch /fc-uplink/switch # create interface 5 10 switch /fc-uplink/switch/interface* # commit-buffer switch /fc-uplink/switch/interface # </pre>	
Related Commands	Command	Description
	show interface	
	show switch	

create ipmi-access-profile

To create an IPMI (Intelligent Platform Management Interface) access profile, use the **create ipmi-access-profile** command.

create ipmi-access-profile *name*

Syntax Description	<i>name</i>	IPMI access profile name. The range of valid values is 1 to 16.
---------------------------	-------------	---

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create an IPMI access profile, and enter organization IPMI access profile mode.

Examples

This example shows how to create an IPMI access profile:

```
switch# scope org org3
switch /org # create ipmi-access-profile ipmiProf1

switch /org/ipmi-access-profile* # commit-buffer
switch /org/ipmi-access-profile #
```

Related Commands

Command	Description
show epuser	
show ipmi-access-profile	

create keyring

To create a keyring, use the **create keyring** command.

create keyring *name*

Syntax Description

<i>name</i>	Keyring name. The range of valid values is 1 to
-------------	---

Command Default

None

Command Modes

Security (/security)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to implement RSA public-key cryptography, and enter organization keyring mode.

Examples

This example shows how to create a keyring:

```
switch# scope security
switch /security # create keyring kr220
switch /security/keyring* # commit-buffer
switch /security/keyring #
```

Related Commands

Command	Description
show keyring	
show radius	

create lan

To create a LAN, use the **create lan** command.

create lan

This command has no arguments or keywords.

Command Default

None

Command Modes

Boot policy under organization (/org/boot-policy)

Boot definition under service-profile (/org/service-profile/boot-def)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a LAN, and enter organization lan mode.

Examples

This example shows how to create a LAN:

```
switch-A# scope org org3
switch-A /org # scope boot-policy bp6
switch-A /org/boot-policy # create lan
switch-A /org/boot-policy/lan* # commit-buffer
switch-A /org/boot-policy/lan #
```

Related Commands

Command	Description
show boot-policy	
show lan	

create local

To create local storage, use the **create local** command.

create local

Command Default

None

Command Modes

Storage (/org/boot-policy/storage)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to create local storage:

```
switch# scope org org10
switch /org # scope boot-policy bp10
switch /org/boot-policy # scope storage
switch /org/boot-policy/storage # create local storage10
switch /org/boot-policy/storage* # commit-buffer
switch /org/boot-policy/storage #
```

Related Commands

Command	Description
show local	
show storage	

create local-disk-config

To create a local disk configuration, use the **create local-disk-config** command.

create local-disk-config

This command has no arguments or keywords.

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a local disk configuration, and enter organization local disk configuration mode.

Examples

This example shows how to create a local disk configuration:

```
switch# scope org org3
switch /org # scope service-profile sp1
switch /org/service-profile # create local-disk-config
switch /org/service-profile/local-disk-config* # commit-buffer
switch /org/service-profile/local-disk-config #
```

Related Commands

Command	Description
show local-disk-config	
show local-disk-config-policy	

create local-disk-config-policy

To create a local disk configuration policy, use the **create local-disk-config-policy** command.

create local-disk-config-policy *name*

Syntax Description

<i>name</i>	Local disk configuration policy name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a local disk configuration policy, and enter organization local disk configuration policy mode.

Examples

This example shows how to create a local disk configuration policy:

```
switch# scope org org3
switch /org # create local-disk-config-policy ldcpl
switch /org/local-disk-config-policy* # commit-buffer
Pubs-A /org/local-disk-config-policy #
```

Related Commands

Command	Description
show local-disk-config	
show local-disk-config-policy	

create locale

To create a locale, use the **create locale** command.

create locale *name*

Syntax Description

<i>name</i>	Locale name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Local user (/security/local-user)
Security (/security)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a locale, and enter organization local user mode.

Examples

This example shows how to create a locale:

```
switch# scope security
switch /security # scope local-user lu1
switch /security # create locale locale1
switch /security/local-user* # commit-buffer
switch /security/local-user #
```

Related Commands

Command	Description
show locale	
show local-user	

create local-user

To create a local user, use the **create local-user** command.

create local-user *name*

Syntax Description

<i>name</i>	Local user name. The range of valid values is 1 to 74.
-------------	--

Command Default

None

Command Modes

Security (/security)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a local user, and enter organization local user mode.

Examples

This example shows how to create a local user:

```
switch# scope security
switch /security # scope local-user lu1
switch /security # create local-user lu2
switch /security/local-user* # commit-buffer
switch /security/local-user #
```

Related Commands

Command	Description
show locale	
show local-user	

create mac-pool

To create a MAC pool, use the **create mac-pool** command.

create mac-pool *name*

Syntax Description

<i>name</i>	MAC pool name. The range of valid values is 1 to 70.
-------------	--

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a block of MAC addresses, and enter organization MAC pool mode.

Examples

This example shows how to create a MAC pool:

```
switch# scope org org3
switch /org # create mac-pool mp1
switch /org/mac-pool* # commit-buffer
switch /org/mac-pool #
```

Related Commands

Command	Description
show block	
show pooled	

create mac-security

To create MAC security, use the **create mac-security** command.

create mac-security

This command has no arguments or keywords.

Command Default

None

Command Modes

Port profile (/eth-uplink/port-profile)

Command History	Release	Modification
	1.0(1)	This command was introduced.
Usage Guidelines	Use this command to create MAC security, and enter organization MAC security mode.	
Examples	<p>This example shows how to create MAC security:</p> <pre>switch# scope eth-uplink switch /eth-uplink # scope port-profile ppl switch /eth-uplink/port-profile # create mac-security switch /eth-uplink/port-profile/mac-security* # commit-buffer switch /eth-uplink/port-profile/mac-security #</pre>	
Related Commands	Command	Description
	show mac-security	
	show port-profile	

create member-port

To create a member port, use the **create member-port** command.

create member-port { **a** | **b** } *slot-id* *port-id*

Syntax Description	a	Specifies port A.
	b	Specifies port B.
	<i>slot-id</i>	Slot identification number. The range of valid values is 1 to 5.
	<i>port-id</i>	Port identification number. The range of valid values is 1 to 40.

Command Default None

Command Modes

- Port channel (/eth-uplink/switch/port-channel)
- VSAN under Fibre Channel uplink (/fc-uplink/vsan)
- VSAN under fabric interconnect (/fc-uplink/fabric/vsan)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a member port, and enter organization member port mode.

Examples

This example shows how to create a member port:

```
switch# scope eth-uplink
switch /eth-uplink # scope switch b
switch /eth-uplink/switch # scope port-channel 3
switch /eth-uplink/switch/port-channel # create member-port 2 4
switch /eth-uplink/switch/port-channel/member-port* # commit-buffer
switch /eth-uplink/switch/port-channel/member-port #
```

Related Commands

Command	Description
show member-port	
show port-channel	

create memory

To create a memory qualifier, use the **create memory** command.

create memory

This command has no arguments or keywords.

Command Default

None

Command Modes

Server qualification (/org/server-qual)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a memory qualifier, and enter organization memory mode.

Examples

This example shows how to create a memory qualifier:

```
Pubs-A# scope org org3
Pubs-A /org # scope server-qual sq20
Pubs-A /org/server-qual # create memory
Pubs-A /org/server-qual/memory* # commit-buffer
Pubs-A /org/server-qual/memory #
```

Related Commands

Command	Description
show memory	
show processor	

create network

To create a Ethernet interface, use the **create network** command.

create network *name*

Syntax Description

<i>name</i>	Ethernet interface name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Port profile (/eth-uplink/port-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Use this command to create a network, and enter organization network mode.

Examples

This example shows how to create an Ethernet interface:

```
switch# scope eth-uplink
switch /eth-uplink # scope port-profile ppl
switch /eth-uplink/port-profile # create network eth1
switch /eth-uplink/port-profile/network* # commit-buffer
switch /eth-uplink/port-profile/network #
```

Related Commands

Command	Description
show fc-uplink	
show network	

create ntp-server

To create an NTP server, use the **create ntp-server** command.

create ntp-server *name*

Syntax Description	
<i>name</i>	Server name.

Command Default	None
-----------------	------

Command Modes	Services (/system/services)
---------------	-----------------------------

Command History	Release	Modification
	1.0(1)	This command was introduced.

Usage Guidelines	Use this command to create an NTP server, and enter organization NTP server mode.
------------------	---

Examples	<p>This example shows how to create an NTP server:</p> <pre>switch-A# scope system switch-A /system # scope services switch-A /system/services # create ntp-server ntps1 switch-A /system/services/ntp-server* # commit-buffer switch-A /system/services/ntp-server #</pre>
----------	---

Related Commands	Command	Description
	show dns	
	show ntp	

create org

To create an org, use the **create org** command.

create org *name*

Syntax Description	
<i>name</i>	Org name. The range of valid values is 1 to 80.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Organizations are logical entities that you can use to divide up large physical infrastructures into smaller infrastructures.

Use this command to create an organization, and enter organization mode.

Examples

This example shows how to create an org:

```
Pubs-A# scope org org3
Pubs-A /org # create org org4
Pubs-A /org* # commit-buffer
Pubs-A /org #
```

Related Commands

Command	Description
show mac-pool	
show org	

create org-ref

To create a organization reference, use the **create org-ref** command.

create org-ref *name orgdn domain-name*

Syntax Description

<i>name</i>	Organization name. The range of valid values is 1 to 16.
orgdn	Specifies the organization domain name.
<i>domain-name</i>	Domain name.

Command Default

None

Command Modes

Locale (/security/locale)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

The **create org-ref** command creates a an organization reference to a locale. Use this command to create a organization reference, and enter organization organization reference mode.

You can specify more than one org-ref-name and orgdn-name argument on the same command line to reference multiple organizations to the locale, or you can add organizations to the same locale using multiple **create org-ref** commands.

Examples

This example shows how to create an organization reference to a locale:

```
switch# scope security
switch /security # scope locale locale1
switch /security/locale # create org-ref or3 orgdn or30
switch /security/locale/org-ref* # commit-buffer
switch /security/locale/org-ref #
```

Related Commands

Command	Description
show locale	
show org	

create pack-image

To create an image pack, use the **create pack-image** command.

create pack-image *hw-vendor hw-model* { **server-bios** | **adapter** | **raid-controller** | **host-nic** | **host-hba** | **host-hba-optionrom** } *version*

Syntax Description

<i>hw-vendor</i>	Hardware vendor.
<i>hw-model</i>	Hardware model number.
server-bios	Specifies the image for the server.
adapter	Specifies the image for the adapter.
raid-controller	Specifies the image for the RAID array.
host-nic	Specifies the image for the host NIC.
host-hba	Specifies the image for the host HBA.

host-hba-optionrom	Specifies the image for the host HBA optional ROM.
<i>version</i>	Hardware version.

Command Default

None

Command Modes

Firmware management package (/org/fw-mgmt-pack)
 Firmware host package (/org/fw-host-pack)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

A pack is a collection of host firmware images.
 Use this command to create a pack-image, and enter organization pack image mode.
 Keywords found in the **create pack-image** command are not supported in /org/fw-mgmt-pack mode.

Examples

This example shows how to create an image pack:

```
switch# scope org org3
switch /org # scope fw-mgmt-pack fmp1
switch /org/fw-mgmt-pack # create pack-image hp 1100 bmc 1.2
switch /org/fw-mgmt-pack/pack-image* # commit-buffer
switch /org/fw-mgmt-pack/pack-image #
```

Related Commands

Command	Description
show fw-host-pack	
show fw-mgmt-pack	

create path

To create a LAN image path, use the **create path** command.

create path { **primary** | **secondary** }

Syntax Description

primary	Specifies a primary path.
secondary	Specifies specifies a secondary path.

Command Default

None

Command Modes

SAN image under boot-definition/storage (/org/service-profile/boot-def/storage/san-image)

LAN under boot-policy (/org/boot-policy/lan)

LAN under boot-definition /org/service-profile/boot-def/lan

SAN image under boot-policy/storage (/org/boot-policy/storage/san-image)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

The LAN image path is the path the vNIC used when booting from an image on a LAN, such as a PXE boot. For each path you can specify the vNIC to use.

Use this command to create a LAN image path, and enter organization path mode.

Examples

This example shows how to create a LAN image path:

```
switch# scope org org3
switch /org # scope boot-policy boot1
switch /org/boot-policy # scope lan
switch /org/boot-policy/lan # create path primary
switch /org/boot-policy/lan/path* # commit-buffer
switch /org/boot-policy/lan/path #
```

Related Commands

Command	Description
show lan	
show path	

create pin-group

To create a pin group, use the **create pin-group** command.

create pin-group *name*

Syntax Description

<i>name</i>	Pin group name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Ethernet uplink (/eth-uplink)
Fibre Channel uplink (/fc-uplink)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Pinning in Cisco UCS is only relevant to uplink ports.

When you determine the optimal configuration for pin groups and pinning for an uplink port, consider the estimated bandwidth usage for the servers. If you know that some servers in the system will use a lot of bandwidth, ensure that you pin these servers to different uplink ports.

Use this command to create a pin group, and enter organization pin-group mode.

Examples

This example shows how to create a pin group:

```
switch# scope eth-uplink
switch /eth-uplink # create pin-group pg110
switch /eth-uplink/pin-group* # commit-buffer
switch /eth-uplink/pin-group #
```

Related Commands

Command	Description
show eth-uplink	
show pin-group	

create policy

To create a policy, use the **create policy** command.

callhome mode

create policy { **equipment-degraded** | **equipment-inoperable** | **fru-problem** | **identity-unestablishable** | **power-problem** | **thermal-problem** | **voltage-problem** }

flow-control mode

create policy *name*

Syntax Description

equipment-degraded	Specifies an equipment degraded policy.
equipment-inoperable	Specifies an equipment inoperable policy.
fru-problem	Specifies a field replaceable unit policy.

identity-unestablishable	Specifies an identity unestablishable policy.
power-problem	Specifies a power problem policy.
thermal-problem	Specifies a thermal problem policy.
voltage-problem	Specifies a voltage problem policy.
<i>name</i>	Policy name. The range of valid values is 1 to 16.

Command Default

None

Command Modes

Callhome (/monitoring/callhome)

Flow control (/eth-uplink/flow-control)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a policy, and enter either organization callhome or organization flow control mode.

Examples

This example shows how to create a policy:

```
switch# scope eth-uplink
switch /eth-uplink # scope flow-control

switch /eth-uplink/flow-control # create policy policy1
switch /eth-uplink/flow-control* # commit-buffer
switch /eth-uplink/flow-control #
```

Related Commands

Command	Description
show policy	
show stats-threshold-policy	

create pooling-policy

To create a pooling policy, use the **create pooling-policy** command.

create pooling-policy *name*

Syntax Description

<i>name</i>	Policy name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Creates a server pooling policy, and enters organization pooling policy mode.

Examples

This example shows how to create a pooling policy:

```
switch# scope org org3
switch /org # create pooling-policy pp110
switch /org/pooling-policy* # commit-buffer
switch /org/pooling-policy #
```

Related Commands

Command	Description
show policy	
show pooling-policy	

create port-channel

To create a port channel, use the **create port-channel** command.

create port-channel *id*

Syntax Description

<i>id</i>	Port identification number. The range of valid values is 1 to 40.
-----------	---

Command Default

None

Command Modes

Fabric interconnect (/eth-uplink/fabric)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Consider using a port channel to make best use of capacity when multiple uplinks are used on a switch.

Use this command to create a port channel, and enter organization port channel mode.

Examples

This example shows how to create a port channel:

```
switch# scope eth-uplink
switch /eth-uplink # scope switch b
switch /eth-uplink/switch # create port-channel 20
switch /eth-uplink/switch/port-channel* # commit-buffer
switch /eth-uplink/switch/port-channel #
```

Related Commands

Command	Description
show port-channel	
show switch	

create port-profile

To create a port profile, use the **create port-profile** command.

create port-profile *name*

Syntax Description

<i>name</i>	Port profile name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Ethernet uplink (/eth-uplink)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a port profile, and enter organization port profile mode.

Examples

This example shows how to create a port profile:

```
switch# scope eth-uplink
switch /eth-uplink # create port-profile pp110
switch /eth-uplink/port-profile* # commit-buffer
switch /eth-uplink/port-profile #
```

Related Commands

Command	Description
show eth-uplink	
show port-profile	

create processor

To create a processor, use the **create processor** command.

create processor

This command has no arguments or keywords.

Command Default

None

Command Modes

Server qualification (/org/server-qual)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a processor, and enter organization processor mode.

Only one processor qualifier can be created.

Examples

This example shows how to create a processor:

```
switch# scope org org3
switch /org # scope server-qual sq20
switch /org/server-qual # create processor
switch /org/server-qual/processor* # commit-buffer
switch /org/server-qual/processor #
```

Related Commands

Command	Description
show processor	
show server-qual	

create profile

To create a profile, use the **create profile** command.

create profile *name*

Syntax Description	<p><i>name</i> Profile name. The range of valid values is 1 to 16.</p>						
Command Default	None						
Command Modes	Callhome (/monitoring/callhome)						
Command History	<table> <tr> <th>Release</th><th>Modification</th></tr> <tr> <td>1.0(1)</td><td>This command was introduced.</td></tr> </table>	Release	Modification	1.0(1)	This command was introduced.		
Release	Modification						
1.0(1)	This command was introduced.						
Usage Guidelines	Use this command to create a profile, and enter organization profile mode.						
Examples	<p>This example shows how to create a profile:</p> <pre>switch# scope monitoring switch /monitoring # scope callhome switch /monitoring/callhome # create profile p210 switch /monitoring/callhome/profile* # commit-buffer switch /monitoring/callhome/profile #</pre>						
Related Commands	<table> <tr> <th>Command</th><th>Description</th></tr> <tr> <td>show callhome</td><td></td></tr> <tr> <td>show profile</td><td></td></tr> </table>	Command	Description	show callhome		show profile	
Command	Description						
show callhome							
show profile							

create property (cpu)

To create a CPU property, use the **create property** command.

create property { **cpu-temp-max** | **cpu-temp** | **cpu-temp-avg** | **cpu-temp-min** }

Syntax Description	<p>cpu-temp-max Specifies maximum CPU temperature.</p>
	<p>cpu-temp Specifies CPU temperature.</p>
	<p>cpu-temp-avg Specifies average CPU temperature.</p>
	<p>cpu-temp-min Specifies minimum CPU temperature.</p>

Command Default

No CPU statistics are recorded.

Command Modes

Property (/org/stats-threshold-policy/class/property)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a CPU property, and to enter property mode.
You must create a cpu-stats statistic class before you can create a CPU property.

Examples

This example shows how to create a CPU property:

```
switch-A# scope org org10
switch-A /org # scope stats-threshold-policy stp10
switch-A /org/stats-threshold-policy # scope class cpu-stats

switch-A /org/stats-threshold-policy/class # create property cpu-temp
switch-A /org/stats-threshold-policy/class/property* # commit-buffer
switch-A /org/stats-threshold-policy/class/property #
```

Related Commands

Command	Description
show property	
showw threshold-value	

create property (packet errors)

To create a packet errors property, use the **create property** command.

```
create property { bad-crc-packets-delta | mac-discarded-packets-max | mac-discarded-packets-avg |
bad-length-packets-max | bad-length-packets-delta | bad-crc-packets-avg | bad-length-packets-min |
mac-discarded-packets-min | bad-crc-packets-max | mac-discarded-packets-delta | bad-length-packets-avg
| bad-crc-packets-min }
```

Syntax Description

bad-crc-packets-delta	Specifies the change in the number of packets with a bad CRC.
mac-discarded-packets-max	Specifies the maximum number of packets that have been discarded because of MAC address.
mac-discarded-packets-avg	Specifies the average number of packets that have been discarded because of MAC address.

bad-length-packets-max	Specifies the maximum number of packets with bad length.
bad-length-packets-delta	Specifies the change in the number of packets with bad length.
bad-crc-packets-avg	Specifies the average number of packets with a bad CRC.
bad-length-packets-min	Specifies the minimum number of packets with bad length.
mac-discarded-packets-min	Specifies the minimum number of packets that have been discarded because of MAC address.
bad-crc-packets-max	Specifies the maximum number of packets with a bad CRC.
mac-discarded-packets-delta	Specifies the change in the number of packets that have been discarded because of MAC address.
bad-length-packets-avg	Specifies the number of packets with bad length.
bad-crc-packets-min	Specifies the minimum number of packets with a bad CRC.

Command Default No packet error statistics are recorded.

Command Modes Property (/org/stats-threshold-policy/class/property)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Usage Guidelines Use this command to create a packet errors property, and to enter property mode.
You must create an Ethernet port error statistic class before you can create a packet size property.

Examples This example shows how to create a packet discard or length property:

```
switch-A# scope org org10
switch-A /org # scope stats-threshold-policy stp10
switch-A /org/stats-threshold-policy # scope class ethernet-port-err-stats

switch-A /org/stats-threshold-policy/class # create property bad-crc-packets-max
switch-A /org/stats-threshold-policy/class/property* # commit-buffer
switch-A /org/stats-threshold-policy/class/property #
```

Related Commands	Command	Description
	show property	
	showw threshold-value	

create property (packet size)

To create a packet size property, use the **create property** command.

```
create property { oversized-packets-delta | undersized-bad-crc-packets-max |
oversized-bad-crc-packets-delta | undersized-good-crc-packets-avg | oversized-packets-avg |
oversized-good-crc-packets-max | oversized-bad-crc-packets-min | oversized-good-crc-packets-delta |
oversized-bad-crc-packets-max | oversized-packets-max | undersized-good-crc-packets-min |
undersized-bad-crc-packets-delta | oversized-bad-crc-packets-avg | undersized-bad-crc-packets-min |
oversized-packets-min | oversized-good-crc-packets-min | oversized-good-crc-packets-avg |
undersized-good-crc-packets-max | undersized-bad-crc-packets-avg | undersized-good-crc-packets-delta
}
```

Syntax Description

oversized-packets-delta	Specifies the change in the number of oversized packets.
undersized-bad-crc-packets-max	Specifies the maximum number of undersized packets with a bad CRC.
oversized-bad-crc-packets-delta	Specifies the change in the number of oversized packets with a bad CRC.
undersized-good-crc-packets-avg	Specifies the average of undersized packets with a good CRC.
oversized-packets-avg	Specifies the average of oversized packets.
oversized-good-crc-packets-max	Specifies the maximum number of oversized packets with a good CRC.
oversized-bad-crc-packets-min	Specifies the minimum number of oversized packets with a bad CRC.
oversized-good-crc-packets-delta	Specifies the change in the number of oversized packets with a good CRC.
oversized-bad-crc-packets-max	Specifies the maximum number of oversized packets with a bad CRC.
oversized-packets-max	Specifies the maximum number of oversized packets.
undersized-good-crc-packets-min	Specifies the maximum number of undersized packets with a bad CRC.
undersized-bad-crc-packets-delta	Specifies the change in the number of undersized packets with a bad CRC.
oversized-bad-crc-packets-avg	Specifies the average of oversized packets with a bad CRC.
undersized-bad-crc-packets-min	Specifies the minimum number of undersized packets with a bad CRC.

oversized-packets-min	Specifies the minimum number of oversized packets.
oversized-good-crc-packets-min	Specifies the minimum number of oversized packets with a good CRC.
oversized-good-crc-packets-avg	Specifies the average of oversized packets with a good CRC.
undersized-good-crc-packets-max	Specifies the maximum number of undersized packets with a good CRC.
undersized-bad-crc-packets-avg	Specifies the average of undersized packets with a bad CRC.
undersized-good-crc-packets-delta	Specifies the change in the number of undersized packets with a good CRC.

Command Default No packet size statistics are recorded.

Command Modes Property (/org/stats-threshold-policy/class/property)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Usage Guidelines Use this command to create a packet size property, and to enter property mode.
You must create an Ethernet port oversized/undersized packet statistic class before you can create a packet size property.

Examples This example shows how to create a packet size property:

```

switch-A# scope org org10
switch-A /org # scope stats-threshold-policy stp10
switch-A /org/stats-threshold-policy # scope class ethernet-port-over-under-sized-stats

switch-A /org/stats-threshold-policy/class # create property undersized-bad-crc-packets-max

switch-A /org/stats-threshold-policy/class/property* # commit-buffer
switch-A /org/stats-threshold-policy/class/property #

```

Related Commands	Command	Description
	show property	
	showw threshold-value	

create qos-policy

To create a QoS policy, use the **create qos-policy** command.

create qos-policy *name*

Syntax Description

<i>name</i>	QoS policy name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a QoS policy, and enter organization QoS policy mode.

Examples

This example shows how to create a QoS policy:

```
switch# scope org org3
switch /org # create qos-policy qp1
switch /org/qos-policy* # commit-buffer
switch /org/qos-policy #
```

Related Commands

Command	Description
show qos-policy	
show vnic-egress-policy	

create role

To create a role, use the **create role** command.

create role *name*

Syntax Description

<i>name</i>	Role name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Local user (/security/local-user)
 Security (/security)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a role, and enter organization role mode.

Examples

This example shows how to create a role:

```
switch# scope security
switch /security # create role admin
switch /security/role* # commit-buffer
switch /security/role #
```

Related Commands

Command	Description
show local-user	
show role	

create san-image

To create a SAN image, use the **create san-image** command.

create san-image { primary | secondary }

Syntax Description

primary	Specifies primary image.
secondary	Specifies secondary image.

Command Default

None

Command Modes

Storage (/org/service-profile/boot-def/storage)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Only one SAN image can be created and committed.

Use this command to create a SAN image, and enter organization SAN image mode.

Examples

This example shows how to create a SAN image:

```
switch#scope org org3
switch /org # scope service-profile sp1
switch /org/service-profile # scope boot-def
switch /org/service-profile/boot-def # scope storage
switch /org/service-profile/boot-def/storage # create san-image primary

switch /org/service-profile/boot-def/storage/san-image* # commit-buffer
switch /org/service-profile/boot-def/storage/san-image #
```

Related Commands

Command	Description
show local	
show san-image	

create scrub-policy

To create a scrub policy, use the **create scrub-policy** command.

create scrub-policy *name*

Syntax Description

<i>name</i>	Scrub policy name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a scrub policy, and enter organization scrub policy mode.

Examples

This example shows how to create a scrub policy:

```
switch# scope org org100
switch /org # create scrub-policy scrub100
switch /org/scrub-policy* # commit-buffer
switch /org/scrub-policy #
```

Related Commands

Command	Description
show server-disc-policy	
show scrub-policy	

create server

To create a server, use the **create server** command.

create server {*name* | *chassis-id/slot-id*}

Syntax Description

<i>name</i>	Server name. Valid entries for this value are a name or an IP address. The range of valid values for a name is 1 to 16.
<i>chassis-id/slot-id</i>	Chassis and slot identification numbers.

Command Default

None

Command Modes

VMware management (/system/vm-mgmt)
 LDAP (/security/ldap)
 TACACS (/security/tacacs)
 RADIUS (/security/radius)
 Server pool (/org/server-pool)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

This command takes the *name* argument only in the /org/server-pool mode.

Use this command to create a server, and enter organization server mode.

Examples

This example shows how to create a server:

```
switch#scope security
switch /security # scope radius
switch /security/radius # create server radius 209.165.200.226
switch /security/radius/server* # commit-buffer
switch /security/radius/server #
```

Related Commands

Command	Description
show aaa	
show server	

create server-autoconfig-policy

To create a server automatic configuration policy, use the **create server-autoconfig-policy** command.

create server-autoconfig-policy *name*

Syntax Description

<i>name</i>	Policy name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

The **server-autoconfig-policy** command is definable only in org /.

Use this command to create a server automatic configuration policy with the specified policy name, and enters organization server automatic configuration policy mode.

Examples

This example shows how to create a server autoconfiguration policy:

```
switch#scope org org3
switch /org # create server-autoconfig-policy sap110

switch /org/server-autoconfig-policy* # commit-buffer
switch /org/server-autoconfig-policy #
```

Related Commands

Command	Description
show server-disc-policy	
show server-autoconfig-policy	

create server-disc-policy

To create a server discovery policy, use the **create server-disc-policy** command.

create server-disc-policy *name*

Syntax Description

<i>name</i>	Server discovery policy name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

The **server-disc-policy** command is definable only in org /.
Use this command to create a server discovery policy, and enter organization server discovery policy mode.

Examples

This example shows how to create a server discovery policy:

```
switch#scope org org3
switch /org # create server-disc-policy sdp110
switch /org/server-disc-policy* # commit-buffer
switch /org/server-disc-policy #
```

Related Commands

Command	Description
show server-disc-policy	
show server-autoconfig-policy	

create server-inherit-policy

To create a server inherit policy, use the **create server-inherit-policy** command.

create server-inherit-policy *name*

Syntax Description	<i>name</i> Policy name. The range of valid values is 1 to 16.	
Command Default	None	
Command Modes	Organization (/org)	
Command History	Release	Modification
	1.0(1)	This command was introduced.
Usage Guidelines	<p>The server-inherit-policy command is definable only in org /.</p> <p>Use this command to create a server inherit policy, and enter organization server inherit policy mode.</p>	
Examples	<p>This example shows how to create a server inherit policy:</p> <pre>switch#scope org / switch /org # create server-inherit-policy sip110 switch /org/server-inherit-policy* # commit-buffer switch /org/server-inherit-policy #</pre>	
Related Commands	Command	Description
	show server-disc-policy	
	show server-inherit-policy	

create server-pool

To create a server pool, use the **create server-pool** command.

create server-pool *name*

Syntax Description	<i>name</i> Server pool name. The range of valid values is 1 to 16.	
Command Default	None	
Command Modes	Organization (/org)	

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a server pool, and enter organization server pool mode.

Examples

This example shows how to create a server pool:

```
switch#scope org org3
switch /org # create server-pool sPool10
switch /org/server-pool* # commit-buffer
switch /org/server-pool #
```

Related Commands

Command	Description
show org	
show server-pool	

create server-qual

To create a server qualifier, use the **create server-qual** command.

create server-qual *name*

Syntax Description

<i>name</i>	Server qualifier name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a server qualifier, and enter organization server qualification mode.

Examples

This example shows how to create a server qualifier:

```
switch#scope org org3
switch /org # create server-qual sql10
```

```
switch /org/server-qual* # commit-buffer
switch /org/server-qual #
```

Related Commands

Command	Description
show server-pool	
show server-qual	

create service-profile

To create a service profile, use the **create service-profile** command.

create service-profile *name* [**initial-template** | **instance** | **updating-template**]

Syntax Description

<i>name</i>	Service profile name. The range of valid values is 1 to 16.
initial-template	Specifies
instance	Specifies
updating-template	Specifies

Command Default

None.

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a service profile, and enter organization service profile mode.

Examples

The following example

```
switch# scope org org110
switch /org # create service-profile spEast110

switch /org/service-profile* # commit-buffer
switch /org/service-profile #
```

Related Commands

Command	Description
show ipmi-access-profile	

Command	Description
show service-profile	

create slot

To create a slot, use the **create slot** command.

create slot *min-id max-id*

Syntax Description

<i>min-id</i>	Minimum slot identification number. The range of valid values is 1 to 8.
<i>max-id</i>	Maximum slot identification number. The range of valid values is 1 to 8.

Command Default

None

Command Modes

Chassis (/org/server-qual/chassis)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a slot with the specified ID, and enters organization slot mode.

Examples

This example shows how to create a slot:

```
switch# scope org org10
switch /org # scope server-qual sq10
switch /org/server-qual # scope chassis 1 1
switch /org/server-qual/chassis # create slot 1 1
switch /org/server-qual/chassis/slot* # commit-buffer
switch /org/server-qual/chassis/slot #
```

Related Commands

Command	Description
show chassis	
show slot	

create snmp-trap

To create an SNMP trap, use the **create snmp-trap** command.

create snmp-trap *name*

Syntax Description

<i>name</i>	Host IP address. Specify the IP address in the format A.B.C.D.
-------------	--

Command Default

None

Command Modes

Monitoring (/monitoring)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a SNMP trap with the specified name, and enters organization snmp-trap mode.

Examples

This example shows how to create an SNMP trap:

```
switch#scope monitoring
switch /monitoring # create snmp-trap 209.165.200.226

switch /monitoring/snmp-trap* # commit-buffer
switch /monitoring/snmp-trap #
```

Related Commands

Command	Description
show callhome	
show snmp-trap	

create sol-config

To create a Serial over LAN (SoL) configuration, use the **create sol-config** command.

create sol-config

This command has no arguments or keywords.

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a SoL configuration, and enter organization SoL configuration mode.

Examples

This example shows how to create a SoL configuration:

```
switch-A# scope org org30
switch-A /org # scope service-profile sp30a
switch-A /org/service-profile # create sol-config
switch-A /org/service-profile/sol-config* # commit-buffer
switch-A /org/service-profile/sol-config #
```

Related Commands

Command	Description
show sol-config	
show sol-policy	

create sol-policy

To create an SoL policy, use the **create sol-policy** command.

create sol-policy *name*

Syntax Description

<i>name</i>	SoL policy name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a SoL policy with the specified name, and enters organization SoL policy mode.

Examples

This example shows how to create a SoL policy:

```
switch-A# scope org org3
switch-A /org # create sol-policy solpoll
switch-A /org/sol-policy* # commit-buffer
switch-A /org/sol-policy #
```

Related Commands

Command	Description
show org	
show sol-policy	

create stats-threshold-policy

To create a statistics threshold policy, use the **create stats-threshold-policy** command.

create stats-threshold-policy *name*

Syntax Description

<i>name</i>	Policy name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0	This command was introduced.

Usage Guidelines

Use this command to create a statistics threshold policy, and enter organization statistics threshold policy mode.

Examples

This example shows how to create a statistics threshold policy:

```
switch# scope org org10
switch /org # create stats-threshold-policy stp10

switch /org/stats-threshold-policy* # commit-buffer
switch /org/stats-threshold-policy #
```

Related Commands

Command	Description
show pooling-policy	

Command	Description
show stats-threshold-policy	

create storage

To create storage, use the **create storage** command.

create storage

This command has no arguments or keywords.

Command Default

None

Command Modes

Boot definition (/org/service-profile/boot-def)

Boot policy (/org/boot-policy)

Server qualification (/org/server-qual)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a storage qualification, and enter organization server qualification storage mode.

Examples

This example shows how to create storage:

```
switch-A# scope org org3
switch-A /org # scope service-profile spl
switch-A /org/service-profile # scope boot-def bd1
switch-A /org/service-profile/boot-def # create storage
switch-A /org/service-profile/boot-def/storage* # commit-buffer
switch /org/service-profile/boot-def/storage #
```

Related Commands

Command	Description
show boot-definition	
show storage	

create trustpoint

To create a trust point, use the **create trustpoint** command.

create trustpoint *name*

Syntax Description	<div><i>name</i></div> <div>Trust point name. The range of valid values is 1 to 16.</div>							
Command Default	None							
Command Modes	Security (/security)							
Command History	<table><tr><th>Release</th><th>Modification</th></tr><tr><td>1.0(1)</td><td>This command was introduced.</td></tr></table>		Release	Modification	1.0(1)	This command was introduced.		
Release	Modification							
1.0(1)	This command was introduced.							
Usage Guidelines	Use this command to identify the trustpoints that will be used to validate a certificate during Internet Key Exchange (IKE) authentication, and enter organization trustpoint mode.							
Examples	<div>This example shows how to create a trustpoint:</div> <div>switch-A# scope security switch-A /security # create trustpoint tPoint10 switch-A /security/trustpoint* # commit-buffer switch-A /security/trustpoint # create fcoe-if</div>							
Related Commands	<table><tr><th>Command</th><th>Description</th></tr><tr><td>show keyring</td><td></td></tr><tr><td>show trustpoint</td><td></td></tr></table>		Command	Description	show keyring		show trustpoint	
Command	Description							
show keyring								
show trustpoint								

create uuid-suffix-pool

To create a UUID suffix pool, use the **create uuid-suffix-pool** command.

create uuid-suffix-pool *name*

Syntax Description	<table><tr><td><i>name</i></td><td>UUID suffix pool name. The range of valid values is 1 to 16.</td></tr></table>	<i>name</i>	UUID suffix pool name. The range of valid values is 1 to 16.
<i>name</i>	UUID suffix pool name. The range of valid values is 1 to 16.		
Command Default	None		
Command Modes	Organization (/org)		

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Creates a UUID suffix pool with the specified name, and enters organization UUID suffix pool mode.

Examples

This example shows how to create a UUID suffix pool:

```
switch-A# scope org org3
switch-A /org # create uuid-suffix-pool uuidspl
switch-A /org/uuid-suffix-pool* # commit-buffer
switch-A /org/uuid-suffix-pool #
```

Related Commands

Command	Description
show uuid-suffix-pool	
show wwn-pool	

create vhba

To create a virtual HBA (vHBA), use the **create vhba** command.

create vhba *name* { **fabric** { **a** | **b** } | **fc-if** *fc-if* } *

Syntax Description

<i>name</i>	vHBA name. The range of valid values is 1 to 16.
fabric	Specifies a fabric.
a	Specifies fabric A.
b	Specifies fabric B.
fc-if	Specifies a Fibre Channel interface.
<i>interface-name</i>	Interface name. The range of valid values is 1 to 16.

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a vHBA, and enter organization virtual HBA mode.

Examples

This example shows how to create a vHBA:

```
switch-A# scope org org30
switch-A /org # scope service-profile sp10a
switch-A /org/service-profile # create vhba 10a
switch-A /org/service-profile/vhba* # commit-buffer
switch-A /org/service-profile/vhba #
```

Related Commands

Command	Description
show vhba	
show vnic	

create vhba-templ

To create a vHBA template, use the **create vhba-templ** command.

create vhba-templ *name* { **fabric** { **a** | **b** } | **fc-if** *fci-name* } *

Syntax Description

<i>name</i>	vHBA template name. The range of valid values is 1 to 16.
fabric	Specifies fabric.
a	Specifies fabric A.
b	Specifies fabric B.
fc-if	Specifies a Fibre Channel interface.
<i>fci-name</i>	Fibre Channel interface name. The range of valid values is 1 to 16.

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

A vHBA is a virtualized host bus adapter that is configured on a physical network adapter and appears to be a physical HBA to the operating system of the server. The type of adapter in the system determines how many vHBAs you can create.

Use this command to create a vHBA template, and enter organization virtual HBA template mode.

Examples

This example shows how to create a vHBA template:

```
switch-A# scope org org10
switch-A /org # create vhba-templ vhat10
switch-A /org/vhba-templ* # commit-buffer
switch-A /org/vhba-templ #
```

Related Commands

Command	Description
show fc-if	
show vhba-templ	

create virtual-media

To create virtual media, use the **create virtual-media** command.

create virtual-media { read-only | read-write }

Syntax Description

read-only	Specifies read-only virtual media.
read-write	Specifies read and write virtual media.

Command Default

None

Command Modes

Boot policy (/org/boot-policy)

Boot definition (/org/service-profile/boot-def)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create virtual media with the specified name, and enters organization virtual-media mode.

Examples

This example shows how to create virtual media:

```
switch-A# scope org org3
switch-A /org # scope service-profile sp1
switch-A /org/service-profile # scope boot-def
switch-A /org/service-profile/boot-definition # create virtual-media read-write
switch-A /org/service-profile/boot-definition/virtual-media* # commit-buffer
switch-A /org/service-profile/boot-definition/virtual-media #
```

Related Commands

Command	Description
show storage	
show virtual-media	

create vlan

To create a VLAN, use the **create vlan** command.

create vlan *name id*

Syntax Description

<i>name</i>	VLAN name. The range of valid values is 1 to 16.
<i>id</i>	VLAN identification number. The range of valid values is 1 to 3967 and 4048 to 4093.

Command Default

None

Command Modes

Switch (/eth-uplink/switch)
Ethernet uplink (/eth-uplink)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a VLAN pool with the specified name, and enters organization vlan mode.

Examples

This example shows how to create a VLAN:

```
switch-A# scope eth-uplink
switch-A /eth-uplink # create vlan vlan1 10
switch-A /eth-uplink/vlan* # commit-buffer
switch-A /eth-uplink/vlan #
```

Related Commands

Command	Description
show interface	
show vlan	

create vnic

To create a VNIC (Virtual Network Interface Card), use the **create vnic** command.

create vnic *name* { **fabric** { **a** | **a-b** | **b** | **b-a** } | **eth-if** *eth-if* } *

Syntax Description

<i>name</i>	VNIC template name. The range of valid values is 1 to 16.
fabric	Specifies the fabric switch identification number.
a	Specifies switch A.
a-b	Specifies redundant, with switch A as primary.
b	Specifies switch B.
b-a	Specifies redundant, with switch B as primary.
eth-if	Specifies a Ethernet interface.
<i>eth-if</i>	Ethernet interface name. The range of valid values is 1 to 16.

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a vNIC with the specified name, and enters organization virtual NIC mode.

Examples

This example shows how to create a vNIC:

```
switch-A# scope org org3
switch-A /org # scope service-profile sp1
switch-A /org/service-profile # create vnic vnic110
switch-A /org/service-profile/vnic* # commit-buffer
switch-A /org/service-profile/vnic #
```

Related Commands

Command	Description
show interface	
show vnic	

create vnic-egress-policy

To create a VNIC egress policy, use the **create vnic-egress-policy** command.

create vnic-egress-policy

This command has no arguments or keywords.

Command Default

None

Command Modes

Virtual NIC QoS (/org/vnic-qos)

Command History

Release	Modification
1.0(1)	This command was introduced.

Use this command to create a vNIC egress policy, and enter organization virtual NIC egress policy mode.

Examples

This example shows how to create a vNIC egress policy:

```
switch-A# scope org org3
switch-A /org # scope vnic-qos vnicq1
switch-A /org/vnic-qos # create vnic-egress-policy
switch-A /org/vnic-qos* # commit-buffer
switch-A /org/vnic-qos #
```

Related Commands

Command	Description
show vnic	

Command	Description
show vnic-egress-policy	

create vnic-templ

To create a vNIC template, use the **create vnic-templ** command.

create vnic-templ *name* { **fabric** { **a** | **a-b** | **b** | **b-a** } | **target** { **adapter** | **vm** } + | **eth-if** *eth-if* } *

Syntax Description

<i>name</i>	vNIC template name. The range of valid values is 1 to 16.
fabric	Specifies the fabric switch identification number.
a	Specifies switch A.
a-b	Specifies redundant, with switch A as primary.
b	Specifies switch B.
b-a	Specifies redundant, with switch B as primary.
target	Specifies the target, either adapter or vm.
adapter	Specifies the adapter.
vm	Specifies the virtual machine.
eth-if	Specifies a Ethernet interface.
<i>eth-if</i>	Ethernet interface name. The range of valid values is 1 to 16.

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a vNIC template, and enters organization virtual NIC template mode.

Examples

This example shows how to create a vNIC template:

```
switch-A# scope org org3
switch-A /org # create vnic-templ vnic1 eth-if 10
switch-A /org/vnic-templ* # commit-buffer
switch-A /org/vnic-templ #
```

Related Commands

Command	Description
show eth-if	
show vnic-templ	

create vsan

To create a VSAN, use the **create vsan** command.

create vsan *name id fcoe-vlan*

Syntax Description

<i>name</i>	VSAN name. The range of valid values is 1 to 16.
<i>id</i>	VSAN identification number. The range of valid values is 1 to 4093.
default-2	Specifies default 1.
<i>fcoe-vlan</i>	Fibre Channel over Ethernet VLAN. The range of valid values is 1 to 4093.
default-1	Specifies default 2.

Command Default

None

Command Modes

Fibre Channel uplink (/fc-uplink)
Switch (/fc-uplink/switch)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a VSAN with the specified name, and enters organization VSAN mode.

You can create a named VSAN with IDs from 1 to 4093. VSANs configured on different FCoE VLANs cannot share the same ID.

Examples

This example shows how to create a VSAN:

```
switch-A# scope fc-uplink
switch-A /fc-uplink # create vsan vs2 6 10
switch-A /fc-uplink/vsan* # commit-buffer
switch-A /fc-uplink/vsan #
```

Related Commands

Command	Description
show vif	
show vsan	

create wwn-pool

To create a WWN (World Wide Name) pool, use the **create wwn-pool** command.

create wwn-pool *name* {*node-wwn-assignment*|*port-wwn-assignment*}

Syntax Description

<i>name</i>	WWN pool name. The range of valid values is 1 to 16.
node-wwn-assignment	Specifies world wide node name assignment.
port-wwn-assignment	Specifies world wide node port assignment.

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to create a WWN pool with the specified name, and enters organization WWN pool mode. A WWN pool can include only WWNNs or WWPNNs in the 20:xx range. All other WWN ranges are reserved.

Examples

This example shows how to create a WWN pool:

```
switch-A# scope org org3
switch-A /org # create wwn-pool wwnp1 port-wwn-assignment
switch-A /org/wwn-pool* # commit-buffer
switch-A /org/wwn-pool #
```

Related Commands

Command	Description
show mac-pool	
show wwn-pool	

cycle

To cycle a server, use the **cycle** command.

cycle { **cycle-immediate** | **cycle-wait** }

Syntax Description

cycle-immediate	Specifies cycle immediately.
cycle-wait	Specifies wait to cycle.

Command Default

None

Command Modes

Server (/chassis/server)
Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to cycle a server:

```
switch-A# scope server 2/4
switch-A /chassis/server # cycle cycle-immediate

switch-A /chassis/server* # commit-buffer
switch-A /chassis/server #
```

decommission chassis

To decommission a chassis, use the **decommission chassis** command.

decommission chassis *id*

Syntax Description

<i>id</i>	Chassis identification number.
-----------	--------------------------------

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to decommission a chassis:

```
switch-A# decommission chassis 2
switch-A* # commit-buffer
switch-A #
```

Related Commands

Command	Description
show chassis	
show server	

decommission server

To decommission a server, use the **decommission server** command.

decommission server *chassis-id/blade-id*

Syntax Description

<i>chassis-id/blade-id</i>	Server chassis and blade identification number.
----------------------------	---

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to decommission a server:

```
switch-A# decommission server 1 1
switch-A* # commit-buffer
switch-A #
```

Related Commands

Command	Description
show chassis	
show server	

delete adapter

To delete the adapter, use the **delete adapter** command.

delete adapter

This command has no arguments or keywords.

Command Default

None

Command Modes

Server qualification (/org/server-qual)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete an adapter:

```
switch-A# scope org org3
switch-A /org # scope server-qual squal100
switch-A /org/server-qual # delete adapter
switch-A /org/server-qual* # commit-buffer
switch-A /org/server-qual #
```

Related Commands

Command	Description
show adapter	
show server-qual	

delete backup

To delete backup, use the **delete backup** command.

delete backup *name***Syntax Description**

<i>name</i>	Backup name.
-------------	--------------

Command Default

None

Command Modes

System (/system)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete backup:

```
switch-A# scope system
switch-A /system # delete backup backUpFDrive
switch-A /system* # commit-buffer
switch-A /system #
```

Related Commands

Command	Description
show backup	
show import-config	

delete block

To delete a block, use the **delete block** command.

delete block *from to*

Syntax Description

<i>from</i>	Start UUID.
<i>to</i>	End UUID.

Command Default

None

Command Modes

UUID suffix pool (/org/uuid-suffix-pool)
 IP pool (/org/ip-pool)
 WWN pool (/org/wwn-pool)
 MAC pool (/org/mac-pool)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a block:

```
switch-A# scope org org10
switch-A /org # scope uuid-suffix-pool usp10

switch-A /org/uuid-suffix-pool # delete block 1234-123412341230 1234-123412341234
switch-A /org/uuid-suffix-pool* # commit-buffer
switch-A /org/uuid-suffix-pool #
```

Related Commands

Command	Description
show block	
show pooled	

delete boot-definition

To delete a boot definition, use the **delete boot-definition** command.

delete boot-definition

This command has no arguments or keywords.

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a boot definition:

```
switch-A# scope org org10
switch-A /org # scope service-profile sp10
switch-A /org/service-profile # delete boot-definition bp10
switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show boot-definition	
show boot-policy	

delete boot-policy

To delete a boot policy, use the **delete boot-policy** command.

delete boot-policy *name*

Syntax Description

<i>name</i>	Boot policy name.
-------------	-------------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a boot policy:

```
switch-A# scope org org3
switch-A /org # delete boot-policy bp110
switch-A /org* # commit-buffer
switch-A /org #
```

Related Commands

Command	Description
show boot-policy	
show chassis-disk-policy	

delete certreq

To delete a certificate request, use the **delete certreq** command.

delete certreq

This command has no arguments or keywords.

Command Default

None

Command Modes

Keyring (/security/keyring)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete certificate request:

```
switch-A# scope security
switch-A /security # scope keyring kr10
switch-A /security/keyring # delete certreq
switch-A /security/keyring* # commit-buffer
switch-A /security/keyring #
```

Related Commands

Command	Description
show certreq	
showkeyring	

delete chassis

To delete a chassis, use the **delete chassis** command.

delete chassis *min-id max-id*

Syntax Description

<i>min-id</i>	Minimum chassis identification number. The range of valid values is 1 to 8.
<i>max-id</i>	Minimum chassis identification number. The range of valid values is 1 to 8.

Command Default

None

Command Modes

Server qualification (/org/server-qual)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a chassis:

```
switch-A# scope org org10
switch-A /org # scope server-qual sq10
switch-A /org/server-qual # delete chassis 1 1
switch-A /org/server-qual* # commit-buffer
switch-A /org/server-qual #
```

Related Commands

Command	Description
show chassis	
show server-qual	

delete class chassis-stats

To delete the chassis statistics class, use the **delete class chassis-stats** command.

delete class chassis-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete the chassis statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy stp10

switch-A /eth-server/stats-threshold-policy # delete class chassis-stats
switch-A /eth-server/stats-threshold-policy* # commit-buffer
switch-A /eth-server/stats-threshold-policy #
```

Related Commands

Command	Description
show chassis	
show stats-threshold-policy	

delete class cpu-stats

To delete the CPU statistics class, use the **delete class cpu-stats** command.

delete class cpu-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

The following example shows how to delete the CPU statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy stp10

switch-A /eth-server/stats-threshold-policy # delete class cpu-stats
switch-A /eth-server/stats-threshold-policy* # commit-buffer
switch-A /eth-server/stats-threshold-policy #
```

Related Commands

Command	Description
show chassis	
show class	

delete class dimm-stats

To delete the DIMM statistics class, use the **delete class dimm-stats** command.

delete class dimm-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete the DIMM statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy stp10

switch-A /eth-server/stats-threshold-policy # delete class dimm-stats
switch-A /eth-server/stats-threshold-policy* # commit-buffer
switch-A /eth-server/stats-threshold-policy #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

delete class ether-error-stats

To delete the Ethernet error statistics class, use the **delete class ether-error-stats** command.

delete class ether-error-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy under Ethernet server (/eth-server/stats-threshold-policy)
 Statistics threshold policy under Ethernet uplink /eth-uplink/stats-threshold-policy

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete the Ethernet error statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy stp10

switch-A /eth-server/stats-threshold-policy # delete class ether-error-stats
switch-A /eth-server/stats-threshold-policy* # commit-buffer
switch-A /eth-server/stats-threshold-policy #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

delete class ether-if-stats

To delete the Ethernet interface statistics class, use the **delete class ether-if-stats** command.

delete class ether-if-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy (/org/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete the Ethernet interface statistics class:

```
switch-A#scope org org3
switch-A /org # scope stats-threshold-policy stp20
switch-A /org/stats-threshold-policy # delete class ether-if-stats
switch-A /org/stats-threshold-policy* # commit-buffer
switch-A /org/stats-threshold-policy #
```

Related Commands

Command	Description
show class	
show ether-if-stats	

delete class ether-loss-stats

To delete the Ethernet loss statistics class, use the **delete class ether-loss-stats** command.

delete class ether-loss-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy under Ethernet uplink (/eth-uplink/stats-threshold-policy)
 Statistics threshold policy under Ethernet server (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete the Ethernet loss statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy stp10

switch-A /eth-server/stats-threshold-policy # delete class ether-loss-stats
switch-A /eth-server/stats-threshold-policy* # commit-buffer
switch-A /eth-server/stats-threshold-policy #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

delete class ether-rx-stats

To delete the Ethernet receive statistics class, use the **delete class ether-rx-stats** command.

delete class ether-rx-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy under Ethernet uplink (/eth-uplink/stats-threshold-policy)
 Statistics threshold policy under Ethernet server (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete the Ethernet receive statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy stp10

switch-A /eth-server/stats-threshold-policy # delete class ether-rx-stats
switch-A /eth-server/stats-threshold-policy* # commit-buffer
switch-A /eth-server/stats-threshold-policy #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

delete class ether-tx-stats

To delete the Ethernet transmit statistics class, use the **delete class ether-tx-stats** command.

delete class ether-tx-stats

This command has no arguments or keywords.

Command Default

None

Command Modes

Statistics threshold policy under Ethernet uplink (/eth-uplink/stats-threshold-policy)

Statistics threshold policy under Ethernet server (/eth-server/stats-threshold-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete the Ethernet transmit statistics class:

```
switch-A# scope eth-server
switch-A /eth-server # scope stats-threshold-policy stp10

switch-A /eth-server/stats-threshold-policy # delete class ether-tx-stats
switch-A /eth-server/stats-threshold-policy* # commit-buffer
switch-A /eth-server/stats-threshold-policy #
```

Related Commands

Command	Description
show class	
show stats-threshold-policy	

delete destination

To delete the destination, use the **delete destination** command.

delete destination *email*

Syntax Description

<i>email</i>	Email destination.
--------------	--------------------

Command Default

None

Command Modes

Profile (/monitoring/callhome/profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete the destination:

```
switch-A# scope monitoring
switch-A /monitoring # scope callhome
switch-A /monitoring/callhome # scope profile pro10
switch-A /monitoring/callhome/profile # delete destination test@csx.com
switch-A /monitoring/callhome/profile* # commit-buffer
switch-A /monitoring/callhome/profile #
```

Related Commands

Command	Description
show destination	
show profile	

delete dns

To delete DNS service, use the **delete dns** command.

delete dns *name*

Syntax Description

<i>name</i>	DNS service name.
-------------	-------------------

Command Default

None

Command Modes Services (/system/services)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples This example shows how to delete DNS service:

```
switch-A# scope system
switch-A /system # scope services
switch-A /system/services # delete dns dns100
switch-A /system/services* # commit-buffer
switch-A /system/services #
```

Related Commands	Command	Description
	show dns	
	show ntp	

delete dynamic-vnic-conn-policy

To delete a dynamic vNIC connection policy, use the **delete dynamic-conn-policy** command.

delete dynamic-conn-policy *name*

Syntax Description	<i>name</i>	vNIC connection policy name.

Command Default None

Command Modes Organization (/org)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples This example shows how to delete a dynamic vNIC connection policy:

```
switch-A# scope org org10
switch-A /org # delete dynamic-vnic-conn-policy dvcp10
switch-A /org* # commit-buffer
switch-A /org #
```

Related Commands

Command	Description
show dynamic-vnic-conn-policy	
show stats-threshold-policy	

delete epuser

To delete an end-point user, use the **delete epuser** command.

delete epuser *name*

Syntax Description

<i>name</i>	End-point user name.
-------------	----------------------

Command Default

None

Command Modes

IPMI access profile (/org/ipmi-access-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete an end-point user:

```
switch-A# scope org org10
switch-A /org # scope ipmi-access-profile ipmiAP10

switch-A /org/ipmi-access-profile # delete epuser epuser10
switch-A /org/ipmi-access-profile* # commit-buffer
switch-A /org/ipmi-access-profile #
```

Related Commands

Command	Description
show epuser	
show ipmi-access-profile	

delete eth-if

To delete an Ethernet interface, use the **delete eth-if** command.

delete eth-if *name*

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This following example shows how to delete an Ethernet profile:

```
switch-A# scope org org10
switch-A /org # delete eth-profile ep10
switch-A /org* # commit-buffer
switch-A /org #
```

Related Commands

Command	Description
show eth-profile	
show service-profile	

delete fc-profile

To delete a Fibre Channel profile, use the **delete fc-profile** command.

delete fc-profile *name*

Syntax Description

<i>name</i>	Fibre Channel profile name.
-------------	-----------------------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a Fibre Channel profile:

```
switch-A# scope org org10
switch-A /org # delete fc-profile fcp10
switch-A /org* # commit-buffer
switch-A /org #
```

Related Commands

Command	Description
show eth-profile	
show fc-profile	

delete image

To delete an image, use the **delete image** command.

delete image *{name}* | { **type** { **adapter** | **server-bios** | **bmc** | **host-hba** | **host-hba-combined** | **host-hba-optionrom** | **host-nic** | **iom** | **raid-controller** | **switch-kernel** | **switch-software** | **system** | **unspecified** } | **version** *version* } +

Syntax Description

<i>name</i>	Image name.
type	Specifies image type.
adapter	Specifies an adapter image.
server-bios	Specifies the server BIOS image.
bmc	Specifies the BMC image.
host-hba	Specifies the host HBA image.
host-hba-combined	Specify the combined host HBA image.
host-hba-optionrom	Specifies the host optional ROM image.
host-nic	Specifies the host NIC image.
iom	Specifies the I/O module image.
raid-controller	Specifies the RAID controller image.
switch-kernel	Specifies the switch kernel image.
switch-software	Specifies the switch software image.
system	Specifies the system image.
unspecified	Specifies an unspecified image.

delete import-config

version	Specifies the version number.
<i>version</i>	Version number.

Command Default None

Command Modes Firmware (/firmware)

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete an image:

```
switch-A# scope firmware
switch-A /firmware # delete image serverImage10

switch-A /firmware* # commit-buffer
switch-A /firmware #
```

Related Commands	Command	Description
	show image	
	show package	

delete import-config

To delete an import configuration, use the **delete import-config** command.

delete import-config *name*

Syntax Description	<i>name</i>	Import configuration name.
---------------------------	-------------	----------------------------

Command Default None

Command Modes System (/system)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples

This example shows how to delete an import configuration:

```
switch-A# scope system
switch-A /system # delete import-config ic10
switch-A /system* # commit-buffer
switch-A /system #
```

Related Commands

Command	Description
show import-config	
show managed-entity	

delete initiator

To delete an initiator, use the **delete initiator** command.

delete initiator *id*

Syntax Description

<i>id</i>	Initiator identification number.
-----------	----------------------------------

Command Default

None

Command Modes

WWN pool (/org/wwn-pool)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete an initiator:

```
switch-A# scope org org10
switch-A /org # scope wwn-pool wwnp10
switch-A /org/wwn-pool # delete initiator init10

switch-A /org/wwn-pool* # commit-buffer
switch-A /org/wwn-pool #
```

Related Commands

Command	Description
show initiator	
show wwn-pool	

delete interface

To delete an interface, use the **delete interface** command.

delete interface *slot-id* *port-id*

Syntax Description

<i>slot-id</i>	Slot identification number.
<i>port-id</i>	Port identification number.

Command Default

None

Command Modes

Switch under Ethernet uplink (/eth-uplink/switch)
 Switch under Ethernet server (/eth-server/switch)
 Switch under Fibre Channel uplink (/fc-uplink/switch)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete an interface:

```
switch-A#scope eth-uplink
switch-A /eth-uplink # scope fabric b
switch-A /eth-uplink/fabric # delete interface 1 3
switch-A /eth-uplink/fabric* # commit-buffer
switch /eth-uplink/fabric #
```

Related Commands

Command	Description
show interface	
show vlan	

delete ipmi-access-profile

To delete an IPMI access profile, use the **delete ipmi-access-profile** command.

delete ipmi-access-profile *name*

Syntax Description	<i>name</i> IPMI access profile name.
--------------------	---------------------------------------

Command Default	None
-----------------	------

Command Modes	Organization (/org)
---------------	---------------------

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples

This example shows how to delete an IPMI access profile:

```
switch-A# scope org org300
switch-A /org # delete ipmi-access-profile ipmiap100
switch-A /org* # commit-buffer
switch-A /org #
```

Related Commands	Command	Description
	show service-profile	
	show ipmi-access-profile	

delete keyring

To delete a keyring, use the **delete keyring** command.

delete keyring *name*

Syntax Description	<i>name</i> Keyring name.
--------------------	---------------------------

Command Default	None
-----------------	------

Command Modes

Security (/security)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a keyring:

```
switch-A# scope security
switch-A /security # delete keyring kr10

switch-A /security* # commit-buffer
switch-A /security #
```

Related Commands

Command	Description
show keyring	
show trustpoint	

delete lan

To delete the LAN, use the **delete lan** command.

delete lan

Command Default

None

Command Modes

Boot policy (/org/boot-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete the LAN:

```
switch-A# scope org org10
switch-A /org # scope boot-policy bp10
switch-A /org/boot-policy # delete lan

switch-A /org/boot-policy* # commit-buffer
switch-A /org/boot-policy #
```

Related Commands

Command	Description
show boot-policy	
show lan	

delete local

To delete the local storage, use the **delete local** command.

delete local

This command has no arguments or keywords.

Command Default

None

Command Modes

Storage (/org/boot-policy/storage)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete the local storage:

```
switch-A# scope org org10
switch-A /org # scope boot-policy bp10
switch-A /org/boot-policy # scope storage
switch-A /org/boot-policy/storage # delete local

switch-A /org/boot-policy/storage* # commit-buffer
switch-A /org/boot-policy/storage #
```

Related Commands

Command	Description
show local	
show storage	

delete locale

To delete a locale, use the **delete locale** command.

delete locale *name*

Syntax Description	<i>name</i>	
--------------------	-------------	--

delete local-disk-config

To delete the local disk configuration, use the **delete local-disk-config** command.

delete local-disk-config

This command has no arguments or keywords.

Command Default	None					
Command Modes	Service profile (/org/service-profile)					
Command History	<table><tr><th>Release</th><th>Modification</th></tr><tr><td>1.0(1)</td><td>This command was introduced.</td></tr></table>		Release	Modification	1.0(1)	This command was introduced.
Release	Modification					
1.0(1)	This command was introduced.					

Examples

This example shows how to delete the local disk configuration:

```
switch-A# scope org org10
switch-A /org # scope service-profile sp10
switch-A /org/service-profile # delete local-disk-config

switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show local-disk-config	
show local-disk-config-policy	

delete local-user

To delete a local user, use the **delete local-user** command.

delete local-user *name*

Syntax Description

<i>name</i>	Local user name.
-------------	------------------

Command Default

None

Command Modes

Security (/security)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to delete a user account.

Examples

This example shows how to delete a local user:

```
switch-B# scope security
switch-B /security # delete local-user lu1
switch-B /security* # commit-buffer
switch-B /security #
```

Related Commands

Command	Description
show local-user	
show remote-user	

delete mac-pool

To delete a MAC pool, use the **delete mac-pool** command.

delete mac-pool *name*

Syntax Description

<i>name</i>	MAC pool name.
-------------	----------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a MAC pool:

```
switch-A# scope org org10
switch-A /org # delete mac-pool mp10

switch-A /org* # commit-buffer
switch-A /org #
```

Related Commands

Command	Description
show mac-pool	
show server-pool	

delete mac-security

To delete MAC security, use the **delete mac-security** command.

delete mac-security

This command has no arguments or keywords.

Command Default

None

Command Modes

Port profile (/eth-uplink/port-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to delete the MAC security policy.

Examples

This example shows how to delete MAC security:

```
switch-A# scope eth-uplink
switch-A /eth-uplink # scope port-profile pp10
switch-A /eth-uplink/port-profile # delete mac-security

switch-A /eth-uplink/port-profile* # commit-buffer
switch-A /eth-uplink/port-profile #
```

Related Commands

Command	Description
show mac-security	
show port-profile	

delete member-port

To delete a member port, use the **delete member-port** command.

port channel configuration

delete member-port *slot-id port-id*

vsan configuration

delete member-port { **a** | **b** } *slot-id port-id*

Syntax Description

a	Specifies switch A.
b	Specifies switch B.
<i>slot-id</i>	Slot identification number. The range of valid values is 2 to 5.

delete memory

<i>port-id</i>	Port identification number. The range of valid values is 1 to 40.
----------------	---

Command Default

None

Command Modes

Port channel (/eth-uplink/switch/port-channel)
 VSAN (/fc-uplink/switch/vsan)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a member port:

```
switch-A#scope fc-uplink
switch-A /fc-uplink # scope fabric a
switch-A /fc-uplink/fabric # scope vsan vs1
switch-A /fc-uplink/fabric/vsan # delete member-port a 3 3
switch-A /fc-uplink/fabric/vsan* # commit-buffer
switch-A /fc-uplink/fabric/vsan #
```

Related Commands

Command	Description
show fc-uplink	
show port-channel	

delete memory

To delete memory, use the **delete memory** command.

delete memory

This command has no arguments or keywords.

Command Default

None

Command Modes

Server qualification (/org/server-qual)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete memory:

```
switch-A# scope org org99
switch-A /org # scope server-qual sq100
switch-A /org/server-qual # delete memory
switch-A /org/server-qual* # commit-buffer
switch-A /org/server-qual #
```

Related Commands

Command	Description
show memory	
show server-qual	

delete org-ref

To delete an organization reference, use the **delete org-ref** command.

delete org-ref *name*

Syntax Description

<i>name</i>	Organization reference name.
-------------	------------------------------

Command Default

None

Command Modes

Locale (/security/locale)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete an organization reference:

```
switch-A#scope security
switch-A /security # scope locale
switch-A /security/locale # delete org-ref marketing
switch-A /security/locale* # commit-buffer
switch-A /security/locale #
```

Related Commands

Command	Description
show locale	
show org	

delete path

To delete the path, use the **delete path** command.

delete path { **primary** | **secondary** }

Syntax Description

primary	Specifies the primary path.
secondary	Specifies the secondary path.

Command Default

None

Command Modes

SAN image (/org/boot-policy/storage/san-image)
 LAN (/org/boot-policy/lan)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete the path:

```
switch-A# scope org org3
switch-A /org # scope boot-policy bp10
switch-A /org/boot-policy/lan # delete path primary
switch-A /org/boot-policy/lan* # commit-buffer
switch-A /org/boot-policy/lan #
```

Related Commands

Command	Description
show lan	
show storage	

delete pin-group

To delete the pin group, use the **delete pin-group** command.

delete pin-group *name*

Syntax Description

<i>name</i>	Pin group name.
-------------	-----------------

Command Default

None

Command Modes

Fibre Channel uplink (/fc-uplink)
 Ethernet uplink (/eth-uplink)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete the pin group:

```
switch-A# scope eth-uplink
switch-A /eth-uplink # delete pin-group pg10
switch-A /eth-uplink* # commit-buffer
switch-A /eth-uplink #
```

Related Commands

Command	Description
show pin-group	
show port-profile	

delete policy

To delete a policy, use the **delete policy** command.

callhome mode

```
delete policy { equipment-degraded | equipment-inoperable | fru-problem | identity-unestablishable |
thermal-problem | voltage-problem }
```

flow control mode

```
delete policy name
```

Syntax Description

equipment-degraded	Specifies an equipment degraded policy.
equipment-inoperable	Specifies an equipment inoperable policy.
fru-problem	Specifies a field replaceable unit policy.
identity-unestablishable	Specifies an identity unestablishable policy.
power-problem	Specifies a power problem policy.

thermal-problem	Specifies a thermal problem policy.
voltage-problem	Specifies a voltage problem policy.
<i>name</i>	Policy name.

Command Default None

Command Modes Callhome (/monitoring/callhome)
Flow control (/eth-uplink/flow-control)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples

This example shows how to delete a policy:

```
switch-A# scope eth-uplink
switch-A /eth-uplink # scope flow-control

switch-A /eth-uplink/flow-control # delete policy policy1
switch-A /eth-uplink/flow-control* # commit-buffer
switch-A /eth-uplink/flow-control #
```

Related Commands	Command	Description
	show policy	
	show stats-threshold-policy	

delete pooling-policy

To delete a pooling policy, use the **delete pooling-policy** command.

delete pooling-policy *name*

Syntax Description	<i>name</i>
	Pooling policy name.

Command Default None

Command Modes Organization (/org)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples

This example shows how to delete a pooling policy:

```
switch-A# scope org org3
switch-A /org # delete pooling-policy pp110
switch-A /org/pooling-policy* # commit-buffer
switch-A /org/pooling-policy #
```

Related Commands

Command	Description
show mac-pool	
show pooling-policy	

delete port-channel

To delete a port channel, use the **delete port-channel** command.

delete port-channel *port-id*

Syntax Description

<i>port-id</i>	Port identification number.
----------------	-----------------------------

Command Default

None

Command Modes

Fabric interconnect (/eth-uplink/fabric)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a port channel:

```
switch-A#scope eth-uplink
switch-A /eth-uplink # scope fabric b
switch-A /eth-uplink/fabric # delete port-channel 10
switch-A /eth-uplink/fabric* # commit-buffer
switch-A /eth-uplink/fabric #
```

Related Commands

Command	Description
show fabric	
show port-channel	

delete processor

To delete a processor, use the **delete processor** command.

delete processor

This command has no arguments or keywords.

Command Default

None

Command Modes

Server qualification (/org/server-qual)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a processor:

```
switch-A# scope org org3
switch-A /org # scope server-qual squal10
switch-A /org/server-qual # delete processor
switch-A /org/server-qual* # commit-buffer
switch-A /org/server-qual #
```

Related Commands

Command	Description
show memory	
show processor	

delete qos-policy

To delete a QoS policy, use the **delete qos-policy** command.

delete qos-policy *name*

Syntax Description

<i>name</i>	QoS policy name.
-------------	------------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a QoS policy:

```
switch-A# scope org org3
switch-A /org # delete qp1
switch-A /org* # commit-buffer
switch-A /org #
```

Related Commands

Command	Description
show qos-policy	
show vnic-egress-policy	

delete role

To delete a role, use the **delete role** command.

delete role *name*

Syntax Description

<i>name</i>	Role name.
-------------	------------

Command Default

None

Command Modes

Local user (/security/local-user)
Security (/security)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a role:

```
switch-A#scope security
switch-A /security # scope local-user appsUser
switch-A /security/local-user # delete role appsUser
switch-A /security/local-user* # commit-buffer
switch-A /security/local-user #
```

Related Commands

Command	Description
show local-user	
show role	

delete scrub-policy

To delete a scrub policy, use the **delete scrub-policy** command.

delete scrub-policy *name*

Syntax Description

<i>name</i>	Scrub policy name.
-------------	--------------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a scrub policy:

```
switch-A# scope org org10
switch-A /org # delete scrub-policy scrub101
switch-A /org* # commit-buffer
switch-A /org #
```

Related Commands

Command	Description
show qos-policy	
show scrub-policy	

delete server

To delete a server, use the **delete server** command.

delete server *chassis-id blade-id*

Syntax Description

<i>chassis-id</i>	Server identification number.
<i>blade-id</i>	Server identification number.

Command Default

None

Command Modes

Server pool (/org/server-pool)
RADIUS (/security/radius)
TACACS (/security/tacacs)
LDAP (/security/ldap)
VMware management (/system/vm-mgmt)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a server:

```
switch-A# scope org org10
switch-A /org # scope server-pool spGroup10

switch-A /org/server-pool # delete server 1 1
switch-A /org/server-pool* # commit-buffer
switch-A /org/server-pool #
```

Related Commands

Command	Description
show server	
show server-pool	

delete server-disc-policy

To delete a server discovery policy, use the **delete server-disc-policy** command.

delete server-disc-policy *name*

Syntax Description

<i>name</i>	Server discovery policy name.
-------------	-------------------------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a server discovery policy:

```
switch-A# scope org org100
switch-A /org # delete server-disc-policy sdp100
switch-A /org* # commit-buffer
switch-A /org #
```

Related Commands

Command	Description
show chassis-disc-policy	
show server-disc-policy	

delete server-pool

To delete a server pool, use the **delete server-pool** command.

delete server-pool *name*

Syntax Description

<i>name</i>	Server pool name.
-------------	-------------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a server pool:

```
switch-A# scope org org100
switch-A /org # delete server-pool serverpool101
switch-A /org* # commit-buffer
switch-A /org #
```

Related Commands

Command	Description
show mac-pool	
show server-pool	

delete server-qual

To delete a server qualifier, use the **delete server-qual** command.

delete server-qual *name*

Syntax Description

<i>name</i>	Server qualifier name.
-------------	------------------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a server qualifier:

```
switch-A#scope org org3
switch-A /org # delete server-qual sql10
switch-A /org/server-qual* # commit-buffer
switch-A /org/server-qual #
```

Related Commands

Command	Description
show server-pool	
show server-qual	

delete storage

To delete storage, use the **delete storage** command.

delete storage

Command Default

None

Command Modes

Server qualification (/org/server-qual)
Boot policy (/org/boot-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete storage:

```
switch-A# scope org org200
switch-A /org # scope server-qual sQual220
switch-A /org/server-qual # delete storage
switch-A /org/server-qual* # commit-buffer
switch-A /org/server-qual #
```

Related Commands

Command	Description
show memory	
show storage	

delete target

To delete a target, use the **delete target** command.

delete target { a | b | dual }

Syntax Description

a	Specifies switch A.
b	Specifies switch B.
dual	Specifies

Command Default

None

Command Modes	Pin group under Fibre Channel uplink (/fc-uplink/pin-group)
	Pin group under Ethernet uplink (/eth-uplink/pin-group)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples	This example shows how to delete a target:
	<pre>switch-A# scope fc-uplink switch-A /fc-uplink # scope pin-group pGroup10 switch-A /fc-uplink/pin-group # delete target a switch-A /fc-uplink/pin-group* # commit-buffer switch-A /fc-uplink/pin-group #</pre>

Related Commands	Command	Description
	show pin-group	
	show target	

delete trustpoint

To delete a trustpoint, use the **delete trustpoint** command.

delete trustpoint *name*

Syntax Description	<i>name</i>	Trustpoint name.

Command Default	None
------------------------	------

Command Modes	Security (/security)
----------------------	----------------------

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples	This example shows how to delete a trustpoint:
	<pre>switch# scope security switch /security # delete trustpoint tp10</pre>

```
switch /security* # commit-buffer
switch /security #
```

Related Commands

Command	Description
show authentication	
show trustpoint	

delete uuid-suffix-pool

To delete a UUID suffix pool, use the **delete uuid-suffix-pool** command.

delete uuid-suffix-pool *name*

Syntax Description

<i>name</i>	UUID suffix pool name.
-------------	------------------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a UUID suffix pool:

```
switch-A# scope org org100
switch-A /org # delete uuid-suffix-pool pool101
switch-A /org* # commit-buffer
switch-A /org #
```

Related Commands

Command	Description
show mac-pool	
show uuid-suffix-pool	

delete vhba

To delete a virtual HBA, use the **delete vhba** command.

delete vhba *name*

Syntax Description	<table><tr><td><i>name</i></td><td>Virtual HBA name.</td></tr></table>	<i>name</i>	Virtual HBA name.				
<i>name</i>	Virtual HBA name.						
Command Default	None						
Command Modes	Service profile (/org/service-profile)						
Command History	<table><tr><th>Release</th><th>Modification</th></tr><tr><td>1.0(1)</td><td>This command was introduced.</td></tr></table>	Release	Modification	1.0(1)	This command was introduced.		
Release	Modification						
1.0(1)	This command was introduced.						
Examples	<p>This example shows how to delete a virtual HBA:</p> <pre>switch-A# scope org org10 switch-A /org # scope service-profile sp10 switch-A /org/service-profile # delete vhba vHBA10 switch-A /org/service-profile* # commit-buffer switch-A /org/service-profile #</pre>						
Related Commands	<table><tr><th>Command</th><th>Description</th></tr><tr><td>show vhba</td><td></td></tr><tr><td>show vnic</td><td></td></tr></table>	Command	Description	show vhba		show vnic	
Command	Description						
show vhba							
show vnic							

delete vlan

To delete a VLAN, use the **delete vlan** command.

delete vlan *name*

Syntax Description	<table><tr><td><i>name</i></td><td>VLAN name.</td></tr></table>	<i>name</i>	VLAN name.
<i>name</i>	VLAN name.		
Command Default	None		
Command Modes	Ethernet uplink (/eth-uplink)		

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a VLAN:

```
switch-A# scope eth-uplink
switch-A /eth-uplink # delete vlan vlan1
switch-A /eth-uplink* # commit-buffer
switch-A /eth-uplink #
```

Related Commands

Command	Description
show interface	
show vlan	

delete vnic

To delete a virtual NIC, use the **delete vnic** command.

delete vnic *name*

Syntax Description

<i>name</i>	Virtual NIC name.
-------------	-------------------

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a virtual NIC:

```
switch-A# scope org org10
switch-A /org # scope service-profile sp10
switch-A /org/service-profile # delete vnic vNIC10
switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```


Related Commands

Command	Description
show vhba	
show vnic	

delete vnic-templ

To delete a virtual NIC template, use the **delete vnic-templ** command.

delete vnic-templ *name*

Syntax Description

<i>name</i>	Virtual NIC template name.
-------------	----------------------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a virtual NIC template:

```
switch-A# scope org org10
switch-A /org # delete vnic-templ vnicT10
switch-A /org* # commit-buffer
switch-A /org/wnn-pool #
```

Related Commands

Command	Description
show vhba-templ	
show vnic-templ	

delete vsan

To delete a VSAN, use the **delete vsan** command.

delete vsan *name*

Syntax Description

<i>name</i>	VSAN name.
-------------	------------

Command Default

None

Command Modes

Fibre Channel uplink (/fc-uplink)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a VSAN:

```
switch-A# scope fc-uplink
switch-A /fc-uplink # delete vsan vs110
switch-A /fc-uplink* # commit-buffer
switch-A /fc-uplink #
```

Related Commands

Command	Description
show pin-group	
show vsan	

delete wwn-pool

To delete a WWN pool, use the **delete wwn-pool** command.

delete wwn-pool *name*

Syntax Description

<i>name</i>	WWN pool name.
-------------	----------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to delete a WWN pool:

```
switch-A# scope org org10
switch-A /org # delete wwn-pool wwnP10
switch-A /org* # commit-buffer
switch-A /org/wwn-pool #
```

Related Commands

Command	Description
show org	
show wwn-pool	

disable cimxml

To disable CIM XML services, use the **disable cimxml** command.

disable cimxml

This command has no arguments or keywords.

Command Default

CIM XML services are enabled.

Command Modes

Services (/system/services)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to disable CIM XML services:

```
switch-A#scope system
switch-A /system # scope services
switch-A /system/services # disable cimxml
switch-A /system/services* # commit-buffer
switch-A /system/services #
```

Related Commands

Command	Description
show cimxml	
show dns	

disable http

To disable HTTP services, use the **disable http** command.

disable http

This command has no arguments or keywords.

Command Default

HTTP services are enabled.

Command Modes

Services (/system/services)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to disable HTTP services:

```
switch-A#scope system
switch-A /system # scope services
switch-A /system/services # disable http
switch-A /system/services* # commit-buffer
switch-A /system/services #
```

Related Commands

Command	Description
show http	
show https	

disable https

To disable HTTPS services, use the **disable https** command.

disable https

This command has no arguments or keywords.

Command Default

HTTPS services are enabled.

Command Modes

Services (/system/services)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to disable HTTPS services:

```
switch-A#scope system
switch-A /system # scope services
switch-A /system/services # disable https
switch-A /system/services* # commit-buffer
switch-A /system/services #
```

Related Commands

Command	Description
show https	
show ntp	

disable snmp

To disable SNMP services, use the **disable snmp** command.

disable snmp

This command has no arguments or keywords.

Command Default

SNMP services are enabled.

Command Modes

Monitoring (/monitoring)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to disable SNMP services:

```
switch-A#scope monitoring
switch-A /monitoring # disable snmp
switch-A /monitoring* # commit-buffer
switch-A /monitoring #
```

Related Commands

Command	Description
show snmp-trap	

Command	Description
show stats-collection-policy	

disable telnet-server

To disable TELNET server services, use the **disable telnet-server** command.

disable telnet-server

This command has no arguments or keywords.

Command Default TELNET server services are enabled.

Command Modes Services (/system/services)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples This example shows how to disable TELNET server services:

```
switch-A#scope system
switch-A /system # scope services
switch-A /system/services # disable telnet-server
switch-A /system/services* # commit-buffer
switch-A /system/services #
```

Related Commands	Command	Description
	show ssh-server	
	show telnet-server	

disassociate

To disassociate servers, use the **disassociate** command.

disassociate

This command has no arguments or keywords.

Command Default None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to disassociate servers:

```
switch-A# scope org org10
switch-A /org # scope service-profile sp10
switch-A /org/service-profile # disassociate
switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show server	
show service-profile	

download image

To download an image, use the **download image** command.

download image {ftp:| scp:| sftp:| tftp:}

Syntax Description

ftp:	Specifies FTP.
scp:	Specifies SCP.
sftp:	Specifies SFTP.
tftp:	Specifies TFTP.

Command Default

None

Command Modes

Firmware (/firmware)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to download an image:

```
switch-A# scope firmware
switch-A /firmware # download image
scp://user1@192.168.10.10/images/ucs-k9-bundle.1.0.0.988.gbin

switch-A /firmware* # commit-buffer
switch-A /firmware #
```

Related Commands

Command	Description
show image	
show package	

enable cimxml

To CIM (Common Information Model) XML services, use the **enable cimxml** command.

enable cimxml

This command has no arguments or keywords.

Command Default

CIM XML services are disabled.

Command Modes

Services (/system/services)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Cisco recommends that you enable only the communication services that are required to interface with other network applications.

Examples

This example shows how to enable CIM XML services:

```
switch-A#scope system
switch-A /system # scope services
switch-A /system/services # enable cimxml
switch-A /system/services* # commit-buffer
switch-A /system/services #
```

Related Commands

Command	Description
show cimxml	

Command	Description
show dns	

enable core-export-target

To enable a core export target, use the **enable core-export-target** command.

enable core-export-target

Command Default Core export target services are disabled.

Command Modes System debug (/monitoring/sysdebug)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples

This example shows how to enable a core export target:

```
switch-A# scope monitoring
switch-A /monitoring # scope sysdebug
switch-A /monitoring/sysdebug # enable core-export-target
switch-A /monitoring/sysdebug* # commit-buffer
switch-A /monitoring/sysdebug #
```

Related Commands	Command	Description
	show cores	
	show core-export-target	

enable http

To enable HTTP services, use the **enable http** command.

enable http

This command has no arguments or keywords.

Command Default HTTP services are disabled.

Command Modes Services (/system/services)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Cisco recommends that you enable only the communication services that are required to interface with other network applications.

Examples

This example shows how to enable HTTP services:

```
switch-A#scope system
switch-A /system # scope services
switch-A /system/services # enable http
switch-A /system/services* # commit-buffer
switch-A /system/services #
```

Related Commands

Command	Description
show cimxml	
show http	

enable https

To enable HTTPS services, use the **enable https** command.

enable https

This command has no arguments or keywords.

Command Default

HTTPS services are disabled.

Command Modes

Services (/system/services)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Cisco recommends that you enable only the communication services that are required to interface with other network applications.

Examples

This example shows how to enable HTTPS services:

```
switch-A#scope system
switch-A /system # scope services
switch-A /system/services # enable https
switch-A /system/services* # commit-buffer
switch-A /system/services #
```

Related Commands

Command	Description
show cimxml	
show https	

enable snmp

To enable SNMP services, use the **enable snmp** command.

enable snmp

This command has no arguments or keywords.

Command Default

SNMP services are disabled.

Command Modes

Monitoring (/monitoring)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Cisco recommends that you enable only the communication services that are required to interface with other network applications.

Examples

This example shows how to enable SNMP services:

```
switch-A#scope monitoring
switch-A /monitoring # enable snmp
switch-A /monitoring* # commit-buffer
switch-A /monitoring #
```

Related Commands

Command	Description
show cimxml	
show snmp-trap	

enable telnet-server

To enable TELNET server services, use the **enable telnet-server** command.

enable telnet-server

This command has no arguments or keywords.

Command Default

TELNET server services are disabled.

Command Modes

Services (/system/services)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Cisco recommends that you enable only the communication services that are required to interface with other network applications.

Examples

This example shows how to enable TELNET server services:

```
switch-A#scope system
switch-A /system # scope services
switch-A /system/services # enable telnet-server
switch-A /system/services* # commit-buffer
switch-A /system/services #
```

Related Commands

Command	Description
show ssh-server	
show telnet-server	

enter adapter

To enter the adapter, use the **enter adapter** command.

enter adapter

This command has no arguments or keywords.

Command Default

None

Command Modes Server qualification (/org/server-qual)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Usage Guidelines Use this command to enter adapter capacity qualification. In this qualification, you can create and delete capacity qualifications. Use the **exit** command to exit adapter.

If you are entering an adapter for the first time, once you have entered you will need to execute the **commit-buffer** command.

Examples This example shows how to enter the adapter:

```
switch-A# scope org org10
switch-A /org # scope server-qual sq10
switch-A /org/server-qual # enter adapter
switch-A /org/server-qual/adapter* # commit-buffer
switch-A /org/server-qual/adapter #
```

Related Commands	Command	Description
	show adapter	
	show cap-qual	

enter chassis

To enter a chassis, use the **enter chassis** command.

enter chassis *min-chassis-id max-chassis-id*

Syntax Description	<i>min-chassis-id</i>	Minimum chassis identification number. The range of valid values is 1 to 255.
	<i>max-chassis-id</i>	Maximum chassis identification number. The range of valid values is 1 to 255.

Command Default None

Command Modes Server qualification (/org/server-qual)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to enter slot capacity qualification. In this qualification, you can create and delete capacity qualifications. Use the **exit** command to exit the chassis.

If you are entering a chassis for the first time, once you have entered you will need to execute the **commit-buffer** command.

Examples

This example shows how to enter a chassis:

```
switch-A# scope org org10
switch-A /org # scope server-qual sq10
switch-A /org/server-qual # enter chassis 1 1
switch-A /org/server-qual/chassis* # commit-buffer
switch-A /org/server-qual/chassis #
```

Related Commands

Command	Description
show cap-qual	
show chassis	

enter memory

To enter memory, use the **enter memory** command.

enter memory

This command has no arguments or keywords.

Command Default

None

Command Modes

Server qualification (/org/server-qual)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to enter memory and set memory property values. Use the **exit** command to exit memory.

If you are entering memory for the first time, once you have entered you will need to execute the **commit-buffer** command.

Examples

This example shows how to enter memory:

```
switch-A# scope org org10
switch-A /org # scope server-qual sq10
switch-A /org/server-qual # enter memory
switch-A /org/server-qual/memory* # commit-buffer
switch-A /org/server-qual/memory #
```

Related Commands

Command	Description
show detail	
show memory	

enter processor

To enter the processor, use the **enter processor** command.

enter processor

This command has no arguments or keywords.

Command Default

None

Command Modes

Server qualification (/org/server-qual)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to enter the processor and set processor property values. Use the **exit** command to exit the processor.

If you are entering memory for the first time, once you have entered you will need to execute the **commit-buffer** command.

Examples

This example shows how to enter the processor:

```
switch-A# scope org org10
switch-A /org # scope server-qual sq10
switch-A /org/server-qual # enter processor
switch-A /org/server-qual/processor* # commit-buffer
switch-A /org/server-qual/processor #
```

Related Commands

Command	Description
show memory	
show processor	

enter storage

To enter storage, use the **enter storage** command.

enter storage

This command has no arguments or keywords.

Command Default

None

Command Modes

Boot policy (/org/boot-policy)
 Server qualification (/org/server-qual)
 Boot definition (/org/service-profile/boot-def)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to enter storage and set storage property values. Use the **exit** command to exit storage.

If you are entering storage for the first time, once you have entered you will need to execute the **commit-buffer** command.

Examples

The following example shows how to enter storage:

```
switch-A# scope org org10
switch-A /org # scope server-qual sq10
switch-A /org/server-qual # enter storage
switch-A /org/server-qual/storage* # commit-buffer
switch-A /org/server-qual/storage #
```

Related Commands

Command	Description
show detail	
show storage	

power

To power up or down, use the **power** command.

power

power { up | down }

Syntax Description

up	Specifies power up.
down	Specifies power down.

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to power up:

```
switch-A# scope org org10a  
switch-A /org # scope service-profile servProf10a  
switch-A /org/service-profile # power down
```

reboot

To reboot, use the **reboot** command.

reboot

This command has no arguments or keywords.

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to reboot:

```
switch-A# scope org org10
switch-A /org # scope service-profile sp10
switch-A /org/service-profile # reboot
```

recommission chassis

To recommission a chassis, use the **recommission chassis** command.

recommission chassis *vendor model serial-num*

Syntax Description

<i>vendor</i>	Vendor.
<i>model</i>	Model.
<i>serial-num</i>	Serial number.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to recommission a chassis:

```
switch-A# recommission chassis "Cisco Systems Inc" "Cisco UCS 5108" FOX1252GNNN
switch-A* # commit-buffer
switch-A #
```

Related Commands

Command	Description
show chassis	
show slot	

remove privilege

To remove privileges, use the **remove privilege** command.

```
remove privilege { aaa | admin | ext-lan-config | ext-lan-policy | ext-lan-qos | ext-lan-security |
ext-san-config | ext-san-policy | ext-san-qos | ext-san-security | fault | service-profile-config |
service-profile-config-policy | service-profile-network | service-profile-network-policy | service-profile-qos
| service-profile-qos-policy | service-profile-security | service-profile-security-policy | service-profile-server
| service-profile-server-policy | service-profile-storage | service-profile-storage-policy | operations |
server-equipment | server-maintenance | server-policy | server-security | pod-config | pod-policy | pod-qos
| pod-security | read-only } +
```

Syntax Description

aaa	Specifies AAA privileges.
admin	Specifies admin privileges.
ext-lan-config	Specifies external LAN configuration privileges.
ext-lan-policy	Specifies external LAN policy privileges.
ext-lan-qos	Specifies external LAN QoS privileges.
ext-lan-security	Specifies external LAN security privileges.
ext-san-config	Specifies external SAN configuration privileges.
ext-san-policy	Specifies external SAN policy privileges.
ext-san-qos	Specifies external SAN QoS privileges.
ext-san-security	Specifies external SAN security privileges.
fault	Specifies fault privileges.
service-profile-config	Specifies service profile configuration privileges.
service-profile-config-policy	Specifies service profile configuration policy privileges.
service-profile-network	Specifies service profile network privileges.
service-profile-network-policy	Specifies service profile network policy privileges.
service-profile-qos	Specifies service profile QoS privileges.
service-profile-qos-policy	Specifies service profile QoS policy privileges.
service-profile-security	Specifies service profile security privileges.
service-profile-security-policy	Specifies service profile security policy privileges.

service-profile-server	Specifies service profile server privileges.
service-profile-server-policy	Specifies service profile server policy privileges.
service-profile-storage	Specifies service profile storage privileges.
service-profile-storage-policy	Specifies service profile storage policy privileges.
operations	Specifies operations privileges.
server-equipment	Specifies server equipment privileges.
server-maintenance	Specifies server maintenance privileges.
server-policy	Specifies server policy privileges.
server-security	Specifies server security privileges.
pod-config	Specifies pod configuration privileges.
pod-policy	Specifies pod policy privileges.
pod-qos	Specifies pod QoS privileges.
pod-security	Specifies pod security privileges.
read-only	Specifies read-only privileges.

Command Default

None

Command Modes

Role (/security/role)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to remove privileges:

```
switch-A#scope security
switch-A /security # scope role serverAdmin
switch-A /security/role # remove privilege server-policy
switch-A /security/role* # commit-buffer
switch-A /security/role #
```

Related Commands

Command	Description
show local-user	

Command	Description
show role	

remove server

To remove a server, use the **remove server** command.

remove server *slot*

Syntax Description	<i>slot</i>	Slot number. The range of valid values is 1 to 255.
--------------------	-------------	---

Command Default	None
-----------------	------

Command Modes	Any command mode
---------------	------------------

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples This example shows how to remove a server:

```
switch-A# remove server 1/1
switch-A* # commit-buffer
switch-A #
```

Related Commands	Command	Description
	show iom	
	show server	

reset

To reset, use the **reset** command.

logcontrol, bmc, and iom mode

reset

server and service profile mode

reset { hard-reset-immediate | hard-reset-wait }

Syntax Description	hard-reset-immediate						
	hard-reset-wait						
Command Default	None						
Command Modes	Logcontrol (/monitoring/sysdebug/logcontrol) BMC (/chassis/server/bmc) Server (/chassis/server) Service profile (/org/service-profile) IO module (/chassis/iom)						
Command History	<table> <tr> <th>Release</th><th>Modification</th></tr> <tr> <td>1.0(1)</td><td>This command was introduced.</td></tr> </table>	Release	Modification	1.0(1)	This command was introduced.		
Release	Modification						
1.0(1)	This command was introduced.						
Examples	<p>The following example shows how to reset:</p> <pre>switch-A# scope chassis 1 switch-A /chassis # scope iom 1/1 switch-A /chassis/iom # reset switch-A /chassis/iom* # commit-buffer switch-A /chassis/iom #</pre>						
Related Commands	<table> <tr> <th>Command</th><th>Description</th></tr> <tr> <td>show chassis</td><td></td></tr> <tr> <td>show server</td><td></td></tr> </table>	Command	Description	show chassis		show server	
Command	Description						
show chassis							
show server							

reset-cmos

To reset the CMOS, use the **reset-cmos** command.

reset-cmos

This command has no arguments or keywords.

Command Default	None
Command Modes	Server (/chassis/server)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples

This example shows how to reset CMOS:

```
switch-A# scope chassis 1
switch-A /chassis # scope server 1
switch-A /chassis/server # reset cmos
switch-A /chassis/server* # commit-buffer
switch-A /chassis/server #
```

Related Commands

Command	Description
show cpu	
show firmware	

scope adapter

To enter adapter mode, use the **scope adapter** command.

scope adapter *chassis/slot/adapter*

Syntax Description

<i>chassis/slot/id</i>	Adapter location.
------------------------	-------------------

Command Default

None

Command Modes

Any command mode

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples

This example shows how to enter adapter mode:

```
scope adapter 1/1/1
switch /chassis/server/adapter #
```

Related Commands

Command	Description
show chassis	
show iom	

scope backup

To enter backup mode, use the **scope backup** command.

scope backup *name*

Syntax Description

<i>name</i>	Host name.
-------------	------------

Command Default

None

Command Modes

System (/system)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter backup mode:

```
switch-A# scope system
switch-A /system # scope backup backUpFDrive
switch-A /system #* commit-buffer
switch-A /system #
```

Related Commands

Command	Description
show backup	
show import-config	

scope block

To enter block mode, use the **scope block** command.

scope block *from to*

Syntax Description	<i>from</i>	From value.
	<i>to</i>	To value.
Command Default	None	
Command Modes	IP pool (/org/ip-pool) WWN pool (/org/wwn-pool) UUID suffix pool (/org/uuid-suffix-pool) MAC pool (/org/mac-pool)	
Command History	Release	Modification
	1.0(1)	This command was introduced.
Examples	This example shows how to enter block mode: <pre>switch-A# scope org org10 switch-A /org # scope ip-pool ipp10 switch-A /org/ip-pool # scope block 209.165.200.225 209.165.200.235 switch-A /org/ip-pool #</pre>	
Related Commands	Command	Description
	show ip-pool	
	show mac-pool	

scope bmc

To enter bmc mode, use the **scope bmc** command.

scope bmc

This command has no arguments or keywords.

Command Default None

Command Modes Server (/chassis/server)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter bmc mode:

```
switch-A# scope chassis 1
switch-A /chassis # scope server 1/1
switch-A /chassis/server # scope bmc
switch-A /chassis/server/bmc #
```

Related Commands

Command	Description
show bmc	
show raid-controller	

scope boot-definition

To enter boot definition mode, use the **scope boot-definition** command.

scope boot-definition

This command has no arguments or keywords.

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter boot definition mode:

```
switch-A# scope org org3
switch-A /org # scope service-profile sp3a
switch-A /org/service-profile # scope boot-definition
switch-A /org/service-profile/boot-definition #
```

Related Commands

Command	Description
show boot-definition	
show lan	

scope boot-policy

To enter boot-policy mode, use the **scope boot-policy** command.

scope boot-policy *name*

Syntax Description

<i>name</i>	Boot policy name.
-------------	-------------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter boot-policy mode:

```
switch-A# scope org org10
switch-A /org # scope boot-policy
switch-A /org/boot-policy #
```

Related Commands

Command	Description
show boot-policy	
show qos-policy	

scope capability

To enter capability mode, use the **scope capability** command.

scope capability

Command Default

None

Command Modes

System (/system)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter capability mode:

```
switch-A# scope system
switch-A /system # scope capability
switch-A /system/capability #
```

Related Commands

Command	Description
show memory	
show version	

scope cap-qual

To enter capacity qualification mode, use the **scope cap-qual** command.

```
scope cap-qual { fcoe | non-virtualized-eth-if | non-virtualized-fc-if | path-encap-consolidated |
path-encap-virtual | protected-eth-if | protected-fc-if | protected-fcoe | virtualized-eth-if | virtualized-fc-if
| virtualized-scsi-if }
```

Syntax Description

fcoe	Specifies Fibre Channel over Ethernet.
non-virtualized-eth-if	Specifies a non-virtualized Ethernet interface.
non-virtualized-fc-if	Specifies a non-virtualized Fibre Channel interface.
path-encap-consolidated	Specifies a consolidated encapsulated path.
path-encap-virtual	Specifies a virtual encapsulated path.
protected-eth-if	Specifies a protected Ethernet interface.
protected-fc-if	Specifies a protected Fibre Channel interface.
protected-fcoe	Specifies a protected Fibre Channel over Ethernet interface.
virtualized-eth-if	Specifies a virtualized Ethernet interface.
virtualized-fc-if	Specifies a virtualized Fibre Channel interface.
virtualized-scsi-if	Specifies a virtualized SCSI interface.

Command Default

None

Command Modes

Adapter (/org/server-qual/adapter)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter capacity qualification mode:

```
switch-A# scope org org10
switch-A /org # scope server-qual sq10
switch-A /org/server-qual # scope adapter

switch-A /org/server-qual/adapter # scope cap-qual fcoe
```

Related Commands

Command	Description
show adapter	
show cap-qual	

scope chassis

To enter chassis mode, use the **scope chassis** command.

scope chassis *chassis-id*

Syntax Description

<i>id</i>	Chassis identification number.
-----------	--------------------------------

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter chassis mode:

```
switch-A# scope chassis 1
switch-A /chassis #
```

Related Commands

Command	Description
show chassis	
show slot	

scope chassis-disc-policy

To enter chassis discovery policy mode, use the **scope chassis-disc-policy** command.

scope chassis-disc-policy

This command has no arguments or keywords.

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter chassis discovery policy mode:

```
switch-A# scope org org30
switch-A /org # scope chassis-disc-policy
switch-A /org/chassis-disc-policy #
```

Related Commands

Command	Description
show chassis-disc-policy	
show org	

scope eth-classified

To enter eth-classified mode, use the **scope eth-classified** command.

scope eth-classified { best-effort | bronze | gold | platinum | silver }

Syntax Description

best-effort	Specifies
bronze	Specifies bronze classified mode.
gold	Specifies gold classified mode.
platinum	Specifies platinum classified mode.
silver	Specifies silver classified mode.

Command Default

None

Command Modes

QoS (/eth-server/qos)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

You do not have to enter this mode with a managed object.

Enters Ethernet server QoS Ethernet classified mode for the specified system class.

Examples

The following example shows how to enter eth-classified mode:

```
switch-A# eth-server
switch-A /eth-server # scope qos
switch-A /eth-server/qos # scope eth-classified
switch-A /eth-server/qos/eth-classified #
```

Related Commands

Command	Description
show eth-best-effort	
show eth-classified	

scope eth-server

To enter eth-server mode, use the **scope eth-server** command.

scope eth-server

This command has no arguments or keywords.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

You do not have to enter this mode with a managed object.

Examples

This example shows how to enter eth-server mode:

```
switch-A#scope eth-server
switch-A /eth-server #
```

Related Commands

Command	Description
show interface	
show server	

scope eth-uplink

To enter eth-uplink mode, use the **scope eth-uplink** command.

scope eth-uplink

This command has no arguments or keywords.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

You do not have to enter this mode with a managed object.

Examples

This example shows how to enter eth-uplink mode:

```
switch-A#scope eth-uplink
switch-A /eth-uplink #
```

Related Commands

Command	Description
show eth-uplink	
show port-profile	

scope fc-uplink

To enter fc-uplink mode, use the **scope fc-uplink** command.

scope fc-uplink

This command has no arguments or keywords.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

You do not have to enter this mode with a managed object.

Examples

This example shows how to enter fc-uplink mode:

```
switch-A# scope fc-uplink
switch-A /fc-uplink #
```

Related Commands

Command	Description
show interface	
show vlan	

scope firmware

To enter firmware mode, use the **scope firmware** command.

scope firmware

This command has no arguments or keywords.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

You do not have to enter this mode with a managed object.

Examples

This example shows how to enter firmware mode:

```
switch-A# scope firmware
switch-A /firmware #
```

Related Commands

Command	Description
show firmware	
show version	

scope flow-control

To enter flow control mode, use the **scope flow-control** command.

scope flow-control

This command has no arguments or keywords.

Command Default

None

Command Modes

Ethernet uplink (/eth-uplink)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Usage Guidelines You do not have to enter this mode with a managed object.

Examples This example shows how to enter flow control mode:

```
switch-A# scope eth-uplink
switch-A /eth-uplink # scope flow-control
switch-A /eth-uplink/flow-control #
```

Related Commands	Command	Description
	show policy	
	show port-profile	

scope import-config

To enter import configuration mode, use the **scope import-config** command.

scope import-config *name*

Syntax Description	<i>name</i>	Import configuration name.

Command Default None

Command Modes System (/system)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples This example shows how to enter import configuration mode:

```
switch-A# scope system
switch-A /system # scope import-config ic10
switch-A /system/import-config #
```

Related Commands

Command	Description
show import-config	
show managed-entity	

scope iom

To enter iom mode, use the **scope iom** command.

chassis mode

scope iom { *id* | **a** | **b** } *id*

capability mode

scope iom *vendor model hw-rev*

Syntax Description

<i>id</i>	Module identification number.
a	Specifies switch A.
b	Specifies switch B.
<i>vendor</i>	Vendor name.
<i>model</i>	Model number.
<i>hw-rev</i>	Hardware revision.

Command Default

None

Command Modes

Chassis (/chassis)
Capability (/system/capability)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter iom mode:

```
switch-A# scope chassis
switch-A /chassis # scope iom 1
switch-A /chassis/iom #
```

Related Commands

Command	Description
show iom	
show slot	

scope ipmi-access-profile

To enter IPMI access profile mode, use the **scope ipmi-access-profile** command.

scope ipmi-access-profile *name*

Syntax Description

<i>name</i>	Access profile name.
-------------	----------------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

The following example shows how to enter IPMI access profile mode:

```
switch-A# scope org org10
switch-A /org # scope ipmi-access-profile ipmiAP10
switch-A /org/ipmi-access-profile #
```

Related Commands

Command	Description
show epuser	
show ipmi-access-profile	

scope ldap

To enter LDAP mode, use the **scope ldap** command.

scope ldap

This command has no arguments or keywords.

Command Default

None

Command Modes

LDAP (/security/ldap)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

You do not have to enter this mode with a managed object.

Examples

This example shows how to enter LDAP mode:

```
switch-A#scope security
switch-A /security # scope ldap
switch-A /security/ldap #
```

Related Commands

Command	Description
show ldap	
show tacacs	

scope locale

To enter locale mode, use the **scope locale** command.

scope locale *name*

Syntax Description

<i>name</i>	Locale name.
-------------	--------------

Command Default

None

Command Modes

Security (/security)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter locale mode:

```
switch-A#scope security
switch-A /security # scope locale
switch-A /security/locale #
```

Related Commands

Command	Description
show locale	
show remote-user	

scope monitoring

To enter monitoring mode, use the **scope monitoring** command.

scope monitoring

This command has no arguments or keywords.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

You do not have to enter this mode with a managed object.

Examples

This example shows how to enter monitoring mode:

```
switch-A#scope monitoring
switch-A /monitoring #
```

Related Commands

Command	Description
show callhome	
show syslog	

scope org

To enter org mode, use the **scope org** command.

scope org *name*

Syntax Description

<i>name</i>	Organization name.
-------------	--------------------

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter org mode:

```
switch-A# scope org org100  
switch-A /org #
```

Related Commands

Command	Description
show mac-pool	
show org	

scope port-channel

To enter port channel mode, use the **scope port-channel** command.

scope port-channel *id*

Syntax Description

<i>id</i>	Port identification number.
-----------	-----------------------------

Command Default

None

Command Modes

Fabric interconnect (/eth-uplink/fabric)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter port channel mode:

```
switch-A#scope eth-uplink
switch-A /eth-uplink # scope fabric b
switch-A /eth-uplink/fabric # scope port-channel 10
switch-A /eth-uplink/fabric/port-channel #
```

Related Commands

Command	Description
show switch	
show port-channel	

scope qos

To enter QoS mode, use the **scope qos** command.

scope qos

This command has no arguments or keywords.

Command Default

None

Command Modes

Ethernet server (/eth-server)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

You do not have to enter this mode with a managed object.

Examples

This example shows how to enter QoS mode:

```
switch-A# scope eth-server
switch-A /eth-server # scope qos
switch-A /eth-server/qos #
```

Related Commands

Command	Description
show eth-best-effort	
show eth-classified	

scope radius

To enter radius mode, use the **scope radius** command.

scope radius

This command has no arguments or keywords.

Command Default

None

Command Modes

Security (/security)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

You do not have to enter this mode with a managed object.

Examples

This example shows how to enter radius mode:

```
switch-A#scope security
switch-A /security # scope radius
switch-A /security /radius #
```

Related Commands

Command	Description
show ldap	
show radius	

scope role

To enter role mode, use the **scope role** command.

scope role *name*

Syntax Description	<i>name</i> Role name.						
Command Default	None						
Command Modes	Security (/security)						
Command History	<table><tr><th>Release</th><th>Modification</th></tr><tr><td>1.0(1)</td><td>This command was introduced.</td></tr></table>	Release	Modification	1.0(1)	This command was introduced.		
Release	Modification						
1.0(1)	This command was introduced.						
Examples	<p>This example shows how to enter role mode:</p> <pre>switch-A#scope security switch-A /security # scope role admin switch-A /security #</pre>						
Related Commands	<table><tr><th>Command</th><th>Description</th></tr><tr><td>show local-user</td><td></td></tr><tr><td>show role</td><td></td></tr></table>	Command	Description	show local-user		show role	
Command	Description						
show local-user							
show role							

scope security

To enter security mode, use the **scope security** command.

scope security

This command has no arguments or keywords.

Command Default	None				
Command Modes	Any command mode				
Command History	<table><tr><th>Release</th><th>Modification</th></tr><tr><td>1.0(1)</td><td>This command was introduced.</td></tr></table>	Release	Modification	1.0(1)	This command was introduced.
Release	Modification				
1.0(1)	This command was introduced.				
Usage Guidelines	You do not have to enter this mode with a managed object.				

Examples

This example shows how to enter security mode:

```
switch-A# scope security
switch-A /security #
```

Related Commands

Command	Description
show ldap	
show tacacs	

scope server

To enter server mode, use the **scope server** command.

scope server {*name*| **dynamic-uuid**}

Syntax Description

<i>name</i>	Server name.
dynamic-uuid	Specifies the unique server identity.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter server mode:

```
switch-A# scope server 1/1
switch-A /chassis/server #
```

Related Commands

Command	Description
show server adapter	
show server identity	

scope server-qual

To enter server-qual mode, use the **scope server-qual** command.

scope server-qual *name*

Syntax Description	<table><tr><td><i>name</i></td><td>Server qualifier name.</td></tr></table>	<i>name</i>	Server qualifier name.				
<i>name</i>	Server qualifier name.						
Command Default	None						
Command Modes	Organization (/org)						
Command History	<table><tr><th>Release</th><th>Modification</th></tr><tr><td>1.0(1)</td><td>This command was introduced.</td></tr></table>	Release	Modification	1.0(1)	This command was introduced.		
Release	Modification						
1.0(1)	This command was introduced.						
Examples	<p>This example shows how to enter server-qual mode:</p> <pre>switch-A# scope org org3 switch-A /org # scope server-qual squal1 switch-A /org/server-qual #</pre>						
Related Commands	<table><tr><th>Command</th><th>Description</th></tr><tr><td>show server-pool</td><td></td></tr><tr><td>show server-qual</td><td></td></tr></table>	Command	Description	show server-pool		show server-qual	
Command	Description						
show server-pool							
show server-qual							

scope services

To enter services mode, use the **scope services** command.

scope services

This command has no arguments or keywords.

Command Default	None
Command Modes	Services (/system/services)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

You do not have to enter this mode with a managed object.

Examples

This example shows how to enter services mode:

```
switch-A#scope system
switch-A /system # scope services
switch-A /system/services #
```

Related Commands

Command	Description
show cimxml	
show dns	

scope system

To enter system mode, use the **scope system** command.

scope system

This command has no arguments or keywords.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

You do not have to enter this mode with a managed object.

Examples

This example shows how to enter system mode:

```
switch-A# scope system
switch-A /system #
```

Related Commands

Command	Description
show fabric	
show version	

scope tacacs

To enter TACACS mode, use the **scope tacacs** command.

scope tacacs

This command has no arguments or keywords.

Command Default

None

Command Modes

Security (/security)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

You do not have to enter this mode with a managed object.

Examples

This example shows how to enter TACACS mode:

```
switch-A#scope security
switch-A /security # scope tacacs
switch-A /security/tacacs #
```

Related Commands

Command	Description
show radius	
show ttacacs	

scope vhba

To enter virtual HBA mode, use the **scope vhba** command.

scope vhba *name*

Syntax Description	<table> <tr> <th><i>name</i></th><th>Virtual HBA name.</th></tr> </table>	<i>name</i>	Virtual HBA name.				
<i>name</i>	Virtual HBA name.						
Command Default	None						
Command Modes	Service profile (/org/service-profile)						
Command History	<table> <tr> <th>Release</th><th>Modification</th></tr> <tr> <td>1.0(1)</td><td>This command was introduced.</td></tr> </table>	Release	Modification	1.0(1)	This command was introduced.		
Release	Modification						
1.0(1)	This command was introduced.						
Examples	<p>This example shows how to enter virtual HBA mode:</p> <pre>switch-A# scope org org10 switch-A /org # scope service-profile sp10 switch-A /org # scope vhba vHBA10 switch-A /org/vhba #</pre>						
Related Commands	<table> <tr> <th>Command</th><th>Description</th></tr> <tr> <td>show service-profile</td><td></td></tr> <tr> <td>show vhba</td><td></td></tr> </table>	Command	Description	show service-profile		show vhba	
Command	Description						
show service-profile							
show vhba							

scope vhba-templ

To enter virtual HBA template mode, use the **scope vhba-templ** command.

scope vhba-templ

scope vhba-templ *name*

Syntax Description	<table> <tr> <th><i>name</i></th><th>Virtual HBA template name.</th></tr> </table>	<i>name</i>	Virtual HBA template name.
<i>name</i>	Virtual HBA template name.		
Command Default	None		
Command Modes	Organization (/org)		

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter virtual HBA template mode:

```
switch-A# scope org org10
switch-A /org # scope vhba-templ vhbaT10
switch-A /org/vhba-templ #
```

Related Commands

Command	Description
show fc-if	
show vhba-templ	

scope vnic

To enter virtual NIC mode, use the **scope vnic** command.

scope vnic *name*

Syntax Description

<i>name</i>	Virtual NIC name.
-------------	-------------------

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter virtual NIC mode:

```
switch-A# scope org org10
switch-A /org # scope service-profile sp10
switch-A /org # scope vnic vNIC10
switch-A /org/vnic #
```

Related Commands

Command	Description
show service-profile	
show vnic	

scope vnic-templ

To enter virtual NIC template mode, use the **scope vnic-templ** command.

scope vnic-templ *name*

Syntax Description

<i>name</i>	Virtual NIC template name.
-------------	----------------------------

Command Default

None

Command Modes

Organization (/org)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter virtual NIC template mode:

```
switch-A# scope org org10
switch-A /org # scope vnic-templ vnicT10
switch-A /org/vnic-templ #
```

Related Commands

Command	Description
show eth-if	
show vnic-templ	

scope wwn-pool

To enter WWN pool mode, use the **scope wwn-pool** command.

scope wwn-pool *name*

Syntax Description	<i>name</i> WWN pool name.						
Command Default	None						
Command Modes	Organization (/org)						
Command History	<table> <tr> <th>Release</th><th>Modification</th></tr> <tr> <td>1.0(1)</td><td>This command was introduced.</td></tr> </table>	Release	Modification	1.0(1)	This command was introduced.		
Release	Modification						
1.0(1)	This command was introduced.						
Examples	<p>This example shows how to enter WWN pool mode:</p> <pre>switch-A# scope org org10 switch-A /org # scope wwn-pool wwnP10 switch-A /org/wwn-pool #</pre>						
Related Commands	<table> <tr> <th>Command</th><th>Description</th></tr> <tr> <td>show initiator</td><td></td></tr> <tr> <td>show org</td><td></td></tr> </table>	Command	Description	show initiator		show org	
Command	Description						
show initiator							
show org							

set action

To set action, use the **set action** command.

chassis-disc-policy mode

set action { 1-link | 2-link | 4-link }

import-config mode

set action { merge | replace }

server-disc-policy mode

set action { diag | immediate | user-acknowledged }

Syntax Description	1-link Specifies one uplink.
	2-link Specifies two uplinks.
	4-link Specifies four uplinks.

merge	Specifies merge.
replace	Specifies replace.
diag	Specifies diagnostic.
immediate	Specifies immediate.
user-acknowledged	Specifies user acknowledged.

Command Default

None

Command Modes

Chassis discovery policy (/org/chassis-disc-policy)

Import configuration (/system/import-config)

Server discovery policy /org/server-disc-policy

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command in chassis-disc-policy mode to specify the number of links to the switch that the chassis must have to be discovered.

Examples

This example shows how to set action:

```
switch-A# scope org org10
switch-A /org/chassis-disc-policy # scope chassis-disc-policy cdp10

switch-A /org/chassis-disc-policy # set action 4-link
switch-A /org/chassis-disc-policy* # commit-buffer
switch-A /org/chassis-dis-policy #
```

Related Commands

Command	Description
show chassis	
show chassis-disc-policy	

set adaptor-profile

To set an adaptor profile, use the **set adaptor-profile** command.

set adaptor-profile *name*

Syntax Description	<table> <tr> <th><i>name</i></th><th>Adapter profile name. The range of valid values is 1 to 16.</th></tr> </table>	<i>name</i>	Adapter profile name. The range of valid values is 1 to 16.				
<i>name</i>	Adapter profile name. The range of valid values is 1 to 16.						
Command Default	None						
Command Modes	Hypervisor connection (/org/service-profile/hv-conn) Dynamic connection policy (/org/dynamic-conn-policy) Virtual HBA (/org/service-profile/vhba) Virtual NIC (/org/service-profile/vnic)						
Command History	<table> <tr> <th>Release</th><th>Modification</th></tr> <tr> <td>1.0(1)</td><td>This command was introduced.</td></tr> </table> <p>Use this command to associate the specified profile with the service profile you used to enter service profile mode.</p>	Release	Modification	1.0(1)	This command was introduced.		
Release	Modification						
1.0(1)	This command was introduced.						
Examples	<p>This example shows how to set an adapter profile:</p> <pre>switch-A# scope org org30a switch-A /org # scope service-profile sp10 switch-A /org/service-profile # scope vnic switch-A /org/service-profile/vnic # set adaptor-profile 20a switch-A /org/service-profile/vnic* # commit-buffer switch-A /org/service-profile/vnic #</pre>						
Related Commands	<table> <tr> <th>Command</th><th>Description</th></tr> <tr> <td>show vhba</td><td></td></tr> <tr> <td>show vnic</td><td></td></tr> </table>	Command	Description	show vhba		show vnic	
Command	Description						
show vhba							
show vnic							

set adminstate

To set the administration state, use the **set adminstate** command.

set adminstate { disabled | enabled }

Syntax Description	<table> <tr> <td>disabled</td><td>Specifies administration state enabled.</td></tr> <tr> <td>enabled</td><td>Specifies administration state disabled.</td></tr> </table>	disabled	Specifies administration state enabled.	enabled	Specifies administration state disabled.
disabled	Specifies administration state enabled.				
enabled	Specifies administration state disabled.				

Command Default

None

Command Modes

Ethernet classified (/eth-server/qos/eth-classified)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set the administration state:

```
switch-A# scope eth-server
switch-A /eth-server # scope qos
switch-A /eth-server/qos # scope eth-classified silver
switch-A /eth-server/qos/eth-classified # set adminstate enabled
switch-A /eth-server/qos/eth-classified* # commit-buffer
switch-A /eth-server/qos/eth-classified #
```

Related Commands

Command	Description
show eth-best-effort	
show eth-classified	

set agent-policy

To set the agent policy, use the **set agent-policy** command.

set agent-policy *name*

Syntax Description

<i>name</i>	Agent policy name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to associate the specified agent policy with the service profile you used to enter service profile mode.

Examples

This example shows how to set the agent policy:

```
switch-A# scope org org10
switch-A /org # scope service-profile servProf10
switch-A /org/service-profile # set agent-policy agentP10
switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show association	
show service-profile	

set arch

To set processor architecture (arch), use the **set arch** command.

set arch { dual-core-opteron | intel-p4-c | opteron | pentium-4 | turion-64 | xeon | xeon-mp | any }

Syntax Description

dual-core-opteron	Specifies the dual-core Opteron processor.
intel-p4-c	Specifies the Intel P4 C processor.
opteron	Specifies the Opteron processor.
pentium-4	Specifies the Pentium 4 processor.
turion-64	Specifies the Turion 4 processor.
xeon	Specifies the Xeon processor.
xeon-mp	Specifies the Xeon MP processor.
any	Specifies any processor.

Command Default

None

Command Modes

Processor (/org/server-qual/processor)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set processor architecture:

```
switch-A# scope org org3
switch-A /org # scope server-qual squal10
switch-A /org/server-qual # scope processor
switch-A /org/server-qual/processor # set arch xeon-mp
switch-A /org/server-qual/processor* # commit-buffer
switch-A /org/server-qual/processor #
```

Related Commands

Command	Description
show memory	
show processor	

set attribute

To set an attribute, use the **set attribute** command.

set attribute *attribute*

Syntax Description

<i>attribute</i>	Attribute name. The range of valid values is 1 to 63.
------------------	---

Command Default

None

Command Modes

LDAP (/security/ldap)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to restrict database searches to records that contain the specified attribute.

Examples

This example shows how to set an attribute:

```
switch-A#scope security
switch-A /security # scope ldap
switch-A /security/ldap # set attribute name
```



```
switch-A /security/ldap* # commit-buffer
switch-A /security/ldap #
```

Related Commands

Command	Description
show ldap	
show tacacs	

set authentication console

To set up the authentication console, use the **set authentication console** command.

set authentication console { ldap | local | radius | tacacs }

Syntax Description

ldap	Specifies an LDAP authentication console.
local	Specifies a local authentication console.
radius	Specifies a RADIUS authentication console.
tacacs	Specifies a TACACS authentication console.

Command Default

None

Command Modes

Security (/security)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set up the authentication console:

```
switch-A#scope security
switch-A /security # set authentication console ldap

switch-A /security* # commit-buffer
switch-A /security #
```

Related Commands

Command	Description
show authentication	
show ldap	

set authentication default

To set an authentication default, use the **set authentication default** command.

set authentication default { **ldap** | **local** | **radius** | **tacacs** }

Syntax Description

ldap	Specifies an LDAP authentication console.
local	Specifies a local authentication console.
radius	Specifies a RADIUS authentication console.
tacacs	Specifies a TACACS authentication console.

Command Default

None

Command Modes

Security (/security)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set an authentication default:

```
switch-A#scope security
switch-A /security # set authentication default ldap

switch-A /security* # commit-buffer
switch-A /security #
```

Related Commands

Command	Description
show authentication	
show ldap	

set authport

To set up an authentication port, use the **set authport** command.

set authport *id*

Syntax Description	<i>id</i> Authentication port identification number. The range of valid values is 1 to 65535.						
Command Default	None						
Command Modes	Server (/security/radius/server)						
Command History	<table> <tr> <th>Release</th><th>Modification</th></tr> <tr> <td>1.0(1)</td><td>This command was introduced.</td></tr> </table>	Release	Modification	1.0(1)	This command was introduced.		
Release	Modification						
1.0(1)	This command was introduced.						
Usage Guidelines	Use this command to specify the port used to communicate with a RADIUS server.						
Examples	<p>This example shows how to set up an authentication port:</p> <pre>switch-A#scope security switch-A /security # scope radius switch-A /security/radius # scope server s100 switch-A /security/radius/server # set authport 100 switch-A /security/radius/server* # commit-buffer switch-A /security/radius/server #</pre>						
Related Commands	<table> <tr> <th>Command</th><th>Description</th></tr> <tr> <td>show ldap</td><td></td></tr> <tr> <td>show radius</td><td></td></tr> </table>	Command	Description	show ldap		show radius	
Command	Description						
show ldap							
show radius							

set basedn

To set up a distinguished name, use the **set basedn** command.

set basedn *name*

Syntax Description	<i>name</i> Distinguished name. The range of valid values is 1 to 127.
Command Default	None
Command Modes	LDAP (/security/ldap)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to restrict database searches to records that contain the specified distinguished name.

Examples

This example shows how to set up a distinguished name:

```
switch-A#scope security
switch-A /security # scope ldap
switch-A /security/ldap # set basedn ldap
switch-A /security/ldap* # commit-buffer
switch-A /security/ldap #
```

Related Commands

Command	Description
show ldap	
show tacacs	

set blocksize

To set the block size, use the **set blocksize** command.

set blocksize { *blocksize* | **unspecified** }

Syntax Description

<i>blocksize</i>	Storage block size. The range of valid values is 0 to 4294967295.
unspecified	Specifies an unspecified block size.

Command Default

None

Command Modes

Storage (/org/server-qual/storage)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set the block size:

```
switch-A# scope org org3
switch-A /org # scope server-qual squal10
```

```
switch-A /org/server-qual # scope storage
switch-A /org/server-qual/storage # set blocksize 1000
switch-A /org/server-qual/storage* # commit-buffer
switch-A /org/server-qual/storage #
```

Related Commands

Command	Description
show memory	
show processor	

set boot-policy

To set the boot policy, use the **set boot-policy** command.

set boot-policy *name*

Syntax Description

<i>name</i>	Boot policy name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to associate the specified boot policy with the service profile you used to enter service profile mode.

Examples

This example shows how to set the boot policy:

```
switch-A# scope org org10
switch-A /org # scope service-profile servProf10
switch-A /org/service-profile # set boot-policy bootP10
switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show association	
show boot-definition	

set cimxml port

To set up a CIM (Common Information Model) XML port, use the **set cimxml port** command.

set cimxml port *port*

Syntax Description

<i>port</i>	Port number. The range of valid values is 1 to 65535.
-------------	---

Command Default

None

Command Modes

Services (/system/services)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set up a CIM XML port:

```
switch-A#scope system
switch-A /system # scope services
switch-A /system/services # set cimxml port 10
switch-A /system/services* # commit-buffer
switch-A /system/services #
```

Related Commands

Command	Description
show cimxml	
show dns	

set clock

To set the memory clock speed, use the **set clock** command.

set clock {*number* | **unspec**}

Syntax Description

<i>number</i>	Memory clock speed, in seconds. The range of valid values is 1 to 65535.
unspec	Specifies unspecified speed.

Command Default

None

Command Modes

Memory (/org/server-qual/memory)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set the memory clock speed:

```
switch-A# scope org org10
switch-A /org # scope server-qual sq10
switch-A /org/server-qual # scope memory
switch-A /org/server-qual/memory # set clock 10
switch-A /org/server-qual/memory* # commit-buffer
switch-A /org/server-qual/memory #
```

Related Commands

Command	Description
show memory	
show processor	

set cos

To set up CoS (Class of Service), use the **set cos** command.

set cos { *cos* | **any** }

Syntax Description

<i>cos</i>	Class of Service. The range of valid values is 0 to 6.
any	Specifies any level of CoS.

Command Default

None

Command Modes

Ethernet classified (/eth-server/cos/eth-classified)
Fibre Channel default (/eth-server/cos/fc-default)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to restrict the passage of traffic. A higher value indicates more important traffic. Setting CoS at 6 specifies the most important traffic.

Examples

This example shows how to set up CoS:

```
switch-A# scope eth-server
switch-A /eth-server # scope cos
switch-A /eth-server/qos # scope eth-classified
switch-A /eth-server/qos/eth-classified # set cos 6
switch-A /eth-server/qos/eth-classified* # commit-buffer
switch-A /eth-server/qos/eth-classified #
```

Related Commands

Command	Description
show eth-best-effort	
show eth-classified	

set descr

To set a description, use the **set descr** command.

set descr *description*

Syntax Description

<i>description</i>	Description. The range of valid values is 1 to 256.
--------------------	---

Command Default

None

Command Modes

Backup (/system/backup)
 Statistics threshold policy under Ethernet server (/eth-server/stats-threshold-policy)
 Virtual NIC template (/org/vnic-templ)
 Statistics threshold policy under organization (/org/stats-threshold-policy)
 MAC pool (/org/mac-pool)
 Partition (/org/local-disk-config/partition)
 Import configuration (/system/import-config)
 Pooling policy (/org/pooling-policy)
 VMM provider (/system/vm-mgmt/vmm-provider)
 Service profile (/org/service-profile)
 UUID suffix pool (/org/uuid-suffix-pool)
 Pin group under Ethernet uplink (/eth-uplink/pin-group)

Fibre Channel profile (/org/fc-profile)
 SoL (/org/service-profile/sol)
 IP pool (/org/ip-pool)
 Ethernet profile (/org/eth-profile)
 Statistics threshold policy under Fibre Channel uplink (/fc-uplink/stats-threshold-policy)
 Server discovery policy (/org/server-disc-policy)
 Pin group under Fibre Channel uplink (/fc-uplink/pin-group)
 PSU policy (/org/psu-policy)
 Boot policy (/org/boot-policy)
 Statistics threshold policy under Ethernet uplink (/eth-uplink/stats-threshold-policy)
 Local disk configuration under organization (/org/local-disk-config)
 Virtual HBA template (/org/vhba-templ)
 Firmware management pack (/org/fw-mgmt-pack)
 Initiator (/org/wwn-pool/initiator)
 Boot definition (/org/service-profile/boot-def)
 Chassis discovery policy under organization (/org/chassis-disc-policy)
 Automatic configuration policy (/org/autoconfig-policy)
 SoL policy (/org/sol-policy)
 Scrub policy (/org/scrub-policy)
 Local disk configuration under service profile (/org/service-profile/local-disk-config)
 Firmware host pack under organization (/org/fw-host-pack)
 Port profile (/eth-uplink/port-profile)
 WWN pool (/org/wwn-pool)
 Server inherit policy under organization (/org/server-inherit-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

If your description includes spaces, special characters, or punctuation, you must begin and end your description with quotation marks. The quotation marks will not appear in the description field of any show command output

Examples

This example shows how to set a description:

```

switch-A# scope org org10
switch-A /org # scope boot-policy boot100
switch-A /org/boot-policy # set descr bootOnce
switch-A /org/boot-policy* # commit-buffer
switch-A /org/boot-policy #
  
```

Related Commands

Command	Description
show boot-policy	
show detail	

set disk-scrub

To set disk scrub, use the **set disk-scrub** command.

set disk-scrub { no | yes }

Syntax Description

no	Specifies no scrub.
yes	Specifies scrub.

Command Default

None

Command Modes

Scrub policy (/org/scrub-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set disk scrub:

```
switch-A# scope org org3
switch-A /org # scope scrub-policy scrub101
switch-A /org/scrub-policy # set disk-scrub yes
switch-A /org/scrub-policy* # commit-buffer
switch-A /org/scrub-policy #
```

Related Commands

Command	Description
show server-inherit-policy	
show scrub-policy	

set email

To set up email, use the **set email** command.

set email *email***Syntax Description**

<i>email</i>	Email address. Specify in the format <name>@<domain name>.
--------------	--

Command Default

None

Command Modes

Callhome (/monitoring/callhome)
 Local user (/security/local-user)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to set up customer contact email.

Examples

This example shows how to set up email:

```
switch-A# scope monitoring
switch-A /monitoring # scope callhome
switch-A /monitoring/callhome # set email foo@foo.com
switch-A /monitoring/callhome* # commit-buffer
switch-A /monitoring/callhome #
```

Related Commands

Command	Description
show callhome	
show event	

set expiration

To set the expiration date, use the **set expiration** command.**set expiration** { never | { apr | aug | dec | feb | jan | jul | jun | mar | may | nov | oct | sep } *day year* }**Syntax Description**

never	Specifies
apr	Specifies April.
aug	Specifies August.
dec	Specifies December.

feb	Specifies February.
jan	Specifies January.
jul	Specifies July.
jun	Specifies June.
mar	Specifies March.
may	Specifies May.
nov	Specifies November.
oct	Specifies October.
sep	Specifies September.
<i>day</i>	Day.
<i>year</i>	Year.

Command Default None

Command Modes Local user (/security/local-user)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Usage Guidelines Use this command to set the date the user account expires.

Examples This example shows how to set the expiration date:

```
switch-A#scope security
switch-A /security # scope local-user lul
switch-A /security/local-user # set expiration 30 nov

switch-A /security* # commit-buffer
switch-A /security #
```

Related Commands	Command	Description
	show local-user	
	show remote-user	

set filter

To set up a filter, use the **set filter** command.

set filter *name*

Syntax Description

<i>name</i>	Filter name. The range of valid values is 1 to 63.
-------------	--

Command Default

None

Command Modes

LDAP (/security/ldap)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to restrict database searches to records that contain the specified filter.

Examples

This example shows how to set up a filter:

```
switch-A#scope security
switch-A /security # scope ldap
switch-A /security/ldap # set filter domainNames
switch-A /security/ldap* # commit-buffer
switch-A /security/ldap #
```

Related Commands

Command	Description
show ldap	
show tacacs	

set firstname

To set the first name, use the **set firstname** command.

set firstname *name*

Syntax Description

<i>name</i>	First name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Local user (/security/local-user)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set the first name:

```
switch-A#scope security
switch-A /security # scope local-user lul
switch-A /security/local-user # set firstname bob
switch-A /security/local-user* # commit-buffer
switch-A /security/local-user #
```

Related Commands

Command	Description
show local-user	
show remote-user	

set flow-control-policy

To set up a flow control policy, use the **set flow-control-policy** command.

set flow-control-policy *name*

Syntax Description

<i>name</i>	Flow control policy name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Port channel (/eth-uplink/fabric/port-channel)
Interface (/eth-uplink/fabric/interface)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set up a flow control policy:

```
switch-A# scope eth-uplink
switch-A /eth-uplink # scope fabric b
switch-A /eth-uplink/fabric # scope interface 1 2
switch-A /eth-uplink/fabric/interface # set flow-control-policy fcp110
switch-A /eth-uplink/fabric/interface* # commit-buffer
switch-A /eth-uplink/fabric/interface #
```

Related Commands

Command	Description
show interface	
show port-channel	

set host-fw-policy

To set the host firmware policy, use the **set host-fw-policy** command.

set host-fw-policy *name*

Syntax Description

<i>name</i>	Host firmware policy name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to associate the specified host firmware policy with the service profile you used to enter service profile mode.

Examples

This example shows how to set the host firmware policy:

```
switch-A# scope org org10
switch-A /org # scope service-profile servProf10
switch-A /org/service-profile # set host-fw-policy hostFP10
switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show assoc	
show service-profile	

set http port

To set up an HTTP port, use the **set http port** command.

set http port *port*

Syntax Description

<i>port</i>	Port identification number. The range of valid values is 1 to 65535.
-------------	--

Command Default

None

Command Modes

Services (/system/services)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Cisco recommends that you enable only the communication services that are required to interface with other network applications.

Examples

This example shows how to set up an HTTP port:

```
switch-A#scope system
switch-A /system # scope services
switch-A /system/services # set http port 100
switch-A /system/services* # commit-buffer
switch-A /system/services #
```

Related Commands

Command	Description
show cimxml	
show http	

set https keyring

To set up an HTTPS keyring, use the **set https keyring** command.

set https keyring *keyring*

Syntax Description	<i>keyring</i> Keyring name. The range of valid values is 1 to 16.							
Command Default	None							
Command Modes	Services (/system/services)							
Command History	<table><tr><th>Release</th><th>Modification</th></tr><tr><td>1.0(1)</td><td>This command was introduced.</td></tr></table>		Release	Modification	1.0(1)	This command was introduced.		
Release	Modification							
1.0(1)	This command was introduced.							
Usage Guidelines	When the HTTPS keyring is modified using the set https keyring command, all current HTTP and HTTPS sessions will be closed without any warning.							
Examples	<p>This example shows how to set up an HTTPS keyring:</p> <pre>switch-A#scope system switch-A /system # scope services switch-A /system/services # set https keyring kr100 switch-A /system/services* # commit-buffer switch-A /system/services #</pre>							
Related Commands	<table><tr><th>Command</th><th>Description</th></tr><tr><td>show http</td><td></td></tr><tr><td>show keyring</td><td></td></tr></table>		Command	Description	show http		show keyring	
Command	Description							
show http								
show keyring								

set https port

To set up an HTTPS port, use the **set https port** command.

set https port *port*

Syntax Description	<table> <tr> <th><i>port</i></th><th>Port identification number. The range of valid values is 1 to 65535.</th></tr> </table>	<i>port</i>	Port identification number. The range of valid values is 1 to 65535.
<i>port</i>	Port identification number. The range of valid values is 1 to 65535.		

Command Default

None

Command Modes

Services (/system/services)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Cisco recommends that you enable only the communication services that are required to interface with other network applications.

Examples

This example shows how to set up an HTTP port:

```
switch-A#scope system
switch-A /system # scope services
switch-A /system/services # set https port 200
switch-A /system/services* # commit-buffer
switch-A /system/services #
```

Related Commands

Command	Description
show cimxml	
show http	

set ipmi-access-profile

To set the IPMI access profile, use the **set ipmi-access-profile** command.

set ipmi-access-profile *name*

Syntax Description

<i>name</i>	IPMI access profile name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to associate the specified IPMI access profile with the service profile you used to enter service profile mode.

Examples

This example shows how to set the IPMI access profile:

```
switch-A# scope org org10
switch-A /org # scope service-profile servProf10
switch-A /org/service-profile # set ipmi-access-profile iaP10
switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show association	
show service-profile	

set key

To set up a key, use the **set key** command.

set key

This command has no arguments or keywords.

Command Default

None

Command Modes

Server under TACACS (/security/tacacs/server)

Server under LDAP (/security/ldap/server)

Server under RADIUS (/security/radius/server)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

When you execute **set key**, the prompt **Enter the key:** appears on the command line. When you enter the key at the prompt and then press Enter, the prompt **Confirm the key:** appears. Confirm the key and then press Enter again. The key is set.

Examples

This example shows how to set up a key:

```
switch-A#scope security
switch-A /security # scope ldap
switch-A /security/ldap # scope server s100
```

```
switch-A /security/ldap/server # set key
Enter the key:
Confirm the key:
switch-A /security/ldap/server* # commit-buffer
switch-A /security/ldap/server #
```

Related Commands

Command	Description
show ldap	
show server	

set lastname

To set the user name last name, use the **set lastname** command.

set lastname *name*

Syntax Description

<i>name</i>	Last name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Local user (/security/local-user)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set the user name last name:

```
switch-A#scope security
switch-A /security # scope local-user lul
switch-A /security/local-user # set lastname foo
switch-A /security/local-user* # commit-buffer
switch-A /security/local-user #
```

Related Commands

Command	Description
show local-user	
show remote-user	

set local-disk-policy

To set the local disk policy, use the **set local-disk-policy** command.

set local-disk-policy *name*

Syntax Description

<i>name</i>	Local disk policy name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0	This command was introduced.

Usage Guidelines

Use this command to associate the specified local disk policy with the service profile you used to enter service profile mode.

Examples

This example shows how to set the local disk policy:

```
switch-A# scope org org10
switch-A /org # scope service-profile servProf10
switch-A /org/service-profile # set local-disk-policy ldiskP10
switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show association	
show service-profile	

set lun

To set a LUN name, use the **set lun** command.

set lun *name*

Syntax Description

<i>name</i>	LUN name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

SAN image path (/org/boot-policy/storage/san-image/path)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set a LUN name:

```
switch-A# scope org org3
switch-A /org # scope boot-policy bp10a
switch-A /org/boot-policy # scope storage
switch-A /org/boot-policy/storage # scope san-image primary
switch-A /org/boot-policy/storage/san-image # scope path primary
switch-A /org/service-profile/storage/san-image/path # set lun lun100
switch-A /org/service-profile/path* # commit-buffer
switch-A /org/service-profile/path #
```

Related Commands

Command	Description
show path	
show storage	

set maxcap

To set the maximum capacity, use the **set maxcap** command.

set maxcap { *max-cap* | **unspecified** }

Syntax Description

<i>max-cap</i>	Maximum capacity. The range of valid values is 0 to 9223372036854775807.
unspecified	Specifies unspecified capacity.

Command Default

None

Command Modes

Storage (/org/server-qual/storage)
Memory (/org/server-qual/memory)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the maximum capacity of the memory array.

Examples

This example shows how to set the maximum capacity:

```
switch-A# scope org org3
switch-A /org # scope server-qual sq3
switch-A /org/server-qual # scope storage
switch-A /org/service-qual/storage # set maxcap 10000000
switch-A /org/service-qual/storage* # commit-buffer
switch-A /org/service-qual/storage #
```

Related Commands

Command	Description
show memory	
show storage	

set maxcores

To set the maximum number of cores, use the **set maxcores** command.

set maxcores { *max-cores* | **unspecified** }

Syntax Description

<i>max-cores</i>	Maximum number of cores. The range of valid values is 0 to 65535.
unspecified	Specifies an unspecified number of cores.

Command Default

None

Command Modes

Processor (/org/server-qual/processor)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the maximum number of processor cores.

Examples

This example shows how to set the maximum number of cores:

```
switch-A# scope org org3
switch-A /org # scope server-qual squal10
switch-A /org/server-qual # scope processor
switch-A /org/server-qual/processor # set maxcores 100
switch-A /org/server-qual/processor* # commit-buffer
switch-A /org/server-qual/processor #
```

Related Commands

Command	Description
show memory	
show processor	

set maximum

To set the maximum, use the **set maximum** command.

set maximum { *maximum* | **unspecified** }

Syntax Description

<i>maximum</i>	Maximum
unspecified	Specifies unspecified maximum.

Command Default

None

Command Modes

Capacity qualification (/org/server-qual/adapter/cap-qual)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the maximum capacity for the selected adapter type.

Examples

This example shows how to set the maximum:

```
switch-A# scope org org3
switch-A /org # scope server-qual sq100
switch-A /org/server-qual # scope adapter
switch-A /org/server-qual/adapter # scope cap-qual fcoe
switch-A /org/server-qual/adapter/cap-qual # set maximum 100
switch-A /org/server-qual/adapter/cap-qual # commit-buffer
switch-A /org/server-qual/adapter/cap-qual #
```


Related Commands

Command	Description
show adapter	
show cap-qual	

set maxprocs

To set the maximum number of processors, use the **set maxprocs** command.

set maxprocs { *maxprocs* | **unspecified** }

Syntax Description

<i>max-procs</i>	Maximum number of processors. The range of valid values is 0 to 65535.
unspecified	Specifies an unspecified number of processors.

Command Default

None

Command Modes

Processor (/org/server-qual/processor)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set the maximum number of processors:

```
switch-A# scope org org3
switch-A /org # scope server-qual squal10
switch-A /org/server-qual # scope processor
switch-A /org/server-qual/processor # set maxprocs 10
switch-A /org/server-qual/processor* # commit-buffer
switch-A /org/server-qual/processor #
```

Related Commands

Command	Description
show memory	
show processor	

set maxthreads

To set the maximum number of threads, use the **set maxthreads** command.

set maxthreads { *maxthreads* | **unspecified** }

Syntax Description

<i>max-threads</i>	Maximum number of threads. The range of valid values is 0 to 65535.
unspecified	Specifies an unspecified number of threads.

Command Default

None

Command Modes

Processor (/org/server-qual/processor)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set the maximum number of threads:

```
switch-A# scope org org3
switch-A /org # scope server-qual squal10
switch-A /org/server-qual # scope processor
switch-A /org/server-qual/processor # set maxthreads 10
switch-A /org/server-qual/processor* # commit-buffer
switch-A /org/server-qual/processor #
```

Related Commands

Command	Description
show memory	
show processor	

set mgmt-fw-policy

To set the management firmware policy, use the **set mgmt-fw-policy** command.

set mgmt-fw-policy *name*

Syntax Description

<i>name</i>	Management firmware policy name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to associate the specified management firmware policy with the service profile you used to enter service profile mode.

Examples

This example shows how to set the management firmware policy:

```
switch-A# scope org org10
switch-A /org # scope service-profile servProf10
switch-A /org/service-profile # set mgmt-fw-policy mfwP10
switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show association	
show service-profile	

set mincap

To set the minimum capacity, use the **set mincap** command.

set mincap { *mincap* | *unspec* }

Syntax Description

<i>min-cap</i>	Maximum capacity. The range of valid values is 0 to 9223372036854775807.
unspecified	Specifies unspecified capacity.

Command Default

None

Command Modes

Storage (/org/server-qual/storage)
Memory (/org/server-qual/memory)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the minimum capacity of the memory array.

Examples

This example shows how to set the minimum capacity:

```
switch-A# scope org org3
switch-A /org # scope server-qual sq3
switch-A /org/server-qual # scope storage
switch-A /org/service-qual/storage # set mincap 1000000
switch-A /org/service-qual/storage* # commit-buffer
switch-A /org/service-qual/storage #
```

Related Commands

Command	Description
show memory	
show storage	

set mincores

To set the minimum number of cores, use the **set mincores** command.

set mincores { *mincores* | **unspecified** }

Syntax Description

<i>min-cores</i>	Minimum number of cores. The range of valid values is 0 to 65535.
unspecified	Specifies an unspecified number of cores.

Command Default

None

Command Modes

Processor (/org/server-qual/processor)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the minimum number of processor cores.

Examples

This example shows how to set the minimum number of cores:

```
switch-A# scope org org3
switch-A /org # scope server-qual squal10
switch-A /org/server-qual # scope processor
switch-A /org/server-qual/processor # set mincores 2
```

```
switch-A /org/server-qual/processor* # commit-buffer
switch-A /org/server-qual/processor #
```

Related Commands

Command	Description
show memory	
show processor	

set minprocs

To set the minimum number of processors, use the **set minprocs** command.

set minprocs { *min-procs* | **unspecified** }

Syntax Description

<i>min-procs</i>	Minimum number of processors. The range of valid values is 0 to 65535.
unspecified	Specifies an unspecified number of processors.

Command Default

None

Command Modes

Processor (/org/server-qual/processor)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set the maximum number of processors:

```
switch-A# scope org org3
switch-A /org # scope server-qual squal10
switch-A /org/server-qual # scope processor
switch-A /org/server-qual/processor # set minprocs 1
switch-A /org/server-qual/processor* # commit-buffer
switch-A /org/server-qual/processor #
```

Related Commands

Command	Description
show memory	
show processor	

set minthreads

To set the minimum number of threads, use the **set minthreads** command.

set minthreads { *min-threads* | **unspecified** }

Syntax Description

<i>min-threads</i>	Minimum number of threads. The range of valid values is 0 to 65535.
unspecified	Specifies an unspecified number of threads.

Command Default

None

Command Modes

Processor (/org/server-qual/processor)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set the minimum number of threads:

```
switch-A# scope org org3
switch-A /org # scope server-qual squal10
switch-A /org/server-qual # scope processor
switch-A /org/server-qual/processor # set minthreads 1
switch-A /org/server-qual/processor* # commit-buffer
switch-A /org/server-qual/processor #
```

Related Commands

Command	Description
show memory	
show processor	

set mode

To set the mode, use the **set mode** command.

set mode { **any-configuration** | **no-local-storage** | **no-raid** | **raid-mirrored** | **raid-striped** } { **end-host** | **switch** } { **one-shot** | **staged** }

Syntax Description

any-configuration	Specifies any configuration for the local disk.
--------------------------	---

no-local-storage	Specifies no local storage.
no-raid	Specifies no RAID configuration on the local disk.
raid-mirrored	Specifies RAID mirroring on the local disk.
raid-striped	Specifies RAID striping on the local disk.
end-host	Specifies end host Ethernet switching mode.
switch	Specifies switch Ethernet switching mode.
one-shot	Specifies one shot.
staged	Specifies staged.

Usage Guidelines

The Ethernet switching mode determines how the switch behaves as a switching device between the servers. End-host mode allows the switch to act as an end host to the network, representing all server (hosts) connected to it through vNICs and the network. Switch mode is the traditional Ethernet switching mode.

Command Modes

Local disk configuration under organization (/org/local-disk-config)
 Firmware management pack (/org/fw-mgmt-pack)
 Ethernet uplink (/eth-uplink)
 Firmware host pack (/org/fw-host-pack)
 Local disk configuration under service profile (/org/service-profile/local-disk-config)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Mode eth-uplink only supports the keywords **end-host** and **switch**.
 Modes /org/fw-host-pack and /org/fw-mgmt only support the keywords **one-shot** and **staged**.
 Modes /org/service-profile/local-disk-config and /org/local-disk-config only support the keywords **any-configuration**, **no-local-storage**, **no-raid**, **raid-mirrored**, and **raid-striped**.

Examples

This example shows how to set the mode:

```
switch-A# scope eth-uplink
switch-A /eth-uplink # set mode switch
switch-A /eth-uplink* # commit-buffer
switch-A /eth-uplink #
```

set mtu

To set an Maximum Transmission Unit (MTU), use the **set mtu** command.

set mtu { *mtu* | **fc** | **normal** }

Syntax Description

<i>mtu</i>	MTU. The range of valid values is 1538 to 9216.
fc	Specifies Fibre Channel MTU.
normal	Specifies normal MTU.

Command Default

None

Command Modes

Ethernet classified (/eth-server/qos/eth-classified)

Ethernet default (/eth-server/qos/eth-default)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set an MTU:

```
switch-A# scope eth-server
switch-A /eth-server # scope qos
switch-A /eth-server/qos # scope eth-classified
switch-A /eth-server/qos/eth-classified # set mtu fc
switch-A /eth-server/qos/eth-classified* # commit-buffer
switch-A /eth-server/qos/eth-classified #
```

Related Commands

Command	Description
show eth-best-effort	
show eth-classified	

set name

To set name, use the **set name** command.

set name *name*

Syntax Description	<div><div><i>name</i></div><div>Name. The range of valid values is 1 to 16.</div></div>						
Command Default	None						
Command Modes	Port channel (/eth-uplink/fabric/port-channel)						
Command History	<table><tr><th>Release</th><th>Modification</th></tr><tr><td>1.0(1)</td><td>This command was introduced.</td></tr></table>	Release	Modification	1.0(1)	This command was introduced.		
Release	Modification						
1.0(1)	This command was introduced.						
Examples	<p>This example shows how to set a name:</p> <pre>switch-A# scope eth-uplink switch-A /eth-uplink # scope switch switch-A /eth-uplink/switch # scope port-channel 10 switch-A /eth-uplink/switch/port-channel # set name pc10 switch-A /eth-uplink/switch/port-channel* # commit-buffer switch-A /eth-uplink/switch/port-channel #</pre>						
Related Commands	<table><tr><th>Command</th><th>Description</th></tr><tr><td>show member-port</td><td></td></tr><tr><td>show port-channel</td><td></td></tr></table>	Command	Description	show member-port		show port-channel	
Command	Description						
show member-port							
show port-channel							

set numberofblocks

To set the number of blocks, use the **set numberofblocks** command.

set numberofblocks { *number* | **unspecified** }

Syntax Description	<table> <tr> <td><i>number</i></td><td>Number of storage blocks. The range of valid values is 0 to 9223372036854775807.</td></tr> <tr> <td>unspecified</td><td>Specifies an unspecified number of blocks.</td></tr> </table>	<i>number</i>	Number of storage blocks. The range of valid values is 0 to 9223372036854775807.	unspecified	Specifies an unspecified number of blocks.
<i>number</i>	Number of storage blocks. The range of valid values is 0 to 9223372036854775807.				
unspecified	Specifies an unspecified number of blocks.				
Command Default	None				
Command Modes	Storage (/org/server-qual/storage)				

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

The following example shows how to set the number of blocks:

```
switch-A# scope org org120
switch-A /org # scope server-qual sq20
switch-A /org/server-qual # scope storage
switch-A /org/server-qual/storage # set numberofblocks 100000
switch-A /org/server-qual/storage* # commit-buffer
switch-A /org/server-qual/storage #
```

Related Commands

Command	Description
show memory	
show storage	

set order

To set the order, use the **set order** command.

virtual-media, storage, vnic, and lan command modes

set order { 1 | 2 | 3 | 4 }

vhba command mode

set order { order | max | unspecified }

Syntax Description

1	Specifies first.
2	Specifies second.
3	Specifies third.
4	Specifies fourth.
<i>order</i>	Order. The range of valid values is 0 to 99.
unspecified	Unspecified order.

Command Default

None

Command Modes

Virtual media (/org/boot-policy/virtual-media)

Storage (/org/boot-policy/storage)

Virtual NIC (/org/service-profile/vnic)

Virtual HBA (/org/service-profile/vhba)

LAN (/org/boot-policy/lan)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the PCI scan order for the vNIC.

Examples

This example shows how to set the order:

```
switch-A# scope org org3
switch-A /org # scope service-profile sp100
switch-A /org/service-profile # scope vhba vhba100

switch-A /org/service-profile/vhba # set order order 10
switch-A /org/service-profile/vhba* # commit-buffer
switch-A /org/service-profile/vhba #
```

Related Commands

Command	Description
show vhba	
show vnic	

set password

To set up a password, use the **set password** command.

set password

This command has no arguments or keywords.

Command Default

None

Command Modes

End point user (/org/ipmi-access-profile/epuser)

Backup (/system/backup)

Import configuration (/system/import-config)

Local user (/security/local-user)

Security (/security)

Download task (/firmware/download-task)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

The password must be a minimum of eight characters.

After entering the set password command, you are prompted to enter and confirm the password. For security purposes, the password that you type does not appear in the CLI.

Examples

This example shows how to set up a password:

```
switch-A#scope security
switch-A /security # set password
Enter the password:
Confirm the password:
switch-A /security* # commit-buffer
switch-A /security #
```

Related Commands

Command	Description
show local-user	
show remote-user	

set perdiskcap

To set per-disk capacity, use the **set perdiskcap** command.

set perdiskcap { *number* | **unspecified** }

Syntax Description

<i>number</i>	Capacity number. The range of valid values is 0 to 9223372036854775807.
unspecified	Specifies an unspecified amount of capacity.

Command Default

None

Command Modes

Storage (/org/server-qual/storage)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

The following example shows how to set the per-disk capacity:

```
switch-A# scope org org120
switch-A /org # scope server-qual sq20
switch-A /org/server-qual # scope storage
switch-A /org/server-qual/storage # set perdiskcap 110000
switch-A /org/server-qual/storage* # commit-buffer
switch-A /org/server-qual/storage #
```

Related Commands

Command	Description
show memory	
show storage	

set pers-bind

To disable or enable persistent binding, use the **set pers-bind** command.

set pers-bind { disabled | enabled }

Syntax Description

disabled	Specifies binding disabled.
enabled	Specifies binding enabled.

Command Default

None

Command Modes

Virtual HBA (/org/service-profile/vhba)

Command History

Release	Modification
1.0	This command was introduced.

Usage Guidelines

Use this command to disable or enable persistent binding to fibre channel targets.

Examples

This example shows how to disable or enable persistent binding:

```
switch-A# scope org org30a
switch-A /org # scope service-profile sp101
switch-A /org/service-profile # scope vhba vhba17
switch-A /org/service-profile/vhba # set pers-bind enabled
switch-A /org/service-profile/vhba* # commit-buffer
switch-A /org/service-profile/vhba #
```

Related Commands

Command	Description
show vhba	
show vnic	

set phone

To set the phone user name, use the **set phone** command.

set phone *name*

Syntax Description

<i>name</i>	Name of the user. The range of valid values is 1 to 512.
-------------	--

Command Default

None

Command Modes

Local user (/security/local-user)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set the phone user name:

```
switch-A# scope security
switch-A /security # scope local-user admin10
switch-A /security/local-user # set phone admin10
switch-A /security/local-user* # commit-buffer
switch-A /security/local-user #
```

Related Commands

Command	Description
show local-user	
show user-sessions	

set pin-group

To set the pin group, use the **set pin-group** command.

set pin-group *name*

Syntax Description	<i>name</i> Pin group name. The range of valid values is 1 to 16.							
Command Default	None							
Command Modes	Hypervisor connectivity (/org/service-profile/hv-conn) Virtual HBA (/org/service-profile/vhba) Virtual NIC (/org/service-profile/vnic) Virtual HBA template (/org/vhba-templ) Virtual NIC (/org/vnic-templ) Dynamic connection policy (/org/dynamic-conn-policy)							
Command History	<table><tr><th>Release</th><th>Modification</th></tr><tr><td>1.0(1)</td><td>This command was introduced.</td></tr></table>		Release	Modification	1.0(1)	This command was introduced.		
Release	Modification							
1.0(1)	This command was introduced.							
Usage Guidelines	Use this command to specify the pin group to use for the vNIC.							
Examples	This example shows how to set the pin group: switch-A# scope org org10 switch-A /org # scope service-profile sp10 switch-A /org/service-profile # scope vnic vnic20 switch-A /org/service-profile/vnic # set pin-group pgl switch-A /org/service-profile/vnic* # commit-buffer switch-A /org/service-profile/vnic #							
Related Commands	<table><tr><th>Command</th><th>Description</th></tr><tr><td>show eth-if</td><td></td></tr><tr><td>show vnic</td><td></td></tr></table>		Command	Description	show eth-if		show vnic	
Command	Description							
show eth-if								
show vnic								

set pool

To set a pool, use the **set pool** command.

set pool *name*

Syntax Description	<i>name</i> Pool name. The range of valid values is 1 to
---------------------------	--

Command Default

None

Command Modes

Pooling policy (/org/pooling-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to add a pool to your pooling policy. Only one pool can be set for each pooling policy.

Examples

This example shows how to set a pool:

```
switch-A# scope org org3
switch-A /org # scope pooling-policy pp100
switch-A /org/pooling-policy # set pool pool100
switch-A /org/pooling-policy* # commit-buffer
switch-A /org/pooling-policy #
```

Related Commands

Command	Description
show mac-pool	
show pooling-policy	

set port

To set the port number, use the **set port** command.

set port *number*

Syntax Description

<i>number</i>	Port number. The range of valid values is 1 to 65535.
---------------	---

Command Modes

Callhome (/monitoring/callhome)
 Server under LDAP (/security/ldap/server)
 SNMP host (/monitoring/snmp host)
 Server under TACACS (/security/tacacs/server)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the port used to communicate with the LDAP server.

Examples

This example shows how to set the port number:

```
switch-A#scope security
switch-A /security # scope ldap
switch-A /security/ldap # scope server s100
switch-A /security/ldap/server # set port 100
switch-A /security/ldap/server* # commit-buffer
switch-A /security/ldap/server #
```

Related Commands

Command	Description
show ldap	
show server	

set prio

To set priority, use the **set prio** command.

set prio { auto | on }

Syntax Description

auto	Specifies automatic prio.
on	Specifies prio on.

Command Default

None

Command Modes

Flow control policy (/eth-uplink/flow-control/policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set priority:

```
switch-A# scope eth-uplink
switch-A /eth-uplink # scope flow-control
switch-A /eth-uplink/flow-control # scope policy
switch-A /eth-uplink/flow-control/policy # set prio on
switch-A /eth-uplink/flow-control/policy* # commit-buffer
switch-A /eth-uplink/flow-control/policy #
```

Related Commands

Command	Description
show policy	
show stats-threshold-policy	

set qos-policy

To set the QoS policy, use the **set qos-policy** command.

set qos-policy *name*

Syntax Description

<i>name</i>	QoS policy name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Virtual NIC template (/org/vnic-templ)
 Virtual HBA (/org/service-profile/vhba)
 Virtual NIC (/org/service-profile/vnic)
 Port profile (/eth-uplink/port-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the QoS policy to use for the vNIC.

Examples

This example shows how to set the QoS policy:

```
switch-A# scope org org30
switch-A /org # scope vnic-templ vnict10
switch-A /org/vnic-templ # set qos-policy qp10
switch-A /org/vnic-templ* # commit-buffer
switch-A /org/vnic-templ #
```

Related Commands

Command	Description
show eth-if	
show qos-policy	

set qualifier

To set a qualifier, use the **set qualifier** command.

set qualifier *name*

Syntax Description	<table> <tr> <td><i>name</i></td><td>Qualifier name. The range of valid values is 1 to 16.</td></tr> </table>	<i>name</i>	Qualifier name. The range of valid values is 1 to 16.				
<i>name</i>	Qualifier name. The range of valid values is 1 to 16.						
Command Default	None						
Command Modes	Server inherit policy (/org/server-inherit-policy) Server discovery policy (/org/server-disc-policy) Pooling policy (/org/pooling-policy) Chassis discovery policy (/org/chassis-disc-policy) Automatic configuration policy (/org/autoconfig-policy)						
Command History	<table> <tr> <th>Release</th><th>Modification</th></tr> <tr> <td>1.0(1)</td><td>This command was introduced.</td></tr> </table>	Release	Modification	1.0(1)	This command was introduced.		
Release	Modification						
1.0(1)	This command was introduced.						
Usage Guidelines	Use this command to add a qualifier to your policy. Only one qualifier can be set for each policy.						
Examples	This example shows how to set a qualifier: <pre>switch-A# scope org org3 switch-A /org # scope server-disc-policy sdp100 switch-A /org/server-disc-policy # set qualifier q100 switch-A /org/server-disc-policy* # commit-buffer switch-A /org/server-disc-policy #</pre>						
Related Commands	<table> <tr> <th>Command</th><th>Description</th></tr> <tr> <td>show pooling policy</td><td></td></tr> <tr> <td>show server-disc-policy</td><td></td></tr> </table>	Command	Description	show pooling policy		show server-disc-policy	
Command	Description						
show pooling policy							
show server-disc-policy							

set reboot-on-update

To set reboot on updates, use the **set reboot-on-update** command.

set reboot-on-update { no | yes }

Syntax Description	no	Specifies no reboot on updates.
	yes	Specifies reboot on updates.
Command Default	None	
Command Modes	Boot policy (/org/boot-policy) Boot definition (/org/service-profile/boot-def)	
Command History	Release	Modification
	1.0(1)	This command was introduced.
Examples	This example shows how to set reboot on updates: <pre> switch-A# scope org org3 switch-A /org # scope boot-policy bp112 switch-A /org/boot-policy # set reboot-on-update yes switch-A /org/boot-policy* # commit-buffer switch-A /org/boot-policy # </pre>	
Related Commands	Command	Description
	show boot-policy	
	show storage	

set receive

To set receive, use the **set receive** command.

set receive { off | on }

Syntax Description	off	Specifies receive off.
	on	Specifies receive on.
Command Default	None	
Command Modes	Flow control policy (/eth-uplink/flow-control/policy)	

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify flow control receive options.

When you specify **off**, pause requests from the network are ignored and traffic flow continues as normal.

When you specify **on**, pause requests are honored and all traffic is halted on that uplink port until the network cancels the pause request

Examples

This example shows how to set receive:

```
switch-A# scope eth-uplink
switch-A /eth-uplink # scope flow-control
switch-A /eth-uplink/flow-control # scope policy fcpolicy110
switch-A /eth-uplink/flow-control/policy # set receive on
switch-A /eth-uplink/flow-control/policy* # commit-buffer
switch-A /eth-uplink/flow-control/policy #
```

Related Commands

Command	Description
show stats-threshold-policy	
show policy	

set retries

To set the number of retries, use the **set retries** command.

set retries *number*

Syntax Description

<i>number</i>	Number of retries. The range of valid values is 0 to 5.
---------------	---

Command Default

None

Command Modes

RADIUS (/security/radius)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to set the number of times to retry communicating with the RADIUS server before noting the server as down.

Examples

This example shows how to set the number of retries:

```
switch-A#scope security
switch /security # scope radius
switch /security/radius # set retries 3
switch /security/radius* # commit-buffer
switch /security/radius #
```

Related Commands

Command	Description
show ldap	
show radius	

set rootdn

To set a root distinguished name, use the **set rootdn** command.

set rootdn *name*

Syntax Description

<i>name</i>	Root distinguished name. The range of valid values is 1 to 127.
-------------	---

Command Default

None

Command Modes

Server (/security/ldap/server)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the distinguished name for the LDAP database superuser account.

Examples

This example shows how to set a root distinguished name:

```
switch-A#scope security
switch-A /security # scope ldap
switch-A /security/ldap # scope server s100
switch-A /security/ldap/server # set rootdn administrator
switch-A /security/ldap/server* # commit-buffer
switch-A /security/ldap/server #
```

Related Commands

Command	Description
show ldap	
show server	

set scrub-policy

To set the scrub policy, use the **set scrub-policy** command.

set scrub-policy *name*

Syntax Description

<i>name</i>	Scrub policy name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Server discovery policy (/org/server-disc-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to associate the specified scrub policy with the service profile you used to enter service profile mode.

Examples

This example shows how to set the scrub policy:

```
switch-A# scope org org10
switch-A /org # scope server-disc-policy sdp100
switch-A /org/server-disc-policy # set scrub-policy scrub101

switch-A /org/server-disc-policy* # commit-buffer
switch-A /org/server-disc-policy #
```

Related Commands

Command	Description
show scrub-policy	
show server-disc-policy	

set send

To set send, use the **set send** command.

set send { off | on }

Syntax Description

off	Specifies send off.
on	Specifies send on.

Command Default

None

Command Modes

Flow control policy (/eth-uplink/flow-control-policy)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify flow control send options.

When you specify **off**, traffic on the port flows normally regardless of the packet load.

When you specify **on**, the UCS system sends a pause request to the network if the incoming packet rate becomes too high. The pause remains in effect for a few milliseconds before traffic is reset to normal levels.

Examples

This example shows how to set send:

```
switch-A# scope eth-uplink
switch-A /eth-uplink # scope flow-control
switch-A /eth-uplink/flow-control # scope policy fcpolicy110
switch-A /eth-uplink/flow-control/policy # set send on
switch-A /eth-uplink/flow-control/policy* # commit-buffer
switch-A /eth-uplink/flow-control/policy #
```

Related Commands

Command	Description
show stats-threshold-policy	
show policy	

set snmp community

To set up an SNMP community, use the **set snmp community** command.

set snmp community *community*

Syntax Description	<div>community</div> <div>Community name. The range od valid values is 1 to 512.</div>							
Command Default	None							
Command Modes	Monitoring (/monitoring)							
Command History	<table><tr><th>Release</th><th>Modification</th></tr><tr><td>1.0(1)</td><td>This command was introduced.</td></tr></table>		Release	Modification	1.0(1)	This command was introduced.		
Release	Modification							
1.0(1)	This command was introduced.							
Usage Guidelines	<p>Cisco recommends that you enable only the communication services that are required to interface with other network applications.</p> <p>The community name can be any alphanumeric string. Enter this command multiple times to create multiple community strings.</p>							
Examples	<p>This example shows how to set up an SNMP community:</p> <pre>switch-A#scope monitoring switch-A /monitoring # set snmp community snmpcom10 switch-A /monitoring* # commit-buffer switch-A /monitoring #</pre>							
Related Commands	<table><tr><th>Command</th><th>Description</th></tr><tr><td>show callhome</td><td></td></tr><tr><td>show snmp-trap</td><td></td></tr></table>		Command	Description	show callhome		show snmp-trap	
Command	Description							
show callhome								
show snmp-trap								

set sol-policy

To set the serial over LAN (SoL) policy, use the **set sol-policy** command.

set sol-policy *name*

Syntax Description	<table> <tr> <th><i>name</i></th><th>SoL policy name. The range of valid values is 1 to 16.</th></tr> </table>	<i>name</i>	SoL policy name. The range of valid values is 1 to 16.
<i>name</i>	SoL policy name. The range of valid values is 1 to 16.		
Command Default	None		

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to associate the specified SoL policy with the service profile you used to enter service profile mode.

Examples

This example shows how to set the SoL policy:

```
switch-A# scope org org110
switch-A /org # scope service-profile spEast110
switch-A /org/service-profile # set sol-policy apEast110

switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show sol-config	
show sol-policy	

set speed

To set the speed, use the **set speed** command.

memory mode

set speed { *speed* | **unspec** }

sol-config and sol-policy modes

set speed { **115200** | **19200** | **38400** | **57600** | **9600** }

Syntax Description

<i>speed</i>	Baud rate. The range of valid values is 0 to 65535.
unspec	Specifies unspecified baud rate.
115200	Specifies 115200 baud rate.
19200	Specifies 19200 baud rate.
38400	Specifies 38400 baud rate.

57600	Specifies 57600 baud rate.
9600	Specifies 9600 baud rate.

Command Default

None

Command Modes

/org/server-qual/memory
 /org/service-profile/sol-config
 /org/sol-policy

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the memory data rate.

Examples

This example shows how to set the speed:

```
switch-A# scope org org10
switch-A /org # scope service-profile sp10
switch-A /org/service-profile # scope sol-config
switch-A /org/service-profile/sol-config # set speed 9600
switch-A /org/service-profile/sol-config* # commit-buffer
switch-A /org/service-profile/sol-config #
```

Related Commands

Command	Description
show memory	
show sol-config	

set src-templ-name

To set the source template name, use the **set src-templ-name** command.

set src-templ-name *name*

Syntax Description

<i>name</i>	Source template name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Service profile (/org/service-profile)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to associate the specified source template with the service profile you used to enter service profile mode.

Examples

This example shows how to set the source template name:

```
switch-A# scope org org110
switch-A /org # scope service-profile spEast110
switch-A /org/service-profile # set src-templ-name srcTemplateName110

switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show service-policy	
show vhma-templ	

set sshkey

To set an SSH key, use the **set sshkey** command.

set sshkey [*key* | none]

Syntax Description

<i>key</i>	SSH key.
------------	----------

Command Default

None

Command Modes

Security (/security)
Local user (/security/local-user)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the SSH key used for passwordless access.

Examples

This example shows how to set an SSH key:

```
switch-A# scope security
switch-A /security # set sshkey "ssh-rsa
AAAAB3NzaC1yc2EAAAABIwAAAIEAuo9VQ2CmWBI9/S1f30k1CWjnV3lgdXMzO0W
U15iPw85lkdQqap+NFuNmHcb4K iaQB8X/PDdmt1xQQcawclj+k8f4VcOelBxls
Gk5luq5ls1ob1VOIEwcKEL/h5lrdBN1I8y3SS9I/gGiBZ9ARlop9LDpD m8HPh2
LOgyH7EilMI8="
switch-A /security* # commit-buffer
switch-A /security #
```

Related Commands

Command	Description
show keyring	
show trustpoint	

set ssl

To set up SSL on a server, use the **set ssl** command.

set ssl { no | yes }

Syntax Description

no	Specifies no SSL.
yes	Specifies SSL.

Command Modes

Servre (/security/ldap/server)

Command History

Release	Modification
1.0	This command was introduced.

Usage Guidelines

Use this command to enable or disable the use of SSL when communicating with the LDAP server.

Examples

This example shows how to set up SSL on a server:

```
switch#scope security
switch /security # scope ldap
switch /security/ldap # scope server s100
switch /security/ldap/server # set ssl yes
switch /security/ldap/server* # commit-buffer
switch /security/ldap/server #
```

Related Commands

Command	Description
show ldap	
show server	

set stats-policy

To set the statistics policy, use the **set stats-policy** command.

set stats-policy *name*

Syntax Description

<i>name</i>	Statistics policy name. The range of valid values is 1 to 16.
-------------	---

Command Default

None

Command Modes

Virtual NIC template (/org/vnic-templ)
 Virtual NIC (/org/service-profile/vnic)
 Service profile (/org/service-profile)
 Virtual HBA template (/org/vhba-templ)
 Virtual HBA (/org/service-profile/vhba)

Command History

Release	Modification
1.0(1)	This command was introduced.

Use this command to associate the specified statistics policy with the service profile you used to enter service profile mode, or the template you used to enter virtual NIC template or virtual HBA template modes.

Examples

This example shows how to set the statistics policy:

```
switch-A# scope org org110
switch-A /org # scope service-profile spEast110
switch-A /org/service-profile # set stats-policy statsEast110

switch-A /org/service-profile* # commit-buffer
switch-A /org/service-profile #
```

Related Commands

Command	Description
show service-profile	
show stats-threshold-policy	

set stepping

To set stepping, use the **set stepping** command.

set stepping { *number* | **unspecified** }

Syntax Description

<i>number</i>	Stepping number. The range of valid value is 0 to 4294967295.
unspecified	Specifies an unspecified stepping number.

Command Default

None

Command Modes

Processor (/org/server-qual/processor)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the processor stepping number.

Examples

This example shows how to set the minimum number of cores:

```
switch-A# scope org org3
switch-A /org # scope server-qual squal10
switch-A /org/server-qual # scope processor
switch-A /org/server-qual/processor # set stepping 1
switch-A /org/server-qual/processor* # commit-buffer
switch-A /org/server-qual/processor #
```

Related Commands

Command	Description
show memory	
show processor	

set syslog console

To set the syslog console, use the **set syslog console** command.

set syslog console { state { disabled | enabled } | level { alerts | critical | emergencies } } +

Syntax Description

state	Specifies the state of the syslog console.
disabled	Specifies disable syslog console.
enabled	Specifies enable syslog console.
level	Specifies the level of the syslog message.
alerts	Specifies alert level.
critical	Specifies critical level.
emergencies	Specifies emergency level.

Command Default

Disabled.

Command Modes

Monitoring (/monitoring)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to enable the syslog console. Enabling the console allows the operating to generate system log messages. You can also use this command to set the level of syslog console messages.

When you enable the syslog console, the default for Level is Critical.

Examples

This example shows how to set the syslog console:

```
switch-A# scope monitoring
switch-A /monitoring # set syslog console state enabled

switch-A # /monitoring* commit-buffer
switch-A # /monitoring
```

Related Commands

Command	Description
show callhome	
show syslog	

set syslog file

To set the syslog file, use the **set syslog file** command.

set syslog file { **state** { **disabled** | **enabled** } | **level** { **alerts** | **critical** | **debugging** | **emergencies** | **errors** | **information** | **notifications** | **warnings** } | **name** *name* | **size** *size* } +

Syntax Description

state	Specifies the state of the syslog file.
disabled	Specifies syslog file disabled.
enabled	Specifies syslog file enabled.
level	Specifies the level of the syslog message.
alerts	Specifies alert level.
critical	Specifies critical level.
debugging	Specifies debug level.
emergencies	Specifies emergency level.
errors	Specifies error level.
information	Specifies information level.
notifications	Specifies notification level.
warnings	Specifies warning level.
name	Specify file name.
<i>name</i>	Name of the file. The range of valid values is 1 to 16.
size	Specify file size.
<i>size</i>	File size. The range of valid values is 4096 to 10485760.

Command Default

Disabled.

Command Modes

Monitoring (/monitoring)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to enable the syslog file. Enabling the file allows the operating system to place messages in a syslog file. You can also use this command to set the level of syslog file messages.

When you enable the syslog file, the default for Level is Critical and the default for Size is 10485760.

Examples

This example shows how to set the syslog file:

```
switch-A# scope monitoring
switch-A /monitoring # set syslog file state enabled

switch-A # /monitoring* commit-buffer
switch-A # /monitoring
```

Related Commands

Command	Description
show callhome	
show syslog	

set syslog min-level

To set the minimum level for syslog messages, use the **set syslog min-level** command.

set syslog min-level { crit | debug0 | debug1 | debug2 | debug3 | debug4 | info | major | minor | warn }

Syntax Description

crit	Specifies minimum level as critical.
debug0	Specifies minimum level as debug 0.
debug1	Specifies minimum level as debug 1.
debug2	Specifies minimum level as debug 2.
debug3	Specifies minimum level as debug 3.
debug4	Specifies minimum level as debug 4.
info	Specifies minimum level as information.
major	Specifies minimum level as major.
minor	Specifies minimum level as minor.
warn	Specifies minimum level as warning.

Command Default

Minimum level is not set.

Command Modes

Management logging (/monitoring/sysdebug/mgmt-logging)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set the minimum level for syslog messages:

```
switch-A#scope monitoring
switch-A /monitoring # scope sysdebug

switch-A /monitoring/sysdebug # scope mgmt-logging
switch-A /monitoring/sysdebug/mgmt-logging # scope mgmt-logging
switch-A /monitoring/sysdebug/mgmt-logging # set syslog min-level crit
switch-A /monitoring/sysdebug/mgmt-logging* # commit-buffer
switch-A /monitoring/sysdebug/mgmt-logging #
```

Related Commands

Command	Description
show fsm	
show syslog	

set syslog monitor

To set the syslog monitor, use the **set syslog monitor** command.

set syslog monitor { state { disabled | enabled } | level { alerts | critical | debugging | emergencies | errors | information | notifications | warnings } } +

Syntax Description

state	Specifies the state of the syslog monitor.
disabled	Specifies disable syslog monitor.
enabled	Specifies enable syslog monitor.
level	Specifies the level of the syslog message.
alerts	Specifies alert level.
critical	Specifies critical level.
debugging	Specifies debug level.
emergencies	Specifies emergency level.
errors	Specifies error level.
information	Specifies information level.

notifications	Specifies notification level.
warnings	Specifies warning level.

Command Default

Disabled.

Command Modes

Monitoring (monitoring)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to enable the syslog monitor. Enabling the monitor allows the operating system to monitor syslog messages. You can also use this command to set the level of syslog file messages.

When you enable the syslog file, the default for Level is Critical.

Examples

This example shows how to set the syslog monitor:

```
switch-A# scope monitoring
switch-A /monitoring # set syslog monitor state enabled

switch-A # /monitoring* commit-buffer
switch-A # /monitoring
```

Related Commands

Command	Description
show callhome	
show syslog	

set syslog remote-destination

To set syslog remote destination, use the **set syslog remote-destination** command.

set syslog remote-destination { server-1 | server-2 | server-3 } { state { disabled | enabled } | level { alerts | critical | debugging | emergencies | errors | information | notifications | warnings } | hostname *hostname* | facility { local0 | local1 | local2 | local3 | local4 | local5 | local6 | local7 } } +

Syntax Description

server-1	Specifies server 1.
server-2	Specifies server 2.
server-3	Specifies server 3.

state	Specifies the state of syslog remote destination.
disabled	Specifies disable syslog remote destination.
enabled	Specifies enable syslog remote destination.
level	Specifies the level of the syslog message.
alerts	Specifies alert level. Set to 1 .
critical	Specifies critical level. Set to 2 .
debugging	Specifies debug level. Set to 7 .
emergencies	Specifies emergency level. Set to 0 .
errors	Specifies error level. Set to 3 .
information	Specifies information level. Set to 6 .
notifications	Specifies information level. Set to 5 .
warnings	Specifies warning level. Set to 4 .
hostname	Specifies host name.
<i>hostname</i>	Host name. The range of valid values is 1 to 256.
facility	Specifies the facility.
local0	Specifies local facility 0.
local1	Specifies local facility 1.
local2	Specifies local facility 2.
local3	Specifies local facility 3.
local4	Specifies local facility 4.
local5	Specifies local facility 5.
local6	Specifies local facility 6.
local7	Specifies local facility 7.

Command Default

None

Command Modes

Monitoring (/monitoring)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to enable syslog remote destination. When you enable syslog remote destination, the default for Hostname is None.

Examples

This example shows how to set syslog remote destination:

```
switch-A# scope monitoring
switch-A /monitoring # set syslog remote-destination server-1 hostname ITEast1

switch-A # /monitoring* commit-buffer
switch-A # /monitoring
```

Related Commands

Command	Description
show callhome	
show syslog	

set target

To set a target, use the **set target** command.

set target { a | b } {port slot-id/port-id | port-channel id }

Syntax Description

a	Specifies switch A.
b	Specifies switch B.
port	Specifies port.
slot-id/port-id	Specifies the slot and port identification number.
port-channel	Specifies port channel.
id	Specifies the port channel identification number.

Command Default

None

Command Modes

Pin group under Fibre Channel uplink (/fc-uplink/pin-group)
Pin group under Ethernet uplink (/eth-uplink/pin-group)

Command History	Release	Modification
	1.0(1)	This command was introduced.
Usage Guidelines	Use this command to set the Fibre Channel or Ethernet pin target to the specified switch and port, or switch and port channel. Scope to /fc-uplink/pin-group to set the Fibre Channel pin target. Scope to /eth-uplink/pin-group to set the Ethernet pin target.	
Examples	<p>This example shows how to set a target:</p> <pre>switch-A# scope eth-uplink switch-A /eth-uplink # scope pin-group pinGroupOne switch-A /eth-uplink/pin-group # set target a port 1/1 switch-A /eth-uplink/pin-group* # commit-buffer switch-A /eth-uplink/pin-group #</pre>	
Related Commands	Command	Description
	show pin-group	
	show target	

set template-name

To set the template name, use the **set template-name** command.

set template-name *name*

Syntax Description	<i>name</i>	Template name. The range of valid values is 1 to 16.
Command Default	None	
Command Modes	vNIC (/org/service-profile/vnic)	
Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples

This example

```
switch-A# scope org org10
switch-A /org # scope service-profile sp10
switch-A /org/service-profile # scope vnic vnic10
switch-A /org/service-profile/vnic # set template-name temp10
switch-A /org/service-profile/vnic* # commit-buffer
switch-A /org/service-profile/vnic #
```

Related Commands

Command	Description
show vhba	
show vnic	

set timeout

To set a timeout, use the **set timeout** command.

set timeout *timeout*

Syntax Description

<i>timeout</i>	Timeout interval, in seconds. The range of valid values is 1 to 60.
----------------	---

Command Default

None

Command Modes

TACACS (/security/tacacs)
 RADIUS (/security/radius)
 LDAP (/security/ldap)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set a timeout:

```
switch-A#scope security
switch-A /security # scope ldap
switch-A /security/ldap # set timeout 30
switch-A /security/ldap* # commit-buffer
switch-A /security/ldap #
```

Related Commands

Command	Description
show ldap	

Command	Description
show tacacs	

set units

To set memory units, use the **set units** command.

set units { *units* | **unspec** }

Syntax Description

<i>units</i>	Memory units. The range of valid values is 0 to 65535.
unspec	Specifies unspecified memory units.

Command Default

None

Command Modes

/org/server-qual/memory
/org/server-qual/storage

Command History

Release	Modification
1.0	This command was introduced.

Usage Guidelines

Memory units refer to the DRAM chips mounted on the PCB.

Examples

This example shows how to set memory units:

```
switch-A# scope org org10
switch-A /org # scope server-qual squal10
switch-A /org/server-qual # scope memory
switch-A /org/server-qual/memory # set units 1000
switch-A /org/server-qual/memory* # commit-buffer
switch-A /org/server-qual/memory #
```

Related Commands

Command	Description
show memory	
show storage	

set version

To set the version number, use the **set version** command.

set version *number*

Syntax Description

<i>number</i>	Version number.
---------------	-----------------

Command Default

None

Command Modes

Pack image (/org/fw-host-pack/pack-image)

Command History

Release	Modification
1.0(1)	This command was introduced.

Usage Guidelines

Use this command to specify the package image version number. Changing this number triggers firmware updates on all components using the firmware through a service profile.

Examples

This example shows how to set the version number:

```
switch-A# scope org org100
switch-A /org # scope fw-host-pack fhp10
switch-A /org/fw-host-pack # scope pack-image pi10
switch-A /org/fw-host-packpack-image # set version 1.3
switch-A /org/fw-host-packpack-image* # commit-buffer
switch-A /org/fw-host-packpack-image #
```

Related Commands

Command	Description
show pack-image	
show version	

set vhb

To set a vHBA, use the **set vhb** command.

set vhb *name*

Syntax Description

<i>name</i>	vHBA name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes Path (/org/boot-policy/storage/san-image/path)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples This example shows how to set a vHBA:

```
switch-A# scope org org3
switch-A /org # scope boot-policy boot1
switch-A /org/boot-policy # scope storage
switch-A /org/boot-policy/storage # scope san-image primary
switch-A /org/boot-policy/storage/san-image # scope path primary
switch-A /org/boot-policy/storage/san-image/path # set vhba vhb100
switch-A /org/boot-policy/storage/san-image/path* # commit-buffer
switch-A /org/boot-policy/storage/san-image/path #
```

Related Commands	Command	Description
	show interface	
	show vhma	

set virtual-ip

To set up a virtual IP address, use the **set virtual-ip** command.

set virtual-ip *address*

Syntax Description	<i>address</i>	Virtual IP address. Enter the argument in the format A.B.C.D.

Command Default None

Command Modes System (/system)

Command History	Release	Modification
	1.0(1)	This command was introduced.

Examples This example shows how to set up a virtual IP address:

```
switch# scope system
switch /system # set virtual-ip 209.165.200.225
```

```
switch /system* # commit-buffer
switch /system #
```

Related Commands

Command	Description
show image	
show vif	

set vnic

To set the vNIC, use the **set vnic** command.

set vnic *vnic*

Syntax Description

<i>vnic</i>	VNIC name. The range of valid values is 1 to 16.
-------------	--

Command Default

None

Command Modes

Path (/org/boot-policy/lan/path)

Command History

Release	Modification
1.0(1)	This command was introduced.

A vNIC is a virtualized network interface that is configured on a physical network adapter and appears to be a physical NIC to the operating system of the server. The type of adapter in the system determines how many vNICs you can create. For example, a Cisco UCS CNA M71KR adapter has two NICs, which means you can create a maximum of two vNICs for each of those adapters.

Examples

This example shows how to set the VNIC:

```
switch-A# scope org org3
switch-A /org # scope boot-policy boot1
switch-A /org/boot-policy # scope lan
switch-A /org/boot-policy/lan # scope path
switch-A /org/boot-policy/lan/path # set vnic 101
switch-A /org/boot-policy/lan/path* # commit-buffer
switch-A /org/boot-policy/lan/path #
```

Related Commands

Command	Description
show path	
show vnic	

set weight

To set the weight, use the **set weight** command.

set weight { *weight* | **best-effort** | **none** }

Syntax Description

<i>weight</i>	Weight number. The range of valid values is 0 to 10.
best-effort	Specifies best effort.
none	Specifies no weight.

Command Default

None

Command Modes

Ethernet classified (/eth-server/qos/eth-classified)

Ethernet default (/eth-server/qos/eth-default)

Fibre Channel default (/eth-server/qos/fc-default)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set the weight:

```
switch-A# scope eth-server
switch-A /eth-server # scope qos
switch-A /eth-server/qos # scope eth-classified
switch-A /eth-server/qos/eth-classified # set weight 5
switch-A /eth-server/qos/eth-classified* # commit-buffer
switch-A /eth-server/qos/eth-classified #
```

Related Commands

Command	Description
show eth-best-effort	
show eth-classified	

set width

To set the width, use the **set width** command.

set width { *width* | **unspec** }

Syntax Description	<i>width</i>	Width. The range of valid values is 0 to 65535.
	unspec	Specifies width unspecified.
Command Default	None	
Command Modes	Memory (/org/server-qual/memory)	
Command History	Release	Modification
	1.0(1)	This command was introduced.
Usage Guidelines	Use this command to specify the bit width of the data bus.	
Examples	<p>This example shows how to set the width:</p> <pre>switch-A# scope org org10 switch-A /org # scope server-qual squal10 switch-A /org/server-qual # scope memory switch-A /org/server-qual/memory # set width 1000000 switch-A /org/server-qual/memory* # commit-buffer switch-A /org/server-qual/memory #</pre>	
Related Commands	Command	Description
	show memory	
	show storage	

set wwn

To set a World Wide Name (WWN), use the **set wwn** command.

set wwn *name*

Syntax Description	<i>name</i>	WWN name. The name entered must be in hh:hh:hh:hh:hh:hh:hh:hh format.
Command Default	None	

Command Modes

Path (/org/boot-policy/storage/san-image/path)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to set a WWN:

```
switch-A# scope org org10a
switch-A /org # scope boot-policy boot6b
switch-A /org/boot-policy # scope storage
switch-A /org/boot-policy/storage # scope san-image primary
switch-A /org/boot-policy/storage/san-image # scope path primary
switch-A /org/boot-policy/storage/san-image/path # set wwn 20:00:00:20:00:00:23
switch-A /org/boot-policy/storage/san-image/path* # commit-buffer
switch-A /org/boot-policy/storage/san-image/path* #
```

Related Commands

Command	Description
show path	
show san-image	

top

To enter root from any mode, use the **top** command.

top

This command has no arguments or keywords.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to enter root from any mode:

```
switch /system/services # top
switch#
```

up

To move up one mode, use the **up** command.

up

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to move up one mode:

```
switch-A /org/service-profile # up
switch-A /org #
```

update firmware

To update the firmware, use the **update firmware** command.

update firmware *version* **activate**[**force**] **set-startup**

Syntax Description

<i>version</i>	Version number.
activate	(Optional) Specifies activation of firmware.
force	(Optional) Specifies force of firmware update.
set-startup	(Optional) Specifies set the firmware update on startup.

Command Default

None

Command Modes

Input output module (/chassis/iom)

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to update the firmware:

```
switch-A# scope chassis 1
switch-A /chassis # scope iom 2
switch-A# /chassis/iom # update firmware 1.0(0.988)
switch-A# /chassis/iom* # activate firmware 1.0(0.988)

switch-A# /chassis/iom* # commit-buffer
switch-A# /chassis/iom #
```

Related Commands

Command	Description
show firmware	
show image	

where

To determine where you are in the CLI, use the **where** command.

where

This command has no arguments or keywords.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
1.0(1)	This command was introduced.

Examples

This example shows how to determine where you are in the CLI:

```
switch-A /org/service-profile # where
Mode: /org/service-profile
Mode Data:
  scope org
  enter org org10
  enter service-profile sp10 instance
switch-A /org/service-profile #
```

 where