



Alcatel 4400 Release 5.0 and 5.1 to Cisco IOS Voice Gateway using E1 QSIG with H.323

October 30, 2007 Revision 4

Table of Contents


Introduction	1
Network Topology.....	2
System Components	2
Hardware Requirements	2
Software Requirements	2
Features	3
Features Supported	3
Limitations.....	3
Configuration.....	4
Configuring the Alcatel 4400, Release 5.1	4
Configuring the Alcatel 4400, Release 5.0	30
Configuring the Cisco 2651XM	58
Configuring the Cisco 3745.....	63
Acronyms	69

Introduction

- Although specific gateway router models were used to validate its content, this application note also applies to all Cisco 1700/2600/3600/3700/2800/3800 series Cisco IOS voice gateways.
- This application note provides configuration guidelines for a toll-bypass network using Cisco IOS voice gateways to connect Alcatel 4400 Release 5.0 and 5.1 PBXs. The PBXs are connected to the Cisco IOS voice gateways by E1 QSIG trunk circuits. The Cisco IOS voice gateways “extend” the E1 QSIG trunk circuits with VoIP, using the H.323 protocol.
- An Alcatel 4400 Release 5.0 PBX and an Alcatel 4400 Release 5.1 PBX were each connected via E1 QSIG trunk circuits to a Cisco IOS voice gateway. The two voice gateways were connected via IP over Ethernet, and configured for VoIP using H.323. End-to-end calls were placed between the PBXs to exercise and test basic calls as well as QSIG supplementary services such as call transfer, call conference, and call forward.
- Using the Alcatel PBX configurations and Cisco IOS voice gateway configurations in this application note, successful toll bypass integration was achieved. This includes basic call, call transfer, call conference, and call forward, with some limitations on Called Name features during call forward scenarios.

Network Topology

Figure 1. Network Topology or Test Setup



System Components

Hardware Requirements

- (2) Cisco IOS voice gateways with E1 VWICs (voice/WAN interface cards)
- (2) Alcatel 4400 PBX
- (4) Alcatel digital station telephones

Software Requirements

- Alcatel Release 5.0 (or higher).
- Cisco IOS voice gateways: Cisco IOS Release Version 12.4(1.8)T or later.



Features

Features Supported

- Basic Call (ENBLOC and Overlap)
- Caller ID (Calling Name/Number and Called and/or Connected Name/Number)
- Call Transfer: Supervised Local Transfer
- Call Transfer: Supervised Network/External Transfer
- Call Conference: Local
- Call Conference: Network/External
- Call Forward: Local
- Call Forward: Network/External
- Call Hold

Limitations

- On basic calls, Calling Number was displayed only after the destination picked up. This is inherent to the PBXs and also occurs with the PBXs connected directly via an E1 QSIG trunk.
- On basic calls, the Called Number displayed was actually dialed number or Connected number. This is inherent to the PBXs and also occurs with the PBXs connected directly via an E1 QSIG trunk.
- On basic calls using Overlap Sending, the Called Name displayed was actually Connected Name, and displays only after the destination answers. This is inherent to the PBXs and also occurs with the PBXs connected directly via an E1 QSIG trunk.
- On Supervised Transfers, the originating Calling Name and Number were displayed on the final destination phone only after the destination answered and the transfer was completed. This is inherent to the PBXs and also occurs with the PBXs connected directly via an E1 QSIG trunk.
- On forwarded calls, the originating Calling Number was displayed on the final destination only after the destination answered and the transfer was completed. This is inherent to the PBXs and also occurs with the PBXs connected directly via an E1 QSIG trunk.
- On forwarded calls, the forwarding Called Name was not passed to the final destination. This is inherent to the PBXs and also occurs with the PBXs connected directly via an E1 QSIG trunk.
- MWI was not tested, as a local voice mail system was not available on the PBXs at the time of testing.



Configuration

Configuring the Alcatel 4400, Release 5.1

Figure 2. Configure "ISO function" System Parameter






Figure 3. Configure "ISO function" System Parameter (continued)






Figure 4. Configure "ISO function" System Parameter (continued)






Figure 5. Configure "ISO function" System Parameter (continued)






Figure 6. Configure Board 4

Interface type must be set to **PRA2**






Figure 7. Configure Board 4






Figure 8. Configure Board 4 Digital Access Options

Network mode must be set to **Yes** for (Master/Network) or **No**- (Slave/User).
Access Type must be set to **T2**.






Figure 9. Configure Trunk Group 1

Q931 **signal variant** is used to set the protocol type to **ABC-F**




Figure 10. Configure Trunk Group 1 (continued)




Figure 11. Configure Trunk Detail





Figure 12. Configure Trunk Detail (continued)



Configuration: alcatel51

Configuration


alcatel51:1	
Instance (reserved)	1
Automated Attendant	NO
Calling party Rights COS	0
Entity Number	1
TS Overflow	YES
Number To Be Added	
Supervised by Routing	NO
VPN Cost Limit for Incom.Calls	0
Immediate Trk Listening if VPNC	YES
VPN TS %	50
CSTA-Monitored	NO
Max.% of trunks out CCD	0
Charge Calling And ADN Creatio	NO
Ratio analog.to ISDN cost	
Logical Channel	1__15 & 17__31
TS Distribution on Accesses	YES
Use Split Access	NO

All Action

[1:44:03 PM] > Request 10 sent to alcatel51.
[1:44:03 PM] > Request 10 completed on alcatel51: 1 instance(s) received.

Configuration: alcatel51

Figure 13. Configure Trunk Detail (continued)







Figure 15. Network Routing Table

Ensure that **Protocol Type** is configured for QSIG-GF which ensures that all Alcatel proprietary QSIG signaling messages are stripped from outgoing calls.



The screenshot displays the Cisco Configuration Manager interface for the configuration of alcatel51. The left pane shows the network hierarchy, with the 'Network Routing Table' selected under the 'Translator' node. The right pane shows the configuration details for 'alcatel51:1'.

alcatel51:1	
Network Number	0
Rank of First Digit to be Sent	1
Incoming identification prefix	
Protocol Type	QSIG-GF
Dialing Plan Descriptor ID	11
ARS Route list	0
Schedule number	-1
ATM Address ID	-1
Network call prefix	
City/Town Name	
Send City/Town Name	<input type="checkbox"/>
Associated Ext SIP gateway	-1

The bottom status bar shows the following messages:

```
[1:48:19 PM] > Request 16 sent to alcatel51.
[1:48:19 PM] > Request 16 completed on alcatel51: 16 instance(s) received.
```



Figure 16. Prefix Plan

Alcatel51/translator/prefix plan/6




Figure 17. Configure User (Station)




Figure 18. Configure User (Station, Continued)




Figure 19. Configure User (Station, Continued)




Figure 20. Configure User (Station, Continued)






Figure 21. Configure User (Station, Continued)




Figure 22. Configure User (Station, Continued)




Figure 23. Configure User (Station, Continued)






Figure 24. Configure User (Station, Continued)




Figure 25. Configure User (Station, Continued)




Figure 26. Alcatel 4400 Software release 5.1







Figure 27. Alcatel 4400 Software release 5.1 (continued)



Configuring the Alcatel 4400, Release 5.0

Figure 28. Configure "ISO function" System Parameter




Figure 29. Configure "ISO function" System Parameter, continued




Figure 30. Configure "ISO function" System Parameter, continued




Figure 31. Configure "ISO function" System Parameter, continued




Figure 32. Configure Board 4

Interface type must be set to **PRA2**




Figure 33. Configure Board 4, continued




Figure 34. Configure Board 4 Digital Access Options

Network mode must be set to **Yes** for (Master/Network) or **No**- (Slave/User).
Access Type must be set to **T2**.




Figure 35. Configure Trunk Group 1

Q931 signal variant is used to set the protocol type to ABC-F




Figure 36. Configure Trunk Group 1, continued




Figure 37. Configure Trunk Group 1, continued




Figure 38. Configure Trunk Detail




Figure 39. Configure Trunk Detail, continued




Figure 40. Configure Trunk Detail, continued




Figure 41. Configure Trunk Detail, continued




Figure 42. T2 Access




Figure 43. Network Routing Table

Ensure that **Protocol Type** is configured for QSIG-GF which ensures that all Alcatel proprietary QSIG signaling messages are stripped from outgoing calls.




Figure 44. Prefix Plan

Alcatel51/translator/prefix plan/3




Figure 45. Configure User (Station)




Figure 46. Configure User (Station, continued)




Figure 47. Configure User (Station, continued)




Figure 48. Configure User (Station, continued)




Figure 49. Configure User (Station, continued)




Figure 50. Configure User (Station, continued)




Figure 51. Configure User (Station, continued)




Figure 52. Configure User (Station, continued)




Figure 53. Configure User (Station, continued)




Figure 54. Configure User (Station, continued)





Figure 55. Alcatel 4400 Software release 5.0





Configuring the Cisco 2651XM

2651XM_West#sho ver

Cisco IOS Software, C2600 Software (C2600-IPVOICE-M), Version 12.4(1.8)T, INTERI
M SOFTWARE

Technical Support: <http://www.cisco.com/techsupport>

Copyright (c) 1986-2005 by Cisco Systems, Inc.

Compiled Thu 05-May-05 06:32 by kellmill

ROM: System Bootstrap, Version 12.2(8r) [cmong 8r], RELEASE SOFTWARE (fc1)

2651XM_West uptime is 1 week, 1 day, 1 hour, 33 minutes

System returned to ROM by reload

System image file is "flash:c2600-ipvoice-mz.124-1.8.T"

Cisco 2651XM (MPC860P) processor (revision 0x300) with 125770K/5302K bytes of me
mory.

Processor board ID JAE0817EK5Z (1672255744)

M860 processor: part number 5, mask 2

2 FastEthernet interfaces

31 Serial interfaces

2 Channelized E1/PRI ports

32K bytes of NVRAM.

49152K bytes of processor board System flash (Read/Write)

Configuration register is 0x2102



```
2651XM_West#sho run
```

```
Building configuration...
```

```
Current configuration : 1528 bytes
```

```
!
```

```
version 12.4
```

```
service timestamps debug datetime msec
```

```
service timestamps log datetime msec
```

```
no service password-encryption
```

```
!
```

```
hostname 2651XM_West
```

```
!
```

```
boot-start-marker
```

```
boot system flash
```

```
boot-end-marker
```

```
!
```

```
!
```

```
no aaa new-model
```

```
!
```

```
resource policy
```

```
!
```

```
no network-clock-participate slot 1
```

```
no network-clock-participate wic 0
```

```
voice-card 1
```

```
!
```

```
ip subnet-zero
```

```
ip cef
```

```
!
```

```
!
```



```
no ip dhcp use vrf connected
!
!
no ip domain lookup
isdn switch-type primary-qsig
!
!
voice class codec 1
codec preference 1 g729r8
codec preference 2 g711ulaw
codec preference 3 g711alaw
!
!
controller E1 1/0
pri-group timeslots 1-31
description ECN-4
!
controller E1 1/1
!
!
interface FastEthernet0/0
ip address 172.20.4.7 255.255.255.0
duplex auto
speed auto
!
interface FastEthernet0/1
no ip address
shutdown
duplex auto
```




```
speed auto

!

interface Serial1/0:15

description D-channel for ECN-4

no ip address

no logging event link-status

isdn switch-type primary-qsig

isdn overlap-receiving

isdn incoming-voice voice

isdn bchan-number-order ascending

no cdp enable

!

ip classless

ip route 0.0.0.0 0.0.0.0 FastEthernet0/0

!

ip http server

!

!

control-plane

!

!

voice-port 1/0:15

description voice port for ECN-4

!

!

dial-peer voice 323 voip

destination-pattern 6...

session target ipv4:172.20.4.9

!
```



```
dial-peer voice 1015 pots
destination-pattern 3...
direct-inward-dial
port 1/0:15
forward-digits all
!
!
line con 0
line aux 0
line vty 0 4
exec-timeout 0 0
password cisco
login
transport input telnet
!
!
end
```



Configuring the Cisco 3745

3745_West#sho ver

Cisco IOS Software, 3700 Software (C3745-IPVOICE-M), Version 12.4(1.8)T, INTERIM
SOFTWARE

Technical Support: <http://www.cisco.com/techsupport>

Copyright (c) 1986-2005 by Cisco Systems, Inc.

Compiled Thu 05-May-05 02:04 by kellmill

ROM: System Bootstrap, Version 12.2(8r)T2, RELEASE SOFTWARE (fc1)

3745_West uptime is 1 week, 1 day, 53 minutes

System returned to ROM by reload

System image file is "flash:c3745-ipvoice-mz.124-1.8.T"

Cisco 3745 (R7000) processor (revision 2.0) with 110592K/20480K bytes of memory.

Processor board ID JMX0813L0Z3

R7000 CPU at 350MHz, Implementation 39, Rev 3.3, 256KB L2, 2048KB L3 Cache

2 FastEthernet interfaces

31 Serial interfaces

4 Channelized E1/PRI ports

2 Voice FXS interfaces

DRAM configuration is 64 bits wide with parity disabled.

151K bytes of NVRAM.

31168K bytes of ATA System CompactFlash (Read/Write)

Configuration register is 0x2102



```
3745_West#sho run
```

```
Building configuration...
```

```
Current configuration : 1732 bytes
```

```
!
```

```
version 12.4
```

```
service timestamps debug datetime msec
```

```
service timestamps log datetime msec
```

```
no service password-encryption
```

```
!
```

```
hostname 3745_West
```

```
!
```

```
boot-start-marker
```

```
boot system flash
```

```
boot-end-marker
```

```
!
```

```
card type e1 1 1
```

```
logging buffered 5000000 debugging
```

```
!
```

```
no aaa new-model
```

```
!
```

```
resource policy
```

```
!
```

```
no network-clock-participate slot 1
```

```
ip subnet-zero
```

```
ip cef
```

```
!
```

```
!
```



```
no ip dhcp use vrf connected
!
!
no ip domain lookup
isdn switch-type primary-qsig
voice-card 1
dspfarm
!
!
voice call carrier capacity active
!
!
voice class codec 1
codec preference 2 g711ulaw
codec preference 3 g711alaw
!
!
controller E1 1/0
pri-group timeslots 1-31
description ECN10
!
controller E1 1/1
!
controller E1 1/2
!
controller E1 1/3
!
!
interface FastEthernet0/0
```




```
ip address 172.20.4.9 255.255.255.0
```

```
duplex auto
```

```
speed auto
```

```
!
```

```
interface FastEthernet0/1
```

```
no ip address
```

```
shutdown
```

```
duplex auto
```

```
speed auto
```

```
!
```

```
interface Serial1/0:15
```

```
description D-channel for ECN10
```

```
no ip address
```

```
no logging event link-status
```

```
isdn switch-type primary-qsig
```

```
isdn overlap-receiving
```

```
isdn protocol-emulate network
```

```
isdn incoming-voice voice
```

```
isdn T310 120000
```

```
no cdp enable
```

```
!
```

```
router eigrp 10
```

```
network 172.20.0.0
```

```
no auto-summary
```

```
!
```

```
ip classless
```

```
ip route 0.0.0.0 0.0.0.0 FastEthernet0/0
```

```
!
```

```
ip http server
```



```
!  
!  
control-plane  
!  
!  
voice-port 1/0:15  
description voice port for ECN10  
!  
voice-port 3/0/0  
!  
voice-port 3/0/1  
!  
!  
dial-peer cor custom  
!  
!  
dial-peer voice 323 voip  
destination-pattern 3...  
session target ipv4:172.20.4.7  
!  
dial-peer voice 1015 pots  
destination-pattern 6...  
direct-inward-dial  
port 1/0:15  
forward-digits all  
!  
!  
line con 0  
line aux 0
```



```
line vty 0 4
exec-timeout 0 0
password cisco
login
transport input telnet
!
!
end
```



Acronyms

Acronym	Definitions



Important Information

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.



Corporate Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
www.cisco.com
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 526-4100

European Headquarters

Cisco Systems International
BV
Haarlerbergpark
Haarlerbergweg 13-19
1101 CH Amsterdam
The Netherlands
www-europe.cisco.com
Tel: 31 0 20 357 1000
Fax: 31 0 20 357 1100

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
www.cisco.com
Tel: 408 526-7660
Fax: 408 527-0883

Asia Pacific Headquarters

Cisco Systems, Inc.
Capital Tower
168 Robinson Road
#22-01 to #29-01
Singapore 068912
www.cisco.com
Tel: +65 317 7777
Fax: +65 317 7799

Cisco Systems has more than 200 offices in the following countries and regions. Addresses, phone numbers, and fax numbers are listed on the Cisco Web site at www.cisco.com/go/offices.

Argentina • Australia • Austria • Belgium • Brazil • Bulgaria • Canada • Chile • China PRC • Colombia • Costa Rica • Croatia • Czech Republic • Denmark • Dubai, UAE • Finland • France • Germany • Greece • Hong Kong SAR • Hungary • India • Indonesia • Ireland • Israel • Italy • Japan • Korea • Luxembourg • Malaysia • Mexico • The Netherlands • New Zealand • Norway • Peru • Philippines • Poland • Portugal • Puerto Rico • Romania • Russia • Saudi Arabia • Scotland • Singapore • Slovakia • Slovenia • South Africa • Spain • Sweden • Switzerland • Taiwan • Thailand • Turkey • Ukraine • United Kingdom • United States • Venezuela • Vietnam • Zimbabwe

© 2007 Cisco Systems, Inc. All rights reserved.

CCVP, the Cisco logo, and Welcome to the Human Network are trademarks of Cisco Systems, Inc.; Changing the Way We Work, Live, Play, and Learn is a service mark of Cisco Systems, Inc.; and Access Registrar, Aironet, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Enterprise/Solver, EtherChannel, EtherFast, EtherSwitch, Fast Step, Follow Me Browsing, FormShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, IP/TV, iQ Expertise, the iQ logo, iQ Net Readiness Scorecard, iQuick Study, LightStream, Linksys, MeetingPlace, MGX, Networkers, Networking Academy, Network Registrar, PIX, ProConnect, ScriptShare, SMARTnet, StackWise, The Fastest Way to Increase Your Internet Quotient, and TransPath are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0711R)

Printed in the USA