



M

Last Updated: November 17, 2010

[messaging-gateway secondary](#)

messaging-gateway secondary

To specify a secondary messaging gateway, use the **messaging-gateway secondary** command in Cisco UMG endpoint configuration mode.

messaging-gateway secondary *location-id*

Syntax Description	<i>location-id</i>	Location ID of the secondary messaging gateway (range: 1-10 digits).
--------------------	--------------------	--

Command Default The default secondary messaging gateway is none.

Command Modes Cisco UMG endpoint configuration (config-endpoint)

Command History	Cisco UMG Version	Modification
	1.0	This command was introduced.

Usage Guidelines Use this command to provide failover support for <Abbreviation>Cisco Unity Express (all supported versions) and Cisco Unity endpoints.



Note Avaya Interchange endpoints rely on a DNS server for failover support.

Examples The following example illustrates the use of the **messaging-gateway secondary** command.

```
umg-1# config t
umg-1(config)# endpoint 5000 cue
umg-1(config-endpoint)# messaging-gateway secondary 20000
umg-1(config-endpoint)# end
umg-1(config)# end
umg-1# show endpoint local
A total of 1 local endpoint(s) have been found:
```

Location ID	Location Prefix	Endpoint Type	Endpoint Status	Primary Gateway	Secondary Gateway
40000		CUE	Offline	57000	50000

```
umg-1#
```

Related Commands

Command	Description
endpoint	Enters endpoint configuration mode to provision endpoints manually.
show endpoint	Displays endpoint details.
show messaging-gateway	Displays details for any or all messaging gateways in the system.

