



CHAPTER 12

J Commands

The commands in this chapter apply to the Cisco MDS 9000 Family of multilayer directors and fabric switches. All commands are shown here in alphabetical order regardless of command mode. See [“About the CLI Command Modes”](#) section on page 1-3 to determine the appropriate mode for each command. For more information, refer to the *Cisco MDS 9000 Family CLI Configuration Guide*.

Send documentation comments to mdsfeedback-doc@cisco.com

job name

To assign a job to a command schedule, use the **job name** command. To remove the job, use the **no** form of the command.

job name *job-name*

no job name *job-name*

Syntax Description	<i>job-name</i>	Specifies the job name for the command schedule to run.
---------------------------	-----------------	---

Defaults	None.
-----------------	-------

Command Modes	Scheduler schedule configuration submode.
----------------------	---

Command History	Release	Modification
	2.0(x)	This command was introduced.

Usage Guidelines	To use this command, the command scheduler must be enabled using the scheduler enable command. You can configure multiple jobs in a command schedule.
-------------------------	--

Examples	The following example shows how to specified the job for a command schedule:
-----------------	--

```
switch# config terminal
switch(config)# scheduler schedule name MySchedule
switch(config-schedule)# job name MyJob
```

Related Commands	Command	Description
	scheduler enable	Enables the command scheduler.
	scheduler schedule name	Configures a schedule for the command scheduler.
	show scheduler	Displays scheduler information.