

Send documentation comments to mdsfeedback-doc@cisco.com



Cisco MDS 9000 Family Release Notes for Storage Services Interface Image Release 5.2(2a)

Release Date: January 25, 2012

Text Part Number: OL-29007-03

This document describes the caveats and limitations for the Storage Service Interface (SSI) software for the various Cisco MDS Services Modules (SSN-16, MSM-18/4, and MDS 9222i). Use this document in conjunction with the documents listed in the “[Related Documentation](#)” section on page 9.



Note

Release notes are sometimes updated with new information on restrictions and caveats. Refer to the following website for the most recent version of the *Cisco MDS 9000 Family Release Notes*:
http://www.cisco.com/en/US/products/ps5989/prod_release_notes_list.html

Contents

This document includes the following sections:

- [Introduction](#), page 2
- [System Requirements](#), page 2
- [Upgrade and Downgrade Caveats](#), page 7
- [New Features](#), page 8
- [Limitations](#), page 8
- [Compatibility Matrix](#), page 8
- [Caveats](#), page 8
- [Related Documentation](#), page 9



Americas Headquarters:

Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

- [Obtaining Documentation and Submitting a Service Request, page 11](#)

Introduction

The SSI interface provides the following features:

- Network-based volume management (EMC Invista, Incipient iNSP)
- Fibre Channel Write Acceleration (FC-WA) and SCSI flow statistics
- Data Mobility Manager (DMM)



Note

As of NX-OS Release 4.1(1b), SAN-OS has been changed to NX-OS. References to SAN-OS releases before 4.1(1b) still apply.

System Requirements

This section describes the system requirements for Cisco MDS SSI Release 5.2(2a) and includes the following topics:

- [Components Supported, page 2](#)
- [Determining the Software Version, page 7](#)

Components Supported

[Table 1](#) lists the software and hardware components supported by the Cisco MDS 9000 Family.

Table 1 Cisco MDS 9000 Family Supported Software and Hardware Components

Component	Part Number	Description	Applicable Product
Software	M95S2K9-5.2.2a	MDS 9500 Supervisor/Fabric-2, NX-OS software.	MDS 9500 Series only
	M92S2K9-5.2.2a	MDS 9222 Supervisor/Fabric-2, NX-OS software.	MDS 9200 Series only
	M91S2K9-5.2.2a	MDS 9100 Supervisor/Fabric-2, NX-OS software.	MDS 9124 Switch and MDS 9134 Switch
	M91S3K9-5.2.2a	MDS 9148 Supervisor/Fabric-3 NX-OS software	MDS 9148 Switch
SSI Interface	SSI-M9K9-522a	Storage Services Interface for Release 5.2(2a)	MDS 9000 Family
Licenses	M9500SSE184K9	Storage Services Enabler License for one MSM-18/4 module	MDS 9500 Series only
	M9222ISSE1K9	Storage Services Enabler License	MDS 9222i Switch only
	M9200SSE184K9	Storage Services Enabler License for one MSM-18/4 module	MDS 9200 Series only
	M95DMM184K9	Data Mobility Manager License for one MSM-18/4 module	MDS 9500 Series only
	M9222IDMMK9	Data Mobility Manager License for Cisco MDS 9222i	MDS 9222i Switch

Send documentation comments to mdsfeedback-doc@cisco.com

Table 1 *Cisco MDS 9000 Family Supported Software and Hardware Components (continued)*

Component	Part Number	Description	Applicable Product
Licenses (continued)	M92DMM184K9	Data Mobility Manager License for one MSM-18/4 module	MDS 9200 Series only
	M95DMM184TSK9	Data Mobility Manager for one MSM-18/4 module — Time limited to 180 days only	MDS 9500 Series only
	M9222IDMMTSK9	Data Mobility Manager — Time limited to 180 days only	MDS 9222i Switch only
	M92DMM184TSK9	Data Mobility Manager for one MSM-18/4 module — Time limited to 180 days only	MDS 9200 Series only
Chassis	DS-C9513	Cisco MDS 9513 Multilayer Director (13-slot multilayer director with 2 slots for Supervisor-2 modules, with 11 slots available for switching modules — SFPs sold separately)	MDS 9513 Switch
	DS-C9509	Cisco MDS 9509 Multilayer Director (9-slot multilayer director with 2 slots for Supervisor modules, with 7 slots available for switching modules — SFPs sold separately)	MDS 9509 Switch
	DS-C9506	Cisco MDS 9506 Multilayer Director (6-slot multilayer director with 2 slots for Supervisor modules, with 4 slots available for switching modules — SFPs sold separately)	MDS 9506 Switch
	DS-C9222i-K9	Cisco MDS 9222i Multilayer Fabric Switch (3-rack-unit (3RU) semimodular multilayer fabric switch with 18 4-Gbps Fibre Channel ports, 4 Gigabit Ethernet ports, and a modular expansion slot for Cisco MDS 9000 Family Switching and Services modules)	MDS 9222i Switch
	DS-C9148-K9	Cisco MDS 9148 48-Port Multilayer Fabric Switch (1RU fixed-configuration multilayer fabric switch with 48 8-Gbps Fibre Channel ports)	MDS 9148i Switch
	DS-C9134-K9	Cisco MDS 9134 34-Port Multilayer Fabric Switch (1RU fixed-configuration multilayer fabric switch with 32 4-Gbps and 2 10-Gbps Fibre Channel ports)	MDS 9134 Switch
	DS-C9124-K9	Cisco MDS 9124 24-Port Multilayer Fabric Switch (1RU fixed-configuration multilayer fabric switch with 24 4-Gbps Fibre Channel ports)	MDS 9124 Switch
Supervisor Modules	DS-X9530-SF2-K9	Cisco MDS 9500 Series Supervisor-2 Module	MDS 9500 Series
	DS-X9530-SF2A-K9	Cisco MDS 9500 Series Supervisor-2A Module	MDS 9500 Series

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

Table 1 Cisco MDS 9000 Family Supported Software and Hardware Components (continued)

Component	Part Number	Description	Applicable Product
Switching Modules	DS-X9112	Cisco MDS 9000 12-port 4-Gbps Fibre Channel Switching Module with SFP LC connectors	MDS 9500 Series MDS 9200 Series
	DS-X9124	Cisco 24-port 4-Gbps Fibre Channel Switching Module with SFP LC connectors	MDS 9500 Series MDS 9200 Series
	DS-X9148	Cisco MDS 9000 48-port 4-Gbps Fibre Channel Switching Module with SFP LC	MDS 9500 Series Mds 9200 Series
	DS-X9704	Cisco MDS 9000 Family 4-Port 10-Gbps Fibre Channel Switching Module with SFP LC	MDS 9500 Series Mds 9200 Series
	DS-X9224-96K9	Cisco MDS 9000 24-Port 8-Gbps Fibre Channel Switching Module with SFP and SFP+ LC connectors	MDS 9500 Series
	DS-X9248-96K9	Cisco MDS 9000 48-Port 8-Gbps Fibre Channel Switching Module with SFP and SFP+ LC connectors	MDS 9500 Series
	DS-X9248-48K9	Cisco MDS 9000 4/44-Port Host-Optimized 8-Gbps Fibre Channel Switching Module with SFP and SFP+ LC connectors	MDS 9500 Series MDS 9222i Switch
	DS-X9708-K9	Cisco MDS 9000 8-port 10-Gbps Fibre Channel over Ethernet (FCoE) module	MDS 9500 Series
	DS-X9232-256K9	Cisco MDS 9000 32-port 8-Gbps Advanced Fibre Channel Switching module	MDS 9500 Series
	DS-X9248-256K9	Cisco MDS 9000 48-port 8-Gbps Advanced Fibre Channel Switching module	MDS 9500 Series
Services Modules	DS-X9304-18K9	Cisco MDS 9000 18/4-Port Multiprotocol Services Module (MSM-18/4) — 18-port, 4-Gbps Fibre Channel plus 4-port Gigabit Ethernet IP services and switching module with SFP LC connectors	MDS 9500 Series MDS 9200 Series
	DS-X9316-SSNK9	Cisco MDS 9000 Family 16-Port Storage Services Node (SSN-16) — 16 fixed 1-Gbps Ethernet ports, plus 4 service engines that support 16 Gigabit Ethernet IP storage services ports	MDS 9500 Series MDS 9222i Switch
External crossbar module	DS-13SLT-FAB1	Cisco MDS 9513 Switching Fabric1 Module	MDS 9513 Switch
	DS-13SLT-FAB2	Cisco MDS 9513 Switching Fabric2 Module	MDS 9513 Switch
	DS-13SLT-FAB3	Cisco MDS 9513 Switching Fabric 3 module	MDS 9513 Switch

Send documentation comments to mdsfeedback-doc@cisco.com

Table 1 Cisco MDS 9000 Family Supported Software and Hardware Components (continued)

Component	Part Number	Description	Applicable Product
Optics	DS-X2-FC10G-SR	X2 SC optics, 10-Gbps Fibre Channel for short reach	MDS 9500 Series MDS 9200 Series
	DS-X2-FC10G-LR	X2 SC optics, 10-Gbps Fibre Channel for long reach (10 km)	MDS 9500 Series MDS 9200 Series
	DS-X2-FC10G-ER	X2 SC optics, 10-Gbps Fibre Channel for extended reach (40 km)	MDS 9500 Series MDS 9200 Series
	DS-X2-FC10G-CX4	X2 SC optics, 10-Gbps Fibre Channel over copper	MDS 9500 Series MDS 9200 Series
	DS-X2-E10G-SR	X2 SC optics, 10-Gbps Ethernet for short reach	MDS 9500 Series MDS 9200 Series
LC-type fiber-optic SFP	DS-SFP-FC8G-SW	SFP+ optics (LC type) for 2-, 4-, or 8-Gbps Fibre Channel for shortwave mode	MDS DS-X9200 Series switching modules
	DS-SFP-FC8G-LW	SFP+ optics (LC type) for 2-, 4-, or 8-Gbps Fibre Channel for longwave mode; supports distances up to 10 km	MDS DS-X9200 Series switching modules
	DS-SFP-FC4G-SW	SFP optics (LC type) for 1-, 2-, or 4-Gbps Fibre Channel for shortwave mode	MDS 9124 and DS-X9100 Series switching modules
	DS-SFP-FC4G-MR	SFP optics (LC type) for 1-, 2-, or 4-Gbps Fibre Channel for longwave mode; supports distances up to 4 km	MDS 9124 and DS-X9100 Series switching modules
	DS-SFP-FC4G-LW	SFP optics (LC type) for 1-, 2-, or 4-Gbps Fibre Channel for longwave mode; supports distances up to 10 km	MDS 9124 and DS-X9100 Series switching modules
	DS-SFP-FC-2G-SW	SFP optics (LC type) for 1- or 2-Gbps Fibre Channel for shortwave mode; not supported for use in 4-Gbps-capable ports	MDS 9000 Series
	DS-SFP-FC-2G-LW	SFP optics (LC type) for 1- or 2-Gbps Fibre Channel for longwave mode for Cisco MDS 9500, MDS 9200, and MDS 9100 Series; not supported for use in 4-Gbps-capable ports	MDS 9000 Series
	DS-SFP-FCGE-SW	SFP optics (LC type) for 1-Gbps Ethernet and 1- or 2-Gbps Fibre Channel for shortwave mode; not supported for use in 4-Gbps-capable ports	MDS 9000 Series
	DS-SFP-FCGE-LW	SFP optics (LC type) for 1-Gbps Ethernet and 1- or 2-Gbps Fibre Channel for longwave mode; not supported for use in 4-Gbps-capable ports	MDS 9000 Series
	DS-SFP-GE-T	SFP (RJ-45 connector) for Gigabit Ethernet over copper	MDS 9000 Series

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

Table 1 Cisco MDS 9000 Family Supported Software and Hardware Components (continued)

Component	Part Number	Description	Applicable Product
Cisco Coarse Wavelength-Division Multiplexing (CWDM)	DS-CWDM-xxxx	CWDM Gigabit Ethernet and 1- or 2-Gbps Fibre Channel SFP LC type, where product number xxxx = 1470, 1490, 1510, 1530, 1550, 1570, 1590, or 1610 nm	MDS 9000 Family
	DS-CWDM4Gxxxx	CWDM 4-Gbps Fibre Channel SFP LC type, where product number xxxx = 1470, 1490, 1510, 1530, 1550, 1570, 1590, or 1610 nm	MDS 9000 Family
Dense Wavelength-Division Multiplexing (DWDM)	DWDM-X2-xx.xx	DWDM X2 SC optics for 10-Gbps Fibre Channel connectivity to an existing Ethernet DWDM infrastructure, with 15xx.xx nm wavelength, where xx.xx = 60.61, 59.79, 58.98, 58.17, 56.55, 55.75, 54.94, 54.13, 52.52, 51.72, 50.92, 50.12, 48.51, 47.72, 46.92, 46.12, 44.53, 43.73, 42.94, 42.14, 40.56, 39.77, 38.98, 38.19, 36.61, 35.82, 35.04, 34.25, 32.68, 31.90, 31.12, or 30.33	MDS 9500 Series MDS 9200 Series
	DWDM-SFP-xxxx	DWDM Gigabit Ethernet and 1- or 2-Gbps Fibre Channel SFP LC type, where product number xxxx = 3033, 3112, 3190, 3268, 3425, 3504, 3582, 3661, 3819, 3898, 3977, 4056, 4214, 4294, 4373, 4453, 4612, 4692, 4772, 4851, 5012, 5092, 5172, 5252, 5413, 5494, 5575, 5655, 5817, 5898, 5979, or 6061nm	MDS 9000 Family
Add/Drop Multiplexer (ADM)	DS-CWDMOADM4A	4-channel CWDM optical ADM (OADM) module (Cisco CWDM 1470, 1490, 1510, or 1530 NM Add/Drop Module)	MDS 9000 Family
	DS-CWDMOADM4B	4-channel CWDM OADM module (Cisco CWDM 1550, 1570, 1590, or 1610 NM Add/Drop Module)	MDS 9000 Family
	DS-CWDM-MUX8A	ADM for 8 CWDM wavelengths	MDS 9000 Family
CWDM Multiplexer Chassis	DS-CWDMCHASSIS	2-slot chassis for CWDM ADMs	MDS 9000 Family
Power Supplies	DS-CAC-300W	300W AC power supply	MDS 9100 Series
	DS-C24-300AC	300W AC power supply	MDS 9124 Switch
	DS-CAC-845W	845W AC power supply for Cisco MDS 9200 Series	MDS9200 Series
	DS-CAC-3000W	3000W AC power supply for Cisco MDS 9509	MDS 9509 Switch
	DS-CAC-6000W	6000W AC power supply for Cisco MDS 9513	MDS 9513 Switch
	DS-CAC-1900W	1900W AC power supply for Cisco MDS 9506	MDS 9506 Switch
CompactFlash	MEM-MDS-FLD512M	External 512-MB CompactFlash memory for supervisor module	MDS 9500 Series
Port Analyzer Adapter	DS-PAA-2, DS-PAA	A standalone Fibre Channel-to-Ethernet adapter that allows for simple, transparent analysis of Fibre Channel traffic in a switched fabric	MDS 9000 Family
Smart Card Reader	DS-SCR-K9	Storage Media Encryption (SME) Smart Card Reader	MDS 9000 Family

Send documentation comments to mdsfeedback-doc@cisco.com

Table 1 Cisco MDS 9000 Family Supported Software and Hardware Components (continued)

Component	Part Number	Description	Applicable Product
Smart Card	DS-SC-K9	SME Smart Card	MDS 9000 Family
CD-ROM	M90FM-CD-441	Cisco MDS 9000 Management Software and Documentation CD-ROM for Cisco MDS 9000 NX-OS Software Release 4.1(3)	MDS 9000 Family

Determining the Software Version



Note

Use the latest available software release supported by your vendor for all Cisco MDS 9000 Family products.

To determine the version of the Cisco NX-OS software currently running on a Cisco MDS 9000 Family switch using the CLI, log into the switch and enter the **show version** command.

To determine the version of the Cisco NX-OS software currently running on a Cisco MDS 9000 Family switch using the Fabric Manager, from the Switches tab in the information pane, locate the switch using the IP address, logical name, or WWN, and then check its version in the Release column.

Downloading Software

To download the latest Cisco software, access the Software Center at this URL:

<http://www.cisco.com/software/navigator>



Note

If you would like to request code to be provided under the terms of either GNU General Public License (GPL) or the GNU Lesser General Public License (LGPL), contact mds-software-disclosure@cisco.com.

Upgrade and Downgrade Caveats

This section provides information about upgrading to the current release or downgrading from it.

Upgrading to Cisco MDS SSI Release 5.2(2a)

Following a software upgrade to SSI Release 5.2(2a) in a 32-bit environment, you must unmount and remount all SCSI devices. The following procedure is specific to hosts or targets that see 32-bit LUN IDs. Follow these steps:

1. Quiesce all applications on the host.
2. Enter the following commands:

```
umount <file system>
varyoffvg <volume group>
```

Send documentation comments to mdsfeedback-doc@cisco.com

exportvg <volume group>

3. Perform the upgrade.

4. Enter the following commands:

rmdev -dl <hdisk#> -R (Repeat this for all hdisks.)

cfgmgr

lsdev -Cc disk (See if all the LUNs are discovered.)

lsattr -El <hdisk#> (Check LUN ID field to check that host sees the same LUN ID as the target LUN ID.)

importvg -y <volume group> <hdisk#> (Volume group name is same as the one that was exported earlier. hdisk# can be just one of the hdisks in the volume group.)

varyonvg <volume group>

mount <file system>

New Features

There are no new features in Cisco MDS SSI Release 5.2(2a).

Limitations

This sections lists limitations or restrictions associated with this release.

GUI Support Not Available for Target IO Timeout DVT Configuration

A target IO timeout for DVT can only be configured through the CLI. GUI support for this configuration is not available in Cisco MDS SSI Release 5.2(2a).

Compatibility Matrix

Before upgrading your SSI image, refer to the [Cisco MDS NX-OS Release Compatibility Matrix for Storage Service Interface Images](#).

The SSI Release 5.2(2a) image is compatible with the Cisco MDS NX-OS Release 5.2(2a), 5.2(2), and 5.2(1) images.

Resolved Caveats

There are no resolved caveats.

Send documentation comments to mdsfeedback-doc@cisco.com

Open Caveats

There are no open caveats.

Related Documentation

The documentation set for NX-OS for the Cisco MDS 9000 Family includes the following documents. To find a document online, access the following web site:

http://www.cisco.com/en/US/products/ps5989/tsd_products_support_series_home.html

The documentation set for Cisco Data Center Network Manager appears in the Cisco DCNM Release Notes for Release 5.2, which is available from the following website:

http://www.cisco.com/en/US/partner/products/ps9369/prod_release_notes_list.html

Release Notes

- *Cisco MDS 9000 Family Release Notes for Cisco MDS NX-OS Releases*
- *Cisco MDS 9000 Family Release Notes for MDS SAN-OS Releases*
- *Cisco MDS 9000 Family Release Notes for Storage Services Interface Images*
- *Cisco MDS 9000 Family Release Notes for Cisco MDS 9000 EPLD Images*

Regulatory Compliance and Safety Information

- *Regulatory Compliance and Safety Information for the Cisco MDS 9000 Family*

Compatibility Information

- *Cisco Data Center Interoperability Support Matrix*
- *Cisco MDS 9000 NX-OS Hardware and Software Compatibility Information and Feature Lists*
- *Cisco MDS NX-OS Release Compatibility Matrix for Storage Service Interface Images*
- *Cisco MDS 9000 Family Switch-to-Switch Interoperability Configuration Guide*
- *Cisco MDS NX-OS Release Compatibility Matrix for IBM SAN Volume Controller Software for Cisco MDS 9000*
- *Cisco MDS SAN-OS Release Compatibility Matrix for VERITAS Storage Foundation for Networks Software*

Hardware Installation

- *Cisco MDS 9500 Series Hardware Installation Guide*
- *Cisco MDS 9200 Series Hardware Installation Guide*
- *Cisco MDS 9100 Series Hardware Installation Guide*

[Send documentation comments to mdsfeedback-doc@cisco.com](mailto:mdsfeedback-doc@cisco.com)

- *Cisco MDS 9124 and Cisco MDS 9134 Multilayer Fabric Switch Quick Start Guide*

Software Installation and Upgrade

- *Cisco MDS 9000 NX-OS Software Upgrade and Downgrade Guide*
- *Cisco MDS 9000 Family Storage Services Interface Image Install and Upgrade Guide*
- *Cisco MDS 9000 Family Storage Services Module Software Installation and Upgrade Guide*

Cisco NX-OS

- *Cisco MDS 9000 Family NX-OS Licensing Guide*
- *Cisco MDS 9000 Family NX-OS Fundamentals Configuration Guide*
- *Cisco MDS 9000 Family NX-OS System Management Configuration Guide*
- *Cisco MDS 9000 Family NX-OS Interfaces Configuration Guide*
- *Cisco MDS 9000 Family NX-OS Fabric Configuration Guide*
- *Cisco MDS 9000 Family NX-OS Quality of Service Configuration Guide*
- *Cisco MDS 9000 Family NX-OS Security Configuration Guide*
- *Cisco MDS 9000 Family NX-OS IP Services Configuration Guide*
- *Cisco MDS 9000 Family NX-OS Intelligent Storage Services Configuration Guide*
- *Cisco MDS 9000 Family NX-OS High Availability and Redundancy Configuration Guide*
- *Cisco MDS 9000 Family NX-OS Inter-VSAN Routing Configuration Guide*

Command-Line Interface

- *Cisco MDS 9000 Family Command Reference*

Intelligent Storage Networking Services Configuration Guides

- *Cisco MDS 9000 I/O Acceleration Configuration Guide*
- *Cisco MDS 9000 Family SANTap Deployment Guide*
- *Cisco MDS 9000 Family Data Mobility Manager Configuration Guide*
- *Cisco MDS 9000 Family Storage Media Encryption Configuration Guide*
- *Cisco MDS 9000 Family Secure Erase Configuration Guide*
- *Cisco MDS 9000 Family Cookbook for Cisco MDS SAN-OS*

Troubleshooting and Reference

- *Cisco NX-OS System Messages Reference*
- *Cisco MDS 9000 Family NX-OS Troubleshooting Guide*

Send documentation comments to mdsfeedback-doc@cisco.com

- *Cisco MDS 9000 Family NX-OS MIB Quick Reference*
- *Cisco MDS 9000 Family NX-OS SMI-S Programming Reference*

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as a Really Simple Syndication (RSS) feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service and Cisco currently supports RSS version 2.0.

This document is to be used in conjunction with the documents listed in the “[Related Documentation](#)” section.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

© 2005 – 2012 Cisco Systems, Inc. All rights reserved.

Send documentation comments to mdsfeedback-doc@cisco.com