

Send comments to nexus5k-docfeedback@cisco.com



C Commands

This chapter describes the Cisco NX-OS MSDP commands that begin with C.

[Send comments to nexus5k-docfeedback@cisco.com](mailto:nexus5k-docfeedback@cisco.com)

clear ip msdp event-history

To clear information in the Multicast Source Discovery Protocol (MSDP) event history buffers, use the **clear ip msdp event-history** command.

clear ip msdp event-history

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Any command mode

Command History	Release	Modification
	5.0(3)N1(1)	This command was introduced.

Usage Guidelines This command requires the LAN Base Services license.

Examples This example shows how to clear information in the MSDP event history buffers:

```
switch(config)# clear ip msdp event-history
switch(config)#
```

Related Commands	Command	Description
	ip msdp event-history	Configures the size of the MSDP event history buffers.
	show ip msdp event-history	Displays information in the MSDP event history buffers.

Send comments to nexus5k-docfeedback@cisco.com

clear ip msdp peer

To clear a TCP connection to Multicast Source Discovery Protocol (MSDP) peers, use the **clear ip msdp peer** command.

clear ip msdp peer *peer-address* [**vrf** *vrf-name* | **default** | **management**]

Syntax Description

<i>peer-address</i>	IP address of the MSDP peer.
vrf	(Optional) Clears the virtual routing and forwarding (VRF) instance information.
<i>vrf-name</i>	VRF name. The name can be a maximum of 32 alphanumeric characters and is case sensitive.
default	Specifies that the default VRF entry be cleared from the multicast routing table.
management	Specifies that the management VRF entry be cleared from the multicast routing table.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
5.0(3)N1(1)	This command was introduced.

Usage Guidelines

This command requires the LAN Base Services license.

Examples

This example shows how to clear a TCP connection to an MSDP peer:

```
switch# clear ip msdp peer 192.168.1.10
switch#
```

Related Commands

Command	Description
show ip msdp peer	Displays information about MSDP peers.

[Send comments to nexus5k-docfeedback@cisco.com](mailto:nexus5k-docfeedback@cisco.com)

clear ip msdp policy statistics sa-policy

To clear the Source-Active (SA) policy for Multicast Source Discovery Protocol (MSDP) peers, use the **clear ip msdp policy statistics sa-policy** command.

clear ip msdp policy statistics sa-policy *peer-address* { **in** | **out** } [**vrf** *vrf-name* | **default** | **management**]

Syntax Description	
<i>peer-address</i>	IP address of the MSDP peer for the SA policy.
in	Specifies the input policy.
out	Specifies the output policy.
vrf	(Optional) Clears the virtual routing and forwarding (VRF) instance information.
<i>vrf-name</i>	VRF name. The name can be a maximum of 32 alphanumeric characters and is case sensitive.
default	(Optional) Specifies that the default VRF entry be cleared from the multicast routing table.
management	(Optional) Specifies that the management VRF entry be cleared from the multicast routing table.

Command Default None

Command Modes Any command mode

Command History	Release	Modification
	5.0(3)N1(1)	This command was introduced.

Usage Guidelines This command requires the LAN Base Services license.

Examples This example shows how to clear an SA policy for an MSDP peer:

```
switch# clear ip msdp policy statistics sa-policy
switch#
```

Related Commands	Command	Description
	show ip msdp peer	Displays information about MSDP peers.

Send comments to nexus5k-docfeedback@cisco.com

clear ip msdp route

To clear routes that match group entries in the Multicast Source Discovery Protocol (MSDP) Source-Active (SA) cache, use the **clear ip msdp route** command.

```
clear ip msdp route { * | group | group-prefix } [vrf { vrf-name | all | default | management }]
```

Syntax Description		
*		Specifies all sources for the group from the SA cache.
<i>group</i>		Group address in the format <i>A.B.C.D</i> .
<i>group-prefix</i>		Group prefix in the format <i>A.B.C.D/length</i> .
vrf		(Optional) Clears the virtual routing and forwarding (VRF) instance information.
<i>vrf-name</i>		VRF name. The name can be a maximum of 32 alphanumeric characters and is case sensitive.
all		Specifies that all VRF entries be cleared from the SA-cache.
default		Specifies that the default VRF entry be cleared from the SA-cache.
management		Specifies that the management VRF entry be cleared from the SA-cache.

Command Default	None
-----------------	------

Command Modes	Any command mode
---------------	------------------

Command History	Release	Modification
	5.0(3)N1(1)	This command was introduced.

Usage Guidelines	You can also use the clear ip msdp sa-cache command for the same function. This command requires the LAN Base Services license.
------------------	---

Examples	This example shows how to clear the MSDP SA cache: switch# clear ip msdp route * switch#
----------	---

Related Commands	Command	Description
	clear ip msdp sa-cache	Clears the MSDP SA cache.

[Send comments to nexus5k-docfeedback@cisco.com](mailto:nexus5k-docfeedback@cisco.com)

clear ip msdp sa-cache

To clear routes that match group entries in the Multicast Source Discovery Protocol (MSDP) Source-Active (SA) cache, use the **clear ip msdp sa-cache** command.

clear ip msdp sa-cache { * | *group* | *group-prefix* } [**vrf** { *vrf-name* | **all** | **default** | **management** }]

Syntax Description

*	Specifies all sources for the group from the SA cache.
<i>group</i>	Group address in the format <i>A.B.C.D</i> .
<i>group-prefix</i>	Group prefix in the format <i>A.B.C.D/length</i> .
vrf	(Optional) Clears the virtual routing and forwarding (VRF) instance information.
<i>vrf-name</i>	VRF name. The name can be a maximum of 32 alphanumeric characters and is case sensitive.
all	Specifies that all VRF entries be cleared from the SA-cache.
default	Specifies that the default VRF entry be cleared from the SA-cache.
management	Specifies that the management VRF entry be cleared from the SA-cache.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
5.0(3)N1(1)	This command was introduced.

Usage Guidelines

You can also use the **clear ip msdp route** command for the same function.
This command requires the LAN Base Services license.

Examples

This example shows how to clear the MSDP SA cache:

```
switch# clear ip msdp sa-cache
switch#
```

Related Commands

Command	Description
clear ip msdp route	Clears the MSDP SA cache.
show ip msdp sa-cache	Displays route information in the MSDP Source-Active cache.

[Send comments to nexus5k-docfeedback@cisco.com](mailto:nexus5k-docfeedback@cisco.com)

clear ip msdp statistics

To clear statistics for Multicast Source Discovery Protocol (MSDP) peers, use the **clear ip msdp statistics** command.

clear ip msdp statistics [*peer-address*] [**vrf** *vrf-name* | **default** | **management**]

Syntax Description

<i>peer-address</i>	(Optional) IP address of the MSDP peer.
vrf	(Optional) Clears the virtual routing and forwarding (VRF) instance information.
<i>vrf-name</i>	VRF name. The name can be a maximum of 32 alphanumeric characters and is case sensitive.
default	(Optional) Specifies that the default VRF entry be cleared from the multicast routing table.
management	(Optional) Specifies that the management VRF entry be cleared from the multicast routing table.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
5.0(3)N1(1)	This command was introduced.

Usage Guidelines

This command requires the LAN Base Services license.

Examples

This example shows how to clear MSDP statistics for all MSDP peers:

```
switch# clear ip msdp statistics
switch#
```

Related Commands

Command	Description
show ip msdp peer	Displays information about MSDP peers.

■ clear ip msdp statistics

Send comments to nexus5k-docfeedback@cisco.com