



I Commands

This chapter describes the Cisco NX-OS FabricPath commands that begin with I.

install feature-set fabricpath

To install the FabricPath feature set on the switch, use the **install feature-set fabricpath** command. To remove the FabricPath feature set, use the **no** form of this command.

install feature-set fabricpath

no install feature-set fabricpath

Syntax Description This command has no arguments or keywords.

Command Default Disabled

Command Modes Global configuration mode

Command History

Release	Modification
5.2(1)N1(1)	This command was introduced.

Usage Guidelines



Note

The FabricPath feature is supported only on the Cisco Nexus 5500 Series switches.

This command requires an Enhanced Layer 2 license.

Examples

This example shows how to install the FabricPath features on the switch:

```
switch# configure terminal
switch(config)# install feature-set fabricpath
switch(config)#
```

Related Commands

Command	Description
feature fabric-binding	Enables or disables fabric binding on the switch.
feature-set fabricpath	Enables the FabricPath feature set on the switch.
show running-config	Displays the running system configuration information.