



# C Commands

---

This chapter describes the Cisco NX-OS Virtual Router Redundancy Protocol (VRRP) commands that begin with **C**.

# clear ip interface statistics

To clear IP interface statistics, use the **clear ip interface statistics** command.

**clear ip interface statistics**

---

<b>Syntax Description</b>	This command has no arguments or keywords.
---------------------------	--

---

<b>Command Default</b>	None
------------------------	------

---

<b>Command Modes</b>	Any command mode
----------------------	------------------

---

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	5.2(1)N1(1)	This command was introduced.

---

---

<b>Examples</b>	This example shows how to clear the IP interface statistics:  switch# <b>clear ip interface statistics</b>
-----------------	--

---

<b>Related Commands</b>	<b>Command</b>	<b>Description</b>
	<b>show ip interface</b>	Displays IP interface information.

---

# clear vrrp

To clear the Virtual Router Redundancy Protocol (VRRP) statistics, use the **clear vrrp** command.

```
clear vrrp vr id interface {ethernet slot[/QSFP-module]/port|port-channel
number[.sub_if_number]}
```

Syntax Description		
<b>vr</b> <i>id</i>		Clears VRRP statistics in a VRRP group on an interface. The range is from 1 to 255.
<b>interface</b>		Specifies an Ethernet or EtherChannel interface or a subinterface.
<b>ethernet</b> <i>slot</i> [/ <i>QSFP-module</i> ]/ <i>port</i>		Clears VRRP statistics on the Ethernet interface. The <i>slot</i> number is from 1 to 255. The <i>QSFP-module</i> number is from 1 to 4. The <i>port</i> number is from 1 to 128.  <b>Note</b> The <i>QSFP-module</i> number applies only to the QSFP+ Generic Expansion Module (GEM).
<b>port-channel</b> <i>number</i>		Clears VRRP statistics on the EtherChannel interface. The EtherChannel number is from 1 to 4096.
<i>.sub_if_number</i>		(Optional) Subinterface number. The range is from 1 to 4093.

<b>Command Default</b>	None
------------------------	------

<b>Command Modes</b>	Any command mode
----------------------	------------------

Command History	Release	Modification
	6.0(2)N1(2)	Support for the QSFP+ GEM was added.
	5.2(1)N1(1)	This command was introduced.

<b>Examples</b>	This example shows how to clear VRRP statistics from a specific Ethernet interface:
-----------------	---

```
switch(config)# clear vrrp vr 1 interface ethernet 1/5
switch(config)#
```

Related Commands	Command	Description
	<b>feature vrrp</b>	Enables the VRRP feature.

■ clear vrrp