



# I Commands

---

This chapter describes the Cisco NX-OS FabricPath commands that begin with I.

# install feature-set fabricpath

To install the FabricPath feature set on the switch, use the **install feature-set fabricpath** command. To remove the FabricPath feature set, use the **no** form of this command.

**install feature-set fabricpath**

**no install feature-set fabricpath**

**Syntax Description** This command has no arguments or keywords.

**Command Default** Disabled

**Command Modes** Global configuration mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

## Usage Guidelines



### Note

The FabricPath feature is supported only on the Cisco Nexus 5500 Series switches.

This command requires an Enhanced Layer 2 license.

**Examples** This example shows how to install the FabricPath features on the switch:

```
switch# configure terminal
switch(config)# install feature-set fabricpath
switch(config)#
```

Command	Description
<b>feature fabric-binding</b>	Enables or disables fabric binding on the switch.
<b>feature-set fabricpath</b>	Enables the FabricPath feature set on the switch.
<b>show running-config</b>	Displays the running system configuration information.