



# C Commands

---

This chapter describes the Cisco NX-OS IGMP commands that begin with C.

# clear ip igmp event-history

To clear information in the IGMP event history buffers, use the **clear ip igmp event-history** command.

```
clear ip igmp event-history {cli | debugs | errors | events | ha | igmp-internal | mtrace | policy |
vrf}
```

## Syntax Description

<b>cli</b>	Clears the CLI event history buffer.
<b>debugs</b>	Clears the debug event history buffer.
<b>events</b>	Clears the event history buffer.
<b>ha</b>	Clears the high availability (HA) event history buffer.
<b>igmp-internal</b>	Clears the IGMP internal event history buffer.
<b>mtrace</b>	Clears the mtrace event history buffer.
<b>policy</b>	Clears the policy event history buffer.
<b>vrf</b>	Clears the virtual routing and forwarding (VRF) event history buffer.

## Command Default

None

## Command Modes

Any command mode

## Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

## Usage Guidelines

This command does not require a license.

## Examples

This example shows how to clear information in the IGMP HA event history buffer:

```
switch(config)# clear ip igmp event-history ha
switch(config)#
```

## Related Commands

Command	Description
<b>ip igmp event-history</b>	Configures the size of the IGMP event history buffers.

# clear ip igmp groups

To clear IGMP-related information in the IPv4 multicast routing table, use the **clear ip igmp groups** command.

```
clear ip igmp groups { * | group [source] | group-prefix } [vrf { vrf-name | all | default | management }]
```

Syntax Description		
	<b>*</b>	Specifies all routes.
	<i>group</i>	Group address in the format <i>A.B.C.D</i> .
	<i>source</i>	(Optional) Source (S, G) route.
	<i>group-prefix</i>	Group prefix in the format <i>A.B.C.D/length</i> .
	<b>vrf</b>	(Optional) Clears the virtual routing and forwarding (VRF) instance information.
	<i>vrf-name</i>	VRF name. The name can be a maximum of 32 alphanumeric characters and is case sensitive.
	<b>all</b>	Specifies that all VRF entries be cleared from the IPv4 multicast routing table.
	<b>default</b>	Specifies that the default VRF entry be cleared from the IPv4 multicast routing table.
	<b>management</b>	Specifies that the management VRF entry be cleared from the IPv4 multicast routing table.

**Command Default** None

**Command Modes** Any command mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

**Usage Guidelines** The **clear ip igmp route** command is an alternative form of this command.  
This command does not require a license.

**Examples** This example shows how to clear all the IGMP-related routes in the IPv4 multicast routing table:

```
switch(config)# clear ip igmp groups *
switch(config)#
```

Related Commands	Command	Description
	<b>clear ip igmp route</b>	Clears IGMP-related information in the IPv4 multicast routing table.
	<b>show ip mroute</b>	Displays information about the IPv4 multicast routing table.

# clear ip igmp interface statistics

To clear the IGMP statistics for an interface, use the **clear ip igmp interface statistics** command.

**clear ip igmp interface statistics** [**ethernet** *slot/port* | **loopback** *if\_number* | **port-channel** *number*[*.sub\_if\_number*]]

<b>Syntax Description</b>	<b>ethernet</b> <i>slot/port</i>	(Optional) Specifies the Ethernet interface and the slot number and port number. The slot number is from 1 to 255, and the port number is from 1 to 128.
	<b>loopback</b> <i>if_number</i>	(Optional) Specifies the loopback interface. The loopback interface number is from 0 to 1023.
	<b>port-channel</b> <i>number</i>	(Optional) Specifies the EtherChannel interface and EtherChannel number. The range is from 1 to 4096.
	<i>sub_if-number</i>	(Optional) Subinterface number. The range is from 1 to 4093.

**Command Default** None

**Command Modes** Any command mode

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	6.0(2)N1(1)	This command was introduced.

**Usage Guidelines** This command does not require a license.

**Examples** This example shows how to clear IGMP statistics for an interface:

```
switch# clear ip igmp interface statistics ethernet 2/1
switch#
```

<b>Related Commands</b>	<b>Command</b>	<b>Description</b>
	<b>show ip igmp interface</b>	Displays information about IGMP interfaces.

# clear ip igmp route

To clear IGMP-related information in the IPv4 multicast routing table, use the **clear ip igmp route** command.

```
clear ip igmp route { * | group [source] | group-prefix } [vrf { vrf-name | all | default | management }]
```

Syntax Description		
	<b>*</b>	Specifies all routes.
	<i>group</i>	Group address in the format <i>A.B.C.D</i> .
	<i>source</i>	(Optional) Source (S, G) route.
	<i>group-prefix</i>	Group prefix in the format <i>A.B.C.D/length</i> .
	<b>vrf</b>	(Optional) Clears the virtual routing and forwarding (VRF) instance information.
	<i>vrf-name</i>	VRF name. The name can be a maximum of 32 alphanumeric characters and is case sensitive.
	<b>all</b>	Specifies that all VRF entries be cleared from the IPv4 multicast routing table.
	<b>default</b>	Specifies that the default VRF entry be cleared from the IPv4 multicast routing table.
	<b>management</b>	Specifies that the management VRF entry be cleared from the IPv4 multicast routing table.

**Command Default** None

**Command Modes** Any command mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

**Usage Guidelines** The **clear ipigmp groups** command is an alternative form of this command.  
This command does not require a license.

**Examples** This example shows how to clear all the IGMP-related routes in the IPv4 multicast routing table:

```
switch(config)# clear ip igmp route *
switch(config)#
```

Related Commands	Command	Description
	<b>clear ip igmp groups</b>	Clears IGMP-related information in the IPv4 multicast routing table.
	<b>show ip mroute</b>	Displays information about the IPv4 multicast routing table.

■ clear ip igmp route