



## CHAPTER 2

# CTRS Delete Commands

---

October 2011

This chapter contains Cisco TelePresence Recording Server (CTRS) **delete** commands:

- [delete account](#), page 2-2
- [delete dns addr](#), page 2-3
- [delete process](#), page 2-4
- [delete recording](#), page 2-5



### Note

For information about using the CTRS administration software, refer to the *Cisco TelePresence Recording Server Release 1.8 Administration Guide* at the following URL:

[http://www.cisco.com/en/US/products/ps10341/prod\\_maintenance\\_guides\\_list.html](http://www.cisco.com/en/US/products/ps10341/prod_maintenance_guides_list.html)

---

# delete account

**delete account** *name*

<b>Syntax Description</b>	<i>name</i>	Name of the administrative account to be deleted
<b>Command Modes</b>	Admin	
<b>Command History</b>	<b>Release</b>	<b>Modifications</b>
	1.6	This command was introduced.
<b>Usage Guidelines</b>	Use this command to delete an administrative account.	
<b>Examples</b>	admin: <b>delete account admin1</b>	

# delete dns addr

**delete dns addr** *address*

Syntax Description	<i>address</i>	IP address of the Domain Name System (DNS) server to be deleted
--------------------	----------------	-----------------------------------------------------------------

Command Modes	Admin
---------------	-------

Command History	Release	Modifications
	1.6	This command was introduced.

Usage Guidelines	Use this command to delete the specified Domain Name System (DNS) server from the system.
------------------	-------------------------------------------------------------------------------------------

**Examples**

```
admin: delete dns addr 1xx.2xx.3xx.4xx
***  W A R N I N G  ***
This will cause the system to temporarily lose network connectivity

Do you want to continue ?

Enter "yes" to continue or any other key to abort
yes
executing...
```

# delete process

**delete process** *pid* [**force** | **terminate** | **crash**]

## Syntax Description

<i>pid</i>	Process identification number
<b>force</b>	Stops the process. Use this option only if the <b>delete process</b> <i>pid</i> command does not terminate the process.
<b>terminate</b>	Tells the operating system to stop the process. Use this option only if the <b>delete process</b> <i>pid</i> <b>force</b> command does not terminate the process.
<b>crash</b>	Crashes the process with a crash dump

## Command Modes

Admin

## Command History

Release	Modifications
1.6	This command was introduced.

## Usage Guidelines

Use this command to delete a process.

## Examples

admin: **delete process 1429**

# delete recording

**delete recording** *recid*

<b>Syntax Description</b>	<i>recid</i>	Recording identification number
<b>Command Modes</b>	Admin	
<b>Command History</b>	<b>Release</b>	<b>Modifications</b>
	1.6	This command was introduced.
<b>Usage Guidelines</b>	Use this command to delete an mp4 file corresponding to its recording identification number.	
<b>Examples</b>	admin: <b>delete recording 3</b>	

■ delete recording