



Release Notes for Cisco UCS Central, Release 1.1

First Published: July 15, 2013

Updated: December 12, 2013

OL-29853-01

This document describes system requirements, new features, resolved caveats, known caveats, and open caveats with workarounds for Cisco UCS Central software Release 1.1(1a) and 1.1(1b). This document also includes information that became available after the technical documentation was published.

Use this release notes as a supplement with the other documents listed in documentation roadmap <http://www.cisco.com/go/unifiedcomputing/b-series-doc>.

Make sure to review other available documentation on Cisco.com to obtain current information on Cisco UCS Central.

Contents

This document includes the following sections:

- [Revision History](#)
- [Introduction](#)
- [New Software Features in Release 1.1](#)
- [Upgrading to 1.1\(1b\)](#)
- [Resolved Caveats](#)
- [Open Caveats](#)
- [Known Limitations and Behaviors](#)
- [Documentation and Support](#)



Revision History

Table 1 shows the revision history:

Table 1 Online Change History

Part Number	Revision	Release	Date	Description
OL-29853-01	A0	1.1(1a)	July 15, 2013	Created release notes for Cisco UCS Central Release 1.1.
	B0	1.1(1a)	July 30, 2013	Added additional caveats.
	CO	1.1(1a)	August 19, 2013	Added CSCui54228 in open caveats.
	D0	1.1(1b)	October 31, 2013	Updated release notes for Release 1.1(1b).
	EO	1.1(1b)	December 12, 2013	Added CSCum00747 in open caveats.

Introduction

Cisco UCS Central, Release 1.1 allows you to take charge of the data center environment by delivering easy to use, integrated solution for managing multiple Cisco UCS Domains from a single management point with high availability. With Cisco UCS Central 1.1, you can efficiently manage server, storage and network policies and generate network traffic reports for your entire UCS environment in one or more data centers.

System Requirements

To access the browser based Cisco UCS Central GUI, your computer must meet or exceed the following minimum system requirements:

- Windows
 - Internet Explorer 9 and above
 - Firefox 15 and above
 - Chrome 22 and above
- Linux RHEL
 - Firefox 15 and above
 - Chrome 22 and above
- MacOS
 - Firefox 15 and above
 - Chrome 22 and above
 - Safari 6 and above

Adobe Flash Player 11.7 and above.

For the Chrome browser, remove the bundled flash player and install the flash player from Adobe.

The released OVA or ISO is supported with ESXi4.1, ESXi5.0, and ESXi5.1GA.

The released ISO is supported with Microsoft Hyper-V Server 2008 R2 SP1 and Microsoft Hyper-V Server 2012.



Note

If you are using Cisco UCS Release 1.1(1a), you must be running Cisco UCS Release 2.1(2a) or higher.

New Software Features in Release 1.1

Release 1.1(1a) supports the following:

- Global Service Profile and Templates
- Global Policies
 - Server Policies
 - Adapter
 - BIOS
 - Boot
 - IPMI Access Profiles
 - iSCSI Authentication
 - Host Firmware Packages
 - Local Disk Configuration
 - Power Control
 - Maintenance
 - Scrub
 - Serial over LAN
 - Server Pool
 - Server Pool Qualification
 - Stats Threshold
 - vNIC/vHBA Placement
 - Network Policies
 - VLAN
 - vNIC
 - vNIC Template
 - Default vNIC Behaviour
 - QoS
 - Network Control
 - Dynamic vNIC Connection
 - LAN Connectivity
 - Threshold
 - Storage Policies

- VSAN
- vHBA
- vHBA Template
- Default vHBA Behaviour
- SAN Connectivity
- Threshold
- Policy Globalization and Localization
- Global VLAN and VSAN Support
- VLAN Aliasing
- Org Aware Policies
- Domain-specific ID pools
- Enhanced Inventory
- Network Statistics Collection and Aggregation
- Reporting on Collected Statistics for Networks
- Centralized XML API
- High Availability
- SNMP support
- Licensing
- 64-Bit Support
- SQL MIT
- Service Profile Renaming

Release 1.1(1b) supports the following:

- LDAP Group maps
- Nested LDAP groups

Upgrading to 1.1(1b)

- To deploy a fresh installation of Cisco UCS Central, release 1.1(1b), you can use either the OVA file or ISO image. See [Cisco UCS Central Install and Upgrade Guides](#) for more information.
- If you want to upgrade from 1.1(1a) to 1.1(1b) use the ISO image.
- Upgrading from 1.0(1a) to 1.1(1b) is not supported.

Resolved Caveats

Resolved Caveats in Release 1.1(1b)

The following caveats are resolved in Release 1.1(1b):

Table 2 *Resolved Caveats in Release 1.1(1b)*

Defect ID	Description
CSCui08318	Microsoft Hyper-V Server 2008 and 2012 no longer experiences time-drift issues.
CSCuj76375	Cisco UCS Central LDAP user will no longer have any authentication issues to log into one VM using the CLI when logged into another VM.
CSCui67339	When you upgrade Cisco UCS Central from release 1.0 to 1.1, the local service profiles will no longer be missing from the GUI.
CSCuj60761	The UCS Central resource manager will no longer crash and fail to restart.
CSCui38707	When you delete a service profile template with at least one global service profile, the Fabric VCon from the placement policy will get deleted.
CSCui56705	When you move IP address from one IP pool to another the ID usage will automatically be updated.
CSCui02748	The UCS fault panel will no longer show blank space.
CSCui08275	Overall status icon will no longer display wrong status message.
CSCuj63268	Cisco UCS Central resource manager no longer crashes after PMON restart when restrict migration is set on any associated global service profiles.

Resolved Caveats in Release 1.1(1a)

The following caveats are resolved in Release 1.1(1a):

Table 3 *Resolved Caveats in Release 1.1(1a)*

Defect ID	Description
CSCuc94589	When creating a maintenance policy in the CLI, the set reboot-policy immediate command is now saved when the maintenance policy is created.
CSCuc98962	In the Cisco UCS Central GUI, the suspend state shown in the Equipment > UCS Domains table now updates immediately.
CSCud20882	If there are two DNS entries configured in Cisco UCS Central, and the first DNS entry is incorrect or non-reachable, UCS Central will import or export files using the second DNS entry.
CSCud26790	When the CIMC management ip-address is changed from pool ip-address to static ip-address for a server, Cisco UCS Central can crosslaunch KVM for that server.
CSCue21033	Cisco UCS Central OVA no longer misaligns I/O requests at the storage filers hosting the related VMDKs.
CSCue62790	Special characters for password and shared secret no longer corrupt the sam.config file.

Table 3 *Resolved Caveats in Release 1.1(1a)*

Defect ID	Description
CSCud25795	When a full-state restore is done on Cisco UCS Central, subsequent Cisco UCS Manager registrations will now be successful.
CSCud21949	After full-state import and erase samdb, the equipment tab no longer remains in loading state.
CSCud26193	The "Overall Status" column on the Tech Support Files page (Administration > Diagnostics > Tech Support Files) now changes from "in-progress" to "available" when tech-support collection process is complete.

Open Caveats

Open Caveats in Release 1.1(1b)

The following caveats are found in Release 1.1(1b):

Table 4 *Open Caveats in Release 1.1(1b)*

Defect ID	Symptom	Workaround
CSCum00747	Local service profile templates are not deleted from Cisco UCS Central inventory when they are deleted from a registered UCS domain.	Log into the Cisco UCS Central resource manager using CLI, from the specific domain, run "refresh-inventory" command to remove the local service profile templates.
CSCuj84470	If the local-users have usernames with specific strings and use password reset ISO to reset the password, Cisco UCS Central SecAG keeps crashing.	Out of sync entries must be removed from the config files. Contact Cisco TAC for workaround.
CSCui51884	When you create a global service profile using the service profile template and create iSCSI vNIC using LAN connectivity policy, the global service profile enters a loop and does not complete process.	Make sure to create iSCSI vNIC using the expert mode. Do not create iSCSI vNIC from the LAN connectivity policy.
CSCuj65996	When you create a simple password using Cisco UCS Central GUI, if password strength is enforced, the simple password will not be applied on the server.	The new password change did not take effect, because it was weak. Login using the original password, and change the password using the CLI.


Open Caveats in Release 1.1(1a)

The following caveats are found in Release 1.1(1a):

Table 5 *Open Caveats in Release 1.1(1a)*

Defect ID	Symptom	Workaround
CSCui54228	On Microsoft Hyper-V, If the storage reserved for disk1, disk 2 or shared storage is exactly 40 GB, Cisco UCS Central installation fails even if the minimum storage requirement is set at 40 GB.	To install Cisco UCS Central in standalone or high availability mode, the minimum storage requirement for disk 1,disk 2 and shared storage is 45 GB.
CSCuf85283	<p>The Cisco UCS Central CLI session might fail to communicate with the data management engine (DME) and return the following error:</p> <pre>Exception during execution: [Error: Timed out communicating with DME]</pre> <p>This occurs when the CLI is accessed immediately after a reboot before the DME is ready.</p>	Wait a few seconds, then run the Cisco UCS Central CLI command again.
CSCuh90667	The Status column on the Global Service Profiles table may not match the actual status of the service profile as reported by Cisco UCS Manager.	To view the actual status of a global service profile, right-click the service profile and choose Properties . The Properties dialog box displays the overall status, assigned status, associated status, and any configuration errors.
CSCui06133	Dynamic vNIC connection policy configuration for SRIOV is not supported in Cisco UCS Central, Release 1.1(1a).	Create a dynamic vNIC connection policy for SRIOV in Cisco UCS Manager, and reference the policy in a local service profile.
CSCuh01992	<p>The Estimate Impact action states that a reboot is not required when changing from one policy to another, and that the new policy does not exist in Cisco UCS Manager.</p> <p>The Estimate Impact action also states that a reboot is not required when a new host firmware pack with a different firmware version is selected on the global service profile properties page. A reboot is part of the firmware activation and is not being reported by Estimate Impact.</p>	This issue has no known workaround.

Table 5 Open Caveats in Release 1.1(1a)

Defect ID	Symptom	Workaround
CSCub26954	Pending user-acks from maintenance policies defined in Cisco UCS domains are not displayed in Cisco UCS Central.	To see pending user-acks in Cisco UCS Central, use the schedules defined in Cisco UCS Central. Modify the maintenance policy to refer to a schedule owned by Cisco UCS Central. If you are using the local scheduler, use Cisco UCS Manager to acknowledge the pending acks.
CSCuf85283	When the system boots, you may experience errors when issuing CLI commands before the system has booted successfully.	Wait for the system to complete the boot process before continuing.
CSCug53341	An hrDeviceStatus value is not retrieved for all devices while doing an snmpwalk or snmpGet. A value is only retrieved for interfaces and not for hard disks.	This issue has no known workaround.
CSCtz35499	When you modify the UCS Central IP address, Cisco UCS Manager may not be receive the update, and might go into lost-visibility status.	Unregister the Cisco UCS domain and re-register the domain with Cisco UCS Central.
CSCud27361	<p>The following is not supported on the Cisco UCS Central GUI:</p> <ul style="list-style-type: none"> Changing the Cisco UCS Central shared-secret. Changing the Cisco UCS Central hostname. Changing the Cisco UCS Central IP address. <p> Note If Cisco UCS Central is running in High-Availability mode, you can change the IP address under Administration > Service Registry > System > General.</p>	<p>Run the following commands from the Cisco UCS Central CLI:</p> <ul style="list-style-type: none"> Use the local-mgmt command to change the shared-secret. Use the scope system command to change the hostname. Use the scope network-interface mgmt command to change the IP address.
CSCuc96920	In the Cisco UCS Central GUI, the policies under Operation Management > Domain Group > Operational Policies cannot be saved simultaneously. This includes Time Zone, DNS, Remote Access, SNMP, Debug, Call Home, Security, Equipment, and Identifier policies.	When you configure an operational policy, click Save before viewing or changing a different policy.

Known Limitations and Behaviors

The following known limitations and behaviors are not otherwise documented:

Table 6 *Known Limitations in Release 1.1*

Defect ID	Symptom	Workaround
CSCug39587	Running VMware vMotion, suspending a VM, or restoring a suspended VM on a Cisco UCS Central VM that is currently the primary node in a cluster results in process crashes on the node.	Before triggering a vMotion or suspend operation on the primary Cisco UCS Central VM, use the local-mgmt cluster lead b command in the Cisco UCS Central CLI to do an administrative failover, which changes the primary node to the secondary node.
CSCuh71425 CSCuh01992	<p>The Estimate Impact option does not display that a reboot is required under some situations. For example:</p> <ul style="list-style-type: none"> When you add or remove vNICs or vHBAs from an associated global service profile where the MAC or WWxN IDs are derived from ID pools. When you change policies in a global service profile to a policy that was created in Cisco UCS Central, and does not yet exist in Cisco UCS Manager. When a new host firmware pack with a different firmware version is selected in the global service profiles properties page. 	<ul style="list-style-type: none"> For vNICs/vHBAs in pools, add and remove vNICs and vHBAs during a maintenance window. Estimate impact analysis works correctly for vNICs/vHBAs where the IDs are set manually. For policies, create an unassociated local service profile in Cisco UCS Manager. Reference the new policy in the service profile. Estimate impact analysis will now work correctly. For host firmware packages, create a host firmware package in Cisco UCS Central under the same domain group as the global service profile. Create an unassociated service profile in Cisco UCS Manager and reference the new host firmware package in the service profile. Estimate impact analysis will now work correctly.
CSCud26491	A critical disk read speed fault is shown in an UCS Central deployed on a Hyper-V host.	None. In testing, it was found that the disk read speed measured on Hyper-V guests showed a lower speed in comparison to guests running on ESX on the same datastore. Typically, this didn't result in a functional impact.

Table 6 Known Limitations in Release 1.1 (continued)

Defect ID	Symptom	Workaround
CSCui08318	Microsoft Hyper-V Server 2008 and 2012 experience time-drift issues.	<p>Perform the following:</p> <ol style="list-style-type: none"> 1. Disable the Time Synchronization option on the Central VM Guest OS using Hyper-V Manager. 2. Acquire a Redhat version 5.8 compatible Rescue CD and perform the boot process. For more information, see http://www.redhat.com/advice/tips/rescue_mode.html 3. After booting the RedHat Rescue CD, mount the /boot filesystem to a temporary mount location, for example, /tmp/boot. 4. Open the grub.conf file, locate the kernel line, and add the following: notsc divider=10 It should look like: ***** UCSCentral#cat /boot/grub/grub.conf ***** # grub.conf generated by anaconda # # Note that you do not have to rerun grub after making changes to this file # NOTICE: You have a /boot partition. This means that # all kernel and initrd paths are relative to /boot/, eg. # root (hd0,0) # kernel /vmlinuz-version ro root=/dev/VolGroup00/LogVol100 # initrd /initrd-version.img #boot=/dev/hda default=0 timeout=0 title Cisco UCS Central root (hd0,0) kernel /vmlinuz-2.6.18-308.11.1.el5 ro root=/dev/VolGroup00/LogVol100 notsc divider=10 initrd /initrd-2.6.18-308.11.1.el5.img 5. Reboot the system, and verify the change works successfully by monitoring for one hour.

Table 6 **Known Limitations in Release 1.1 (continued)**

Defect ID	Symptom	Workaround
CSCug68204	When performing maintenance operations such as admin failover or pmon restart on a UCS Central VM running on VMware ESX, the file system goes into read-only state. For more information, see http://kb.vmware.com/selfservice/microsites/search.do?cmd=displayKC&externalId=51306 .	There is no known workaround.

Documentation and Support

You can obtain documentation, submit a service request or find additional information from *What's New in Cisco Product Documentation* at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>.

Subscribe to *What's New in Cisco Product Documentation*, which lists all new and revised Cisco technical documentation, as an RSS feed and deliver content directly to your desktop using a reader application. The RSS feeds are a free service.

For more information, you can access related documents from the following links:

- [Cisco UCS Documentation Roadmap](#)
- [Cisco UCS Central Install and Upgrade Guides](#)

This document is to be used in conjunction with the documents listed in the “Documentation and Support” section.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2013 Cisco Systems, Inc. All rights reserved.

