



CHAPTER 17

MIB2 System Group Configuration

Cisco Unified Presence Serviceability provides the MIB2 System Group Configuration window where you can configure the system contact and system location objects for the MIB-II system group. For example, you could enter Administrator, 555-121-6633, for the system contact and San Jose, Bldg 23, 2nd floor, for the system location. This chapter contains information on the following topics:

- [Configuring the MIB2 System Group, page 17-1](#)
- [MIB2 System Group Configuration Settings, page 17-2](#)
- [Related Topics, page 17-2](#)

Configuring the MIB2 System Group

Perform the following procedure to configure a system contact and system location for the MIB-II system group.



Tip

This procedure supports SNMP v1, v2c, and v3 configuration.

Procedure

- Step 1** Choose **Snmp > SystemGroup > MIB2 System Group**.
- Step 2** Configure the settings, as described in [Table 17-1](#).
- Step 3** Click **Save**.
- Step 4** A message indicates that changes will not take effect until you restart the SNMP master agent. To continue the configuration without restarting the SNMP master agent service, click **Cancel**. To restart the SNMP master agent service, click **OK**.



Note

To clear the System Contact and System Location fields, click the **Clear All** button. To delete the system configuration, click the **Clear All** button and the **Save** button.

Additional Information

See the [“Related Topics” section on page 17-2](#).

MIB2 System Group Configuration Settings

Table 17-1 describes the MIB2 System Group configuration settings. For related procedures, see the “Related Topics” section on page 17-2.

Table 17-1 MIB2 System Group Configuration Settings

Field	Description
Server	From the drop-down list box, choose the server for which you want to configure contacts; then, click Go .
System Contact	In the field, enter a person to notify when problems occur.
System Location	In the field, enter the location of the person that is identified as the system contact.
Apply To All Nodes	To apply the system configuration to all of the nodes in the cluster, check the check box.

Related Topics

- [SNMP V1/V2c Configuration, page 15-1](#)
- [SNMP V3 Configuration, page 16-1](#)