

Interstage Trim Networks for System Amplifier I, II, II+ and Line Extender I, II, III



22368

DESCRIPTION

Scientific-Atlanta manufactures a broad line of interstage trim networks to meet the needs of the variety of advanced amplifiers and architectures being deployed today. These passive trim networks compensate for amplitude/frequency variations by superimposing a response that is opposite to that of the uncompensated cascade. Trim networks allow adjustment of an amplifiers frequency response to be as uniform as possible across the entire output spectrum. They can be adjusted, within limits, to cover a wide range of individual requirements.

There are two basic types of trim networks available, peak and dip trim networks. Peak networks operate as broad bandwidth tunable attenuators, while dip networks operate as narrow bandwidth tunable attenuators. Trim networks introduce 1 to 3 dB of flat loss in an amplifier station. This loss can be compensated for by reducing input or interstage pad values as necessary.

Trims are classified according to their operational characteristics (i.e., frequency, insertion loss, pad socket, peak or dip, and forward or reverse direction). The type and use factor for specific trim networks is determined by evaluating actual system frequency response. A broad selection of trim networks should be on hand at the outset of balance and alignment procedures.

INTERSTAGE TRIM NETWORKS NAMING CONVENTIONS

Each trim network has been assigned a part number and descriptive title defining the operational characteristics of that particular network. The alphanumeric designation on the trim defines the network function. These functions are as follows:

- frequency
- insertion loss
- whether it has a pad socket
- which device it is intended to be used in
- signal direction it affects (forward or reverse)

Example:

Interstage trim network model number LSP-2SDF equates to a trim that performs the following functions:

LSP = Low Single Peak

2 = 2 dB insertion loss

S = Pad Socket

D = Distribution Amplifier, System Amplifier I and II

F = Forward

The chart below outlines the abbreviated nomenclature used by Scientific-Atlanta for identifying and selecting interstage trim networks.

NOMENCLATURE ABBREVIATION TABLE

Band	Number of Peaks	Trim Type	Loss	Pad Socket	Application	Signal Direction
L = Low	S = Single	D = Dip	1 = 1 dB	N = No Socket	L = LEI	F = Forward
M = Mid	D = Dual	P = Peak	2 = 2 dB	S = Socket	M = LEII (550 MHz)	R = Reverse
H = High	T = Triple	---	3 = 3 dB	---	D = Distribution Amp,	---
U = Universal	---	---	---	---	System Amp and LEIII	---
N = Narrow	---	---	---	---	N = LEII (750 MHz)	---
D = Diplexer	---	---	---	---	---	---

INTERSTAGE TRIM NETWORKS

Part Number	Name	Description	Module
276754	LDP-2SDF	Low Frequency Dual Peak	DA / SA I / SA II / LEIII
381101	MDP-2SDF	Mid-Frequency Dual Peak	DA / SA I / SA II / LEIII
500221	MSD-2SDF	Mid-Frequency Single Dip	DA / SA I / SA II / LEIII
500300	MDP-3SDF	Mid-Frequency Dual Peak	DA / SA I / SA II / LEIII
501769	HSP-3NDF	High Frequency Single Peak	DA / SA I / SA II / LEIII
506506	HSP-3SDF	High Frequency Single Peak	DA / SA I / SA II / LEIII
536640 ¹	HSP-3SDF w/ HPF	High Frequency Single Peak w/ Low Pass Filter	DA / SA I / SA II / LEIII
536644 ¹	MSD-2SDF	Mid-Frequency Single Dip	DA / SA I / SA II / LEIII
541635	HSP-2NNF	High Frequency Single Peak	LEII - 750 MHz
541636	MSD-2NNF	Mid-Frequency Single Dip	LEII - 750 MHz
541637	LDP-2NNF	Low Frequency Dual Peak	LEII - 750 MHz
544125 ²	HSP-2NNF w/ HPF	High Frequency Single Peak w/ High Pass Filter	LEII - 750 MHz
544126 ²	MSD-2NNF w/ HPF	Mid-Frequency Single Dip w/ High Pass Filter	LEII - 750 MHz
544127 ²	LDP-2NNF w/ HPF	Low Frequency Dual Peak w/ High Pass Filter	LEII - 750 MHz
501967	LDP-2SMF	Low-Frequency Dual Peak	LEII - 550 MHz
502273	MDP-3SMF	Mid-Frequency Dual Peak	LEII - 550 MHz
372728	LDP-2SLF	Low Frequency Dual Peak	LEI - 550 MHz

Notes

¹ Pass band of Low Pass Filter is 51 to 750 MHz.

² Unique for 5-40 MHz upgrade of 750 MHz LEII with 5-30 split.

³ Trims with pad sockets are shipped with a jumper installed.

ORDERING INFORMATION

- Order interstage trim networks by part number.

ADDITIONAL INFORMATION

- For additional information on interstage trim networks refer to the following application notes as needed:
 - #564214 - Distribution Amplifier / System Amplifier Trim Networks
 - #564215 - Line Extender Trim Networks
 - #564216 - Trunk Amplifier Trim Networks

Interstage Trim Networks



Scientific-Atlanta, Inc.

<http://www.sciatl.com>

United States: 4261 Communications Drive, Norcross, GA 30093; Tel: 800-433-6222; Fax: 770-903-4617

Canada: 7725 Lougheed Highway, Burnaby, BC V5A 4V8; Tel: 604-420-5322; Fax: 604-420-5941

United Kingdom: Home Park Estate, Kings Langley, Herts WD4 8LZ, England; Tel: 44-923-266-133; Fax: 44-192-327-0448

Singapore: 1 Claymore Drive, #08-11 Orchard Towers, Singapore 229594; Tel: 65-733-4314; Fax: 65-733-2706

Hong Kong: Suite 56 & 57, 5/F New Henry House, 10 Ice House Street, Central, Hong Kong; Tel: 852-2522-5059; Fax: 852-2522-5624

88D114Z

© 1996 Scientific-Atlanta, Inc. All rights reserved.

Printed in USA.

0996M