



APPENDIX A

Provisioning Default Values for Maximum Calls and Busy Trigger Attributes

Maximum Calls and Busy Trigger are Line provisioning attributes that Provisioning sets with default values based on the phone type. [Table A-1](#) lists the default values that Provisioning sets for each phone type.

Table A-1 *Default Settings for Maximum Calls and Busy Trigger Provisioning Attributes*

Product	Maximum Calls	Busy Trigger
Analog Phones	1	1
Blackberry MVS Client	2	2
CTI Port	4	2
Cisco 3905	2	2
Cisco 6901	2	2
Cisco 6911	2	2
Cisco 6921	2	1
Cisco 6941	2	1
Cisco 6945	2	1
Cisco 6961	2	1
Cisco 7902	2	2
Cisco 7905	4	2
Cisco 7905 (SIP)	2	2
Cisco 7906	4	2
Cisco 7906 (SIP)	4	2
Cisco 7910	2	2
Cisco 7911	4	2
Cisco 7911 (SIP)	4	2
Cisco 7912	4	2
Cisco 7912 (SIP)	2	2
Cisco 7920	2	2

Table A-1 *Default Settings for Maximum Calls and Busy Trigger Provisioning Attributes (continued)*

Product	Maximum Calls	Busy Trigger
Cisco 7921	4	2
Cisco 7925	4	2
Cisco 7926 G	4	2
Cisco 7931	1	1
Cisco 7935	2	1
Cisco 7936	2	1
Cisco 7937	6	2
Cisco 7940	4	2
Cisco 7940 (SIP)	2	2
Cisco 7941	4	2
Cisco 7941 (SIP)	4	2
Cisco 7941G-GE	4	2
Cisco 7941G-GE (SIP)	4	2
Cisco 7942	4	2
Cisco 7942 (SIP)	4	2
Cisco 7945	4	2
Cisco 7945 (SIP)	4	2
Cisco 7960	4	2
Cisco 7960 (SIP)	2	2
Cisco 7961	4	2
Cisco 7961 (SIP)	4	2
Cisco 7961G-GE	4	2
Cisco 7961G-GE (SIP)	4	2
Cisco 7962	4	2
Cisco 7962 (SIP)	4	2
Cisco 7965	4	2
Cisco 7965 (SIP)	4	2
Cisco 7970	4	2
Cisco 7970 (SIP)	4	2
Cisco 7971	4	2
Cisco 7971 (SIP)	4	2
Cisco 7975	4	2
Cisco 7975 (SIP)	4	2
Cisco 7985	4	2
Cisco 8941	3	2
Cisco 8945	3	2

Table A-1 *Default Settings for Maximum Calls and Busy Trigger Provisioning Attributes (continued)*

Product	Maximum Calls	Busy Trigger
Cisco 8961(SIP)	4	2
Cisco 9951(SIP)	4	2
Cisco 9971 (SIP)	4	2
Cisco IP Communicator	4	2
Cisco IP Communicator (SIP)	4	2
Cisco ATA-186	2	2
Cisco ATA-187	2	2
Cisco Dual Mode for Android	3	2
Cisco Cius	4	2
Cisco E20	5	2
Cisco Dual Mode for iPhone	3	2
Cisco EX60	4	4
Cisco EX90	4	4
Cisco Unified Client Services Framework	6	2
Cisco Unified Personal Communicator	6	2
Nokia S60 ¹	3	2
Remote Destination Profile	2	2
Third-party SIP device (advanced)	2	2
Third-party SIP device (basic)	2	2

1. After upgrade new phones like Nokia and iPhone cannot be ordered by default. You must associate these new phone types to the appropriate user types.

