

3 Breakout Session Features

Press	Description	Then Press	Description
#	Hear options	An option number	Choose an option that you hear
		*	Rejoin the main meeting
#0	Get assistance	—	—
#1	Leave the breakout session	0	Rejoin the main meeting
		1-9	Choose a breakout session
#2	Roll call	1	Hear participant names
		*	Rejoin the breakout session
#4	Admittance options	1	Lock or unlock the breakout session
		*	Rejoin the breakout session
#5	Mute or unmute yourself	—	—

4 More Information

Visit http://www.cisco.com/en/US/products/ps6533/products_user_guide_list.html.

Corporate Headquarters
Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 526-4100

Cisco, Cisco IOS, Cisco Systems, and the Cisco Systems logo are registered trademarks of Cisco Systems, Inc. or its affiliates in the United States and certain other countries. All other brands, names, or trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0501R)

© 2005–2006 Cisco Systems, Inc. All rights reserved.

OL-8975-03



Telephone Commands for Cisco Unified MeetingPlace Express Releases 1.1 and 1.2

- 1 Entering Cisco Unified MeetingPlace Express
- 2 In-Session Features
- 3 Breakout Session Features
- 4 More Information



1 Entering Cisco Unified MeetingPlace Express

Write your Cisco Unified MeetingPlace Express phone number here:

Dial the Cisco Unified MeetingPlace Express Phone Number, Then Enter	Description	Then	Description
0#	Get assistance	—	—
Meeting ID number, then #	Join the meeting as a guest ¹	If prompted, enter password	—
1#	Start now	Enter your profile number, then #, and password, then #	—
2#	Access your profile	Enter your profile number, then #, and password, then #	—
		Enter the Meeting ID number, then #	Join the meeting as a profiled user
		2#	Record your name
		3#	Change your phone profile password
3# or 4# or ...	Select your preferred language ²	If prompted, select language version	—
#	Hear options again	—	—

1. Guest users cannot join meetings that are scheduled with a “Who can attend” setting of “Users with Cisco Unified MeetingPlace Express profiles only.”
2. Available only on systems that are configured to provide multiple language options.

2 In-Session Features

Press	Description	Then Press	Description
#	Hear options	An option number	Choose an option that you hear
		*	Rejoin the meeting
#0	Get assistance	—	—
#1	Breakout session	1-9	Choose a breakout session
		0	Rejoin the meeting
#2	Roll call	1	Hear participant names
		*	Rejoin the meeting
#3	Call new participant or get all missing invitees	1, then the phone number, then #	Dial a new participant
		3	Get all missing invitees
		*	Rejoin the meeting
#4	Admittance options	1	Lock or unlock the meeting
		2	Admit participant
		3	Disconnect the last entrant
		*	Rejoin the meeting
#5	Mute or unmute your phone	—	—
#6	Recording	1	Start or stop recording
		*	Rejoin the meeting
#8	End meeting	3	End the meeting ¹
		*	Rejoin the meeting
#9	Exit meeting	—	—

1. In Cisco Unified MeetingPlace Express Release 1.1.1 and earlier releases, enter **#81** to end a meeting.